

Description

This invention concerns apparatus for automatically limiting excessive beam currents conducted by an image display device (such as a kinescope) in a video signal processing and display system.

Excessive beam currents conducted by an image reproducing kinescope in a television receiver can result in a degraded image display. Specifically, excess beam currents can degrade the performance of the receiver deflection system which is operatively associated with the kinescope, and can cause electron beam spot defocussing and picture blooming. High beam currents can also exceed the safe operating current capability of the kinescope, possibly damaging the kinescope and associated circuit components which may be sensitive to high beam current levels.

Various arrangements for automatically controlling both excessive average and peak beam currents are known. One such arrangement is described in U.S. patent US-A-4,167,025 - Willis. In that arrangement, as well as in other known automatic beam current limiter arrangements, a signal representative of the magnitude of the kinescope beam current is derived from the kinescope high voltage resupply system of the receiver. The beam current limiter responds to such signal when it exceeds a threshold level indicating the presence of excessively high kinescope beam current levels as manifested by the kinescope resupply current.

Beam current limiters of the type which operate in conjunction with the kinescope resupply system, as mentioned above, do not respond instantaneously to an excessive beam current condition due to delays inherent in the kinescope resupply system. For example, the kinescope anode capacitance can be discharged greatly in response to video signals representative of very bright or peak white scenes. The kinescope capacitance is eventually recharged via the high voltage resupply system, but with a delay associated with the value of the kinescope capacitance and the effective charging impedance of the resupply system, among other factors. This delay is often approximately 20 milliseconds.

Another beam current limiting apparatus is known from DE-A-1,462,091 (Telefunken). Such an apparatus comprises: a source of plural color video signals; a current-conducting color image display device; plural color signal output paths associated with respective outputs of said source of plural color signals; a video output signal display driver stage for providing plural amplified color signals suitable for driving signal inputs of said display device in response to plural color signals received as inputs from said plural signal output paths; combining means for providing a combined signal representative of an additive combination of said plural color signals from said source; and means for comparing said combined signal with a substantially fixed threshold

reference level to provide an output signal representative of said combined signal. The combining means includes an integrating capacitor so that the additive combination of said plural color signals is an average value.

The present invention is characterized in that the combining means provides a combined signal representative of the sum of the instantaneous magnitudes of said plural control signals from said source; and by: a supply network including a source of high voltage coupled to said image display device for providing a high operating voltage and resupply current to said image display device; a display device beam current limiter network coupled to said supply network and to said source of video signals, said beam current limiter network being responsive to the magnitude of resupply current representative of beam currents conducted by said image display device for providing a first control signal representative of the magnitude of said representative resupply current above a threshold level; means for coupling said first control signal to said signal source for limiting the magnitudes of said plural color signals from said source in accordance with the magnitude of said first control signal; means for detecting said representative output signal to provide a second control signal; and means for coupling said second control signal to said signal source for limiting the magnitudes of said plural color signals from said source in accordance with the magnitude of said second control signal.

In an embodiment of the present invention said combining means is coupled to said plural color signal output paths for providing a combined signal representative of the sum of the instantaneous magnitudes of plural color signals conveyed by said plural color signal output paths.

The single Figure of the drawing shows a portion of a color television receiver, partly in block form and partly in schematic circuit form, including apparatus in accordance with the principles of the present invention.

A composite color television signal from a source 10 is applied to a frequency selection network 11 which provides separated luminance (Y) and chrominance (c) components of the television signal at respective outputs. A chrominance processor 12 derives plural color difference signals $r-y$, $g-y$ and $b-y$ from the separated chrominance component. The separated luminance component is processed by a luminance processor 14 which includes DC level shifting, amplifying and gain control circuits, for example. The wiper of a manual, viewer adjustable brightness control potentiometer 13 is coupled via a terminal T_1 to a luminance signal DC level control input of processor 14. The DC level of the luminance signal and the brightness of a displayed image vary in accordance with the level of the voltage applied to terminal T_1 . The wiper of a manual, viewer adjustable picture control 15 is coupled via a terminal T_2 to a luminance signal gain control input of processor 14, and via a terminal T_3 to a chrominance signal gain control

input of chrominance processor 12. The gains of the luminance and chrominance signals and thereby the contrast of a displayed image vary in accordance with the level of the voltage applied to terminals T_2 and T_3 .

Processed luminance signals from processor 14 are combined with the color difference signals from processor 12 in a matrix amplifier 17 for producing low level color image representative signals r, g and b. These signals are applied to respective kinescope driver amplifiers in a driver stage 18 for producing high level video output signals R, G, B suitable for driving the intensity control electrodes, e.g., cathode electrodes, of a color image displaying kinescope 20. The driver amplifiers in stage 18 illustratively comprise feedback cascode driver amplifiers of the type shown, for example, in U.S. Patent 4,096,517, and in U.S. Patent Number 4577234—titled "Driver Amplifier for an Image Display Device" of Wayne E. Harlan, filed October 31, 1983 (corresponding to British Patent Application 8426667).

A high operating voltage for the ultor (anode) electrode of kinescope 20 is provided from an output terminal T_4 of a high voltage supply network 22 which includes a high voltage multiplier. Horizontal flyback pulses from receiver deflection circuits 25 are applied to network 22 via a terminal T_5 , and kinescope resupply current (I_R) from a current source comprising a resistor 26 and an associated DC voltage supply ($B+$) is provided to network 22 via a terminal T_6 .

Operatively associated with the kinescope resupply current source is an automatic kinescope beam current limiter network 30 comprising a filter capacitor 31, a switching diode 32, a bias resistor 33, and a beam current limiter control signal sequencing network 35. The beam current limiter responds to the magnitude of the resupply current, which is representative of the magnitude of the beam current conducted by the kinescope, for automatically limiting both excessive peak and average kinescope beam currents as will be discussed subsequently.

Additional automatic beam current limiting is provided by means of an adjunct beam current limiter network which acts as a video signal conditioning circuit, as described immediately below.

The instantaneous magnitudes of color signals r, g and b in the signal path between matrix 17 and driver 18 are respectively sensed by means of resistors 41, 42 and 43 which are separately connected to low impedance (e.g., emitter follower) outputs of matrix 17. A combined signal representative of the sum of the instantaneous magnitudes of the r, g, b signals is developed at a summing node A. The combined signal at node A is not subject to filtering since filtering of the combined signal can distort the information content of the combined signal, e.g., with respect to high frequency information associated with small, bright image areas. The combined signal is applied to the base input of a normally non-conductive comparator transistor 50. A resistor 60

forms a voltage divider with resistors 41—43 for attenuating by a given amount the combined signal at the base electrode of transistor 50. The threshold conduction level of transistor 50 is established by means of a bias voltage applied to the emitter of transistor 50 from a voltage divider comprising resistors 54 and 55. When conductive, transistor 50 provides a collector output signal which is representative of the instantaneous magnitude of the combined signal at node A above the threshold level. The collector output signal is detected by means of an integrating capacitor 16. Capacitor 16 is otherwise provided for filtering the picture control voltage developed at the wiper of potentiometer 15, e.g., for filtering noise, power supply ripple components and horizontal rate interference developed by the deflection circuits. The voltage across capacitor 16 is modified in accordance with the conduction of transistor 50 such that a resulting voltage applied to the gain control inputs of luminance processor 14 and chrominance processor 12 reduces the magnitudes of the color signals which are ultimately applied to the kinescope, thereby reducing kinescope beam current by closed loop feedback action.

The threshold conduction level of comparator transistor 50 is established so that transistor 50 conducts when the magnitude of the combined signal at node A is representative of video signals of a magnitude exceeding approximately two-thirds of a maximum white (100 IRE) video signal level. At such time the conduction level of transistor 50 is related to the magnitude of the combined signal at node A. The collector output signal from transistor 50 is detected by capacitor 16 such that the charge on capacitor 16 is reduced by an amount proportional to the collector signal level. The reduced voltage on capacitor 16 causes a related change in the voltage applied to the gain control inputs of processors 14 and 12 for limiting the magnitudes of the r, g, b signals and corresponding kinescope current.

The signal conditioning circuit exhibits a time constant, e.g., 3 or 4 milliseconds, which is preferably slow relative to the horizontal line scanning rate, but fast relative to the vertical field scanning rate. The time constant is a function of the emitter impedance of transistor 50, the value of filter capacitor 16, and the control loop gain of the signal conditioning circuit. The time constant of the signal conditioning circuit introduces a slight delay between the onset of a large video signal condition and the gain reduction of the video signal so as to reduce the likelihood of unwanted visible artifacts being displayed, such as including a vertical image peaking effect (i.e., image contrast transients) which may occur if the video signal gain reduction is instantaneous. On the other hand, if the time constant is too slow an associated greater delay may result in overload of the deflection circuits which are associated with the kinescope beam current resupply system as will be discussed.

The effect of the signal conditioning circuit to

reduce excessive kinescope beam currents supplements the operation of beam current limiter circuit 30, which exhibits both peak and average beam current limiting modes of operation.

For purposes of average beam current limiting, average responding filter capacitor 31 is coupled between a node B and ground via diode 32, which is maintained conductive by means of bias provided via resistor 33. A voltage developed across capacitor 31 at node B varies in accordance with the level of average beam current conducted by the kinescope.

A source current I_s conducted by resistor 26 of the kinescope resupply system comprises a control current component I_c which flows to the input of sequencing circuit 35, and a resupply current component I_R which flows to the input of high voltage supply 22. Resupply current I_R varies in magnitude in accordance with the beam current conducted by the kinescope. In the normal, non-beam limiting mode, the voltage developed at node B is sufficiently large to forward bias the base-collector junction of an input emitter follower transistor 36 of network 35; whereby control current I_c flows from the base to the collector of transistor 36. The forward biased base-collector junction acts as a voltage clamp with respect to node B. The collector current of transistor 36 corresponds to current I_c , and the emitter current of transistor 36 is supplied by a current source 38. No beam limiting control action is produced as long as the base-collector junction of transistor 36 is forward biased, during which time node B is clamped to a voltage approximately 0.7 volts greater than the collector bias voltage (+V) of transistor 36. Also at this time, transistor 36 operates non-linearly with respect to variations of current I , whereby the emitter current and voltage of transistor 36 remain substantially unchanged as a function of base current.

Automatic beam current limiting action commences when resupply current I_R increases to the point where current I_c diminishes to a level on the order of a few microamperes. When this occurs, the base-collector junction of transistor 36 becomes reverse biased, whereby node B is unclamped and exhibits a voltage which decreases with increasing resupply current I_R . Transistor 36 then operates linearly to produce an emitter control voltage which varies proportionally with variations of resupply current I_R and the corresponding voltage at node B.

The emitter control voltage of transistor 36 is utilized to develop variable beam limiting control voltages V_p and V_b at the output of network 35. Specifically, variable control voltage V_p is developed when excessive beam currents occur throughout a first range, in which case voltage V_p serves to limit such excessive beam currents by reducing the amplitudes of the luminance and chrominance signals via gain control inputs T_2 and T_3 of luminance processor 14 and chrominance processor 12. Control voltage V_b is developed in response to excessive beam cur-

rents throughout a second range having a magnitude greater than the magnitude of beam currents within the first range. In such case the picture gain control beam current limiting action is supplemented by reducing the DC level of the video signal (i.e., reducing image brightness) via control voltage V_b and terminal T_1 of luminance processor 14. A sequentially operating beam current limiter of this type is described in U.S. Patent 4,253,110 of L.A. Harwood et al., and is also discussed in U.S. Patent No. 4,451,849 of J. S. Fuhrer issued May 29, 1984 and titled "Plural Operating Mode Ambient Light Responsive Television Picture Control."

In the presence of excessive transient peak kinescope beam current conditions a transient, negative-going voltage developed at node B is coupled through capacitor 31 to diode 32, rendering diode 32 non-conductive and thereby decoupling capacitor 31. Changes in peak beam resupply currents are then sensed directly (i.e., without filtering) by network 35 and are controlled via the control voltage outputs from network 35 in the manner previously discussed. The peak beam current limiting operation of network 30 is described in greater detail in U.S. Patent 4,167,025 — Willis.

The signal conditioning circuit including summing resistors 41—43, comparator transistor 50 and detector 16 serves to reduce the likelihood of the kinescope being damaged by excessive beam currents, and also reduces the likelihood of the kinescope resupply system, including elements 22 and 25, from being overloaded in response to excessive currents conducted by the kinescope. The resupply system can be modeled as a high voltage source in series with a high impedance and which is switched at the horizontal line rate in response to horizontal flyback pulses provided by the deflection circuits. The resupply system exhibits a delay on the order of 20 milliseconds due to a time constant determined by the high impedance of the resupply system and the capacitance of the kinescope anode which is being recharged, among other factors. Excessive peak beam currents on the order of 5—6 milliamperes, which are capable of being produced in receivers with low output impedance feedback kinescope driver amplifiers, for example, can disrupt the operation of the resupply system. In particular, transformers (e.g., a chopper transformer) in the horizontal deflection circuits can be caused to saturate in the presence of such high peak beam currents. Excessive average beam currents are less troublesome for the resupply system since maximum expected average beam currents are typically significantly lower in magnitude than maximum expected peak beam currents.

The signal conditioning circuit comprising resistors 41—43, comparator transistor 50 and peak detector capacitor 16 advantageously cooperates with beam limiter network 30 when operating in a beam current limiting mode, to limit the magnitude of beam currents conducted by the kinescope. The signal conditioning circuit

senses the color video signals directly for instantaneously limiting the magnitudes of video drive signals, except for the prescribed 3 millisecond output delay as discussed. Any additional peak beam currents, such as may occur during the 3 millisecond delay interval associated with the operation of the signal conditioning circuit, are subject to being limited by the action of network 30 in the peak beam current limiting mode if such additional peak beam currents are of sufficient magnitude. The use of the signal conditioning circuit to limit peak beam currents avoids the delays associated with the kinescope resupply system with which beam limiter network 30 is associated.

The signal conditioning network is preferably DC coupled to the video signal path, e.g., between the output of matrix network 17 and the gain control inputs of luminance processor 14 and chrominance processor 12, and controls the video signal amplitude substantially without affecting the video signal DC level to avoid transient image brightness changes as the video signal peak-to-peak amplitude is controlled.

The signal conditioning network also is preferably coupled to a low level video signal path, rather than to a high level video signal path such as between the outputs of driver 18 and the kinescope cathode electrodes. This preference is dictated by the desirability of avoiding the use of more costly larger power sensing resistors (e.g., 41—43) which exhibit increased parasitic capacitance, and to minimize the likelihood of signal loading effects and parasitic bandwidth limiting effects. The latter two effects can readily occur in the case of sensing video signals in the signal path from the output driver stage to the kinescope cathodes.

Sensing the plural r, g and b color signals rather than sensing only the luminance signal component provides a more accurate indication of the presence of excessive peak currents. In this regard it is noted that excessive beam currents can be generated in response to a yellow (r+g) color signal, a cyan (b+g) color signal, a magenta (r+b) color signal, or a combination of these color signals, even when the level of the luminance signal is below the threshold of comparator transistor 50. Thus sensing only the luminance component may result in the signal conditioning circuit remaining inoperative when excessive beam currents resulting from color information are present.

Claims

1. In a system for processing and displaying color video signal image information, apparatus comprising:

a source (10, 11, 12, 14, 17) of plural color video signals;

a current-conducting color image display device (20);

plural color signal output paths (outputs of 17) associated with respective outputs of said source of plural color signals;

a video output signal display driver stage (18) for

providing plural amplified color signals suitable for driving signal inputs of said display device in response to plural color signals received as inputs from said plural signal output paths;

combining means (41, 42, 43) for providing (A) a combined signal representative of an additive combination of said plural color signals from said source; and means (50) for comparing said combined signal with a substantially fixed threshold reference level (54, 55) to provide an output signal representative of said combined signal; characterized in that said combining means provides a combined signal representative of the sum of the instantaneous magnitudes of said plural control signals from said source; and by:

a supply network (22) including a source of high voltage coupled to said image display device for providing a high operating voltage and resupply current to said image display device;

a display device beam current limiter network (26, 30 to 33, 36) coupled to said supply network and to said source of video signals, said beam current limiter network being responsive to the magnitude of resupply current (I_R) representative of beam currents conducted by said image display device for providing a first control signal representative of the magnitude of said representative resupply current above a threshold level;

means (35) for coupling said first control signal to said signal source (12, 14) for limiting the magnitudes of said plural color signals from said source in accordance with the magnitude of said first control signal;

means (16) for detecting said representative output signal to provide a second control signal; and means for coupling said second control signal to said signal source (12, 14) for limiting the magnitudes of said plural color signals from said source in accordance with the magnitude of said second control signal.

2. A system according to Claim 1, characterized in that said combining means (41, 42, 43) is coupled to said plural color signal output paths for providing a combined signal representative of the sum of the instantaneous magnitudes of plural color signals conveyed by said plural color signal output paths.

Patentansprüche

1. Einrichtung in einem System zum Verarbeiten und Wiedergeben von Farbvideosignal-Bildinformation, mit

einer Quelle (10, 11, 12, 14, 17) für mehrere Farbvideosignale;

einer stromleitenden Farbbildwiedergabevorrichtung (20);

mehreren Farbsignalausgangswegen (Ausgänge von 17), die entsprechenden Ausgängen der Quelle für die mehreren Farbvideosignale zugeordnet sind;

einer Videoausgangssignal-Wiedergabetreiberstufe (18) zum Erzeugen mehrerer verstärkter, zur Ansteuerung von Signaleingängen der Wiedergabevorrichtung geeigneter Farbsignale in Anspra-

senses the color video signals directly for instantaneously limiting the magnitudes of video drive signals, except for the prescribed 3 millisecond output delay as discussed. Any additional peak beam currents, such as may occur during the 3 millisecond delay interval associated with the operation of the signal conditioning circuit, are subject to being limited by the action of network 30 in the peak beam current limiting mode if such additional peak beam currents are of sufficient magnitude. The use of the signal conditioning circuit to limit peak beam currents avoids the delays associated with the kinescope resupply system with which beam limiter network 30 is associated.

The signal conditioning network is preferably DC coupled to the video signal path, e.g., between the output of matrix network 17 and the gain control inputs of luminance processor 14 and chrominance processor 12, and controls the video signal amplitude substantially without affecting the video signal DC level to avoid transient image brightness changes as the video signal peak-to-peak amplitude is controlled.

The signal conditioning network also is preferably coupled to a low level video signal path, rather than to a high level video signal path such as between the outputs of driver 18 and the kinescope cathode electrodes. This preference is dictated by the desirability of avoiding the use of more costly larger power sensing resistors (e.g., 41—43) which exhibit increased parasitic capacitance, and to minimize the likelihood of signal loading effects and parasitic bandwidth limiting effects. The latter two effects can readily occur in the case of sensing video signals in the signal path from the output driver stage to the kinescope cathodes.

Sensing the plural r, g and b color signals rather than sensing only the luminance signal component provides a more accurate indication of the presence of excessive peak currents. In this regard it is noted that excessive beam currents can be generated in response to a yellow (r+g) color signal, a cyan (b+g) color signal, a magenta (r+b) color signal, or a combination of these color signals, even when the level of the luminance signal is below the threshold of comparator transistor 50. Thus sensing only the luminance component may result in the signal conditioning circuit remaining inoperative when excessive beam currents resulting from color information are present.

Claims

1. In a system for processing and displaying color video signal image information, apparatus comprising:

a source (10, 11, 12, 14, 17) of plural color video signals;

a current-conducting color image display device (20);

plural color signal output paths (outputs of 17) associated with respective outputs of said source of plural color signals;

a video output signal display driver stage (18) for

providing plural amplified color signals suitable for driving signal inputs of said display device in response to plural color signals received as inputs from said plural signal output paths;

combining means (41, 42, 43) for providing (A) a combined signal representative of an additive combination of said plural color signals from said source; and means (50) for comparing said combined signal with a substantially fixed threshold reference level (54, 55) to provide an output signal representative of said combined signal; characterized in that said combining means provides a combined signal representative of the sum of the instantaneous magnitudes of said plural control signals from said source; and by:

a supply network (22) including a source of high voltage coupled to said image display device for providing a high operating voltage and resupply current to said image display device;

a display device beam current limiter network (26, 30 to 33, 36) coupled to said supply network and to said source of video signals, said beam current limiter network being responsive to the magnitude of resupply current (I_R) representative of beam currents conducted by said image display device for providing a first control signal representative of the magnitude of said representative resupply current above a threshold level;

means (35) for coupling said first control signal to said signal source (12, 14) for limiting the magnitudes of said plural color signals from said source in accordance with the magnitude of said first control signal;

means (16) for detecting said representative output signal to provide a second control signal; and means for coupling said second control signal to said signal source (12, 14) for limiting the magnitudes of said plural color signals from said source in accordance with the magnitude of said second control signal.

2. A system according to Claim 1, characterized in that said combining means (41, 42, 43) is coupled to said plural color-signal output paths for providing a combined signal representative of the sum of the instantaneous magnitudes of plural color signals conveyed by said plural color signal output paths.

Patentansprüche

1. Einrichtung in einem System zum Verarbeiten und Wiedergeben von Farbvideosignal-Bildinformation, mit

einer Quelle (10, 11, 12, 14, 17) für mehrere Farbvideosignale;

einer stromleitenden Farbbildwiedergabevorrichtung (20);

mehreren Farbsignalausgangswegen (Ausgänge von 17), die entsprechenden Ausgängen der Quelle für die mehreren Farbvideosignale zugeordnet sind;

einer Videoausgangssignal-Wiedergabetreiberstufe (18) zum Erzeugen mehrerer verstärkter, zur Ansteuerung von Signaleingängen der Wiedergabevorrichtung geeigneter Farbsignale in Anspra-



che auf die mehreren Farbsignale, welche als Eingangssignale von den mehreren Signalausgangswegen empfangen wurden;

einer Kombiniervorrichtung (41, 42, 43) zum Erzeugen (A) eines kombinierten Signales, welches eine additive Kombination der mehreren Farbsignale von der Quelle darstellt und

einer Anordnung (50) zum Vergleichen des kombinierten Signales mit einem im wesentlichen festen Referenzschwellenwert (54, 55) zum Erzeugen eines für das kombinierte Signal repräsentativen Ausgangssignales, gekennzeichnet dadurch, daß die Kombiniervorrichtung ein kombiniertes Signal liefert, welches für die Summe der augenblicklichen Größen der mehreren Farbsignale von der Quelle repräsentativ ist, und durch

ein Versorgungsnetzwerk (22), welches eine mit der Bildwiedergabevorrichtung gekoppelte Hochspannungsquelle zum Erzeugen einer Betriebshochspannung und eines Versorgungsrückstromes für die Bildwiedergabevorrichtung enthält;

ein Wiedergabevorrichtungs-Strahlstrombegrenzernetzwerk (26, 30 bis 33, 36), welches mit dem Versorgungsnetzwerk sowie der Videosignalleitung gekoppelt ist und auf die Größe des für die von der Bildwiedergabevorrichtung geführten Strahlströme repräsentativen Versorgungsrückstromes (I_R) anspricht, um ein erstes Steuersignal zu erzeugen, welches für die Größe des repräsentativen Versorgungsrückstromes oberhalb eines Schwellenwertes repräsentativ ist;

eine Anordnung (35) zur Kopplung des ersten Steuersignals auf die Signalquelle (12, 14) zum Begrenzen der Größen der mehreren Farbsignale von der Quelle entsprechend der Größe des ersten Steuersignals;

eine Anordnung (16) zum Erfassen des repräsentativen Ausgangssignales, um ein zweites Steuersignal zu erzeugen; und

eine Anordnung zum Koppeln des zweiten Steuersignales auf die Signalquelle (12, 14) zum Begrenzen der Größen der mehreren Farbsignale von der Quelle entsprechend der Größe des zweiten Steuersignales.

2. Einrichtung nach Anspruch 1, dadurch gekennzeichnet, daß die Kombiniervorrichtung (41, 42, 43) mit den mehreren Farbsignalausgangswegen gekoppelt ist, um ein kombiniertes Signal zu erzeugen, welches für die Summe der augenblicklichen Größen der mehreren Farbsignale, welche von den mehreren Farbsignalausgangswegen geführt werden, repräsentativ ist.

Revendications

1. Dans un système pour le traitement et la visualisation d'une information d'image d'un signal vidéo couleur, un appareil comprenant:

une source (10, 11, 12, 14, 17) de plusieurs signaux vidéo couleurs;

un dispositif de visualisation d'image couleur conducteur de courant (20);

plusieurs trajets de sortie de signaux de couleur (sorties de 17) associés avec des sorties respectives de ladite source de plusieurs signaux de couleur;

un étage d'attaque de visualisation de signaux de sortie vidéo (18) pour produire plusieurs signaux amplifiés de couleur, appropriés à attaquer les entrées de signaux dudit dispositif de visualisation en réponse à plusieurs signaux de couleur reçus en tant qu'entrées desdits plusieurs trajets de sortie de signaux;

un moyen de combinaison (41, 42, 43) pour produire (A) un signal combiné représentatif d'une combinaison additive desdits plusieurs signaux de couleur de ladite source; et un moyen (50) pour comparer ledit signal combiné à un niveau de référence de seuil sensiblement fixe (54, 55) pour produire un signal de sortie représentatif dudit signal combiné; caractérisé en ce que ledit moyen de combinaison produit un signal combiné représentatif de la somme des grandeurs instantanées desdits plusieurs signaux de commande de ladite source; et par

un réseau d'alimentation (22) comprenant une source de haute tension couplée audit dispositif de visualisation de l'image pour produire une haute tension de fonctionnement et un courant de réalimentation pour ledit dispositif de visualisation de l'image;

un réseau limiteur de courant de faisceau du dispositif de visualisation (26, 30 à 33, 36) couplé audit réseau d'alimentation et à ladite source de signaux vidéo, ledit réseau limiteur de courant de faisceau répondant à la grandeur du courant de réalimentation (I_R) représentatif des courants de faisceau conduits par ledit dispositif de visualisation de l'image pour produire un premier signal de commande représentatif de la grandeur dudit courant représentatif de réalimentation au delà d'un niveau de seuil;

un moyen (35) pour coupler ledit premier signal de commande à ladite source de signaux (12, 14) pour limiter les grandeurs desdits plusieurs signaux de commande de ladite source selon la grandeur dudit premier signal de commande;

un moyen (16) pour détecter ledit signal représentatif de sortie pour produire un second signal de commande; et un moyen pour coupler ledit second signal de commande à ladite source de signaux (12, 14) pour limiter les grandeurs desdits plusieurs signaux de couleur de ladite source selon la grandeur dudit second signal de commande.

2. Système selon la revendication 1, caractérisé en ce que ledit moyen de combinaison (41, 42, 43) est couplé auxdits plusieurs trajets de sortie de signaux de couleur pour produire un signal combiné représentatif de la somme des grandeurs instantanées des plusieurs signaux de couleur transmis par lesdits plusieurs trajets de sortie de signaux de couleur.