

MOBILE WIRELESS COMMUNICATIONS DEVICE COMPRISING MULTI-FREQUENCY BAND ANTENNA AND RELATED METHODS

Field of the Invention

[0001] The present invention relates to the field of communications devices, and, more particularly, to mobile wireless communications devices and related methods.

Background of the Invention

[0002] Cellular communications systems continue to grow in popularity and have become an integral part of both personal and business communications. Cellular telephones allow users to place and receive voice calls most anywhere they travel. Moreover, as cellular telephone technology has increased, so too has the functionality of cellular devices. For example, many cellular devices now incorporate personal digital assistant (PDA) features such as calendars, address books, task lists, etc. Moreover, such multi-function devices may also allow users to wirelessly send and receive electronic mail (email) messages and access the Internet via a cellular network and/or a wireless local area network (WLAN), for example.

[0003] Even so, as the functionality of cellular communications devices continues to increase, so too does the demand for smaller devices which are easier and more convenient for users to carry. As a result, one style of cellular telephones which has gained wide popularity is the folding or "flip" phone. Flip phones typically have an upper housing with a display and speaker, and a lower housing or flap which carries the microphone. The keypad on such phones may be on either the upper housing or the lower housing, depending upon the particular model. The lower flap is connected to the upper housing by a hinge so that when not in use the upper and lower housings can be folded together to be more compact.

[0004] One example of a flip phone is disclosed in U.S. Patent No. 5,337,061 to Pye et al. The phone has two antennas, a first one of which is mounted on the lower flap and includes a ground plane and an active monopole fed by a coaxial feed from electronic circuitry inside the phone. The flap is pivotally connected to the main or upper section of the housing, and is folded against the main section when not in use. Another similar antenna is fitted in the main section, and both antennas are connected to transceiver circuitry in the phone. The antennas are designed to introduce deliberate mismatch to provide an effective switching system between the antennas without the need for separate circuit elements.

[0005] The antenna configuration of a cellular telephone may also significantly effect the overall size or footprint of the phone. Cellular telephones typically have antenna structures that support communications in multiple operating frequency bands. Various types of antennas for mobile devices are used, such as helix, "inverted F", folded dipole, and retractable antenna structures, for example. Helix and retractable antennas are typically deployed outside, i.e., on the exterior of, a mobile device, and inverted F and folded dipole antennas are typically within (i.e., on the interior of) a mobile device case or housing adjacent the top thereof.

[0006] Generally speaking, internal antennas allow cell phones to have a smaller footprint than do external antennas. Moreover, they are also preferred over external antennas for mechanical and ergonomic reasons. Internal antennas are also protected by the mobile device housing and therefore tend to be more durable than external antennas. External antennas may be cumbersome and make the mobile device difficult to use, particularly in limited-space environments.

[0007] Yet, one potential drawback of typical internal cellular phone antennas is that they are in relatively close proximity to the user's head when the phone is in use. As an antenna moves closer to a user's body, the amount of radio

frequency (RF) energy radiation absorbed by the body will typically increase. The amount of RF energy absorbed by a body when using a mobile phone is called the specific absorption rate (SAR), and the allowable SAR for mobile phones is typically limited by applicable government regulations to ensure safe user RF energy exposure levels.

[0008] One attempt to reduce radiation exposure from cell phone antennas is set forth in U.S. Patent No. 6,741,215 to Grant et al. This patent discloses various cellular phones with internal and external antenna configurations in which the antennas are positioned at the bottom of the phone to reduce radiation intensity experienced by a user, i.e., by moving the antenna farther away from the user's brain. Further, in some embodiments the housing of the phone forms an obtuse angle so that the bottom portion of the housing angles away from the user's face.

[0009] Despite such antenna configurations which allow for reduced radiation exposure, further advancements in antenna configurations, particularly internal antennas, may be desirable to allow for further reductions in overall device size while still providing relatively low SAR values.

Summary of the Invention

[0010] A mobile wireless communications device may include a housing and a multi-frequency band antenna carried within the housing. More particularly, the multi-frequency band antenna may include a main loop conductor having a gap therein defining first and second ends of the main loop conductor, a first branch conductor having a first end connected adjacent the first end of the main loop conductor and having a second end defining a first feed point, and a second branch conductor having a first end connected adjacent the second end of the main loop conductor and a second end defining a second feed point. Moreover, a third branch conductor has a first portion within the main loop conductor, and a second portion connected to the second feed point. The

antenna may further include a tuning branch conductor having a first end connected to the main loop conductor between the respective first ends of the first and second branches.

[0011] The multi-frequency band antenna may therefore be arranged to take up a relatively small footprint yet still provide desired performance. Moreover, the antenna configuration allows for convenient positioning at the bottom of a mobile device (e.g., cellular phone) printed circuit board (PCB), which aids in complying with applicable SAR requirements. This configuration may also allow for less impact on antenna performance due to blockage by a user's hand. That is, users typically hold cellular phones toward the middle to upper portion of the phone housing, and are therefore more likely to put their hands over such an antenna than they are an antenna positioned adjacent the lower portion of the housing.

[0012] By way of example, the first portion of the third branch conductor may comprise a loop and/or a patch. Also, the second portion of the third branch conductor may be connected to the second feed point via the second branch conductor.

[0013] The main loop conductor may have a generally rectangular shape with opposing first and second sides and opposing first and second ends, and the gap may be in the first side of the main loop conductor. Moreover, the respective first ends of the first branch conductor, the second branch conductor, and the tuning branch conductor may be connected to the first side of the main loop conductor. In particular, the main loop conductor may include non-planar portions to provide further space savings, for example.

[0014] The main loop conductor may advantageously have at least one tuning feature therein. By way of example, such tuning features may include meanders, zig-zags, loops, as well as other geometrical shapes. The first, second, and/or tuning branch conductors may also include similar tuning features therein. The mobile wireless communications device may further

include a dielectric substrate supporting the multi-frequency band antenna, and the main loop conductor, first and second branch conductors, and tuning branch conductor may each comprise a respective conductive trace on the dielectric substrate. The mobile wireless communications device may also include wireless transceiver circuitry carried by the dielectric substrate and connected to the multi-frequency band antenna.

[0015] A method aspect of the invention is for making a mobile wireless communications device and may include providing a housing, and positioning a multi-frequency band antenna within the housing, such as the one described briefly above.

Brief Description of the Drawings

[0016] FIG. 1 is a schematic block diagram of a mobile wireless communications device in accordance with the present invention illustrating certain internal components thereof.

[0017] FIG. 2 is a front elevational view of the mobile wireless communications device of FIG. 1.

[0018] FIG. 3 is a schematic diagram generally illustrating a multi-frequency band antenna for the mobile wireless communications device of FIG. 1.

[0019] FIGS. 4-6 are schematic diagrams of different embodiments of tuning features which may be used in various portions of the antenna of FIG. 3.

[0020] FIG. 7 is a perspective view of an embodiment of a dielectric substrate and associated antenna for use in the mobile wireless communications device of FIG. 1.

[0021] FIG. 8 is a rear elevational view of the dielectric substrate of FIG. 7.

[0022] FIGS 9 and 10 are perspective views of another embodiment of a dielectric substrate and associated antenna for use in the mobile wireless communications device shown from the top of the substrate looking down, and from the bottom of the substrate looking up, respectively.

[0023] FIGS. 11 and 12 are flow diagrams of methods for making a mobile wireless communications device in accordance with the present invention.

[0024] FIG. 13 is a schematic block diagram of an exemplary mobile wireless communications device for use with the present invention.

[0025] FIGS. 14-16 are schematic diagrams of alternate embodiments of the multi-frequency band antenna of FIG. 3.

[0026] FIG. 17 is a graph of gain vs. frequency for the antenna of FIG. 14.

Detailed Description of the Preferred Embodiments

[0027] The present invention will now be described more fully hereinafter with reference to the accompanying drawings, in which preferred embodiments of the invention are shown. This invention may, however, be embodied in many different forms and should not be construed as limited to the embodiments set forth herein. Rather, these embodiments are provided so that this disclosure will be thorough and complete, and will fully convey the scope of the invention to those skilled in the art. Like numbers refer to like elements throughout, and prime notation is used to indicate similar elements in alternate embodiments.

[0028] Referring now more particularly to FIGS. 1 and 2, a mobile wireless communications device, such as a mobile cellular device **20**, in accordance with the present invention is first described. The cellular device **20** illustratively includes a housing **21** having an upper portion **46** and a lower portion **47**, and a main dielectric substrate **67**, such as a printed circuit board (PCB) substrate, for example, carried by the housing. The illustrated housing **21** is a static housing, for example, as opposed to a flip or sliding housing which are used in many cellular telephones. However, these and other housing configurations may also be used.

[0029] Various circuitry **48** is carried by the dielectric substrate **67**, such as a microprocessor, memory, one or more wireless transceivers (e.g., cellular, WLAN, etc.), audio and power circuitry, etc., as will be appreciated by those

skilled in the art, and as will be discussed further below. A battery (not shown) is also preferably carried by the housing **21** for supplying power to the circuitry **48**.

[0030] Furthermore, an audio output transducer **49** (e.g., a speaker) is carried by the upper portion **46** of the housing **21** and connected to the circuitry **48**. One or more user input interface devices, such as a keypad **23**, is also preferably carried by the housing **21** and connected to the circuitry **48**. Other examples of user input interface devices include a scroll wheel **37** and a back button **36**. Of course, it will be appreciated that other user input interface devices (e.g., a stylus or touch screen interface) may be used in other embodiments.

[0031] The cellular device **20** further illustratively includes an antenna **45** carried within the lower portion **47** of the housing **21** comprising a pattern of conductive traces on the dielectric substrate **67**, as will be discussed further below. By placing the antenna **45** adjacent the lower portion **47** of the housing **21**, this advantageously increases the distance between the antenna and the user's head when the phone is in use to aid in complying with applicable SAR requirements.

[0032] More particularly, a user will typically hold the upper portion of the housing **21** very close to his head so that the audio output transducer **49** is directly next to his ear. Yet, the lower portion **47** of the housing **21** where an audio input transducer (i.e., microphone) is located need not be placed directly next to a user's mouth, and is typically held away from the user's mouth. That is, holding the audio input transducer close to the user's mouth may not only be uncomfortable for the user, but it may also distort the user's voice in some circumstances. In addition, the placement of the antenna **45** adjacent the lower portion **47** of the housing **21** also advantageously spaces the antenna farther away from the user's brain.

[0033] Another important benefit of placing the antenna **45** adjacent the lower portion **47** of the housing **21** is that this may allow for less impact on antenna performance due to blockage by a user's hand. That is, users typically hold cellular phones toward the middle to upper portion of the phone housing, and are therefore more likely to put their hands over such an antenna than they are an antenna mounted adjacent the lower portion **47** of the housing **21**.

Accordingly, more reliable performance may be achieved from placing the antenna **45** adjacent the lower portion **47** of the housing **21**.

[0034] Still another benefit of this configuration is that it provides more room for one or more auxiliary input/output (I/O) devices **50** to be carried at the upper portion **46** of the housing. Furthermore, by separating the antenna **45** from the auxiliary I/O device(s) **50**, this may allow for reduced interference therebetween.

[0035] Some examples of auxiliary I/O devices **50** include a WLAN (e.g., Bluetooth, IEEE 802.11) antenna for providing WLAN communication capabilities, and/or a satellite positioning system (e.g., GPS, Galileo, etc.) antenna for providing position location capabilities, as will be appreciated by those skilled in the art. Other examples of auxiliary I/O devices **50** include a second audio output transducer (e.g., a speaker for speaker phone operation), and a camera lens for providing digital camera capabilities, an electrical device connector (e.g., USB, headphone, secure digital (SD) or memory card, etc.).

[0036] It should be noted that the term "input/output" as used herein for the auxiliary I/O device(s) **50** means that such devices may have input and/or output capabilities, and they need not provide both in all embodiments. That is, devices such as camera lenses may only receive an optical input, for example, while a headphone jack may only provide an audio output.

[0037] The device **20** further illustratively includes a display **22** carried by the housing **21** and connected to the circuitry **48**. The back button **36** and scroll wheel **37** are also connected to the circuitry **48** for allowing a user to navigate

menus, text, etc., as will be appreciated by those skilled in the art. The scroll wheel 37 may also be referred to as a “thumb wheel” or a “track wheel” in some instances. The keypad 23 illustratively includes a plurality of multi-symbol keys 24 each having indicia of a plurality of respective symbols thereon. The keypad 23 also illustratively includes an alternate function key 25, a next key 26, a space key 27, a shift key 28, a return (or enter) key 29, and a backspace/delete key 30.

[0038] The next key 26 is also used to enter a “*” symbol upon first pressing or actuating the alternate function key 25. Similarly, the space key 27, shift key 28 and backspace key 30 are used to enter a “0” and “#”, respectively, upon first actuating the alternate function key 25. The keypad 23 further illustratively includes a send key 31, an end key 32, and a convenience (i.e., menu) key 39 for use in placing cellular telephone calls, as will be appreciated by those skilled in the art.

[0039] Moreover, the symbols on each key 24 are arranged in top and bottom rows. The symbols in the bottom rows are entered when a user presses a key 24 without first pressing the alternate function key 25, while the top row symbols are entered by first pressing the alternate function key. As seen in FIG. 2, the multi-symbol keys 24 are arranged in the first three rows on the keypad 23 below the send and end keys 31, 32. Furthermore, the letter symbols on each of the keys 24 are arranged to define a QWERTY layout. That is, the letters on the keypad 23 are presented in a three-row format, with the letters of each row being in the same order and relative position as in a standard QWERTY keypad.

[0040] Each row of keys (including the fourth row of function keys 25-29) are arranged in five columns. The multi-symbol keys 24 in the second, third, and fourth columns of the first, second, and third rows have numeric indicia thereon (i.e., 1 through 9) accessible by first actuating the alternate function key 25. Coupled with the next, space, and shift keys 26, 27, 28, which respectively

enter a “*”, “0”, and “#” upon first actuating the alternate function key **25**, as noted above, this set of keys defines a standard telephone keypad layout, as would be found on a traditional touch-tone telephone, as will be appreciated by those skilled in the art.

[0041] Accordingly, the mobile cellular device **20** may advantageously be used not only as a traditional cellular phone, but it may also be conveniently used for sending and/or receiving data over a cellular or other network, such as Internet and email data, for example. Of course, other keypad configurations may also be used in other embodiments. Multi-tap or predictive entry modes may be used for typing e-mails, etc. as will be appreciated by those skilled in the art.

[0042] Exemplary implementations of the antenna **45** are now discussed with reference to FIGS. 3 through 10. The antenna **45** is preferably a multi-frequency band antenna which provides enhanced transmission and reception characteristics over multiple operating frequencies. More particularly, the antenna **45** is designed to provide high gain, desired impedance matching, and meet applicable SAR requirements over a relatively wide bandwidth and multiple cellular frequency bands. By way of example, the antenna **45** preferably operates over five bands, namely a 850 MHz Global System for Mobile Communications (GSM) band, a 900 MHz GSM band, a DCS band, a PCS band, and a WCDMA band (i.e., up to about 2100 MHz), although it may be used for other bands/frequencies as well.

[0043] To conserve space, the antenna **45** may advantageously be implemented in three dimensions, as seen in FIGS. 7 through 10, although it may be implemented in two-dimensional or planar embodiments as well. The antenna **45** illustratively includes a first section **61** on the PCB **67**. A second section **62** wraps around from the PCB **67** onto an L-shaped dielectric extension or antenna retainer frame **63** which includes a vertical portion **51** extending outwardly from the PCB **67**, and an overhang portion **68** extending outwardly from the vertical portion and above an adjacent portion of the PCB. In some

embodiments, sidewalls **55** may also be positioned on opposing ends of the L-shaped dielectric extension **63** to provide additional support, if desired (see FIGS. 7 and 9).

[0044] The second section **62** of the antenna **45** illustratively includes a main loop antenna conductor **64** having a gap therein defining first and second ends **52**, **53** of the main loop conductor. The first section **61** of the antenna **45** illustratively includes a first branch conductor **70**, a second branch conductor **71**, and a tuning branch conductor **72**. More particularly, the first branch conductor **70** has a first end connected adjacent the first end **52** of the main loop conductor **64**, and a second end defining a first feed point, which in the illustrated example is connected to a signal source **54** (e.g., a wireless transceiver). The second branch conductor **71** has a first end connected adjacent the second end **53** of the main loop conductor **64** and a second end defining a second feed point, which in the illustrated example is connected to a ground plane conductor **69** of the PCB (FIG. 8).

[0045] The tuning branch conductor **72** has a first end connected to the main loop conductor **64** between the respective first ends of the first and second branches. That is, the first end of the tuning branch conductor **72** is connected to the main loop conductor **64** at some point along the length thereof between the first and second branch conductors **70**, **71**. The position of the branch **72** between sections **77** and **78** may conveniently be varied without significant effect on frequency parameters. In the present example, the main loop conductor **64** has a generally rectangular shape with a first side including segments **75-78** and the gap, an opposing second side **74**, and opposing first and second ends **79**, **80**. The first and second sections **61**, **62** of the antenna **45** may be formed using printed or patterned conductive circuit traces, as seen in FIGS. 7-10.

[0046] While the respective first ends of the first branch conductor **70**, the second branch conductor **71**, and the tuning branch conductor **72** are connected

to the first side of the main loop conductor **64** in the illustrated embodiment, other configurations are also possible. For example, the first end of the tuning branch conductor **72** may be connected to the second side **74** or either of the first and second ends **79, 80**.

[0047] As noted above, the second section **62** of the antenna **45** may be positioned on the vertical portion **51** of the L-shaped dielectric extension **63**. This advantageously allows the overall footprint of the antenna **45** on the top (i.e., circuitry) side of the PCB **67** to be significantly reduced. Moreover, portions of the main loop conductor **64** may also wrap around onto the overhang portion **68** of the dielectric extension **63** to provide still further space savings. It should be noted, however, that the antenna **45** may be implemented in two dimensions (i.e., where the first and second sections **61, 62** are in the same plane), in certain embodiments if enough space is available, and that other 3D configurations are also possible, as will be appreciated by those skilled in the art.

[0048] The main loop conductor **64** is defined by sections **74-80**. The first branch conductor **70** may be connected to the signal source **54** with or without a passive matching network, as will be appreciated by those skilled in the art. The second branch conductor **71** is preferably connected to ground without a matching network, and the tuning branch conductor **72** is floating (i.e., not connected to the signal source **54** or ground).

[0049] Generally speaking, the length of branches **70, 71, and 72** are used to set the center frequency of operation. The square meandering or back-and-forth patterns of the branch conductors **70** and **72** is a tuning feature which can be used to change electric length, which varies the center frequency. Moreover, different shapes (i.e., tuning features) of the branches **70, 71, 72** may also be used to provide different frequencies. For example, in addition to the meandering and straight-line shapes illustrated in FIG. 3, other geometries which may be used for these branches include a saw-toothed or triangular

meander **40** (FIG. 4A), a branch **41** with a loop (FIG. 4B), etc. Various other shapes and combinations thereof may also be used to provide different frequency characteristics, as will be appreciated by those skilled in the art.

[0050] The section **73** of the main loop conductor **64** may also be used to control operating frequency. A variety of shapes and/or cut-outs may be used for the section **73**. Such tuning features may include, for example, a “dog bone” **90** (FIG. 5A), a half dog bone **91** (FIG. 5B), a hairpin **92** (FIG. 5C), a double hairpin **93** (FIG. 5D), a hairpin with a loop **94** (FIG. 5E), a meander **95** (FIG. 5F), and a sawtooth **96** (FIG. 5G). Moreover, in some embodiments the entire main loop conductor **64** may take one of the foregoing shapes or others, rather than just a section(s) thereof.

[0051] If a circuit element is needed in certain embodiments to adjust input impedance and/or widen bandwidth, a loop type pattern may be used, which creates an additional resonant tuning stage, as will be appreciated by those skilled in the art. If adequate space is available, straight-line portions may be used in the appropriate length. Yet, space is typically at a premium for internal cellular device antennas, and particularly so for compact models, and thus one of the above-described shapes (or others) will likely be preferred.

[0052] The width and shape of the section **74** influences antenna gain. The length of section **74** also impacts the operating frequency. However, it should be noted that the lengths of the sections **70**, **71**, **72**, and **73** (i.e., the length of the entire antenna **45**) also affects the operating frequency, as is the case with a typical dipole antenna.

[0053] The main loop conductor **64** may take a plurality of shapes, widths, and thicknesses. By way of example, the main loop conductor **64** may also be generally circular, square, polygonal, etc., although other shapes may also be used such as a U-shape **97** (FIG. 6A), a semi-circle **98** (FIG. 6B), and a kidney bean shape **99** (FIG. 6C).

[0054] Moreover, the section 74 may also have notches, patches, etc. Patches may be used to add surface area so that the section 74 can shape the beam. It should be noted that, in the case of a cellular telephone, the beam should preferably be directed away from the telephone, i.e., perpendicular to the plane of the PCB 37. By way of example, the width of the antenna 45 may be about 7 cm or less, the height of the first section 61 may be about .5 to 3 cm, and the height of the second section 62 may be about .5 to 3 cm depending upon the given implementation. Of course, other dimensions may also be used.

[0055] Regarding the S11 impedance characteristics of the antenna 45, to provide wide bandwidth a good match is needed over the frequency range of interest. Thus, it is desirable to shrink the S11 circle and then move the shrunk circle to the 50 Ohm center point, as will be appreciated by those skilled in the art. The area 73, as well as other portions of the antenna 45, may be used to shrink and/or move the S11 circle, which is preferably done in a distributed fashion. Further, the matching network and meandering portions of the antenna 45 may also be used to move the S11 circle toward the desired 50 Ohm center point. The center of the shrunk S11 circle is less critical since it can advantageously be moved toward the 50 Ohm point as noted above in accordance with the present invention.

[0056] General speaking, the above-described antenna 45 allows various shapes and lengths to be utilized to provide appropriate electrical lengths and current distribution. Some shapes are simple delay lines, while other shapes are designed to affect current in a particular area. As noted above, given unlimited space, many of the shapes and geometries described above may not be necessary. However, it is within the space constrained environments of mobile wireless communications devices, such as cellular telephones, where the above-described antenna features are particularly advantageous for providing desired performance over multiple operating bands.

[0057] Various changes in the basic layout of the antenna **45** may be made in certain embodiments. By way of example, the tuning branch **72** may be moved so that it extends from section **74** instead of area **73**. Other changes are also possible, as will be appreciated by those skilled in the art.

[0058] The PCB **67** has a first surface on which the circuitry **48** is positioned, and a second surface on which the ground plane conductor **69** is positioned. Preferably, the portions of the main loop conductor **64** on the overhang portion **68** of the L-shaped dielectric extension **63** are relatively positioned so as not to overlap the ground plane conductor **69**. This has been found to provide enhanced antenna performance characteristics. Similarly, it is also preferable that none of the first, second or tuning branch conductors **70**, **71**, **72** overlap the ground plane conductor **69**.

[0059] In accordance with another embodiment discussed now with reference to FIG. 14, the antenna **45'** may also advantageously include a third branch conductor **100'** which widens the antenna bandwidth at high frequencies. By way of example, the antenna **45'** may be used to provide relatively high antenna gain and low return loss over multiple frequency bands including the GSM, DCS, and PCS bands noted above, as well as the Universal Mobile Telecommunications Service (UMTS) band. Of course, it will be appreciated that the antenna **45'** may be designed to operate over different frequency bands as well, as will be appreciated by those skilled in the art.

[0060] In particular, the third branch conductor **100'** illustratively includes a first portion **101'** within the main loop conductor **64'**, and a second portion **102'** connected to the second feed point, which in the illustrated embodiment is a ground connection. The third branch conductor **100'** may take various shapes/configurations depending upon the particular application. In the illustrated example, the second portion **102'** of the third branch conductor **100'** is connected to the second feed point (i.e., ground) via the second branch conductor **71'**.

[0061] In another embodiment illustrated in FIG. 15, the second portion **102''** may be connected directly to the feed point (here ground). The first and/or second portions **101''**, **102''** may also define various tuning features, such as the illustrated loop. Still another possibility is that the first portion **101'''** may be a patch (FIG. 16). As discussed further above with respect to the other branches **70-72**, numerous other tuning features and configurations may also be used, as will be appreciated by those skilled in the art.

[0062] Measured return loss for an antenna having the configuration illustrated in FIG. 14 is shown in the graph of FIG. 17. Inclusion of the third branch conductor **100'** advantageously provided increased gain and S11 bandwidth with respect to the antenna **45** shown in FIG. 3 over the illustrated frequency range. The corresponding frequency and S11 values for measurement points 1-8 shown in the graph are listed in Table 1, below.

Point No.	Frequency (MHz)	S11 (dB)
1	824.0000	-9.493
2	880.0000	-8.070
3	915.0000	-8.428
4	960.0000	-7.185
5	1710.0000	-8.268
6	1828.0000	-13.150
7	1960.0000	-10.319
8	2170.0000	-11.880

Table 1

[0063] A first method aspect of the invention for making a mobile wireless communications device **20** is now described with reference to FIG. 11. The method begins (Block **110**) with providing a housing **21** having an upper

portion 46 and a lower portion 47, a dielectric substrate 67 carried by the housing, circuitry 48 carried by the dielectric substrate, an audio output transducer 49 carried by the upper portion of the housing and connected to the circuitry, and a user input interface device (e.g., the keypad 23) carried by the housing and connected to the circuitry, at Block 111. The method further illustratively includes positioning at least one auxiliary input/output device 50 within the upper portion 46 of the housing 21 and connected to the circuitry 48, at Block 112, and positioning an antenna 45 within the lower portion 47 of the housing and comprising a pattern of conductive traces on the dielectric substrate, at Block 113, thus concluding the illustrated method (Block 114).

[0064] Another method aspect of the invention for making a mobile wireless communications device 20 is now described with reference to FIG. 12. The method begins (Block 120) with forming an L-shaped dielectric extension 63 comprising a vertical portion 51 and an overhang portion 68 extending outwardly from the vertical portion, with at least one conductive trace on the overhang portion, at Block 121. The method further illustratively includes connecting the vertical portion 51 of the L-shaped dielectric extension 63 to a main dielectric substrate 67 so that the vertical portion extends outwardly therefrom, so that the overhang portion 68 extends above an adjacent portion of the main dielectric substrate 67, and the at least one conductive trace does not overlap a ground plane conductor 69 on the dielectric substrate, at Block 122. Further, the main dielectric substrate 67 may be mounted in a housing 21, at Block 123, thus concluding the illustrated method (Block 124). Of course, it will be appreciated by those of skill in the art that the order of steps described in the above-noted methods is merely exemplary, and various steps may be performed in different orders in different embodiments.

[0065] Another example of a hand-held mobile wireless communications device 1000 that may be used in accordance the present invention is further described in the example below with reference to FIG. 13. The device 1000

illustratively includes a housing **1200**, a keypad **1400** and an output device **1600**. The output device shown is a display **1600**, which is preferably a full graphic LCD. Other types of output devices may alternatively be utilized. A processing device **1800** is contained within the housing **1200** and is coupled between the keypad **1400** and the display **1600**. The processing device **1800** controls the operation of the display **1600**, as well as the overall operation of the mobile device **1000**, in response to actuation of keys on the keypad **1400** by the user.

[0066] The housing **1200** may be elongated vertically, or may take on other sizes and shapes (including clamshell housing structures). The keypad may include a mode selection key, or other hardware or software for switching between text entry and telephony entry.

[0067] In addition to the processing device **1800**, other parts of the mobile device **1000** are shown schematically in FIG. 13. These include a communications subsystem **1001**; a short-range communications subsystem **1020**; the keypad **1400** and the display **1600**, along with other input/output devices **1060**, **1080**, **1100** and **1120**; as well as memory devices **1160**, **1180** and various other device subsystems **1201**. The mobile device **1000** is preferably a two-way RF communications device having voice and data communications capabilities. In addition, the mobile device **1000** preferably has the capability to communicate with other computer systems via the Internet.

[0068] Operating system software executed by the processing device **1800** is preferably stored in a persistent store, such as the flash memory **1160**, but may be stored in other types of memory devices, such as a read only memory (ROM) or similar storage element. In addition, system software, specific device applications, or parts thereof, may be temporarily loaded into a volatile store, such as the random access memory (RAM) **1180**. Communications signals received by the mobile device may also be stored in the RAM **1180**.

[0069] The processing device **1800**, in addition to its operating system functions, enables execution of software applications **1300A-1300N** on the device **1000**. A predetermined set of applications that control basic device operations, such as data and voice communications **1300A** and **1300B**, may be installed on the device **1000** during manufacture. In addition, a personal information manager (PIM) application may be installed during manufacture. The PIM is preferably capable of organizing and managing data items, such as e-mail, calendar events, voice mails, appointments, and task items. The PIM application is also preferably capable of sending and receiving data items via a wireless network **1401**. Preferably, the PIM data items are seamlessly integrated, synchronized and updated via the wireless network **1401** with the device user's corresponding data items stored or associated with a host computer system.

[0070] Communication functions, including data and voice communications, are performed through the communications subsystem **1001**, and possibly through the short-range communications subsystem. The communications subsystem **1001** includes a receiver **1500**, a transmitter **1520**, and one or more antennas **1540** and **1560**. In addition, the communications subsystem **1001** also includes a processing module, such as a digital signal processor (DSP) **1580**, and local oscillators (LOs) **1601**. The specific design and implementation of the communications subsystem **1001** is dependent upon the communications network in which the mobile device **1000** is intended to operate. For example, a mobile device **1000** may include a communications subsystem **1001** designed to operate with the Mobitex™, Data TAC™ or General Packet Radio Service (GPRS) mobile data communications networks, and also designed to operate with any of a variety of voice communications networks, such as AMPS, TDMA, CDMA, PCS, GSM, etc. Other types of data and voice networks, both separate and integrated, may also be utilized with the mobile device **1000**.

[0071] Network access requirements vary depending upon the type of communication system. For example, in the Mobitex and DataTAC networks, mobile devices are registered on the network using a unique personal identification number or PIN associated with each device. In GPRS networks, however, network access is associated with a subscriber or user of a device. A GPRS device therefore requires a subscriber identity module, commonly referred to as a SIM card, in order to operate on a GPRS network.

[0072] When required network registration or activation procedures have been completed, the mobile device **1000** may send and receive communications signals over the communication network **1401**. Signals received from the communications network **1401** by the antenna **1540** are routed to the receiver **1500**, which provides for signal amplification, frequency down conversion, filtering, channel selection, etc., and may also provide analog to digital conversion. Analog-to-digital conversion of the received signal allows the DSP **1580** to perform more complex communications functions, such as demodulation and decoding. In a similar manner, signals to be transmitted to the network **1401** are processed (e.g. modulated and encoded) by the DSP **1580** and are then provided to the transmitter **1520** for digital to analog conversion, frequency up conversion, filtering, amplification and transmission to the communication network **1401** (or networks) via the antenna **1560**.

[0073] In addition to processing communications signals, the DSP **1580** provides for control of the receiver **1500** and the transmitter **1520**. For example, gains applied to communications signals in the receiver **1500** and transmitter **1520** may be adaptively controlled through automatic gain control algorithms implemented in the DSP **1580**.

[0074] In a data communications mode, a received signal, such as a text message or web page download, is processed by the communications subsystem **1001** and is input to the processing device **1800**. The received signal is then further processed by the processing device **1800** for an output to the

display **1600**, or alternatively to some other auxiliary I/O device **1060**. A device user may also compose data items, such as e-mail messages, using the keypad **1400** and/or some other auxiliary I/O device **1060**, such as a touchpad, a rocker switch, a thumb-wheel, or some other type of input device. The composed data items may then be transmitted over the communications network **1401** via the communications subsystem **1001**.

[0075] In a voice communications mode, overall operation of the device is substantially similar to the data communications mode, except that received signals are output to a speaker **1100**, and signals for transmission are generated by a microphone **1120**. Alternative voice or audio I/O subsystems, such as a voice message recording subsystem, may also be implemented on the device **1000**. In addition, the display **1600** may also be utilized in voice communications mode, for example to display the identity of a calling party, the duration of a voice call, or other voice call related information.

[0076] The short-range communications subsystem enables communication between the mobile device **1000** and other proximate systems or devices, which need not necessarily be similar devices. For example, the short-range communications subsystem may include an infrared device and associated circuits and components, or a Bluetooth™ communications module to provide for communication with similarly-enabled systems and devices.

[0077] Many modifications and other embodiments of the invention will come to the mind of one skilled in the art having the benefit of the teachings presented in the foregoing descriptions and the associated drawings. Therefore, it is understood that the invention is not to be limited to the specific embodiments disclosed, and that modifications and embodiments are intended to be included within the scope of the appended claims.

THAT WHICH IS CLAIMED IS:

1. A mobile wireless communications device (20) comprising a housing (21) and a multi-frequency band antenna (45-45'') carried within said housing, said multi-frequency band antenna comprises:
 - a main loop conductor (64'-64'') having a gap therein defining first and second ends of said main loop conductor;
 - a first branch conductor (70'-70'') having a first end connected to the main loop conductor adjacent the first end thereof and having a second end defining a first feed point;
 - a second branch conductor (71'-71'') having a first end connected to the main loop conductor adjacent the second end thereof and a second end defining a second feed point,
 - a third branch conductor (100'-100'') having a first portion (101'-101'') located inside said main loop conductor; and
 - a tuning branch conductor (72'-72'') having a first end connected to said main loop conductor between the respective first ends of said first and second branches,
 - characterized in that said third branch conductor (100'-100'') comprises a second portion (102'-102'') located outside said main loop conductor and connected to the second feed point.
2. The mobile wireless communications device (20) of Claim 1 wherein at least one of the first and second portions (101'-101'', 102'-102'') of said third branch conductor (100'-100'') defines a loop.
3. The mobile wireless communications device (20) of Claim 1 wherein the first portion (101'-101'') of said third branch conductor (100'-100'') comprises a patch.

4. The mobile wireless communications device (20) of Claim 1 wherein the second portion (102'-102''') of said third branch conductor (100'-100''') is connected to the second feed point via said second branch conductor (71'-71''').

5. The mobile wireless communications device (20) of Claim 1 wherein said main loop conductor (64'-64''') has a generally rectangular shape with opposing first and second sides and opposing first and second ends; and wherein the gap is in the first side of said main loop conductor.

6. The mobile wireless communications device (20) of Claim 5 wherein the respective first ends of said first branch conductor (70'-70'''), said second branch conductor (71'-71'''), and said tuning branch conductor (72'-72''') are connected to the first side of said main loop conductor (64'-64''').

7. The mobile wireless communications device (20) of Claim 1 wherein said main loop conductor (64'-64''') includes non-planar portions.

8. The mobile wireless communications device (20) of Claim 1 wherein said main loop conductor (64'-64''') has at least one tuning feature therein.

9. The mobile wireless communications device (20) of Claim 1 wherein at least one of said first, second, third, and tuning branch conductors (70'-70''', 71'-71''', 100'-100''', 72'-72''') comprises a tuning feature therein.

10. The mobile wireless communications device (20) of Claim

1 further comprising a dielectric substrate (67) supporting said multi-frequency band antenna (45'-45''); and wherein said main loop conductor (64'-64''), first and second branch conductors (70'-70'', 71'-71''), and tuning branch conductor (72'-72'') each comprises a respective conductive trace on said dielectric substrate.

11. A method for making a mobile wireless communications device comprising:

providing a housing; and

positioning a multi-frequency band antenna according to any of claims 1 to 10 within the housing.