

Description

The present invention relates to optical communications systems, and particularly but not exclusively, to systems employing a broadband passive optical network (BPON) for carrying interactive high definition television (HDTV) services.

Advancing technical standards for television signals and consumer-demand for an increasing range of associated services has led to a need for systems capable of carrying interactive HDTV. For the distribution of conventional PAL encoded television signals the use of a BPON having a branched configuration has been proposed. However, it is found that because of the increased bandwidth needed for HDTV signals conventional networks are unable to carry more than a few channels within the limits imposed by the available power budget. This problem is further exacerbated by the need in an interactive HDTV system to provide channels for return data transmission from the customer stations to the head-end station.

There is known from, ECOC 87, Technical Digest, Vol. III, pages 79-87; C. Baack et al.: "Coherent multicarrier techniques in future broadband communication networks" a system for providing ISDN services, broadband communication service, video telephone and broadband distribution services such as HDTV to customers via respective single fibres. The head station employs a separate laser for each wavelength to be transmitted onto the fibre network and the customer's station employs heterodyne detection. Upstream transmission from customer's station is obtained by feeding the output of a separate opto-electronic converter into a fibre coupler in the customer's station and, for each customer, feeding an output from a respective coupler at the head station to a respective opto-electronic converter.

In Japanese patent application no 58-81812 (publication JP-A-59 208952) in the name of Fujitsu K.K. each of the two stations linked by go and return fibres has a local oscillator laser employed in a coherent heterodyne receiver. Light from the local oscillator laser in one station is modulated by local data for transmission to the other station. In such a point to point arrangement there is no need for a stable laser frequency because the feedback control acts to stabilise the frequency difference between the transmitter laser and local oscillator laser in a station.

The Fujitsu system is limited to one station receiving only f_2 from a single remote station, from which it produces $f_1 - f_2$ and thereby controls the transmitter to maintain $f_1 - f_2$ constant. If a station were to be coupled to more than one remote station then the feedback control would have present the signals $f_1 - f_2$, $f_1 - f_3$, etc and would not be able to function.

There is disclosed in ECOC 87, Technical Digest, Vol II, pages 122-125, R. Olshansky: "RF multiplexing techniques applied to video distribution in local net-

works" a system employing sub-carrier multiplexing in a head station for the distribution of video signals over an optical network.

In the Olshansky system a number of voltage controlled oscillators operating at microwave frequencies are directly frequency modulated. The outputs from the oscillators are combined in a combiner whose output is used to intensity modulate the transmitter laser, and Olshansky refers to wide bandwidth (15 GHz) devices as detectors in the remote terminals. With the Olshansky head-end arrangement, it would not be possible to employ a coherent heterodyne detection system in the customer stations because of a characteristic of the transmission spectrum of such a head-end known by engineers as "chirp".

This problem is avoided in the system of the present invention by the use of the external modulator which receives the light from the head-end laser and modulates it with the transmission signal.

According to the present invention an optical communications system comprises:

a head-end station including an optical source, a bi-directional transmissive broadband passive branched optical network arranged to distribute signals from the head-end station to customer stations and to carry return data transmissions from the customer stations to the head-end station, each customer station being coupled to a respective arm of the optical network, and including a coherent receiver having a local oscillator laser:

characterised in that the head-end station further includes a modulator associated with the optical source and arranged to receive light from its associated optical source and to modulate the light with a signal for distribution to the customer stations, and a broadband optical receiver arranged to receive and demodulate return data received via the optical network from the customer stations, and in that each customer station further includes transmission means arranged to receive light from its associated local oscillator laser and to modulate the light with the return data for transmission onto the network.

The present invention provides a system which has been found to offer significant advantages as a carrier for e.g. Interactive HDTV. The use of synchronous detection at each customer station increases the effective sensitivity of the system and so allows more channels to be carried within a given power budget. At the same time the local oscillator laser in each receiver provides a source for upstream data transmission. Since there is then effectively one source for each of the return data channels it is possible to use a broadband receiver at the head-end station to receive the return data, despite its relative insensitivity. The use of broadband detection in the head-end station receiver simplifies the requirements for the transmission circuitry in each customer station.

Preferably the bi-directional network is in the form of a single branched optical fibre arrangement, each customer station has its coherent receiver coupled to its respective arm via an optical coupler and the output from its transmission means is fed onto the network via the optical coupler.

Preferably the optical source has a frequency f_0 and its associated modulator is arranged to modulate the light with a sub-carrier multiplex of n channels where n is an integer greater than 2, the n channels having frequencies $f_1, f_2, \dots, f_n$ separated in frequency-space from each other and from f_0 , and the transmission means of each customer station are arranged to transmit the return data at a frequency f_r , where f_r is a frequency different from the frequencies $f_1, f_2, \dots, f_n$ of the downstream channels.

Preferably the head end station includes a further optical source having a frequency f_0 and an associated modulator, the n channels of the corresponding sub-carrier multiplex having frequencies $f_1, f_2, \dots, f_n$, separated in frequency-space from each other and f_0 and from $f_0, f_1, f_2, \dots, f_n$ and the frequency f_r of the return transmission is different from the frequencies $f_1, f_2, \dots, f_n$ of the downstream channels.

Preferably each customer station is arranged to select a frequency f_r spaced from but adjacent to the selected one of the downstream channels selected for reception by that customer station.

Preferably n is greater than or equal to 16.

Preferably the system includes at least 16 customer stations and the or each optical source of the head-end station has an optical power output of substantially 1 mW.

A system in accordance with the present invention will now be described in detail with respect to the accompanying drawings in which:

Figure 1 is a block diagram;

Figure 2 is a schematic showing the head-end station in greater detail;

Figure 3 is a graph showing the spectral positions of frequency components of an HDTV signal;

Figure 4 is a schematic showing a customer station; and

Figure 5 is a graph showing the spectral positions of interactive slots.

A system for distributing HDTV signals comprises a head-end station 1 connected via a passive branched optical fibre network 2 to a number of customer stations 3. In Figure 1, for clarity, only a single customer station is shown but in practice 16 or more stations will be connected to a single head-end station. The head-end station 1 includes a single optical source, which in the present example is provided by a distributed feedback laser 4 having an operating wavelength of 1.52nm and an output power of 1 mW. The output from the laser 4 is fed to an external a LiNbO_3 modulator 5 where it is intensity-modulated by a sub-carrier multiplex signal as described below. Alter-

natively a modulator formed from Potassium titanyl phosphate (KTP) may be used.

The amplitude of the optical output from the modulator 5 varies in accordance with the applied modulating signal. Phase or frequency modulation may alternatively be used. In the present example the modulating signal is a sub-carrier multiplex of 16 HDTV channels occupying a total bandwidth of approximately 10GHz. Although the channels may be analogue encoded in the preferred example they are digitally encoded with a data rate of the order of 500Mb/s, in which case the signals are encoded on the carrier from the laser using frequency shift keying. Figure 3 shows part of the spectrum of the output from the modulator.

The signal from the modulator 5 is coupled to the optical fibre network 2 via a coupler 10. The network 2 comprises a broadband passive branched optical network using a configuration with a single fibre extending to each customer station and passive splitters or couplers at each node of the network.

In Figure 2 the coupler 10 is shown as having two output ports connected to two fibres, and may be considered as the first stage of splitting in the branched network. Depending on the coupler construction it may have any convenient number of output ports.

Each customer station 3 includes a receiver employing a coherent heterodyne detection system. The respective arm of the fibre network 2 is fed to a coupler 6 at the input of each receiver. The coupler 6 also receives an optical input from a local oscillator laser 7 which is mixed with the input signal from the network. The frequency of the local oscillator laser 7 is controlled by an AFC control loop 8 which is in turn controlled by an input from a channel select circuit 9. The AFC control 8 locks the local oscillator laser 7 at a frequency offset from the 1.52nm carrier frequency by an appropriate amount to select a desired channel. Then when the signal from the local oscillator laser 7 is mixed with the input to the coupler 6 a low-frequency heterodyne output is produced. This output is fed to a low-frequency optical receiver 16 having a bandwidth of approximately 80 MHz for an analogue system or 350 MHz for a digital system. Such an ASK heterodyne system has a theoretical maximum sensitivity of -60 dBm and in practice a sensitivity as high as -50 dBm can be achieved.

The data output from the receiver may be used to provide feedback to the channel select mechanism, the initial tuning being achieved by looking for an encoded channel identification on the received signals and the lock subsequently being maintained by the AFC loop. The tuning is controlled by varying the drive current to the local oscillator and only a small shift is required to select a given channel.

In the preferred embodiment digital modulation is used and then it is straightforward to provide polarisation independence in the demodulation at the re-

ceiver. If however it is required to carry analogue modulated signals on the network then polarisation scrambling is used at the receiver to provide the required polarisation independence. The techniques of polarisation scrambling in coherent detection are described in detail in the paper by T.G. Hodgkinson et al. published at pages 513-514 of Electronics Letters, Vol 23, No.10, 7th May 1987.

The use of the network for interactive services requires the transmission of data in the return direction that is from each customer station upstream to the head-end station. The upstream data transmissions from individual stations will typically have a narrower bandwidth than the conventional HDTV signals and may, for example comprise PAL encoded TV signals. The downstream data may comprise an HDTV signal of the type described above as when, for example, the customer selects video programme material from a library held at the head-end station. In other applications when, for example, both upstream and downstream transmissions comprise digitised text, then both the upstream and downstream channels are of narrower bandwidth than the HDTV signals otherwise carried on the network.

As shown in Figure 4 the local oscillator laser 7 provides the optical source for the upstream data transmissions from each customer station. The output of the laser 7 is taken to a coupler 11. One output of the coupler 11 is fed via coupler 6 into the primary detection loop. The other output of the coupler 11 feeds a modulator 13. The modulator 13 modulates the optical signal from the laser 7 with the data for upstream transmission using, for example, amplitude shift keying (ASK). The output from the modulator 13 is fed via a polarisation scrambler 14 to an input/output coupler 12 and from there onto the network.

When a customer station enters interactive mode a frequency slot is allocated to the station from a selection of channels not used for broadcast so enabling wavelength reuse. Within the slot, the return channel is positioned adjacent to, but spaced from, the downstream channel, as shown in Figure 5.

At the head-end a wideband optical receiver 17 receives the entire multiplex of upstream customer traffic. If the split ratio is high then a coherent detector is used at the head-end, otherwise direct detection is employed. As shown in Figure 2, a portion of the output from the transmit laser 4 is coupled via a coupler 15 having a coupling ratio of typically 10: 1 into the path of the incoming optical signal to provide the reference signal for a conventional coherent detection system.

Although the above described embodiment is concerned with the distribution of HDTV signals and the return transmission of PAL encoded TV signals, it will be appreciated that the technique of the present invention can be used with any other suitable signals, so that the number of channels available in the SCM

will be inversely proportional to the bandwidth of the channels.

Whereas the optical network 2 is in the form of a single branched optical fibre, in an alternative arrangement it can be in the form of separate go and return branched optical fibres, in which case the output from the polarization scrambler 14 is fed directly to the respective arm of the return optical fibre, and the respective arm of the go optical fibre is connected to the coupler 6.

Claims

1. An optical communications system comprising; a head-end station (1) including an optical source (4), a bi-directional transmissive broadband passive branched optical network (2) arranged to distribute signals from the head-end station (1) to customer stations (3) and to carry return data transmissions from the customer stations (3) to the head-end station (1), each customer station (3) being coupled to a respective arm of the optical network (2), and including a coherent receiver (6, 7, 8, 16) having a local oscillator laser (7) : characterised in that the head-end station (1) further includes a modulator (5) associated with the optical source (4) and arranged to receive light from its associated optical source and to modulate the light with a signal for distribution to the customer stations, and a broadband optical receiver (17) arranged to receive and demodulate return data received via the optical network (2) from the customer stations (3), and in that each customer station (3) further includes transmission means (11, 13, 14) arranged to receive light from its associated local oscillator laser (7) and to modulate the light with the return data for transmission onto the network (2).
2. A system according to claim 1, in which the bi-directional network is in the form of a single branched optical fibre arrangement, each customer station (3) has its coherent receiver (6, 7, 3, 16) coupled to its respective arm via an optical coupler (12) and the output from its transmission means (11, 13, 14) is fed onto the network (2) via the optical coupler (12).
3. A system according to either claim 1 or claim 2, in which the optical source (4) has a frequency f_0 and its associated modulator (5) is arranged to modulate the light with a sub-carrier multiplex of n channels where n is an integer greater than 2, the n channels having frequencies $f_1, f_2, \dots, f_n$ separated in frequency-space from each other and from f_0 , and the transmission means (11, 13, 14) of each customer station (3) are arranged to



ceiver. If however it is required to carry analogue modulated signals on the network then polarisation scrambling is used at the receiver to provide the required polarisation independence. The techniques of polarisation scrambling in coherent detection are described in detail in the paper by T.G. Hodgkinson et al. published at pages 513-514 of Electronics Letters, Vol 23, No.10, 7th May 1987.

The use of the network for interactive services requires the transmission of data in the return direction that is from each customer station upstream to the head-end station. The upstream data transmissions from individual stations will typically have a narrower bandwidth than the conventional HDTV signals and may, for example comprise PAL encoded TV signals. The downstream data may comprise an HDTV signal of the type described above as when, for example, the customer selects video programme material from a library held at the head-end station. In other applications when, for example, both upstream and downstream transmissions comprise digitised text, then both the upstream and downstream channels are of narrower bandwidth than the HDTV signals otherwise carried on the network.

As shown in Figure 4 the local oscillator laser 7 provides the optical source for the upstream data transmissions from each customer station. The output of the laser 7 is taken to a coupler 11. One output of the coupler 11 is fed via coupler 6 into the primary detection loop. The other output of the coupler 11 feeds a modulator 13. The modulator 13 modulates the optical signal from the laser 7 with the data for upstream transmission using, for example, amplitude shift keying (ASK). The output from the modulator 13 is fed via a polarisation scrambler 14 to an input/output coupler 12 and from there onto the network.

When a customer station enters interactive mode a frequency slot is allocated to the station from a selection of channels not used for broadcast so enabling wavelength reuse. Within the slot, the return channel is positioned adjacent to, but spaced from, the downstream channel, as shown in Figure 5.

At the head-end a wideband optical receiver 17 receives the entire multiplex of upstream customer traffic. If the split ratio is high then a coherent detector is used at the head-end, otherwise direct detection is employed. As shown in Figure 2, a portion of the output from the transmit laser 4 is coupled via a coupler 15 having a coupling ratio of typically 10: 1 into the path of the incoming optical signal to provide the reference signal for a conventional coherent detection system.

Although the above described embodiment is concerned with the distribution of HDTV signals and the return transmission of PAL encoded TV signals, it will be appreciated that the technique of the present invention can be used with any other suitable signals, so that the number of channels available in the SCM

will be inversely proportional to the bandwidth of the channels.

Whereas the optical network 2 is in the form of a single branched optical fibre, in an alternative arrangement it can be in the form of separate go and return branched optical fibres, in which case the output from the polarization scrambler 14 is fed directly to the respective arm of the return optical fibre, and the respective arm of the go optical fibre is connected to the coupler 6.

Claims

1. An optical communications system comprising; a head-end station (1) including an optical source (4), a bi-directional transmissive broadband passive branched optical network (2) arranged to distribute signals from the head-end station (1) to customer stations (3) and to carry return data transmissions from the customer stations (3) to the head-end station (1), each customer station (3) being coupled to a respective arm of the optical network (2), and including a coherent receiver (6, 7, 8, 16) having a local oscillator laser (7) : characterised in that the head-end station (1) further includes a modulator (5) associated with the optical source (4) and arranged to receive light from its associated optical source and to modulate the light with a signal for distribution to the customer stations, and a broadband optical receiver (17) arranged to receive and demodulate return data received via the optical network (2) from the customer stations (3), and in that each customer station (3) further includes transmission means (11, 13, 14) arranged to receive light from its associated local oscillator laser (7) and to modulate the light with the return data for transmission onto the network (2).
2. A system according to claim 1, in which the bi-directional network is in the form of a single branched optical fibre arrangement, each customer station (3) has its coherent receiver (6, 7, 3, 16) coupled to its respective arm via an optical coupler (12) and the output from its transmission means (11, 13, 14) is fed onto the network (2) via the optical coupler (12).
3. A system according to either claim 1 or claim 2, in which the optical source (4) has a frequency f_0 and its associated modulator (5) is arranged to modulate the light with a sub-carrier multiplex of n channels where n is an integer greater than 2, the n channels having frequencies $f_1, f_2, \dots, f_n$ separated in frequency-space from each other and from f_0 , and the transmission means (11, 13, 14) of each customer station (3) are arranged to



transmit the return data at a frequency f_r where f_r is a frequency different from the frequencies $f_1, f_2, \dots, f_n$ of the downstream channels.

4. A system according to claim 3 in which the head-end station includes a further optical source (4) having a frequency f_0 and an associated modulator (5), the n channels of the corresponding sub-carrier multiplex having frequencies $f_1, f_2, \dots, f_n$ separated in frequency-space from each other and from f_0 and from $f_1, f_2, \dots, f_n$ and the frequency f_r of the return transmission is different from the frequencies $f_1, f_2, \dots, f_n$ of the downstream channels.
5. A system according to either claim 3 or claim 4, in which each customer station (3) is arranged to select a frequency f_r spaced from but adjacent to the one of the downstream channels selected for reception by that customer station.
6. A system according to any one of claims 3 to 5, in which n is greater than or equal to 16.
7. A system according to any one of the preceding claims, in which the system includes at least 16 customer stations (3) and the or each optical source (4) of the head-end station (1) has an optical power output of substantially 1 mW.

Patentansprüche

1. Optisches Kommunikationssystem mit einer Kopfstation (1) mit einer optischen Quelle (4), einem bidirektional übertragenden verzweigten passiven optischen Breitbandnetz (2), das eingerichtet ist, um Signale von der Kopfstation (1) an Kundenstationen (3) zu verteilen und Datenrückübertragungen von den Kundensationen (3) zur Kopfstation (1) zu leiten, wobei jede Kundenstation (3) jeweils an einen Zweig des optischen Netzes (2) gekoppelt ist und einen kohärenten Empfänger (6, 7, 8, 16) mit einem Lokaloszillator-Laser (7) umfaßt, dadurch gekennzeichnet, daß die Kopfstation (1) ferner einen Modulator (5), der der optischen Quelle (4) zugeordnet ist und eingerichtet ist, um Licht von der ihm zugeordneten optischen Quelle (4) zu empfangen und das Licht mit einem Signal zur Verteilung an die Kundenstationen zu modulieren, und einen optischen Breitbandempfänger (17) umfaßt, der eingerichtet ist, um über das optische Netz (2) von den Kundenstationen (3) empfangene Rückübertragungsdaten zu empfangen und zu demodulieren, und daß jede Kundenstation (3) ferner Sendemit-

tel (11, 13; 14) umfaßt, die eingerichtet sind, um Licht vom ihr zugeordneten Lokaloszillator-Laser (7) zu empfangen und das Licht mit den Rückübertragungsdaten für die Übertragung auf dem Netz (2) zu modulieren.

2. System nach Anspruch 1, bei dem das bidirektionale Netz die Form einer einzelnen verzweigten Faseranordnung hat und der kohärente Empfänger (6, 7, 8, 16) einer jeden Kundenstation (3) an den ihr entsprechenden Zweig über einen optischen Richtkoppler (12) gekoppelt ist und das Ausgangssignal der Sendemittel (11, 13, 14) einer jeden Kundenstation (3) über den optischen Richtkoppler (12) ins Netz (2) gespeist wird.
3. System nach Anspruch 1 oder 2, bei dem die optische Quelle (4) eine Frequenz f_0 hat und der ihr zugeordnete Modulator (5) eingerichtet ist, um das Licht mit einem n -kanaligen Subträger-Multiplexsignal zu modulieren, wobei n eine ganze Zahl größer als 2 ist und die n Kanäle voneinander im Frequenzraum beabstandete Frequenzen $f_1, f_2, \dots, f_n$ haben, und bei dem die Sendemittel (11, 13, 14) einer jeden Kundenstation (3) eingerichtet sind, um die Rückübertragungsdaten bei einer Frequenz f_r zu übertragen, wobei f_r eine von den Frequenzen $f_1, f_2, \dots, f_n$ der Stromabkanäle verschiedene Frequenz ist.
4. System nach Anspruch 3, bei dem die Kopfstation eine weitere optische Quelle (4) mit einer Frequenz f_0' und einen zugeordneten Modulator (5) enthält, wobei die n Kanäle der entsprechenden Subträger-Multiplexsignale Frequenzen $f_1', f_2', \dots, f_n'$ haben, die im Frequenzraum voneinander, von f_0' und von $f_1, f_2, \dots, f_n$ beabstandet sind, und bei dem die Frequenz f_r der Rückübertragung sich von den Frequenzen $f_1, f_2, \dots, f_n$ der Stromabkanäle unterscheidet.
5. System nach Anspruch 3 oder 4, bei dem jede Kundenstation (3) eingerichtet ist, um eine Frequenz f_r auszuwählen, die derjenigen der zum Empfang durch diese Kundenstation ausgewählten Stromabkanäle benachbart, doch von dieser verschieden ist.
6. System nach einem der Ansprüche 3 bis 5, bei dem n größer oder gleich 16 ist.
7. System nach einem der vorhergehenden Ansprüche, bei dem das System wenigstens 16 Kundenstationen (3) enthält, und bei dem die oder jede optische Quelle (4) der Kopfstation (1) eine optische Ausgangsleistung von ca. 1 mW hat.



Revendications

1. Système de communication optique comprend :

une station d'extrémité de tête (1) contenant une source optique (4), un réseau optique (2) ramifié passif à large bande, à transmission bi-directionnelle, agencé pour distribuer des signaux en provenance de la station d'extrémité de tête (1) à des stations de clients (3), et pour transporter des transmissions de données de retour des stations de clients (3) à la station d'extrémité de tête (1), chaque station de client (3) étant couplée à une branche respective du réseau optique (2) et comprenant un récepteur cohérent (6, 7, 8, 16) ayant un laser oscillateur local (7), caractérisé en ce que la station d'extrémité de tête (1) comprend en outre un modulateur (5) associé à la source optique (4) et agencé pour recevoir la lumière de sa source optique respective, et pour moduler la lumière avec un signal qu'il s'agit de distribuer aux stations de clients, et un récepteur optique à large bande (17) agencé pour recevoir et démoduler des données de retour reçues par l'intermédiaire du réseau optique (2) en provenance des stations de clients (3), et en ce que chaque station de client (3) comprend en outre des moyens d'émission (11, 13, 14) agencés pour recevoir de la lumière issue de son laser oscillateur local (7) respectif et pour moduler la lumière avec les données de retour afin de les transmettre sur le réseau (2).

2. Système selon la revendication 1, dans lequel le réseau bidirectionnel se présente sous la forme d'un unique dispositif à fibres optiques ramifié, chaque station de clients (3) possède son récepteur cohérent (6, 7, 8, 16) couplé à sa branche respective à travers un coupleur optique (12), et la sortie de son moyen d'émission (11, 13, 14) est envoyée sur le réseau (2) à travers le coupleur optique (12).

3. Système selon la revendication 1 ou la revendication 2, dans lequel la source optique (4) possède une fréquence (f_0), et son modulateur respectif (5) est agencé pour moduler la lumière avec un multiplex de sous-porteuses de n canaux, où n est un nombre entier supérieur à 2, les n canaux ayant des fréquences $f_1, f_2, \dots, f_n$ séparées les unes des autres et de f_0 par des intervalles de fréquence et les moyens d'émission (11, 13, 14) de chaque station de client (3) sont agencés pour transmettre les données de retour à une fréquence f_r , où f_r est une fréquence différente des fréquences $f_1, f_2, \dots, f_n$ des canaux descendants.

4. Système selon la revendication 3, dans lequel la station d'extrémité de tête comprend une autre

source optique (4) ayant une fréquence f_0' et un modulateur (5) respectif, les n canaux du multiplex de sous-porteuses ayant des fréquences $f_1', f_2', \dots, f_n'$ séparées les unes des autres et de f_0' ainsi que de $f_1, f_2, \dots, f_n$ par des intervalles de fréquence, et la fréquence f_r de l'émission de retour est différente des fréquences $f_1', f_2', \dots, f_n'$ canaux descendants.

5. Système selon la revendication 3 ou la revendication 4, dans lequel chaque station de client (3) est agencée pour sélectionner une fréquence f_r séparée de, mais adjacente à, celle des canaux descendants qui est sélectionnée pour la réception par cette station de client.

6. Système selon une quelconque des revendications 3 à 5, dans lequel n est supérieur ou égal à 16.

7. Système selon une des revendications précédentes, dans lequel le système comprend au moins 16 stations de clients (3) et la source optique ou chaque source optique (4) de chaque extrémité de tête (1) a une sortie de puissance optique de l'ordre de 1 mW.