

Description

The invention relates to a self-starting brushless two-phase type d.c. motor comprising a stator, a rotor and a commutating device which includes a presettable energizing circuit for the commutated energization of the stator phases and a detection device with only one detector for indicating the rotor position.

In brushless motors commutation is effected electronically. Rotor-position information can then be obtained by means of detectors, such as Hall elements. For polyphase motors satisfactory commutation and starting characteristics are obtained by the use of one detector per phase, which detectors are circumferentially spaced in conformity with the number of phases of the rotor. The disadvantage of this is that such motors are comparatively expensive. Therefore, the aim is to use only one detector. Single-phase motors obviously employ one detector. However, these motors have the inherent disadvantage that the direction of rotation is undefined. Moreover, the starting situation may be such, that upon energization, the rotor is in a stable position, which problem may also occur in polyphase motors. The two problems can be overcome by mechanical means, such as the provision of a "detent position", for example by ensuring by means of an auxiliary magnet that the motor stops in a position in which starting is possible in a predetermined direction. However, the drawback of mechanical and/or magnetic means is that such means also adversely affect the steady-state behaviour of the motor. In order to permit the use of only one detector in polyphase motors, specifically three-phase motors, it has therefore been proposed to start the motor by means of a rotating auxiliary field. This has the disadvantage that, during starting, the motor is not self-commutating and consequently exhibits unfavourable starting characteristic. The problem in the starting situation is solved in a motor according to DE-OS 24 28 718 where one rotor position detector is used to bring the rotor to a predetermined rest-position before starting it. In that motor one position detector for starting only is used and other measures have to be taken for commutation and further a test arrangement is provided to switch-off the starting circuit after start.

The invention aims at providing a brushless motor which is self-commutating during starting, thereby enabling it to be started by purely electronic means without the need for a separate rotor position-detector for starting only.

To this end the invention is characterized in that the detector is arranged to distinguish which of the two stator phases the rotor is mainly directed towards and when commutation has to take place, and in that the motor comprises a pre-setting circuit adapted to be controlled by the detection device for setting the energizing circuit, at least when the rotor is stationary, to one of the

two states which correspond to energization of the stator phase other than that towards which the rotor is mainly directed.

This combination of characteristic features results in a motor which comprises only one detector, which is self-commutating during starting, and which does not require any non-electronic starting means, nor a separate detector for starting only.

The invention is based on the insight that, although in a polyphase motor the rotor position cannot be detected unambiguously by means of only one detector, in a two-phase motor the two rotor positions that cannot be distinguished by means of one detector always correspond to one specific stator phase, so that self-commutating starting is possible using only one detector.

A motor in accordance with the invention, which comprises p pole-pairs, may further be characterized in that the detection device comprises a permanent-magnetic member having $2p$ pole-pairs, which member is rotatable in synchronism with the rotor, and in that the detector comprises a magneto-sensitive element, specifically a Hall element.

This embodiment may further be characterized in that the presetting circuit comprises a polarity detector for detecting the polarity of the magnetic field sensed by the magneto-sensitive element and a gate circuit for comparing the detected polarity with the state of the energizing circuit.

The undefined starting direction of some motors in accordance with the invention is not a problem for some uses. If a specific direction of rotation is required, an additional advantage of a solution in accordance with the invention will become apparent: in the motor in accordance with the invention the correct direction of rotation can be guaranteed in a simple manner. For this purpose a preferred embodiment of the invention may further be characterized in that the presettable energizing circuit is preset to the switching sequence corresponding to the desired direction of rotation of the rotor and can be switched, in accordance with a cyclic permutation, under command of commutation signals, regardless of the actual direction of rotation of the rotor. This further characteristic feature is based on the insight that when the motor is started commutating pulses are generated as a result of the self-commutating starting behaviour of the motor in accordance with the invention. By electronically laying down the switching sequence of the motor phases it is achieved that the phases are consecutively energized in the correct sense, even in the case of an incorrect starting direction. In the case of such an incorrect starting direction the rotating stator field and the rotor which rotates in the opposite sense "meet" each other and the rotor locks in after a maximum of two commutations. In the case of a p -pole motor the maximum rotation in the incorrect direction is equal to substantially

(11)

360°

p

For many uses, such as motors in cassette recorders, such an incorrect starting motion presents no problem at all. It may then be advantageous that the presettable energizing circuit comprises a control input and is adapted to preset the switching sequence to one of the two possible directions as a function of a signal on said control input in order to render the direction of rotation of the motor reversible.

This preferred embodiment may further be characterized in that the detection device comprises a permanent-magnetic member having 2p pole-pairs, which member is rotatable in synchronism with the rotor, in that the detector comprises a magneto-sensitive element, specifically a Hall element, and in that there is provided a commutating-signal generator for generating commutating signals for the energizing circuit in synchronism with the magnetic-field polarity changes detected by the detector.

A first version of said preferred embodiment may be characterized in that the presetting circuit comprises a polarity detector for detecting the polarity of the magnetic field sensed by the magneto-sensitive element and a first gate circuit for comparing the detected polarity with the state of the energizing circuit.

A further characteristic feature is that the comparator circuit is adapted to supply additional commutating signals to the energizing circuit. In said first version of the preferred embodiment of the invention an incorrect rotor position is corrected by supplying an additional commutating pulse.

A second alternative version of the preferred embodiment of the invention may be characterized in that the commutating-signal generator comprises a polarity detector for detecting the polarity of the magnetic field sensed by the magneto-sensitive element and a gate circuit for comparing the detected polarity with the state of the energizing circuit and generating a commutating signal if said state does not correspond to the detected polarity. In this version the commutating signal is supplied by the presetting circuit. This version is based on the insight that each commutation is in fact preceded by an "incorrect" energizing condition. Indeed, the output signal of the position detector changes, at the commutation instant, whilst the energizing condition of the stator changes only shortly afterwards. This means that the rotor position and the energizing condition briefly do not correspond to each other, which non-correspondence can be signalled by the presetting circuit. In the present version this is utilized by having the presetting circuit generate the commutating pulses in the case of these apparently incorrect rotor positions, so that a separate commutating-pulse generator may be dispensed with.

In said first and second version the detected

rotor position is compared with the energizing condition at the instant of starting. However, regardless of the energizing condition which would occur up on starting of the motor, it is alternatively possible to set the energizing circuit to one of the two possible correct states depending on the detected rotor position during build-up of the supply voltage. For this purpose a third version of the preferred embodiment of the invention is characterized in that there are provided means for detecting the application of a supply voltage, in that the presetting circuit comprises a polarity detector for detecting the polarity of the magnetic field sensed by the magneto-sensitive element, and a first gate circuit for comparing the detected polarity with the state of the energizing circuit and, after detection of the application of a supply voltage, setting the energizing circuit to a state which is in conformity with the detected polarity.

In this third version these steps also ensure correct starting. Since the commutation may be disturbed by spurious pulses and this is not readily corrected as in the first and second versions, it is advantageous if appropriate steps are taken in this third version. A suitable solution is then characterized in that there is provided a second gate circuit for suppressing the next commutating signal under command of the comparator circuit.

By suppressing the next commutating pulse instead of generating an additional commutating pulse it is achieved that the commutation is corrected immediately. Indeed a spurious impulse will practically always give rise to an additional commutation instead of suppressing a commutation, so that it is more favourable to suppress a commutating pulse than to generate an additional pulse.

It is advantageous if the energizing circuit of the motor in accordance with the invention comprises a shift register. A further characteristic feature is that the shift register has an adjustable shifting direction. Thus, the direction of rotation of the motor can be selected in a simple manner. With respect to its construction, the motor in accordance with the invention may further be characterized by

a rotor having a cylindrical permanent magnet which is magnetized to have substantially 2p-poles,

a stator having two-phase windings, arranged coaxially with the rotor inside the cylindrical permanent magnet,

a wiring support secured to the stator, to which support the stator windings are connected, and a substrate arranged on the wiring support, on which substrate at least the magneto-sensitive element is arranged in such a way that said element is disposed within the magnetic range of influence of the end face of the cylindrical permanent magnet which faces said support, the permanent magnet being provided with a 4p-pole magnetization at the location of said end face.

12

The invention will now be described in more detail with reference to the drawings, in which Figure 1 schematically represents the principle of the motor in accordance with the invention, Figure 2 is a diagram to explain the operation of the motor of Figure 1,

Figure 3 shows a first version of the circuit 4 in the motor of Figure 1,

Figure 4 shows an alternative to a part of the circuit of Figure 3,

Figure 5 shows a second version of said circuit 4,

Figure 6 shows a third version of said circuit 4 and

Figure 7 is a sectional view of a preferred embodiment of the invention.

Figure 1 schematically represents a motor with energizing circuit in accordance with the invention. The motor has a rotor 1, which in the present example is magnetized to have two poles (N, S). The rotor position is specified by an angle ϕ , which in the condition shown is zero. The stator comprises four coils L_1 , L_2 , L_3 and L_4 with connections 5, 6, 7 and 8 respectively. A position encoder 2, which is magnetized to have four poles, is mechanically coupled to—or arranged on—the rotor 1. A field sensor H, specifically a Hall element, is in magnetic contact with said position encoder 2. The position of the position encoder 2 and sensor H relative to the rotor position is such that the sensor H detects polarity changes via the position encoder 2 at those rotor positions ϕ where commutation of the energization of the stator coils L_1 , L_2 , L_3 and L_4 is most appropriate, that is, approximately at the positions $\phi=45^\circ$, 135° , 225° and 315° . The output signal of the field sensor H is applied to an input 3 of an energizing circuit 4, which energizing circuit 4 in turn energizes each of the stator coils L_1 , L_2 , L_3 and L_4 .

Figure 2 shows the variation T_{L1} , T_{L2} , T_{L3} and T_{L4} of the torque T exerted on the rotor 1 as a function of the rotor position ϕ upon energization of the coils L_1 , L_2 , L_3 and L_4 respectively, and the field (N, S) of the position encoder 2 sensed by the field sensor H as a function of said rotor position ϕ .

If upon starting of the motor—after application of a supply voltage or after blocking of the rotor—a specific coil is energized, the rotor will or will not begin to revolve depending on the instantaneous position ϕ . If, for example, coil L_4 is energized, the diagram of Figure 2 shows that the torque exerted on the rotor is zero at $\phi=270^\circ$. An unstable position of equilibrium for which $T=0$ is found at $\phi=90^\circ$, in which position the motor will not start in the loaded condition. For rotor positions ϕ between 270° and 315° and those between 225° and 270° the rotor will be drawn towards the position of equilibrium $\phi=270^\circ$. Outside this range of 225° — 315° the rotor will also be attracted towards $\phi=270^\circ$, but commutation is effected at the appropriate instant when at $\phi=225^\circ$ or $\phi=315^\circ$ the field sensor H senses a field change via the position encoder 2.

When the rotor positions for which energization

of the stator coil L_4 gives rise to starting problems are compared with the positions of the position encoder 2 coupled thereto, it is found that starting is problematic when the field sensor H senses S-magnetization of the position encoder 2. A similar comparison carried out for energization of the stator coils L_1 , L_2 and L_3 shows that when the field sensor H senses an S-magnetization starting is problematic upon energization of coil L_2 or L_3 and that when the field sensor H senses N-magnetization starting is problematic when L_1 or L_3 is energized. In accordance with the invention starting can be guaranteed by constraining the energizing circuit 4 so that the combinations of energization of one of the coils to L_4 and the polarity of the field from the position encoder 2 sensed by the field sensor H for which starting gives rise to problems are excluded. The motor will then always start though with an undefined direction of rotation.

A specific direction of rotation can be obtained by designing the energizing circuit 4 so that the energizing sequence of the coils L_1 to L_4 is fixed, for example the sequence L_1 , L_2 , L_3 , L_4 for clockwise rotation, switching to the next coil in said sequence being effected under command of the field sensor H. Thus, after starting a rotating field is obtained in a specified direction, regardless of the starting direction of the rotor 1, so that upon starting of the rotor in the incorrect direction the rotor position will be in conformity with the energization and the rotor locks in to the rotating field and begins to rotate in the correct direction after half a revolution at most. If, for example, coil L_4 in the configuration shown in Figure 1 is energized when the position of the rotor 1 is as shown, the energizing circuit 4 being set for clockwise energization, the rotor 1 will begin to revolve in the anticlockwise direction. At $\phi=-45^\circ$ commutation is effected under command of the field sensor H and coil L_1 is energized, so that the rotor motion is braked and the direction is reversed. The rotor then continues to the position $\phi=-45^\circ$ at which instant coil L_2 is energized and the rotor locks in to the clockwise rotating field. The maximum rotation in the incorrect direction is less than 180° , namely the rotation from $\phi<-45^\circ$ to $\phi>-135^\circ$. For many uses such as in cassette recorders this incorrect rotation upon starting presents no problem.

Figure 3 shows an example of the energizing circuit 4 (see Figure 1), which together with the field sensor H may be incorporated in one integrated circuit. The circuit comprises a circuit 1 which is cyclically switched under command of a pulse on an input 13, for example a 4-bit shift register which is coupled end-around and in which one logic "one" and three logic "zeros" are stored. Thus, one of the four outputs Q_1 to Q_4 of the circuit 12 is always energized differently. The four outputs Q_1 to Q_4 are connected to the terminals 5 to 8 of the coils L_1 to L_4 , as the case may be via buffer amplifiers 14 to 17, so that always one of the coils L_1 to L_4 is energized. The shift register 12 has a fixed shifting direction

which is for example optionally presettable by the application of one of two possible logic levels to an input 24. This ensures that the coils L_1 to L_4 are energized in a predetermined sequence. By making the shifting direction of the shift register 12 adjustable it is possible to select the direction of rotation of the rotor by applying the logic level which corresponds to the desired direction of rotation to the input 24.

The shift register 12 is advanced under control of pulses on input 13. In order to synchronize this shifting with the rotor motion the signal supplied by the field sensor H is applied to a pulse shaper 9 via input 3, which pulse shaper produces a pulse on input 13 upon the occurrence of each field transition which is detected, that is at the desired commutation instants when the rotor position ϕ is 45° , 135° , 225° or 315° , so that self-commutating operation of the motor is possible.

In order to prevent the stator coils from being energized in such a way that the motor does not start, the polarity of the field sensed by the field sensor H is compared with the position of the shift register 12, as has been explained with reference to Figure 2. For this purpose the signal from the field sensor H is applied, via input 3, to a detector 10 which detects a signal corresponding to N-magnetization, and to a detector 11 which detects a signal corresponding to S-magnetization. Whether coil L_1 or coil L_3 is energized is detected by means of an OR-gate 18 connected to outputs Q_1 and Q_3 and whether coil L_2 or coil L_4 is energized is detected by means of an OR-gate 19 connected to outputs Q_2 and Q_4 . The output signals of the detector 10 and OR-gate 18 are applied to an AND-gate 20 and the signals from detector 11 and OR-gate 19 are applied to an AND-gate 21. The output signals of the AND-gates 20 and 21 are combined, for example by means of an OR-gate or, as is shown in Figure 3, by interconnecting the outputs ("wired-or"). This combined output signal is an indication of an impermissible energizing condition, that is a condition in which the energization can keep the rotor in a position in which the torque $T=0$, so that the motor does not start. A method of eliminating the impermissible energizing condition is then, for example, to set the shift register 12 to a position corresponding to a permissible condition, which in the example of Figure 3 is achieved by advancing the shift register 12 by one additional position. For this purpose the combined output signal of the AND-gates 20 and 21 is applied to a pulse shaper 22 which, upon the occurrence of such an impermissible condition, supplies a pulse which is added to the output signal of the pulse shaper 9 by means of an OR-gate 23, so that an additional shifting pulse appears on input 13 of the shift register 12.

An alternative to this method is obtained by for example, removing the pulse shaper 22 (and OR-gate 23) from the circuit of Figure 3 and by completing the remainder with the circuit section shown in Figure 4. The outputs Q_1 , Q_2 , Q_3 and Q_4

of the shift register 12 are then connected to switches S_1 , S_2 , S_3 and S_4 respectively, which switches may be formed by means of logic gates. In the positions of the switches S_1 to S_4 shown, the situation is then as shown in Figure 3, whilst in the other positions of said switches (the positions shown dotted) the outputs Q_1 , Q_2 , Q_3 and Q_4 are connected to the buffer amplifiers 15, 16, 17 and 14, respectively, so that the energizing condition is shifted by one position in the specified direction. The switches S_1 to S_4 are controlled by the output signals of AND-gates 20 and 21, which signals are combined by means of the OR-gate 41.

In the circuit arrangement of Figure 3 steps must be taken to prevent an undesired pulse from being formed by the pulse shaper 22 as a result of the non-simultaneous change-over of the shift register 12 and the detectors 10 and 11. This is for example possible by the use of clocked logic. Another possibility is to utilize this situation by removing the pulse shaper 9 and the OR-gate 23 from the circuit of Figure 3 and connecting the pulse shaper 22 to the input 13 of the shift register 12, which alternative is shown in Figure 5. The circuit then, operates in the same way as regards undesired rotor positions. As regards the commutation the circuit then operates in that at the instant that the polarity of the signal on input 3 changes the shift register remains in the same state. This is detected by AND-gate 20 or 21 in the same way as is an incorrect position of the shift register and a pulse is applied to input 13 of the shift register 12 by pulse shaper 22.

In the circuit arrangement and the alternatives described in the foregoing an additional pulse which advances the shift register 12 by one position is applied to the shift register each time that a spurious pulse appears. Since spurious pulses are generally additional pulses and do not suppress a desired pulse, this results in the shift register 12 being advanced by two steps in total, which temporarily gives rise to the same situation as described in the case of starting in the wrong direction. This may not be a problem if the risk of spurious pulses occurring is minimized, for example by electronic means—such as generating time windows for blocking pulses during time intervals in which no commutating pulse can occur. However, in cases in which such a situation must be precluded, the circuit arrangement of Figure 3 may be modified to suppress the next pulse supplied by the pulse shaper 9, instead of generating an additional pulse, under command of the AND-gate 20 and 21, which modification is shown in Figure 6.

In comparison with the version of Figure 3 the OR-gate 23 has been replaced by an AND-gate 45 having an inverting input which is driven by the output signal of the AND-gates 20 and 21. However, this method fails during starting when the motor is still stationary. If the initial energizing condition is a condition in which the rotor is in a stable position, the pulse shaper 9 initially does not supply a pulse, so that said pulse cannot be

suppressed. A solution to this is to set the shift register to a position which corresponds to a desired position under control of the detectors 10 and 11 during the build-up of the supply voltage. If during the build-up of the supply voltage the detector 10 is activated, the shift register 12 should be set so that output Q_2 or Q_4 goes high whereas if the detector 11 is activated the shift register 12 should be set so that output Q_1 or Q_3 goes high.

In comparison with the circuit of Figure 3, the circuit of Figure 6 therefore also comprises a supply-voltage detector 46, which supplies a pulse at the instant that the supply voltage appears on terminal V_s . This pulse is compared with the output signals of the detectors 10 and 11 by AND-gates 47 and 48 respectively. The output signals of the gates 47 and 48 are applied to respective set inputs S_1 and S_2 of the shift register to energize output Q_1 or Q_2 respectively. This ensures that, when the detector 10 is actuated during application of the supply voltage, the shift register is set so that output 6 is energized and, when the detector 11 is actuated, so that output 5 is energized.

The circuit of Figure 3—is so far as already described—as well as other versions may be provided with a useful extension, especially when these circuits are integrated. This extension utilizes the fact that the signal generated by the field sensor H can also be used as a tacho-signal. For this purpose said signal or, as is shown in Figure 3, the output signal of pulse shaper 9 may be applied to a control circuit 39 to which a control signal can be applied via an input 40. Especially in the case of speed control the frequency of the pulses supplied by the pulse shaper 9 can be determined in the circuit 39 using, for example, a frequency-voltage converter and may be compared with a d.c. control signal which is, for example, supplied by a reference source 42 incorporated in the same integrated circuit. In particular in the case of phase control the phase of the pulse train supplied by the pulse shaper 9 may be compared with a reference-pulse train applied to input 40. Other servo-control circuits are also possible. The output signal of the servo-control circuit 39 can influence the speed and/or phase of the motor, for example by controlling the magnitude of the drive, for example by control of the amplitude of the output signals of the buffer amplifier 14 to 17 by the control circuit 39, which is represented symbolically by arrows 40 in Figure 3, or for example by the use of pulse-width control.

Figure 7 shows an example of a motor in accordance with the invention in axial cross-section. Said motor comprises a mounting plate 25, which may for example form part of an enclosure. The rotor shaft 27 is secured to the plate 25 via a bearing arrangement 26. The rotor 1 is cup-shaped and comprises a magnetically conductive cup 28 which is provided with a cylindrical permanent magnet 29 on the inside of

its cylindrical portion. The stator is secured to said bottom plate 25 inside said cup and magnet 28, 29 and comprises a lamination assembly (30, 30') forming poles, and coils (32, 33). A printed circuit board 34 in which pins, such as the pin 37 shown in the present cross-section, are mounted is secured to the stator. The stator coils are connected to these pins (connection 36). The printed circuit board also accommodates an integrated circuit 35, which comprises the energizing circuit 4 and the field sensor H (in the present case a Hall element).

In order to arrange said Hall element as near as possible to the rotor magnet 29 the integrated circuit 35 is arranged in an opening in the p.c. board 34. A projecting part 31 of said printed circuit board comprises connection facilities for the supply voltage and, as the case may be, an input 24 (for adjusting the direction of rotation) and/or 40 (for adjusting the speed) (see Figure 3). The magnet 29 is radially magnetized. The position encoder 2 is formed by providing the side of the permanent magnet 29 which faces the printed circuit board 34 with locally different magnetizations, which does not significantly influence the motor operation whilst the main field of magnet 29 does not perceptibly influence the output signal of the Hall element. In a particular example the motor comprised 6 poles and the position encoder consequently 12 poles.

In general the invention may be used in a two-phase motor having p pole-pairs and a position encoder with $2p$ pole-pairs. It is to be noted that a motor as is shown schematically in Figure 1 is sometimes referred to as a four-phase motor, the motor being a two-phase motor when the coils L_1 and L_3 as well as the coils L_2 and L_4 are connected in series. Each of the two series arrangements can then be energized in both senses. In this application the term applied "two-phase" relates to both types of motor. Furthermore it will be appreciated that a permanent-magnetic rotor is not essential.

Claims

1. A self-starting brushless two-phase type d.c. motor comprising a stator, a rotor and a commutating device which includes a presettable energizing circuit for the commutated energization of the stator phases and a detection device with only one detector for indicating the rotor position, characterized in that the detector is arranged to distinguish which of the two stator phases the rotor is mainly directed towards and when commutation has to take place, and in that the motor comprises a presetting circuit adapted to be controlled by the detection device for setting the energizing circuit, at least when the rotor is stationary, to one of the two states which correspond to energization of the stator phase other than that towards which the rotor is mainly directed.

2. A self-starting brushless d.c. motor as claimed in Claim 1, characterized in that the

suppressed. A solution to this is to set the shift register to a position which corresponds to a desired position under control of the detectors 10 and 11 during the build-up of the supply voltage. If during the build-up of the supply voltage the detector 10 is activated, the shift register 12 should be set so that output Q_2 or Q_4 goes high whereas if the detector 11 is activated the shift register 12 should be set so that output Q_1 or Q_3 goes high.

In comparison with the circuit of Figure 3, the circuit of Figure 6 therefore also comprises a supply-voltage detector 46, which supplies a pulse at the instant that the supply voltage appears on terminal V_s . This pulse is compared with the output signals of the detectors 10 and 11 by AND-gates 47 and 48 respectively. The output signals of the gates 47 and 48 are applied to respective set inputs S_1 and S_2 of the shift register to energize output Q_1 or Q_2 respectively. This ensures that, when the detector 10 is actuated during application of the supply voltage, the shift register is set so that output 6 is energized and, when the detector 11 is actuated, so that output 5 is energized.

The circuit of Figure 3—is so far as already described—as well as other versions may be provided with a useful extension, especially when these circuits are integrated. This extension utilizes the fact that the signal generated by the field sensor H can also be used as a tacho-signal. For this purpose said signal or, as is shown in Figure 3, the output signal of pulse shaper 9 may be applied to a control circuit 39 to which a control signal can be applied via an input 40. Especially in the case of speed control the frequency of the pulses supplied by the pulse shaper 9 can be determined in the circuit 39 using, for example, a frequency-voltage converter and may be compared with a d.c. control signal which is, for example, supplied by a reference source 42 incorporated in the same integrated circuit. In particular in the case of phase control the phase of the pulse train supplied by the pulse shaper 9 may be compared with a reference-pulse train applied to input 40. Other servo-control circuits are also possible. The output signal of the servo-control circuit 39 can influence the speed and/or phase of the motor, for example by controlling the magnitude of the drive, for example by control of the amplitude of the output signals of the buffer amplifier 14 to 17 by the control circuit 39, which is represented symbolically by arrows 40 in Figure 3, or for example by the use of pulse-width control.

Figure 7 shows an example of a motor in accordance with the invention in axial cross-section. Said motor comprises a mounting plate 25, which may for example form part of an enclosure. The rotor shaft 27 is secured to the plate 25 via a bearing arrangement 26. The rotor 1 is cup-shaped and comprises a magnetically conductive cup 28 which is provided with a cylindrical permanent magnet 29 on the inside of

its cylindrical portion. The stator is secured to said bottom plate 25 inside said cup and magnet 28, 29 and comprises a lamination assembly (30, 30') forming poles, and coils (32, 33). A printed circuit board 34 in which pins, such as the pin 37 shown in the present cross-section, are mounted is secured to the stator. The stator coils are connected to these pins (connection 36). The printed circuit board also accommodates an integrated circuit 35, which comprises the energizing circuit 4 and the field sensor H (in the present case a Hall element).


In order to arrange said Hall element as near as possible to the rotor magnet 29 the integrated circuit 35 is arranged in an opening in the p.c. board 34. A projecting part 31 of said printed circuit board comprises connection facilities for the supply voltage and, as the case may be, an input 24 (for adjusting the direction of rotation) and/or 40 (for adjusting the speed) (see Figure 3). The magnet 29 is radially magnetized. The position encoder 2 is formed by providing the side of the permanent magnet 29 which faces the printed circuit board 34 with locally different magnetizations, which does not significantly influence the motor operation whilst the main field of magnet 29 does not perceptibly influence the output signal of the Hall element. In a particular example the motor comprised 6 poles and the position encoder consequently 12 poles.

In general the invention may be used in a two-phase motor having p pole-pairs and a position encoder with $2p$ pole-pairs. It is to be noted that a motor as is shown schematically in Figure 1 is sometimes referred to as a four-phase motor, the motor being a two-phase motor when the coils L_1 and L_3 as well as the coils L_2 and L_4 are connected in series. Each of the two series arrangements can then be energized in both senses. In this application the term applied "two-phase" relates to both types of motor. Furthermore it will be appreciated that a permanent-magnetic rotor is not essential.

Claims

1. A self-starting brushless two-phase type d.c. motor comprising a stator, a rotor and a commutating device which includes a presettable energizing circuit for the commutated energization of the stator phases and a detection device with only one detector for indicating the rotor position, characterized in that the detector is arranged to distinguish which of the two stator phases the rotor is mainly directed towards and when commutation has to take place, and in that the motor comprises a presetting circuit adapted to be controlled by the detection device for setting the energizing circuit, at least when the rotor is stationary, to one of the two states which correspond to energization of the stator phase other than that towards which the rotor is mainly directed.

2. A self-starting brushless d.c. motor as claimed in Claim 1, characterized in that the



presetable energizing circuit is preset to the switching sequence corresponding to the desired direction of rotation of the rotor and can be switched in accordance with a cyclic permutation, under command of commutation signals, regardless of the actual direction of rotation of the rotor.

3. A self-starting brushless d.c. motor as claimed in Claim 2, characterized in that the presetable energizing circuit comprises a control input and is adapted to preset the switching sequence to one of the two possible directions as a function of a signal on said control input in order to render the direction of rotation of the motor reversible.

4. A self starting brushless d.c. motor as claimed in Claim 1, comprising p pole pairs, characterized in that the detection device comprises a permanent-magnetic member having 2p pole-pairs, which member is rotatable in synchronism with the rotor, and the detector comprises a magneto-sensitive element, specifically a Hall element.

5. A self-starting brushless d.c. motor as claimed in Claim 4 and 2 or 3, characterized in that there is provided a commutating-signal generator for generating commutating signals for the energizing circuit in synchronism with the magnetic-field polarity changes detected by the detector.

6. A self-starting brushless d.c. motor as claimed in Claim 4 or 5, characterized in that the presetting circuit comprises a polarity detector for detecting the polarity of the magnetic field sensed by the magneto-sensitive element and a first gate circuit for comparing the detected polarity with the state of the energizing circuit.

7. A self-starting brushless d.c. motor as claimed in Claim 6, characterized in that the presetting circuit is adapted to supply additional commutating signals to the energizing circuit.

8. A self-starting brushless d.c. motor as claimed in Claim 5, characterized in that there are provided means for detecting the application of a supply voltage, the presetting circuit comprises a polarity detector for detecting the polarity of the magnetic field sensed by the magneto-sensitive element, and a first gate circuit for comparing the detected polarity with the state of the energizing circuit and, after detection of the application of a supply voltage setting the energizing circuit to a state which is in conformity with the detected polarity.

9. A self-starting brushless d.c. motor as claimed in Claim 6 or 8, characterized in that there is provided a second gate circuit for suppressing the next commutating signal under command of the presetting circuit.

10. A self-starting brushless d.c. motor as claimed in Claim 5, characterized in that the commutating signal generator comprises a polarity detector for detecting the polarity of the magnetic field sensed by the magneto-sensitive element and a gate circuit for comparing the detected polarity with the state of the energizing circuit and generating a commutating signal each

time that said state does not correspond to the detected polarity.

11. A self-starting brushless d.c. motor as claimed in any of the Claims 2, 3, 4, 5, 6, 7, 8, 9 and 10, characterized in that the energizing circuit comprises a shift register.

12. A self-starting brushless d.c. motor as claimed in Claim 11, characterized in that the shift register has an adjustable shifting direction.

13. A self-starting brushless d.c. motor as claimed in any of the Claims 1 to 12, characterized by

a rotor having a cylindrical permanent magnet which is magnetized to have substantially 2p poles,

a stator having two-phase windings, arranged coaxially with the rotor inside the cylindrical permanent magnet,

a wiring support secured to the stator, to which support the stator windings are connected, and

a substrate arranged on said wiring support, on which substrate at least the magneto-sensitive element is arranged in such a way that said element is disposed within magnetic range of influences of the end face of the cylindrical permanent magnet which faces said support, the permanent magnet being provided with a 4p-pole magnetization at the location of said end face.

Patentansprüche

1. Selbststartender büstenloser Zweiphasen-Gleichstrommotor mit einem Ständer, einem Läufer und einem Kommutator, der eine voreinstellbare Erregerschaltung für die geschaltete Aktivierung der Ständerphasen, sowie eine Detektoranordnung mit nur einem Detektor zum anzeigen der der Läuferposition enthält, dadurch gekennzeichnet, dass der Detektor so ausgelegt ist, dass er unterscheidet, auf welche der zwei Ständerphasen der Läufer im wesentlichen gerichtet ist und zu welchem Zeitpunkt die Kommutierung erfolgen muss, und dass der Motor eine Voreinstellschaltung zur Steuerung der Detektoranordnung enthält, mit dem die Erregerschaltung zumindest bei stationärem Läufer auf einen der beiden Zustände eingestellt wird, der der Erregung der Ständerphase entspricht, im Gegensatz zu dem auf den der Läufer im wesentlichen gerichtet ist.

2. Selbststartender büstenloser Gleichstrommotor nach Anspruch 1, dadurch gekennzeichnet, dass die voreinstellbare Erregerschaltung auf die Schaltfolge entsprechend der verlangten Drehrichtung des Läufers eingestellt ist und entsprechend einer zyklischen Permutation unter der Steuerung von Kommutierungssignalen ungeachtet der momentanen Drehrichtung des Läufers geschaltet werden kann.

3. Selbststartender büstenloser Gleichstrommotor nach Anspruch 2, dadurch gekennzeichnet, dass die voreinstellbare Erregerschaltung einen Steuereingang enthält und zum Einstellen der Schaltfolge auf eine der zwei möglichen Richtungen abhängig von einem Signal am



erwähnten Steuereingang dient, um die Drehrichtung des Motors umkehrbar zu machen.

4. Selbststartender bürstenloser Gleichstrommotor nach Anspruch 1 mit p Polpaaren, dadurch gekennzeichnet, dass die Detektoranordnung ein dauermagnetisches Element mit 2p Polpaaren enthält, das synchron mit dem Läufer drehbar ist, und wobei der Detektor ein magnetoempfindliches Element enthält, vorzugsweise ein Hall-Element.

5. Selbststartender bürstenloser Gleichstrommotor nach Anspruch 4 und 2 oder 3, dadurch gekennzeichnet, dass ein Kommutierungssignalgenerator zum Erzeugen von Kommutierungssignalen für die Erregerschaltung synchron mit den vom Detektor detektierten Änderungen in der Magnetfeldpolarität vorgesehen ist.

6. Selbststartender bürstenloser Gleichstrommotor nach Anspruch 4 oder 5, dadurch gekennzeichnet, dass die Voreinstellschaltung einen Polaritätsdetektor zum Detektieren der Polarität des vom magnetoempfindlichen Element detektierten Magnetfelds sowie eine erste Gatterschaltung zum Vergleichen der detektierten Polarität mit dem Zustand der Erregerschaltung enthält.

7. Selbststartender bürstenloser Gleichstrommotor nach Anspruch 6, dadurch gekennzeichnet, dass die Voreinstellschaltung zur Lieferung zusätzlicher Kommutierungssignale an die Erregerschaltung dient.

8. Selbststartender bürstenloser Gleichstrommotor nach Anspruch 5, dadurch gekennzeichnet, dass Mittel zum Detektieren der Zufuhr einer Speisespannung vorgesehen sind, dass die Voreinstellschaltung einen Polaritätsdetektor zum Detektieren der Polarität des vom magnetoempfindlichen Element detektierten Magnetfelds und eine erste Gatterschaltung zum Vergleichen der detektierten Polarität mit dem Zustand der Erregerschaltung enthält, die nach der Detektierung der Zufuhr einer Speisespannung die Erregerschaltung in einen Zustand bringt, die mit der detektierten Polarität übereinstimmt.

9. Selbststartender bürstenloser Gleichstrommotor nach Anspruch 6 oder 8, dadurch gekennzeichnet, dass eine zweite Gatterschaltung zum Unterdrücken des folgenden Kommutierungssignals unter der Steuerung der Voreinstellschaltung vorgesehen ist.

10. Selbststartender bürstenloser Gleichstrommotor nach Anspruch 5, dadurch gekennzeichnet, dass der Kommutierungssignalgenerator einen Polaritätsdetektor zum Detektieren der Polarität des vom magnetoempfindlichen Element detektierten Magnetfelds und eine Gatterschaltung zum Vergleichen der detektierten Polarität mit dem Zustand der Erregerschaltung enthält, und diese Gatterschaltung jedesmal ein Kommutierungssignal erzeugt, wenn dieser Zustand der detektierten Polarität nicht entspricht.

11. Selbststartender bürstenloser Gleichstrommotor nach einem oder mehreren der

Ansprüche 2 bis 10, dadurch gekennzeichnet, dass die Erregerschaltung ein Schieberegister enthält.

12. Selbststartender bürstenloser Gleichstrommotor nach Anspruch 11, dadurch gekennzeichnet, dass das Schieberegister eine einstellbare Schieberichtung hat.

13. Selbststartender bürstenloser Gleichstrommotor nach einem oder mehreren der Ansprüche 1 bis 12, dadurch gekennzeichnet, dass

eine Läufer mit einem im wesentlichen 2p-polig magnetisierten zylindrischen Magneten,

einen Ständer mit zweiphasigen Wicklungen, der koaxial mit dem Läufer innerhalb des zylindrischen Dauermagneten angebracht ist,

einen am Ständer befestigten Verdrahtungsträger, mit dem die Ständerwicklungen verbunden sind, und

ein auf diesem Verdrahtungsträger angebrachtes Substrat vorgesehen sind, auf dem wenigstens das magnetoempfindliche Element derart angebracht ist, dass es sich im magnetischen Wirkungsbereich der diesem Träger zugekehrten Stirnfläche des zylindrischen Dauermagneten befindet, wobei der Dauermagnet an der Stelle dieser Stirnfläche mit einer 2p-poligen Magnetisierung versehen ist.

Revendications

1. Moteur à courant continu autodémarrant sans balais et de type bisphasé comportant un stator, un rotor en un dispositif de commutation muni d'un circuit d'excitation pré réglable pour l'excitation commutée des phases de stator, et d'un dispositif de détection comportant un seul détecteur pour indiquer la position du rotor, caractérisé en ce que le détecteur est conçu pour distinguer celle des deux phases de stator vers laquelle le rotor est dirigé essentiellement ainsi que l'instant où une commutation doit avoir lieu et en ce que le moteur comporte un circuit de pré réglage pouvant être commandé par le dispositif de détection pour régler le circuit d'excitation, au moins lorsque le rotor est arrêté, à l'un des deux états qui correspondent à l'excitation de la phase de stator autre que celle vers laquelle le rotor est dirigé essentiellement.

2. Moteur à courant continu autodémarrant sans balais selon la revendication 1, caractérisé en ce que le circuit d'excitation pré réglable est pré réglé à l'ordre de commutation correspondant au sens de rotation souhaité du rotor et peut être commuté suivant une permutation cyclique sous la commande de signaux de commutation, quel que soit les sens de rotation du rotor à cet instant.

3. Moteur à courant continu autodémarrant sans balais selon la revendication 2, caractérisé en ce que le circuit d'excitation pré réglable est muni d'une entrée de commande et est conçu pour pré régler l'ordre de commutation à l'un des deux sens de rotation possibles en fonction d'un signal sur ladite entrée de commande pour rendre le sens de rotation du moteur réversible.

4. Moteur à courant continu autodémarrant



sans balais selon la revendication 1, comportant p paires de pôles, caractérisé en ce que le dispositif de détection comporte un élément à aimantation permanente ayant 2p paires de pôles et pouvant tourner en synchronisme avec le rotor et en ce que le détecteur comporte un élément magnétosensible, notamment un élément à effet Hall.

5. Moteur à courant continu autodémarrant sans balais selon les revendications 4 et 2 ou 3, caractérisé en ce qu'il est prévu un générateur de signaux de commutation pour engendrer des signaux de commutation pour le circuit d'excitation en synchronisme avec les changements de polarité du champ magnétique détectés par le détecteur.

6. Moteur à courant continu autodémarrant sans balais selon la revendication 4 ou 5, caractérisé en ce que le circuit de prééclage comporte, d'une part, un détecteur de polarité servant à détecter la polarité du champ magnétique détecté par l'élément magnétosensible et, d'autre part, un premier circuit de porte servant à comparer la polarité détectée avec l'état du circuit d'excitation.

7. Moteur à courant continu autodémarrant sans balais selon la revendication 6, caractérisé en ce que le circuit de prééclage est conçu pour fournir des signaux de commutation additionnels au circuit d'excitation.

8. Moteur à courant continu autodémarrant sans balais selon la revendication 5, caractérisé en ce qu'il est prévu des moyens de détection de l'application d'une tension d'alimentation, et en ce que le circuit de prééclage comporte, d'une part, un détecteur de polarité servant à détecter la polarité du champ magnétique détecté par l'élément magnétosensible et, d'autre part, un premier circuit de porte servant à comparer la polarité détectée avec l'état du circuit d'excitation et, après la détection de l'application d'une tension d'alimentation, à amener le circuit d'excitation dans un état qui cadre avec la polarité détectée.

9. Moteur à courant continu autodémarrant sans balais selon la revendication 6 ou 8, caractérisé en ce qu'il est prévu un second circuit de porte servant à supprimer le signal de commutation suivant sous la commande du circuit de prééclage.

10. Moteur à courant continu autodémarrant sans balais selon la revendication 5, caractérisé en ce que le générateur de signaux de commutation comporte, d'une part, un détecteur de polarité servant à détecter la polarité du champ magnétique détecté par l'élément magnétosensible et, d'autre part, un circuit de porte servant à comparer la polarité détectée avec l'état du circuit d'excitation et à engendrer un signal de commutation toutes les fois que ledit état ne correspond pas à la polarité détectée.

11. Moteur à courant continu autodémarrant sans balais selon l'une quelconque des revendications 2, 3, 4, 5, 6, 7, 8, 9 et 10, caractérisé en ce que le circuit d'excitation comporte un registre à décalage.

12. Moteur à courant continu autodémarrant sans balais selon la revendication 11, caractérisé en ce que le registre à décalage a une direction de décalage réglable.

13. Moteur à courant continu autodémarrant sans balais selon l'une quelconque des revendications 1 à 12, caractérisé par

un rotor muni d'un aimant permanent cylindrique aimanté de façon à présenter essentiellement 2p pôles,

un stator muni d'enroulements biphasés disposés coaxialement avec le rotor à l'intérieur de l'aimant permanent cylindrique,

un support de câblage qui est fixé au stator et auquel sont reliés les enroulements du stator et

un substrat qui est placé sur ledit support de câblage et sur lequel est disposé au moins l'élément magnétosensible, et cela de telle manière que ledite élément soit situé dans le domaine d'influence magnétique de la face terminale de l'aimant permanent cylindrique regardant ce support, l'aimant permanent présentant une aimantation à 4p pôles à l'endroit de ladite face terminale.



* C L M S *