

SYNCHRONOUS REGULATION CIRCUIT FOR TURN-ON AND TURN-OFF PHASE ANGLE OF THE AC VOLTAGE

BACKGROUND OF THE INVENTION

5 (1) Field of the Invention

The present invention relates to a synchronous regulation for the turn-on and turn-off phase angles of the sine waveform voltage output by an AC power source, which is a novel regulation mode capable of synchronously regulating the turn-on and turn-off phase angles that breaks
10 through the conventional regulation mode of either regulating the trigger phase angle or regulating the turn-off phase angle, and especially provided with a feature of regulating both of the turn-on and turn-off phase angles with the same phase angle, so that the sine waveform voltage of the AC power source can be kept to output in symmetrical waveforms within the
15 range in which the turn-on and turn-off phase angles being synchronously regulated; the synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage, provided by the present invention, can be applied to regulate the voltage output by a single-phase AC power source or a multiphase AC power source, for supplying power with stable voltage
20 to a load, or for regulating the output current to the load.

(2) Description of the Prior Art

The conventional regulation method for an AC power source is amplitude modulation (as shown in FIG. 1), and till now, the control
25 means for phase angle is to either regulate the trigger phase angle (as shown in FIG. 2), or regulate the turn-off phase angle (as shown in FIG. 3), thereby the application is limited.

SUMMARY OF THE INVENTION

30 The present invention provides a synchronous regulation circuit for

turn-on and turn-off phase angle of the AC voltage, wherein a solid switch unit is installed between an AC power source and a load, and a phase angle regulation circuit is utilized to synchronously regulate both of the turn-on phase angle and turn-off phase angle of the solid switch unit, so
5 that the sine waveform voltage of the AC power source can be kept to output in symmetrical waveforms within the range in which the turn-on and turn-off phase angles being synchronously regulated; the synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage, provided by the present invention, can be applied to regulate the voltage
10 output by a single-phase AC power source or a multiphase AC power source, for supplying power with stable voltage to a load or for regulating the output current to the load.

BRIEF DESCRIPTION OF THE DRAWINGS

15 FIG. 1 is a schematic view showing the waveform of the conventional amplitude modulation type voltage regulation for the sine-waveform AC voltage.

FIG. 2 is a schematic view showing the voltage regulation waveform of the conventional regulation for the turn-on phase angle of the
20 sine-waveform AC voltage.

FIG. 3 is a schematic view showing the voltage regulation waveform of the conventional regulation for the turn-off phase angle of the sine-waveform AC voltage.

FIG. 4 is a circuit block diagram showing utilizing the bipolar solid
25 switch unit for structuring the synchronous regulation for turn-on and turn-off phase angles of the AC voltage, according to the present invention.

FIG. 5 is a circuit block diagram showing configuring the regulation for the turn-on phase angle and the turn-off phase angle to the bipolar
30 solid switch unit, according to the present invention.

FIG. 6 is a circuit block diagram showing utilizing two bipolar solid switch units for structuring the synchronous regulation for turn-on and turn-off phase angles of the AC voltage, according to the present invention.

5 FIG. 7 is a circuit block diagram showing configuring the regulation for the turn-on and the turn-off phase angles to two solid switch units, according to the present invention.

FIG. 8 is a circuit block diagram showing utilizing the bridge rectifiers combining with the solid switch unit for structuring the synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage.

FIG. 9 is a circuit block diagram showing configuring the regulation for the turn-on and turn-off phase angles to the solid switch unit combined with the bridge rectifiers, according to the present invention.

FIG. 10 is a circuit block diagram showing utilizing the bipolar solid switch unit to structure the synchronous regulation for turn-on and turn-off phase angle of the AC voltage, and through the AC current limiting circuit device (Z10) detecting the current value, to output to the regulation circuit of turn-on and turn-off phase angle, thereby to regulate the voltage or current passing the load via the solid switch unit.

20 FIG. 11 is a circuit block diagram showing utilizing two solid switch units to structure the synchronous regulation for turn-on and turn-off phase angle of the AC voltage, and through the AC current limiting circuit device (Z10) detecting the current value, to output to the regulation circuit of turn-on and turn-off phase angle, thereby to regulate the voltage or current passing the load via the solid switch unit.

FIG. 12 is a circuit block diagram showing utilizing the bridge rectifiers combining with the solid switch unit to structure the synchronous regulation for turn-on and turn-off phase angle of the AC voltage, and through the AC current limiting circuit device (Z10) detecting the current value, to output to the regulation circuit of turn-on

and turn-off phase angle, and to regulate the voltage or current passing through the load via the solid switch unit.

DESCRIPTION OF MAIN COMPONENT SYMBOLS

- 5 (1000) : Bipolar solid switch unit
 (1001) 、(1002) : Unipolar solid switch unit
 (BR101) 、(BR102) : Bridge rectifier
 (CR101) 、(CR102) : Diode
 (L101) : Load
- 10 (PD100) : Regulation circuit of bipolar turn-on and turn-off phase
 angle
 (PD200) : Configuration circuit of bipolar turn-on and turn-off phase
 angle
 (PD101) 、(PD102) : Regulation circuit of unipolar turn-on and turn-off
15 phase angle
 (PD103) 、(PD104) : Configuration circuit of unipolar turn-on and
 turn-off phase angle
 (Z10) : AC current limiting circuit device
 (ZD101) 、(ZD102) 、(ZD103) 、(ZD104) : Zener diode

20

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

The conventional regulation method for an AC power source is amplitude modulation (as shown in FIG. 1), and till now, the control means for phase angle is to either regulate the trigger phase angle (as
25 shown in FIG. 2), or regulate the turn-off phase angle (as shown in FIG. 3), thereby the application is limited.

The present invention relates to a synchronous regulation for the turn-on and turn-off phase angles of the sine waveform voltage output by an AC power source, which is a novel regulation mode capable of
30 synchronously regulating the turn-on and turn-off phase angles that breaks

through the conventional regulation mode of either regulating the trigger phase angle or regulating the turn-off phase angle, and especially provided with a feature of regulating both of the turn-on and turn-off phase angles with the same phase angle, so that the sine-waveform voltage of the AC power source can be kept to output in symmetrical waveforms within the range in which the turn-on and turn-off phase angles being synchronously regulated; the synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage, provided by the present invention, can be applied to regulate the voltage output by a single-phase AC power source or a multiphase AC power source, for supplying power with stable voltage to a load, or for regulating the output current to the load.

The present invention provides a synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage, wherein a solid switch unit is installed between an AC power source and a load, and a phase angle regulation circuit is utilized to synchronously regulate both of the turn-on phase angle and turn-off phase angle of the solid switch unit, so that the sine-waveform voltage of the AC power source can be kept to output in symmetrical waveforms within the range in which the turn-on and turn-off phase angles being synchronously regulated; the synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage, provided by the present invention, can be applied to regulate the voltage output by a single-phase AC power source or a multiphase AC power source, for supplying power with stable voltage to a load or for regulating the output current to the load.

FIG. 4 is a circuit block diagram showing utilizing the bipolar solid switch unit for structuring the synchronous regulation for turn-on and turn-off phase angles of the AC voltage, according to the present invention.

As shown in FIG. 4, it mainly consists of:

--AC current limiting circuit device (Z10): which is constituted by one

or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series with the load (L101) and the bipolar solid switch unit (1000) then connected in parallel with the

5 AC power source;

--Bipolar solid switch unit (1000): which is constituted by one or more than one of following solid switch units:

1) The bipolar solid switch unit (1000) is composed of a bidirectional thyristor component capable of controlling the turn-on phase
10 angle, e.g. bidirectional silicon controlled rectifier TRIAC (Triode AC semiconductor switch); through the regulation function of the regulation circuit of bipolar turn-on and turn-off phase angle (PD100) itself, a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) composed of
15 the TRIAC;

2) The bipolar solid switch unit (1000) is composed of at least two field effect power components, e.g. a bipolar module composed of the metal oxide semiconductor field effect transistor (MOSFET) or the insulated gate bipolar transistor (IGBT); and through the regulation
20 function of the regulation circuit of bipolar turn-on and turn-off phase angle (PD100) itself, a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) composed of at least two field effect power components;

25 -- Regulation circuit of bipolar turn-on and turn-off phase angle (PD100): which is constituted by electronic circuit components for inputting the AC power voltage; and through the regulation function of the circuit itself, and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load
30 (L101), a bipolar driving voltage signal is output to regulate the turn-on

phase angle and the turn-off phase angle of the bipolar solid switch unit (1000);

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

FIG. 5 is a circuit block diagram showing configuring the regulation for the turn-on phase angle and the turn-off phase angle to the bipolar solid switch unit, according to the present invention.

As shown in FIG. 5, it mainly consists of:

--AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series with the load (L101) and the bipolar solid switch unit (1000) then connected in parallel with the AC power source;

--Bipolar solid switch unit (1000): which is constituted by one or more than one of following solid switch units:

1) The bipolar solid switch unit (1000) is composed of a bidirectional thyristor component capable of controlling the turn-on phase angle, e.g. bidirectional silicon controlled rectifier TRIAC (Triode AC semiconductor switch); through the configuration function of the configuration circuit of bipolar turn-on and turn-off phase angle (PD200) itself, a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) composed of the TRIAC, through the zener diodes (ZD101), (ZD102) which are reverse-polarity connected in series;

2) The bipolar solid switch unit (1000) is composed of at least two field effect power components, e.g. a bipolar module compose of the metal oxide semiconductor field effect transistor (MOSFET) or the

integrated gate bipolar transistor (IGBT); and through the configuration function of the configuration circuit of bipolar turn-on and turn-off phase angle (PD200) itself, a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) composed of at least two field effect power components, through the zener diodes (ZD101), (ZD102) which are reverse-polarity connected in series;

-- Configuration circuit of bipolar turn-on and turn-off phase angle (PD200): which is constituted by electronic circuit components for inputting the AC power voltage; and through the configuration function of the circuit itself, a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) through the zener diodes (ZD101), (ZD102) which are reverse-polarity connected in series;

--Zener diode (ZD101), (ZD102): which is constituted by at least two zener diodes, reverse-polarity connected in series for generating the bipolar voltage differentiation, and is provided for being connected in series between a bipolar driving voltage signal output terminal of the regulation circuit of bipolar turn-on and turn-off phase angle (PD100) and a bipolar driving voltage signal input terminal of the bipolar solid switch unit (1000); the zener diode (ZD101), (ZD102) can be replaced by a bidirectional zener diode having the same performance;

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

FIG. 6 is a circuit block diagram showing utilizing two bipolar solid switch units for structuring the synchronous regulation for turn-on and turn-off phase angles of the AC voltage, according to the present invention.

As shown in FIG. 6, it mainly consists of:

--AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series with the load (L101) and the bipolar solid switch unit (1000) then connected in parallel with the AC power source;

--Bipolar solid switch unit (1000): which is constituted by a unipolar solid switch unit (1001) and a unipolar solid switch unit (1002) being reverse-polarity connected in parallel; the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) are composed of one or more than one of following solid switch units:

1) Constituted by at least two unipolar solid switch units (1001, 1002) capable of controlling the turn-on phase angle, e.g. at least two silicon controlled rectifiers (SCRs) being reverse-polarity connected in parallel for forming the bipolar solid switch unit (1000); and through the regulation functions of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and the regulation circuit of unipolar turn-on and turn-off phase angle (PD102) itself, the driving voltage signals having different polarities are respectively output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002);

2) the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) are composed of at least two field effect power components being reverse-polarity connected in parallel to form the bipolar solid switch unit (1000), e.g. the bipolar module composed of the MOSFET and IGBT serving as the bipolar solid switch unit (1000); and through the regulation functions of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and the regulation function of the regulation circuit of unipolar turn-on and turn-off phase

angle (PD102) itself, the driving voltage signals having different polarities are respectively output to control the turn-on phase angle and the turn-off phase angle of the two field effect power components which are connected in parallel and in different polarities for respectively forming
5 the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002);

-- Regulation circuit of unipolar turn-on and turn-off phase angle (PD101): which is constituted by electronic circuit components and normal-polarity connected in series with the diode (CR101) for inputting
10 an AC voltage of a first polarity; and through the regulation function of the circuit itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a driving voltage signal having the same polarity as the unipolar solid switch unit (1001) is output to control the turn-on phase angle and
15 the turn-off phase angle of the unipolar solid switch unit (1001);

-- Configuration circuit of unipolar turn-on and turn-off phase angle (PD102): which is constituted by electronic circuit components and normal-polarity connected in series with the diode (CR102) for inputting
20 an AC voltage of a second polarity; and through the regulation function of the circuit itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a driving voltage signal having the same polarity as the unipolar solid switch unit (1002) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1002);

25 --Diode (CR101): which is constituted by the rectifying diode, and the diode (CR101) and the unipolar solid switch unit (1001) are normal-polarity connected in series with the regulation circuit of unipolar turn-on and turn-off phase angle (PD101);

--Diode (CR102): which is constituted by the rectifying diode, and the
30 diode (CR102) and the unipolar solid switch unit (1002) are

normal-polarity connected in series with the configuration circuit of unipolar turn-on and turn-off phase angle (PD102);

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

FIG. 7 is a circuit block diagram showing configuring the regulation for the turn-on and the turn-off phase angles to two solid switch units, according to the present invention.

As shown in FIG. 7, it mainly consists of:

--AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series with the load (L101) and the bipolar solid switch unit (1000) then connected in parallel with the AC power source;

--Bipolar solid switch unit (1000): which is constituted by a unipolar solid switch unit (1001) and a unipolar solid switch unit (1002) being reverse-polarity connected in parallel; the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) are composed of one or more than one of following solid switch units:

1) Constituted by at least two unipolar solid switch units (1001, 1002) capable of controlling the turn-on phase angle, e.g. at least two silicon controlled rectifiers (SCRs) being reverse-polarity connected in parallel for forming the bipolar solid switch unit (1000); and through the configuration functions of the configuration circuit of single-polarity turn-on and turn-off phase angle (PD103) itself and the configuration circuit of single-polarity turn-on and turn-off phase angle (PD104) itself, the driving voltage signals having different polarities are respectively output, through the zener diode (ZD103) and the zener diode (ZD104), to

the unipolar solid switch unit (1001) and unipolar solid switch unit (1002) for respectively controlling the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) and unipolar solid switch unit (1002);

5 2) the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) are composed of at least two field effect power components being reverse-polarity connected in parallel to form the bipolar solid switch unit (1000), e.g. the bipolar module composed of the MOSFET and IGBT serving as the bipolar solid switch unit (1000); and
10 through the configuration functions of the configuration circuit of single-polarity turn-on and turn-off phase angle (PD103) itself and the configuration circuit of single-polarity turn-on and turn-off phase angle (PD104) itself, the driving voltage signals having different polarities are respectively output, through the zener diode (ZD103) and the zener diode
15 (ZD104), to the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) for respectively controlling the turn-on phase angle and the turn-off phase angle of the two field effect power components which are connected in parallel and in different polarities;

-- Configuration circuit of unipolar turn-on and turn-off phase angle
20 (PD103): which is constituted by electronic circuit components and normal-polarity connected in series with the diode (CR101) for inputting an AC voltage of a first polarity; and through the configuration function of the circuit itself, a driving voltage signal having the same polarity as the unipolar solid switch unit (1001) is output to control the turn-on phase
25 angle and the turn-off phase angle of the unipolar solid switch unit (1001);

-- Configuration circuit of unipolar turn-on and turn-off phase angle (PD104): which is constituted by electronic circuit components and normal-polarity connected in series with the diode (CR102) for inputting an AC voltage of a second polarity; and through the configuration
30 function of the circuit itself, a driving voltage signal having the same

polarity as the unipolar solid switch unit (1002) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1002);

--Diode (CR101): which is constituted by the rectifying diode, and the
5 diode (CR101) and the unipolar solid switch unit (1001) are normal-polarity connected in series with the regulation circuit of unipolar turn-on and turn-off phase angle (PD101);

--Diode (CR102): which is constituted by the rectifying diode, and the
diode (CR102) and the unipolar solid switch unit (1002) are
10 normal-polarity connected in series with the configuration circuit of unipolar turn-on and turn-off phase angle (PD102);

--Zener diode (ZD103): which is constituted by the zener diode having zener voltage effect or the forward bias diode for being connected in series between a driving voltage signal output terminal
15 of the configuration circuit of unipolar turn-on and turn-off phase angle (PD103) and a driving voltage signal input terminal of the unipolar solid switch unit (1001);

--Zener diode (ZD104): which is constituted by the zener diode having zener voltage effect or the forward bias diode for being
20 connected in series between a driving voltage signal output terminal of the configuration circuit of unipolar turn-on and turn-off phase angle (PD104) and a driving voltage signal input terminal of the unipolar solid switch unit (1002);

The mentioned circuit is for regulating the resistance, the inductive
25 load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

FIG. 8 is a circuit block diagram showing utilizing the bridge rectifiers combining with the solid switch unit for structuring the synchronous
30 regulation circuit for turn-on and turn-off phase angle of the AC voltage.

As shown in FIG. 8, it mainly consists of:

--AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series between the AC power source and an AC input terminal of the bridge rectifier (BR101);

--Unipolar solid switch unit (1001): which is constituted by one or more than one of following solid switch units:

1) Constituted by the unipolar solid switch unit (1001) capable of controlling the turn-on phase angle, e.g. silicon controlled rectifier (SCR); and through the regulation function of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself, a driving voltage signal is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) composed of silicon controlled rectifier (SCR);

2) the field effect power component serving as the unipolar solid switch unit (1001), e.g. MOSFET and IGBT; and through the regulation function of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101), a driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) composed of the field effect power component;

-- Regulation circuit of unipolar turn-on and turn-off phase angle (PD101): which is constituted by electronic circuit components and provided for being connected in parallel to a DC output terminal of the bridge rectifier (BR102); and through the regulation function of the circuit itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a driving voltage signal having the same polarity as the unipolar solid switch unit (1001) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001);

--Bridge rectifier (BR101): which is constituted by at least four rectifying diodes, in which the AC power input terminal is provided for being connected in series to the AC current limiting circuit device (Z10) so as to be connected to the AC power source, and is provided with the output terminals having anode and cathode of the DC power source; for
5 output terminals having anode and cathode of the DC power source; for rectifying the AC power source to DC power source, so as to output to the unipolar solid switch unit (1001) and the load (L101) connected in series;

--Bridge rectifier (BR102): which is constituted by at least four rectifying diodes and provided with two input terminals for receiving the
10 AC power source and the output terminals having anode and cathode for outputting the DC power source; for rectifying the AC power source to DC power source, so as to output to the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) then further output the driving voltage signal to the unipolar solid switch unit (1001);

15 The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

FIG. 9 is a circuit block diagram showing configuring the regulation
20 for the turn-on and turn-off phase angles to the solid switch unit combined with the bridge rectifiers, according to the present invention.

As shown in FIG. 9, it mainly consists of:

--AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and
25 capacitive impedance being connected in series, in parallel or in series and parallel, and one terminal thereof is connected to one terminal of the AC power source, and the other terminal thereof is connected in series with the load (L101) for leading to the AC input terminal of the bridge rectifier (BR101), and the other AC input terminal of the bridge rectifier (BR101)
30 is connected to the other terminal of the AC power source;

--Unipolar solid switch unit (1001): which is constituted by one or more than one of following solid switch units:

1) Constituted by the unipolar solid switch unit (1001) capable of controlling the turn-on phase angle, e.g. silicon controlled rectifier (SCR);
5 and through the regulation function of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load (L101), a driving voltage signal is output, through the zener diode (ZD103), to control the turn-on phase
10 angle and the turn-off phase angle of the unipolar solid switch unit (1001) composed of silicon controlled rectifier (SCR);

2) the field effect power component serving as the unipolar solid switch unit (1001), e.g. MOSFET and IGBT; and through the regulation function of the regulation circuit of unipolar turn-on and turn-off phase
15 angle (PD101) and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load (L101), a driving voltage signal is output, through the zener diode (ZD103), to regulate the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) composed of the field effect power
20 component;

-- Configuration circuit of unipolar turn-on and turn-off phase angle (PD103): constituted by electronic circuit components and provided for being connected in parallel to the DC output terminal of the bridge rectifier (BR101); through the configuration function of the circuit itself, a
25 driving voltage signal is output, and through the zener diode (ZD103), to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001);

--Bridge rectifier (BR101): which is constituted by at least four rectifying diodes and provided with two input terminals for receiving the
30 AC power source and the output terminals having anode and cathode for

outputting the DC power source; for rectifying the AC power source to DC power source, so as to output to the unipolar switch unit (1001) and the configuration circuit of single-polarity turn-on and turn-off phase angle (PD103);

5 --Zener diode (ZD103): which is constituted by the zener diode having zener voltage effect or the forward bias diode for being connected in series between a driving voltage signal output terminal of the configuration circuit of unipolar turn-on and turn-off phase angle (PD103) and a driving voltage signal input terminal of the unipolar solid
10 switch unit (1001);

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

15 FIG. 10 is a circuit block diagram showing utilizing the bipolar solid switch unit to structure the synchronous regulation for turn-on and turn-off phase angle of the AC voltage, and through the AC current limiting circuit device (Z10) detecting the current value, to output to the regulation circuit of turn-on and turn-off phase angle, thereby to regulate
20 the voltage or current passing the load via the solid switch unit.

As shown in FIG. 10, it mainly consists of:

25 --AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series with the load (L101) and the bipolar solid switch unit (1000) then connected in parallel with the AC power source;

 --Bipolar solid switch unit (1000): which is constituted by one or more than one of following solid switch units:

30 1) The bipolar solid switch unit (1000) is composed of a

bidirectional thyristor component capable of controlling the turn-on phase angle, e.g. bidirectional silicon controlled rectifier TRIAC (Triode AC semiconductor switch); through the regulation function of the regulation circuit of bipolar turn-on and turn-off phase angle (PD100) itself and with
5 respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) composed of the TRIAC;

10 2) The bipolar solid switch unit (1000) is composed of at least two field effect power components, e.g. a bipolar module composed of the metal oxide semiconductor field effect transistor (MOSFET) or the insulated gate bipolar transistor (IGBT)bipolar solid switch unit; and through the regulation function of the regulation circuit of bipolar turn-on
15 and turn-off phase angle (PD100) itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) composed of at least two field effect
20 power components;

-- Regulation circuit of bipolar turn-on and turn-off phase angle (PD100): which is constituted by electronic circuit components for inputting the AC power voltage; and through the regulation function of the circuit itself, and with respect to the current value passing the AC current
25 limiting circuit device (Z10) and the terminal voltage value of the load (L101), a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000);

The mentioned circuit is for regulating the resistance, the inductive
30 load containing the resistance or the capacitive load containing the

resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

FIG. 11 is a circuit block diagram showing utilizing two solid switch units to structure the synchronous regulation for turn-on and turn-off phase angle of the AC voltage, and through the AC current limiting circuit device (Z10) detecting the current value, to output to the regulation circuit of turn-on and turn-off phase angle, thereby to regulate the voltage or current passing the load via the solid switch unit.

As shown in FIG. 11, it mainly consists of:

10 --AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series with the load (L101) and the bipolar solid switch unit (1000) then connected in parallel with the
15 AC power source;

 --Bipolar solid switch unit (1000): which is constituted by a unipolar solid switch unit (1001) and a unipolar solid switch unit (1002) being reverse-polarity connected in parallel; the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) are composed of one or
20 more than one of following solid switch units:

1) Constituted by at least two unipolar solid switch units (1001, 1002) capable of controlling the turn-on phase angle, e.g. at least two silicon controlled rectifiers (SCRs) being reverse-polarity connected in parallel for forming the bipolar solid switch unit (1000); and
25 through the regulation functions of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and the regulation circuit of unipolar turn-on and turn-off phase angle (PD102) itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load
30 (L101), the driving voltage signals having different polarities are

respectively output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002);

2) the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) are composed of at least two field effect power components being reverse-polarity connected in parallel to form the bipolar solid switch unit (1000), e.g. the bipolar module composed of the MOSFET and IGBT serving as the bipolar solid switch unit (1000); and through the regulation functions of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and the regulation circuit of unipolar turn-on and turn-off phase angle (PD102) itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load (L101), the driving voltage signals having different polarities are respectively output to control the turn-on phase angle and the turn-off phase angle of the two field effect power components which are connected in parallel and in different polarities for respectively forming the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002);

-- Regulation circuit of unipolar turn-on and turn-off phase angle (PD101): which is constituted by electronic circuit components and normal-polarity connected in series with the diode (CR101) for inputting an AC voltage of a first polarity; and through the regulation function of the circuit itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a driving voltage signal having the same polarity as the unipolar solid switch unit (1001) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001);

-- Configuration circuit of unipolar turn-on and turn-off phase angle (PD102): which is constituted by electronic circuit components and

normal-polarity connected in series with the diode (CR102) for inputting an AC voltage of a second polarity; and through the regulation function of the circuit itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a driving voltage signal having the same polarity as the unipolar solid switch unit (1002) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1002);

--Diode (CR101): which is constituted by the rectifying diode, and the diode (CR101) and the unipolar solid switch unit (1001) are normal-polarity connected in series with the regulation circuit of unipolar turn-on and turn-off phase angle (PD101);

--Diode (CR102): which is constituted by the rectifying diode, and the diode (CR102) and the unipolar solid switch unit (1002) are normal-polarity connected in series with the configuration circuit of unipolar turn-on and turn-off phase angle (PD102);

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

FIG. 12 is a circuit block diagram showing utilizing the bridge rectifiers combining with the solid switch unit to structure the synchronous regulation for turn-on and turn-off phase angle of the AC voltage, and through the AC current limiting circuit device (Z10) detecting the current value, to output to the regulation circuit of turn-on and turn-off phase angle, and to regulate the voltage or current passing through the load via the solid switch unit.

As shown in FIG. 12, it mainly consists of:

--AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and

parallel and provided for being connected in series between the AC power source and an AC input terminal of the bridge rectifier (BR101);

--Unipolar solid switch unit (1001): which is constituted by one or more than one of following solid switch units:

5 1) Constituted by the unipolar solid switch unit (1001) capable of controlling the turn-on phase angle, e.g. silicon controlled rectifier (SCR); and through the regulation function of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the
10 terminal voltage value of the load (L101), a driving voltage signal is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) composed of silicon controlled rectifier (SCR);

2) the field effect power component serving as the unipolar solid
15 switch unit (1001), e.g. MOSFET and IGBT; and through the regulation function of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load (L101), a driving voltage signal is output to regulate the turn-on
20 phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) composed of the field effect power component;

-- Regulation circuit of unipolar turn-on and turn-off phase angle (PD101): which is constituted by electronic circuit components, and connected in parallel to a DC output terminal of the bridge rectifier
25 (BR102); and through the regulation function of the circuit itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a driving voltage signal having the same polarity as the unipolar solid switch unit (1001) is output to control the turn-on phase angle and the turn-off phase angle of the
30 unipolar solid switch unit (1001);

--Bridge rectifier (BR101): which is constituted by at least four rectifying diodes, in which the AC power input terminal is provided for being connected in series to the AC current limiting circuit device (Z10) so as to be connected to the AC power source, and is provided with the output terminals having anode and cathode of the DC power source; for rectifying the AC power source to DC power source, so as to output to the unipolar solid switch unit (1001) and the load (L101) connected in series;

--Bridge rectifier (BR102): which is constituted by at least four rectifying diodes and provided with two input terminals for receiving the AC power source and the output terminals having anode and cathode for outputting the DC power source; for rectifying the AC power source to DC power source, so as to output to the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) then further output the driving voltage signal to the unipolar solid switch unit (1001);

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

According to the synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage provided by the present invention, the output driving voltage signal of the regulation circuit of bipolar turn-on and turn-off phase angle (PD100), the configuration circuit of bipolar turn-on and turn-off phase angle (PD200), the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) and (PD102), the configuration circuit of unipolar turn-on and turn-off phase angle (PD103) and (PD104) can be constituted by the followings, which includes:

- 1) Directly outputting the power signal to drive the mated solid switch unit;
- 2) Utilizing a photoelectric coupling device for insulation and outputting the power signal to drive the mated solid switch unit; and

3) Utilizing a pulse transformer for insulation and outputting the power signal to drive the mated solid switch unit.

5

CLAIMS

1. A synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage, wherein a solid switch unit is installed between an AC power source and a load, and a phase angle regulation circuit is utilized to synchronously regulate both of the turn-on phase angle and turn-off phase angle of the solid switch unit, so that the sine waveform voltage of the AC power source can be kept to output in symmetrical waveforms within the range in which the turn-on and turn-off phase angles being synchronously regulated; the synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage, provided by the present invention, can be applied to regulate the voltage output by a single-phase AC power source or a multiphase AC power source, for supplying power with stable voltage to a load or for regulating the output current to the load, which mainly consists of:
- AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series with the load (L101) and the bipolar solid switch unit (1000) then connected in parallel with the AC power source;
 - Bipolar solid switch unit (1000): which is constituted by one or more than one of following solid switch units:
 - 1) The bipolar solid switch unit (1000) is composed of a bidirectional thyristor component capable of controlling the turn-on phase angle, e.g. bidirectional silicon controlled rectifier TRIAC (Triode AC semiconductor switch); through the regulation function of the regulation circuit of bipolar turn-on and turn-off phase angle (PD100) itself, a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000)

composed of the TRIAC;

2) The bipolar solid switch unit (1000) is composed of at least two field effect power components, e.g. a bipolar module composed of the metal oxide semiconductor field effect transistor (MOSFET) or the insulated gate bipolar transistor (IGBT); and through the regulation function of the regulation circuit of bipolar turn-on and turn-off phase angle (PD100) itself, a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) composed of at least two field effect power components;

-- Regulation circuit of bipolar turn-on and turn-off phase angle (PD100): which is constituted by electronic circuit components for inputting the AC power voltage; and through the regulation function of the circuit itself, and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load (L101), a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000);

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

2. A synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage as claimed in claim 1, wherein it includes configuring the regulation for the turn-on phase angle and the turn-off phase angle to the bipolar solid switch unit, which mainly consists of:

--AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and

capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series with the load (L101) and the bipolar solid switch unit (1000) then connected in parallel with the AC power source;

5 --Bipolar solid switch unit (1000): which is constituted by one or more than one of following solid switch units:

1) The bipolar solid switch unit (1000) is composed of a bidirectional thyristor component capable of controlling the turn-on phase angle, e.g. bidirectional silicon controlled rectifier TRIAC (Triode AC semiconductor switch); through the configuration function of the configuration circuit of bipolar turn-on and turn-off phase angle (PD200) itself, a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) composed of the TRIAC, through the zener diodes (ZD101), (ZD102) which are reverse-polarity connected in series;

10

15

2) The bipolar solid switch unit (1000) is composed of at least two field effect power components, e.g. a bipolar module composed of the metal oxide semiconductor field effect transistor (MOSFET) or the integrated gate bipolar transistor (IGBT); and through the configuration function of the configuration circuit of bipolar turn-on and turn-off phase angle (PD200) itself, a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) composed of at least two field effect power components, through the zener diodes (ZD101), (ZD102) which are reverse-polarity connected in series;

20

25

-- Configuration circuit of bipolar turn-on and turn-off phase angle (PD200): which is constituted by electronic circuit components for inputting the AC power voltage; and through the configuration function of the circuit itself, a bipolar driving voltage signal is output to regulate

30

the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) through the zener diodes (ZD101), (ZD102) which are reverse-polarity connected in series;

--Zener diode (ZD101), (ZD102): which is constituted by at least
5 two zener diodes, reverse-polarity connected in series for generating the bipolar voltage differentiation, and is provided for being connected in series between a bipolar driving voltage signal output terminal of the regulation circuit of bipolar turn-on and turn-off phase angle (PD100) and a bipolar driving voltage signal input terminal of the bipolar solid
10 switch unit (1000); the zener diode (ZD101), (ZD102) can be replaced by a bidirectional zener diode having the same performance;

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the
15 capacitive load containing the resistance connected in series.

3. A synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage as claimed in claim 1, wherein it includes utilizing two bipolar solid switch units for structuring the synchronous regulation for turn-on and turn-off phase angles of the AC voltage, which mainly
20 consists of:

--AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series with the load
25 (L101) and the bipolar solid switch unit (1000) then connected in parallel with the AC power source;

--Bipolar solid switch unit (1000): which is constituted by a unipolar solid switch unit (1001) and a unipolar solid switch unit (1002) being reverse-polarity connected in parallel; the unipolar solid
30 switch unit (1001) and the unipolar solid switch unit (1002) are

composed of one or more than one of following solid switch units:

- 1) Constituted by at least two unipolar solid switch units (1001, 1002) capable of controlling the turn-on phase angle, e.g. at least two silicon controlled rectifiers (SCRs) being reverse-polarity connected in parallel for forming the bipolar solid switch unit (1000); and through the regulation functions of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and the regulation circuit of unipolar turn-on and turn-off phase angle (PD102) itself, the driving voltage signals having different polarities are respectively output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002);
- 2) the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) are composed of at least two field effect power components being reverse-polarity connected in parallel to form the bipolar solid switch unit (1000), e.g. the bipolar module composed of the MOSFET and IGBT serving as the bipolar solid switch unit (1000); and through the regulation functions of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and the regulation function of the regulation circuit of unipolar turn-on and turn-off phase angle (PD102) itself, the driving voltage signals having different polarities are respectively output to control the turn-on phase angle and the turn-off phase angle of the two field effect power components which are connected in parallel and in different polarities for respectively forming the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002);
-- Regulation circuit of unipolar turn-on and turn-off phase angle (PD101): which is constituted by electronic circuit components and normal-polarity connected in series with the diode (CR101) for inputting an AC voltage of a first polarity; and through the regulation

function of the circuit itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a driving voltage signal having the same polarity as the unipolar solid switch unit (1001) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001);

-- Configuration circuit of unipolar turn-on and turn-off phase angle (PD102): which is constituted by electronic circuit components and normal-polarity connected in series with the diode (CR102) for inputting an AC voltage of a second polarity; and through the regulation function of the circuit itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a driving voltage signal having the same polarity as the unipolar solid switch unit (1002) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1002);

--Diode (CR101): which is constituted by the rectifying diode, and the diode (CR101) and the unipolar solid switch unit (1001) are normal-polarity connected in series with the regulation circuit of unipolar turn-on and turn-off phase angle (PD101);

--Diode (CR102): which is constituted by the rectifying diode, and the diode (CR102) and the unipolar solid switch unit (1002) are normal-polarity connected in series with the configuration circuit of unipolar turn-on and turn-off phase angle (PD102);

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

4. A synchronous regulation circuit for turn-on and turn-off phase angle of

the AC voltage as claimed in claim 1, wherein it includes configuring the regulation for the turn-on and the turn-off phase angles to two solid switch units, which mainly consists of:

5 --AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series with the load (L101) and the bipolar solid switch unit (1000) then connected in parallel with the AC power source;

10 --Bipolar solid switch unit (1000): which is constituted by a unipolar solid switch unit (1001) and a unipolar solid switch unit (1002) being reverse-polarity connected in parallel; the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) are composed of one or more than one of following solid switch units:

15 1) Constituted by at least two unipolar solid switch units (1001, 1002) capable of controlling the turn-on phase angle, e.g. at least two silicon controlled rectifiers (SCRs) being reverse-polarity connected in parallel for forming the bipolar solid switch unit (1000); and through the configuration functions of the configuration circuit of
20 single-polarity turn-on and turn-off phase angle (PD103) itself and the configuration circuit of single-polarity turn-on and turn-off phase angle (PD104) itself, the driving voltage signals having different polarities are respectively output, through the zener diode (ZD103) and the zener diode (ZD104), to the unipolar solid switch
25 unit (1001) and unipolar solid switch unit (1002) for respectively controlling the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) and unipolar solid switch unit (1002);

30 2) the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) are composed of at least two field effect power

components being reverse-polarity connected in parallel to form the bipolar solid switch unit (1000), e.g. the bipolar module composed of the MOSFET and IGBT serving as the bipolar solid switch unit (1000); and through the configuration functions of the configuration circuit of single-polarity turn-on and turn-off phase angle (PD103) itself and the configuration circuit of single-polarity turn-on and turn-off phase angle (PD104) itself, the driving voltage signals having different polarities are respectively output, through the zener diode (ZD103) and the zener diode (ZD104), to the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) for respectively controlling the turn-on phase angle and the turn-off phase angle of the two field effect power components which are connected in parallel and in different polarities;

-- Configuration circuit of unipolar turn-on and turn-off phase angle (PD103): which is constituted by electronic circuit components and normal-polarity connected in series with the diode (CR101) for inputting an AC voltage of a first polarity; and through the configuration function of the circuit itself, a driving voltage signal having the same polarity as the unipolar solid switch unit (1001) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001);

-- Configuration circuit of unipolar turn-on and turn-off phase angle (PD104): which is constituted by electronic circuit components and normal-polarity connected in series with the diode (CR102) for inputting an AC voltage of a second polarity; and through the configuration function of the circuit itself, a driving voltage signal having the same polarity as the unipolar solid switch unit (1002) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1002);

--Diode (CR101): which is constituted by the rectifying diode, and

the diode (CR101) and the unipolar solid switch unit (1001) are normal-polarity connected in series with the regulation circuit of unipolar turn-on and turn-off phase angle (PD101);

--Diode (CR102): which is constituted by the rectifying diode, and
5 the diode (CR102) and the unipolar solid switch unit (1002) are normal-polarity connected in series with the configuration circuit of unipolar turn-on and turn-off phase angle (PD102);

--Zener diode (ZD103): which is constituted by the zener diode having zener voltage effect or the forward bias diode for
10 being connected in series between a driving voltage signal output terminal of the configuration circuit of unipolar turn-on and turn-off phase angle (PD103) and a driving voltage signal input terminal of the unipolar solid switch unit (1001);

--Zener diode (ZD104): which is constituted by the zener diode having zener voltage effect or the forward bias diode for
15 being connected in series between a driving voltage signal output terminal of the configuration circuit of unipolar turn-on and turn-off phase angle (PD104) and a driving voltage signal input terminal of the unipolar solid switch unit (1002);

20 The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

25 5. A synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage as claimed in claim 1, wherein it includes utilizing the bridge rectifiers combining with the solid switch unit for structuring the synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage, which mainly consists of:

30 --AC current limiting circuit device (Z10): which is constituted by

one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series between the AC power source and an AC input terminal of the bridge rectifier (BR101);

5 --Unipolar solid switch unit (1001): which is constituted by one or more than one of following solid switch units:

1) Constituted by the unipolar solid switch unit (1001) capable of controlling the turn-on phase angle, e.g. silicon controlled rectifier (SCR); and through the regulation function of the regulation circuit
10 of unipolar turn-on and turn-off phase angle (PD101) itself, a driving voltage signal is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) composed of silicon controlled rectifier (SCR);

2) the field effect power component serving as the unipolar solid
15 switch unit (1001), e.g. MOSFET and IGBT; and through the regulation function of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101), a driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) composed of the field effect power
20 component;

-- Regulation circuit of unipolar turn-on and turn-off phase angle (PD101): which is constituted by electronic circuit components and provided for being connected in parallel to a DC output terminal of the bridge rectifier (BR102); and through the regulation function of the
25 circuit itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a driving voltage signal having the same polarity as the unipolar solid switch unit (1001) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit
30 (1001);

--Bridge rectifier (BR101): which is constituted by at least four rectifying diodes, in which the AC power input terminal is provided for being connected in series to the AC current limiting circuit device (Z10) so as to be connected to the AC power source, and is provided with the output terminals having anode and cathode of the DC power source; for
5 rectifying the AC power source to DC power source, so as to output to the unipolar solid switch unit (1001) and the load (L101) connected in series;

--Bridge rectifier (BR102): which is constituted by at least four
10 rectifying diodes and provided with two input terminals for receiving the AC power source and the output terminals having anode and cathode for outputting the DC power source; for rectifying the AC power source to DC power source, so as to output to the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) then
15 further output the driving voltage signal to the unipolar solid switch unit (1001);

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive
20 load and the capacitive load containing the resistance connected in series.

6. A synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage as claimed in claim 1, wherein it includes configuring the regulation for the turn-on and turn-off phase angles to the solid
25 switch unit combined with the bridge rectifiers, which mainly consists of:

--AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series
30 and parallel, and one terminal thereof is connected to one terminal of

the AC power source, and the other terminal thereof is connected in series with the load (L101) for leading to the AC input terminal of the bridge rectifier (BR101), and the other AC input terminal of the bridge rectifier (BR101) is connected to the other terminal of the AC power source;

--Unipolar solid switch unit (1001): which is constituted by one or more than one of following solid switch units:

1) Constituted by the unipolar solid switch unit (1001) capable of controlling the turn-on phase angle, e.g. silicon controlled rectifier (SCR); and through the regulation function of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load (L101), a driving voltage signal is output, through the zener diode (ZD103), to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) composed of silicon controlled rectifier (SCR);

2) the field effect power component serving as the unipolar solid switch unit (1001), e.g. MOSFET and IGBT; and through the regulation function of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load (L101), a driving voltage signal is output, through the zener diode (ZD103), to regulate the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) composed of the field effect power component;

-- Configuration circuit of unipolar turn-on and turn-off phase angle (PD103): constituted by electronic circuit components and provided for being connected in parallel to the DC output terminal of the bridge rectifier (BR101); through the configuration function of the circuit

itself, a driving voltage signal is output, and through the zener diode (ZD103), to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001);

5 --Bridge rectifier (BR101): which is constituted by at least four rectifying diodes and provided with two input terminals for receiving the AC power source and the output terminals having anode and cathode for outputting the DC power source; for rectifying the AC power source to DC power source, so as to output to the unipolar switch unit (1001) and the configuration circuit of single-polarity
10 turn-on and turn-off phase angle (PD103);

 --Zener diode (ZD103): which is constituted by the zener diode having zener voltage effect or the forward bias diode for being connected in series between a driving voltage signal output terminal of the configuration circuit of unipolar turn-on and turn-off
15 phase angle (PD103) and a driving voltage signal input terminal of the unipolar solid switch unit (1001);

 The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which
20 the inductive load and the capacitive load containing the resistance connected in series.

7. A synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage as claimed in claim 1, wherein it includes utilizing the bipolar solid switch unit to structure the synchronous regulation for
25 turn-on and turn-off phase angle of the AC voltage, and through the AC current limiting circuit device (Z10) detecting the current value, to output to the regulation circuit of turn-on and turn-off phase angle, thereby to regulate the voltage or current passing the load via the solid switch unit, which mainly consists of:

30 --AC current limiting circuit device (Z10): which is constituted by

one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series with the load (L101) and the bipolar solid switch unit (1000) then connected in
5 parallel with the AC power source;

--Bipolar solid switch unit (1000): which is constituted by one or more than one of following solid switch units:

- 1) The bipolar solid switch unit (1000) is composed of a bidirectional thyristor component capable of controlling the turn-on phase angle,
10 e.g. bidirectional silicon controlled rectifier TRIAC (Triode AC semiconductor switch); through the regulation function of the regulation circuit of bipolar turn-on and turn-off phase angle (PD100) itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the
15 load (L101), a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) composed of the TRIAC;
- 2) The bipolar solid switch unit (1000) is composed of at least two field effect power components, e.g. a bipolar module composed of
20 the metal oxide semiconductor field effect transistor (MOSFET) or the insulated gate bipolar transistor (IGBT)bipolar solid switch unit; and through the regulation function of the regulation circuit of bipolar turn-on and turn-off phase angle (PD100) itself and with respect to the current value passing the AC current limiting circuit
25 device (Z10) and the terminal voltage of the load (L101), a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000) composed of at least two field effect power components;

-- Regulation circuit of bipolar turn-on and turn-off phase angle
30 (PD100): which is constituted by electronic circuit components for

inputting the AC power voltage; and through the regulation function of the circuit itself, and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load (L101), a bipolar driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the bipolar solid switch unit (1000);

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

8. A synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage as claimed in claim 1, wherein it includes utilizing two solid switch units to structure the synchronous regulation for turn-on and turn-off phase angle of the AC voltage, and through the AC current limiting circuit device (Z10) detecting the current value, to output to the regulation circuit of turn-on and turn-off phase angle, thereby to regulate the voltage or current passing the load via the solid switch unit, which mainly consists of:

--AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series with the load (L101) and the bipolar solid switch unit (1000) then connected in parallel with the AC power source;

--Bipolar solid switch unit (1000): which is constituted by a unipolar solid switch unit (1001) and a unipolar solid switch unit (1002) being reverse-polarity connected in parallel; the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) are composed of one or more than one of following solid switch units:

- 1) Constituted by at least two unipolar solid switch units (1001, 1002) capable of controlling the turn-on phase angle, e.g. at least two silicon controlled rectifiers (SCRs) being reverse-polarity connected in parallel for forming the bipolar solid switch unit (1000); and through the regulation functions of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and the regulation circuit of unipolar turn-on and turn-off phase angle (PD102) itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load (L101), the driving voltage signals having different polarities are respectively output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002);
- 2) the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002) are composed of at least two field effect power components being reverse-polarity connected in parallel to form the bipolar solid switch unit (1000), e.g. the bipolar module composed of the MOSFET and IGBT serving as the bipolar solid switch unit (1000); and through the regulation functions of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and the regulation circuit of unipolar turn-on and turn-off phase angle (PD102) itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load (L101), the driving voltage signals having different polarities are respectively output to control the turn-on phase angle and the turn-off phase angle of the two field effect power components which are connected in parallel and in different polarities for respectively forming the unipolar solid switch unit (1001) and the unipolar solid switch unit (1002);
- Regulation circuit of unipolar turn-on and turn-off phase angle

(PD101): which is constituted by electronic circuit components and normal-polarity connected in series with the diode (CR101) for inputting an AC voltage of a first polarity; and through the regulation function of the circuit itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a driving voltage signal having the same polarity as the unipolar solid switch unit (1001) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001);

-- Configuration circuit of unipolar turn-on and turn-off phase angle (PD102): which is constituted by electronic circuit components and normal-polarity connected in series with the diode (CR102) for inputting an AC voltage of a second polarity; and through the regulation function of the circuit itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a driving voltage signal having the same polarity as the unipolar solid switch unit (1002) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1002);

--Diode (CR101): which is constituted by the rectifying diode, and the diode (CR101) and the unipolar solid switch unit (1001) are normal-polarity connected in series with the regulation circuit of unipolar turn-on and turn-off phase angle (PD101);

--Diode (CR102): which is constituted by the rectifying diode, and the diode (CR102) and the unipolar solid switch unit (1002) are normal-polarity connected in series with the configuration circuit of unipolar turn-on and turn-off phase angle (PD102);

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive

load and the capacitive load containing the resistance connected in series.

9. A synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage as claimed in claim 1, wherein it includes utilizing the bridge rectifiers combining with the solid switch unit to structure the synchronous regulation for turn-on and turn-off phase angle of the AC voltage, and through the AC current limiting circuit device (Z10) detecting the current value, to output to the regulation circuit of turn-on and turn-off phase angle, and to regulate the voltage or current passing through the load via the solid switch unit, which mainly consists of:

--AC current limiting circuit device (Z10): which is constituted by one or more than one of resistive impedance, inductive impedance and capacitive impedance being connected in series, in parallel or in series and parallel and provided for being connected in series between the AC power source and an AC input terminal of the bridge rectifier (BR101);

--Unipolar solid switch unit (1001): which is constituted by one or more than one of following solid switch units:

1) Constituted by the unipolar solid switch unit (1001) capable of controlling the turn-on phase angle, e.g. silicon controlled rectifier (SCR); and through the regulation function of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load (L101), a driving voltage signal is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) composed of silicon controlled rectifier (SCR);

2) the field effect power component serving as the unipolar solid switch unit (1001), e.g. MOSFET and IGBT; and through the regulation function of the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) itself and with respect to the current

value passing the AC current limiting circuit device (Z10) and the terminal voltage value of the load (L101), a driving voltage signal is output to regulate the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001) composed of the field effect power component;

-- Regulation circuit of unipolar turn-on and turn-off phase angle (PD101): which is constituted by electronic circuit components, and connected in parallel to a DC output terminal of the bridge rectifier (BR102); and through the regulation function of the circuit itself and with respect to the current value passing the AC current limiting circuit device (Z10) and the terminal voltage of the load (L101), a driving voltage signal having the same polarity as the unipolar solid switch unit (1001) is output to control the turn-on phase angle and the turn-off phase angle of the unipolar solid switch unit (1001);

--Bridge rectifier (BR101): which is constituted by at least four rectifying diodes, in which the AC power input terminal is provided for being connected in series to the AC current limiting circuit device (Z10) so as to be connected to the AC power source, and is provided with the output terminals having anode and cathode of the DC power source; for rectifying the AC power source to DC power source, so as to output to the unipolar solid switch unit (1001) and the load (L101) connected in series;

--Bridge rectifier (BR102): which is constituted by at least four rectifying diodes and provided with two input terminals for receiving the AC power source and the output terminals having anode and cathode for outputting the DC power source; for rectifying the AC power source to DC power source, so as to output to the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) then further output the driving voltage signal to the unipolar solid switch unit (1001);

The mentioned circuit is for regulating the resistance, the inductive load containing the resistance or the capacitive load containing the resistance driven by the AC power, or the load in which the inductive load and the capacitive load containing the resistance connected in series.

10. A synchronous regulation circuit for turn-on and turn-off phase angle of the AC voltage as claimed in claim 1, wherein the output driving voltage signal of the regulation circuit of bipolar turn-on and turn-off phase angle (PD100), the configuration circuit of bipolar turn-on and turn-off phase angle (PD200), the regulation circuit of unipolar turn-on and turn-off phase angle (PD101) and (PD102), the configuration circuit of unipolar turn-on and turn-off phase angle (PD103) and (PD104) can be constituted by the followings, which includes:
- 1) Directly outputting the power signal to drive the mated solid switch unit;
 - 2) Utilizing a photoelectric coupling device for insulation and outputting the power signal to drive the mated solid switch unit; and
 - 3) Utilizing a pulse transformer for insulation and outputting the power signal to drive the mated solid switch unit.