

Description

This invention relates to circuitry of the type which uses memory devices to perform desired transfer functions. An example of such circuitry is an adaptive compandor using a memory programmed with a plurality of compansion functions, wherein the signal to be companded is applied as address codes to the memory device.

US-A-4187519 discloses an apparatus for correcting a video signal. An "l-getter" acts as a source of control signals determining, from the input pixels, bias and gain parameters. A bias function generator 15 is automatically adjusted by the bias parameters to develop bias correction signals which are applied to the video signal. A gain function generator adjusted by the gain parameters develops a gain correction signal which is applied to the video signal. Each of the function generators produces correction signals by interpolating from the bias parameters received from the "l-getter". This is a slow process and so a delay element is provided in the video signal path.

JP-A-59-181876 discloses apparatus for correcting a video signal. The apparatus has a plurality of wave form generators storing respective correction waveforms. A program stored in a ROM is used to select the appropriate correction waveform.

It is known in the art of digital signal processing to use memory devices as functional elements. The memory device is programmed at respective memory locations with values corresponding to address values transformed by a desired transfer function. For example, if it is desired to scale a digital signal by a particular value, each memory location is programmed with a value equal to the address of the particular memory location multiplied by the scaling value. The system may be made adaptive by segmenting the memory device into tables, each of which corresponds to the address values being multiplied by a different scale factor. The particular table utilized at any given time is accessed by appending control bits to the address codes.

Not all transfer functions can be realized with memory elements in a cost effective manner. Conversely, some transfer functions can only be realized using programmed memories. This is particularly true for certain non-linear functions. Unfortunately the memory devices may become undesirably large. Consider for example an adaptive system processing 8-bit samples, a memory with 8-bit precision, and 8-bit adaptive control signals. The required memory includes 2^8 tables having 2^8 memory locations of 8 bits each or a total memory capacity of 524288 bits. A memory of this size will impose appreciable cost to the system.

The present inventor realized that for certain families of transfer functions that are implemented in adaptive systems, the memory requirements may be

significantly reduced. This is achieved by storing values corresponding to only one representative transfer function in memory. Then by appropriately offsetting the signal applied to the memory and/or scaling the values provided to or by the memory, responses corresponding to others of the family of transfer functions may be effectively realized.

According to the present invention, there is provided apparatus for processing a video signal comprising a source of a video input signal; first circuit means having an input terminal and an output terminal, for performing a transfer function on signals delivered to said input terminal; a source of control values; and second circuit means, coupled between said video input signal source and said input terminal of said first circuit means, for performing one of a scaling function and an offset function upon said video input signal; characterized in that said first circuit means comprises a memory means programmed at respective address locations with values representing corresponding address values which have been transformed in accordance with a single predetermined transfer function, and in that the input terminal of said first circuit means corresponds to an address input port of said memory means; whereby said video input signal is subject to a selected one of a family of transfer functions in dependence upon the control value supplied to said second circuit means.

In the drawings:

FIGURE 1 is a graph of a portion of a family of transfer characteristics which can be realized with the present invention.

FIGURES 2 and 3 are graphs of a single transfer characteristic representative of the family of characteristics illustrated in FIGURE 1 and useful in describing the operation of the invention.

FIGURES 4, 5 and 8 are block diagrams of alternative embodiments of the invention.

FIGURES 6 and 7 are block diagrams of alternative compansion systems wherein either the direct compandor or the inverse compandor or both may be realized with circuitry according to the present invention.

FIGURE 9 is a block diagram of a further embodiment of the invention.

FIGURES 10 and 11 are block diagrams of alternative adaptive compansion circuits utilizing the circuitry illustrated in FIGURE 9.

FIGURE 12 is a block diagram of an adaptive peaking circuit embodying the invention.

Embodiments of the invention are described below in the environment of a compansion system; however its utility is not restricted to this use. It will be appreciated that the invention is applicable to any system requiring selectable transfer functions which transfer functions conform to a family of functions

that can be substantially derived from a single representative transfer function.

Refer to FIGURE 1 which graphically illustrates a family of curves representing a plurality of compander transfer functions. Each curve represents a particular input-output relationship which may be employed for particular signal conditions. For example, if it is known that for a particular time interval the input signal is most likely to have values of $50 \pm \Delta$ (Δ a small value), then the curve labeled TF1 may represent the desired input-output relationship. Alternatively, if for a particular time interval the input signal is expected to have a value of $0 \pm \Delta$, then the curve labeled TF2 may represent the desired input-output relationship. From the figure it can be seen that the curves have the same general shape as the curve TF1 or a portion of TF1. The curve labeled TF3 is similar to curve TF1 but shifted rightward and upward. The curve TF4 is similar to curve TF1 but shifted leftward and downward, etc. Note further that if the curve TF4 is translated leftward and downward by 100 units, the combination of curves TF2 and TF4 will have the same general shape as the curve TF1. Finally, assume that the curves shown only represent a small portion of the family of transfer functions desired, i.e., that between curves TF2 and TF4 there are actually a large number of curves.

The dynamic range of the output values for the family of transfer functions is equal to the dynamic range of possible input values. This is a feature of the exemplary compander systems described herein below, but is not a requirement of the invention.

Refer to FIGURE 2 which illustrates a transfer function STF representative of the family of transfer functions shown in FIGURE 1. In this example the standardized transfer function STF may be derived from the combination of transfer functions TF2 and TF4 connected end-to-end. Note that in FIGURE 2 the input and output dynamic range is twice the input and output dynamic range of the transfer function of FIGURE 1.

Assume a memory device is programmed to output values indicated by the transfer function STF for the corresponding input levels applied as address codes to its address input port. Assume further that the input signal has a dynamic range of 0 to 100 and that it is desired to realize the transfer function TF1.

The inflection point of the curve TF1 is at an input level of 50. The inflection point of the curve STF is at an input level of zero. To apply the transfer function at the inflection point of the curve STF to the input signal level of 50, the input signal is offset by negative 50 units. Offsetting the input signal applied to the memory device by 50 units established the dynamic range of the input levels applied to the memory from -50 to +50 units. This dynamic range of 100 units falls between the dashed lines designated AA. The desired output dynamic range is 100 units for the trans-

fer functions shown in FIGURE 1. However, it is seen from FIGURE 2 that the output dynamic range produced by the transfer function STF for the input range between lines AA is approximately 150 units. The dynamic range of the output signal may be constrained to 100 units by scaling the output values provided by the memory by the factor $100/150$ or $2/3$. Scaling the output values constrains the dynamic range to fall between the dashed lines BB in FIGURE 2 and produces the transfer function labeled TF1'. Depending upon the method of generating the curve STF, relative to the conformity of the family of transfer functions to a single curve, the transfer function TF1' will conform exactly to the function TF1 or very closely approximate the function TF1.

There is one further requirement to render the scaled output values (TF1') in conformance with the transfer function TF1. The output dynamic range of the scaled values is from -50 to +50 units. The desired output dynamic range is 0 to 100 units. Thus the scaled output values must be offset by a positive 50 units.

Refer to FIGURE 3 and assume that the desired transfer function is TF2. Assuming that the inflection point of the curve TF2 is at zero units, and that the inflection point of the curve STF is at 0 units, the range of input levels applied to the memory is the range between the dashed lines C,C. For both FIGURE 1 and FIGURE 2 this range is 0 to 100 units, thus no offset is required to be applied to the input signal applied to the memory. Between the dashed lines C,C, the output dynamic range defined by the curve STF is 100 units, thus no scaling is required of the output values. In addition no offset is required to be applied to the output values.

The transfer function TF4 is realized by using that portion of the curve STF to the left of the dashed line C centered on zero units. In this instance the signal input values must be offset by negative 100 units and the signal output values must be offset by positive 100 units. However, no scaling is required of the output values.

Assume that all of the transfer functions of the desired family and the representative function are monotonic. The input offset value IO_i is determined by a comparison of the desired function against the representative function. This may be performed graphically or numerically depending upon the shape or symmetry of the functions. Assume that the output value provided by the standard function STF for an input value x is $F(x)$. Assume still further that the input signal range extends from a minimum value x_n to a maximum value x_x and that the desired output dynamic range for respective ones of the family of functions is OR_i . The scale factor G_i for the particular selected function is determined from the relation

$$G_i = OR_i / (F(x_x - IO_i) - F(x_n - IO_i)) \quad (1)$$

where $F(x_x - IO_i)$ and $F(x_n - IO_i)$ correspond to the max-

imum and minimum values provided in accordance with the function STF for the offset input range. The quotient represents the ratio of the desired output dynamic range to the output dynamic range of the function STF for the given input range of values applied to the memory address input.

The output offset value OO_i is determined as follows for a system where scaling precedes the application of the output offset value. Let $F_i(x_n)$ equal the maximum output level for the respective desired transfer function. Then it is desired that

$$F_i'(x_n) = G_i \times F(x_n - IO_i) + OO_i \quad (2)$$

$$OO_i = F_i'(x_n) - G_i \times F(x_n - IO_i) \quad (3)$$

Output offsetting may be performed prior to scaling. In this instance the scale factors G_i do not change but the respective values OO_i' are different. The values OO_i' are determined from the relation

$$F_i'(x_n) = G_i \times (F(x_n - IO_i) + OO_i) \quad (4)$$

or

$$OO_i' = F_i'(x_n)/G_i - F(x_n - IO_i) \quad (5)$$

The values G_i , OO_i and IO_i are preprogrammed in a second memory which is addressed by a control signal C_i at appropriate time intervals. Responsive to the control signals C_i , the values G_i , OO_i and IO_i are applied to circuitry coupled in the signal path with the transfer function memory to perform the desired offsetting and scaling functions.

Considering 8-bit input samples, 8-bit output samples and 2^8 different transfer functions, the required memory for the present system is calculated as follows. The memory for storing the standard function has $2^9 \times 8 = 4096$ bits (note the STF memory has twice the input dynamic range). Each of the 2^8 transfer functions requires three values (G_i , OO_i and IO_i) which are assumed to be 8-bits, for a total of $8 \times 3 \times 2^8 = 6144$ bits. The total system bit count is 10240 bits or a savings of 514048 bits.

FIGURE 4 illustrates one embodiment of apparatus for performing the invention. In the figure the signals are presumed to be parallel-bit pulse code modulated (e.g., PCM binary) signals, and the connections are parallel conductor busses. Signal to be processed is applied to an input terminal 10 and control values C_i are applied to a control terminal 20. The control values may be derived from various sources depending upon the function to be accomplished. For example, if the process function is signal compansion, the control values may represent the signal-to-noise ratio of the input signal and be derived from signal/noise apparatus (not shown). Alternatively, the control values C_i may represent predictions of the input signal level and be derived via maximum-likelihood techniques, mean square error techniques or linear prediction methods, etc. The input signal is coupled to signal offset circuitry 12 shown as a subtractor. Output values from the input offset circuit 12 are applied to the address input port of a read only memory (ROM) 14 which is preprogrammed with a transfer function rep-

resentative of a family of transfer functions. The ROM 14 provides output sample values to a scaling circuit 16. Scaled samples generated by the scaling circuit 16 are coupled to output offset circuitry 18, shown as an adder. Output signal from the output offset circuitry 18 corresponds to the input signal transformed by the desired transfer function.

The control signal C_i is coupled to a control ROM 22 which is preprogrammed with respective offset and scale factor values IO_i , OO_i and G_i , corresponding to respective control signals C_i . The ROM provides input offset values IO_i to the input offset circuitry 12, output offset values OO_i to the output offset circuitry 18, and scale factors G_i to the scaling circuit 16. Note that the offset circuitry 12 and 18 may be realized with either signal addition or subtraction circuits with appropriate choice of the polarity of the offset values programmed in the control ROM 22.

FIGURE 5 illustrates a second embodiment wherein the scaling circuit 32 and the output offset circuitry 30 are coupled in reverse order relative the scaling and offset circuits 16 and 18 in FIGURE 4. In addition the control ROM is divided into two ROM circuits, control ROM1 and control ROM2. One further difference is the application of the sign or polarity bit of the sample provided by the input offset circuitry 12 as an extra address bit to the control ROM2.

Consider first that the sign bit is not connected to control ROM2. Control ROM1 is programmed with offset values IO_i and is responsive to control signals C_i . Control ROM2 is programmed with offset values OO_i' and scale factors G_i and the system provides the same input-output signal correspondence as the circuitry of FIGURE 4.

Next consider that it is possible to predict the instantaneous value of the input signal and that there is a different transfer function for each input signal value. In this instance the control ROM1 may be eliminated. The predicted signal corresponds to the control signal C_i , and is applied directly to the subtractor 12 and to the address input of the control ROM 2. An example of this type of system is shown in FIGURE 6.

FIGURE 6 illustrates a differential pulse code modulation (DPCM) system with adaptive compansion circuitry included in the DPCM loop. Input signal is applied to a first input terminal of a subtractor 605. A predicted video signal is coupled to a second input terminal of subtractor 605, the output of which is coupled to an adaptive compandor 612. The predicted video signal is substantially equal to the signal at the same pixel point in the previous image frame. The output signal from the subtractor 605 is thus equal to the difference of corresponding pixels in successive frames and nominally will be of small value. Output signal from the compandor 612 is coupled to an inverse compandor 620. Output signal from the inverse compandor 620 is coupled to an integrator including

an adder 640, a scaling circuit 630 and delay elements 650 and 662. The delay imposed by the combination of elements 630, 650 and 662 is exactly one frame interval. The integrator integrates the signal differences provided by subtractor 605 to reconstruct the video signal in known fashion. Integrated signal from the delay element 650 is coupled as the predicted video signal to the subtractor 605. The total processing delay imposed by the elements coupled in series between the output and second input terminals of subtractor 605 is substantially one frame interval. Delay elements 610, 614 and 616 are included in the system to compensate for delays in generating the control signal for the adaptive companders 612 and 620.

The input video signal and the predicted video signal are coupled to a second subtractor 655 which produces output differences equal to the differences generated by the subtractor 605. The output signal from subtractor 655 is thus an exact prediction of the input signal applied to the direct compandor 612. Thus the direct compandor 612 may be implemented with the circuitry of FIGURE 5, with the control ROM 1 eliminated and the output of subtractor 655 applied directly to subtractor 12 (FIGURE 4) and also as control signal to the address input port of the control ROM 2. As illustrated in FIGURE 6 the circuitry provides DPCM signal at the OUTPUT for transmission or further processing.

Depending on the transfer functions implemented by element 612 it may be necessary to filter the control signals applied thereto to preclude the system from becoming unstable and exhibiting limit cycles for example. This additional filter is shown as element 615 drawn in phantom.

Alternatively, if it is desired to provide companded video signal as output signal rather than a companded DPCM signal, the system of FIGURE 6 may be altered as shown in FIGURE 7. The FIGURE 5 compandor absent the control ROM1 is used as a direct compandor. Companded video signal from the scaling circuit 32 is used as an output signal OUTPUT, and is coupled to an inverse compandor 70 which restores the companded video signal to original form. Video signal from the inverse compandor 70 is coupled to a delay circuit 72 and delayed video signal is applied to for example a spatial filter 74. Spatial filter 74 in cooperation with the delay element 72, provides an estimate of the input signal. This estimate may be formed as the average of a number of pixels occurring a field or frame earlier and which average correspond to the pixel location represented by the current input signal sample.

The estimated signal is applied as input offset values IO_i to the offset circuitry 12 and also as control values C_i to the address input port of the control ROM2.

Referring back to FIGURE 5 the system will be

described with the inclusion of the sign bit from subtractor 12. In this instance the control ROM 2 will include two tables, each containing values OO_i and G_i . The use of the sign bit is to modify the transfer function such that when the input signal equals the value IO_i , the output signal should equal IO_i . In effect the input signal passes through the system unchanged when it is equal to IO_i . The control ROM 2 includes a first table of scale factor values G_{1i} and output offset values OO_{1i} responsive to the control signals C_i and a sign bit signal representing a negative polarity. The values G_{1i} and OO_{1i} are given by

$$G_{1i} = -IO_i / F(IO_i) \quad (6)$$

$$OO_{1i} = -IO_i / G_{1i} \quad (7)$$

In addition the control ROM 2 includes a second table of scale factor values G_{2i} and output offset values OO_{2i} responsive to the control values C_i and a sign bit signal representing a positive value. The values G_{2i} and OO_{2i} are given by

$$G_{2i} = (x_x - IO_i) / F(x_x - IO_i) \quad (8)$$

$$OO_{2i} = -IO_i / G_{2i} \quad (9)$$

where x_x is the upper limit of the dynamic range of the input signal.

FIGURE 8 illustrates a system for performing the inverse function of the system of FIGURE 5. An inverse function may be realized with a system similar to FIGURE 5 with appropriate programming of the respective memory elements. However if both a direct and inverse function is desired in a single circuit as illustrated in FIGURE 6, it is desirable to minimize hardware. The amount of hardware can be minimized if both the direct and inverse functions use common control ROM's. Arranging the inverse function circuitry as illustrated in FIGURE 8 permits the use of at least common output offset values OO_i and common input offset values IO_i for both the direct and inverse function circuits.

In FIGURE 8 the input signal is applied to a scaling circuit 52 wherein it is scaled by values $1/G_i$ which values are the reciprocals of the values G_i stored in the control ROM 1 (FIGURE 5). The scaled input signal values are applied to offset circuitry 54 wherein they are offset by values OO_i which values are equal to the output offset values stored in the control ROM 2 (FIGURE 5). The values $1/G_i$ and OO_i are provided by a control ROM 60 responsive to control signals C_i , which signals C_i are equivalent to the control values C_i applied to control ROM 1 and control ROM 2 (FIGURE 5).

The scaled and offset input signal is applied as address codes to a transfer function ROM 56. ROM 56 is programmed with the same function STF as the ROM 14 in FIGURE 5, only rotated. That is, considering FIGURE 2, values corresponding to the input levels are programmed at address locations corresponding to respective output levels.

Output signal samples provided by the transfer function ROM 56 are coupled to an offset circuit 58

wherein the output samples are offset by the values IO_1 which are equivalent to the input offset values IO_1 stored in the control ROM 1 (FIGURE 5). The values IO_1 are also provided by the control ROM 60.

The inverse function system may also be modified to be responsive to a polarity control signal. This is indicated by the auxiliary circuitry including subtracter 61 drawn in phantom.

FIGURE 9 illustrates another embodiment of the invention which will generate a family of transfer functions from a single transfer function. Consider, for example, the function $Y(x)$ given by

$$Y(x) = x/(1 + x^{2N}) \quad (10)$$

where x corresponds to the input signal and N is an integer. $Y(x)$ is skew symmetric about zero, has a value of zero at $x=0$, tends toward zero for values of x greater than X_{max} and less than X_{min} and wherein X_{max} and X_{min} are equal to plus and minus the $2N^{th}$ root of $1/(2N-1)$ respectively. Consider also that it is desired to adaptively control the values of x defining X_{max} and X_{min} . This may be accomplished by scaling the values of x applied to the circuit performing the function $Y(x)$. For example, if the input values x are scaled by the factor $1/\alpha$, α a positive value, such that the circuitry performing the function $Y(x)$ operates on the values x/α , the values of x defining X_{max} and X_{min} are α times the $2N^{th}$ root of $1/(2N-1)$. Thus the points of occurrence of X_{max} and X_{min} may be controlled by changing the values of α . In order to maintain the output dynamic range of the signal $Y(x)$ for the function of equation (10), the values provided by the function circuit may be scaled by the reciprocal of the input scale factor. FIGURE 9 is an adaptive function generating circuit of this form.

In FIGURE 9 input samples are applied to a scaling circuit 90 wherein the samples are scaled by a scale factor $1/\alpha$. The scaled samples (x/α) are applied to a functional circuit 91 which may be a ROM programmed with a desired transfer function. Transformed samples are coupled to a further scaling circuit 92, wherein the transformed samples are scaled by a scale factor α . The scaling circuit provides the desired output values. Assuming that the transfer function performed by the circuitry 91 corresponds to the function defined by equation 10, the scaling circuit provides output samples of the form given by

$$OUTPUT = x/(1 + (x/\alpha)^{2N}) \quad (11)$$

or more generally

$$OUTPUT = \alpha Y(X/\alpha) \quad (12)$$

Note however that for some applications it may not be necessary to include the latter scaling circuit 92. In addition, if scaling circuit 92 is included, the scale factor applied thereto may have values different from the reciprocal of the values applied to the scaling circuit 90. Further, the scale factor $1/\alpha$, applied to the scaling circuit 90 is not meant to imply that the values $1/\alpha$ are limited to values less than 1, but may include values greater than 1. The scale factors α and $1/\alpha$ may be

provided by a ROM responsive to appropriate control signals, or by other convenient circuitry to promote the desired adaptive response.

FIGURE 10 illustrates a further embodiment of the invention for providing a plurality of transfer functions using an element (91) arranged to generate a single transfer function. In FIGURE 10 (and FIGURE 11) circuit elements designated with the same numerals as circuit elements in FIGURE 9 are similar and operate in like fashion.

Input samples are applied to the minuend input terminal of a subtracter circuit 95, and to the input terminal of the adaptive functional circuitry 96. Output samples from the circuitry 96 are coupled to the subtrahend input terminal of the subtracter 95. The subtracter 95 provides output samples, OUTPUT in conformance with the function

$$OUTPUT = x - \beta Y(x/\alpha) \quad (13)$$

Assume that the functional element 91 performs the function defined by equation 10 and that the scale factor β is equal to α . In this instance the output signal is equal to

$$OUTPUT = x(1 - 1/(1 + (x/\alpha)^{2N})) \quad (14)$$

This function is similar to the function TF1 illustrated in FIGURE 1, except that for larger values of the input signal the slope of the curve tends toward 1. The point of inflection of the curve is adjustable in accordance with the values $1/\alpha$ and α applied to the scaling circuits 90 and 92 respectively. Next assume that the scale factor β is equal to b times α . (b a variable). In this instance the output signal provided by subtracter 95 is given by

$$OUTPUT = x(1 - b/(1 + (x/\alpha)^{2N})) \quad (15)$$

This arrangement permits establishment of the slope of the curve at $x = 0$ to the value $(1-b)$. Note the value N influences the steepness of the slope at the point of inflection, the larger the value N the greater the slope.

The function defined by equation 15 is useful as an adaptive noise coring circuit wherein the degree of attenuation or coring is determined by the factor β , and the range of signal over which coring is performed is determined by the factor α . The factors α and β may be selected as a function of the signal to noise ratio.

The functions defined by either equations (14) or (15) are also useful for performing adaptive compansion, similar to the function performed by the circuitry of FIGURE 8. That is the circuitry of FIGURE 10 may be utilized in a communications receiver to perform a complementary compansion function of signal which has been companded at a transmitter.

FIGURE 11 illustrates circuitry for performing the complementary function of the circuitry illustrated in FIGURE 10. The circuitry of FIGURE 10 tends to compress smaller amplitude signal values and to expand (amplify) larger amplitude signal values, while the circuitry of FIGURE 11 tends to expand smaller

amplitude signal values and to compress larger amplitude signal values.

FIGURE 12 illustrates a further application wherein the invention is used to perform peaking control of a vertical detail signal in a television receiver. In FIGURE 12 composite video signal is converted to digital form in an analog-to-digital converter (A/D) and comb filtered to separate the luminance, Y, and chrominance, C, components. The lower frequency spectrum of the comb filtered chrominance component contains luminance vertical detail which is separated by the bandpass/lowpass filter and added back to the luminance signal in the adder 105, to provide a restored luminance signal. The vertical detail signal is also processed by the circuitry 101, 102 and 103 to provide a cored, peaked and pared vertical detail signal which is added to the restored luminance signal in an adder 104 to generate a luminance signal with peaked vertical detail. The peaking function is well known, and desirably is arranged to be adjustable so that the user can adjust the displayed image according to his viewing preference. The general form of the transfer function applied to the vertical detail signal is illustrated in the block designated 102. Elements 101, 102 and 103 are arranged to operate similar to the elements 90, 91 and 92, respectively of FIGURE 9 to permit the user to select one of a family of transfer functions. The user may select the portion of the dynamic range of the vertical detail signal to be peaked by changing the gain factor α and he may select the degree of peaking by adjusting the gain factor β .

Claims

1. Apparatus for processing a video signal comprising:

a source (10) of a video input signal;
first circuit means (14) having an input terminal and an output terminal, for performing a transfer function on signals delivered to said input terminal;

a source (22) of control values; and
second circuit means (12), coupled between said video input signal source and said input terminal of said first circuit means, for performing one of a scaling function and an offset function upon said video input signal;

characterized in that said first circuit means comprises a memory means (ROM 14) programmed at respective address locations with values representing corresponding address values which have been transformed in accordance with a single predetermined transfer function, and in that the input terminal of said first circuit means corresponds to an address input port of said memory means;

whereby said video input signal is subject

to a selected one of a family of transfer functions in dependence upon the control value supplied to said second circuit means.

- 5 2. Processing apparatus in accordance with claim 1, further characterized by third circuit means (16) responsive to the signal output of said first circuit means, and to an additional control value from said source of control values, for performing one of a scaling function and an offset function upon the signal output of said first circuit means; whereby the selection of said one of said family of transfer functions to which said video input signal is subject is additionally dependent upon the additional control value supplied to said third circuit means.
- 10 3. Processing apparatus in accordance with claim 1 or claim 2, further characterized by further circuit means (54), serially coupled with said second circuit means (52) between said video input signal source and said input terminal of said first circuit means, and also responsive to a further control value from said source of control values, for performing one of a scaling function and an offset function different from the one of said scaling and offset functions performed by said second circuit means (52); whereby the selection of said one of said family of transfer functions to which said video input signal is subject is additionally dependent upon the further control value supplied to said further circuit means (54).
- 15 4. Processing apparatus in accordance with claim 1 or claim 2, further characterized by additional circuit means (32), serially coupled with said third circuit means (30), and also responsive to another control value from said source of control values, for performing one of a scaling function and an offset function different from the one of said scaling and offset functions performed by said third circuit means (30); whereby the selection of said one of said family of transfer functions to which said video input signal is subject is also dependent upon said another control value supplied to said additional circuit means (32).
- 20 5. Processing apparatus in accordance with claim 1 or claim 2, further characterized by further circuit means (54), serially coupled with said second circuit means (52) between said video input signal source and said input terminal of said first circuit means, and also responsive to a further control value from said source of control values, for performing one of a scaling function and an offset function different from the one of said scaling and offset functions performed by said second circuit means (52); whereby the selection of said one of said family of transfer functions to which said video input signal is subject is additionally dependent upon the further control value supplied to said further circuit means (54).
- 25 6. Processing apparatus in accordance with claim 1 or claim 2, further characterized by further circuit means (54), serially coupled with said second circuit means (52) between said video input signal source and said input terminal of said first circuit means, and also responsive to a further control value from said source of control values, for performing one of a scaling function and an offset function different from the one of said scaling and offset functions performed by said second circuit means (52); whereby the selection of said one of said family of transfer functions to which said video input signal is subject is additionally dependent upon the further control value supplied to said further circuit means (54).
- 30 7. Processing apparatus in accordance with claim 1 or claim 2, further characterized by further circuit means (54), serially coupled with said second circuit means (52) between said video input signal source and said input terminal of said first circuit means, and also responsive to a further control value from said source of control values, for performing one of a scaling function and an offset function different from the one of said scaling and offset functions performed by said second circuit means (52); whereby the selection of said one of said family of transfer functions to which said video input signal is subject is additionally dependent upon the further control value supplied to said further circuit means (54).
- 35 8. Processing apparatus in accordance with claim 1 or claim 2, further characterized by further circuit means (54), serially coupled with said second circuit means (52) between said video input signal source and said input terminal of said first circuit means, and also responsive to a further control value from said source of control values, for performing one of a scaling function and an offset function different from the one of said scaling and offset functions performed by said second circuit means (52); whereby the selection of said one of said family of transfer functions to which said video input signal is subject is additionally dependent upon the further control value supplied to said further circuit means (54).
- 40 9. Processing apparatus in accordance with claim 1 or claim 2, further characterized by further circuit means (54), serially coupled with said second circuit means (52) between said video input signal source and said input terminal of said first circuit means, and also responsive to a further control value from said source of control values, for performing one of a scaling function and an offset function different from the one of said scaling and offset functions performed by said second circuit means (52); whereby the selection of said one of said family of transfer functions to which said video input signal is subject is additionally dependent upon the further control value supplied to said further circuit means (54).
- 45 10. Processing apparatus in accordance with claim 1 or claim 2, further characterized by further circuit means (54), serially coupled with said second circuit means (52) between said video input signal source and said input terminal of said first circuit means, and also responsive to a further control value from said source of control values, for performing one of a scaling function and an offset function different from the one of said scaling and offset functions performed by said second circuit means (52); whereby the selection of said one of said family of transfer functions to which said video input signal is subject is additionally dependent upon the further control value supplied to said further circuit means (54).
- 50 11. Processing apparatus in accordance with claim 1 or claim 2, further characterized by further circuit means (54), serially coupled with said second circuit means (52) between said video input signal source and said input terminal of said first circuit means, and also responsive to a further control value from said source of control values, for performing one of a scaling function and an offset function different from the one of said scaling and offset functions performed by said second circuit means (52); whereby the selection of said one of said family of transfer functions to which said video input signal is subject is additionally dependent upon the further control value supplied to said further circuit means (54).
- 55 12. Processing apparatus in accordance with claim 1 or claim 2, further characterized by further circuit means (54), serially coupled with said second circuit means (52) between said video input signal source and said input terminal of said first circuit means, and also responsive to a further control value from said source of control values, for performing one of a scaling function and an offset function different from the one of said scaling and offset functions performed by said second circuit means (52); whereby the selection of said one of said family of transfer functions to which said video input signal is subject is additionally dependent upon the further control value supplied to said further circuit means (54).

Patentansprüche

1. Gerät zum Bearbeiten eines Videosignals, enthaltend:
 - eine Quelle (10) eines Video-Eingangssignals;
 - ein erstes Schaltungsmittel (14) mit einem Eingangsanschluß und einem Ausgangs-



amplitude signal values and to compress larger amplitude signal values.

FIGURE 12 illustrates a further application wherein the invention is used to perform peaking control of a vertical detail signal in a television receiver. In FIGURE 12 composite video signal is converted to digital form in an analog-to-digital converter (A/D) and comb filtered to separate the luminance, Y, and chrominance, C, components. The lower frequency spectrum of the comb filtered chrominance component contains luminance vertical detail which is separated by the bandpass/lowpass filter and added back to the luminance signal in the adder 105, to provide a restored luminance signal. The vertical detail signal is also processed by the circuitry 101, 102 and 103 to provide a cored, peaked and pared vertical detail signal which is added to the restored luminance signal in an adder 104 to generate a luminance signal with peaked vertical detail. The peaking function is well known, and desirably is arranged to be adjustable so that the user can adjust the displayed image according to his viewing preference. The general form of the transfer function applied to the vertical detail signal is illustrated in the block designated 102. Elements 101, 102 and 103 are arranged to operate similar to the elements 90, 91 and 92, respectively of FIGURE 9 to permit the user to select one of a family of transfer functions. The user may select the portion of the dynamic range of the vertical detail signal to be peaked by changing the gain factor α and he may select the degree of peaking by adjusting the gain factor β .

Claims

1. Apparatus for processing a video signal comprising:

a source (10) of a video input signal;
first circuit means (14) having an input terminal and an output terminal, for performing a transfer function on signals delivered to said input terminal;

a source (22) of control values; and
second circuit means (12), coupled between said video input signal source and said input terminal of said first circuit means, for performing one of a scaling function and an offset function upon said video input signal;

characterized in that said first circuit means comprises a memory means (ROM 14) programmed at respective address locations with values representing corresponding address values which have been transformed in accordance with a single predetermined transfer function, and in that the input terminal of said first circuit means corresponds to an address input port of said memory means;

whereby said video input signal is subject

to a selected one of a family of transfer functions in dependence upon the control value supplied to said second circuit means.

2. Processing apparatus in accordance with claim 1, further characterized by third circuit means (16) responsive to the signal output of said first circuit means, and to an additional control value from said source of control values, for performing one of a scaling function and an offset function upon the signal output of said first circuit means; whereby the selection of said one of said family of transfer functions to which said video input signal is subject is additionally dependent upon the additional control value supplied to said third circuit means.

3. Processing apparatus in accordance with claim 1 or claim 2, further characterized by further circuit means (54), serially coupled with said second circuit means (52) between said video input signal source and said input terminal of said first circuit means, and also responsive to a further control value from said source of control values, for performing one of a scaling function and an offset function different from the one of said scaling and offset functions performed by said second circuit means (52);

whereby the selection of said one of said family of transfer functions to which said video input signal is subject is additionally dependent upon the further control value supplied to said further circuit means (54).

4. Processing apparatus in accordance with claim 1 or claim 2, further characterized by additional circuit means (32), serially coupled with said third circuit means (30), and also responsive to another control value from said source of control values, for performing one of a scaling function and an offset function different from the one of said scaling and offset functions performed by said third circuit means (30);

whereby the selection of said one of said family of transfer functions to which said video input signal is subject is also dependent upon said another control value supplied to said additional circuit means (32).

Patentansprüche

1. Gerät zum Bearbeiten eines Videosignals, enthaltend:

- eine Quelle (10) eines Video-Eingangssignals;
- ein erstes Schaltungsmittel (14) mit einem Eingangsanschluß und einem Ausgangs-



- anschluß zum Ausführen einer Übertragungsfunktion für Signale, die dem Eingangsanschluß zugeführt werden;
- eine Quelle (22) von Steuerwerten; und
 - ein zweites Schaltungsmittel (12), das zwischen die Video-Eingangssignal-Quelle und den Eingangsanschluß des ersten Schaltungsmittels gekoppelt ist, zum Ausführen entweder der Skalierfunktion oder einer Offset-Funktion mit dem Video-Eingangssignal;
- dadurch gekennzeichnet,
- daß das erste Schaltungsmittel ein Speichermittel (ROM 14) enthält, das an jeweiligen Adressstellen oder -plätzen mit Werten programmiert ist, die korrespondierende Adressenwerte repräsentieren, die in Übereinstimmung mit einer einzelnen vorbestimmten Übertragungsfunktion transformiert worden sind, und daß der Eingangsanschluß des ersten Schaltungsmittels mit einem Adress-Eingangsport des Speichermittels korrespondiert;
 - wobei das Video-Eingangssignal einer ausgewählten Übertragungsfunktion einer Familie von Übertragungsfunktionen ausgesetzt wird oder ihr unterworfen wird, in Abhängigkeit von dem Steuerwert, der dem zweiten Steuermittel zugeführt wird.
2. Verarbeitungsgerät nach Anspruch 1, weiter gekennzeichnet durch ein drittes Schaltungsmittel (16), das auf das Ausgangssignal des ersten Schaltungsmittels und auf ein zusätzlichen Steuerwert von der Quelle der Steuerwerte anspricht, zum Durchführen entweder einer Skalierfunktion oder einer Offset-Funktion mit dem Ausgangssignal des ersten Schaltungsmittels;
- wobei die Auswahl der einen der Familie von Übertragungsfunktionen, der das Video-Eingangssignal ausgesetzt wird, zusätzlich von dem zusätzlichen Steuerwert abhängt, der dem dritten Schaltungsmittel zugeführt wird.
3. Verarbeitungsgerät nach Anspruch 1 oder 2,
- weiter gekennzeichnet durch ein weiteres Schaltungsmittel (54), das seriell mit dem zweiten Schaltungsmittel (52) zwischen der Video-Eingangssignal-Quelle und dem Eingangsanschluß des ersten Schaltungsmittels gekoppelt ist und das auch auf einen weiteren Steuerwert von der Quelle von Steuerwerten anspricht, zum Ausführen einer Skalierfunktion oder einer Offset-Funktion, die anders ist als die Funktion der Skalier- oder Offset-Funktion, die von dem zweiten Schaltungsmittel (52) ausgeführt wird;
- wobei die Auswahl der einen der Familie von Übertragungsfunktionen, der das Video-Eingangssignal unterworfen wird, zusätzlich von dem weiteren Steuerwert abhängt, der dem zweiten Schaltungsmittel (54) zugeführt wird.
4. Verarbeitungsgerät nach Anspruch 1 oder 2,
- weiter gekennzeichnet durch ein zusätzliches Schaltungsmittel (32), das seriell mit dem dritten Schaltungsmittel (30) gekoppelt ist und auch auf einen weiteren Steuerwert von der Steuerwert-Quelle anspricht, zum Ausführen einer Skalierfunktion oder einer Offset-Funktion, die anders ist als die Funktion der Skalier- oder Offset-Funktion, die von dem dritten Schaltungsmittel (30) ausgeführt wird;
 - wobei die Auswahl der einen der Familie von Übertragungsfunktionen, der das Video-Eingangssignal unterworfen wird, auch abhängt von dem zusätzlichen Steuerwert, der dem zusätzlichen Schaltungsmittel (32) zugeführt wird.

Revendications

1. Dispositif pour le traitement d'un signal vidéo comprenant :

- une source (10) d'un signal d'entrée vidéo ; des premiers moyens de circuit (14) comportant une borne d'entrée et une borne de sortie, pour exécuter une fonction de transfert sur des signaux délivrés à ladite borne d'entrée ;
 - une source (22) de valeurs de commande ; et
 - des seconds moyens de circuit (12) couplés entre ladite source de signal d'entrée vidéo et ladite borne d'entrée desdits premiers moyens de circuit, pour exécuter l'une des fonctions de changement d'échelle et de décalage sur ledit signal d'entrée vidéo ;
- caractérisé en ce que lesdits premiers moyens de circuit comprennent des moyens de mémoire (ROM 14) programmés à des emplacements d'adresse respectifs avec des valeurs représentant des valeurs d'adresse correspondantes qui ont été transformées selon une fonction de transfert unique prédéterminée et en ce que la borne d'entrée desdits premiers moyens de circuit correspond à un point d'accès d'entrée d'adresse desdits moyens de mémoire ;
- de manière que ledit signal d'entrée vidéo soit soumis à une fonction de trans-



fert choisie dans une famille de fonctions de transfert en dépendance avec la valeur de commande délivrée auxdits seconds moyens de circuit.

2. Dispositif de traitement selon la revendication 1, caractérisé en outre par des troisièmes moyens de circuit (16) agissant en réponse à la sortie de signal desdits premiers moyens de circuit et à une valeur de commande additionnelle de ladite source de valeurs de commande, pour exécuter l'une des fonctions de changement d'échelle et de décalage sur le signal de sortie desdits premiers moyens de circuit ;
de façon que la sélection de ladite fonction de la famille de fonctions de transfert à laquelle ledit signal d'entrée vidéo est soumis, soit additionnellement dépendante de la valeur de commande additionnelle délivrée auxdits troisièmes moyens de circuit.
3. Dispositif de traitement selon la revendication 1 ou 2 caractérisé en outre par d'autres moyens de circuit (54), couplés en série avec lesdits seconds moyens de circuit (52) entre ladite source de signal d'entrée vidéo et ladite borne d'entrée desdits premiers moyens de circuit, et agissant aussi en réponse à une autre valeur de commande de ladite source de valeurs de commande, pour exécuter l'une des fonctions de changement d'échelle et de décalage différente de l'une des fonctions de changement d'échelle et de décalage exécutée par lesdits seconds moyens de circuit (52) ;
de manière que la sélection de la fonction de transfert choisie dans la famille de fonction de transfert à laquelle est soumis ledit signal d'entrée vidéo est additionnellement dépendante de l'autre valeur de commande délivrée auxdits autres moyens de circuit (54).
4. Dispositif de traitement selon la revendication 1 ou 2 caractérisé en outre par des moyens additionnels de circuit (32), couplés en série avec lesdits troisièmes moyens de circuit (30) et agissant également en réponse à une autre valeur de commande de ladite source de valeurs de commande, pour exécuter l'une des fonctions de changement d'échelle et de décalage, différente de la fonction de changement d'échelle ou de décalage exécutée par lesdits troisièmes moyens de circuit (30) ;
de manière que la sélection de ladite fonction de la famille de fonctions de transfert à laquelle est soumis ledit signal d'entrée vidéo soit également dépendante de ladite autre valeur de commande délivrée auxdits moyens additionnels de circuit (32).