

Description

The present invention generally relates to clock generators for picture-in-picture (PIP) images for video signals. More particularly, the present invention relates to a pseudo line locked clock generator for e.g. capturing PIP images for both standard and nonstandard video signals.

In generating a PIP television image, it is standard to use a "write" clock for capturing the TV images from transmitted signals. The write clock is used to control the analog/digital conversion sample rate as well as to control the writing of the A/D converted signals into the addresses of a memory. In addition, the write clock controls the incoming data sequencing and compression of chrominance data. Once the data is stored at desired addresses in memory, a separate "read" clock is utilized to read the PIP data into the video data stream being sent to the television. The read clock controls the reading of digital signals from the memory as well as the conversion rate of the D/A converter. In addition, the read clock controls the outgoing data sequencing and expansion of the compressed chrominance data.

Because the video signal being captured for PIP display is typically independent of the main video signal which is to be displayed, the PIP write and read clocks are typically asynchronous. The two separate clocks are typically generated via the use of gated oscillators, line locked phase locked loop (PLL) circuits, or burst locked PLL circuits. Regardless of how generated, the use of two separate clocks has various drawbacks. Gated oscillator clocks often result in frequency instability resulting in the requirement that the PIP control integrated circuit must be designed to operate with the clock being off during part of each horizontal line. The line locked PLL clock, on the other hand, is stable, but is expensive to implement and is subject to frequency jitter. The burst locked PLL clock is also expensive to implement and does not operate well with non-standard signals such as might be generated by a VCR.

While the following disclosure is in terms of a write clock for the PIP circuit, other applications for generating a clock signal having a predetermined frequency and locked to a particular reset signal will readily come to mind and should not be excluded.

In light of the drawbacks of the clocking alternatives for PIP applications, it would be advantageous to produce a stable, inexpensive circuit which could replace the write clock. It is therefore the primary object of the invention to provide a stable, inexpensive pseudo line locked circuit utilizing an available clock asynchronous to the incoming PIP video signals for acting as a PIP write

clock. It is a further object of the invention to provide a pseudo line locked circuit for use as a PIP write clock which introduces substantially no visible artifacts into the PIP display.

In accord with the object of the invention, a simple PIP write clock which does not introduce visible artifacts comprises a dividing means for receiving and dividing by at least six a clock input asynchronous to incoming PIP video information which is at least six times the speed of the incoming PIP video information. The dividing means includes a cycle reset coupled to the horizontal synchronization signal of the incoming PIP video information, such that the clock signal output is at the rate of the incoming PIP video information and is pseudo line locked to the horizontal synchronization signal. Because the provided pseudo line locked PIP write clock causes data to be written at one sixth or less of a cycle out of sync with the horizontal sync signal, and because the PIP image is small (typically one-ninth the original screen size), substantially no visible artifacts are introduced into the PIP image.

In accord with a further embodiment of the invention, a horizontal synchronization leading edge pulse generator is provided for taking the horizontal synchronization signal and providing a stable leading edge pulse which may be reliably used as a horizontal reset for the divider means. Of course, where the trailing edge of the horizontal sync signal is stable, the horizontal sync signal may be directly used as a reset.

In accord with a first aspect of the invention, it provides an apparatus for generating an output clock signal synchronized to a preselected horizontal synchronization signal of a video information signal to be transferred and having a predetermined output clock frequency for clocking the transfer of said video information, comprising:

means for generating a clock input signal asynchronous to said preselected horizontal synchronization signal and having a clock input signal frequency at least n times said predetermined output clock frequency, where n is an integer greater than 1;

divider means for dividing said clock input signal by n to provide a divider output signal having said predetermined output clock frequency, and

being coupled to receive said preselected horizontal synchronization signal for being reset in response to said preselected horizontal synchronization signal, whereby said divider output signal constitutes said output clock signal.

In accord with a second aspect of the invention, it provides a method for generating an output clock signal synchronized to a preselected horizontal synchronization signal of a video information signal to be transferred and having a predeter-

mined output clock frequency for clocking the transfer of said video information, comprising the steps of:

generating a clock input signal synchronous to said preselected horizontal synchronization signal and having a clock input signal frequency at least n times said predetermined output clock frequency, where n is an integer greater than 1;

dividing said clock input signal by n thereby providing a divider output signal having said predetermined output clock frequency; and

restarting said dividing step in response to each received preselected horizontal synchronization signals, whereby said divider output signal constitutes said output clock signal.

Additional objects, features, and advantages of the invention will become apparent to those skilled in the art upon reference to the following detailed description of the invention and the accompanying drawings.

Figure 1 is a block diagram of the write clock circuit of the invention shown in conjunction with typical blocks for receiving and processing PIP luminance data;

Figure 2 is a circuit diagram of the preferred write clock circuit of the invention including a leading edge pulse generator and a divide by six means;

Figure 3 is a logic chart showing the values at different flip-flop ports of the divide by six means; and

Figure 4 is a timing diagram of the pseudo line locked write clock circuit.

Turning to Figure 1, a block diagram of the write clock 10 of the invention is seen in conjunction with the A/D conversion of PIP luminance data for storing in memory. The inputs into the write clock circuit 10 include a fast clock 15 of at least six times the speed ($6.W_c$) of the desired write clock, and a horizontal synchronization signal 18. Both the fast clock 15 and the horizontal synchronization signal are fed to the horizontal synchronization leading edge pulse generator 20 which generates a horizontal reset pulse (H_{reset}). The output pulse of the generator 20 and the fast clock are both input into the dividing means 30 which divides the fast clock rate by at least six, and provides a pseudo line locked clock of desired rate W_c . The write clock, while not exactly synchronized to the incoming PIP data 34, is pseudo line locked to the horizontal synchronization signal and hence the incoming data. Thus, the incoming data 34, which is filtered by standard low pass filter 36, is fed to A/D converter 38 whose conversion sample rate is controlled by the generated clock of desired rate W_c . The converted data is then sent over N bit bus 42 to a memory such as a RAM (not shown) where it is stored until being read into a main video data

stream.

While Figure 1 is indicative of PIP luminance processing, it should be appreciated that chrominance processing is accomplished in an identical manner. Further, while a fast clock 15 of six times the desired clock signal W_c is seen in conjunction with a divider 30 which divides by six, the division by the dividing means is set to correspond to the fast clock rate; i.e. if the fast clock is ten times faster than the desired write clock speed, the divider is arranged to be a divider by ten. In fact, the fast clock may be thought of as being at a rate $n W_c$, where n is preferably greater than or equal to six. The divider means is then correspondingly arranged to divide by n . Also, as indicated in Figure 1, while the horizontal sync leading edge pulse generator 20 is preferably provided, if the trailing edge of the horizontal synchronization signal 18 is sufficiently stable, the generator 20 may be dispensed with and the signal 18 may be used directly as an input into the divider means.

Details of the divider means 30 and the leading edge pulse generator 20 are seen in Figure 2. The pulse generator 20 is preferably comprised of two DQ flip-flops 52 and 54, and a NAND gate 56. The fast clock signal is used as a clock signal input into both DQ flip-flops with the D input of flip-flop 52 having the horizontal synchronization as an input thereto, and the Q output of flip-flop 52 connected to the D input of flip-flop 54. The inputs into NAND gate 56 are the Q output of flip-flop 52 and the not Q output of flip-flop 54. With the provided arrangement, whatever is at the D input of flip-flop 52 is gated to its Q output at the leading edge of the fast clock. Thus, if the H_{sync} signal 18 is zero, at the leading edge of fast clock 15, a zero is transferred to the Q output of flip-flop 52. With a zero at the Q output of flip-flop 52, a one appears at the not Q output of flip-flop 54 after a second leading edge of clock 15. With a zero and a one being input to NAND gate 56, NAND gate 56 outputs a one value which does not reset the flip-flops of divider 30.

Upon the horizontal synchronization signal 18 going high, flip-flop 52 outputs a one at the Q output at the leading edge of the fast clock. However, flip-flop 54 remains static for one fast clock cycle. Thus, at the first cycle of fast clock 15 after signal 18 goes high, NAND gate receives two high inputs and outputs a zero to the divider means 30. This zero acts as a reset (RST) of the divider means. At the next positive edge of fast clock 15, flip-flop 54 changes state to produce a zero on the non Q output, resulting in NAND gate 56 again outputting a one value. Hence, it will be appreciated that the horizontal reset signal (RST) lasts one cycle of fast clock 15, and then only when the horizontal sync signal 18 goes from zero to one. These transitions may be seen with reference to

Figure 4.

Turning to the divider 30, it will be appreciated that the function of the divider is to take the fast clock signal 15, divide the same by a desired amount, and generate a desired write clock signal W_c . In the preferred embodiment, the divide by six divider 30 utilizes two JK flip-flops 62 and 64, and a DQ flip-flop 66. Each flip-flop of the divider 30 has a reset port coupled to the output of NAND gate 56. JK flip-flops 62 and 64 have their not K inputs tied to ground; i.e. a zero value, and their clock inputs coupled to the fast clock 15. The Q output of flip-flop 62 is coupled to the J input of flip-flop 64 and the clock input of DQ flip-flop 66. The not Q output of flip-flop 64 is coupled to the J input of flip-flop 62. The not Q output of flip-flop 66 is coupled to the D input thereof, while the Q output of flip-flop 66 is the desired W_c signal.

In operation, and as indicated in the logic chart of Figure 3, when the flip-flops 62, 64 and 66 are reset (R), the Q output of flip-flop 62 is zero, the not Q output of flip-flop 64 is one, the Q output (clock W_c) of flip-flop 66 is zero, and the not Q output of flip-flop 66 is one. At the next fast clock pulse (C1) (when the reset goes high) the one value at the J input to flip-flop 62 (from the not Q output of flip-flop 64) toggles the Q output of flip-flop 62 causing the J input to flip-flop 64 to go a value of one. The not Q output of flip-flop 64 does not change. However, because of the rising pulse at the Q output of flip-flop 62, DQ flip-flop 66 is toggled, with the one value at the D input being transferred to the Q output, and the not Q output and the D input going to zero. Hence, as seen in Figure 4, at the first fast clock pulse (C1) after reset, the output of divider 30 is high (i.e. value one).

At the next fast clock pulse (C2), flip-flops 62 and 64 toggle as their J inputs are high. Hence, the Q output of flip-flop 62 and the J input to flip-flop 64 go low, while the not Q output of flip-flop 64 and the J input to flip-flop 62 stay low. During pulse C2, flip-flop 66 is inactive, as no rising edge pulse is received from the Q output of flip-flop 62.

At cycle C3, the Q output of flip-flop 62 remains low as the J input was low at cycle C2. Because flip-flop 64 has a low J input, but a high Q output, the Q output of flip-flop 64 is forced low, resulting in the not Q output of flip-flop 64 and the J input to flip-flop 62 going high. Again, because no rising edge is seen at the clock input to DQ flip-flop 66, the DQ flip-flop remains static.

At cycle C4, the high value at the J input to flip-flop 62 toggles the Q output of flip-flop 62 and causes the J input to flip-flop 64 to go to a logic one (high). The outputs of flip-flop 64 remain the same. However, because of the rising value at the Q output of flip-flop 62, flip-flop 66 is toggled, with

the zero value at the D input being transferred to the Q output, and the D and not Q values going to one. Hence, at cycle C4, after three fast clock cycles, the output of divider 30 goes low. This output pulse lasting three fast clock cycles is seen in Figure 4.

Those skilled in the art will appreciate (as shown in Figure 3) that the provided circuitry continues to cause the Q output of flip-flop 66 to provide a low output for three fast clock cycles. Then at fast clock C7, the output changes to a value of one again for three clock cycles. Thus, the output of divider 30 is a write clock having a cycle equal to the length of six fast clock cycles, with a high value for three fast clock cycles and a low value for three fast clock cycles. Again, this result is seen graphically in Figure 4. The provided write clock is also pseudo locked to the horizontal synchronization signal input 18 as the horizontal synchronization signal causes the reset signal to toggle within one fast clock cycle. In turn, the reset signal causes the generated write clock to start its cycle. In fact, because the generated write clock goes low for two complete fast clock cycles after the horizontal synchronization signal goes high (starting at the first fast clock leading edge following the horizontal sync signal), it will be appreciated that the generated clock is at most $(1/6)W_c$ out of phase, and at average $(1/12)W_c$ out of phase with the incoming data. It has been found that such a phase difference does not introduce substantially visible artifacts in a standard PIP display; i.e. where the PIP is one-ninth a screen size for standard television signals.

As indicated in Figure 4, another clock at a write of $2W_c$ may also be generated if desired. The $2W_c$ clock may be taken from the Q output of flip-flop 62 and is particularly useful for color PIP applications where it provides timing for a (R-Y)-(Y)-(B-Y)-(Y) or a (B-Y)-(Y)-(R-Y)-(Y) sequence which samples luminance at the W_c rate.

There has been described and illustrated herein a pseudo line locked write clock for PIP applications. While a particular embodiment of the invention has been described, other embodiments would be within the abilities of one skilled in the art. Thus, while a clock input of six times the desired write clock speed and a divide by six means were described, those skilled in the art will appreciate that other clock input speeds and corresponding dividing means could be utilized provided that substantially no visible artifacts are introduced into the resulting PIP display. While a clock input speed is substantially equal to or greater than six times the speed of the desired write clock to be generated has been found to substantially eliminate artifacts in a PIP display of one-ninth a standard screen, it is within possibility that acceptable PIP displays



might be generated even where a pseudo line-line locked write clock generated from fast clocks between six and four and even less than four times the desired write clock speed are utilized. Indeed, those skilled in the art could make such determinations without undue experimentation and without new invention. Further, it will be appreciated that the visibility of artifacts in the PIP display will also be somewhat dependent on the actual size of the PIP display as well as the resolution of the same. All other things being equal, the larger the PIP display on the screen, the easier it will be to view artifacts. Hence, in choosing a fast clock which is to be divided down to the desired write clock speed, the size and resolution of the PIP display as well as the fast clock may all affect the likelihood of visible artifacts appearing. However, again, it is well within the ability of those skilled in the art given the disclosure herein to tailor the fast clock speed to the other circumstances so as to substantially eliminate visible artifacts from the generated PIP display.

While particular circuitry was disclosed for the divider means, it will be appreciated that other circuitry accomplishing the same would be well within the abilities of one skilled in the art. Similarly, those skilled in the art could provide different means for creating an edge (positive or negative) pulse generator, and the leading edge pulse generator described is only one of many circuits that could be utilized to create a reset pulse for the divider means. Further, it should be appreciated that the generated write clock can be utilized for any of many purposes, including but not limited to controlling the A/D conversion sample rate of the incoming PIP data, and controlling data compression of chrominance data. Indeed, the generated write clock is for use with one or both of chrominance and luminance information, in any of many formats, as is required for the particular circumstances. Finally, it will be appreciated that methods for generating a write clock for PIP video information which is pseudo line locked to the incoming PIP information will suggest themselves to those skilled in the art and will be closely connected with the disclosed write clock means.

Claims

1. Apparatus for generating an output clock signal synchronized to a preselected horizontal synchronization signal (HSYNC) of a video information signal to be transferred and having a predetermined output clock frequency (WC) for clocking the transfer of said video information, comprising:

means for generating a clock input signal (15) asynchronous to said preselected horizontal

tal synchronization signal and having a clock input signal frequency at least n times said predetermined output clock frequency, where n is an integer greater than 1;

divider means (30) for dividing said clock input signal by n to provide a divider output signal having said predetermined output clock frequency, and being coupled to receive said preselected horizontal synchronization signal for being reset in response to said preselected horizontal synchronization signal, whereby said divider output signal constitutes said output clock signal.

2. Apparatus according to Claim 1, wherein said video information is picture-in-picture (PIP) information having an associated PIP horizontal synchronization signal; and

wherein said PIP horizontal synchronization signal constitutes said preselected horizontal synchronization signal.

3. Apparatus according to Claim 2, wherein n is equal to or greater than six.

4. Apparatus according to Claim 3, wherein:

said divider means comprises a first JK flip-flop (62), a second JK flip-flop (64), and a first DQ flip-flop (66), wherein a not Q output of said second JK flip-flop is coupled to a J input of said first JK flip-flop, a Q output of said first JK flip-flop is coupled to a J input of said second JK flip-flop, a clock input to said first DQ flip-flop is coupled to said Q output of said first JK flip-flop, a not Q output of said first DQ flip-flop is coupled to a D input of said first DQ flip-flop, a not K input of said first and second JK flip-flops are arranged to be maintained in a low state, and a Q output of said first DQ flip-flop furnishes said output clock signal.

5. Apparatus according to Claim 4, wherein:

said divider means comprises reset inputs to said first and second JK flip-flops and said first DQ flip-flop, said reset inputs being coupled to receive said horizontal synchronization signal.

6. Apparatus according to Claim 5, wherein:

said reset inputs reset said first and second JK flip-flops and said first DQ flip-flop after a trailing edge of said horizontal synchronization signal.

7. Apparatus according to Claim 5, further comprising:

edge pulse generator means for receiving said preselected horizontal synchronization



signal and for providing a reset pulse to said reset inputs after a respective leading edge of said preselected horizontal synchronization signal.

8. Apparatus according to Claim 7, wherein:

said edge pulse generator means comprises second (52) and third (54) DQ flip-flops and a NAND gate (56), wherein a D input to said second DQ flip-flop is coupled to receive said preselected horizontal synchronization signal, a Q output of said second DQ flip-flop is coupled to a D input to said third DQ flip-flop and a first input to said NAND gate, a not Q output of said third DQ flip-flop is coupled to a second input to said NAND gate, clock inputs into said second and third DQ flip-flops are coupled to said clock input signal, and an output of said NAND gate provides said reset pulse to said reset inputs.

9. Apparatus according to Claim 1, further comprising:

edge pulse generator means for receiving said preselected horizontal synchronization signal and for providing a reset pulse for resetting said divider means after a respective leading edge of said preselected horizontal synchronization signal.

10. Apparatus according to Claim 9, wherein:

said edge pulse generator means comprises first (52) and second (54) DQ flip-flops and a NAND gate (56), wherein a D input to said first DQ flip-flop is coupled to receive said preselected horizontal synchronization signal, a Q output of said first DQ flip-flop is coupled to a D input to said second DQ flip-flop and a first input to said NAND gate, a not Q output of said second DQ flip-flop is coupled to a second input to said NAND gate, clock inputs into said first and second DQ flip-flops are coupled to receive said clock input signal, and an output of said NAND gate provides said reset pulse.

11. Apparatus according to Claim 1, wherein said preselected horizontal synchronization signal has a respective trailing edge; and

wherein said divider means is reset in response to said trailing edge of said preselected horizontal synchronization signal.

12. Method for generating an output clock signal synchronized to a preselected horizontal synchronization signal (HSYNC) of a video information signal to be transferred and having a predetermined output clock frequency (WC) for

clocking the transfer of said video information, comprising the steps of:

generating a clock input signal synchronous to said preselected horizontal synchronization signal and having a clock input signal frequency at least n times said predetermined output clock frequency, where n is an integer greater than 1;

dividing said clock input signal by n thereby providing a divider output signal having said predetermined output clock frequency; and

restarting said dividing step in response to each received preselected horizontal synchronization signal, whereby said divider output signal constitutes said output clock signal.

13. A method according to Claim 12 wherein n is at least six.

Patentansprüche

1. Anordnung zum Erzeugen eines Ausgangstaktimpulssignals synchron zu einem vorselektierten Horizontal-Synchronsignal (HSYNC) eines zu übertragenden Video-Informationssignals und mit einer vorbestimmten Ausgangstaktimpulsfrequenz (W_c) zum Takten der Übertragung der genannten Video-Information, wobei diese Anordnung die nachfolgenden Elemente aufweist:

Mittel zum Erzeugen eines Taktimpulseingangssignals (15) asynchron zu dem genannten vorselektierten Horizontal-Synchronsignal und mit einer Taktimpulseingangssignalfrequenz, die mindestens der n -fachen genannten vorbestimmten Ausgangstaktimpulsfrequenz entspricht, wobei n eine ganze Zahl größer als 1 ist;

Teilmittel (30) zum Teilen des genannten Taktimpulseingangssignals durch n zum Schaffen eines Teiler Ausgangssignals mit der genannten vorbestimmten Ausgangstaktimpulsfrequenz, und

wobei diese Mittel gekoppelt sind zum Empfangen des genannten vorselektierten Horizontal-Synchronsignals, damit dies in Antwort auf das genannte vorselektierte Horizontal-Synchronsignal rückgestellt wird, wobei das genannte Teiler Ausgangssignal das genannte Ausgangstaktimpulssignal bildet.

2. Anordnung nach Anspruch 1, wobei die genannte Video-Information Bildim-Bild-Information (PIP) ist mit einem zugeordneten PIP-Horizontal-Synchronsignal; und

wobei das genannte PIP-Horizontal-Synchronsignal das genannte vorselektierte Horizontal-Synchronsignal bildet.



3. Anordnung nach Anspruch 2, wobei n gleich oder größer als sechs ist.

4. Anordnung nach Anspruch 3, wobei:

das genannte Teilmittel eine erste JK-Flip-Flop-Schaltung (62), eine zweite JK-Flip-Flop-Schaltung (64) und eine erste DQ-Flip-Flop-Schaltung (66) aufweist, wobei ein Nicht-Q-Ausgang der genannten zweiten JK-Flip-Flop-Schaltung mit einem J-Eingang der genannten ersten JK-Flip-Flop-Schaltung gekoppelt ist, ein Q-Ausgang der genannten ersten JK-Flip-Flop-Schaltung mit einem J-Eingang der genannten zweiten JK-Flip-Flop-Schaltung gekoppelt ist, wobei ein Taktimpulseingang der ersten DQ-Flip-Flop-Schaltung mit dem genannten Q-Ausgang der genannten ersten JK-Flip-Flop-Schaltung gekoppelt ist, wobei ein Nicht-Q-Ausgang der genannten ersten DQ-Flip-Flop-Schaltung mit einem D-Eingang der genannten ersten DQ-Flip-Flop-Schaltung gekoppelt ist, wobei ein Nicht-K-Eingang der genannten ersten und zweiten JK-Flip-Flop-Schaltung dazu vorgesehen ist, daß er in dem niedrigen Zustand gehalten wird, und wobei ein Q-Ausgang der genannten ersten DQ-Flip-Flop-Schaltung das genannte Ausgangstaktimpulssignal liefert.

5. Anordnung nach Anspruch 4, wobei:

das genannte Teilmittel Rückstelleingänge aufweist für die genannte erste und zweite JK-Flip-Flop-Schaltung und die genannte erste DQ-Flip-Flop-Schaltung, wobei diese Rückstelleingänge zum Empfangen des genannten Horizontal-Synchronsignals gekoppelt sind.

6. Anordnung nach Anspruch 5, wobei:

die genannten Rückstelleingänge die genannte erste und zweite JK-Flip-Flop-Schaltung und die genannte erste DQ-Flip-Flop-Schaltung nach einer Rückflanke des genannten Horizontal-Synchronsignals rückstellt.

7. Anordnung nach Anspruch 5, weiterhin mit:

einem Flankenimpulsgeneratormittel zum Empfangen des vorselektierten Horizontal-Synchronsignals und zum Liefern eines Rückstellimpulses zu den genannten Rückstelleingängen nach einer betreffenden Vorderflanke des genannten vorselektierten Horizontal-Synchronsignals.

8. Anordnung nach Anspruch 7, wobei:

das genannte Flankenimpulsgeneratormittel eine zweite (52) und eine dritte (54) DQ-Flip-Flop-Schaltung und ein NAND-Glied (56) aufweist, wobei ein D-Eingang der genannten

zweiten DQ-Flip-Flop-Schaltung zum Empfangen des genannten vorselektierten Horizontal-Synchronsignals gekoppelt ist, wobei ein Q-Ausgang der genannten DQ-Flip-Flop-Schaltung mit einem D-Eingang der genannten dritten DQ-Flip-Flop-Schaltung und mit einem, ersten Eingang des genannten NAND-Gliedes gekoppelt ist, wobei ein Nicht-Q-Ausgang der genannten dritten DQ-Flip-Flop-Schaltung mit einem zweiten Eingang des genannten NAND-Gliedes gekoppelt ist, wobei die Taktimpulseingänge der genannten zweiten und dritten DQ-Flip-Flop-Schaltung mit dem genannten Taktimpulseingangssignal gekoppelt sind, und wobei ein Ausgang des genannten NAND-Gliedes den genannten Rückstellimpuls zu den genannten Rückstelleingängen liefert.

9. Anordnung nach Anspruch 1, weiterhin mit:

einem Flankenimpulsgeneratormittel zum Empfangen des genannten vorselektierten Horizontal-Synchronsignals und zum Liefern eines Rückstellimpulses zum Rückstellen des genannten Teilmittels nach einer betreffenden Vorderflanke des genannten vorselektierten Horizontal-Synchronsignals.

10. Anordnung nach Anspruch 9, wobei:

das genannte Flankenimpulsgeneratormittel eine erste (52) und eine zweite (54) DQ-Flip-Flop-Schaltung und ein NAND-Glied (56) aufweist, wobei ein D-Eingang der ersten DQ-Flip-Flop-Schaltung zum Empfangen des genannten vorselektierten Horizontal-Synchronsignals gekoppelt ist, wobei ein Q-Ausgang der genannten ersten DQ-Flip-Flop-Schaltung mit einem D-Eingang der genannten zweiten DQ-Flip-Flop-Schaltung und einem ersten Eingang des genannten NAND-Gliedes gekoppelt ist, wobei ein Nicht-Q-Ausgang der genannten zweiten DQ-Flip-Flop-Schaltung mit einem zweiten Eingang des genannten NAND-Gliedes gekoppelt ist, wobei ein Taktimpulseingang der genannten ersten und zweiten DQ-Flip-Flop-Schaltung zum Empfangen des genannten Taktimpulseingangssignals gekoppelt ist und wobei ein Ausgang des genannten NAND-Gliedes den genannten Rückstellimpuls liefert.

11. Anordnung nach Anspruch 1, wobei das genannte vorselektierte Horizontal-Synchronsignal eine betreffende Rückflanke hat; und

wobei das genannte Teilmittel in Antwort auf die genannte Rückflanke des genannten vorselektierten Horizontal-Synchronsignals rückgestellt wird.



12. Verfahren zum Erzeugen eines zu einem vorselektierten Horizontal-Synchronsignal synchronisierten Ausgangstaktimpulssignals (HSYNC) eines zu übertragenden Video-Informationssignals und mit einer vorbestimmten Ausgangs-Taktimpulsfrequenz (W_0) zum Fahren der Übertragung der genannten Video-Information, wobei dieses Verfahren die nachfolgenden Verfahrensschritte aufweist:

das Erzeugen eines Taktimpulseingangssignals synchron zu dem genannten vorselektierten Horizontal-Synchronsignal und mit einer Taktimpulseingangssignalfrequenz, die mindestens der n-fachen vorbestimmten Ausgangstaktimpulsfrequenz entspricht, wobei n eine ganze Zahl größer als 1 ist;

das Teilen des genannten Taktimpulseingangssignals durch n, wodurch ein Teiler-Ausgangssignal mit der genannten vorbestimmten Ausgangstaktimpulsfrequenz geschaffen wird; und

das Neustarten des genannten Teilerschrittes in Antwort auf jedes empfangene vorselektierte Horizontal-Synchronsignal, wobei das genannte Teiler-Ausgangssignal das genannte Ausgangstaktimpulssignal bildet.

13. Verfahren nach Anspruch 12, wobei n mindestens sechs beträgt.

Revendications

1. Appareil prévu pour produire un signal d'horloge de sortie synchronisé sur un signal de synchronisation horizontale présélectionné (HSYNC) d'un signal d'information vidéo à transférer et présentant une fréquence d'horloge de sortie prédéterminée (W_0) pour synchroniser le transfert de ladite information vidéo, comprenant :

des moyens pour produire un signal d'entrée d'horloge (15) asynchrone par rapport au signal de synchronisation horizontale présélectionné et présentant une fréquence de signal d'entrée d'horloge valant au moins n fois la fréquence d'horloge de sortie prédéterminée, où n est un nombre entier supérieur à 1;

des moyens de division (30) pour diviser le signal d'entrée d'horloge par n afin de fournir un signal de sortie de diviseur présentant ladite fréquence d'horloge de sortie prédéterminée, et

étant couplé pour recevoir le signal de synchronisation horizontale présélectionné en vue d'être ramené à l'état initial en réponse au signal de synchronisation horizontale présélectionné, le signal de sortie du diviseur constituant le signal d'horloge de sortie.

2. Appareil suivant la revendication 1, dans lequel l'information vidéo est une information PIP (image incrustée dans image) comportant un signal de synchronisation horizontale de PIP associé, et

dans lequel le signal de synchronisation horizontale de PIP constitue le signal de synchronisation horizontale présélectionné.

3. Appareil suivant la revendication 2, dans lequel n est égal ou supérieur à six.

4. Appareil suivant la revendication 3, dans lequel :

les moyens de division comprennent une première bascule JK (62), une seconde bascule JK (64) et une première bascule DQ (66), une sortie $\bar{Q}$ de la seconde bascule JK étant couplée à une entrée J de la première bascule JK, une sortie Q de la première bascule JK étant couplée à une entrée J de la seconde bascule JK, une entrée d'horloge de la première bascule DQ étant couplée à la sortie Q de la première bascule JK, une sortie $\bar{Q}$ de la première bascule DQ étant couplée à une entrée D de la première bascule DQ, une entrée K de la première et de la seconde bascules JK étant prévues pour être maintenues dans un état bas, et une sortie Q de la première bascule DQ fournissant le signal d'horloge de sortie.

5. Appareil suivant la revendication 4, dans lequel :

les moyens de division comprennent des entrées de remise à l'état initial de la première et de la seconde bascules JK et de la première bascule DQ, les entrées de remise à l'état initial étant couplées pour recevoir le signal de synchronisation horizontale.

6. Appareil suivant la revendication 5, dans lequel :

les entrées de remise à l'état initial ramènent la première et la seconde bascules JK et la première bascule DQ à l'état initial après un flanc arrière du signal de synchronisation horizontale.

7. Appareil suivant la revendication 5, comprenant en outre :

un générateur d'impulsions de flanc destiné à recevoir le signal de synchronisation horizontale présélectionné et à fournir une impulsion de remise à l'état initial aux entrées de remise à l'état initial après un flanc avant du signal de synchronisation horizontale présélectionné.



8. Appareil suivant la revendication 7, dans lequel

le générateur d'impulsions de flanc comprend une deuxième et une troisième bascules DQ (52) et (54) et un circuit-porte NON-ET (56), dans lequel une entrée D de la deuxième bascule DQ est couplée pour recevoir le signal de synchronisation horizontale présélectionné, une sortie Q de la deuxième bascule DQ est couplée à une entrée D de la troisième bascule DQ et à une première entrée du circuit-porte NON-ET, une sortie $\bar{Q}$ de la troisième bascule DQ est couplée à une seconde entrée du circuit-porte NON-ET, des entrées d'horloge dans la deuxième et la troisième bascules DQ sont couplées au signal d'entrée d'horloge et une sortie du circuit-porte NON-ET fournit l'impulsion de remise à l'état initial aux entrées de remise à l'état initial.

9. Appareil suivant la revendication 1, comprenant en outre :

un générateur d'impulsions de flanc destiné à recevoir le signal de synchronisation horizontale présélectionné et à fournir une impulsion de remise à l'état initial destinée à ramener les moyens de division à l'état initial après un flanc avant respectif du signal de synchronisation horizontale présélectionné.

10. Appareil suivant la revendication 9, dans lequel

le générateur d'impulsions de flanc comprend une première et une seconde bascules DQ (52) et (54) et un circuit-porte NON-ET (56), dans lequel une entrée D de la première bascule DQ est couplée pour recevoir le signal de synchronisation horizontale présélectionné, une sortie Q de la première bascule DQ est couplée à une entrée D de la seconde bascule DQ et à une première entrée du circuit-porte NON-ET, une sortie $\bar{Q}$ de la seconde bascule DQ est couplée à une seconde entrée du circuit-porte NON-ET, des entrées d'horloge dans la première et la seconde bascules DQ sont couplées pour recevoir le signal d'entrée d'horloge et une sortie du circuit-porte NON-ET fournit l'impulsion de remise à l'état initial.

11. Appareil suivant la revendication 1, dans lequel le signal de synchronisation horizontale présélectionné comporte un flanc arrière respectif, et dans lequel les moyens de division sont ramenés à l'état initial en réponse au flanc arrière du signal de synchronisation horizontale présélectionné.

12. Procédé prévu pour produire un signal d'horloge de sortie synchronisé sur un signal de synchronisation horizontale présélectionné (HSYNC) d'un signal d'information vidéo à transférer et présentant une fréquence d'horloge de sortie (WC) prédéterminée pour synchroniser le transfert de ladite information vidéo, comprenant les étapes:

produire un signal d'entrée d'horloge synchrone à l'égard du signal de synchronisation horizontale présélectionné et présentant une fréquence de signal d'entrée d'horloge valant au moins n fois la fréquence d'horloge de sortie prédéterminée, où n est un nombre entier supérieur à 1;

diviser le signal d'entrée d'horloge par n afin de fournir un signal de sortie de diviseur présentant la fréquence d'horloge de sortie prédéterminée, et

faire redémarrer l'étape de division en réponse à chaque signal de synchronisation horizontale présélectionné reçu, de sorte que le signal de sortie de diviseur constitue le signal d'horloge de sortie.

13. Procédé suivant la revendication 12, dans lequel n est au moins égal à six.