

POWER CIRCUIT FOR A CAMERA

5 This invention relates to power circuits for
cameras.

 Over the past few years, electronic circuits have
been used more and more in cameras, and many operations,
which had previously depended on the experience and
10 perception of human operators, are now automatically
performed by electronic circuits which, for example,
control exposure time, control automatically camera-to-
shutter distance, etc. Microcomputers are often used as
the electronic circuits in view of the degree of freedom
15 of control and reduction in development time.

 Although a battery is generally used as a power
source in a camera, the voltage of the battery in a
camera which has a strobo (flash) unit or an auto-
loading function for automatically winding on films, can
20 temporarily vary. In such a camera, the source voltage
to a microcomputer will also vary, resulting in
malfunctioning of the microcomputer. It is therefore
necessary to use a step-up power source as a source of
voltage for such a microcomputer.

25 However, there is a danger that, if the voltage of
the step-up power source is not sufficiently high when

the microcomputer starts operation even after the voltage has been stepped up, or if the voltage of the step-up power source is not completely stepped up and falls for some reason during operation of the microcomputer, the operation of the microcomputer becomes unstable, resulting in malfunctioning.

Figure 2 is a block diagram of a conventional power source for a camera. Heretofore, a battery voltage is directly applied to a microcomputer, with no step-up circuit being provided. Therefore, a controller X which can operate at lower voltages is used to supply power to a driver MD which drives a strobo circuit ST and a motor for winding on and rewinding films, and a switch S for supplying power to a microcomputer V, are controlled so that, if the battery voltage drops, the supply of the battery voltage to the microcomputer V is turned off to ensure that the microcomputer cannot be operated. There is, therefore, a disadvantage in that the usable range of battery voltage is extremely limited, and thus vital shutter release time can be lost. In Figure 2, reference letter U represents a shutter, reference letter W an A/F circuit and reference letter T a photometric circuit.

Although the above described problem can be solved by providing a multifunctional controller X, it is

disadvantageous to provide those functions in the microcomputer itself in view of reduction in development time and the degree of freedom to change. To overcome the problem, it was, therefore, thought that the source voltage of the microcomputer could be maintained at a value above a limiting operation voltage, i.e. the minimum operation voltage, even if the battery voltage falls, by using a step-up circuit. However, the functions of a step-up circuit are limited, and there is a danger than when, for example, the capacity of the battery is reduced in the last stages of its life or if a film is being wound on or rewound immediately after a strobo has been charged, the step-up source voltage of the microcomputer will become lower and the minimum operation voltage and the microcomputer will misoperate.

The present invention seeks to provide a power circuit for a camera using a microcomputer, malfunction of which is prevented by resetting it when the voltage of a step-up power source is lower than a minimum operation voltage of the microcomputer or becomes lower than the minimum operation voltage of the microcomputer during operation thereof.

According to the present invention, there is provided a power circuit for a camera comprising: a power activation means containing switch means operable for initiating a camera function; a step-up means for starting to step up the voltage of a battery under the control of said power activation means; a CPU arranged to be driven by an output voltage of said step-up means so as to control the operation of said camera and which has a reset terminal for stopping said operation; and a voltage detecting means for detecting the output voltage of said step-up means and for generating a detection signal when said output voltage is lower than a predetermined set voltage, said predetermined set voltage corresponding to a limiting operation voltage of said CPU and said detection signal being connected to said reset terminal so as to stop the operation of said CPU when the output of said step-up means is lower than said limiting operation voltage of said CPU, said voltage detecting means being arranged to co-operate with the power activation means so as to begin detecting when the switch means are operated and so as to continue detecting until the switch means are released or the camera function is completed whichever is the later.

The power circuit may include oscillator means the output of which is provided to the step-up means.

Preferably said voltage detecting means includes a constant current source and resistor means for

determining said predetermined set voltage and a comparator for generating said detection signal when said output voltage of the step-up means is lower than
5 said predetermined set voltage.

In one embodiment the power circuit includes an inverter, which together with the voltage detecting means, constitutes reset means connected to the reset terminal of the CPU to stop operation thereof.

10 The step-up means may include a coil.

The invention is illustrated, merely by way of example, in the accompanying drawings, in which:-

Figure 1 is a block diagram of a power circuit according to the present invention for a camera;

15 Figure 2 is a block diagram of a conventional power circuit for a camera;

Figure 3 is a circuit diagram of a V_{DD} detecting regulator of the power circuit of Figure 1; and

20 Figure 4 is a circuit diagram of a V_{DD} detecting resetter of the power circuit of Figure 1.

Figure 1 is a circuit diagram of a power circuit according to the present invention for a camera. A portion A surrounded by a broken line in Figure 1 denotes a power activation unit which includes a power
25 activation switch group 1, for example, comprising a shutter release switch and a film-rewinding switch. A

CPU 2 determines which switch has activated the power source and performs a given function. For example, if the power source is turned on by the shutter release switch, an exposure is performed and then the film is automatically wound on.

If any one of the switches of the power activation switch group 1 turns on the power source, the output of an OR gate 8, i.e., an output a of the power activation unit A, goes high and a start signal is produced. The power activation cause that produced the output a is also fed to the CPU 2. A PH signal connected to one input terminal of the OR gate 8 is set when a program in the CPU 2 is started, so that the output a of the power activation unit A is maintained high even if the power activation switch group 1 is turned off during the operation of the CPU 2.

A portion B surrounded by a broken line in Figure 1 denotes a standby oscillator in which, when the output a of the power activation unit A goes high, an N-channel FET 6 is turned off so that oscillation is started and is output to the CPU 2. A step-up clock b is also output to a step-up circuit C through a frequency division circuit 11. When the output a of the power activation unit A goes low, the N-channel FET 6 is turned on so that oscillation is stopped and the current

consumed by the standby oscillator B becomes zero.

In a standby state wherein the output a of the power activation unit A is low, all of transistors Tr1, Tr2, Tr3 of the step-up circuit C are turned off. Thus, a step-up power source V_{DD} is made to be V_E (V_E = battery voltage) by a resistor R1, a step-up coil L1, and a diode D1. Since, at the same time, transistors Tr4, Tr5 are both turned off, when $V_{DD} = V_E$, the current consumed by the step-up circuit C becomes substantially zero. The resistor R1 is a resistor for increasing the step-up power source V_{DD} to the battery voltage V_E .

When the step-up clock b is input to the transistor Tr3, it is amplified by the transistors Tr2, Tr1 so as to switch the step-up coil L1. When the transistor Tr1 is turned on, a current passes through the step-up coil L1, and, when it is turned off, the energy stored in the step-up coil L1 is stored in a capacitor C1 through the diode D1. If the voltage V_{DD} of the capacitor C1 is above a given value, a transistor Tr7 is turned on and the transistor Tr3 is turned off so that the input of the step-up clock b is blocked. If the voltage V_{DD} falls below the given value, the transistor Tr7 is turned off so that the step-up clock is input. Therefore, the voltage V_{DD} is stepped up to a substantially constant voltage.

When the output a of the power activation circuit A goes high, the transistor Tr5, Tr4 are turned on so that the step-up power source V_{DD} is applied to a V_{DD} detecting regulator 4 and the step-up clock is input to the transistor Tr3 to start the stepping up. The V_{DD} detecting regulator 4 controls the step-up clock b input to the base of the transistor Tr3 so as to stabilise the step-up power source V_{DD} (the transistor Tr7 is turned on or off by the voltage V_{DD}).

When the output a of the power activation circuit A goes low, the stepping up is immediately stopped so that the voltage of the step-up power source V_{DD} gradually becomes closer to the battery voltage V_E .

A portion D surrounded by a broken line in Figure 1 denotes a reset circuit for controlling the resetting of the CPU 2. A V_{DD} detecting resetter 5 turns off the transistor Tr6 when the voltage of the step-up power source V_{DD} becomes higher than a voltage V1, and turns on the transistor Tr6 when the step-up power source V_{DD} becomes lower than a voltage V2. The voltages V1, V2 are each set at a value slightly higher than the minimum operation voltage of the CPU 2.

When the output a of the power activation unit A is low, the transistor Tr4 is turned off so that the step-up power source V_{DD} is not applied to the V_{DD}

detecting resetter 5. In addition, the output of an inverter comprising FETs 9,10 goes low so that the CPU 2 is reset. At this point, the current consumed by the
 5 reset circuit D becomes substantially zero. When the output a of the power activation unit A goes high, the output of the inverter also goes high, and the voltage of the step-up power source V_{DD} is immediately applied to the V_{DD} detecting resetter 5. At this point, if V_{DD}
 10 $< V_1$, the transistor Tr6 is turned on so that the CPU 2 is kept in the reset state. If $V_E \geq V_1$ i.e., if $V_{DD} \geq V_1$, the reset state is immediately removed. Therefore if the voltage of the step-up power source V_{DD} is lowered for some reason and becomes less than the
 15 voltage V_2 during the operation of the CPU 2, the transistor Tr6 is turned on so that the CPU is reset, thus preventing runaway. Hysteresis is imparted to the V_{DD} detecting resetter 5 since $V_1 > V_2$.

A portion E surrounded by a broken line in Figure
 20 1 denotes a strobo step-up inhibiting signal output unit in which, when the output a of the power activation unit A goes high, transistors Tr8, Tr9 are turned on so as to inhibit strobo step-up and, when the output a goes low, the transistors Tr8, Tr9 turn off so as to release the
 25 inhibition of the strobo set-up.

The voltage of the step-up power source V_{DD} is

always applied to the CPU 2. When the reset is released, the program in the CPU 2 is started, the PH signal is reset so that the output a of the power
5 activation unit A is kept high, and the CPU 2 checks which of the switches of the power activation switch group 1 activated the power source and performs a given operation.

Even if the power activation switch group 1 is
10 turned off while the CPU 2 is operating, the operation can continue because the PH signal is set. When the given operation is completed, the PH signal is reset and, if the power activation switch group 1 has been turned off at this point, the CPU is reset. If the
15 power activation switch group 1 is turned on, the CPU is reset when the power activation switch group 1 is turned off.

When on standby, in which all the switches of the power activation switch group 1 are turned off and no
20 operation is being performed, the capacitor C1 is charged with the battery voltage V_E by the step-up coil L1, the diode D1, and the resistor R1, so the output a of the power activation unit A goes low and the N-channel FET 6 is turned on, so that the standby
25 oscillator B is not operated. In addition, the transistors Tr1, Tr2, Tr3, Tr4, Tr8 are turned off and

the output of the inverter comprising FETs 9,10 in the reset circuit D goes low, so that the current consumed from the battery voltage V_E becomes substantially zero.

5 This means that, during standby, the battery voltage is applied to the CPU 2.

If one of the switches of the power activation switch group 1 is turned on when the device is on standby, the output a of the power activation unit A
10 goes high and the standby oscillator B starts to oscillate. At the same time, the step-up clock B is applied to the base of the transistor Tr5 so as to start the stepping up, and the transistors Tr2, Tr6 are turned on so as to output a strobo step-up inhibiting signal.
15 The step-up power source V_{DD} detection is applied to the V_{DD} detecting resetter 5 and the V_{DD} detecting regulator 4.

In this state, if the battery voltage is higher than the voltage V1, the reset is removed by the output
20 from the V_{DD} detecting resetter so that the program is started. Alternatively, if the battery voltage is lower than the voltage V1, the reset state is held by the output from the V_{DD} detecting resetter 5.
Thereafter, when the voltage of the step-up power source
25 V_{DD} becomes higher than the voltage V1, the reset is removed so that the program is started. When the

program is started, the CPU 2 checks which power activation switch started the power source, and the PH signal from the CPU 2 is set so that the operation
5 corresponding to the selected switch of the power activation switch group 1 is started. While the CPU 2 is operating, its operation is continued by the PH signal even if the power activation switch group 1 is turned off.

10 When the given operation has been completed, the PH signal is reset, and, if the power activation switch group 1 is not on at this point, the output a of the power activation unit goes low and the CPU 2 is immediately reset so that it is on standby. If the
15 power activation switch group 1 is on, the CPU is reset when the power activation switch group is turned off, so that it is on standby. While it is on standby, if the battery voltage drops during strobo step-up, immediately after strobo step-up, or immediately after the film has
20 been wound on, and if the power activation switch group 1 has been turned on, the reset state is maintained until the voltage of the step-up power source V_{DD} becomes higher than the voltage V_1 .

If the voltage of the step-up power source V_{DD}
25 falls below the voltage V_2 for some reason during operation (for example, the fall of battery voltage or

instantaneous termination of the battery voltage) the CPU 2 is immediately reset by the signal of the V_{DD} detecting resetter 5 so as to prevent runaway. In addition, the transistor Tr5 is turned on and the transistors Tr8, Tr9 are thus turned on, so that step-up of a strobo circuit 3 is inhibited during operation.

After the operation of the CPU 2 has been completed, the CPU 2 is reset. Therefore, if the power activation switch group 1 is turned off when the PH signal is reset, the output a of the power activation unit A goes low, so the transistor Tr5 is turned on to ensure that the step-up is stopped and the CPU is reset. The oscillation of the standby oscillator B is also stopped so that the power circuit returns to the standby state. If the operation is completed in the state wherein the power activation switch group 1 is on, the power circuit returns to the standby state when the power activation switch group 1 is turned off.

The V_{DD} detecting resetter 5 comprises a known comparator 15, a unit 14 for generating a constant current and a breeder resistor for detecting the voltage V_{DD} , as shown in Figure 4. The V_{DD} detecting regulator is constructed in the same manner as the detecting resetter 5, as shown in Figure 3, and comprises a known comparator 13, a unit 12 for generating a constant

current and a breeder resistor. In the embodiment of the present invention described above, each of the units A to E are employed independently of the CPU, but any
5 may be formed on the same chip as the CPU.

As described above, the present invention has the effect that it can prevent runaway of a microcomputer, which is the most difficult phenomenon to prevent in an instrument using a microcomputer, and also brings about
10 no undesirable malfunctioning and no increase in the current consumed while the device is on standby, and can realise control with some degree of freedom.

15

20

25

C L A I M S

1. A power circuit for a camera comprising: a power
activation means containing switch means operable for
5 initiating a camera function; a step-up means for
starting to step up the voltage of a battery under the
control of said power activation means; a CPU arranged
to be driven by an output voltage of said step-up means
so as to control the operation of said camera and which
10 has a reset terminal for stopping said operation; and a
voltage detecting means for detecting the output voltage
of said step-up means and for generating a detection
signal when said output voltage is lower than a
predetermined set voltage, said predetermined set
15 voltage corresponding to a limiting operation voltage of
said CPU and said detection signal being connected to
said reset terminal so as to stop the operation of said
CPU when the output of said step-up means is lower than
said limiting operation voltage of said CPU, said
20 voltage detecting means being arranged to co-operate
with the power activation means so as to begin detecting
when the switch means are operated and so as to continue
detecting until the switch means are released or the
camera function is completed whichever is the later.

25 2. A power circuit as claimed in claim 1 including
oscillator means the output of which is provided to the
step-up means.

3. A power circuit as claimed in claim 1 or 2 in
which said voltage detecting means includes a constant
30 current source and resistor means for determining said
predetermined set voltage and a comparator for
generating said detection signal when said output



voltage of the step-up means is lower than said predetermined set voltage.

4. A power circuit as claimed in any preceding claim including an inverter, which together with the voltage detecting means, constitutes reset means connected to the reset terminal of the CPU to stop operation thereof.

5. A power circuit as claimed in any preceding claim in which the step-up means includes a coil.

6. A power circuit for a camera substantially as herein described with reference to and as shown in Figures 1, 3 and 4 of the accompanying drawings.
