



\*166166\*

## SPECIFICATION

## TITLE OF THE INVENTION

SEMICONDUCTOR INTEGRATED CIRCUIT DEVICE AND  
5 METHOD FOR MANUFACTURING THE SAME

## BACKGROUND OF THE INVENTION

The present invention relates to a semiconductor  
integrated circuit device and a technique for  
10 manufacturing the same and, more particularly, to a  
technique which is effective when applied to a  
semiconductor integrated circuit device having a  
memory cell by making a capacitor insulating film of a  
capacitive element (capacitor), of a highly dielectric  
15 material.

In a large capacity DRAM (Dynamic Random Access  
Memory) of recent years, in order to compensate the  
reduction in the accumulated charge of a capacitive  
element, resulting from the miniaturization of a  
20 memory cell, there has been adopted a stacked  
capacitor structure in which the capacitive element is  
arranged over a memory cell selecting MISFET.  
Moreover, the surface area of the capacitive element  
is enlarged by forming its lower electrode (storage  
25 electrode) into a fin shape or a cylindrical shape,



\*G00002\*

and the capacitor insulating film is made of a material having a high dielectric constant.

Especially, a tantalum oxide ( $\text{Ta}_2\text{O}_5$ ) of one of highly dielectric materials has a dielectric constant as high  
5 as 20 to 25 and has a high matching with the DRAM process of the prior art, so that the application of the DRAM to the capacitive element is being advanced.

When the capacitor insulating film of the capacitive element is made of tantalum oxide, a  
10 material for preventing the deterioration of the film quality of tantalum oxide has to be selected as the material of the upper electrode (or plate electrode) to be formed over the capacitor insulating film. This upper electrode material may be suitably exemplified  
15 by a refractory metal such as W (tungsten), Pt (platinum) or Mo (molybdenum) or its nitride such as TiN (titanium nitride).

According to "Jpn. J. Appl. Phys. Vol. 33 (1994) Pt. 1, No. 3A" having investigated the influences of  
20 the leakage current upon the tantalum oxide film before and after the annealing step of the electrode material, it has been reported, based on the experimental results the electric characteristics of the tantalum oxide film are determined by the work  
25 function of the electrode material and the stability

of the interface between the upper electrode and the tantalum oxide, that the most appropriate material is TiN for the annealing at a low temperature (about 400°C) and Mo or MoN (molybdenum nitride) for the  
5 annealing at a high temperature (about 800°C).

Since the lower electrode of the capacitive element of the DRAM has a complicated surface shape, as described above, the CVD (Chemical Vapor Deposition) method having an excellent step coverage  
10 has to be used rather than the sputtering method when a tantalum oxide film is deposited over the lower electrode. However, the tantalum oxide film deposited by the CVD method has to be annealed, after formed, at a temperature as high as about 700 to 800°C because a  
15 desired dielectric constant cannot be achieved as it is. With this annealing, however, an oxide film is formed at the interface with the lower electrode material (the polycrystalline silicon film) of the substrate to lower the effective dielectric constant of the  
20 capacitor insulating film. Another problem is that the oxygen in the tantalum oxide film becomes scarce to lower the breakdown voltage of the film thereby to increase the leakage current.

Japanese Patent Laid-Open No. 3548/1986 has  
25 disclosed a technique for correcting the defect due to

the oxygen vacancy in the tantalum oxide film deposited over a semiconductor substrate by the CVD method, thereby to improve the insulating breakdown voltage of the film by annealing the surface of the film in the atmosphere of dry oxygen.

In "International Conference on Solidstate Devices and Materials 1992" (pp. 521 to 523) has disclosed a technique for preventing an oxide film from being formed on the surface of a polycrystalline silicon film constituting a lower electrode of a capacitive element, when a tantalum oxide film is to be deposited, by annealing the polycrystalline silicon film in the atmosphere of  $\text{NH}_3$  (ammonia) to form a nitride film on the surface of the polycrystalline silicon film.

In the DRAM disclosed in Japanese Patent Laid-Open No. 66300/1995, the capacitor insulating film of the capacitive element is made of one of the tantalum oxide, strontium titanate ( $\text{SrTiO}_3$ ) or barium titanate deposited by the CVD method, and the upper electrode is made of W, Pt or TiN deposited by the CVD method or the sputtering method. Moreover, the lower electrode is made of such a material as zinc oxide ( $\text{ZnO}$ ) or tin oxide ( $\text{SnO}_2$ ) exhibiting a high resistance to oxidation, so that any oxidized film is prevented from being

formed at the interface with the lower electrode at the time of annealing the capacitor insulating film.

In the DRAM disclosed in Japanese Patent Laid-Open No. 66369/1995, the capacitor insulating film of  
5 a capacitive element is made of tantalum oxide deposited by the CVD method. By annealing the formed film at a lower temperature (lower than about 600°C) than that for crystallization, thereby to hold the film in an amorphous structure, moreover, the  
10 occurrence of the grain boundary, the crack or the micro defect which might establish paths for the leakage current is suppressed to improve the leakage current characteristics.

In the DRAM disclosed in Japanese Patent Laid-Open No. 222469/1989, the capacitor insulating film of  
15 a capacitive element is made of tantalum oxide or hafnium oxide ( $\text{HfO}_2$ ) deposited by the CVD method, and a barrier film of TiN is formed between the tantalum oxide (or hafnium oxide) and the electrodes (the upper  
20 electrode and the lower electrode) of polycrystalline silicon thereby to prevent the reaction between the silicon and the tantalum oxide.

In the DRAM disclosed in Japanese Patent Laid-Open No. 232344/1994, the capacitor insulating film of  
25 a capacitive element is made of tantalum oxide or

hafnium oxide deposited by the CVD method, and the upper electrode is made of TiN. By forming a nonmetal buffering film of polycrystalline silicon over the TiN, the capacitive element is prevented from  
5 deteriorating when a BPSG (Boron-doped Phospho Silicate Glass) film deposited over the capacitive element is subjected to hot reflow (at about 850°C for 30 minutes).

#### 10 SUMMARY OF THE INVENTION

We deposited a conductive film of polycrystalline silicon over a semiconductor substrate and then a tantalum oxide film over them and deposited a TiN film over the tantalum oxide film by the CVD method using a  
15 titanium containing source gas such as  $\text{TiCl}_4$  (titanium tetrachloride) TDMAT (Tetraxy Di-Methyl Amino Titanium) or TDEAT (Tetraxy Di-Ethyl Amino Titanium) and a nitrogen-containing reducing gas such as  $\text{NH}_3$  or MMH (Mono-Methyl Hydrazine). Then, these films were  
20 patterned to form a capacitive element and the breakdown voltage of the capacitor insulating film (the tantalum oxide film) was examined and a phenomenon that the breakdown voltage was deteriorated and the leakage current increased was observed.

25 The cause of this phenomenon has not been

sufficiently clarified yet, but we consider that the cause is that if the surface of the tantalum oxide film is hot and contacts with the reducing gas, the oxygen (O) atoms in the film partially react with the  
5 reducing gas and are released, the dangling bonds of Ta or O increase in the film.

An object of the present invention is to provide a technique for preventing the drawback that the breakdown voltage of a capacitor insulating film made  
10 of a highly dielectric material such as tantalum oxide is deteriorated when an upper electrode material is deposited over the capacitor insulating film by the CVD method using a reactive gas containing a reducing gas.

15 The foregoing and other objects and novel features of the present invention will become apparent from the description of the present invention and the accompanying drawings.

A representative one of the inventions disclosed  
20 herein will be briefly summarized in the following.

According to the present invention, there is provided a semiconductor integrated circuit device comprising a capacitive element including: a lower electrode; a capacitor insulating film made of one or  
25 more films including a highly dielectric film formed

over the lower electrode; and an upper electrode made of one or more films including a titanium nitride film formed over the capacitor insulating film, wherein the upper electrode of the capacitive element is formed  
5 over the highly dielectric film through a passivation film formed by a low temperature CVD method under the condition that no reducing gas is contained.

In a semiconductor integrated circuit device of the present invention, the capacitor insulating film  
10 includes a tantalum oxide film.

In a semiconductor integrated circuit device of the present invention, the capacitive element is arranged over a memory cell selecting MISFET constituting a memory cell of a DRAM.

15 According to the present invention, there is provided a method for manufacturing a semiconductor integrated circuit device, comprising:

- (a) the step of forming a first conductor film constituting a lower electrode of a capacitive  
20 element, over the principal face of a semiconductor substrate;
- (b) the step of forming a capacitor insulating film made of one or more films including a highly dielectric film, over the first conductive film;
- 25 (c) the step of forming a passivation film over the

capacitor insulating film by a low temperature CVD method under the condition that no reducing gas is contained; and

(d) the step of forming a second conductive film made  
5 of one or more films including a titanium nitride film forming an upper electrode of the capacitive element, over the passivation film.

In a method for manufacturing a semiconductor integrated circuit device of the present invention,  
10 the capacitor insulating film includes a tantalum oxide film.

In a method for manufacturing a semiconductor integrated circuit device of the present invention, the passivation film includes a amorphous titanium  
15 film or a polycrystalline titanium film.

In a method for manufacturing a semiconductor integrated circuit device of the present invention, the capacitive element is arranged over a memory cell selecting MISFET constituting a memory cell of a DRAM.

20 A method for manufacturing a semiconductor integrated circuit device of the present invention further comprises the step of patterning at least a portion of the lower electrode of the capacitive element into a fin shape or a cylindrical shape.

25 According to the present invention, there is

provided a method for manufacturing a semiconductor integrated circuit device, comprising:

- (a) the step of forming a MISFET over the principal face of a semiconductor substrate;
- 5 (b) the step of forming a first conductive film made of one or more films, over the MISFET;
- (c) the step of forming a lower electrode of a capacitive element by patterning at least a portion of the first conductive film into a fin shape or a  
10 cylindrical shape;
- (d) the step of forming a capacitor insulating film made of one or more films including a highly dielectric film, over the lower electrode;
- (e) the step of forming a passivation film over the  
15 capacitor insulating film by a low temperature CVD method under the condition that a titanium-containing source gas is contained but no nitrogen containing reducing gas is contained;
- (f) the step of forming a second conductive film made  
20 of one or more films including a titanium nitride film, over the passivation film by a low temperature CVD method under the condition that a titanium-containing source gas and a nitrogen-containing reducing gas are contained; and
- 25 (g) the step of forming an upper electrode of the

capacitive element by patterning the second conductive film, the passivation film and the capacitor insulating film.

In a method for manufacturing a semiconductor integrated circuit device of the present invention, the passivation film and the second conductive film are continuously formed by introducing the titanium-containing source gas and then the nitrogen-containing reducing gas into the chamber of a CVD apparatus.

10 In a method for manufacturing a semiconductor integrated circuit device of the present invention, the capacitor insulating film includes a tantalum oxide film.

In a method for manufacturing a semiconductor integrated circuit device of the present invention, the passivation film includes an amorphous titanium film or a polycrystalline titanium film.

In a method for manufacturing a semiconductor integrated circuit device of the present invention, the titanium-containing source gas contains tetrachloride titanium, tetraoxydimethylamino titanium or tetraoxydimethylamino titanium, or their mixed gas.

In a method for manufacturing a semiconductor integrated circuit device of the present invention, the nitrogen containing reducing gas contains ammonia

or monomethyl hydrazine, or their mixed gas.

#### BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a sectional diagram of an essential  
5 portion of a semiconductor substrate, showing a method  
for manufacturing a DRAM of one embodiment according  
to the present invention;

Fig. 2 is a sectional diagram of the essential  
portion of the semiconductor substrate, showing the  
10 method for manufacturing the DRAM of the embodiment  
according to the present invention;

Fig. 3 is a sectional diagram of the essential  
portion of the semiconductor substrate, showing the  
method for manufacturing the DRAM of the embodiment  
15 according to the present invention;

Fig. 4 is a sectional diagram of the essential  
portion of the semiconductor substrate, showing the  
method for manufacturing the DRAM of the embodiment  
according to the present invention;

20 Fig. 5 is a sectional diagram of the essential  
portion of the semiconductor substrate, showing the  
method for manufacturing the DRAM of the embodiment  
according to the present invention;

Fig. 6 is a sectional diagram of the essential  
25 portion of the semiconductor substrate, showing the

method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 7 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment  
5 according to the present invention;

Fig. 8 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment  
10 according to the present invention;

Fig. 9 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

15 Fig. 10 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 11 is a sectional diagram of the essential  
20 portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 12 is a sectional diagram of the essential portion of the semiconductor substrate, showing the  
25 method for manufacturing the DRAM of the embodiment

according to the present invention;

Fig. 13 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment  
5 according to the present invention;

Fig. 14 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

10 Fig. 15 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 16 is a sectional diagram of the essential  
15 portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 17 is a sectional diagram of the essential portion of the semiconductor substrate, showing the  
20 method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 18 is a construction diagram of the essential portion of a CVD apparatus used for manufacturing the DRAM of the embodiment according to  
25 the present invention;

Fig. 19 is a block diagram showing a DRAM of another embodiment according to the present invention;

Fig. 20 is a circuit diagram of a memory array and a sense amplifier of the DRAM of the embodiment  
5 according to the present invention;

Fig. 21 is a sectional diagram of an essential portion of a semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

10 Fig. 22 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 23 is a sectional diagram of the essential  
15 portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 24 is a sectional diagram of the essential portion of the semiconductor substrate, showing the  
20 method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 25 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment  
25 according to the present invention;

Fig. 26 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

5        Fig. 27 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

10       Fig. 28 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

15       Fig. 29 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

20       Fig. 30 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 31 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

25       Fig. 32 is a sectional diagram of the essential

portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 33 is a sectional diagram of the essential  
5 portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 34 is a sectional diagram of the essential  
10 portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 35 is a graph illustrating the step of forming a TiN film for an upper electrode;

Fig. 36 is a sectional diagram of an essential  
15 portion of a semiconductor substrate, showing a method for manufacturing a DRAM of another embodiment according to the present invention;

Fig. 37 is a sectional diagram of the essential  
20 portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 38 is a diagram showing formulas expressing the reactions between titanium-containing source gases and nitrogen containing reducing gases;

25 Fig. 39 is a graph illustrating the step of

forming a TiN film for an upper electrode;

Fig. 40 is a graph illustrating the step of forming a TiN film for an upper electrode;

Fig. 41 is a graph illustrating the relations  
5 between the temperatures at which the passivation film and the TiN film are formed and the field strength of a tantalum oxide film;

Fig. 42 is a graph illustrating the relations between the temperatures at which the passivation film  
10 and the TiN film are formed and the field strength of a tantalum oxide film;

Fig. 43 is a graph illustrating the relations between the temperatures at which the passivation film and the TiN film are formed and the concentration of  
15 chloride introduced into the films;

Fig. 44 is a sectional diagram of an essential portion of a semiconductor substrate, showing a method for manufacturing a DRAM of another embodiment according to the present invention;

20 Fig. 45 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention;

Fig. 46 is a sectional diagram of the essential  
25 portion of the semiconductor substrate, showing the

method for manufacturing the DRAM of the embodiment according to the present invention; and

Fig. 47 is a sectional diagram of the essential portion of the semiconductor substrate, showing the method for manufacturing the DRAM of the embodiment according to the present invention.

#### DESCRIPTION OF THE PREFERRED EMBODIMENTS

The present invention will be described in detail in the following in connection with its embodiments with reference to the accompanying drawings. Incidentally, throughout all the drawings for explaining the embodiments, parts and members having identical functions will be designated by common reference numerals, and their repeated description will be omitted.

##### (Embodiment 1)

The present embodiment is applied to a DRAM having memory cells of a capacitor-over-bit line (COB) structure in which bit lines are arranged over memory cell selecting MISFETs and data storing capacitive elements are arranged over the bit lines.

In order to form such a memory cell, first of all, the principal face of a semiconductor substrate made of p-type monocrystalline silicon is doped with

ions of a p-type impurity (boron) to form a p-type well 2, as shown in Fig. 1. After this, element isolating field oxide film 3 and gate oxide film 4 are formed over the surface of the p-type well 2 by a well-known LOCOS method. Next, the p-type well 2, including the lower portion of the field oxide film 3, is doped with ions of a p-type impurity (boron) to form an element isolating p-type channel stopper layer 5.

Next, gate electrodes 6 (and word lines WL to be formed integrally with the gate electrode 6) of the memory cell selecting MISFET are formed over the p-type well 2, as shown in Fig. 2. These gate electrodes 6 act as the word lines WL of the memory cell. The gate electrodes 6 are formed by depositing a polycrystalline silicon film (a polycide film comprising a polycrystalline silicon film and a refractory metal silicide film) and a silicon oxide film 7 over the p-type well 2 by a CVD method, and by subsequently patterning those films by the etching method using a photoresist as the mask.

Next, the p-type well 2 is doped with an n-type impurity (phosphor) to form n-type semiconductor regions 8 (the source region and the drain region) of a memory cell selecting MISFET, as shown in Fig. 3.

Subsequently, side wall spacers 9 on the side walls of the gate electrodes 6 (the word lines WL), as shown in Fig. 4, and a silicon oxide film 10 is then deposited by the CVD method. The side wall spacers 9 are formed  
5 by patterning the silicon oxide film, deposited by the CVD method, by the reactive ion etching method.

Next, the silicon oxide film 10 and the gate oxide film 4, located over one of the source the drain regions (the n-type semiconductor region 8) of the  
10 memory cell selecting MISFET, are opened to form connection holes 11, as shown in Fig. 5. After this, an n-type polycrystalline silicon film 12 is deposited over the silicon oxide film 10 by the CVD method and is then patterned, as shown in Fig. 6.

15 Next, a BPSG film 13, deposited by the CVD method, is subjected to reflow thereby to flatten its surface, as shown in Fig. 7. After this, the BPSG film 13, the silicon oxide film 10 and the gate oxide film 4, located over the other of the source and drain  
20 regions (the n-type semiconductor region 8) of the memory cell selecting MISFET, are opened to form a connection hole 14.

Next, the n-type polycrystalline silicon film, deposited over the BPSG film 13 by the CVD method, is  
25 patterned to form a bit line BL connected with the

n-type semiconductor region 8 through the connection hole 14, as shown in Fig. 8. The bit line BL may be made of a multilayered film of a TiN film and a W film deposited by the sputtering method.

5       Next, a silicon oxide film 15, a silicon nitride film 16 and a silicon oxide film 17 are sequentially deposited over the BPSG film 13 by the CVD method, as shown in Fig. 9. After this, the silicon oxide film 17, the silicon nitride film 16 and the silicon oxide  
10 film 15, located over the n-type semiconductor region 8, are opened to form connection holes 18 reaching the polycrystalline silicon film 12, as shown in Fig. 10.

Next, an n-type polycrystalline silicon film 19 is deposited over the silicon oxide film 17 by the CVD  
15 method, as shown in Fig. 11, and a silicon oxide film 20 is then deposited over the polycrystalline silicon film 19 by the CVD method. Subsequently, the silicon oxide film 20 is cylindrically patterned, leaving the portions only in and over the connection holes 18, as  
20 shown in Fig. 12, and an n-type polycrystalline silicon film 21 is then deposited by the CVD method.

Next, the polycrystalline silicon film 21 is patterned by the reactive ion etching method so that it is left only on the side wall of the cylindrical  
25 silicon oxide film 20, as shown in Fig. 13. After

this, the polycrystalline silicon film 19, underlying the polycrystalline silicon film 12, is patterned and only the portions below the silicon oxide film 20 and polycrystalline silicon film 21 forming the side wall  
5 of the former.

Next, the silicon oxide film 20 and the underlying silicon oxide film 17 are removed by using a wet etching liquid such as an aqueous solution of hydrofluoric acid. At this time, the silicon nitride  
10 film 16 below the silicon oxide film 17 acts as the etching stopper so that the silicon oxide film 15 or the BPSG film 13 located below the silicon nitride film 16 is not removed. As a result, there are obtained cylindrical (crown-shaped) storage electrodes  
15 22, each of which has three layers of the polycrystalline silicon films 12, 19 and 21.

Next, a silicon nitride film 23 is thinly deposited over the surface of the storage electrodes 22 by the CVD method, as shown in Fig. 15. After  
20 this, a tantalum oxide film 24 is thinly deposited over the surface of the silicon nitride film 23 by the CVD method to form a capacitor insulating film 25 for a data storing capacitive element, of a multilayer film having the silicon nitride film 23 and the  
25 tantalum oxide film 24. This tantalum oxide film 24

is deposited at a temperature of about 400°C by using  $\text{Ta}(\text{OC}_2\text{H}_5)_5$  (ethoxy tantalum) as the reaction gas and is then annealed at a temperature of about 700 to 1,000°C by using an electric furnace or a lamp annealing apparatus. Since the silicon nitride film is formed between the tantalum oxide film 24 and the storage electrode, no oxide is formed at the interface between the tantalum oxide film 24 and the lower electrode 22 (polycrystalline silicon film), which may be produced by their reaction at the high temperature annealing.

Next, the semiconductor substrate 1 is transferred into the chamber 41 of a CVD apparatus 40, as shown in Fig. 18, so that the upper electrodes of the data storing capacitive element may be formed over the capacitor insulating film 25.

As shown in the same Figure, this CVD apparatus 40 has a structure in which a titanium-containing source gas such as  $\text{TiCl}_4$ , TDMAT or TDEAT, a nitrogen-containing reducing gas such as  $\text{NH}_3$  or MMH for bringing the composition rate of Ti and N close to 1 : 1, and an inert gas such as He (helium), Ar (argon) or  $\text{N}_2$  (nitrogen) individually through different gas supply pipes into the chamber 41. Thanks to this structure, it is possible to prevent a drawback that the gases react in the individual gas supply pipes so that the

reactants deposit on the inner walls of the pipes.

This CVD apparatus is so constructed that only either the nitrogen-containing reducing gas or the inert gas can be selectively introduced into the chamber 41 by controlling the ON/OFF of valves 42 and 43 disposed in the gas supply pipe.

In this CVD apparatus 40, moreover, a vacuum pump 45 other than a vacuum pump 44 for adjusting the degree of vacuum in the chamber 41 is connected to a portion of the gas supply pipe for introducing the nitrogen-containing reducing gas into the chamber 41. Thanks to this construction, in which the gas in the gas supply pipe is partially discharged by the vacuum pump 45 at the initial stage at which the nitrogen-containing reducing gas is introduced into the chamber 41, it is possible to prevent the drawback that an excessive amount of nitrogen-containing reducing gas is instantly introduced into the chamber 41.

In the present embodiment, the semiconductor substrate 1 is transferred into the chamber 41 of the aforementioned CVD apparatus 40. After this, the inside of the chamber 41 is evacuated to a predetermined degree of vacuum by the vacuum pump 44. Subsequently, the titanium-containing source gas and the inert gas are introduced at predetermined flow

rates into the chamber 41 so that the titanium-containing source gas is thermally decomposed at about 300 to 600°C, more preferably at about 400 to 450°C to deposit an amorphous Ti film 26 thinly over the  
5 surface of the tantalum oxide film 24, as shown in Fig. 16. Incidentally, when either the N<sub>2</sub> gas or a mixed gas of N<sub>2</sub> and another inert gas is used as the inert gas, there may be formed the amorphous Ti film 26 containing amorphous TiN partially, which raises no  
10 problem though.

Next, the titanium-containing source gas, the nitrogen-containing reducing gas and the inert gas are introduced at predetermined flow rates into the chamber 41 of the CVD apparatus 40, so that the  
15 titanium-containing source gas and the nitrogen-containing reducing gas react, as shown in Fig. 17, to deposit a TiN film 27 over the amorphous Ti film 26 thereby to form an upper electrode 28 for the data storing capacitive element of a multilayer film of the  
20 amorphous Ti film 26 and the TiN film 27.

According to the method thus far described, the surface of the tantalum oxide film 24 is covered with the amorphous Ti film 26, so that the nitrogen-containing reducing gas is kept from  
25 contacting with the tantalum oxide film 24. As a

result, the breakdown strength of the tantalum oxide film can be reliably prevented from being deteriorated by the nitrogen-containing reducing gas. By discharging the gas in the gas supply pipe partially  
5 by the vacuum pump 45 at the initial stage at which the nitrogen-containing reducing gas is introduced into the chamber 41 to prevent the excessive amount of nitrogen-containing reducing gas from being instantly introduced into the chamber 41, the composition of Ti  
10 and N in the TiN film 27 can be brought close to the optimum value (Ti : N = 1 : 1).

Thus, according to the present embodiment, when the TiN film 27 is deposited by the CVD method over the tantalum oxide film 24 forming the capacitor  
15 insulating film 25 of the data storing capacitive element to form the upper electrode 28, the amorphous Ti film 26 impermeable to the nitrogen-containing reducing gas is formed in advance over the surface of the tantalum oxide film 24, so that the breakdown  
20 strength (the increase in the leakage current) of the tantalum oxide film 24 can be prevented reliably. As a result, it is possible to realize a DRAM which has an improved refresh characteristics.

(Embodiment 2)

25 Fig. 19 is a block diagram of a DRAM of the

present embodiment, and Fig. 20 is a circuit diagram of a memory array and a sense amplifier of this DRAM.

The DRAM of the present embodiment basically has a memory array MARY which occupies the major portion  
5 of the principal face of a semiconductor substrate. This memory array MARY includes, as shown in Fig. 20,  $(m + 1)$  word lines ( $W0 - Wm$ ) arranged in parallel in the longitudinal direction of the drawing, and  $(n + 1)$  complementary bit lines (non-inverted bit lines BOT -  
10 BNT and inverted bit lines BOB - BOB) arranged in parallel in the horizontal direction. At the intersections of these word lines and complementary bit lines, there are arranged in a lattice shape  $(m + 1) \times (n + 1)$  memory cells which have data storing  
15 capacitive elements (Cs) and memory cell selecting MISFETs Qa.

The drain regions of  $(m + 1)$  memory cell selecting MISFETs Qa, arranged in a common column of the memory array MARY, are alternately coupled with a  
20 predetermined regularity to the non-inverted or inverted signal lines of the corresponding complementary bit lines. Moreover, the gate electrodes of the memory cell selecting MISFETs Qa of the  $(n + 1)$  memory cells, arranged in a common row of  
25 the memory array MARY, are coupled integrally with the

corresponding word lines. A predetermined plate voltage VP is commonly fed to the other electrodes of the data storing capacitive elements (Cs) of all the memory cells constituting the memory array MARY.

5       The word lines ( $W_0 - W_m$ ), constituting the memory array MARY, are coupled therebelow to an X-address decoder XD, and one of them is selectively brought into a selected state. The X-address decoder XD is fed with internal address signals ( $X_0 - X_i$ ) of  $(i + 1)$   
10 bits from an X-address buffer XB and with an internal control signal SDG from a timing generator TG. The X-address buffer XB is fed in a time sharing manner through address input terminals ( $A_0 - A_i$ ) with X-address signals ( $XA_0 - XA_i$ ) and with an internal  
15 control signal XL from the timing generator TG.

      The X-address buffer XB captures the X-address signals ( $XA_0$  to  $XA_i$ ), fed through the address input terminals ( $A_0$  to  $A_i$ ), in accordance with the internal control signal XL and holds them. On the basis of  
20 these X-address signals, the X-address buffer XB generates and feeds the internal address signals ( $X_0 - X_i$ ) to the X-address decoder XD. This X-address decoder XD is selectively made to operate to decode the internal address signals ( $X_0 - X_i$ ) in response to  
25 the high level of the internal control signal XDG and

brings the corresponding word lines ( $W0 - Wm$ ) of the memory array MARY selectively into a selected state of the high level.

The complementary bit lines (BOT - BNT and BOB - BNB), constituting the memory array MARY, are coupled to a sense amplifier SA and are selectively connected therethrough with a complementary common data line CD. This sense amplifier SA is fed with bit line select signals ( $YS0 - YSn$ ) of  $(n + 1)$  bits from a Y-address decoder YD and with an internal control signal PA from the timing generator TG. The Y-address decoder YD is fed with internal address signals ( $Y0 - Yi$ ) of  $(i + 1)$  bits from a Y-address buffer YB and with an internal control signal YDG from the timing generator TG. Moreover, the Y-address buffer YB is fed in a time sharing manner through the address input terminals ( $A0 - Ai$ ) with Y-address signals ( $AY0 - AYi$ ) and with an internal control signal YL from the timing generator TG.

The Y-address buffer YB captures the Y-address signals ( $YAO$  to  $YAi$ ), fed through the address input terminals ( $A0$  to  $Ai$ ), in accordance with the internal control signal YL and holds them. On the basis of these Y-address signals, the Y-address buffer YB generates and feeds the internal address signals ( $Y0 -$

Yi) to the Y-address decoder YD. The Y-address decoder YD is selectively made to operate to decode the internal address signals (Y0 - Yi) in response to the high level of the internal control signal YDG and  
5 brings the corresponding bit-line selecting signals (YS0 - YSn) selectively into a selected state of the high level.

The sense amplifier SA includes (n + 1) unit circuits which are so provided as to correspond to the  
10 complementary bit lines of the memory array MARY. Each of these unit circuits includes, typically shown in Fig. 20: a bit line precharge circuit arranged between the non-inverted and inverted signal lines of the complementary bit lines and having a pair of  
15 n-channel MISFETs N5 and N6; and a unit amplifier having a CMOS inverter having a p-channel MISFET P1 and an n-channel MISFET N1 and a CMOS inverter cross-connected with the former inverter and having a  
p-channel MISFET P2 and an n-channel MISFET N2,  
20 although especially not limited thereto. Of these, the commonly coupled source regions of the n-channel MISFETs N5 and N6, constituting the bit line precharge circuit of each unit circuit, are commonly fed with an internal voltage HV, and the gate electrodes of the  
25 same are commonly fed with an internal control signal

PC. Incidentally, the internal voltage HV is an intermediate potential between the power supply voltage of the circuit and the ground potential. The internal control signal PC is selectively brought to  
5 the high level when the memory cell is not selected. As a result, when the memory cell is not selected but the internal control signal PC is set at the high level, the n-channel MISFETs N5 and N6 are selectively turned on together to precharge the non-inverted and  
10 inverted signal lines of the corresponding complementary bit lines of the memory array MARY to the internal voltage HV.

The source regions of the p-channel MISFETs P1 and P2, constituting the unit amplifier of each unit  
15 circuit, are commonly coupled to a common source line SP. This common source line SP is coupled to the power supply voltage of the circuit through a p-channel drive MISFET P3 which receives, at its gate electrode, an inverted internal control signal PAB,  
20 i.e., a signal which is the inverted signal of the internal control signal PA by an inverter V1. Likewise, the source regions of the n-channel MISFETs N1 and N2, constituting the unit amplifier of each unit circuit, are commonly coupled to a common source  
25 line SN. This common source line SN is coupled to the

ground potential of the circuit through an n-channel drive MISFET N7 which receives the internal control signal PA at its gate electrode. As a result, the individual unit amplifiers are selectively made to  
5 operate altogether, when the internal control signal PA is set at the high level whereas the inverted internal control signal PAB is set at the low level, to amplify the minute read signal outputted from the  $(n + 1)$  memory cells coupled to the selected word  
10 lines of the memory array MARY through the corresponding complementary bit lines, thereby to generate binary read signals of the high or low level.

Each unit circuit of the sense amplifier SA further includes a pair of n-channel switch MISFETs N3 and N4 which are interposed between the non-inverted  
15 and inverted input/output nodes of the unit amplifier and the complementary common data line CD. The gate electrodes of these paired switch MISFETs are commonly coupled, so that they are individually fed with the  
20 bit line select signals  $(YS0 - YSn)$  from the Y-address decoder YD. As a result, the switch MISFETs N3 and N4 of each unit circuit are selectively turned on, when the corresponding bit line select signals  $(YS0 - YSn)$  are set at the high level, to connect the  
25 corresponding unit amplifier of the sense amplifier

SA, i.e., the corresponding pair of complementary bit lines of the memory array MARY selectively with the complementary common data line CD.

This complementary common data line CD, with  
5 which is connected the designated pair of the complementary bit lines of the memory array MARY, is coupled to a data input/output circuit IO. This data input/output circuit IO includes a write amplifier, a main amplifier, a data input buffer and a data output  
10 buffer, although not shown. Of these, the output terminal of the write amplifier and the input terminal of the main amplifier are commonly coupled to the complementary common data line CD. The input terminal of the write amplifier is coupled to the output  
15 terminal of the data input buffer the input terminal of which is coupled to a data input terminal Din. Moreover, the output terminal of the main amplifier is coupled to the input terminal of the data output buffer the output terminal of which is coupled to a  
20 data output terminal Dout.

When the memory cell is brought into a selected state in the write mode, the data input buffer of the data input/output circuit IO captures the write data fed through the data input terminal Din to transmit  
25 the data to the write amplifier. These write data are

changed into predetermined complementary write signals by the write amplifier and then written through the complementary common data line CD in one selected memory cell of the memory array MARY. When the memory  
5 cell is brought into a selected state in the read mode, the main amplifier of the data input/output circuit IO further amplifies the binary read signal outputted from the selected memory cell of the memory array MARY through the complementary common data line  
10 CD, to transmit the amplified signal to the data output buffer. These read data are sent out from the data output buffer through the data output terminal Dout.

The timing generator TG generates the  
15 aforementioned various internal control signals selectively on the basis of a row address strobe signal RASB, a column address strobe signal CASB and a write enable signal WEB fed as the start control signals from the outside, to feed the generated  
20 internal control signals to the individual parts of the DRAM.

With reference to Figs. 21 to 47, here will be described a method for manufacturing a DRAM of the present embodiment.

25 In order to manufacture this DRAM, the surface of

the semiconductor substrate 1 made of p-type monocrystalline silicon is oxidized at first, as shown in Fig. 21, to form a thin silicon oxide film 53. After this, the CVD method is used to deposit a silicon nitride film 54 over the silicon oxide film 53. Next, the silicon nitride film 54 is etched by using a photoresist as the mask, to remove the silicon nitride film 54 of the element isolating region.

Next, the semiconductor substrate 1 is annealed by using the silicon nitride film 54 as the mask, as shown in Fig. 22, to form the field oxide film 3. Next, the silicon nitride film 54 is removed, and the regions of the semiconductor substrate 1 where the memory array and the n-channel MISFET of the peripheral circuit are to be formed are doped with ions of a p-type impurity (boron (B)) to form the p-type well 2, as shown in Fig. 23. The regions of the semiconductor substrate 1, where the p-channel MISFET of the peripheral circuit is to be formed is also doped with ions of an n<sup>-</sup>-type impurity (phosphor (P)) to form an n<sup>-</sup>-type well 55. Subsequently, the p-type well 2 is doped with ions of the p-type impurity (B) to form the p-channel stopper layer 5, and the n<sup>-</sup>-type well 55 is doped with ions of the n<sup>-</sup>-type impurity (P) to form the n<sup>-</sup>-type channel

stopper layer 6. After this, the surfaces of the individual active regions of the p-type well 2 and the n<sup>-</sup>-type well 55 defined by the field oxide film 3 are thermally oxidized to form the gate oxide film 4.

5 Next, there are formed a gate electrode 6A (the word line WL) of the memory cell selecting MISFET, and a gate electrode 6B of the n-channel MISFET and a gate electrode 6C of the p-channel MISFET of the peripheral circuit, as shown in Fig. 24. The gate electrode 6A (the word line WL) and the gate electrodes 6B and 6C are simultaneously formed by depositing a tungsten (W) film over the semiconductor substrate 1 by the CVD method, by depositing a silicon nitride film 57 over the W film by the plasma CVD method, and then by patterning those films by the etching method using a photoresist as its mask.

15 Next, the p-type well 2 is doped with ions of the n<sup>-</sup>-type impurity (P), and the n<sup>-</sup>-type well 55 is doped with the ions of the p-type impurity (B), as shown in Fig. 25. By the later annealing step, the n<sup>-</sup>-type impurity (P) forms the n<sup>-</sup>-type semiconductor region 8 (the source region and the drain region) of the memory cell selecting MISFET and an n<sup>-</sup>-type semiconductor region 58 of the n-channel MISFET of the peripheral circuit, and the p-type impurity (B) forms a p-type

20

25

semiconductor region 59 of the p-channel MISFET of the peripheral circuit.

Next, the side wall spacers 9 are formed on the individual side walls of the gate electrode 6A (the word line WL) and the gate electrodes 6B and 6C, as shown in Fig. 26. After this, the p-type well 2 of the peripheral circuit is doped with ions of the n<sup>-</sup>-type impurity (P), and the n<sup>-</sup>-type well 55 is doped with ions of the p-type impurity (B). The side wall spacers 9 are formed by depositing a silicon nitride film over the semiconductor substrate 1 by the plasma CVD method and then by processing the silicon nitride film by the anisotropic etching method.

Next, the semiconductor substrate 1 is annealed in an atmosphere of nitrogen to diffuse the aforementioned n<sup>-</sup>-type impurity (P) and p-type impurity, as shown in Fig. 27, thereby to form the n<sup>-</sup>-type semiconductor region 8 (the source region and the drain region) of the memory cell selecting MISFET, the n<sup>-</sup>-type semiconductor region 58 and an n<sup>+</sup>-type semiconductor region 60 of the n-channel type MISFET and the p<sup>-</sup>-type semiconductor region 59 and a p<sup>+</sup>-type semiconductor region 61 of the p-channel MISFET of the peripheral circuit. The source region and drain region of the n-channel MISFET of the peripheral

circuit individually have an LDD (Lightly Doped Drain) structure having the n<sup>-</sup>-type semiconductor region 58 and the n<sup>+</sup>-type semiconductor region 60, and the source region and drain region of the p-channel MISFET

5 individually have an LDD structure having the p<sup>-</sup>-type semiconductor region 59 and the p<sup>+</sup>-type semiconductor region 61.

Next, a silicon oxide film 62 is deposited over the memory cell selecting MISFET and the n-channel

10 MISFET and the p-channel MISFET of the peripheral circuit by the plasma CVD method, as shown in Fig. 28, and is polished to flatten the surface by the chemino-mechanical polishing (CMP) method. After this, the silicon oxide film 62 and the gate oxide film 4 are

15 etched by using a photoresist as the mask to make connection holes 63 and 64 over the n-type semiconductor region 8 (the source region and the drain region) of the memory cell selecting MISFET, connection holes 65 and 66 over the n<sup>+</sup>-type

20 semiconductor region 60 (the source region and the drain region) of the n-channel type MISFET of the peripheral circuit, and connection holes 67 and 68 over the p<sup>+</sup>-type semiconductor region 61 (the source region and the drain region) of the p-channel type

25 MISFET.

At this time, the silicon nitride film 57 formed over the gate electrode 6A (the word line WL) of the memory cell selecting MISFET, and the side wall spacers 9 of silicon nitride formed on the side walls are slightly etched, so that the connection holes 63 and 64 are formed in a self-alignment manner. Likewise, the silicon nitride film 57 formed over the gate electrode 6B of the n-channel MISFET of the peripheral circuit and the gate electrode 6C of the p-channel MISFET, and the side wall spacers 9 formed on the side walls are slightly etched, so that the connection holes 65 to 68 are formed in a self-alignment manner.

The insulating films deposited over the memory cell selecting MISFET and the n-channel MISFET and p-channel MISFET of the peripheral circuit can be exemplified by not only the aforementioned silicon oxide film 62 but also an ozone ( $O_3$ )-BPSG film deposited by the CVD method, or an ozone-TEOS (Tetra Ethoxy Silane) deposited by the CVD method. The surfaces of the insulating films are flattened like the silicon oxide film 62 by the chemino-mechanical polishing (CMP) method.

Next, plugs 69 made of a multilayered film of TIN and W are buried in the connection holes 63 to 68, as

shown in Fig. 29. These plugs 69 are formed by depositing the TiN film of the bonding layer between the substrate and the W film over the silicon oxide film 62 by the sputtering method, by subsequently  
5 depositing a W film over the TiN film by the CVD method and then by etching back the W film and the TiN film.

At this time, a Ti silicide ( $\text{TiSi}_2$ ) layer may be formed over the bottoms of the connection holes 63 to  
10 68 so as to reduce the contact resistance between the plugs 69 and the substrate. The Ti silicide layer is formed by depositing the Ti film over the silicon oxide film 62 by the sputtering method, causing the Ti film and the substrate over the bottoms of the  
15 connection holes 63 to 68 to react with each other by the annealing method at about  $800^\circ\text{C}$ , and then removing the unreacted Ti film left over the silicon oxide film 62 by the wet etching method. After this, the TiN film and the W film deposited over the silicon oxide  
20 film 62 are etched back to form the plugs 69.

Next, bit lines  $\text{BL}_1$  and  $\text{BL}_2$  and wiring lines 70A and 70B of the peripheral circuit are formed over the silicon oxide film 62, as shown in Fig. 30. These bit lines  $\text{BL}_1$  and  $\text{BL}_2$  and wiring lines 70A and 70B are  
25 simultaneously formed by depositing a W film over the

silicon oxide film 62 by the plasma CVD method, by subsequently depositing a silicon nitride film 71 over the W film by the CVD method and then by patterning those films by the etching method using a photoresist as the mask.

The bit line  $BL_1$  is electrically connected through the connection hole 63 with one (an  $n^-$ -type semiconductor region 8) of the source region and drain region of the memory cell selecting MISFET. The bit line  $BL_2$  is electrically connected through the connection hole 65 with one ( $n^+$ -type semiconductor region 60) of the source region and drain region of the n-channel type MISFET  $Q_n$  of the peripheral circuit.

One end of the wiring line 70A of the peripheral circuit is electrically connected through the connection hole 66 with the other (or the  $n^+$ -type semiconductor region 60) of the source region and drain region of the n-channel MISFET, and the other end is electrically connected through the connection hole 67 with one (the  $p^+$ -type semiconductor region 61) of the source region and drain region of the p-channel MISFET. The wiring line 70B is electrically connected through the connection hole 68 with the other (the  $p^+$ -type semiconductor region 61) of the source region

and drain region of the p-channel MISFET.

Next, side wall spacers 72 are formed over the individual side walls of the bit lines  $BL_1$  and  $BL_2$  and the wiring lines 70A and 70B, as shown in Fig. 31.

5 These side wall spacers 72 are formed by depositing a silicon nitride film over the silicon oxide film 62 by the plasma CVD method and then by processing the silicon nitride film by the anisotropic etching method.

10 Next, connection holes 74 are formed above the aforementioned connection holes 64 which are formed over one of the n-type semiconductor region 8 (the source region and the drain region) of the memory cell selecting MISFET, as shown in Fig. 32, by depositing a  
15 silicon oxide film 73 over the individual bit lines  $BL_1$  and  $BL_2$  and wiring lines 70A and 70B by the plasma CVD method, by subsequently polishing the silicon oxide film 73 to give it a flat surface by the chemino-mechanical polishing (CMP) method, and then by etching  
20 the silicon oxide film 73 by using a photoresist as the mask. At this time, the silicon nitride film 71 formed over the bit line  $BL_1$ , and the side wall spacers 72 of silicon nitride formed on the side walls are slightly etched, so that the connection holes 74 are  
25 formed in a self-alignment manner.

The insulating film deposited over the bit lines BL<sub>1</sub> and BL<sub>2</sub> and the wiring lines 70A and 70B can be exemplified by not only the aforementioned silicon oxide film 73 but also the aforementioned ozone-BPSG film or ozone-TEOS film, or a spin-on-glass (SOG) film. When the ozone-BPSG film or the ozone-TEOS film is used, it is polished to flatten the surface by the chemino-mechanical polishing (CMP) method similarly to the polishment of the silicon oxide film 73.

Next, plugs 75 of W are buried in the connection holes 74, as shown in Fig. 33, and lower electrodes (storage electrodes) 76 of the data storing capacitive element are then formed over the connection holes 74. The W plugs 75 are formed by depositing a W film over the silicon oxide film 73 by the CVD method and then by etching back the W film. The lower electrodes 76 are formed by depositing the W film over the silicon oxide film 73 by the CVD method and then by patterning the W film by the etching method using a photoresist as the mask.

Next, a tantalum oxide film 77 is deposited over the lower electrode 22, as shown in Fig. 34. The tantalum oxide film 77 is deposited by using the CVD method of an excellent step coverage. The tantalum oxide 77 is deposited at a temperature of about 400°C

by using, for example,  $\text{TA}(\text{OC}_2\text{H}_5)$  as the reaction gas and is then annealed at a temperature of about 700 to  $1,000^\circ\text{C}$  by using an electric furnace or a lamp annealing apparatus.

5       Next, a conductive film for the upper electrodes is deposited over the tantalum oxide film 77 by using the CVD apparatus, as used in the foregoing first embodiment 1. The titanium-containing source gas used at this time is exemplified by  $\text{TiCl}_4$ , TDMAT or TDEAT;  
10       the nitrogen-containing reducing gas is exemplified by  $\text{NH}_3$  or MMH, or their mixed gas; and the inert gas is exemplified by He, Ar or  $\text{N}_2$ , or their mixed gas.

          In the present embodiment, the gases are introduced into the chamber of the CVD apparatus in  
15       accordance with the steps, as illustrated in Fig. 35. Specifically, the chamber is evacuated to a predetermined degree of vacuum, and the inert gas is then introduced while raising the temperature of the substrate. When the substrate temperature becomes  
20       substantially constant, the titanium-containing source gas is introduced and thermally decomposed to form a passivation film 78 made mainly of Ti and having a thickness as small as about 30 to 50 angstroms, over the surface of the tantalum oxide film 77, as shown in  
25       Fig. 36. Subsequently, the nitrogen-containing

reducing gas is introduced into the chamber and reacted with the titanium-containing gas thereby to deposit a TiN film 79 over the surface of the passivation film 78, as shown in Fig. 37.

- 5 Representative reactions at this time between the titanium-containing source gas and the nitrogen-containing reducing gas are shown in Fig. 38.

The titanium-containing source gas may be introduced substantially simultaneously with the inert  
10 gas while the temperature of the substrate is raised, as shown in Fig. 39, or just before the introduction of the nitrogen-containing reducing gas, as shown Fig. 40. In either case, however, the titanium-containing source gas is introduced prior to the introduction of  
15 the nitrogen-containing reducing gas. Then, the passivation film 78 is formed on the surface of the tantalum oxide film 77 by the thermal decomposition of the titanium-containing source gas, and prevents the contact between the nitrogen-containing reducing gas  
20 to be later introduced and the tantalum oxide film 77 thereby to prevent the deterioration of the tantalum oxide film 77.

When the passivation film 78 and the TiN film 79 are deposited over the tantalum oxide film 77, under  
25 such a film forming temperature condition that the

barrier of the passivation film 78 against the permeation of the nitrogen-containing reducing gas is sufficiently high. Specifically, the film forming step is executed at a temperature lower than the  
5 crystallization temperature to form the amorphous or polycrystalline passivation film 78 which has less paths therein through which gas permeates than a crystalline film.

The optimum temperature at which the passivation  
10 film 78 and the TiN film 79 are formed is different depending upon the kind of the titanium-containing source gas and the nitrogen-containing reducing gas to be used and their combination but is generally 550°C or less when the nitrogen-containing reducing gas is  
15 exemplified by  $\text{NH}_3$ , preferably 500°C or less, and more preferably 450°C or less when the MMH is used.

Figs. 41 and 42 are graphs showing the results of an experiment in which the relation between the film forming temperatures of the passivation film 78 and  
20 the TiN film 79 and the field strength of the tantalum oxide film 77. Fig. 41 shows the field strength of  $10^{-8}$  A/cm<sup>2</sup> when the positive (+) voltage is applied to the upper electrode made of the TiN film 79, and Fig. 42 shows the field strength of  $10^{-8}$  A/cm<sup>2</sup> when the  
25 negative (-) voltage is applied to the same upper

electrode. In the drawings: open circles (O) indicate the field strength when the films are formed at the steps shown in Fig. 35 (the inert gas = He + Ar, the titanium-containing source gas =  $\text{TiCl}_4$ , and the  
5 nitrogen-containing reducing gas =  $\text{NH}_3$ ); solid circles (●) indicate the field strength when the films are formed at the steps shown in Fig. 39 (the inert gas = He + Ar, the titanium-containing source gas =  $\text{TiCl}_4$ , and the nitrogen-containing reducing gas =  $\text{NH}_3$ ); open  
10 squares (□) indicate the field strength when the films are formed at the steps shown in Fig. 40 (the inert gas = He + Ar, the titanium-containing source gas =  $\text{TiCl}_4$ , and the nitrogen-containing reducing gas =  $\text{NH}_3$ ); and solid squares (■) indicate the field strength when  
15 the films are formed at the steps shown in Fig. 40 (the inert gas = He + Ar, the titanium-containing source gas =  $\text{TiCl}_4$ , and the nitrogen-containing reducing gas =  $\text{NH}_3$  + MMH).

It has been found out from the aforementioned  
20 results of the experiment that the field strength of the tantalum oxide film 77 generally increases and the leakage breakdown voltage of the capacitor insulating film is improved when the film forming temperature of the passivation film 78 and the TiN film 79 are low.

Incidentally in the aforementioned film forming process, chlorine produced by the decomposition of the titanium-containing source gas ( $\text{TiCl}_4$ ) is included in the films. This chlorine concentration increases as the film forming temperature lowers, as shown in Fig. 43. If chlorine of high concentration is captured in the conductive film constituting the upper electrode, the chlorine atoms further enter the wiring lines containing Al (aluminum) through the connection holes connecting the upper electrode and the wiring lines when the wiring lines are formed over the upper electrode, so that the potential causing the wiring corrosion rises. Therefore, the lower limit of the film forming temperature of the passivation film 78 and the TiN film 79 has to be determined considering the rise in the potential.

Next, a high selection ratio film 80 is deposited over the TiN film 79, as shown in Fig. 44. After this, the high selection ratio film 80, the TiN film 79, the passivation film 78 and the tantalum oxide film 77 are patterned by the dry etching method using a photoresist as the mask, to form an upper electrode (plate electrode) 90 and the capacitor insulating film (the tantalum oxide film 77) thereby to complete the data storing capacitive element Cs. Simultaneously

with this, there are further formed wiring lines 81 and 82 of the peripheral circuit. The high selection ratio film 80 is a film acting as the etching stopper when the silicon oxide film and the silicon nitride  
5 film are etched at the later steps and may be either an insulating film or a conductive film if it is made of a material having a high etching selection ratio of the silicon oxide film or the silicon nitride film.

Next, a silicon oxide film 83 is deposited over  
10 the data storing capacitive element Cs and the wiring lines 81 and 82, as shown in Fig. 45. After this, the silicon oxide film 83 is dry-etched by using a photoresist as the mask to form a connection hole 84 over the upper electrode 90 of the data storing  
15 capacitive element Cs and a connection hole 85 over the wiring line 81. Simultaneously with this, the silicon oxide film 83 in the region where the wiring line 82 is formed, the silicon oxide film 73 and the silicon nitride film 71 are etched to form a  
20 connection hole 86 over the wiring line 70B of the peripheral circuit. At this time, the upper electrode 90 and the wiring lines 81 and 82 are covered with the high selection ratio film 80, so that they are not etched and thinned.

25       Next, the high selection ratio film 80 covering

the upper electrode 90 and the wiring lines 81 and 82 is etched, as shown in Fig. 46 to expose a portion of the wiring line 81 in the connection hole 85 and one end of the wiring line 82 in the connection hole 86.

5       Next, plugs 87 of TiN (or W) are buried in the connection holes 84, 85 and 86, as shown in Fig. 47. After this, wiring lines 88A, 88B and 88C made of a multilayer film of Al and TiN, are formed over the silicon oxide film 83. As a result, the wiring line  
10       81 of the peripheral circuit is connected through the wiring lines 88C and 82 with the underlying wiring line 70B.

      Thus, according to the present embodiment, when the TiN film 79 is deposited by the low temperature  
15       CVD method over the tantalum oxide film 77 constituting the capacitor insulating film of the data storing capacitive element Cs to form the upper electrode 90, the passivation film 78 impermeable to the nitrogen-containing reducing gas is formed in  
20       advance over the surface of the tantalum oxide film 73, so that the degradation of the breakdown voltage (the increase in the leakage current) of the tantalum oxide film 77 can be prevented reliably. As a result, it is possible to realize a DRAM which improved  
25       refreshing characteristics.

Although our invention has been specifically described in connection with its embodiments, it should not be limited thereto but can naturally be modified in various manners without departing from the gist thereof.

The foregoing embodiments have been described in cases where the upper electrode of the capacitive element is made of TiN, but the present invention can also be applied to a semiconductor integrated circuit device in which the upper electrode is made of a material other than TiN, exemplified by TaN. When a TaN film is deposited over the tantalum oxide film by the CVD method, for example, there is used a method in which  $\text{Ta}(\text{OC}_2\text{H}_5)_5$  is reduced with a nitrogen-containing reducing gas such as  $\text{NH}_3$  or MMH. By forming the passivation film over the surface of the tantalum oxide film prior to the formation of the TaN film, therefore, it is possible to prevent the degradation of the breakdown voltage of the tantalum oxide film which may be caused by the contact with the nitrogen-containing reducing gas.

The present invention can also be applied to the DRAM or nonvolatile memory in which the capacitor insulating film of the capacitive element is made of a highly dielectric film or a ferroelectric film other

than the tantalum oxide, such as BaSrTiO<sub>3</sub>, SrTiO<sub>3</sub>, BaTiO<sub>3</sub> or PZT, or ZnO doped with B (boron) or F (fluorine).

5 The effects obtained by a representative one of the inventions disclosed herein will be briefly described in the following.

According to the present invention, when the TiN film is deposited over the tantalum oxide film constituting the capacitor insulating film of the capacitive element to form the upper electrode, the  
10 passivation film is formed in advance over the surface of the tantalum oxide film, so that the contact between the nitrogen-containing reducing gas and the tantalum oxide film can be prevented to form a  
15 capacitive element having improved breakdown voltage characteristics.

According to the present invention, the accumulated charge of the capacitive element can be increased by constructing the capacitor insulating  
20 film of the capacitive element of a film having a high dielectric constant.

## Claims:-

1. A method for manufacturing a semiconductor integrated circuit device, comprising the steps of:

(a) forming a capacitor insulating film of tantalum oxide over an lower electrode over a first major surface of a semiconductor substrate;

(b) annealing the capacitor insulating film at a first temperature; and then

(c) depositing an upper electrode of titanium nitride over the capacitor insulating film at a second temperature lower than the first temperature,

the step (c) comprising the substeps of:

(i) prior to substep (ii), introducing a titanium-containing source gas into a reaction chamber where the semiconductor substrate has been introduced;

(ii) introducing a nitrogen-containing reducing gas into the reaction chamber, while introducing the titanium-containing source gas into the reaction chamber, thereby depositing a titanium nitride film constituting the upper electrode.

2. A method for manufacturing a semiconductor integrated circuit device, according to claim 2, wherein the deposition of the upper electrode is carried

out by a chemical vapor deposition.

3. A method for manufacturing a semiconductor integrated circuit device, according to claim 2, wherein step (c) further comprises the substep of:

(iii) prior to substep (i), introducing an inert gas into the reaction chamber where the semiconductor substrate has been introduced.

4. A method for manufacturing a semiconductor integrated circuit device, according to claim 3, wherein step (c) further comprises the substep of:

(iv) after substep (ii), introducing an inert gas into the reaction chamber where the semiconductor substrate has been introduced, without introducing the nitrogen-containing reducing gas nor the titanium-containing source gas.

5. A method for manufacturing a semiconductor integrated circuit device, according to claim 4, wherein the inert gas is a gas or a mixed gas selected from nitrogen, helium, argon, and their mixed gas.

6. A method for manufacturing a semiconductor integrated circuit device, according to claim 5, wherein the lower electrode has a cylindrical portion and constitutes a memory capacitor together with the capacitor insulating film and the upper electrode.

7. A method for manufacturing a semiconductor integrated circuit device, comprising the steps of:

- 56 -

- (a) forming a capacitor insulating film of tantalum oxide over an lower electrode over a first major surface of a semiconductor substrate;
- (b) annealing the capacitor insulating film at a first temperature; and then
- (c) depositing an upper electrode of titanium nitride over the capacitor insulating film at a second temperature lower than the first temperature,

the step (c) comprising the substeps of:

- (i) prior to substep (ii), introducing an inert gas into a reaction chamber where the semiconductor substrate has been introduced;
- (ii) introducing a nitrogen-containing reducing gas and a titanium-containing source gas into the reaction chamber, thereby depositing a titanium nitride film constituting the upper electrode.

8. A method for manufacturing a semiconductor integrated circuit device, according to claim 7, wherein the deposition of the upper electrode is carried out by a chemical vapor deposition.

9. A method for manufacturing a semiconductor integrated circuit device, according to claim 8, wherein the inert gas is a gas or a mixed gas selected from nitrogen, helium, argon, and their mixed gas.

10. A method for manufacturing a semiconductor integrated circuit device, according to claim 9, wherein the lower electrode has a cylindrical portion and constitutes a memory capacitor together with the capacitor insulating film and

the upper electrode.

11. A method for manufacturing a semiconductor integrated circuit device, comprising the steps of:

(a) forming a capacitor insulating film of metal oxide over an lower electrode over a first major surface of a semiconductor substrate; and then

(b) depositing an upper electrode of metal-containing conducting material over the capacitor insulating film by a chemical vapor deposition,

the step (b) comprising the substeps of:

(i) prior to substep (ii), introducing a metal-containing source gas into a reaction chamber where the semiconductor substrate has been introduced;

(ii) introducing a reducing gas into the reaction chamber, while introducing the metal-containing source gas into the reaction chamber, thereby depositing a metal-containing conducting film constituting the upper electrode.

12. A method for manufacturing a semiconductor integrated circuit device, according to claim 11, wherein step (c) further comprises the substep of:

(iii) prior to substep (i), introducing an inert gas into the reaction chamber where the semiconductor substrate has been introduced.

13. A method for manufacturing a semiconductor integrated circuit device, according to claim 12, wherein step (c) further comprises the substep of:

(iv) after substep (ii), introducing an inert gas into the reaction chamber where the semiconductor substrate has been introduced, without introducing the reducing gas nor the metal-containing source gas.

14. A method for manufacturing a semiconductor integrated circuit device, according to claim 13, wherein the inert gas is a gas or a mixed gas selected from nitrogen, helium, argon, and their mixed gas.

15. A method for manufacturing a semiconductor integrated circuit device, according to claim 14, wherein the lower electrode has a cylindrical portion and constitutes a memory capacitor together with the capacitor insulating film and the upper electrode.

16. A method for manufacturing a semiconductor integrated circuit device, comprising the steps of:

(a) forming a capacitor insulating film of metal oxide over an lower electrode over a first major surface of a semiconductor substrate; and then

(b) depositing an upper electrode of metal-containing conducting material over the capacitor insulating film by a chemical vapor deposition,

the step (b) comprising the substeps of:

(i) prior to substep (ii), introducing an inert gas into a reaction chamber where the semiconductor substrate has been introduced;

(ii) introducing a reducing gas and a metal-containing source gas into the

reaction chamber, thereby depositing a metal-containing conducting film constituting the upper electrode.

17. A method for manufacturing a semiconductor integrated circuit device, according to claim 16, wherein the inert gas is a gas or a mixed gas selected from nitrogen, helium, argon, and their mixed gas.

18. A method for manufacturing a semiconductor integrated circuit device, according to claim 17, wherein the lower electrode has a cylindrical portion and constitutes a memory capacitor together with the capacitor insulating film and the upper electrode.

19. A method for manufacturing a semiconductor integrated circuit device, comprising the steps of:

(a) depositing a capacitor insulating film of tantalum oxide over an lower electrode over a first major surface of a semiconductor substrate by a chemical vapor deposition at a first temperature;

(b) annealing the capacitor insulating film at a second temperature higher than the first temperature; and then

(c) depositing an upper electrode of titanium nitride over the capacitor insulating film by a chemical vapor deposition at a third temperature lower than 600 degrees centigrade.

20. A method for manufacturing a semiconductor integrated circuit device,

according to claim 19, wherein the lower electrode has a cylindrical portion and constitutes a memory capacitor together with the capacitor insulating film and the upper electrode.

21. A method for manufacturing a semiconductor integrated circuit device, according to claim 20, wherein the third temperature is not higher than 550 degrees centigrade.

22. A method for manufacturing a semiconductor integrated circuit device, comprising the steps of:

- (a) forming a capacitor insulating film of tantalum oxide over an lower electrode over a first major surface of a semiconductor substrate;
- (b) annealing the capacitor insulating film at a first temperature; and then
- (c) depositing an upper electrode of titanium nitride over the capacitor insulating film at a second temperature lower than the first temperature,

the step (c) comprising the substeps of:

- (i) introducing a nitrogen-containing reducing gas and a titanium-containing source gas into the reaction chamber where the semiconductor substrate has been introduced, thereby depositing a titanium nitride film constituting the upper electrode; and then

- (ii) introducing an inert gas into the reaction chamber where the semiconductor substrate has been introduced, without introducing the

nitrogen-containing reducing gas nor the titanium-containing source gas.

23. A method for manufacturing a semiconductor integrated circuit device, according to claim 22, wherein the deposition of the upper electrode is carried out by a chemical vapor deposition.

24. A method for manufacturing a semiconductor integrated circuit device, according to claim 23, wherein step (c) further comprises the substep of:

(iii) prior to substep (i), introducing an inert gas into the reaction chamber where the semiconductor substrate has been introduced.

25. A method for manufacturing a semiconductor integrated circuit device, according to claim 24, wherein the inert gas is a gas or a mixed gas selected from nitrogen, helium, argon, and their mixed gas.

26. A semiconductor integrated circuit device comprising:

(a) a semiconductor substrate having a first major surface;

(b) a plurality of memory cells disposed over the major surface of the substrate, each of the memory cells having:

(i) a cylindrical lower electrode;

(ii) a capacitor insulating film of tantalum oxide over both an inner and an outer surfaces of the lower electrode;

(iii) an upper electrode of metal nitride over the capacitor insulating film.

27. A method for manufacturing a semiconductor integrated circuit device

having (x) a semiconductor substrate having a first major surface; (y) a plurality of memory cells disposed over the major surface of the substrate, each of the memory cells including (i) a cylindrical lower electrode; (ii) a capacitor insulating film over both an inner and an outer surfaces of the lower electrode; (iii) an upper electrode over the capacitor insulating film, comprising the steps of:

(a) forming the capacitor insulating film of metal oxide insulating material over the lower electrode over the first major surface of the semiconductor substrate; and then

(b) depositing the upper electrode over the capacitor insulating film by a metal chemical vapor deposition,

the step (b) comprising the substeps of:

(i) prior to substep (ii), introducing an inert gas into a reaction chamber where the semiconductor substrate has been introduced;

(ii) introducing a reducing gas and a metal-containing source gas into the reaction chamber, thereby depositing a metal-containing film constituting the upper electrode.

28. A method for manufacturing a semiconductor integrated circuit device, according to claim 27, wherein step (c) further comprises the substep of:

(iv) after substep (ii), introducing an inert gas into the reaction chamber

where the semiconductor substrate has been introduced, without introducing the nitrogen-containing reducing gas nor the titanium-containing source gas.

29. A method for manufacturing a semiconductor integrated circuit device, according to claim 28, wherein the inert gas is a gas or a mixed gas selected from nitrogen, helium, argon, and their mixed gas.

30. A method for manufacturing a semiconductor integrated circuit device having (x) a semiconductor substrate having a first major surface; (y) a plurality of memory cells disposed over the major surface of the substrate, each of the memory cells including (i) a cylindrical lower electrode; (ii) a capacitor insulating film over both an inner and an outer surfaces of the lower electrode; (iii) an upper electrode over the capacitor insulating film, comprising the steps of:

(a) forming the capacitor insulating film of metal oxide insulating material over the lower electrode over the first major surface of the semiconductor substrate; and then

(b) depositing the upper electrode over by a metal chemical vapor deposition, the step (c) comprising the substeps of:

(i) prior to substep (ii), introducing a metal-containing source gas into a reaction chamber where the semiconductor substrate has been introduced;

- 64 -

(ii) introducing a reducing gas into the reaction chamber, while introducing the metal-containing source gas into the reaction chamber, thereby depositing a metal-containing film constituting the upper electrode.

31. A method for manufacturing a semiconductor integrated circuit device, according to claim 30, wherein step (c) further comprises the substep of:

(iv) after substep (ii), introducing an inert gas into the reaction chamber where the semiconductor substrate has been introduced, without introducing the nitrogen-containing reducing gas nor the titanium-containing source gas.

32. A method for manufacturing a semiconductor integrated circuit device, according to claim 31, wherein the inert gas is a gas or a mixed gas selected from nitrogen, helium, argon, and their mixed gas.

33. A method for manufacturing a semiconductor integrated circuit device, comprising the steps of:

(a) forming a capacitor insulating film of metal oxide over an lower electrode over a first major surface of a semiconductor substrate; and then

(b) depositing an upper electrode of metal-containing conducting material over the capacitor insulating film by a chemical vapor deposition,

the step (b) comprising the substeps of:

(i) introducing a reducing gas and a metal-containing source gas into the reaction chamber where the semiconductor substrate has been introduced, thereby depositing a metal-containing conducting film constituting the upper electrode; and then

(ii) introducing an inert gas into the reaction chamber where the semiconductor substrate has been introduced, without introducing the reducing gas nor the metal-containing source gas.

34. A method for manufacturing a semiconductor integrated circuit device, according to claim 33, wherein step (c) further comprises the substep of:

(iii) prior to substep (i), introducing an inert gas into the reaction chamber where the semiconductor substrate has been introduced.

35. A method for manufacturing a semiconductor integrated circuit device, according to claim 34, wherein the inert gas is a gas or a mixed gas selected from nitrogen, helium, argon, and their mixed gas.