

SENSE AMPLIFIER, MEMORY, AND CONTROL METHOD

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] The present application claims the priority to Chinese Patent Application No. 202110313685.5, titled "SENSE AMPLIFIER, MEMORY, AND
5 CONTROL METHOD" and filed with the China National Intellectual Property Administration (CNIPA) on March 24, 2021, which is hereby incorporated by reference in its entirety.

TECHNICAL FIELD

[0002] The present application relates to, but is not limited to, a sense
10 amplifier, a memory, and a control method.

BACKGROUND

[0003] With the popularity of electronic devices such as cell phones, tablets, and personal computers, semiconductor memory technologies are also developing rapidly.

15 **[0004]** A sense amplifier (SA) is an important composition part of a semiconductor memory, which mainly functions to amplify a small signal on a bit line, to further perform a read or write operation.

[0005] However, in a process of reading data, it is easy to fail to read the data or to read the data incorrectly.

SUMMARY

20 **[0006]** An embodiment of the present application provides a sense amplifier, including:

an amplification module, configured to: when the sense amplifier is at an amplification stage, amplify a voltage difference between a bit line and a reference bit line; and

5 a controlled power supply module, connected to the amplification module, and configured to: determine a drive parameter according to a first rated pull rate range of the bit line and a second rated pull rate range of the reference bit line, and supply power to the amplification module according to the drive parameter, to control the amplification module to pull a voltage of the bit line or a voltage of the reference bit line to a first preset value at a first rated
10 pull rate at the amplification stage and pull the voltage of the reference bit line or the voltage of the bit line to a second preset value at a second rated pull rate at the amplification stage, where

the first rated pull rate is within the first rated pull rate range, and the second rated pull rate is within the second rated pull rate range.

15 **[0007]** An embodiment of the present application provides a memory, including the sense amplifier in the foregoing embodiment of the present application and memory cells,

a plurality of memory cells constitute a first storage array, a plurality of memory cells constitute a second storage array, the sense amplifier is
20 located between the first storage array and the second storage array, a third terminal of the sense amplifier is connected to a bit line of the first storage array, and a fourth terminal of the sense amplifier is connected to a bit line of the second storage array.

[0008] The present application provides a control method, a sense amplifier
25 includes an amplification module and a controlled power supply module; and the method includes:

obtaining a first rated pull rate range and a second rated pull rate range;

determining a drive parameter of the controlled power supply
30 module according to the first rated pull rate range and the second rated pull

rate range; and

generating, according to the drive parameter, a control signal used to control the controlled power supply module, such that the controlled power supply module controls the amplification module to pull a voltage of a bit line or a voltage of a reference bit line to a first preset value at a first rated pull rate at an amplification stage and pull the voltage of the reference bit line or the voltage of the bit line to a second preset value at a second rated pull rate at an amplification stage, where

the first rated pull rate is within the first rated pull rate range, and the second rated pull rate is within the second rated pull rate range.

BRIEF DESCRIPTION OF DRAWINGS

[0009] FIG. 1 is a schematic diagram of a circuit structure of a memory according to an embodiment of the present application;

[0010] FIG. 2 is a time sequence diagram of data read according to another embodiment of the present application;

[0011] FIG. 3 is a schematic diagram of a circuit structure of a sense amplifier according to another embodiment of the present application;

[0012] FIG. 4A, FIG. 4B, and FIG. 4C are each a schematic diagram of comparison between pull rates of a voltage of a bit line and a voltage of a reference bit line according to the present application;

[0013] FIG. 5 is a schematic diagram of a circuit structure of a sense amplifier according to another embodiment of the present application;

[0014] FIG. 6 is a schematic diagram of a circuit structure of a sense amplifier according to another embodiment of the present application;

[0015] FIG. 7 is a schematic diagram of a circuit structure of a sense amplifier according to another embodiment of the present application;

[0016] FIG. 8 is a time sequence diagram of data read according to another embodiment of the present application; and

[0017] FIG. 9 is a schematic diagram of a procedure of a control method of a sense amplifier according to another embodiment of the present application.

DESCRIPTION OF EMBODIMENTS

[0018] In order to make the objectives, technical solutions and advantages of the present application clearer, the following clearly and completely describes the technical solutions in the present application with reference to the accompanying drawings in the present application. Apparently, the described embodiments are some rather than all of the embodiments of the present application. All other embodiments obtained by those of ordinary skill in the art based on the embodiments of the present application without creative efforts should fall within the protection scope of the present application.

[0019] As shown in FIG. 1, an embodiment of the present application provides a memory 100. The memory 100 includes a sense amplifier 10 and a plurality of memory cells 21. A plurality of memory cells 21 constitute a first storage array 20, and a plurality of memory cells 21 constitute a second storage array 30. Each memory cell 21 in the first storage array 20 is connected to a bit line 40 of the first storage array 20, and each memory cell 21 in the second storage array 30 is connected to a bit line 50 of the second storage array 30.

[0020] The sense amplifier 10 is located between the first storage array 20 and the second storage array 30, a first terminal of the sense amplifier 10 is connected to a first power supply terminal, a second terminal of the sense amplifier 10 is connected to a second power supply terminal, a third terminal of the sense amplifier 10 is connected to the bit line 40 of the first storage array 20, and a fourth terminal of the sense amplifier 10 is connected to the bit line 50 of the second storage array 30.

[0021] Each memory cell 21 is configured to store one-bit data, the bit line 40 of the first storage array 20 is configured to access data stored inside each

memory cell 21 in the first storage array 20, and the bit line 50 of the second storage array 30 is configured to access data stored inside each memory cell 21 in the second storage array 30. The sense amplifier 10 is configured to amplify the data stored in each memory cell 21, and present the data on the bit line 40 of the first storage array 20 and the bit line 50 of the second storage array 30. The sense amplifier 10 is further configured to: after a data read operation is completed once, restore the memory cell 21 to a state before the read operation.

[0022] Each memory cell 21 includes a storage capacitor C and an access transistor T, a first terminal of the storage capacitor C is connected to a fixed power supply, which is, for example, $0.5V_{CC}$, a second terminal of the storage capacitor C is connected to a first terminal of the access transistor T, a second terminal of the access transistor T is connected to the bit line 40, and a control terminal of the access transistor T is connected to a word line.

[0023] 1 and 0 in logic are represented by using a large and a small amount of charge stored in the storage capacitor C, or a high and low voltage difference between two ends of the storage capacitor C. The access transistor T is configured to control whether to allow or forbid to read or rewrite information stored in the storage capacitor C.

[0024] For ease of description, when data in a specific memory cell 21 in the first storage array 20 is read, the bit line of the first storage array 20 is referred to as a bit line 40, and the bit line of the second storage array 30 is referred to as a reference bit line 50. When data in a specific memory cell 21 in the second storage array 30 is read, the bit line of the second storage array 30 is referred to as a bit line 40, and the bit line of the first storage array 20 is referred to as a reference bit line 50.

[0025] A process of reading data "1" from one memory cell 21 in the first storage array 20 is described below. As shown in FIG. 2, reading data includes a precharge stage, an access stage, an amplification stage, and a restore stage.

[0026] At the precharge stage, both a voltage of the bit line 40 of the first storage array 20 and a voltage of the reference bit line 50 are pulled up to a reference voltage, and the reference voltage is a voltage of a fixed power supply connected to the storage capacitor C, which is, for example, $0.5V_{CC}$.

5 **[0027]** At the access stage, a signal on a word line corresponding to the accessed memory cell 21 is controlled, such that an access transistor T in the accessed memory cell 21 is on, and the storage capacitor C enables the voltage of the bit line 40 to rise.

[0028] At the amplification stage, the voltage of the bit line 40 is higher than
10 the reference voltage, such that the sense amplifier 10 pulls the voltage of the bit line 40 up to a first preset value, and pulls the voltage of the reference bit line 50 down to a second preset value, the voltage of the bit line 40 is higher than the voltage of the reference bit line 50, and a voltage difference between the bit line 40 and the reference bit line 50 may reflect that data in the
15 accessed memory cell 21 is "1".

[0029] At the restore stage, the sense amplifier 10 stabilizes the voltages of the bit line 40 and the reference bit line 50 at logical data "1", the bit line 40 further charges the storage capacitor C, and after a specific time of charging, charge in the storage capacitor C is restored to a state before the read
20 operation. Then, a signal inside a line is selected through a control column, such that an external read circuit may read the data stored in the accessed memory cell 21 on the bit line 40 and the reference bit line 50.

[0030] However, in a process of reading data in the memory cell 21, it is easy to fail to read the data or read the data incorrectly. To resolve the
25 technical problem, the present application provides a sense amplifier, a memory, and a control method, aiming to provide a solution of improving data read accuracy and a data read success rate of the sense amplifier.

[0031] A technical concept of the present application is that the controlled power supply module controls rates at which the amplification module pulls the
30 voltage of the bit line 40 and the voltage of the reference bit line 50, such that

the pull rates of the voltage of the bit line 40 and the voltage of the reference bit line 50 are within a rated pull rate range, and the data stored in the memory cell 21 has been stably presented on the bit line 40 and the reference bit line 50 when the external read circuit reads the data presented on the bit line 40 and the reference bit line 50, thereby further improving a data read success rate and data read accuracy.

[0032] As shown in FIG. 3, another embodiment of the present application provides a sense amplifier 10. The sense amplifier 10 includes an amplification module 101 and a controlled power supply module 102, and the amplification module 101 is connected to the controlled power supply module 102.

[0033] The amplification module 101 is configured to amplify a voltage difference between a bit line 40 and a reference bit line 50 when the sense amplifier 10 is at an amplification stage. The controlled power supply module 102 is configured to determine a drive parameter according to a first rated pull rate range and a second rated pull rate range, and supply power to the amplification module 101 according to the drive parameter.

[0034] Under control of the controlled power supply module 102, the amplification module 101 pulls a voltage of the bit line 40 or a voltage of the reference bit line 50 to a first preset value at a first rated pull rate and pulls the voltage of the reference bit line 50 or the voltage of the bit line 40 to a second preset value at a second rated pull rate at the amplification stage. The first rated pull rate is within the first rated pull rate range, and the second rated pull rate is within the second rated pull rate range. A difference between the first preset value and the second preset value can reflect logical data "1" or logical data "0".

[0035] To facilitate description of a process in which the sense amplifier reads data from a memory cell, it is assumed that when the first preset value is greater than the second preset value, it represents the logical data "1". The first preset value may be, for example, V_{CC} , and the second preset value may be, for example, 0.

[0036] When the logical data "1" is read from the memory cell 21, under control of the controlled power supply module 102, the amplification module 101 pulls the voltage of the bit line 40 to the first preset value at the first rated pull rate and pulls the voltage of the reference bit line 50 to the second preset value at the second rated pull rate at the amplification stage.

[0037] When the logical data "0" is read from the memory cell 21, under control of the controlled power supply module 102, the amplification module 101 pulls the voltage of the reference bit line 50 to the first preset value at the first rated pull rate and pulls the voltage of the bit line 40 to the second preset value at the second rated pull rate at the amplification stage.

[0038] In a process of reading data from the memory cell 21, a pull rate of the voltage of the bit line 40 and a pull rate of the voltage of the reference bit line 50 affect a data read success rate and data read accuracy.

[0039] As shown in FIG. 4A, if voltage pulling capabilities of a first terminal $v_p(t)$ and a second terminal $v_n(t)$ of the sense amplifier are excessively strong, pull rates of the voltage $v_1(t)$ of the bit line and the voltage $v_2(t)$ of the reference bit line are excessively high, resulting in occurrence of fluctuation in the voltage of the bit line and the voltage of the reference bit line, for example, the voltage of the bit line first decreases and then rises. In this case, data stored in the memory cell 21 cannot be stably presented on the bit line 40 and the reference bit line 50, to further cause an external read circuit to incorrectly read data on the bit line 40 and the reference bit line 50.

[0040] As shown in FIG. 4B, if voltage pulling capabilities of a first terminal $v_p(t)$ and a second terminal $v_n(t)$ of the sense amplifier are excessively weak, pull rates of the voltage $v_1(t)$ of the bit line and the voltage $v_2(t)$ of the reference bit line are excessively low, to further cause the voltages of the bit line 40 and the reference bit line 50 to fail to be pulled to a preset value when the external read circuit reads the voltages on the bit line 40 and the reference bit line 50, resulting in a data read failure.

[0041] As shown in FIG. 4C, in this embodiment, the controlled power

supply module 102 determines a drive parameter according to a first rated pull rate range and a second rated pull rate range, and supplies power to the amplification module 101 according to the drive parameter, to control the amplification module 101 to pull a voltage of the bit line 40 or a voltage of the reference bit line 50 to a first preset value at a first rated pull rate and pull the voltage of the reference bit line 50 or the voltage of the bit line 40 to a second preset value at a second rated pull rate at the amplification stage. The first rated pull rate is within the first rated pull rate range, and the second rated pull rate is within the second rated pull rate range.

[0042] The first rated pull rate range and the second rated pull rate range are determined according to a time sequence of selected signals on a column selection line, a time sequence of signals on a word line connected to the memory cell 21, and voltages of the bit line 40 and the reference bit line 50. The first rated pull rate range and the second rated pull rate range may be further obtained by testing the sense amplifier 10, to ensure that data on the bit line 40 and the reference bit line 50 can be accurately read. For example, as shown in FIG. 4A, FIG. 4B, and FIG. 4C, an embodiment is provided. It is assumed that a rising rate of $v_p(t)$ in FIG. 4A is 5 (a corresponding speed unit is V/ μ s), and a rising rate of $v_p(t)$ in FIG. 4B is 0.8 (a corresponding speed unit is V/ μ s). In this case, the first rated pull rate range may be from 2 to 4 (a corresponding speed unit is V/ μ s), and a first rated pull rate in FIG. 4C may be 3. It should be noted that one embodiment is merely provided herein, both the first rated pull rate range and the first rated pull rate are not limited thereto. Similarly, the second rated pull rate range and the second rated pull rate may be obtained in a similar manner. This is not limited herein.

[0043] When the sense amplifier 10 is at the amplification stage, the voltage of the bit line 40 or the reference bit line 50 is pulled at a pull rate within the first rated pull rate range, and the voltage of the reference bit line 50 or the bit line 40 is pulled at a pull rate within the second rated pull rate range. When the sense amplifier 10 is at a restore stage, the external read circuit reads data

presented on the bit line 40 and the reference bit line 50. In this case, the data stored in the memory cell 21 has been stably presented on the bit line 40 and the reference bit line 50, such that the external data read circuit can accurately read the data presented on the bit line 40 and the reference bit line 50.

5 **[0044]** In the foregoing embodiment, the controlled power supply module controls rates at which the amplification module pulls the voltage of the bit line 40 and the voltage of the reference bit line 50, such that the pull rates of the voltage of the bit line 40 and the voltage of the reference bit line 50 are within a rated pull rate range, and the data stored in the memory cell has been stably
10 presented on the bit line 40 and the reference bit line 50 when the external read circuit reads the data presented on the bit line 40 and the reference bit line 50, thereby further improving a data read success rate and data read accuracy.

[0045] As shown in FIG. 5, another embodiment of the present application
15 provides a sense amplifier 10, the sense amplifier 10 includes an amplification module 101 and a controlled power supply module 102, and the amplification module 101 is connected to the controlled power supply module 102.

[0046] The controlled power supply module 102 includes a first controlled power supply unit 1021, a second controlled power supply unit 1022, and a
20 control unit 1025. The amplification module 101 is provided with a first terminal, a second terminal, a third terminal, and a fourth terminal.

[0047] An output terminal of the first controlled power supply unit 1021 is connected to the first terminal of the amplification module 101, an output terminal of the second controlled power supply unit 1022 is connected to the
25 second terminal of the amplification module 101, the third terminal of the amplification module 101 is connected to a bit line, and the fourth terminal of the amplification module is connected to a reference bit line. The control unit 1025 is connected to a control terminal of the first controlled power supply unit 1021, and the control unit 1025 is further connected to a control terminal of the
30 second controlled power supply unit 1022.

[0048] Both the first controlled power supply unit 1021 and the second controlled power supply unit 1022 are configured to supply power to the amplification module 101. The control unit 1025 is configured to determine a drive parameter according to a first rated pull rate and a second rated pull rate,
5 and control, according to a drive parameter, a first controlled current source 1023 and a second controlled current source 1024 to supply power to the amplification module 101.

[0049] Under control of the first controlled power supply unit 1021 and the second controlled power supply unit 1022, the amplification module 101 pulls a
10 voltage of the bit line 40 or a voltage of the reference bit line 50 to a first preset value at a first rated pull rate and pulls the voltage of the reference bit line 50 or the voltage of the bit line 40 to a second preset value at a second rated pull rate at an amplification stage.

[0050] For ease of description, it is specified herein that a voltage provided
15 by the first controlled power supply unit 1021 is higher than a voltage provided by the second controlled power supply unit 1022, and data "1" is presented when the voltage of the bit line 40 is higher than the voltage of the reference bit line 50.

[0051] When data stored in a memory cell 21 is "1", the first controlled
20 power supply unit 1021 controls the amplification module 101 to pull the voltage of the bit line 40 to the first preset value at the first rated pull rate, and the second controlled power supply unit 1022 controls the amplification module 101 to pull the voltage of the reference bit line 50 to the second preset value at the second rated pull rate. When data stored in a memory cell 21 is "0", the first
25 controlled power supply unit 1021 controls the amplification module 101 to pull the voltage of the reference bit line 50 to the first preset value at the first rated pull rate, and the second controlled power supply unit 1022 controls the amplification module 101 to pull the voltage of the bit line 40 to the second preset value at the second rated pull rate. The first preset value may be, for
30 example, V_{CC} , and the second preset value may be, for example, 0.

[0052] When the sense amplifier 10 is at the amplification stage, the voltage of the bit line 40 or the voltage of the reference bit line 50 is pulled at a pull rate within the first rated pull rate range, and the voltage of the reference bit line 50 or the voltage of the bit line 40 is pulled at a pull rate within the second rated pull rate range. When the sense amplifier 10 is at a restore stage, the external read circuit reads data presented on the bit line 40 and the reference bit line 50. In this case, the data stored in the memory cell 21 has been stably presented on the bit line 40 and the reference bit line 50, such that the external data read circuit can accurately read the data presented on the bit line 40 and the reference bit line 50.

[0053] In another embodiment, the first controlled power supply unit 1021 includes N first controlled current sources 1023. Each first controlled current source 1023 is provided with a control terminal, a first terminal, and a second terminal. The second terminal of each first controlled current source 1023 is the output terminal of the first controlled power supply unit 1021, and the control terminal of each first controlled current source 1023 is the control terminal of the first controlled power supply unit 1021. The first terminal of the first controlled current source 1023 is connected to a first power supply terminal, the second terminal of the first controlled current source 1023 is connected to the first terminal of the amplification module 101, and the control terminal of the first controlled current source 1023 is connected to the control unit 1025, where N is a positive integer.

[0054] The second controlled power supply unit 1022 includes N second controlled current sources 1024, and the second controlled current source 1024 is provided with a control terminal, a first terminal, and a second terminal. The second terminal of each second controlled current source 1024 is the output terminal of the second controlled power supply unit 1022, and the control terminal of each second controlled current source 1024 is the control terminal of the second controlled power supply unit 1022. The first terminal of the second controlled current source 1024 is connected to a second power

supply terminal, the second terminal of the second controlled current source 1024 is connected to the second terminal of the amplification module 101, and the control terminal of the second controlled current source 1024 is connected to the control unit 1025.

5 **[0055]** For ease of description of work states of the first controlled current source 1023 and the second controlled current source 1024, it is continuously specified herein that when a voltage of the first power supply terminal is higher than a voltage of the second power supply terminal, and the voltage of the bit line 40 is higher than the voltage of the reference bit line 50, it presents data
10 "1".

[0056] When the data stored in the memory cell 21 is "1", the control unit 1025 is configured to: determine a first drive current range according to the first rated pull rate range, and select at least one first target current source in the N first controlled current sources 1023, such that a total current provided by the
15 at least one first target current source is within the first drive current range; and generate a first control signal used to control the first target current source to work, such that the first controlled power supply unit 1021 controls the amplification module 101 to pull the voltage of the bit line 40 to the first preset value at the first rated pull rate at the amplification stage.

20 **[0057]** The control unit 1025 is further configured to: determine a second drive current range according to the second rated pull rate range, and select at least one second target current source in the N second controlled current sources 1024, such that a total current provided by the at least one second target current source is within the second drive current range; and generate a
25 second control signal used to control the second target current source to work, such that the second controlled power supply unit 1022 controls the amplification module 101 to pull the voltage of the reference bit line 50 to the second preset value at the second rated pull rate at the amplification stage.

[0058] When the data stored in the memory cell 21 is "0", the control unit
30 1025 is configured to determine a first drive current range according to the first

rated pull rate range, and select at least one first target current source in the N first controlled current sources 1023, such that a total current provided by the at least one first target current source is within the first drive current range; and generate a third control signal used to control the first target current source to work, such that the first controlled power supply unit 1022 controls the amplification module 101 to pull the voltage of the reference bit line 50 to the first preset value at the first rated pull rate at the amplification stage.

[0059] The control unit 1025 is further configured to: determine a second drive current range according to the second rated pull rate range, and select at least one second target current source in the N second controlled current sources 1024, such that a total current provided by the at least one second target current source is within the second drive current range; and generate a fourth control signal used to control the second target current source to work, such that the second controlled power supply unit 1021 controls the amplification module 101 to pull the voltage of the bit line 40 to the second preset value at the second rated pull rate at the amplification stage.

[0060] In another embodiment, an i^{th} first controlled current source 1023 provides a drive current $2^{i-1} \times I_b$, a j^{th} second controlled current source 1024 provides a drive current $2^{j-1} \times I_b$, and I_b represents a unit current. The N first controlled current sources 1023 may provide $2^N - 1$ levels of drive current, and the N second controlled current sources 1024 may also provide $2^N - 1$ levels of drive current. Rates at which the amplification module 101 pulls the voltage of the bit line 40 and the voltage of the reference bit line 50 can be accurately adjusted by adjusting an amplitude value of the unit current, to pull the voltage of the bit line 40 or the voltage of the reference bit line 50 to the first preset value at the first rated pull rate and pull the voltage of the reference bit line 50 or the voltage of the bit line 40 to the second preset value at the second rated pull rate at the amplification stage.

[0061] In the foregoing embodiment, the first controlled power supply unit controls the amplification module to pull the voltage of the bit line 40 or the

voltage of the reference bit line 50 at the first rated pull rate, and the second controlled power supply unit controls the amplification module to pull the voltage of the reference bit line 50 or the voltage of the bit line 40 at the second rated pull rate, such that data stored in the memory cell has been stably presented on the bit line 40 and the reference bit line 50 when the external read circuit reads the data presented on the bit line 40 and the reference bit line 50 at the restore stage, and the external data read circuit can accurately read the data presented on the bit line 40 and the reference bit line 50.

[0062] As shown in FIG. 6, an embodiment of the present application provides a sense amplifier 10, the sense amplifier 10 includes an amplification module 101 and a controlled power supply module 102, and the amplification module 101 is connected to the controlled power supply module 102.

[0063] The amplification module 101 includes at least one cross-coupled amplifier circuit, each cross-coupled amplifier circuit is provided with a first terminal, a second terminal, a third terminal, and a fourth terminal, the first terminal of the cross-coupled amplifier circuit is connected to an output terminal of a first controlled power supply unit 1021, the second terminal of the cross-coupled amplifier circuit is connected to an output terminal of the second controlled power supply unit 1022, the third terminal of the cross-coupled amplifier circuit is connected to a bit line 40, and the fourth terminal of the cross-coupled amplifier circuit is connected to a reference bit line 50.

[0064] The cross-coupled amplifier circuit includes: a first transistor T1, a second transistor T2, a third transistor T3, and a fourth transistor T4.

[0065] A first terminal of the first transistor T1 is the first terminal of the cross-coupled amplifier circuit, a second terminal of the second transistor T2 is the second terminal of the cross-coupled amplifier circuit, a second terminal of the first transistor T1 is the third terminal of the cross-coupled amplifier circuit, and a second terminal of the third transistor T3 is the fourth terminal of the cross-coupled amplifier circuit.

[0066] The second terminal of the first transistor T1 is connected to a first

terminal of the second transistor T2, the second terminal of the third transistor T3 is connected to a first terminal of the fourth transistor T4, the first terminal of the first transistor T1 is connected to a first terminal of the third transistor T3, and the second terminal of the second transistor T2 is connected to a second terminal of the fourth transistor T4.

[0067] A control terminal of the first transistor T1 is connected to the second terminal of the third transistor T3, a control terminal of the second transistor T2 is connected to the second terminal of the third transistor T3, a control terminal of the third transistor T3 is connected to the second terminal of the first transistor T1, and a control terminal of the fourth transistor T4 is connected to the second terminal of the first transistor T1.

[0068] The first transistor T1 and the third transistor T3 are P-type transistors, and the second transistor T2 and the fourth transistor T4 are N-type transistors.

[0069] The controlled power supply module 102 includes the first controlled power supply unit 1021 and the second controlled power supply unit 1022, the first controlled power supply unit 1021 includes N first controlled current sources 1023, and the second controlled power supply unit 1022 includes N second controlled current sources 1024. The first controlled current source 1023 is a P-type transistor, and the second controlled current source 1024 is an N-type transistor.

[0070] A process of reading data "1" from one memory cell 21 in a first storage array 20 is described below.

[0071] At a precharge stage, both a voltage of the bit line 40 of the first storage array 20 and a voltage of the reference bit line 50 are pulled up to a reference voltage, and the reference voltage may be a voltage $0.5V_{CC}$ of a fixed power supply connected to the storage capacitor C.

[0072] At an access stage, a signal on a word line corresponding to the accessed memory cell 21 is controlled, such that an access transistor T in the accessed memory cell 21 is on, and the storage capacitor C pulls the voltage

of the bit line 40 to rise.

[0073] At an amplification stage, the voltage of the bit line 40 is higher than the reference voltage, such that the first transistor T1 and the fourth transistor T4 are on, and the second transistor T2 and the third transistor T3 are off. If the
5 first transistor T1 is on and the third transistor T3 is off, the first controlled power supply unit 1021 pulls the voltage of the bit line 40 up to a first preset value. In addition, the first controlled power supply unit 1021 includes a plurality of P-type transistors. In this case, a rate at which the first controlled power supply unit 1021 pulls the voltage of the bit line 40 and that is used
10 when the first transistor T1 is on may be controlled by controlling a quantity of P-type transistors in an on state.

[0074] If the second transistor T2 is off and the fourth transistor T4 is on, the second controlled power supply unit 1022 pulls to the voltage of the reference bit line 50 down to a second preset value. In addition, the second
15 controlled power supply unit 1022 includes a plurality of N-type transistors. In this case, a rate at which the second controlled power supply unit 1022 pulls the voltage of the reference bit line 50 and that is used when the fourth transistor T4 is off may be controlled by controlling a quantity of N-type transistors in an on state.

[0075] The quantity of P-type transistors in the on state in the first controlled power supply unit 1021 and the quantity of N-type transistors in the on state in the second controlled power supply unit 1022 are controlled, such that the voltage of the bit line 40 is pulled to the first preset value at a first rated pull rate and the voltage of the reference bit line 50 is pulled to the second preset value
25 at a second rated pull rate, and a voltage difference between the bit line 40 and the reference bit line 50 can stably reflect that data in the accessed memory cell 21 is "1".

[0076] At the restore stage, the sense amplifier 10 has stabilized the voltage of the bit line 40 and the voltage of the reference bit line 50 at logical
30 data "1", the bit line 40 charges the storage capacitor C, and after a specific

time of charging, charge in the storage capacitor C is restored to a state before the read operation. Then, a signal inside a line is selected through a control column, such that an external read circuit may read the data stored in the accessed memory cell 21 on the bit line 40 and the reference bit line 50.

5 **[0077]** In another embodiment, an j^{th} P-type transistor in the first controlled power supply unit 1021 may provide a drive current $2^{j-1} \times I_b$, a j^{th} N-type transistor in the second controlled power supply unit 1022 may provide a drive current $2^{j-1} \times I_b$, and I_b represents a unit current. The first controlled power supply unit 1021 may provide $2^N - 1$ levels of drive current, and the second
10 controlled power supply unit 1022 may also provide $2^N - 1$ levels of drive current, such that the controlled power supply module 102 can provide $2^N - 1$ levels of drive current.

[0078] A level of a drive current that may be provided by the controlled power supply module 102 is described by using an example below. The first
15 controlled power supply unit 1021 includes three P-type transistors. A drive current that may be provided by the 1st P-type transistor is I_b , a drive current that may be provided by the 2nd P-type transistor is $2I_b$, and a drive current that may be provided by the 3rd P-type transistor is $4I_b$. The second controlled power supply unit 1022 includes three N-type transistors. A drive current that
20 may be provided by the 1st N-type transistor is I_b , a drive current that may be provided by the 2nd N-type transistor is $2I_b$, and a drive current that may be provided by the 3rd N-type transistor is $4I_b$.

[0079] The controlled power supply module 102 may provide 7 levels of drive current. Control signals of N-type transistors and P-type transistors at
25 each level are shown in Table 1 and Table 2. "1" represents a high level control signal and "0" represents a low level control signal.

Table 1 Control signal of an N-type transistor

3 rd transistor	N-type	2 nd transistor	N-type	1 st transistor	N-type	Level of a drive current
-------------------------------	--------	-------------------------------	--------	-------------------------------	--------	-----------------------------

0	0	1	I_b
0	1	0	$2I_b$
0	1	1	$3I_b$
1	0	0	$4I_b$
1	0	1	$5I_b$
1	1	0	$6I_b$
1	1	1	$7I_b$

Table 2 Control signal of a P-type transistor

3 rd P-type transistor	2 nd P-type transistor	1 st P-type transistor	Level of a drive current
1	1	0	I_b
1	0	1	$2I_b$
1	0	0	$3I_b$
0	1	1	$4I_b$
0	1	0	$5I_b$
0	0	1	$6I_b$
0	0	0	$7I_b$

[0080] In the foregoing technical solution, the quantity of P-type transistors in the on state and the quantity of N-type transistors in the on state are controlled, to control the controlled power supply module to provide a level of a drive current to the amplification module, so as to control rates at which the amplification module pulls the voltage of the bit line 40 and the voltage of the reference bit line 50 to be in a rated range, such that the bit line 40 and the reference bit line 50 can stably present the data stored in the memory cell at the restore stage, thereby improving data read accuracy and a data read success rate.

[0081] As shown in FIG. 7, an embodiment of the present application provides a sense amplifier 10, the sense amplifier 10 includes an amplification

module 101 and a controlled power supply module 102, and the amplification module 101 is connected to the controlled power supply module 102.

[0082] The amplification module 101 includes at least one cross-coupled amplifier circuit, each cross-coupled amplifier circuit is provided with a first terminal, a second terminal, a third terminal, and a fourth terminal, the first terminal of the cross-coupled amplifier circuit is connected to an output terminal of a first controlled power supply unit 1021, the second terminal of the cross-coupled amplifier circuit is connected to an output terminal of the second controlled power supply unit 1022, the third terminal of the cross-coupled amplifier circuit is connected to a bit line 40, and the fourth terminal of the cross-coupled amplifier circuit is connected to a reference bit line 50.

[0083] The cross-coupled amplifier circuit has an offset elimination function, and the cross-coupled amplifier circuit specifically includes: a fifth transistor T5, a sixth transistor T6, a seventh transistor T7, an eighth transistor T8, a first switch K1, a second switch K2, a third switch K3, and a fourth switch K4.

[0084] A first terminal of the fifth transistor T5 is the first terminal of the cross-coupled amplifier circuit, a second terminal of the sixth transistor T6 is the second terminal of the cross-coupled amplifier circuit, a second terminal of the fifth transistor T5 is the third terminal of the cross-coupled amplifier circuit, and a second terminal of the seventh transistor T7 is the fourth terminal of the cross-coupled amplifier circuit.

[0085] The second terminal of the fifth transistor T5 is connected to a first terminal of the sixth transistor T6, the second terminal of the seventh transistor T7 is connected to a first terminal of the eighth transistor T8, the first terminal of the fifth transistor T5 is connected to a first terminal of the seventh transistor T7, and the second terminal of the sixth transistor T6 is connected to a second terminal of the eighth transistor T8.

[0086] A control terminal of the fifth transistor T5 is connected to the second terminal of the seventh transistor T7, a control terminal of the sixth transistor T6 is connected to the second terminal of the seventh transistor T7 through the

first switch K1, and the control terminal of the sixth transistor T6 is connected to the first terminal of the sixth transistor T6 through the third switch K3.

[0087] A control terminal of the seventh transistor T7 is connected to the second terminal of the fifth transistor T5, a control terminal of the eighth transistor T8 is connected to the second terminal of the fifth transistor T5 through the second switch K2, and the control terminal of the eighth transistor T8 is connected to the first terminal of the eighth transistor T8 through the fourth switch K4.

[0088] The fifth transistor T5 and the seventh transistor T7 are P-type transistors, and the sixth transistor T6 and the eighth transistor T8 are N-type transistors.

[0089] The controlled power supply module 102 includes the first controlled power supply unit 1021 and the second controlled power supply unit 1022, the first controlled power supply unit 1021 includes N first controlled current sources 1023, and the second controlled power supply unit 1022 includes N second controlled current sources 1024. The first controlled current source 1023 is a P-type transistor, and the second controlled current source 1024 is a P-type transistor.

[0090] Different from that in the embodiment shown in FIG. 6, a data read process of the sense amplifier provided in this embodiment further includes an offset elimination stage. For ease of description, a connection line between the second terminal of the fifth transistor T5 and the first terminal of the sixth transistor T6 is referred to as an internal bit line 70 of a first storage array 20, and a connection line between the second terminal of the seventh transistor T7 and the first terminal of the eighth transistor T8 is referred to as an internal reference bit line 60 of the first storage array 20.

[0091] A process of reading data "1" from one memory cell 21 in the first storage array 20 is described below. As shown in FIG. 8, reading data includes an idle stage, an offset elimination stage, a precharge stage, an access stage, an amplification stage, and a restore stage.

[0092] At the idle stage, the third switch K3 and the fourth switch K4 are closed, and the first switch K1 and the second switch K2 are also closed. The first terminal of the sixth transistor T6 is short circuited to the control terminal, and the first terminal of the eighth transistor T8 is short circuited to the control terminal. The charge switches CK1 and CK2 are closed, and the internal bit line 70 and the internal reference bit line 60 are charged through a charge power supply. In this case, in an embodiment, the bit line 40, the reference bit line 50, the internal bit line 70, and the internal reference bit line 60 are all charged to $0.5V_{CC}$.

[0093] At the offset elimination stage, the first switch K1 and the second switch K2 are disconnected, and the third switch K3 and the fourth switch K4 are still closed. At least one N-type transistor of N11, N12, N13 is controlled according to a waveform in the figure, and at least one N-type transistor of N21, N22, N23 is controlled according to a waveform in the figure, such that the first controlled power supply unit 1021 and the second controlled power supply unit 1022 supply power to the cross-coupled amplifier circuit. In addition, the sixth transistor T6 is connected to the eighth transistor T8 through a diode. A compensation voltage occurs on the bit line 40 and the reference bit line 50, and the compensation voltage may eliminate a manufacturing difference in the N-type transistor or the P-type transistor (which may be referred to as an offset voltage). For example, the voltage on the bit line 40 minus the voltage on the reference bit line 50 equals the offset voltage, or the voltage on the reference bit line 50 minus the voltage on the bit line 40 equals the offset voltage.

[0094] At the precharge stage, the first switch K1 to the fourth switch K4 are all disconnected. Both a voltage of the internal bit line 70 of the first storage array 20 and a voltage of the internal reference bit line 60 are pulled up to a reference voltage, and the reference voltage is a voltage of a fixed power supply connected to the storage capacitor C. In an embodiment, the voltage of the fixed power supply is $0.5V_{CC}$.

[0095] At the access stage, the first switch K1 and the second switch K2

are closed, the third switch K3 and the fourth switch K4 are still disconnected, and the compensation voltage is still reserved on the bit line 40 and the reference bit line 50. For example, at the offset elimination stage, the voltage on the bit line 40 is higher than the voltage of the reference bit line 50, and a difference is a compensation voltage V_{os} . At the access stage, the voltage on the bit line 40 is still higher than the voltage of the reference bit line 50, and a difference is also the compensation voltage V_{os} . If an offset between threshold voltages of T6 and T8 is V_{os} , an offset between threshold voltages of T5 and T7 is V_{os} , or an offset between threshold voltages that occur on T6 and T5 together with T8 and T7 is V_{os} , at the access stage, impact of V_{os} on the sense amplifier is eliminated or at least weakened.

[0096] At the access stage, a signal on a word line corresponding to the accessed memory cell 21 is controlled, such that an access transistor T in the accessed memory cell 21 is on, and the storage capacitor C enables the voltage of the bit line 40 to rise.

[0097] Cases at the amplification stage and the restore stage are the same as those in the embodiment shown in FIG. 6, and details are not described herein again.

[0098] In the foregoing technical solution, a quantity of transistors in an on state is controlled, to control the controlled power supply module to provide a level of a drive current to the amplification module, so as to control rates at which the amplification module pulls the voltage of the bit line 40 and the voltage of the reference bit line 50 to be in a rated range, such that the bit line 40 and the reference bit line 50 can stably present the data stored in the memory cell at the restore stage, thereby improving data read accuracy and a data read success rate.

[0099] As shown in FIG. 9, the present application provides a control method of a sense amplifier. A structure of the sense amplifier has been described in detail in the foregoing embodiment, and details are not described herein again. The control method specifically includes the following step.

[0100] S1001. Obtain a preset first rated pull rate range and a preset second rated pull rate range.

[0101] The first rated pull rate range and the second rated pull rate range are determined according to a time sequence of selected signals on a column selection line, a time sequence of signals on a word line connected to the memory cell, and voltages of a bit line and a reference bit line. The first rated pull rate range and the second rated pull rate range may be further obtained by testing the sense amplifier, to ensure that data on the bit line and the reference bit line can be accurately read.

[0102] S1002. Determine a drive parameter of a controlled power supply module according to the first rated pull rate range and the second rated pull rate range.

[0103] The sense amplifier is tested, to obtain a mapping relationship between pull rates at which the sense amplifier pulls a voltage of the bit line and a voltage of the reference bit line and a drive parameter of the controlled power supply module, and then the drive parameter of the controlled power supply module is determined according to the mapping relationship and the two rated pull rate ranges.

[0104] S1003. Generate, according to the drive parameter, a control signal used to control the controlled power supply module.

[0105] After the drive parameter of the controlled power supply module is obtained, the control signal is generated according to the drive parameter, to control the controlled power supply module to supply power to an amplification module according to the drive parameter, and further control the controlled power supply module to control the amplification module to pull the voltage of the bit line or the voltage of the reference bit line to a first preset value at a first rated pull rate and pull the voltage of the reference bit line or the voltage of the bit line to a second preset value at a second rated pull rate at an amplification stage. The first rated pull rate is within the first rated pull rate range, and the second rated pull rate is within the second rated pull rate range.

[0106] In the control method provided in this embodiment of the present application, the drive parameter output by the controlled power supply module is controlled, to control rates at which the amplification module pulls the voltage of the bit line and the voltage of the reference bit line, such that the pull rates of the voltage of the bit line and the voltage of the reference bit line are within a rated pull rate range, and the data stored in the memory cell has been stably presented on the bit line and the reference bit line when the external read circuit reads the data presented on the bit line and the reference bit line, thereby further improving a data read success rate and data read accuracy.

[0107] Another embodiment of the present application provides a control method of a sense amplifier. The control method specifically includes the following step.

[0108] S2001. Obtain a preset first rated pull rate range and a preset second rated pull rate range.

[0109] The step has been described in detail in the foregoing embodiment, and details are not described herein again.

[0110] S2002. Determine a drive parameter of a controlled power supply module according to the first rated pull rate range and the second rated pull rate range.

[0111] A first drive current range is determined according to the first rated pull rate range, and a second drive current range is determined according to the second rated pull rate range. The first drive current range is a drive parameter of a first controlled current source, and the second drive current range is a drive parameter of a second controlled current source.

[0112] S2003. Generate, according to the drive parameter, a control signal used to control the controlled power supply module.

[0113] For ease of description of work states of the first controlled current source and the second controlled current source, it is continuously specified herein that when a voltage of a first power supply terminal is higher than a voltage of a second power supply terminal, and a voltage of a bit line is higher

than a voltage of a reference bit line, it presents data "1".

[0114] When the data stored in the memory cell is "1", at least one first target current source is selected in N first controlled current sources, such that a total current provided by the at least one first target current source is within the first drive current range; and a first control signal used to control the first target current source to work is generated, such that a first controlled power supply unit controls an amplification module to pull the voltage of the bit line to a first preset value at a first rated pull rate at an amplification stage.

[0115] At least one second target current source is selected in N second controlled current sources, such that a total current provided by the at least one second target current source is within the second drive current range; and a second control signal used to control the second target current source to work is generated, such that a second controlled power supply unit controls the amplification module to pull the voltage of the reference bit line to a second preset value at a second rated pull rate at the amplification stage.

[0116] When the data stored in the memory cell 21 is "0", at least one first target current source is selected in N first controlled current sources, such that a total current provided by the at least one first target current source is within the first drive current range; and a third control signal used to control the first target current source to work is generated, such that a first controlled power supply unit controls an amplification module to pull the voltage of the reference bit line to a first preset value at a first rated pull rate at an amplification stage.

[0117] At least one second target current source is selected in N second controlled current sources, such that a total current provided by the at least one second target current source is within the second drive current range; and a fourth control signal used to control the second target current source to work is generated, such that a second controlled power supply unit controls the amplification module to pull the voltage of the bit line to a second preset value at a second rated pull rate at the amplification stage.

[0118] In the foregoing embodiment, the first controlled power supply unit

controls the amplification module to pull the voltage of the bit line or the voltage of the reference bit line at the first rated pull rate, and the second controlled power supply unit controls the amplification module to pull the voltage of the reference bit line or the voltage of the bit line at the second rated pull rate, such that data stored in the memory cell has been stably presented on the bit line and the reference bit line when an external read circuit reads the data presented on the bit line and the reference bit line at a restore stage, and the external data read circuit can accurately read the data presented on the bit line and the reference bit line.

10 **[0119]** Finally, it should be noted that the above embodiments are merely used to explain the technical solutions of the present application, but are not intended to limit the present application. Although the present application is described in detail with reference to the foregoing embodiments, those of ordinary skill in the art should understand that they can still modify the technical solutions described in the foregoing embodiments, or make equivalent substitutions on some or all technical features therein. These modifications or substitutions do not make the essence of the corresponding technical solutions deviate from the technical solutions of the embodiments of the present application.

CLAIMS

1. A sense amplifier, comprising:

an amplification module, configured to: when the sense amplifier is at an amplification stage, amplify a voltage difference between a bit line and a reference bit line; and

a controlled power supply module, connected to the amplification module, and configured to: determine a drive parameter according to a first rated pull rate range and a second rated pull rate range, and supply power to the amplification module according to the drive parameter, to control the amplification module to pull a voltage of the bit line or a voltage of the reference bit line to a first preset value at a first rated pull rate at the amplification stage and pull the voltage of the reference bit line or the voltage of the bit line to a second preset value at a second rated pull rate at the amplification stage, wherein

the first rated pull rate is within the first rated pull rate range, and the second rated pull rate is within the second rated pull rate range;

wherein the controlled power supply module comprises:

a first controlled power supply unit, connected to a first terminal of the amplification module, and configured to supply power to the amplification module;

a second controlled power supply unit, connected to a second terminal of the amplification module, and configured to supply power to the amplification module; and

a control unit, connected to the first controlled power supply unit, further connected to the second controlled power supply unit, and configured to: determine the drive parameter according to the first rated pull rate range and the second rated pull rate range, and control, according to the drive parameter, one or more first controlled current sources and one or more second controlled current sources to supply power to the amplification module;

wherein the first controlled power supply unit comprises:

N first controlled current sources, wherein each of the first controlled current sources is provided with a control terminal, a first terminal, and a second terminal, the first terminal of the first controlled current source is connected to a first power supply terminal, the second terminal of the first controlled current source is connected to the first terminal of the amplification module, and the control terminal of the first controlled current source is connected to the control unit, wherein N is a positive integer;

wherein the second controlled power supply unit comprises:

N second controlled current sources, wherein each of the second controlled current sources is provided with a control terminal, a first terminal, and a second terminal, the first terminal of the second controlled current source is connected to a second power supply terminal, the second terminal of the second controlled current source is connected to the second terminal of the amplification module, and the control terminal of the second controlled current source is connected to the control unit;

wherein the control unit is configured to:

determine a first drive current range according to the first rated pull rate range, and determine a second drive current range according to the second rated pull rate range;

select at least one first target current source in the N first controlled current sources, and select at least one second target current source in the N second controlled current sources, wherein a total current provided by the at least one first target current source is within the first drive current range, and a total current provided by the at least one second target current source is within the second drive current range; and

generate a first control signal used to control the first target current source to work, and generate a second control signal used to control the second target current source to work, such that the first controlled power supply unit controls the amplification module to pull the voltage of the bit line to the first

preset value at the first rated pull rate at the amplification stage, and the second controlled power supply unit controls the amplification module to pull the voltage of the reference bit line to the second preset value at the second rated pull rate at the amplification stage; or,

5 wherein the control unit is configured to:

determine a first drive current range according to the first rated pull rate range, and determine a second drive current range according to the second rated pull rate range;

10 select at least one first target current source in the N first controlled current sources, and select at least one second target current source in the N second controlled current sources, wherein a total current provided by the at least one first target current source is within the second drive current range, and a total current provided by the at least one second target current source is within the first drive current range; and

15 generate a third control signal used to control the first target current source to work, and generate a fourth control signal used to control the second target current source to work, such that the first controlled power supply unit controls the amplification module to pull the voltage of the reference bit line to the first preset value at the first rated pull rate at the amplification stage, and
20 the second controlled power supply unit controls the amplification module to pull the voltage of the bit line to the second preset value at the second rated pull rate at the amplification stage.

2. The sense amplifier according to claim 1, wherein a drive current provided by an i^{th} first controlled current source is $2^{i-1} \times I_b$, a drive current
25 provided by a j^{th} second controlled current source is $2^{j-1} \times I_b$, and I_b represents a unit current.

3. The sense amplifier according to claim 1, wherein

each of the first controlled current sources is a P-type transistor, and each of the second controlled current sources is an N-type transistor; or

30 each of the first controlled current sources and each of the second

controlled current sources are both N-type transistors.

4. The sense amplifier according to claim 1, wherein the amplification module comprises:

at least one cross-coupled amplifier circuit, wherein the cross-coupled
5 amplifier circuit is provided with a first terminal, a second terminal, a third
terminal, and a fourth terminal, the first terminal of the cross-coupled amplifier
circuit is connected to an output terminal of the first controlled power supply
unit, the second terminal of the cross-coupled amplifier circuit is connected to
an output terminal of the second controlled power supply unit, the third terminal
10 of the cross-coupled amplifier circuit is connected to the bit line, and the fourth
terminal of the cross-coupled amplifier circuit is connected to the reference bit
line.

5. The sense amplifier according to claim 4, wherein the cross-coupled
amplifier circuit comprises: a first transistor, a second transistor, a third
15 transistor, and a fourth transistor;

a first terminal of the first transistor is the first terminal of the
cross-coupled amplifier circuit, a second terminal of the second transistor is
the second terminal of the cross-coupled amplifier circuit, a second terminal of
the first transistor is the third terminal of the cross-coupled amplifier circuit, and
20 a second terminal of the third transistor is the fourth terminal of the
cross-coupled amplifier circuit;

the second terminal of the first transistor is connected to a first terminal of
the second transistor, the second terminal of the third transistor is connected to
a first terminal of the fourth transistor, the first terminal of the first transistor is
25 connected to a first terminal of the third transistor, and the second terminal of
the second transistor is connected to a second terminal of the fourth transistor;
and

a control terminal of the first transistor is connected to the second terminal
of the third transistor, a control terminal of the second transistor is connected to
30 the second terminal of the third transistor, a control terminal of the third

transistor is connected to the second terminal of the first transistor, and a control terminal of the fourth transistor is connected to the second terminal of the first transistor.

6. The sense amplifier according to claim 4, wherein the cross-coupled amplifier circuit comprises: a fifth transistor, a sixth transistor, a seventh transistor, an eighth transistor, a first switch, a second switch, a third switch, and a fourth switch;

a first terminal of the fifth transistor is the first terminal of the cross-coupled amplifier circuit, a second terminal of the sixth transistor is the second terminal of the cross-coupled amplifier circuit, a second terminal of the fifth transistor is the third terminal of the cross-coupled amplifier circuit, and a second terminal of the seventh transistor is the fourth terminal of the cross-coupled amplifier circuit;

the second terminal of the fifth transistor is connected to a first terminal of the sixth transistor, the second terminal of the seventh transistor is connected to a first terminal of the eighth transistor, the first terminal of the fifth transistor is connected to a first terminal of the seventh transistor, and the second terminal of the sixth transistor is connected to a second terminal of the eighth transistor;

a control terminal of the fifth transistor is connected to the second terminal of the seventh transistor, a control terminal of the sixth transistor is connected to the second terminal of the seventh transistor through the first switch, and the control terminal of the sixth transistor is connected to the first terminal of the sixth transistor through the third switch; and

a control terminal of the seventh transistor is connected to the second terminal of the fifth transistor, a control terminal of the eighth transistor is connected to the second terminal of the fifth transistor through the second switch, and the control terminal of the eighth transistor is connected to the first terminal of the eighth transistor through the fourth switch.

7. A memory, comprising the sense amplifier according to any one of

claims 1 to 2 and memory cells, wherein

a plurality of memory cells constitute a first storage array, a plurality of memory cells constitute a second storage array, the sense amplifier is located between the first storage array and the second storage array, a third terminal
5 of the sense amplifier is connected to a bit line of the first storage array, and a fourth terminal of the sense amplifier is connected to a bit line of the second storage array.

8. A control method of a sense amplifier, wherein the sense amplifier comprises an amplification module and a controlled power supply module; and
10 the method comprises:

obtaining a first rated pull rate range and a second rated pull rate range;

determining a drive parameter of the controlled power supply module according to the first rated pull rate range and the second rated pull rate range; and

15 generating, according to the drive parameter, a control signal used to control the controlled power supply module, such that the controlled power supply module controls the amplification module to pull a voltage of a bit line or a voltage of a reference bit line to a first preset value at a first rated pull rate at an amplification stage and pull the voltage of the reference bit line or the
20 voltage of the bit line to a second preset value at a second rated pull rate at an amplification stage, wherein

the first rated pull rate is within the first rated pull rate range, and the second rated pull rate is within the second rated pull rate range;

wherein the controlled power supply module comprises a first controlled
25 power supply unit and a second controlled power supply unit, the first controlled power supply unit comprises N first controlled current sources, and the second controlled power supply unit comprises N second controlled current sources; and

the determining a drive parameter of the controlled power supply module
30 according to the first rated pull rate range and the second rated pull rate range

comprises:

determining a first drive current range according to the first rated pull rate range, and determining a second drive current range according to the second rated pull rate range;

5 wherein the generating, according to the drive parameter, a control signal used to control the controlled power supply module comprises:

selecting at least one first target current source in the N first controlled current sources, and selecting at least one second target current source in the N second controlled current sources, wherein a total current provided by the at least one first target current source is within the first drive current range, and a
10 total current provided by the at least one second target current source is within the second drive current range; and

generating a first control signal used to control the first target current source to work, and generating a second control signal used to control the second target current source to work, such that the first controlled power supply unit controls the amplification module to pull the voltage of the bit line to the first preset value at the first rated pull rate at the amplification stage, and
15 the second controlled power supply unit controls the amplification module to pull the voltage of the reference bit line to the second preset value at the second rated pull rate at the amplification stage; or,
20 wherein the generating, according to the drive parameter, a control signal used to control the controlled power supply module comprises:

selecting at least one first target current source in the N first controlled current sources, and selecting at least one second target current source in the N second controlled current sources, wherein a total current provided by the at least one first target current source is within the first drive current range, and a
25 total current provided by the at least one second target current source is within the second drive current range; and

generating a third control signal used to control the first target current source to work, and generating a fourth control signal used to control the
30 source to work, and generating a fourth control signal used to control the

second target current source to work, such that the first controlled power supply unit controls the amplification module to pull the voltage of the reference bit line to the first preset value at the first rated pull rate at the amplification stage, and the second controlled power supply unit controls the

5 amplification module to pull the voltage of the bit line to the second preset value at the second rated pull rate at the amplification stage.