

HIERARCHICAL LOSSLESS ENCODING AND DECODING METHOD,
HIERARCHICAL LOSSLESS ENCODING METHOD,
HIERARCHICAL LOSSLESS DECODING METHOD,
APPARATUS AND PROGRAM THEREFOR

5

TECHNICAL FIELD

The present invention relates to a hierarchical lossless encoding and decoding technology for digital signals such as of music data, audio data, or the like.

10

BACKGROUND ART

One process for lossless encoding of audio signals such as music signals is a hierarchical lossless encoding process. Data encoded by the hierarchical lossless encoding process is characterized in that it includes
15 low-bit-rate non-lossless encoded data hierarchically as part thereof. A summary of the hierarchical lossless encoding process is described in IEEE Signal Processing Magazine, pp. 21 - 32, July 2001. The conventional hierarchical lossless encoding and decoding technology will briefly be described below with reference to Figs. 1 and 2 of the accompanying
20 drawings which show a conventional hierarchical lossless encoding apparatus and a conventional hierarchical lossless decoding apparatus, respectively.

In the conventional hierarchical lossless encoding apparatus shown in Fig. 1, an input signal from input terminal 100 is supplied to low-bit-rate
25 encoder 101 and delay compensator 102. The input signal supplied to low-bit-rate encoder 101 is encoded thereby and is output as low-bit-rate

encoded data to output terminal 105 and low-bit-rate decoder 103. Low-bit-rate decoder 103 decodes the supplied low-bit-rate encoded data into a low-bit-rate decoded signal. The input signal supplied to delay compensator 102 is delayed by a time corresponding to a delay caused by the low-bit-rate
5 encoding and decoding process (a processing time required by low-bit-rate encoder 101 and low-bit-rate decoder 103), and thereafter output as a delayed input signal. Lossless encoder 104 encodes a differential signal, which is produced by subtracting the low-bit-rate decoded signal from the delayed input signal, according to a lossless encoding process, and outputs
10 lossless encoded data to output terminal 106.

In the conventional hierarchical lossless decoding apparatus shown in Fig. 2, low-bit-rate encoded data from input terminal 200 is decoded into a low-bit-rate decoded signal by low-bit-rate decoder 201. Lossless encoded data from input terminal 202 is decoded into a differential signal by lossless
15 decoder 203. The low-bit-rate decoded signal is output to output terminal 204, and added to the differential signal from lossless decoder 203, producing a sum signal that is output as a lossless reproduced signal to output terminal 205. The lossless reproduced signal is the same as the input signal insofar as the low-bit-rate decoded signal in the decoding apparatus is
20 identical to the low-bit-rate decoded signal in the encoding apparatus.

The low-bit-rate encoding and decoding process may be a transform encoding and decoding process or a CELP (Code Excited Linear Prediction) encoding and decoding process. The transform encoding and decoding process will not be described in detail below as reference can be made to
25 Proceedings on ICASSP, pp. 1093 - 1096, Apr. 1990 for details of the transform encoding and decoding process. The CELP encoding and

decoding process will not be described in detail below as reference can be made to Proceedings on ICASSP, pp. 937 - 940, Mar. 1985 for details of the CELP encoding and decoding process. The lossless encoding and decoding process will not be described in detail below as reference can be made to
5 IEEE Signal Processing Magazine, pp. 21 - 32, July 2001 for details of the lossless encoding and decoding process.

The conventional hierarchical lossless encoding and decoding process is problematic in that if the low-bit-rate decoded signal in the decoding apparatus is not identical to the low-bit-rate decoded signal in the
10 encoding apparatus, then the lossless reproduced signal is not the same as the input signal. This problem occurs primarily when the processing accuracy in the low-bit-rate decoder in the encoding apparatus and the processing accuracy in the low-bit-rate decoder in the decoding apparatus are different from each other. For example, if international standards
15 ISO/IEC 13818-7 (generally known as MPEG-2 AAC) for audio data encoding are used as the low-bit-rate encoding and decoding process, then the processing accuracy in the low-bit-rate decoder is allowed to be of such a level that the decoded signal produced thereby has a decoding error of ± 1 at maximum with respect to a reference decoded signal. Therefore, each of
20 the low-bit-rate decoded signals in the encoding apparatus and the decoding apparatus may possibly have a decoding error of ± 1 at maximum with respect to the reference decoded signal, and hence the total error of the low-bit-rate decoded signals in the encoding apparatus and the decoding apparatus may possibly reach ± 2 at maximum. As a result, it is possible
25 that the lossless reproduced signal derived from the low-bit-rate decoded signal may not be identical to the input signal.

DISCLOSURE OF THE INVENTION

It is an object of example embodiments of the present invention to make a lossless reproduced signal identical to an input signal even when the processing accuracy in a low-bit-rate decoder in an encoding apparatus and the processing accuracy in a low-bit-rate decoder in a decoding apparatus are different from each other.

In accordance with one aspect of the present invention, there is provided a hierarchical lossless encoding and decoding method comprising the steps of: in an encoding apparatus, encoding an input signal into low-bit-rate encoded data and transmitting the low-bit-rate encoded data to a decoding apparatus; encoding a differential signal between a low-bit-rate decoded signal produced by decoding said low-bit-rate encoded data and said input signal, into lossless encoded data, and transmitting the lossless encoded data to the decoding apparatus; and extracting corrective information from said low-bit-rate decoded signal and transmitting the corrective information to the decoding apparatus; in the decoding apparatus, decoding the low-bit-rate encoded data transmitted from the encoding apparatus into a low-bit-rate decoded signal; decoding the lossless encoded data transmitted from the encoding apparatus into a differential signal; and correcting said low-bit-rate decoded signal based on the corrective information transmitted from said encoding apparatus, and adding the corrected low-bit-rate decoded signal and said differential signal into a lossless reproduced signal.

In a second aspect of the present invention, there is provided a hierarchical lossless encoding and decoding method comprising the steps of: in an encoding apparatus, encoding an input signal into low-bit-rate encoded data and transmitting the low-bit-rate encoded data to a decoding apparatus;

encoding a differential signal between a low-bit-rate decoded signal produced by decoding said low-bit-rate encoded data and said input signal, into lossless encoded data, and transmitting the lossless encoded data to the decoding apparatus; and extracting corrective information from said input signal and transmitting the corrective information to the decoding apparatus; in the decoding apparatus, decoding the low-bit-rate encoded data transmitted from the encoding apparatus into a low-bit-rate decoded signal; decoding the lossless encoded data transmitted from the encoding apparatus into a differential signal; adding said low-bit-rate decoded signal and said differential signal into a lossless reproduced signal; and correcting said lossless reproduced signal based on said corrective information.

In accordance with a third aspect of the present invention, there is provided a hierarchical lossless encoding and decoding method comprising the steps of: in an encoding apparatus, encoding an input signal into low-bit-rate encoded data and transmitting the low-bit-rate encoded data to a decoding apparatus; decoding said low-bit-rate encoded data into a low-bit-rate decoded signal, extracting corrective information from said low-bit-rate decoded signal, and transmitting the corrective information to the decoding apparatus; and encoding a differential signal between a corrected low-bit-rate decoded signal produced by correcting said low-bit-rate decoded signal and said input signal, into lossless encoded data, and transmitting the lossless encoded data to the decoding apparatus; in the decoding apparatus, decoding the low-bit-rate encoded data transmitted from the encoding apparatus into a low-bit-rate decoded signal; decoding the lossless encoded data transmitted from the encoding apparatus into a differential signal; and correcting said low-bit-rate decoded signal based on said corrective information, and adding the corrected low-bit-rate decoded signal to said differential signal.

In a fourth aspect of the present invention, there is provided a hierarchical lossless encoding method comprising the steps of: encoding an input signal into low-bit-rate encoded data; decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; encoding a differential signal between said low-bit-rate decoded signal and said input signal into lossless encoded data; and extracting corrective information from said low-bit-rate decoded signal.

In a fifth aspect of the present invention, there is provided a hierarchical lossless encoding method comprising the steps of: encoding an input signal into low-bit-rate encoded data; decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; encoding a differential signal between said low-bit-rate decoded signal and said input signal into lossless encoded data; and extracting corrective information from said input signal.

In a sixth aspect of the present invention, there is provided a hierarchical lossless encoding method comprising the steps of: encoding an input signal into low-bit-rate encoded data; decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; extracting corrective information from said low-bit-rate decoded signal; and encoding a differential signal between a corrected low-bit-rate decoded signal produced by correcting said low-bit-rate decoded signal and said input signal, into lossless encoded data.

In a seventh aspect of the present invention, there is provided a hierarchical lossless decoding method comprising the steps of: inputting hierarchical lossless encoded data comprising low-bit-rate encoded data, lossless encoded data, and corrective information; decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; decoding said lossless encoded data into a differential signal; and correcting said low-bit-rate

decoded signal based on said corrective information, and thereafter adding the corrected low-bit-rate decoded signal and said differential signal into a lossless reproduced signal.

In an eighth aspect of the present invention, there is provided a hierarchical lossless decoding method comprising the steps of: inputting hierarchical lossless encoded data comprising low-bit-rate encoded data, lossless encoded data, and corrective information; decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; decoding said lossless encoded data into a differential signal; adding said low-bit-rate decoded signal and said differential signal into a lossless reproduced signal; and correcting said lossless reproduced signal based on said corrective information.

In a ninth aspect of the present invention, there is provided a hierarchical lossless encoding and decoding apparatus comprising an encoding apparatus and a decoding apparatus, said encoding apparatus comprising: a low-bit-rate encoder for encoding an input signal into low-bit-rate encoded data and transmitting the low-bit-rate encoded data to the decoding apparatus; a low-bit-rate decoder for decoding said low-bit-rate encoded data into a low-bit-rate decoded signal and outputting the low-bit-rate decoded signal; a lossless encoder for encoding a differential signal between the low-bit-rate decoded signal output from said low-bit-rate decoder and said input signal, into lossless encoded data, and transmitting the lossless encoded data to the decoding apparatus; and a corrective information extractor for extracting corrective information from said low-bit-rate decoded signal and transmitting the corrective information to the decoding apparatus; said decoding apparatus comprising: a low-bit-rate decoder for decoding the low-bit-rate encoded data transmitted from said encoding apparatus into a low-bit-rate decoded signal; a lossless decoder for

decoding the lossless encoded data transmitted from said encoding apparatus into a differential signal; a corrector for correcting said low-bit-rate decoded signal based on the corrective information transmitted from said encoding apparatus; and an adder for adding the low-bit-rate decoded signal corrected by said corrector and said differential signal into a lossless reproduced signal.

In a tenth aspect of the present invention, there is provided a hierarchical lossless encoding and decoding apparatus comprising an encoding apparatus and a decoding apparatus, said encoding apparatus comprising: a low-bit-rate encoder for encoding an input signal into low-bit-rate encoded data and transmitting the low-bit-rate encoded data to the decoding apparatus; a low-bit-rate decoder for decoding said low-bit-rate encoded data into a low-bit-rate decoded signal and outputting the low-bit-rate decoded signal; a lossless encoder for encoding a differential signal between the low-bit-rate decoded signal output from said low-bit-rate decoder and said input signal, into lossless encoded data, and transmitting the lossless encoded data to the decoding apparatus; and a corrective information extractor for extracting corrective information from said input signal and transmitting the corrective information to the decoding apparatus; said decoding apparatus comprising: a low-bit-rate decoder for decoding the low-bit-rate encoded data transmitted from said encoding apparatus into a low-bit-rate decoded signal; a lossless decoder for decoding the lossless encoded data transmitted from said encoding apparatus into a differential signal; an adder for adding said low-bit-rate decoded signal and said differential signal into a lossless reproduced signal; and a corrector for correcting said lossless reproduced signal based on said corrective information.

In an eleventh aspect of the present invention, there is provided a hierarchical lossless encoding and decoding apparatus comprising an encoding apparatus and a decoding apparatus, said encoding apparatus comprising: a low-bit-rate encoder for encoding an input signal into low-bit-rate encoded data and transmitting the low-bit-rate encoded data to the decoding apparatus; a low-bit-rate decoder for decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; a corrective information extractor for extracting corrective information from said low-bit-rate decoded signal and transmitting the corrective information to the decoding apparatus; and a lossless encoder for encoding a differential signal between a corrected low-bit-rate decoded signal produced by correcting the low-bit-rate decoded signal and said input signal, into lossless encoded data, and transmitting the lossless encoded data to the decoding apparatus; and said decoding apparatus comprising: a low-bit-rate decoder for decoding the low-bit-rate encoded data transmitted from said encoding apparatus into a low-bit-rate decoded signal; a lossless decoder for decoding the lossless encoded data transmitted from said encoding apparatus into a differential signal; and a corrector for correcting said low-bit-rate decoded signal based on said corrective information, and adding the corrected low-bit-rate decoded signal to said differential signal.

In a twelfth aspect of the present invention, there is provided a hierarchical lossless encoding apparatus comprising: a low-bit-rate encoder for encoding an input signal into low-bit-rate encoded data; a low-bit-rate decoder for decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; a lossless encoder for encoding a differential signal between the low-bit-rate decoded signal and said input signal, into lossless encoded data; and a corrective information extractor for extracting corrective information from said low-bit-rate decoded signal.

In a thirteenth aspect of the present invention, there is provided a hierarchical lossless encoding apparatus comprising: a low-bit-rate encoder for encoding an input signal into low-bit-rate encoded data; a low-bit-rate decoder for decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; a lossless encoder for encoding a differential signal between the low-bit-rate decoded signal and said input signal, into lossless encoded data; and a corrective information extractor for extracting corrective information from said input signal.

In a fourteenth aspect of the present invention, there is provided a hierarchical lossless encoding apparatus comprising: a low-bit-rate encoder for encoding an input signal into low-bit-rate encoded data; a low-bit-rate decoder for decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; a corrective information extractor for extracting corrective information from said low-bit-rate decoded signal; a corrector for correcting said low-bit-rate decoded signal and outputting the corrected low-bit-rate decoded signal; and a lossless encoder for encoding a differential signal between the corrected low-bit-rate decoded signal and said input signal, into lossless encoded data.

In a fifteenth aspect of the present invention, there is provided a hierarchical lossless decoding apparatus comprising: a low-bit-rate decoder for decoding low-bit-rate encoded data into a low-bit-rate decoded signal; a lossless decoder for decoding lossless encoded data into a differential signal; a corrector for correcting said low-bit-rate decoded signal based on corrective information; and an adder for adding the low-bit-rate decoded signal corrected by said corrector and said differential signal into a lossless reproduced signal.

In a sixteenth aspect of the present invention, there is provided a hierarchical lossless decoding apparatus comprising: a low-bit-rate decoder for decoding low-bit-rate encoded data into a low-bit-rate decoded signal; a lossless decoder for decoding lossless encoded data into a differential signal; an adder for adding said low-bit-rate decoded signal and said differential signal into a lossless reproduced signal; and a corrector for correcting said lossless reproduced signal based on corrective information.

In a seventeenth aspect of the present invention, there is provided a hierarchical lossless encoding apparatus having a program for enabling a computer to perform a process of: encoding an input signal into low-bit-rate encoded data; decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; encoding a differential signal between said low-bit-rate decoded signal and said input signal into lossless encoded data; and extracting corrective information from said low-bit-rate decoded signal.

In an eighteenth aspect of the present invention, there is provided a hierarchical lossless encoding apparatus having a program for enabling a computer to perform a process of: encoding an input signal into low-bit-rate encoded data; decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; encoding a differential signal between said low-bit-rate decoded signal and said input signal into lossless encoded data; and extracting corrective information from said input signal.

In a nineteenth aspect of the present invention, there is provided a hierarchical lossless encoding apparatus having a program for enabling a computer to perform a process of: encoding an input signal into low-bit-rate encoded data; decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; extracting corrective information from said low-bit-rate decoded signal; and encoding a differential signal between a corrected low-

bit-rate decoded signal produced by correcting said low-bit-rate decoded signal and said input signal, into lossless encoded data.

In a twentieth aspect of the present invention, there is provided a hierarchical lossless decoding apparatus having a program for enabling a computer to perform a process of: inputting hierarchical lossless encoded data comprising low-bit-rate encoded data, lossless encoded data, and corrective information; decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; decoding said lossless encoded data into a differential signal; and correcting said low-bit-rate decoded signal based on said corrective information, and thereafter adding the corrected low-bit-rate decoded signal and said differential signal into a lossless reproduced signal.

In a twenty-first aspect of the present invention, there is provided a hierarchical lossless decoding apparatus having a program for enabling a computer to perform a process of: inputting hierarchical lossless encoded data comprising low-bit-rate encoded data, lossless encoded data, and corrective information; decoding said low-bit-rate encoded data into a low-bit-rate decoded signal; decoding said lossless encoded data into a differential signal; adding said low-bit-rate decoded signal and said differential signal into a lossless reproduced signal; and correcting said lossless reproduced signal based on said corrective information.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a block diagram of a conventional hierarchical lossless encoding apparatus;

Fig. 2 is a block diagram of a conventional hierarchical lossless decoding apparatus;

Fig. 3 is a block diagram of a hierarchical lossless encoding apparatus according to a first embodiment of the present invention;

Fig. 4 is a block diagram of a hierarchical lossless decoding apparatus according to the first embodiment of the present invention;

Fig. 5 is a flowchart of a processing sequence of corrector 207;

Fig. 6 is a block diagram of a hierarchical lossless encoding apparatus according to a second embodiment of the present invention;

Fig. 7 is a block diagram of a hierarchical lossless decoding apparatus according to the second embodiment of the present invention;

Fig. 8 is a block diagram of a hierarchical lossless encoding apparatus according to a third embodiment of the present invention;

Fig. 9 is a block diagram of a hierarchical lossless decoding apparatus according to the third embodiment of the present invention; and

Fig. 10 is a flowchart of a processing sequence of corrector 208.

BEST MODE FOR CARRYING OUT THE INVENTION

Embodiments of the present invention will be described in detail below with reference to the drawings. Fig. 3 is a block diagram of hierarchical lossless encoding apparatus 1 according to a first embodiment of the present invention, and Fig. 4 is a block diagram of hierarchical lossless decoding apparatus 2 according to the first embodiment of the present

invention.

As shown in Fig. 3, hierarchical lossless encoding apparatus 1 comprises input terminal 100, low-bit-rate encoder 101, delay compensator 102, low-bit-rate decoder 103, lossless encoder 104, corrective information
 5 extractor 107, adder ADD1, output terminals 105, 106, 108, and recording medium K1. Hierarchical lossless encoding apparatus 1 according to the present embodiment differs from the conventional apparatus shown in Fig. 1 in that corrective information extractor 107, output terminal 108, and recording medium K1 are added to the conventional apparatus. Recording
 10 medium K1 comprises a disk, a semiconductor memory, or another recording medium, and stores a program for enabling a computer to function as hierarchical lossless encoding apparatus 1. The program is read by the computer and controls its operation to realize low-bit-rate encoder 101, delay compensator 102, low-bit-rate decoder 103, lossless encoder 104, corrective
 15 information extractor 107, and adder ADD1 on the computer.

As shown in Fig. 4, hierarchical lossless decoding apparatus 2 comprises input terminals 200, 202, 206, low-bit-rate decoder 201, lossless decoder 203, corrector 207, adder ADD2, output terminals 204, 205, and recording medium K2. Hierarchical lossless decoding apparatus 2 according
 20 to the present embodiment differs from the conventional apparatus shown in Fig. 2 in that corrector 207, input terminal 206, and recording medium K2 added to the conventional apparatus. Recording medium K1 comprises a disk, a semiconductor memory, or another recording medium, and stores a program for enabling a computer to function as hierarchical lossless
 25 decoding apparatus 2. The program is read by the computer and controls its operation to realize low-bit-rate decoder 201, lossless decoder 203, corrector

207, and adder ADD2 on the computer.

Operation of the present embodiment will be described below.

Corrective information extractor 107 in hierarchical lossless encoding apparatus 1 extracts corrective information rx in view of a maximum error of
 5 low-bit-rate decoder 103 from a low-bit-rate decoded signal that has been calculated by low-bit-rate decoder 103 in the same manner as heretofore, and outputs corrective information rx to output terminal 108. Corrective information rx may employ a value represented by low-order M bits of a sampled value of a low-bit-rate decoded signal. If the absolute value of
 10 maximum errors of a low-bit-rate decoded signal in the encoding apparatus and a low-bit-rate decoded signal in the decoding apparatus is represented by E, then M satisfies the following formula:

$$2E + 1 \leq 2^M \quad \dots(1)$$

If the bit width of the sampled value of the low-bit-rate decoded signal
 15 is N bits, then $0 < M < N$. Though the absolute value E of maximum errors is preset in the present embodiment, the absolute value E may be variable depending on the amplitude of the input signal. If the absolute value E is variable, then the setting information of the absolute value needs to be indicated to the decoding apparatus through a transmitting means or a
 20 recording medium. The number M of bits of corrective information rx can be smaller as E is smaller as can be understood from the formula (1).

Therefore, the number of transmitted bits can be reduced by making E variable depending on the amplitude of the input signal and transmitting corrective information rx having the number of bits depending on E to the
 25 decoding apparatus. Low-bit-rate encoded data, lossless encoded data, and corrective information rx that are output from respective output terminals

105, 106, 108 of hierarchical lossless encoding apparatus 1 are inputted respectively to input terminals 200, 202, 206 of hierarchical lossless decoding apparatus 2.

Corrector 207 of hierarchical lossless decoding apparatus 2 corrects a
 5 low-bit-rate decoded signal calculated by low-bit-rate decoder 201 in the same manner as heretofore, based on corrective information rx inputted from input terminal 206, and outputs the corrected low-bit-rate decoded signal. The corrected low-bit-rate decoded signal and a differential signal calculated by lossless decoder in the same manner as heretofore are added to each
 10 other by adder ADD2, and the sum is output as a lossless reproduced signal to output terminal 205. Corrector 207 operates per sample of the low-bit-rate decoded signal. An example of operation of corrector 207 will be described in detail below with reference to a flowchart shown in Fig. 5.

As an initial setting, mt is calculated using the low-order bit number M
 15 according to the following equation (2) (step A1):

$$mt = 2^M \quad \dots(2)$$

Value xhigh represented by high-order (N-M) bits of input value x and value xlow represented by low-order M bits of input value x are calculated according to the following equations (3), (4) (step A2):

$$20 \quad x_{high} = x \ \& \ m_{high} \quad \dots(3)$$

$$x_{low} = x \ \& \ m_{low} \quad \dots(4)$$

where the symbol "&" represents a logical product for bits. mhigh and mlow are mask patterns, and calculated according to the following equations (5), (6):

$$25 \quad m_{high} = -mt \quad \dots(5)$$

$$m_{low} = mt - 1 \quad \dots(6)$$

Value x_{low} of low-order M bits of the low-bit-rate decoded signal output from low-bit-rate decoder 201 and corrective information rx inputted from input terminal 206 are compared with each other to check if the inequality (7) shown below is satisfied or not (step A3). Specifically, in step

5 A3, it is checked whether or not a carry occurs on the low-order $(M+1)$ th bit of the low-bit-rate decoded signal due to an error.

$$x_{low} + E < rx \quad \dots(7)$$

If the inequality (7) is satisfied (Yes in step A3), then it is judged that a carry occurs on the low-order $(M+1)$ th bit due to an error, and output value y

10 is calculated according to the following equation (8) (step A5):

$$y = (x_{high} - mt) | rx \quad \dots(8)$$

where the symbol " $|$ " represents a logical sum for bits. According to the equation (8), the effect of the carry occurring on the low-order $(M+1)$ th bit is eliminated by $x_{high} - mt$, and the low-order M bits are set to rx , making

15 output value y identical to the low-bit-rate decoded signal in the encoding apparatus.

If the inequality (7) is not satisfied (No in step A3), then it is checked whether the inequality (9) shown below is satisfied or not (step A4). Specifically, in step A4, it is checked whether or not a borrow occurs on the

20 low-order $(M+1)$ th bit due to an error.

$$rx < x_{low} - E \quad \dots(9)$$

If the inequality (9) is satisfied (Yes in step A4), then it is judged that a borrow occurs on the low-order $(M+1)$ th bit due to an error, and output value y is calculated according to the following equation (10) (step A7):

$$25 \quad y = (x_{high} + mt) | rx \quad \dots(10)$$

According to the equation (10), the effect of the borrow occurring on

the low-order (M+1)th bit is eliminated by $x_{\text{high}} + m_t$, and the low-order M bits are set to r_x , making output value y identical to the low-bit-rate decoded signal in the encoding apparatus.

If the inequality (9) is not satisfied (No in step A4), then it is judged
 5 that neither carry nor borrow occurs on the low-order (M+1)th bit, and output value y is calculated according to the following equation (11) (step A6):

$$y = x_{\text{high}} | r_x \quad \dots(11)$$

According to the equation (11), the low-order M bits of the low-bit-rate decoded signal are set to corrective information r_x , making output value y
 10 identical to the low-bit-rate decoded signal in the encoding apparatus.

Output value y thus calculated is inputted to one of the input terminals of adder ADD2. Operation of corrector 207 has been described above with reference to Fig. 5.

Using numerical examples of the above correcting process will be
 15 described below in relation to corrections according to the equations (8) and (10). If $N = 16$, $M = 3$, $E = 2$, for example, then x_{low} ranges from 0 to 7, and r_x can take 5 ($= 2E + 1$) types of values shown in the following table:

xlow	rx
0	0,1,2,6,7
1	0,1,2,3,7
2	0,1,2,3,4
3	1,2,3,4,5
4	2,3,4,5,6
5	3,4,5,6,7
6	0,4,5,6,7
7	0,1,5,6,7

For any of combinations of xlow and rx in the above table satisfy the

5 inequality (7) or (9), e.g., for xlow = 0, rx = 6 or xlow = 7, rx = 1, the high-order (N-M) bit value xhigh of the low-bit-rate decoded signal in the decoding apparatus is not identical to the high-order (N-M) bit value of the low-bit-rate decoded signal in the encoding apparatus due to the effect of an error $\pm E$.

In order to correct the error, the high-order (N-M) bit value xhigh needs to be

10 corrected (xhigh-mt, xhigh+m) according to the equation (8) or the equation (10). Since corrective information rx represents the low-order M bit value of the low-bit-rate decoded signal in the encoding apparatus and the corrected high-order (N-M) bit value is the same as the high-order (N-M) bit value of the low-bit-rate decoded signal in the encoding apparatus, a signal which is

15 the same as the low-bit-rate decoded signal in the encoding apparatus can be reproduced in the decoding apparatus, using corrective information and

the corrected high-order (N-M) bit value. Accordingly, even when the processing accuracy in the low-bit-rate decoder in the encoding apparatus and the processing accuracy in the low-bit-rate decoder in the decoding apparatus are different from each other, the present correcting process
 5 makes the low-bit-rate decoded signals in the encoding apparatus and the decoding apparatus identical to each other, thus making the lossless reproduced signal identical to the input signal.

Another embodiment of the present invention will be described below with reference to Figs. 6 and 7. Fig. 6 is a block diagram of a hierarchical
 10 lossless encoding apparatus according to a second embodiment of the present invention, and Fig. 7 is a block diagram of a hierarchical lossless decoding apparatus according to the second embodiment of the present invention.

Hierarchical lossless encoding apparatus 1a shown in Fig. 6 differs
 15 from hierarchical lossless encoding apparatus 1 shown in Fig. 3 in that the input applied to corrective information extractor 107 is a delayed input signal output from delay compensator 102 and recording medium K1a is employed instead of recording medium K1. Recording medium K1a stores a program for enabling a computer to function as hierarchical lossless encoding
 20 apparatus 1a. The program is read by the computer and controls its operation to realize low-bit-rate encoder 101, delay compensator 102, low-bit-rate decoder 103, lossless encoder 104, corrective information extractor 107, and adder ADD1 on the computer.

Hierarchical lossless decoding apparatus 2a shown in Fig. 7 differs
 25 from hierarchical lossless decoding apparatus 2 shown in Fig. 4 in that the input applied to corrector 207 is an output from adder ADD2a which adds the

output of low-bit-rate decoder 201 and the output of lossless decoder 203 to each other, and recording medium K2a is employed instead of recording medium K2. Recording medium K2a stores a program for enabling a computer to function as hierarchical lossless decoding apparatus 2a. The
5 program is read by the computer and controls its operation to realize low-bit-rate decoder 201, lossless decoder 203, corrector 207, and adder ADD2a on the computer.

In hierarchical lossless encoding apparatus 1a, corrective information extractor 107 has its input supplied as a delayed input signal calculated by
10 delay compensator 102. Corrective information extractor 107 extracts corrective information (e.g., a value represented by the low-order M bits of the delayed input signal) from the delayed input signal in view of a maximum error that can occur in the low-bit-rate decoded signal calculated by low-bit-rate decoder 103, and outputs the corrective information to output terminal
15 108.

In hierarchical lossless decoding apparatus 2a, corrector 207 corrects a lossless reproduced signal, which is produced by adding the low-bit-rate decoded signal calculated by low-bit-rate decoder 201 and the differential
20 signal calculated by lossless decoder 203, using corrective information supplied through input terminal 206, in the same manner as with the first embodiment, and outputs the corrected lossless reproduced signal. Since the error in the low-bit-rate decoded signal is the same as the error in the lossless reproduced signal, the lossless reproduced signal becomes identical to the input signal when the lossless reproduced signal is corrected. The
25 second embodiment has been described above.

A third embodiment of the present invention will be described in detail

below. Fig. 8 is a block diagram of hierarchical lossless encoding apparatus 1b according to a third embodiment of the present invention, and Fig. 9 is a block diagram of hierarchical lossless decoding apparatus 2b according to the third embodiment of the present invention.

5 Hierarchical lossless encoding apparatus 1b shown in Fig. 8 differs from hierarchical lossless encoding apparatus 1 shown in Fig. 3 in that it has corrector 110, recording medium K1b is employed instead of recording medium K1, corrective information extractor 109 is employed instead of corrective information extractor 107, and adder ADD1b is employed instead
10 of adder 1. Recording medium K1b stores a program for enabling a computer to function as hierarchical lossless encoding apparatus 1b. The program is read by the computer and controls its operation to realize low-bit-rate encoder 101, delay compensator 102, low-bit-rate decoder 103, lossless encoder 104, corrective information extractor 109, corrector 110, and adder
15 ADD1b on the computer.

Hierarchical lossless decoding apparatus 2b shown in Fig. 9 differs from hierarchical lossless decoding apparatus 2 shown in Fig. 4 in that corrector 208 is employed instead of corrector 207 and recording medium K2b is employed instead of recording medium K2. Recording medium K2b
20 stores a program for enabling a computer to function as hierarchical lossless decoding apparatus 2b. The program is read by the computer and controls its operation to realize low-bit-rate decoder 201, lossless decoder 203, corrector 208, and adder ADD2a on the computer.

In hierarchical lossless encoding apparatus 1b, corrective information
25 extractor 109 extracts corrective information expressed by a single bit in view of a maximum error from the low-bit-rate decoded signal calculated by the

low-bit-rate decoder 103 in the same manner as with the above
embodiments, and outputs single-bit corrective information rb to output
terminal 108. Single-bit corrective information rb may be, for example, a
value represented by the single M th bit counted from the low-order bit of a
5 sampled value of the low-bit-rate decoded signal. The low-order bit
comprises the first bit. M satisfies the above formula (1).

Corrector 110 corrects the low-order M bits of the low-bit-rate
decoded signal output from low-bit-rate decoder 103 by applying a 0 mask
thereto, and outputs the corrected low-bit-rate decoded signal.

10 Adder ADD1b outputs a differential signal representing the difference
between the delayed input signal and the corrected low-bit-rate decoded
signal. The output differential signal is encoded by lossless encoder 104,
which outputs lossless encoded data to output terminal 106.

In hierarchical lossless decoding apparatus 2b, corrector 208 corrects
15 the low-bit-rate decoded signal calculated by the low-bit-rate decoder 201 in
the same manner as with the above embodiments, based on single-bit
corrective information rb , and outputs the corrected low-bit-rate decoded
signal. The corrected low-bit-rate decoded signal is added to a differential
signal calculated by lossless decoder 203 in the same manner as with the
20 above embodiments, and outputs the sum signal as a lossless reproduced
signal to output terminal 205.

An example of operation of corrector 208 will be described in detail
below with reference to a flowchart shown in Fig. 10.

As initial settings,

25 $mt = 2^M$,
 $t1 = E - 1$, and

$$t_h = m_t - E$$

are calculated using the low-order bit number M and the maximum error E (step B1).

Value x_{high} represented by high-order (N-M) bits of input value x and
 5 value x_{low} represented by low-order M bits of input value x are calculated in the same manner as in step A2 in the above embodiments (step B2).

Then, value x_{low} represented by low-order M bits is compared with threshold value t_1 to check if the inequality (12) shown below is satisfied or not (step B3). Specifically, it is checked whether or not a carry occurs on the
 10 low-order (M+1)th bit due to an error.

$$t_1 < x_{low} \quad \dots(12)$$

If the inequality (12) is not satisfied, then since there is a possibility that a carry occurs on the low-order (M+1)th bit, it is checked whether single-bit corrective information rb is an upper limit ("1") or not (step B5).

15 If single-bit corrective information rb is "1" (Yes in step B5), then it is judged that a carry occurs on the low-order (M+1)th bit, and output value y is calculated according to the equation (13) shown below (step B7).

Specifically, in step B7, the effect of the carry due to an error is eliminated.

$$y = x_{high} - m_t \quad \dots(13)$$

20 If single-bit corrective information rb is "0" (No in step B5), then it is judged that neither carry nor borrow occurs on the low-order (M+1)th bit, and output value y is calculated according to the equation (14) shown below (step B8). Specifically, in step B8, a signal produced by setting all the low-order M bits of the low-bit-rate decoded signal output from low-bit-rate
 25 decoder 201 to "0" is output.

$$y = x_{high} \quad \dots(14)$$

If the answer to step B3 is Yes, then it is checked whether the inequality (15) shown below is satisfied or not (step B4). That is, it is checked whether or not there is a possibility that a borrow occurs on the low-order (M+1)th bit due to an error.

$$5 \quad x_{\text{low}} < t_h \quad \dots(15)$$

If the inequality (15) is not satisfied, then since there is a possibility that a borrow occurs on the low-order (M+1)th bit, it is checked whether single-bit corrective information rb is a lower limit ("0") or not (step B6).

If single-bit corrective information rb is "0", then it is judged that a
10 borrow occurs, and output value y is calculated according to the equation (16) shown below (step B9). Specifically, in step B9, the effect of the borrow is eliminated.

$$y = x_{\text{high}} + mt \quad \dots(16)$$

If single-bit corrective information rb is "1" (No in step B6), then it is
15 judged that neither carry nor borrow occurs on the low-order (M+1)th bit, and output value y is calculated according to the equation (14) (step B8).

Operation of corrector 208 has been described above with reference to Fig.
10.

In steps B7, B9, x_{high} is corrected for the reasons that as with the first
20 and second embodiments, the high-order (N-M) bit value x_{high} of the corrected low-bit-rate decoded signal in the decoding apparatus is not identical to the high-order (N-M) bit value x_{high} of the corrected low-bit-rate decoded signal in the encoding apparatus due to the effect of an error $\pm E$. According to the present correcting process, the corrected low-bit-rate
25 decoded signals in the encoding apparatus and the decoding apparatus are made identical to each other, thus making the lossless reproduced signal

identical to the input signal.

The number of bits of corrective information rx in the first and second embodiments, varies depending on maximum error E . According to the third embodiment, the number of bits of corrective information rx is 1 at all times
5 independently of maximum error E , and hence the number of bits required for transmitting the corrective information is reduced.

According to the present invention, as described in detail above, the corrective information extractor in the encoding apparatus extracts corrective information in view of a maximum error that can occur in the low-bit-rate
10 decoder from the low-bit-rate decoded signal, and the corrector in the decoding apparatus corrects the low-bit-rate decoded signal based on the corrective information. Therefore, the low-bit-rate decoded signal in the encoding apparatus and the low-bit-rate decoded signal in the decoding apparatus are made identical to each other, thus making the lossless
15 reproduced signal identical to the input signal.

SCOPE OF CLAIMS

1. A hierarchical lossless encoding and decoding method comprising the steps of:

in an encoding apparatus,

5 encoding an input signal into low-bit-rate encoded data and transmitting the low-bit-rate encoded data to a decoding apparatus;

encoding a differential signal between a low-bit-rate decoded signal produced by decoding said low-bit-rate encoded data and said input signal, into lossless encoded data, and transmitting the lossless encoded

10 data to the decoding apparatus; and

extracting corrective information from said low-bit-rate decoded signal and transmitting the corrective information to the decoding apparatus;

in the decoding apparatus,

15 decoding the low-bit-rate encoded data transmitted from the encoding apparatus into a low-bit-rate decoded signal;

decoding the lossless encoded data transmitted from the encoding apparatus into a differential signal; and

20 correcting said low-bit-rate decoded signal based on the corrective information transmitted from said encoding apparatus, and adding the corrected low-bit-rate decoded signal and said differential signal into a lossless reproduced signal.

2. A hierarchical lossless encoding and decoding method according to claim 1, wherein the corrective information extracted from said
25 low-bit-rate decoded signal represents low-order M bits of said low-bit-rate decoded signal, and said step of correcting said low-bit-rate decoded signal

comprises the steps of:

determining whether a carry or a borrow occurs on a low-order (M+1)th bit of said low-bit-rate decoded signal based on said corrective information and said low-bit-rate decoded signal;

5 if a carry occurs, subtracting "1" from the low-order (M+1)th bit of said low-bit-rate decoded signal and replacing the low-order M bits with said corrective information;

if a borrow occurs, adding "1" to the low-order (M+1)th bit of said low-bit-rate decoded signal and replacing the low-order M bits with said
10 corrective information; and

if neither carry nor borrow occurs, replacing the low-order M bits of said low-bit-rate decoded signal with said corrective information.

3. A hierarchical lossless encoding and decoding method

15 comprising the steps of:

in an encoding apparatus,

encoding an input signal into low-bit-rate encoded data and transmitting the low-bit-rate encoded data to a decoding apparatus;

encoding a differential signal between a low-bit-rate decoded
20 signal produced by decoding said low-bit-rate encoded data and said input signal, into lossless encoded data, and transmitting the lossless encoded data to the decoding apparatus; and

extracting corrective information from said input signal and transmitting the corrective information to the decoding apparatus;

25 in the decoding apparatus,

decoding the low-bit-rate encoded data transmitted from the

encoding apparatus into a low-bit-rate decoded signal;

decoding the lossless encoded data transmitted from the
encoding apparatus into a differential signal;

5 adding said low-bit-rate decoded signal and said differential
signal into a lossless reproduced signal; and

correcting said lossless reproduced signal based on said
corrective information.

4. A hierarchical lossless encoding and decoding method

10 according to claim 3, wherein the corrective information extracted from said
input signal represents low-order M bits of said input signal, and said step of
correcting said lossless reproduced signal comprises the steps of:

determining whether a carry or a borrow occurs on a low-order
(M+1)th bit of said lossless reproduced signal based on said corrective
15 information and said lossless reproduced signal;

if a carry occurs, subtracting "1" from the low-order (M+1)th bit
of said lossless reproduced signal and replacing the low-order M bits with
said corrective information;

20 if a borrow occurs, adding "1" to the low-order (M+1)th bit of
said lossless reproduced signal and replacing the low-order M bits with said
corrective information; and

if neither carry nor borrow occurs, replacing the low-order M
bits of said lossless reproduced signal with said corrective information.

25 5. A hierarchical lossless encoding and decoding method
comprising the steps of:

in an encoding apparatus,
 encoding an input signal into low-bit-rate encoded data and
 transmitting the low-bit-rate encoded data to a decoding apparatus;

5 decoding said low-bit-rate encoded data into a low-bit-rate
 decoded signal, extracting corrective information from said low-bit-rate
 decoded signal, and transmitting the corrective information to the decoding
 apparatus; and

encoding a differential signal between a corrected low-bit-rate
 decoded signal produced by correcting said low-bit-rate decoded signal and
 10 said input signal, into lossless encoded data, and transmitting the lossless
 encoded data to the decoding apparatus;

in the decoding apparatus,

decoding the low-bit-rate encoded data transmitted from the
 encoding apparatus into a low-bit-rate decoded signal;

15 decoding the lossless encoded data transmitted from the
 encoding apparatus into a differential signal; and

correcting said low-bit-rate decoded signal based on said
 corrective information, and adding the corrected low-bit-rate decoded signal
 to said differential signal.

20

6. A hierarchical lossless encoding and decoding method
 according to claim 5, wherein the corrective information extracted from said
 low-bit-rate decoded signal represents low-order M bits of said low-bit-rate
 decoded signal, said low-bit-rate decoded signal is corrected in said

25 encoding apparatus by:

applying a 0 mask to the low-order M bits;

and said step of correcting said low-bit-rate decoded signal in said decoding apparatus comprises the steps of:

determining whether a carry or a borrow occurs on a low-order (M+1)th bit of said low-bit-rate decoded signal based on said corrective

5 information and said low-bit-rate decoded signal;

if a carry occurs, subtracting "1" from the low-order (M+1)th bit of said low-bit-rate decoded signal and setting all the low-order M bits to "0";

if a borrow occurs, adding "1" to the low-order (M+1)th bit of said low-bit-rate decoded signal and setting all the low-order M bits to "0";

10 and

if neither carry nor borrow occurs, setting all the low-order M bits of said low-bit-rate decoded signal to "0".

7. A hierarchical lossless encoding method comprising the steps

15 of:

encoding an input signal into low-bit-rate encoded data;

decoding said low-bit-rate encoded data into a low-bit-rate decoded signal;

20 encoding a differential signal between said low-bit-rate decoded signal and said input signal into lossless encoded data; and

extracting corrective information from said low-bit-rate decoded signal.

8. A hierarchical lossless encoding method comprising the steps

25 of:

encoding an input signal into low-bit-rate encoded data;

decoding said low-bit-rate encoded data into a low-bit-rate
decoded signal;

encoding a differential signal between said low-bit-rate
decoded signal and said input signal into lossless encoded data; and

5 extracting corrective information from said input signal.

9. A hierarchical lossless encoding method comprising the steps
of:

encoding an input signal into low-bit-rate encoded data;

10 decoding said low-bit-rate encoded data into a low-bit-rate
decoded signal;

extracting corrective information from said low-bit-rate decoded
signal; and

15 encoding a differential signal between a corrected low-bit-rate
decoded signal produced by correcting said low-bit-rate decoded signal and
said input signal, into lossless encoded data.

10. A hierarchical lossless decoding method comprising the steps
of:

20 inputting hierarchical lossless encoded data comprising low-bit-
rate encoded data, lossless encoded data, and corrective information;

decoding said low-bit-rate encoded data into a low-bit-rate
decoded signal;

decoding said lossless encoded data into a differential signal;

25 and

correcting said low-bit-rate decoded signal based on said

corrective information, and thereafter adding the corrected low-bit-rate decoded signal and said differential signal into a lossless reproduced signal.

11. A hierarchical lossless decoding method comprising the steps
5 of:

inputting hierarchical lossless encoded data comprising low-bit-rate encoded data, lossless encoded data, and corrective information;

decoding said low-bit-rate encoded data into a low-bit-rate decoded signal;

10 decoding said lossless encoded data into a differential signal;

adding said low-bit-rate decoded signal and said differential signal into a lossless reproduced signal; and

correcting said lossless reproduced signal based on said corrective information.

15

12. A hierarchical lossless encoding and decoding apparatus comprising an encoding apparatus and a decoding apparatus, said encoding apparatus comprising:

20 a low-bit-rate encoder for encoding an input signal into low-bit-rate encoded data and transmitting the low-bit-rate encoded data to the decoding apparatus;

a low-bit-rate decoder for decoding said low-bit-rate encoded data into a low-bit-rate decoded signal and outputting the low-bit-rate decoded signal;

25 a lossless encoder for encoding a differential signal between the low-bit-rate decoded signal output from said low-bit-rate decoder and

said input signal, into lossless encoded data, and transmitting the lossless encoded data to the decoding apparatus; and

a corrective information extractor for extracting corrective information from said low-bit-rate decoded signal and transmitting the

5 corrective information to the decoding apparatus;

said decoding apparatus comprising:

a low-bit-rate decoder for decoding the low-bit-rate encoded data transmitted from said encoding apparatus into a low-bit-rate decoded signal;

10 a lossless decoder for decoding the lossless encoded data transmitted from said encoding apparatus into a differential signal;

a corrector for correcting said low-bit-rate decoded signal based on the corrective information transmitted from said encoding apparatus; and

15 an adder for adding the low-bit-rate decoded signal corrected by said corrector and said differential signal into a lossless reproduced signal.

13. A hierarchical lossless encoding and decoding apparatus
20 comprising an encoding apparatus and a decoding apparatus, said encoding apparatus comprising:

a low-bit-rate encoder for encoding an input signal into low-bit-rate encoded data and transmitting the low-bit-rate encoded data to the decoding apparatus;

25 a low-bit-rate decoder for decoding said low-bit-rate encoded data into a low-bit-rate decoded signal and outputting the low-bit-rate

decoded signal;

a lossless encoder for encoding a differential signal between the low-bit-rate decoded signal output from said low-bit-rate decoder and said input signal, into lossless encoded data, and transmitting the lossless encoded data to the decoding apparatus; and

a corrective information extractor for extracting corrective information from said input signal and transmitting the corrective information to the decoding apparatus;

said decoding apparatus comprising:

a low-bit-rate decoder for decoding the low-bit-rate encoded data transmitted from said encoding apparatus into a low-bit-rate decoded signal;

a lossless decoder for decoding the lossless encoded data transmitted from said encoding apparatus into a differential signal;

an adder for adding said low-bit-rate decoded signal and said differential signal into a lossless reproduced signal; and

a corrector for correcting said lossless reproduced signal based on said corrective information.

14. A hierarchical lossless encoding and decoding apparatus comprising an encoding apparatus and a decoding apparatus, said encoding apparatus comprising:

a low-bit-rate encoder for encoding an input signal into low-bit-rate encoded data and transmitting the low-bit-rate encoded data to the decoding apparatus;

a low-bit-rate decoder for decoding said low-bit-rate encoded

data into a low-bit-rate decoded signal;

a corrective information extractor for extracting corrective information from said low-bit-rate decoded signal and transmitting the corrective information to the decoding apparatus; and

5 a lossless encoder for encoding a differential signal between a corrected low-bit-rate decoded signal produced by correcting the low-bit-rate decoded signal and said input signal, into lossless encoded data, and transmitting the lossless encoded data to the decoding apparatus; and said decoding apparatus comprising:

10 a low-bit-rate decoder for decoding the low-bit-rate encoded data transmitted from said encoding apparatus into a low-bit-rate decoded signal;

a lossless decoder for decoding the lossless encoded data transmitted from said encoding apparatus into a differential signal; and

15 a corrector for correcting said low-bit-rate decoded signal based on said corrective information, and adding the corrected low-bit-rate decoded signal to said differential signal.

15. A hierarchical lossless encoding apparatus comprising:

20 a low-bit-rate encoder for encoding an input signal into low-bit-rate encoded data;

a low-bit-rate decoder for decoding said low-bit-rate encoded data into a low-bit-rate decoded signal;

25 a lossless encoder for encoding a differential signal between the low-bit-rate decoded signal and said input signal, into lossless encoded data; and

a corrective information extractor for extracting corrective information from said low-bit-rate decoded signal.

16. A hierarchical lossless encoding apparatus comprising:

5 a low-bit-rate encoder for encoding an input signal into low-bit-rate encoded data;

a low-bit-rate decoder for decoding said low-bit-rate encoded data into a low-bit-rate decoded signal;

10 a lossless encoder for encoding a differential signal between the low-bit-rate decoded signal and said input signal, into lossless encoded data; and

a corrective information extractor for extracting corrective information from said input signal.

15 17. A hierarchical lossless encoding apparatus comprising:

a low-bit-rate encoder for encoding an input signal into low-bit-rate encoded data;

a low-bit-rate decoder for decoding said low-bit-rate encoded data into a low-bit-rate decoded signal;

20 a corrective information extractor for extracting corrective information from said low-bit-rate decoded signal;

a corrector for correcting said low-bit-rate decoded signal and outputting the corrected low-bit-rate decoded signal; and

25 a lossless encoder for encoding a differential signal between the corrected low-bit-rate decoded signal and said input signal, into lossless encoded data.

18. A hierarchical lossless decoding apparatus comprising:
a low-bit-rate decoder for decoding low-bit-rate encoded data
into a low-bit-rate decoded signal;
5 a lossless decoder for decoding lossless encoded data into a
differential signal;
a corrector for correcting said low-bit-rate decoded signal
based on corrective information; and
an adder for adding the low-bit-rate decoded signal corrected
10 by said corrector and said differential signal into a lossless reproduced
signal.

19. A hierarchical lossless decoding apparatus comprising:
a low-bit-rate decoder for decoding low-bit-rate encoded data
15 into a low-bit-rate decoded signal;
a lossless decoder for decoding lossless encoded data into a
differential signal;
an adder for adding said low-bit-rate decoded signal and said
differential signal into a lossless reproduced signal; and
20 a corrector for correcting said lossless reproduced signal
based on corrective information.

20. A hierarchical lossless encoding apparatus having a program
for enabling a computer to perform a process of:
25 encoding an input signal into low-bit-rate encoded data;
decoding said low-bit-rate encoded data into a low-bit-rate

decoded signal;

encoding a differential signal between said low-bit-rate

decoded signal and said input signal into lossless encoded data; and

extracting corrective information from said low-bit-rate decoded

5 signal.

21. A hierarchical lossless encoding apparatus having a program
for enabling a computer to perform a process of:

encoding an input signal into low-bit-rate encoded data;

10 decoding said low-bit-rate encoded data into a low-bit-rate
decoded signal;

encoding a differential signal between said low-bit-rate

decoded signal and said input signal into lossless encoded data; and

extracting corrective information from said input signal.

15

22. A hierarchical lossless encoding apparatus having a program
for enabling a computer to perform a process of:

encoding an input signal into low-bit-rate encoded data;

decoding said low-bit-rate encoded data into a low-bit-rate

20 decoded signal;

extracting corrective information from said low-bit-rate decoded
signal; and

encoding a differential signal between a corrected low-bit-rate
decoded signal produced by correcting said low-bit-rate decoded signal and
25 said input signal, into lossless encoded data.

23. A hierarchical lossless decoding apparatus having a program for enabling a computer to perform a process of:

inputting hierarchical lossless encoded data comprising low-bit-rate encoded data, lossless encoded data, and corrective information;

5 decoding said low-bit-rate encoded data into a low-bit-rate decoded signal;

 decoding said lossless encoded data into a differential signal;

and

 correcting said low-bit-rate decoded signal based on said
10 corrective information, and thereafter adding the corrected low-bit-rate decoded signal and said differential signal into a lossless reproduced signal.

24. A hierarchical lossless decoding apparatus having a program for enabling a computer to perform a process of:

15 inputting hierarchical lossless encoded data comprising low-bit-rate encoded data, lossless encoded data, and corrective information;

 decoding said low-bit-rate encoded data into a low-bit-rate decoded signal;

 decoding said lossless encoded data into a differential signal;

20 adding said low-bit-rate decoded signal and said differential signal into a lossless reproduced signal; and

 correcting said lossless reproduced signal based on said corrective information.