D E S C R I P T I O N

DISPLAY DEVICE AND DISPLAY DEVICE DRIVING METHOD

Technical Field

The present invention relates to a display device and a display device driving method.

Background Art

Liquid crystal displays are generally classified into active matrix driving liquid crystal displays and simple matrix driving liquid crystal displays. The active matrix driving liquid crystal display displays an image having a higher luminance, higher contrast, and higher resolution as compared to the simple matrix driving liquid crystal display. In the active matrix driving liquid crystal display, a liquid crystal element which also functions as a capacitor and a transistor which activates the liquid crystal element are arranged for each pixel. In the active matrix driving liquid crystal display, a selection signal is input from a scanning driver serving as a shift register to a scanning line so that the scanning line is selected. At this time, when a voltage having a level representing a luminance is applied from a data driver to a signal line, the voltage is applied to the liquid crystal element through the transistor. Even when the transistor is turned off during a period from

the end of signal input to the scanning line to the next signal input, the voltage level is held until the next signal is input to the scanning line because the liquid crystal element functions as a capacitor. As described above, while the signal is input to the scanning line, the light transmittance of the liquid crystal element is newly refreshed. Light from a backlight passes through the liquid crystal element at the refreshed light transmittance so that the gray level of the liquid crystal display is expressed.

On the other hand, an organic EL (ElectroLuminescence) display which uses organic EL elements as spontaneous optical elements requires no backlight, unlike liquid crystal displays. Hence, the organic EL display is optimum for a thin display. In addition, the organic EL display has no limitation on the angle of field, unlike liquid crystal displays. For this reason, practical utilization of organic EL displays as next-generation display devices is greatly expected.

From the viewpoint of a high luminance, high contrast, and high resolution, voltage-controlled active matrix driving schemes have been developed not only for liquid crystal displays but also for organic EL displays. However, the capacity of an organic EL element is much smaller than that of a liquid crystal element so a current flows to the organic EL element

itself. To hold a voltage, the number of transistors increases. This leads to an increase in complexity of a circuit constituted by transistors.

In a transistor, generally, the channel resistance changes due to a change in ambient temperature or long-time use. For this reason, the gate threshold voltage changes over time or varies between transistors. It is therefore difficult to uniquely designate the current level to be supplied to an organic EL element on the basis of the gate voltage level of a switching transistor by changing the value of the voltage to be applied to the gate electrode of the transistor and thus changing the level of the current to be supplied to the organic EL element. In other words, the level of the current to be supplied can hardly be uniquely designated by changing the value of the voltage to be applied to the gate electrode of the transistor and thus changing the luminance of the organic EL element. That is, even when a gate voltage of the same level is applied to the transistors of a plurality of pixels, the organic EL elements of the plurality of pixels may have different emission luminances. This may cause a variation in luminance on the display screen.

Disclosure of Invention

It is an object of the present invention to provide a display device and a display device driving

method, which allow stable display on the basis of a simple driving principle.

In order to solve the above problems, according to an aspect of the present invention, there is provided a display device comprising:

a plurality of scanning lines (e.g., selection scanning lines X_1 to X_m);

a plurality of signal lines (e.g., signal lines Y_1 to Y_n);

a scanning driver (e.g., a selection scanning driver 5) which sequentially supplies to the scanning lines selection signals that select the scanning lines;

a data driver (e.g., a data driver 3) which supplies a designation current (e.g., a gray level designation current I_{DATA}) to the plurality of signal lines within a selection period (e.g., a selection period T_{SE}) when the scanning lines are being selected;

a plurality of pixel circuits (e.g., pixel circuits $D_{1,1}$ to $D_{m,n}$) which supplies a driving current corresponding to a current value of the designation current that flows to the signal lines;

a plurality of optical elements (e.g., light-emitting elements $E_{1,1}$ to $E_{m,n}$) which emit light in accordance with the driving current supplied by the plurality of pixel circuits; and

a power supply (e.g., a common signal power supply 6) which outputs to the plurality of pixel circuits a

driving current reference voltage (e.g., a voltage V_{HIGH}) to supply the driving current.

In the above device, in accordance with the timing when the power supply outputs the driving current reference voltage, the plurality of pixel circuits supply the driving current in accordance with the current value of the designation current that flows within each selection period. Accordingly, the optical elements emit light.

Hence, when the power supply outputs the driving current reference voltage from the end of the selection period of a predetermined scanning line till the beginning of the selection period of the next scanning line, a driving current corresponding to both an optical element corresponding to the predetermined scanning line and an optical element corresponding to the next scanning line flows. Hence, the optical elements can emit light at a desired luminance.

When the power supply outputs the driving current reference voltage to the pixel circuit at once after all the scanning lines are selected, all the optical elements can emit light.

When a reset voltage is output to the plurality of signal lines within a period when none of the plurality of optical elements are selected, the signal lines reset charges stored in the preceding selection period. For this reason, the parasitic capacitance of the

signal lines can be quickly charged within the next selection period so that even when a designation current having a smaller current value is supplied, the current value of the designation current can rapidly be set in the steady state. Hence, even an optical element such as an organic EL element whose luminance is modulated by a small current on the μA order is allowed to quickly display multiple gray level luminances.

Brief Description of Drawings

FIG. 1 is a view showing an organic EL display applied as a display device according to the first embodiment of the present invention;

FIG. 2 is a plan view showing a pixel shown in FIG. 1, in which an oxide insulating film, channel protective insulating film, and common electrode are omitted to help understanding;

FIG. 3 is a sectional view taken along a line III - III in FIG. 2;

FIG. 4 is a sectional view taken along a line IV - IV in FIG. 2;

FIG. 5 is a sectional view taken along a line V - V in FIG. 2;

FIG. 6 is an equivalent circuit diagram of four adjacent pixels;

FIG. 7 is a graph showing the current vs. voltage characteristic of an N-channel field effect transistor

used in the first embodiment;

FIG. 8 is a timing chart showing the levels of signals in the apparatus according to the first embodiment;

FIG. 9A is a view showing a voltage state when no switching circuit is arranged, and a gray level designation current with the maximum current value is supplied across the drain and source of a transistor and a signal line during the selection period of the ith row;

FIG. 9B is a view showing a voltage state when a switching circuit is arranged, and a gray level designation current with the maximum current value is supplied across the drain and source of a transistor and a signal line during the selection period of the ith row;

FIG. 10 is a view showing an organic EL display applied as a display device according to the second embodiment of the present invention, in which a common signal power supply is arranged in a controller;

FIG. 11 is a view showing an organic EL display applied as a display device according to the third embodiment of the present invention, in which the drain of the transistor of a pixel circuit is connected to a selection scanning line;

FIGS. 12A and 12B are equivalent circuit diagrams showing adjacent pixels in the third embodiment to

indicate current flows in different operation periods; and

FIG. 13 is a timing chart showing the levels of signals in the apparatus according to the third embodiment.

Best Mode for Carrying Out the Invention

Detailed embodiments of the present invention will be described below with reference to the accompanying drawings. The scope and spirit of the display device or panel are not limited to the illustrated embodiments.

[First Embodiment]

FIG. 1 is a view showing an organic EL display to which the present invention is applied. An organic EL display 1 comprises, as a basic arrangement, an organic EL display panel 2, data driver 3, selection scanning driver 5, common signal power supply 6, switching circuit 7, and controller 11.

In the organic EL display panel 2, a display section 4 on which an image is actually displayed is formed on a transparent substrate 8. The data driver 3, selection scanning driver 5, common signal power supply 6, and switching circuit 7 are arranged around the display section 4. The data driver 3, selection scanning driver 5, and common signal power supply 6 may be arranged either on the transparent substrate 8 or on a flexible circuit board arranged around the

transparent substrate 8.

In the display section 4, (m × n) pixels $P_{1,1}$ to $P_{m,n}$ (m and n are arbitrary natural numbers) are arranged in a matrix on the transparent substrate 8. In the column direction, i.e., in the vertical direction, m pixels $P_{1,j}$ to $P_{m,j}$ (j is an arbitrary natural number; $1 \leqq j \leqq n$) are arrayed. In the row direction, i.e., in the horizontal direction, n pixels $P_{i,1}$ to $P_{i,n}$ (i is an arbitrary natural number; $1 \leqq i \leqq m$) are arrayed. That is, a pixel which exists on the ith line (i.e., the ith row) from the upper side in the vertical direction and the jth line (i.e., the jth column) from the left side in the horizontal direction is defined as a pixel $P_{i,j}$.

In the display section 4, m selection scanning lines X_1 to X_m running in the row direction are parallelly arranged in the column direction on the transparent substrate 8. In addition, m common signal supply lines Z_1 to Z_m running in the row direction are parallelly arranged in the column direction on the transparent substrate 8 in correspondence with the selection scanning lines X_1 to X_m. Each common signal supply line Z_k ($1 \leqq k \leqq m-1$) is inserted between the selection scanning lines X_k and X_{k+1}. The selection scanning line X_m is inserted between the common signal supply lines Z_{m-1} and Z_m. In addition, n signal lines Y_1 to Y_n running in the column direction are parallelly

arranged in the row direction on the transparent substrate 8. The selection scanning lines X_1 to X_m, common signal supply lines Z_1 to Z_m, and signal lines Y_1 to Y_n are insulated from each other by intervening insulating films. A selection scanning line X_i and common signal supply line Z_i are connected to $\underline{n}$ pixels $P_{i,1}$ to $P_{i,n}$ arrayed in the row direction. A signal line Y_j is connected to $\underline{m}$ pixels $P_{i,j}$ to $P_{m,j}$ arrayed in the column direction. The pixel $P_{i,j}$ is arranged at a portion surrounded by the selection scanning line X_i, common signal supply line Z_i, and signal line Y_j. The selection scanning lines X_1 to X_m are connected to the output terminals of the selection scanning driver 5. The common signal supply lines Z_1 to Z_m are rendered conductive to each other and connected to the output terminal of the common signal power supply 6. That is, the same signal is output to the common signal supply lines Z_1 to Z_m.

The pixel $P_{i,j}$ will be described next with reference to FIGS. 2 to 6. FIG. 2 is a plan view showing the pixel $P_{i,j}$. To help understanding, an oxide insulating film 41, channel protective insulating film 45, and common electrode 53 (to be described later) are omitted. FIG. 3 is a sectional view taken along a line III - III in FIG. 2. FIG. 4 is a sectional view taken along a line IV - IV in FIG. 2. FIG. 5 is a sectional view taken along a line V - V in

FIG. 2.

FIG. 6 is an equivalent circuit diagram of four adjacent pixels $P_{i,j}$, $P_{i+1,j}$, $P_{i,j+1}$, and $P_{i+1,j+1}$.

The pixel $P_{i,j}$ is constituted by a light-emitting element $E_{i,j}$ which emits light with a luminance (nt. = cd/m^2) corresponding to the current value of the driving current and a pixel circuit $D_{i,j}$ which is arranged around the light-emitting element $E_{i,j}$ and drives the light-emitting element $E_{i,j}$. The pixel circuit $D_{i,j}$ holds the current value of a current that flows to the light-emitting element $E_{i,j}$ during a predetermined light-emitting period on the basis of a voltage signal and current output from the data driver 3, selection scanning driver 5, power supply scanning driver 6, and switching circuit 7. With this operation, the luminance of the light-emitting element $E_{i,j}$ is held at a predetermined value during a predetermined period.

The light-emitting element $E_{i,j}$ is made of an organic EL element. The light-emitting element $E_{i,j}$ has a multilayered structure formed by sequentially stacking a pixel electrode 51, an organic EL layer 52, and the common electrode 53. The pixel electrode 51 functions as an anode on the transparent substrate 8. The organic EL layer 52 has a function of receiving holes and electrons by an electric field and a function of transporting holes and electrons. The organic EL

layer 52 has a recombination region where the transported holes and electrons are recombined and a light-emitting region where light is emitted by capturing excitons generated upon recombination. The organic EL layer 52 functions as a light-emitting layer in a broad sense. The common electrode 53 functions as a cathode.

The pixel electrode 51 is patterned and separated for each pixel $P_{i,j}$ in each surrounded region surrounded by the signal lines Y_1 to Y_n and selection scanning lines X_1 to X_m. The peripheral edge of the pixel electrode 51 is covered with an interlayer dielectric film 54 which has a layer of silicon nitride or silicon oxide that covers three transistors 21, 22, and 23 of the pixel circuit $D_{i,j}$. The upper surface at the center of the pixel electrode 51 is exposed through a contact hole 55 in the interlayer dielectric film 54. The interlayer dielectric film 54 may also have a second layer formed of an insulting film of polyimide or the like on the first layer of silicon nitride or silicon oxide.

The pixel electrode 51 has conductivity and transmittance to visible light. The pixel electrode 51 preferably has a relatively high work function and efficiently injects holes into the organic EL layer 52. For example, the pixel electrode 51 contains, as a principal component, indium tin oxide (ITO), indium

zinc oxide, indium oxide (In_2O_3), tin oxide (SnO_2), or zinc oxide (ZnO).

The organic EL layer 52 is formed on each pixel electrode 51. The organic EL layer 52 is also patterned for each pixel $P_{i,j}$. The organic EL layer 52 contains a light-emitting material (phosphor) as an organic compound. The light-emitting material may be either a polymeric material or a low molecular weight material. The organic EL layer 52 may have, e.g., a two-layered structure in which a hole transport layer 52A and a light-emitting layer 52B in a narrow sense are formed sequentially from the side of the pixel electrode 51, as shown in FIG. 3. The light-emitting layer 52B has a recombination region where holes and electrons are recombined and a light-emitting region where light is emitted by capturing excitons generated upon recombination. Alternatively, the organic EL layer 52 may have a three-layered structure in which a hole transport layer, a light-emitting layer in a narrow sense, and electron transport layer are formed sequentially from the side of the pixel electrode 51. The organic EL layer 52 may have a single-layered structure including a light-emitting layer in a narrow sense. The organic EL layer 52 may also have a multilayered structure formed by interposing an electron or hole injection layer between appropriate layers of the above layer structure. The organic EL

layer 52 may have any other layer structure.

The organic EL display panel 2 is capable of full-color display or multi-color display. In this case, the organic EL layer 52 of each of the pixels $P_{i,1}$ to $P_{i,n}$ is formed of a light-emitting layer in a broad sense, which has a function of emitting one of, e.g., red light, green light, and blue light. That is, when the pixels $P_{i,1}$ to $P_{i,n}$ selectively emit red, green, and blue light, a color tone is displayed by appropriately synthesizing the colors.

The organic EL layer 52 is preferably made of an organic compound that is electronically neutral. In this case, holes and electrons are injected and transported in the organic EL layer 52 in good balance. In addition, an electron transportable substance may be appropriately mixed into the light-emitting layer in a narrow sense. A hole transportable substance may be appropriately mixed into the light-emitting layer in a narrow sense. An electron transportable substance and a hole transportable substance may be appropriately mixed into the light-emitting layer in a narrow sense. A charge transport layer serving as an electron transport layer or a hole transport layer may be caused to function as a recombination region. Light may be emitted by mixing phosphor into the charge transport layer.

The common electrode 53 formed on the organic EL

layer 52 is a single electrode connected to all the pixels $P_{1,1}$ to $P_{m,n}$. Alternately, the common electrode 53 may comprise a plurality of stripe-shaped electrodes connected to the respective columns. More specifically, the common electrode 53 may comprise a stripe common electrode connected to a group of pixels $P_{1,h-1}$ to $P_{m,h-1}$ ($\underline{h}$ is an arbitrary natural number; $2 \leqq h \leqq n$) in the column direction, a stripe common electrode connected to a group of pixels $P_{1,h}$ to $P_{m,h}$. In this manner, the common electrode 53 comprises a plurality of stripe-shaped electrodes each connected to each column. Alternatively, the common electrode 53 may comprise a stripe common electrode connected to a group of pixels $P_{g-1,1}$ to $P_{g-1,n}$ ($\underline{g}$ is an arbitrary natural number; $2 \leqq g \leqq m$) in the row direction, a stripe common electrode connected to a group of pixels $P_{g,1}$ to $P_{g,n}$,.... In this manner, the common electrode 53 comprises a plurality of stripe-shaped electrodes connected to each row.

In any case, the common electrode 53 is electrically insulated from the selection scanning line X_i, signal line Y_j, and common signal supply line Z_i. The common electrode 53 is made of a material having a low work function. For example, the common electrode 53 is made of a single element or an alloy containing at least one of indium, magnesium, calcium, lithium, barium, and rare-earth metals. The common electrode 53

may have a multilayered structure formed by stacking a plurality of layers made of the above materials. More specifically, the multilayered structure may include a high purity barium layer which has a low work function and is formed on the side of the interface that is in contact with the organic EL layer 52, and an aluminum layer that covers the barium layer. Alternatively, the multilayered structure may have a lithium layer on the lower side and an aluminum layer on the upper side. When a transparent electrode is used as the pixel electrode 51, and light emitted from the organic EL layer 52 of the organic EL display panel 2 should exit from the side of the transparent substrate 8 through the pixel electrode 51, the common electrode 53 preferably shields the light emitted from the organic EL layer 52. More preferably, the common electrode 53 has a high reflectance against the light emitted from the organic EL layer 52.

As described above, in the light-emitting element $E_{i,j}$ having a multilayered structure, when a forward bias voltage is applied between the pixel electrode 51 and the common electrode 53, holes are injected from the pixel electrode 51 to the organic EL layer 52 while electrons are injected from the common electrode 53 to the organic EL layer 52. The holes and electrons are transported in the organic EL layer 52. When the holes and electrons are recombined in the organic EL layer

52, excitons are generated. The excitons excite the organic EL layer 52. The organic EL layer 52 emits light.

The emission luminance (unit: nt. = cd/m^2) of the light-emitting element $E_{i,j}$ depends on the current value of the current that flows to the light-emitting element $E_{i,j}$. To maintain a predetermined emission luminance of the light-emitting element $E_{i,j}$ during the light-emitting of the light-emitting element $E_{i,j}$ or obtain an emission luminance corresponding to the current value of a gray level designation current I_{DATA} drawn from the data driver 3, the pixel circuit $D_{i,j}$ is arranged around the light-emitting element $E_{i,j}$ of each pixel $P_{i,j}$. The pixel circuit $D_{i,j}$ controls the current value of the light-emitting element $E_{i,j}$.

Each pixel circuit $D_{i,j}$ comprises three transistors 21, 22, and 23 and a capacitor 24. Each transistor is formed of a field effect thin film transistor (TFT) having an N-channel MOS structure.

Each transistor 21 is an MOS field effect transistor constituted by a gate electrode 21g, gate insulating film 42, semiconductor layer 43, source electrode 21s, and drain electrode 21d. Each transistor 22 is an MOS field effect transistor constituted by a gate electrode 22g, gate insulating film 42, semiconductor layer 43, source electrode 22s, and drain electrode 22d. Each transistor 23 is

constituted by a gate electrode 23g, gate insulating film 42, semiconductor layer 43, source electrode 23s, and drain electrode 23d.

More specifically, as shown in FIG. 3, the first transistor 21 is a reverse stagger type transistor comprising the gate electrode 21g, oxide insulating film 41, gate insulating film 42, island-shaped semiconductor layer 43, channel protective insulating film 45, impurity-doped semiconductor layers 44, source electrode 21s, and drain electrode 21d. The gate electrode 21g is made of aluminum and formed on the transparent substrate 8. The oxide insulating film 41 is formed by anodizing aluminum that covers the gate electrode 21g. The gate insulating film 42 is made of silicon nitride or silicon oxide and covers the oxide insulating film 41. The semiconductor layer 43 is formed on the gate insulating film 42. The channel protective insulating film 45 is made of silicon nitride and formed on the gate insulating film 42. The impurity-doped semiconductor layers 44 are made of n^+-silicon and formed at both ends of the semiconductor layer 43. The source electrode 21s and drain electrode 21d are made of a material selected from chromium, a chromium alloy, aluminum and an aluminum alloy, and formed on the impurity semiconductor layers 44.

The second and third transistors 22 and 23 have the same structure as that of the first transistor 21

described above. However, the shapes, sizes, and dimensions of the transistors 21, 22, and 23, and the channel widths and channel lengths of the semiconductor layers 43 are appropriately set in accordance with the functions of the transistors 21, 22, and 23.

The transistors 21, 22, and 23 may be formed simultaneously by the same process. In this case, the gate electrodes, oxide insulating films 41, gate insulating films 42, semiconductor layers 43, impurity semiconductor layers 44, source electrodes, and drain electrodes of the transistors 21, 22, and 23 have the same compositions.

Even when the semiconductor layers 43 of the transistors 21, 22, and 23 are made of amorphous silicon, they can be sufficiently driven. However, the semiconductor layers 43 may be made of polysilicon. The structures of the transistors 21, 22, and 23 are not limited to the reverse stagger type. Even a stagger type or coplanar type structure may be employed.

Each capacitor 24 is constituted by an electrode 24A, electrode 24B, and dielectric body. The electrode 24A is connected to the gate electrode 23g of the third transistor 23. The electrode 24B is connected to the source electrode 23s of the transistor 23. The dielectric body has the gate insulating film 42 interposed between the electrodes 24A and 24B. The

capacitor 24 stores charges between the source electrode 23s and the drain electrode 23d of the transistor 23.

As shown in FIG. 6, in the second transistor 22 of each of the pixel circuit $D_{i,1}$ to $D_{i,n}$ of the ith row, the gate electrode 22g is connected to the selection scanning line X_i of the ith row. The drain electrode 22d is connected to the common signal supply line Z_i of the ith row. As shown in FIG. 5, the drain electrode 23d of the third transistor 23 of each of the pixel circuit $D_{i,1}$ to $D_{i,n}$ of the ith row is connected to the common signal supply line Z_i of the ith row through a contact hole 26. The gate electrode 21g of the first transistor 21 of each of the pixel circuit $D_{i,1}$ to $D_{i,n}$ of the ith row is connected to the selection scanning line X_i of the ith row. The source electrode 21s of the transistor 21 of each of the pixel circuit $D_{1,j}$ to $D_{m,j}$ of the jth column is connected to the signal line Y_j of the jth column.

In each of the pixels $P_{1,1}$ to $P_{m,n}$, the source electrode 22s of the second transistor 22 is connected to the gate electrode 23g of the third transistor 23 through a contact hole 25 formed in the gate insulating film 42, as shown in FIG. 4. The source electrode 22s is also connected to one electrode of the capacitor 24. The source electrode 23s of the transistor 23 is connected to the other electrode of the capacitor 24

and also to the drain electrode 21d of the transistor 21. The source electrode 23s of the transistor 23, the other electrode of the capacitor 24, and the drain electrode 21d of the transistor 21 are connected to the pixel electrode 51 of the light-emitting element $E_{i,j}$. The voltage of the common electrode 53 of the light-emitting element $E_{i,j}$ is a reference voltage V_{SS}. In this embodiment, the common electrode 53 of all light-emitting elements $E_{1,1}$ to $E_{m,n}$ is grounded so that the reference voltage V_{SS} is set to 0 [V].

Protective films 43A formed by patterning the same film as that of the semiconductor layers 43 of the transistors 21 to 23 are arranged between the selection scanning line X_i and the signal line Y_j and between the common signal supply line Z_i and the signal line Y_j as well as the gate insulating film 42.

The controller 11 outputs a control signal group D_{CNT} including a data driver clock signal CK1, start signal ST1 and latch signal L to the data driver 3 on the basis of a dot clock signal CK_{DT}, horizontal sync signal H_{SYNC} and vertical sync signal V_{SYNC}, which are input from the outside. The controller 11 also outputs a control signal group G_{CNT} including a selection scanning driver clock signal CK2 and start signal ST2. The controller 11 also outputs a common signal clock signal CK3 to the common signal power supply 6. The controller 11 also supplies a reset voltage V_{RST} to the

switching circuit 7 and outputs a switching signal ϕ to the switching circuit 7.

More specifically, the data driver clock signal CK1 is a signal to sequentially shift the selected column in synchronism with the dot clock signal CK_{DT}. An 8-bit red digital gray level image signal S_R, green digital gray level image signal S_G, and blue digital gray level image signal S_B are received from an external circuit at the timing of the clock signal CK1. The start signal ST1 is a signal to return the selected column to the first column in synchronism with the horizontal sync signal H_{SYNC}. The latch signal L is a signal to parallelly supply the analog gray level designation current I_{DATA} based on an analog gray level designation signal to the signal lines Y_1 to Y_n. The analog gray level designation signal is obtained by causing the D/A converter in the data driver 3 to D/A-convert the data of one row, i.e., the red digital gray level image signal S_R, green digital gray level image signal S_G, and blue digital gray level image signal S_B which are received in correspondence with the pixels $P_{i,1}$ to $P_{i,n}$.

The selection scanning driver clock signal CK2 is a signal to sequentially shift the selected row in synchronism with the horizontal sync signal H_{SYNC}. The start signal ST2 is a signal to return the selected row to the first row in synchronism with the vertical sync

signal V_{SYNC}.

The common signal clock signal CK3 is a clock signal to output a common signal to the common signal supply lines Z_1 to Z_m.

The data driver 3, selection scanning driver 5, and common signal power supply 6 arranged around the display section 4 will be described next.

The selection scanning driver 5 is a so-called shift register in which m flip-flop circuits are connected in series. The driver 5 outputs a selection signal to the selection scanning lines X_1 to X_m. That is, in accordance with the selection scanning driver clock signal CK2 received from the controller 11, the selection scanning driver 5 sequentially outputs a selection signal of ON level (high level) to the selection scanning lines X_1 to X_m in this order (the selection scanning line X_1 follows the selection scanning line X_m), thereby sequentially selecting the selection scanning lines X_1 to X_m.

More specifically, as shown in FIG. 8, the selection scanning driver 5 individually applies, to the selection scanning lines X_1 to X_m, one of an ON voltage V_{ON} (e.g., much higher than the reference voltage V_{SS}) as a high-level selection signal and an OFF voltage V_{OFF} (e.g., equal to or lower than the reference voltage V_{SS}) as a low-level selection signal, thereby selecting each selection scanning line X_i at a

predetermined period.

During a selection period T_{SE} when the selection scanning line X_i is to be selected, the selection scanning driver 5 applies the ON voltage V_{ON} as a selection signal of ON level (high level) to the selection scanning line X_i. Accordingly, the transistors 21 and 22 (the transistors 21 and 22 of all the pixel circuits $D_{i,1}$ to $D_{i,n}$) connected to the selection scanning line X_i are turned on. When the first transistor 21 is turned on, the current that flows to the signal line Y_j can flow to the pixel circuit $D_{i,j}$. On the other hand, a non-selection period T_{NSE} is present from the end of the selection period T_{SE} of the selection scanning line X_i of the ith row till the beginning of the selection period T_{SE} of the selection scanning line X_{i+1} of the (i+1)th row. When the selection scanning driver 5 applies the OFF voltage V_{OFF} of low level to all the selection scanning lines X_1 to X_m, the transistors 21 and 22 of all the selection scanning lines X_1 to X_m are turned off. When the transistor 21 is turned off, supply of the gray level designation current I_{DATA} to the signal line Y_j is stopped. The period from the start of the selection period T_{SE} of the selection scanning line X_1 of the first row to the start of the next selection period T_{SE} of the selection scanning line X_1 of the first row is defined as one scanning period T_{SC}. The selection

periods T_{SE} of the selection scanning lines X_1 to X_m do not overlap each other.

The common signal power supply 6 is an independent power supply to supply a stable rated voltage to all the common signal supply lines Z_1 to Z_m. The common signal power supply 6 outputs a signal having a phase corresponding to the common signal clock signal CK3 to the common signal supply lines Z_1 to Z_m. While the selection scanning driver 5 is applying the ON voltage V_{ON} to one of all the selection scanning lines X_1 to X_m as a selection signal, i.e., during the selection period T_{SE}, the common signal power supply 6 outputs a low-level voltage V_{LOW} to all the common signal supply lines Z_1 to Z_m as a reference potential for the gray level designation current. During the non-selection period T_{NSE} from the end of the selection period T_{SE} of the selection scanning line X_i of the ith row till the beginning of the selection period T_{SE} of the selection scanning line X_{i+1} of the (i+1)th row, the common signal power supply 6 outputs a high-level voltage V_{HIGH} as a reference potential for a driving current. Hence, when the common signal from the common signal power supply 6 is the voltage V_{LOW}, the selection scanning driver 5 outputs the selection signal of the ON voltage V_{ON} to one selection scanning line X_i of the selection scanning lines X_1 to X_m. The selection scanning driver 5 outputs the selection signal of the

OFF voltage V_{OFF} to the selection scanning lines X_1 to X_m except the selection scanning line X_i. When the common signal output from the common signal power supply 6 drops from the high-level voltage V_{HIGH} to the low-level voltage V_{LOW}, the selection signal output from the selection scanning driver 5 to one of the selection scanning lines X_1 to X_m rises. When the common signal output from the common signal power supply 6 rises from the low-level voltage V_{LOW} to the high-level voltage V_{HIGH}, the selection signal of the ON voltage V_{ON} output from the selection driver 5 to one of the selection scanning lines X_1 to X_m falls.

The low-level voltage V_{LOW} (the reference voltage for the designation current) as the common signal output from the common signal power supply 6 is lower than the reference voltage V_{SS}. However, the low-level voltage V_{LOW} may be equal to the reference voltage V_{SS}. For this reason, even when the third transistors 23 of the pixels $P_{i,1}$ to $P_{i,n}$ are ON during the selection period T_{SE} of the ith row, a voltage of 0 V or a reverse bias voltage is applied between the anode and the cathode of each of the light-emitting elements $E_{i,1}$ to $E_{i,n}$ because the voltage V_{LOW} of the common signal is lower than the reference voltage V_{SS}. Hence, no current flows in the light-emitting elements $E_{i,1}$ to $E_{i,n}$. Light is not emitted. On the other hand, the high-level voltage (the reference voltage for the

driving current) V_{HIGH} output from the common signal power supply 6 is set to be higher than the reference voltage V_{SS}. That is, when the common signal is the voltage V_{HIGH}, the selection scanning driver 5 applies the OFF voltage V_{OFF} to all the selection scanning lines X_1 to X_m. The transistors 21 and 22 of all the pixels $P_{1,1}$ to $P_{m,n}$ are turned off. A forward bias is applied between the light-emitting elements $E_{1,1}$ to $E_{m,n}$ and the transistors 23 connected in series with the light-emitting elements $E_{1,1}$ to $E_{m,n}$.

The voltage V_{HIGH} will be described. FIG. 7 is a graph showing the current vs. voltage characteristic of the N-channel field effect transistor 23. Referring to FIG. 7, the abscissa represents the voltage value between the drain and the source. The ordinate represents the current value between the drain and the source. In the unsaturated region (the region where source-drain voltage V_{DS} < drain saturation threshold voltage V_{TH}: the drain saturation threshold voltage V_{TH} is a function of a gate-source voltage V_{GS} and is uniquely defined in accordance with the source-drain voltage V_{DS} when the gate-source voltage V_{GS} is determined) shown in FIG. 7, when the gate-source voltage V_{GS} has a predetermined value, a source-drain current I_{DS} increases as the source-drain voltage V_{DS} increases. In the saturated region (source-drain voltage $V_{DS} \geqq$ drain saturation threshold voltage V_{TH})

shown in FIG. 7, when the gate-source voltage V_{GS} has a predetermined value, the source-drain current I_{DS} is almost constant even when the source-drain voltage V_{DS} increases.

Referring to FIG. 7, gate-source voltages V_{GS0} to V_{GSMAX} have a relationship given by $V_{GS0} = 0$ [V] < $V_{GS1} < V_{GS2} < V_{GS3} < V_{GS4} < V_{GSMAX}$. That is, as is apparent from FIG. 7, when the source-drain voltage V_{DS} has a predetermined value, the source-drain current I_{DS} increases as the gate-source voltage V_{GS} increases independently of whether it is the unsaturated region or saturated region. In addition, as the gate-source voltage V_{GS} increases, the drain saturation threshold voltage V_{TH} increases.

As described above, in the unsaturated region, when the source-drain voltage V_{DS} changes even slightly, the source-drain current I_{DS} changes. In the saturated region, when the gate-source voltage V_{GS} is defined, the source-drain current I_{DS} is uniquely defined independently of the source-drain voltage V_{DS}.

When the maximum gate-source voltage V_{GSMAX} is being applied to the third transistor 23, the source-drain current I_{DS} is set to the value of the current that flows between the anode 51 and the cathode of the light-emitting element $E_{i,j}$ that emits light at the maximum luminance.

In addition, to make the third transistor 23

maintain the saturated region even when the gate-source voltage V_{GS} of the third transistor 23 is the maximum voltage V_{GSMAX}, the following condition is satisfied.

$$V_{HIGH} - V_E - V_{SS} \geqq V_{THMAX}$$

where V_E is the voltage between the anode and the cathode voltage, which is required by the light-emitting element $E_{i,j}$ for emitting light at the maximum luminance during the light emission life period. V_{THMAX} is the saturation threshold voltage between the source and the drain of the third transistor 23, which corresponds to V_{GSMAX}. The voltage V_{HIGH} is set such that the above condition is satisfied. Hence, even when the source-drain voltage V_{DS} of the third transistor 23 becomes low due to the voltage division of the light-emitting element $E_{i,j}$ connected in series with the transistor 23, the source-drain voltage V_{DS} always falls within the range of the saturated state. For this reason, the source-drain current I_{DS} that flows to the third transistor 23 is uniquely defined by the gate-source voltage V_{GS}.

The data driver 3 will be described next. As shown in FIG. 1, the signal lines Y_1 to Y_n are connected to current terminals CT_1 to CT_n of the data driver 3, respectively. The data driver 3 receives the control signal group D_{CNT} including the data driver clock signal CK1, start signal ST1, and latch signal L

from the controller 11. The data driver 3 also receives the 8-bit red digital gray level image signal S_R, green digital gray level image signal S_G, and blue digital gray level image signal S_B from an external circuit. The received digital signals are converted into analog signals by the D/A converter in the data driver 3. The data driver 3 controls such that the gray level designation current I_{DATA} based on the latch signal L and the converted analog signals flows from the signal lines Y_1 to Y_n to the current terminals CT_1 to CT_n of the data driver 3. The gray level designation current I_{DATA} is a current that is equivalent to the current level (current value) that flows to the light-emitting elements $E_{1,1}$ to $E_{m,n}$ to cause them to emit light at a luminance corresponding to a gray level image signal from an external circuit. The gray level designation current I_{DATA} flows from the signal lines Y_1 to Y_n to the current terminals CT_1 to CT_n.

The switching circuit 7 is formed of switching circuits S_1 to S_n. The switching circuits S_1 to S_n are connected to the signal lines Y_1 to Y_n, respectively. In addition, the current terminals CT_1 to CT_n of the data driver 3 are connected to the switching circuits S_1 to S_n, respectively. Each of the switching circuits S_1 to S_n receives the switching signal ϕ and a reset voltage V_{RST} from the controller 11.

A switching circuit S_j (the switching circuit S_j is connected to the signal line Y_j of the jth column) switches between two operations: an operation in which the gray level designation current I_{DATA} is supplied from the path between the drain 23d and the source 23s of the third transistor 23 and the signal line Y_j to a current terminal CT_j of the data driver 3; and an operation in which the reset voltage V_{RST} having a predetermined voltage level is output from the controller 11 to the signal line Y_j. More specifically, when the switching signal ϕ input from the controller 11 to the switching circuit S_j is at high level, the switching circuit S_j cuts off the current of the current terminal CT_j. The switching circuit S_j also outputs the reset voltage V_{RST} from the controller 11 to the signal line Y_j. On the other hand, when the switching signal ϕ input from the controller 11 to the switching circuit S_j is at low level, the switching circuit S_j supplies the gray level designation current I_{DATA} between the current terminal CT_j and the signal line Y_j to the path between the drain 23d and the source 23s of the transistor 23 and the signal line Y_j. The switching circuit S_j also cuts off the reset voltage V_{RST} from the controller 11.

In the organic EL display 1 having no switching circuit 7 for reset, assume that, e.g., the pixel $P_{i,j}$ of the ith row on the signal line Y_j of the jth column

should emit light at the highest gray level, as shown in FIG. 9A. Assume that, for this purpose, the gray level designation current I_{DATA} having the maximum current value is supplied to the path between the drain 23d and the source 23s of the third transistor 23 and the signal line Y_j during the selection period T_{SE}. At this time, a highest gray level voltage Vhsb of the current terminal CT_j is much lower than the voltage V_{LOW} and reference voltage V_{SS} of the common signal power supply 6. That is, the potential difference between the current terminal CT_j and the voltage V_{LOW} of the common signal power supply 6 is sufficiently large. For this reason, a large current can rapidly be supplied to the path between the drain 23d and the source 23s of the transistor 23 and the signal line Y_j to charge up the parasitic capacitance of the signal line Y_j, and a steady state can quickly be set. Next, assume that the pixel $P_{i+1,j}$ of the (i+1)th row should emit light at the lowest gray level luminance. Assume that, for this purpose, the gray level designation current I_{DATA} having the minimum current value (the current value is not zero) is to be supplied to the signal line Y_j. That is assume that the potential of the current terminal CT_j is to be changed to a lowest gray level voltage Vlsb which has a small potential difference to the voltage V_{LOW} of the common signal power supply 6 by supplying the very small gray level

designation current I_{DATA}, and the gray level designation current I_{DATA} should thus be set in the steady state. At this time, the amount of charges which are stored in the parasitic capacitance of the signal line Y_j when the gray level designation current I_{DATA} for the ith row is supplied is large. For this reason, the potential difference that corresponds to the change in potential of the signal line Y_j per unit time becomes small. A long time may therefore be required until the potential of the signal line Y_j is changed from the highest gray level voltage Vhsb to the lowest gray level voltage Vlsb and set in the steady state. In addition, when the selection period T_{SE} is set to be short, a difference corresponding to a voltage V_{DF} is generated before the potential reaches the lowest gray level voltage Vlsb. Hence, the pixel $P_{i+1,j}$ cannot emit light at an accurate luminance.

The organic EL display 1 of this embodiment has the switching circuit 7. Hence, as shown in FIG. 9B, the switching circuit S_j forcibly switches the potential of the signal line Y_j to the reset voltage V_{RST} much higher than the highest gray level voltage Vhsb during the non-selection period T_{NSE}, i.e., before the gray level designation current I_{DATA} for the (i+1)th row is supplied to the path between the drain 23d and the source 23s of the transistor 23 and the signal line Y_j. During the selection period T_{SE}, the

amount of charges stored in the signal line Y_j serving as a parasitic capacitance quickly changes so the signal line Y_j can rapidly be set at a high potential. For this reason, even when the gray level designation current I_{DATA} for the (i+1)th row has a very small current value corresponding to the lowest gray level, the potential can quickly reach the lowest gray level voltage Vlsb.

The reset voltage V_{RST} is set to be higher than the highest gray level voltage Vhsb. The highest gray level voltage Vhsb is set in the steady state in accordance with charges stored in the signal lines Y_1 to Y_n by the gray level designation current I_{DATA} which has a current value equal to a maximum gray level driving current I_{MAX}. The maximum gray level driving current I_{MAX} flows to the light-emitting elements $E_{1,1}$ to $E_{m,n}$ when they emit light at a maximum gray level luminance L_{MAX} for brightest light during the selection period T_{SE}. More preferably, the reset voltage V_{RST} is set to be equal to or higher than an intermediate voltage that has an intermediate value between the lowest gray level voltage Vlsb and the highest gray level voltage Vhsb. The lowest gray level voltage Vlsb is set in the steady state in accordance with charges stored in the signal lines Y_1 to Y_n by the gray level designation current I_{DATA} which has a current value equal to a minimum gray level driving current I_{MIN}.

The minimum gray level driving current I_{MIN} flows to the light-emitting elements $E_{1,1}$ to $E_{m,n}$ when they have a minimum gray level luminance L_{MIN} (however, the current level is more than 0 A) for darkest light. The reset voltage V_{RST} more preferably has a value equal to or more than the lowest gray level voltage Vlsb.

An example of the switching circuit S_j of the jth column will be described. The switching circuit S_j is constituted by a fourth transistor 31 formed of a P-channel field effect transistor and a fifth transistor 32 formed of an N-channel field effect transistor. The gate electrode of the transistor 31 and the gate electrode of the transistor 32 are connected to the controller 11 so that the switching circuit S_j receives the switching signal ϕ. The source electrode of the transistor 31 is connected to the signal line Y_j. The drain electrode of the transistor 31 is connected to the current terminal CT_j of the data driver 3. The drain electrode of the transistor 32 is connected to the signal line Y_j. The source electrode of the transistor 32 is connected to the controller 11 so that the switching circuit S_j receives the reset voltage V_{RST}. In this arrangement, when the switching signal ϕ from the controller 11 is at high level, the fifth transistor 32 is turned on while the fourth transistor 31 is turned off. On the other hand, when the switching signal ϕ from the

controller 11 is at low level, the transistor 31 is turned on while the transistor 32 is turned off. The transistor 31 may be set to a P-channel type, and the transistor 32 may be set to an N-channel type. In this case, the switching mode of the switching circuit S_j is changed by reversing the phase of the switching signal ϕ.

The period of the switching signal ϕ input to the controller 11 will be described here. As shown in FIG. 8, when the selection scanning driver 5 is applying the ON voltage V_{ON} to one of the selection scanning lines X_1 to X_m, the switching signal ϕ input to the controller 11 is at low level. On the other hand, during the non-selection period T_{NSE} when the selection scanning driver 5 is applying the OFF voltage V_{OFF} to all the selection scanning lines X_1 to X_m, the switching signal ϕ input to the controller 11 is at high level. That is, the switching signal ϕ input to the controller 11 is a pulse signal which changes to high level for each of the $\underline{m}$ non-selection periods T_{NSE} in one selection period T_{SE}.

The switching circuits S_1 to S_n are circuits which switch between two operations: an operation for supplying the gray level designation current I_{DATA} from the signal lines Y_1 to Y_n to the current terminals CT_1 to CT_n in accordance with the switching signal ϕ from the controller 11; and an operation for forcibly

charging the signal lines Y_1 to Y_n to the reset voltage V_{RST}. When the switching signal ϕ input from the controller 11 is at low level, i.e., during the selection period T_{SE} of one of the selection scanning lines X_1 to X_m, each switching circuit turns on the transistor 31 and off the transistor 32. With this operation, the gray level designation current I_{DATA} flows to the current terminals CT_1 to CT_n through the paths between the drain 23d and the source 23s of the transistors 23 and the signal lines Y_1 to Y_n. When the switching signal ϕ input from the controller 11 is at high level, i.e., during the non-selection period T_{NSE} of all the selection scanning lines X_1 to X_m, each switching circuit turns off the transistor 31 and on the transistor 32. At this time, the gray level designation current I_{DATA} does not flow to the drains 23d and sources 23s of the transistors 23 and the signal lines Y_1 to Y_n. Instead, the potentials of the signal lines Y_1 to Y_n are forcibly set to the reset voltage V_{RST}.

Hence, in the selection period T_{SE} of each row, the gray level designation current I_{DATA} flows from the signal lines Y_1 to Y_n to the current terminals CT_1 to CT_n. On the other hand, in the non-selection period T_{NSE} between the rows, the reset voltage V_{RST} is forcibly applied to the signal lines Y_1 to Y_n. The charge amount of the parasitic capacitance of the

signal lines Y_1 to Y_n becomes almost the same as the charge amount when the small gray level designation current I_{DATA} flows, and the steady state is set. For this reason, even when the current value of the gray level designation current I_{DATA} is very small, the steady state can quickly be set.

In the selection period T_{SE} of each row, the data driver 3 generates the gray level designation current I_{DATA} which should flow from the common signal supply lines Z_1 to Z_m to the current terminals CT_1 to CT_n through the transistors 23, transistors 21, signal lines Y_1 to Y_n, and switching circuits S_1 to S_n. The current value of the gray level designation current I_{DATA} is equal to the current value of the driving current which is supplied to the light-emitting elements $E_{1,1}$ to $E_{m,n}$ to cause them to emit light at a luminance gray level corresponding to image data.

A method of causing the data driver 3, selection scanning driver 5, and common signal power supply 6 to drive the organic EL display panel 2 and the display operation of the organic EL display 1 will be described next.

As shown in FIG. 8, on the basis of the selection scanning driver clock signal CK2 received from the controller 11, the selection scanning driver 5 sequentially applies the ON voltage V_{ON} to the selection scanning line X_1 of the first row to the

selection scanning line X_m of the mth row in this order (the selection scanning line X_1 follows the selection scanning line X_m) during each selection period T_{SE} to select the selection scanning line. Accordingly, the selection scanning lines X_1 to X_m are scanned in this order.

Simultaneously when the selection scanning driver 5 sequentially selects and scans the selection scanning lines, the common signal power supply 6 outputs common signals to all the common signal supply lines Z_1 to Z_m. The common signals output to the common signal supply lines Z_1 to Z_m are synchronized with each other. In all pixel circuits $D_{1,1}$ to $D_{m,n}$, the common signal of the voltage V_{LOW} is input to the source electrode 22s of the second transistor 22 and the source electrode 23s of the third transistor 23.

In addition, during the sequential scanning by the selection scanning driver, the data driver 3 receives and latches the 8-bit red digital gray level image signal S_R, green digital gray level image signal S_G, and blue digital gray level image signal S_B from an external circuit on the basis of the data driver clock signal CK1 input from the controller 11. When the selection signal V_{ON} that selects the selection scanning line X_i is output, the switching signal ϕ is synchronously input to the switching circuit 7. The switching signal ϕ turns on the transistor 31 and off

the transistor 32. The gray level designation currents I_{DATA} having current values based on the gray level of the latched signals flow to the current terminals CT_1 to CT_n of the data driver 3 through the common signal supply line Z_i, the paths between the drains 23d and the sources 23s of the transistors 23 of the pixels $P_{i,1}$ to $P_{i,n}$, the paths between the drains 21d and the sources 21s of the transistors 21 of the pixels $P_{i,1}$ to $P_{i,n}$, and the signal lines Y_1 to Y_n.

When the selection signal of ON level V_{ON} is being output to the given selection scanning line X_i, a selection signal of off level is output to the remaining selection scanning lines X_1 to X_m (except X_i). This period is the selection period T_{SE} of the ith row. Hence, for the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row, the first transistor 21 and second transistor 22 are ON. For the pixel circuits $D_{1,1}$ to $D_{m,n}$ (except the pixel circuits $D_{i,1}$ to $D_{i,n}$) of the remaining rows, the first transistor 21 and second transistor 22 are OFF.

That is, when the voltage V_{ON} is applied to the selection scanning line X_i during the selection period T_{SE} of the ith row, the first transistors 21 and second transistors 22 in the pixel circuits $D_{i,1}$ to $D_{i,n}$ are turned on. At this time, the voltage V_{LOW} from the common signal supply lines Z_1 to Z_m is supplied to the drain electrodes 23d of the third transistors 23 and

the drain electrodes 22d of the second transistors 22 of all the pixel circuits $D_{1,1}$ to $D_{m,n}$. Simultaneously, the data driver 3 is going to supply the gray level designation current I_{DATA} to the current terminals CT_1 to CT_n in accordance with the latch signal L. At this time, the switching signal ϕ is input from the controller 11 to the switching circuit 7 to turn on the transistors 31 and off the transistors 32. Hence, the current terminals CT_1 to CT_n are electrically connected to the common signal supply line Z_i. The voltage V_{LOW} of the common signal supply line Z_i is set to be higher than the potentials of the current terminals CT_1 to CT_n. For this reason, a voltage that supplies the gray level designation current I_{DATA} to the path between the source and the drain of the third transistor 23 is applied between the gate 23g and the source 23s and between the source 23s and the drain 23d of the third transistor 23.

The current value of the gray level designation current I_{DATA} is based on the red digital gray level image signal S_R, green digital gray level image signal S_G, and blue digital gray level image signal S_B input to the data driver 3. During the selection period T_{SE}, the data driver 3 stores charges in the capacitor 24 between the gate 23g and the source 23s of the transistor 23 of each of the pixel $P_{i,1}$ to $P_{i,n}$. With this operation, the current value of the gray level

designation current I_{DATA} that flows to the current terminals CT_1 to CT_n of the data driver 3 through the common signal supply line Z_i, the paths between the drains 23d and the sources 23s of the transistors 23 of the pixels $P_{i,1}$ to $P_{i,n}$, the paths between the drains 21d and the sources 21s of the transistors 21 of the pixels $P_{i,1}$ to $P_{i,n}$, and the signal lines Y_1 to Y_n is set in the stead state. That is, the gray level designation current I_{DATA} having a predetermined current value is supplied to the paths between the drains 23d and the sources 23s of the transistors 23 of the pixels $P_{i,1}$ to $P_{i,n}$. After that, the capacitor 24 can hold the charges at least during one scanning period T_{SC} or more. In other words, the transistor 23 is going to supply a driving current having a current value equal to the gray level designation current I_{DATA} at least for a time corresponding to one scanning period T_{SC} or more by the charges in the capacitor 24. That is, the capacitor 24 serves as a storage means for storing the current value of the gray level designation current I_{DATA} that flows during the selection period T_{SE} and flowing a driving current having a current value equal to the gray level designation current I_{DATA} to the light-emitting elements $E_{i,1}$ to $E_{i,n}$ during the non-selection period T_{NSE}.

Hence, during the selection period T_{SE} of the ith row, the first transistors 21 and second transistors 22

of the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row are turned on. Accordingly, the gray level designation current I_{DATA} supplied from the signal lines Y_1 to Y_n to the data driver 3 is stored in the capacitor 24 of each of the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row. In each of the pixel circuits $D_{1,1}$ to $D_{m,n}$ (except the pixel circuits $D_{i,1}$ to $D_{i,n}$) of the remaining rows, the first transistor 21 and second transistor 22 are OFF. Hence, the gray level designation current I_{DATA} is not stored in the capacitors 24 of the remaining rows. That is, the third transistors 23 of the remaining rows cannot flow the gray level designation current I_{DATA}. As described above, during the selection period T_{SE} of the ith row, charges between the gate and the source of the third transistor 23 are received by each of the pixel circuits $D_{i,1}$ to $D_{i,n}$ in correspondence with the gray level designation current I_{DATA}. Accordingly, the charges between the gate and the source of the third transistor 23, which have been stored so far, are refreshed. During the plurality of non-selection periods T_{NSE} after the selection period T_{SE} of the ith row, the pixel circuits $D_{i,1}$ to $D_{i,n}$ supply driving currents (the driving currents have the same level as that of the gray level designation current I_{DATA}) corresponding to the charges stored between the gates and the sources of the third transistors 23 to the light-emitting elements $E_{i,1}$ to $E_{i,n}$, thereby causing

them to emit light.

As described above, the selection scanning driver 5 line-sequentially shifts the selection signal from the first row to the mth row. Accordingly, the gray level designation current I_{DATA} flows sequentially to the pixel circuits $D_{1,1}$ to $D_{1,n}$ of the first row to the pixel circuits $D_{m,1}$ to $D_{m,n}$ of the mth row in accordance with the red digital gray level image signal S_R, green digital gray level image signal S_G, and blue digital gray level image signal S_B input to the data driver 3. With this operation, the charges stored between the gate and the source of each third transistor 23 are refreshed. When such line-sequential scanning is repeated, an image is displayed on the display section 4 of the organic EL display panel 2.

The operation of causing the pixel circuits $D_{i,1}$ to $D_{i,n}$ to receive the gray level designation current I_{DATA} during the selection period T_{SE} of the ith row and the operation of causing the light-emitting elements $E_{i,1}$ to $E_{i,n}$ to emit light on the basis of the received gray level designation current I_{DATA} will be described here in detail.

During the selection period T_{SE} of the ith row, a selection signal of the ON voltage V_{ON} is output from the selection scanning driver 5 to the selection scanning line X_i of the ith row in accordance with the control signal group G_{CNT} including the clock signal

CK2 from the controller 11. Then, the first transistors 21 and second transistors 22 of all the pixel circuits $D_{i,1}$ to $D_{i,n}$ connected to the selection scanning line X_i are set in the ON state during the selection period T_{SE}. At the start of the selection period T_{SE} of the ith row, the common signal changes to the voltage V_{LOW}. During the selection period T_{SE} of the ith row, the voltage V_{LOW} is applied to all the common signal supply lines Z_1 to Z_m. Since the second transistor 22 is ON, a voltage is applied even to the gate electrode 23g of the third transistor 23. Hence, the third transistor 23 is turned on.

Furthermore, when a given column of the light-emitting elements $E_{i,1}$ to $E_{i,n}$ of the selected row is to be caused to emit light during the non-selection period T_{NSE} (to be described later), the data driver 3 controls the potential of one of the current terminals CT_1 to CT_n, which corresponds to the column to be caused to emit light, to be lower than the voltage V_{LOW}. Accordingly, in the column of the pixel circuit $D_{i,j}$, which should emit light, the gray level designation current I_{DATA} flows from the common signal supply line Z_i to the data driver 3. When a given column of the light-emitting elements $E_{i,1}$ to $E_{i,n}$ of the selected ith row is to be inhibited from emitting light during the non-selection period T_{NSE} (to be described later), the data driver 3 controls the

potential of one of the current terminals CT_1 to CT_n, which corresponds to the column that should be inhibited from emitting light, to be equal to the voltage V_{LOW}. Accordingly, in the column of the pixel circuit $D_{i,j}$, which should emit light, the gray level designation current I_{DATA} does not flow from the common signal supply line Z_i to the data driver 3. During the selection period T_{SE} of the ith row, the data driver 3 controls the potentials of the current terminals CT_1 to CT_n to supply the gray level designation current I_{DATA} to the data driver 3 to the signal lines Y_1 to Y_n (the gray level designation current I_{DATA} does not flow for a column which should be inhibited from emitting light). In each of the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row, the first transistor 21 and second transistor 22 are turned on. Hence, the gray level designation current I_{DATA} flows through a path of common signal supply line Z_i → paths between the drains 23d and the sources 23s of the transistors 23 of the pixels $P_{i,1}$ to $P_{i,n}$ → paths between the drains 21d and the sources 21s of the transistors 21 of the pixels $P_{i,1}$ to $P_{i,n}$ → signal lines Y_1 to Y_n → transistors 31 of the switching circuits S_1 to S_n → current terminals CT_1 to CT_n of the data driver 3.

As described above, charges corresponding to the current value of the gray level designation current I_{DATA} are received by the pixel circuits $D_{i,1}$ to $D_{i,n}$.

At this time, in all of the first to nth columns, the current value of the driving current flowing to the light-emitting elements $E_{i,1}$ to $E_{i,n}$ is equal to the current value of the gray level designation current I_{DATA}. The current value is designated by the data driver 3. Hence, the current value of the gray level designation current I_{DATA} which is continuously held during the non-selection period T_{NSE} is constant.

That is, during the selection period T_{SE}, the gray level designation current I_{DATA} flows to the third transistor 23. The voltage across the common signal supply line Z_i, third transistors 23, first transistors 21, signal lines Y_1 to Y_n, switching circuits S_1 to S_n, and data driver 3 is set in the steady state. Accordingly, a voltage at a level corresponding to the level of the gray level designation current I_{DATA} that flows to the third transistor 23 is applied between the gate electrode 23g and the source electrode 23s of the third transistor 23. Charges with a magnitude corresponding to the level of the voltage between the gate electrode 23g and the source electrode 23s of the third transistor 23 are stored in the capacitor 24. During the selection period T_{SE} of the ith row, in each of the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row, the first transistor 21 and second transistor 22 function to supply the gray level designation current I_{DATA} flowing to the signal line Y_j to the third transistor

23. The third transistor 23 functions to convert the current value of the gray level designation current I_{DATA} into the value of the voltage between the gate and the source.

As described above, during the selection period T_{SE} of the ith row, the magnitude of the charges stored in the capacitors 24 of the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row is refreshed from the preceding scanning period T_{SC}. At the same time, the drain-source current level and the source-drain voltage level of the third transistors 23 of the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row are also refreshed from the preceding scanning period T_{SC}.

The potential at an arbitrary point on the path of the third transistor 23, first transistor 21, and signal line Y_j changes depending on the internal resistance of the transistors 21, 22, and 23, which changes over time. However, in this embodiment, the current value of the gray level designation current I_{DATA} that flows through the path of third transistor 23 → first transistor 21 → signal line Y_j is forcibly supplied by the data driver 3. Hence, even when the internal resistance of the transistors 21, 22, and 23 changes over time, the gray level designation current I_{DATA} that flows through the path of third transistor 23 → first transistor 21 → signal line Y_j has a desired level.

During the selection period T_{SE} of the ith row, the common signal supply line Z_i is set to the voltage V_{LOW} that is equal to or lower than the reference voltage V_{SS}. In addition, a zero bias or reverse bias is applied across the anodes and the cathodes of the light-emitting elements $E_{i,1}$ to $E_{i,n}$ of the ith row. Hence, no current flows to the light-emitting elements $E_{i,1}$ to $E_{i,n}$, and they does not emit light.

At the end time of the selection period T_{SE} of the ith row (at the start time of the non-selection period T_{NSE} of the ith row), the selection signal output from the selection scanning driver 5 to the selection scanning line X_i changes from the high-level potential V_{ON} to the low-level potential V_{OFF}. The selection scanning driver 5 applies the OFF voltage V_{OFF} to the gate electrodes 21g of the first transistors 21 and the gate electrodes 22g of the second transistors 22 of the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row.

Hence, during the non-selection period T_{NSE} of the ith row, the first transistors 21 of the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row are turned off. The gray level designation current I_{DATA} that flows from the common signal supply line Z_i to the corresponding signal lines Y_1 to Y_n is cut off. In addition, during the non-selection period T_{NSE} of the ith row, in all the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row, even when the transistor 22 is turned off, charges stored in

the capacitor 24 during the immediately preceding selection period T_{SE} of the ith row are confined by the second transistor 22. For this reason, in all the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row, the third transistor 23 is kept ON during the non-selection period T_{NSE}. That is, in all the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row, the second transistor 22 holds the gate-source voltage level V_{GS} of the third transistor 23 such that the gate-source voltage level V_{GS} of the third transistor 23 during the non-selection period T_{NSE} becomes equal to the gate-source voltage level V_{GS} of the third transistor 23 during the selection period T_{SE}.

During the non-selection period T_{NSE}, the common signal output from the common signal power supply 6 to the common signal supply line Z_i rises to the voltage V_{HIGH}. During the non-selection period T_{NSE}, the cathodes of the light-emitting elements $E_{i,1}$ to $E_{i,n}$ of the ith row are at the reference voltage V_{SS}. The common signal supply line Z_i is at the voltage V_{HIGH} higher than the reference voltage V_{SS}. In addition, charges corresponding to the gray level designation current I_{DATA} flowing during the selection period T_{SE} are stored between the gate 23g and the source 23s of the third transistor 23 connected in series. In this case, a forward bias voltage corresponding to the gray level designation current I_{DATA} is applied to the

light-emitting elements $E_{i,1}$ to $E_{i,n}$ of the ith row. Hence, in all the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row, a driving current equal to the gray level designation current I_{DATA} flows from the common signal supply line Z_i to the light-emitting elements $E_{i,1}$ to $E_{i,n}$ of the ith row through the drains 23s and sources 23s of the third transistors 23. Hence, the light-emitting elements $E_{i,1}$ to $E_{i,n}$ emit light.

More specifically, in each of the pixel circuits $D_{i,1}$ to $D_{i,n}$ during the non-selection period T_{NSE}, the first transistor 21 functions to electrically disconnect the corresponding signal line Y_j from the third transistor 23 such that the gray level designation current I_{DATA} flowing to the signal line Y_j does not flow to the third transistor 23. The second transistor 22 functions to hold the voltage between the gate 23g and the source 23s of the third transistor 23, which is converted during the selection period T_{SE}, by confining the charges in the capacitor 24. In all the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row, when the common signal is set to the voltage V_{HIGH} during the non-selection period T_{NSE}, the third transistor 23 functions to supply a driving current of a level corresponding to the held gate-source voltage level to the light-emitting element $E_{i,j}$.

Hence, the light-emitting elements $E_{i,1}$ to $E_{i,n}$ of the ith row do not emit light during each of the

selection periods T_{SE} of the first to mth rows. The light-emitting elements $E_{i,1}$ to $E_{i,n}$ emit light during each of the m non-selection periods T_{NSE} in one scanning period T_{SC}. The current value of the driving current that flows to the light-emitting elements $E_{i,1}$ to $E_{i,n}$ when the common signal is at V_{HIGH} is the same as that of the current flowing to the third transistor 23 of each of the pixel circuits $D_{i,1}$ to $D_{i,n}$. That is, the current value is equal to that of the gray level designation current I_{DATA} that flows to the third transistor 23 of each of the pixel circuits $D_{i,1}$ to $D_{i,n}$ during the selection period T_{SE} of the ith row. During the selection period T_{SE} of the ith row, when the current value that flows to the third transistor 23 of each of the pixel circuits $D_{i,1}$ to $D_{i,n}$ of the ith row is set, the driving current of each of the light-emitting elements $E_{i,1}$ to $E_{i,n}$ has a desired current value. Hence, the light-emitting elements $E_{i,1}$ to $E_{i,n}$ emit light at a desired gray level luminance.

As described above, in this embodiment, even when the current vs. voltage characteristic of the third transistor 23 changes between the pixel circuits $D_{1,1}$ to $D_{m,n}$, the gray level designation current I_{DATA} having a predetermined current value is forcibly supplied between the source 23s and the drain 23d of the third transistor 23 during the selection period T_{SE}. In addition, when the voltage between the source

23s and the drain 23d of the third transistor 23 is always saturated, as shown in FIG. 7, the common signal of the voltage V_{HIGH} is output to the common signal supply lines Z_1 to Z_m during the non-selection period T_{NSE}. Accordingly, a driving current having a current value equal to the gray level designation current I_{DATA} is supplied between the source 23s and the drain 23d of the third transistor 23. For this reason, the luminance does not vary between the light-emitting elements $E_{1,1}$ to $E_{m,n}$ of the pixels. That is, in this embodiment, even when a luminance gray level signal having the same voltage level is output to pixels, any in-plane variation in luminance between the pixels can be suppressed. Hence, the organic EL display 1 of this embodiment can display a high-quality image.

During the non-selection period T_{NSE}, the common signal changes to V_{HIGH} $\underline{m}$ times. The light emission duty of the light-emitting element $E_{i,j}$ is about 50%. To the contrary, in a simple matrix driving display having $\underline{m}$ light-emitting elements arrayed in the vertical direction and $\underline{n}$ light-emitting elements arrayed in the horizontal direction, the light emission duty is 1/m. In the simple matrix driving display, as the resolution becomes high, the light emission duty of the light-emitting element decreases. In the organic EL display 1 of this embodiment, however, even when the resolution becomes high, the light emission duty of the

light-emitting element $E_{i,j}$ does not decrease. The organic EL display 1 can display an image at a high luminance, high contrast, and high resolution.

One selection scanning line X_i and one common signal supply line Z_i are arranged in each row. Not a signal for scanning but a common signal is simply output from the common signal power supply 6 to the common signal supply line Z_i. The only shift register for scanning, which is arranged in the organic EL display 1, is the selection scanning driver 5. A shift register is generally formed from m flip-flop circuits. The common signal power supply 6 only needs to output signals having the same waveform to all the common signal supply lines Z_1 to Z_m and therefore can have a simplified circuit structure. For this reason, in the common signal power supply 6, the mounting area is smaller, the structure is simpler, and the number of elements is smaller than a shift register. As compared to a conventional organic EL display having two shift registers serving as drivers, the organic EL display 1 of this embodiment can reduce the manufacturing cost and increase the yield.

[Second Embodiment]

An organic EL display according to the second embodiment will be described next.

Even in the second embodiment, the organic EL display comprises an organic EL display panel 2, data

driver 3, and selection scanning driver 5, like the organic EL display 1 according to the first embodiment shown in FIG. 1. The data driver 3, a display section 4, the selection scanning driver 5, pixel circuits $D_{1,1}$ to $D_{m,n}$, and light-emitting elements $E_{1,1}$ to $E_{m,n}$ have the same structures as those in the organic EL display 1 of the first embodiment, and a detailed description thereof will be omitted in the second embodiment.

In the second embodiment, a common signal power supply 6 is arranged in a controller 11 connected to the organic EL display 1, as shown in FIG. 10. For this reason, the ratio of the occupied area of the pixels on the substrate of the organic EL display 1 can be increased.

The organic EL display 1 according to the second embodiment can operate in accordance with the waveform chart shown in FIG. 8, as in the first embodiment.

[Third Embodiment]

The third embodiment will be described next. This embodiment is the same as the first embodiment except that a drain 22d of a second transistor 22 of a pixel circuit $D_{i,j}$ of each pixel $P_{i,j}$ is not connected to a common signal supply line Z_i but to a selection scanning line X_i, as shown in FIG. 11. The same reference numerals as in the first embodiment denote the same parts in the third embodiment, and a detailed description thereof will be omitted.

In the transistor 22, the drain electrode 22d and gate electrode 22g are connected to the selection scanning line X_i. A source electrode 22s is connected to a gate electrode 23g of a third transistor 23. The transistor 22 is an N-channel amorphous silicon thin film transistor, like a first transistor 21 and the transistor 23.

The transistor 22 operates upon receiving the voltage shown in the waveform chart in FIG. 8. That is, as shown in FIG. 12A, during a selection period T_{SE}, the transistor 22 of each of pixels $P_{i,1}$ to $P_{i,n}$ is turned on by a scanning signal of an ON-level (high-level) voltage V_{ON} from the selection scanning line X_i so that the voltage from the selection scanning line X_i is applied to the gate of the transistor 23. Simultaneously, the transistor 21 of each of the pixels $P_{i,1}$ to $P_{i,n}$ is turned on. In addition, the transistor 23 of each of the pixels $P_{i,1}$ to $P_{i,n}$ is turned on by the gate voltage applied by the transistor 22 during the selection period T_{SE}. Hence, the data driver 3 supplies a gray level designation current I_{DATA} to the paths between the drains 23d and the sources 23s of the transistors 23 of the pixels $P_{i,1}$ to $P_{i,n}$ and signal lines Y_1 to Y_n in the direction indicated by the arrow in FIG. 12A. The current value of the gray level designation current I_{DATA} at this time corresponds to the gray level of a red digital gray level image signal

S_R, green digital gray level image signal S_G, and blue digital gray level image signal S_B input to the data driver 3. Charges corresponding to the current value of the gray level designation current I_{DATA} are stored in capacitors 24 connected to the paths between the gates 23g and the sources 23s of the transistors 23 of the pixels $P_{i,1}$ to $P_{i,n}$ during the selection period T_{SE}.

During a non-selection period T_{NSE}, the transistor 21 and transistor 22 of each of the pixels $P_{i,1}$ to $P_{i,n}$ are turned off by a scanning signal of an OFF-level voltage V_{OFF} supplied to the selection scanning line X_i. A voltage V_{HIGH} is applied to all common signal supply lines Z_1 to Z_m. For this reason, the voltages between the sources 23s and the drains 23d of all the transistors 23 are saturated. The voltages between the gates 23g and the sources 23s of all the transistors 23 have a voltage value corresponding to the charges stored in the capacitors 24 during the selection period T_{SE}. As shown in FIG. 12B, a driving current having a current value equal to the gray level designation current I_{DATA} flows between the sources 23s and the drains 23d of all the transistors 23. Since the voltage V_{HIGH} is much higher than a reference voltage V_{SS}, the driving current flows in the direction indicated by the arrow in FIG. 12A to cause light-emitting elements $E_{1,1}$ to $E_{m,n}$ to emit light.

The present invention is not limited to the above embodiments. Various changes and modifications of design may be done without departing from the spirit and scope of the invention.

For example, in the above embodiments, all the first transistor 21, second transistor 22, and third transistor 23 of the pixel circuit $D_{i,j}$ are N-channel transistors. However, all the transistors may be formed from P-channel transistors, and the anode and cathode of the light-emitting element $E_{i,j}$ may be connected in the reverse direction. At this time, the waveforms shown in FIG. 8 are inverted.

In the embodiments, the light-emitting period of the light-emitting elements $E_{1,1}$ to $E_{m,n}$ is the non-selection period T_{NSE} between the selection periods T_{SE}. the light-emitting period of the light-emitting element $E_{i,j}$ is the $\underline{m}$ discontinuous non-selection periods T_{NSE} between the selection period T_{SE} of the ith row and the selection period T_{SE} of the next ith row. As shown in FIG. 13, all the light-emitting elements $E_{1,1}$ to $E_{m,n}$ may be simultaneously caused to emit light during the non-selection period T_{NSE} after charges by the gray level designation current I_{DATA} are written in the capacitors 24 of all the light-emitting elements $E_{1,1}$ to $E_{m,n}$. At this time, when at least one of the selection period T_{SE} during one scanning period T_{SC} and (m-1) reset periods T_R when the reset voltage

V_{RST} is applied to the signal lines Y_1 to Y_n is set to be short, the non-selection period T_{NSE}, i.e., the light-emitting period of the light-emitting elements $E_{1,1}$ to $E_{m,n}$ can be made relatively long. Referring to FIG. 13, after the selection scanning line X_m is selected, to return the charges stored in the parasitic capacitances of the signal lines Y_1 to Y_n in the write mode of the pixels $P_{m,1}$ to $P_{m,n}$ of the selection scanning line X_m, the reset voltage V_{RST} may be applied to increase the number of reset periods T_R during one scanning period T_{SC} to $\underline{m}$.

In the above embodiments, an organic EL element is used. However, any other light-emitting element having rectification properties may be used. That is, the light-emitting element may be an element which flows no current when a reverse bias voltage is applied but flows a current when a forward bias voltage is applied, and also emits light at a luminance correspondence with the magnitude of the flowing current. An example of a light-emitting element having rectification properties is an LED (Light Emitting Diode) element.

In the above embodiments, the data driver 3 and selection scanning driver 5 operate on the basis of a clock signal input from the controller 11. However, the clock signal CK3 that is output from the common signal power supply 6 and used as a common signal may be input to the selection scanning driver 5 as the

clock signal CK2.

In the above embodiments, the number of times the common signal output from the common signal power supply 6 changes to low level, i.e., the gray level designation current I_{DATA} is supplied is one per selection period T_{SE}. However, the number of times may be two or more per selection period T_{SE}.

According to the present invention, when a driving current flows to the light-emitting element, the light-emitting element emits light. The current value of the driving current corresponds to the voltage held between the gates 23g and the source 23s of the transistor 23 of the pixel circuit. The voltage value is obtained by converting the current value of the designation current. For these reasons, the current value of the driving current coincides with the current value of the designation current. The light-emitting element emits light at a luminance depending on the current value of the designation current. That is, the light-emitting element emits light at a luminance set by the current value of the designation current. Hence, if the current value of the designation current does not change between pixels, the luminance does not vary between the plurality of light-emitting elements, and a high-quality image can be displayed.

It is only the scanning driver 5 that supplies a selection signal to each scanning line. No drivers for

scanning are arranged at all. In addition, the common signal power supply 6 has a smaller number of elements than that of the scanning driver and therefore has a simple arrangement. Hence, the mounting area of the driver is small.

C L A I M S

1. A display device comprising:

a plurality of scanning lines;

a plurality of signal lines;

a scanning driver which sequentially supplies to the scanning lines selection signals that select the scanning lines;

a data driver which supplies a designation current to said plurality of signal lines within a selection period when the scanning lines are being selected;

a plurality of pixel circuits which supplies a driving current corresponding to a current value of the designation current that flows to the signal lines;

a plurality of optical elements which emit light in accordance with the driving current supplied by said plurality of pixel circuits; and

a power supply which outputs to said plurality of pixel circuits a driving current reference voltage to supply the driving current.

2. A display device according to claim 1, wherein the power supply outputs the driving current reference voltage to said plurality of pixel circuits within a non-selection period.

3. A display device according to claim 2, wherein the non-selection period is a period when none of said plurality of optical elements are selected.

4. A display device according to claim 2, wherein

a reset voltage is output to said plurality of signal lines within the non-selection period.

5. A display device according to claim 1, wherein the power supply selectively outputs the driving current reference voltage and a designation current reference voltage to supply the designation current.

6. A display device according to claim 5, wherein the designation current reference voltage is lower than the driving current reference voltage.

7. A display device according to claim 5, wherein the power supply outputs the designation current reference voltage within the selection period.

8. A display device according to claim 1, wherein the power supply alternately outputs a designation current reference voltage to supply the designation current and the driving current reference voltage.

9. A display device according to claim 1, wherein

the data driver supplies the designation current to the signal lines and the pixel circuits on the basis of a designation current reference voltage output from the power supply within the selection period, and

each of the pixel circuits stores the current value of the designation current and supplies the driving current that is equal to the current value of the designation current on the basis of the driving current reference voltage output from the power supply.

10. A display device according to claim 1, wherein

each of the pixel circuits comprises a driving transistor and a capacitor which is connected between a gate and a source of the driving transistor,

the data driver supplies the designation current to the signal lines and the driving transistors of the pixel circuits on the basis of a designation current reference voltage output from the power supply within the selection period, and

the capacitor stores charges corresponding to the designation current between the gate and the source, and when the driving current reference voltage is input from the power supply, the driving transistor supplies the driving current corresponding to the charges stored between the gate and the source.

11. A display device according to claim 1, wherein each of the pixel circuits comprises

a first transistor in which a gate is connected to the scanning line and one of a drain and a source is connected to the signal line,

a second transistor in which a gate is connected to the scanning line and a designation current reference voltage and the driving current reference voltage are selectively input to one of a drain and a source, and

a driving transistor in which a gate is connected to the other of the drain and the source of the second transistor, one of a drain and a source is connected to

one of the drain and the source of the second transistor, and the other of the drain and the source is connected to the other of the drain and the source of the first transistor and the optical element.

12. A display device according to claim 11, wherein the scanning driver selects the first transistor and the second transistor, which are connected to a predetermined scanning line, within the selection period.

13. A display device according to claim 1, wherein each of the pixel circuits comprises

a first transistor in which a gate is connected to the scanning line and one of a drain and a source is connected to the signal line,

a second transistor in which a gate is connected to the scanning line and one of a drain and a source is connected to the scanning line, and

a driving transistor in which a gate is connected to the other of the drain and the source of the second transistor, one of a drain and a source is connected to the power supply, and the other of the drain and the source is connected to the other of the drain and the source of the first transistor and the optical element.

14. A display device according to claim 13, wherein the scanning driver selects the first transistor and the second transistor, which are connected to a predetermined scanning line, within the

selection period.

15. A display device according to claim 1, wherein the power supply outputs the driving current reference voltage from the end of the selection period of a predetermined scanning line till the beginning of the selection period of a next scanning line.

16. A display device according to claim 1, wherein the optical element has a first electrode connected to the power supply through the pixel circuit and a second electrode to which a reference voltage is applied.

17. A display device according to claim 16, wherein

the power supply selectively outputs the driving current reference voltage and a designation current reference voltage to supply the designation current, and

the driving current reference voltage is not less than the reference voltage, and the designation current reference voltage is not more than the reference voltage.

18. A display device according to claim 1, wherein the optical element is an organic EL element.

19. A display device comprising:

a scanning line group having a scanning line of a first row and a scanning line of a second row;

an optical element group having a first optical element which is connected to the scanning line of the

first row and emits light in accordance with a current value of a first driving current supplied, and a second optical element which is connected to the scanning line of the second row and emits light in accordance with a current value of a second driving current supplied;

a pixel circuit group having a first pixel circuit which is connected to the first optical element and supplies the first driving current equal to a current value of a first designation current supplied, and a second pixel circuit which is connected to the second optical element and supplies the second driving current equal to a current value of a second designation current supplied; and

a power supply which applies a driving current reference voltage to supply the first driving current to the first optical element through the first pixel circuit and applies the driving current reference voltage to supply the second driving current to the second optical element through the second pixel circuit between a selection period of the scanning line of the first row and a selection period of the scanning line of the second row.

20. A display device according to claim 19, wherein the power supply outputs the driving current reference voltage to the optical element group within a non-selection period.

21. A display device according to claim 20,

wherein the non-selection period is a period when none of the optical elements of the optical element group are selected.

22. A display device according to claim 20, wherein a reset voltage is output to said plurality of signal lines within the non-selection period.

23. A display device according to claim 19, wherein the power supply selectively outputs the driving current reference voltage and a designation current reference voltage to supply the first and second designation currents to the first and second pixel circuits.

24. A display device according to claim 23, wherein the designation current reference voltage is lower than the driving current reference voltage.

25. A display device according to claim 23, wherein the power supply outputs the designation current reference voltage within the selection period.

26. A display device according to claim 19, wherein the power supply alternately outputs a designation current reference voltage to supply the first and second designation currents and the driving current reference voltage.

27. A display device according to claim 19, further comprising a data driver which supplies the first and second designation currents to the first and second pixel circuits on the basis of a designation

current reference voltage output from the power supply within the selection period.

28. A display device according to claim 27, further comprising a signal line which connects the data driver to the pixel circuits.

29. A display device according to claim 19, wherein each of the pixel circuits stores the current value of the designation current supplied within the selection period and supplies the driving current that is equal to the current value of the designation current on the basis of the driving current reference voltage output from the power supply after the selection period.

30. A display device according to claim 19, wherein

each of the pixel circuits comprises a driving transistor and a capacitor which is connected between a gate and a source of the driving transistor,

the data driver supplies the designation current to the driving transistors of the pixel circuits on the basis of a designation current reference voltage output from the power supply within the selection period, and

the capacitor stores charges corresponding to the designation current between the gate and the source, and when the driving current reference voltage is input from the power supply, the driving transistor supplies the driving current corresponding to the charges stored

between the gate and the source.

31. A display device according to claim 19, wherein each of the pixel circuits comprises

a first transistor in which a gate is connected to one scanning line of the scanning line group and one of a drain and a source is connected to the data driver,

a second transistor in which a gate is connected to the scanning line and a designation current reference voltage and the driving current reference voltage are selectively input to one of a drain and a source, and

a driving transistor in which a gate is connected to the other of the drain and the source of the second transistor, one of a drain and a source is connected to one of the drain and the source of the second transistor, and the other of the drain and the source is connected to the other of the drain and the source of the first transistor and one optical element of the optical element group.

32. A display device according to claim 31, further comprising a selection scanning driver which selects the first transistor and the second transistor, which are connected to the predetermined scanning line of the scanning line group within the selection period.

33. A display device according to claim 19, wherein each of the pixel circuits comprises

a first transistor in which a gate is connected to

one scanning line of the scanning line group and one of a drain and a source is connected to the data driver,

a second transistor in which a gate is connected to the scanning line and one of a drain and a source is connected to the scanning line, and

a driving transistor in which a gate is connected to the other of the drain and the source of the second transistor, one of a drain and a source is connected to the power supply, and the other of the drain and the source is connected to the other of the drain and the source of the first transistor and one optical element of the optical element group.

34. A display device according to claim 33, further comprising a selection scanning driver which selects the first transistor and the second transistor, which are connected to the predetermined scanning line of the scanning line group within the selection period.

35. A display device according to claim 19, wherein the power supply outputs the driving current reference voltage within a non-selection period between the selection period of a predetermined scanning line and the selection period of a next scanning line.

36. A display device according to claim 19, wherein the optical element has a first electrode connected to the power supply through the pixel circuit and a second electrode to which a reference voltage is applied.

37. A display device according to claim 36, wherein

the power supply selectively outputs the driving current reference voltage and the designation current reference voltage to supply the first and second designation currents, and

the driving current reference voltage is not less than the reference voltage, and the designation current reference voltage is not more than the reference voltage.

38. A display device according to claim 19, wherein the optical element is an organic EL element.

39. A display device comprising:

a plurality of scanning lines;

a scanning driver which sequentially supplies to the scanning lines selection signals that select one of said plurality of scanning lines;

a plurality of pixel circuits each of which is connected to a corresponding one of said plurality of scanning lines and supplies a driving current corresponding to a current value of the designation current;

a plurality of optical elements each of which emits light in accordance with the driving current supplied by a corresponding one of said plurality of pixel circuits;

a data driver which supplies the designation currents to the pixel circuits within a selection

period when the scanning lines are selected; and

a common voltage output circuit which outputs to the selected pixel circuit a designation current reference voltage to supply the designation currents within the selection period of the scanning lines and outputs to said plurality of pixel circuits a driving current reference voltage to supply the driving currents within a non-selection period.

40. A display device according to claim 39, wherein the common voltage output circuit outputs the driving current reference voltage to all the pixel circuits within the non-selection period.

41. A display device according to claim 39, wherein the designation current reference voltage is lower than the driving current reference voltage.

42. A display device driving method comprising:

a first designation current step of supplying a first designation current to a first driving transistor within a first selection period to store charges corresponding to a current value of the first designation current between a gate and a source of the first driving transistor;

a second designation current step of supplying a second designation current to a second driving transistor within a second selection period to store charges corresponding to a current value of the second designation current between a gate and a source of the

second driving transistor; and

a driving current reference voltage output step of, from the end of the first selection period till the beginning of the second selection period, outputting a driving current reference voltage to the first driving transistor and a first optical element which is connected in series with the first driving transistor and outputting the driving current reference voltage to the second driving transistor and a second optical element which is connected in series with the second driving transistor.

43. A display device driving method according to claim 42, wherein the driving current reference voltage is a voltage at which a source-drain voltage of the first driving transistor and a source-drain voltage of the second driving transistor are set in a saturated state.

44. A display device driving method comprising:

a first designation current step of supplying a first designation current to a first driving transistor within a first selection period to store charges corresponding to a current value of the first designation current between a gate and a source of the first driving transistor;

a second designation current step of supplying a second designation current to a second driving transistor within a second selection period after the

first designation current step to store charges corresponding to a current value of the second designation current between a gate and a source of the second driving transistor; and

a driving current reference voltage output step of, after the second designation current step, outputting a driving current reference voltage to the first driving transistor and a first optical element which is connected in series with the first driving transistor and outputting the driving current reference voltage to the second driving transistor and a second optical element which is connected in series with the second driving transistor.

45. A display device driving method according to claim 44, wherein the driving current reference voltage is a voltage at which a source-drain voltage of the first driving transistor and a source-drain voltage of the second driving transistor are set in a saturated state.