

**SWITCHED SIGNAL PROCESSING CIRCUIT**

REPLACED SHEET 3

SG

4

✓ Application : paged 1 to paged 7  
✓ : paged 2 to paged 7  
✓ : paged 3 to paged 7  
✓ : paged 4 to paged 7

Field of the Invention

5 The present application concerns television receivers having signal processing circuitry for decoding stereo signals which were encoded in accordance with the DBX<sup>TM</sup> format.

Background of the Invention

1 0 The present application relates to wideband expansion of stereophonic signals as discussed in United States Patent No. 5,091,957 of Anderson et al.. The teaching of the '957 patent is expressly incorporated by reference herein. The '957 patent disclosed a wideband expander, and recognized that for practical purposes, satisfactory restoration of an (L-R) audio difference signal companded  
1 5 according to the DBX format can be achieved without spectral expansion. A decoder according to '957 provides a modified fixed deemphasis and wide-band expansion of the received compressed L-R audio signal, but does not provide spectral expansion. Additionally, it was further recognized in '957 that the relatively complex RMS  
2 0 detectors of the DBX system can be replaced with simpler, lower cost integrating peak detectors.

It is desirable to design and build television receivers wherein different decoders can be used depending upon model and options.

SUMMARY OF THE INVENTION

2 5 Briefly, the present invention concerns an expander circuit for decoding audio signals which were encoded in accordance with the BTSC multichannel sound system standard including DBX companding. A wideband expander circuit is utilized and a DBX expander can be  
3 0 accommodated. The wideband expander circuit is provided with a signal path having an input LPF (low pass filter), a stereo difference signal (L-R) demodulator, a second LPF, and a voltage controlled amplifier (VCA), the gain of which is controlled by a control signal derived from the demodulated difference signal which has been  
3 5 operated on by a bandpass filter (BPF) and an integrating peak detector. The output of the VCA is provided to a deemphasis network before being fed to a decoder matrix for combining with the sum stereo signal (L+R) for reconstructing the original L and R signals. When a DBX expander is connected, the DBX expander is substituted in place of the



deemphasis network, the VCA control signal, which provides the wideband expansion, is overridden by a predetermined voltage, the BPF is disabled, and the input is switched to bypass the input LPF. According to aspects of the present invention, the disablement of the  
5 BPF actuates the switching of the input to bypass the input LPF.

### BRIEF DESCRIPTION OF THE DRAWINGS

FIGURE 1 shows a block diagram of a DBX expander as known in the prior art.

1 0 FIGURE 2 shows a block diagram of a wideband expander.

FIGURE 3 show a block diagram of a television receiver having BTSC multichannel sound capability.

FIGURE 4 shows a block diagram of a stereophonic difference signal processor according to aspects of the present  
1 5 invention.

FIGURE 5 is a block diagram showing details of the bandpass filter and switching apparatus of Figure 4.

### DETAILED DESCRIPTION OF THE EMBODIMENT

2 0 In the DBX system of Figure 1, a fixed deemphasis is applied to the incoming (L-R) stereo difference signal, by fixed deemphasis unit 10. A spectral expansion is applied to the deemphasized audio signal by variable deemphasis unit 12 in response to a control signal developed by bandpass filter 14 and RMS detector  
2 5 16. Amplitude expansion is applied to the audio signal by variable gain element 18 in response to a control signal developed by bandpass filter 20 and RMS detector 22. A fixed deemphasis (i.e., a fixed amount of low pass filtering) is applied to the expanded audio signal by fixed deemphasis unit 24 in order to attenuate high frequency products  
3 0 which may have been generated in the expansion process.

FIGURE 2 shows a wideband expander. The units of FIGURE 2 having the same numerical designations as corresponding units of the decoder of FIGURE 1, perform the same function as their counterparts. The wideband expansion provided by variable gain element 18 of  
3 5 FIGURE 2 in response to control signals developed by units 20 and 26, substantially restores the dynamic range of the original signal.

Discussion of the significant differences between the arrangements of FIGURES 1 and 2 are stated in the '957 patent. Briefly, these differences are: 1) that the spectral expansion of the compressed



DBX audio signal was found to be not necessary for the reproduction of an acceptable stereo signal, and accordingly, the variable deemphasis unit 12, its associated control path filter 14, and its associated RMS detector 16 were completely eliminated from the arrangement of  
5 FIGURE 2; 2) that the rolloff frequency of the fixed deemphasis networks was changed to compensate for some of the lost variable deemphasis caused by elimination of the spectral expansion elements; and 3) that the RMS detector 22 was replaced by a much lower cost and more simply constructed integrating peak detector 26.

1 0 The expanders of FIGURES 1 and 2 have been used in television receivers known in the prior art. FIGURE 3 shows such a television receiver having BTSC multichannel television sound (MTS) capability. Broadcast television signal are received by an antenna 25 (or coupled to the receiver via a cable television system) and applied to  
1 5 a tuner 28 for channel selection. Tuner 28 converts a selected one of a plurality of received television signals from its respective broadcast frequency to a common intermediate frequency (IF). The IF frequency television signal is applied to a video and sound IF unit 30 which produces a baseband video signal and a frequency modulated (FM)  
2 0 sound carrier. The video and audio signals are separated, and the video signals are applied to video signal processing circuitry, (not shown).

As shown in FIGURE 3, a composite multichannel sound audio signal is detected from the FM sound carrier by an FM detector  
2 5 32 and applied to a stereo decoder 34. Stereo decoder 34 provides an (L+R) stereo sum signal and an (L-R) stereo difference signal. The (L+R) stereo sum signal is deemphasized in a deemphasis unit 36 (i.e., a low pass filter having the appropriate time constant) and applied, to one input of a stereo matrixing unit 38 in which the original left (L) and  
3 0 right (R) stereo signals are reconstructed. The (L-R) stereo difference signal from stereo decoder unit 34 is applied to expander unit 40. Expander unit 40 can correspond to a full DBX expander as shown in FIGURE 1 or to a wideband expander as shown in FIGURE 2. The expanded (L-R) stereo difference signal is applied to the other input of  
3 5 stereo matrix unit 38. The reconstructed left (L) and right (R) stereo signals are applied to stereo audio amplifier unit 42 for amplification and ultimate reproduction in a dual speaker unit 43.

FIGURE 4 shows a wideband expander, generally designated 44, which according to aspects of the present invention, can be adapted



so that a DBX expander can be used. A composite DBX encoded audio signal including a pilot signal is fed to the system at input terminal 46. The composite DBX encoded audio signal is then filtered by an input low pass filter (LPF) 48, which is a notch filter having its maximum  
5 attenuation at a frequency close to but higher than the fifth harmonic (5H) of the pilot signal. This filter is used because it is desirable to remove any SAP signal from the incoming composite signal since the SAP signal can cause interference with the operation of the (L-R) demodulator. This is because an (L-R) demodulator typically uses a  
1 0 phase-locked loop (PLL) and there is a possibility that the PLL will falsely lock onto the 5H center frequency of the SAP signal if the 5H signal is of sufficient amplitude.

The present LPF 48 may be of a twin-T topology (not shown) with the the notch tuned to a frequency higher than 5H. In  
1 5 such an arrangement, the SAP signal can be sufficiently attenuated via the filter skirt without requiring close tolerance components to precisely determine the notch frequency. Additionally, placing the notch above the frequency of interest permits smaller capacitance values which are more practical to integrate and assures that R/C value  
2 0 variations will not change the skirt attenuation if a high enough "Q" is used. The present LPF 48 may be configured so as to use a portion of the twin-T arrangement as part of the feedback loop for an operational amplifier to thereby increase the Q of the circuit.

The output signal from LPF 48 is fed to a switch 50 for  
2 5 switching the input terminal of the (L-R) demodulator 52 between the output of LPF 48 and input terminal 46. In the exemplary embodiment, LPF 48 is bypassed when a DBX expander is used. When a DBX expander is used, a third order Sallen-Key LPF (not shown) can be used for providing sharper skirts at the notch frequency. The  
3 0 operation of switch 50 will be discussed in greater detail below.

The signal from switch 50 is fed to LPF 53 for deriving the stereo sum signal (L+R) which is subsequently fed to matrix 38. The signal from switch 50 is also provided to demodulator 52 which is a standard demodulator according to the MTS television standard. The  
3 5 output signal from demodulator 52 is fed to the series coupling of LPF 10 and VCA 18, as well as to the series coupling of BPF 20 and integrating peak detector 26, all of which correspond to similarly designated members of the wideband expander shown in FIGURE 2. Integrating peak detector 26 is comprised of an detector 54 and a



integrating capacitor 56 for providing a integrated peak detected control signal at line 58 to VCA 18. The expanded output signal from VCA 18 is fed to a fixed deemphasis network 24 (see FIGURE 2) which in turn is fed to a stereo matrix 38 for reconstructing the L and R signals.

The members so far described in connection with FIGURE 4 for the (L-R) signal correspond with the wideband expander discussed in FIGURE 2, as shown in the '957 patent. The wideband expander of FIGURE 4 provides amplitude expansion for DBX encoded signals with an expander is not a mirror image of the encoder. However, it is recognized herein that it may be desirable to use selected portions of the present expander, e.g., demodulator 52, LPF 10, and VCA 18, when expansion from a DBX expander is utilized instead of wideband expansion. In such a case, some operations of the present wideband expander would be modified to accommodate the operation of the DBX expander. Such circuitry changes are indicated in FIGURE 4 as illustrative switches IS1, IS2, and IS3. These switches are designated as "illustrative" because it is expected that in practice, that such the alternate connections would be hard wired connections.

A DBX expander 60 would be wired in place of the deemphasis network 24 and such substitution is shown by switch IS1. This substitution is made because the DBX expander 60 provides its own deemphasis and thus, emphasis network 24 is not needed.

In wideband expander 44, BPF 20 and integrating peak detector 26 provide a control voltage at line 58 to VCA 18 to provide amplitude expansion of the (L-R) signal. Since DBX expander 60 provides its own amplitude expansion of the signal, the amplitude expansion provided by the control voltage at line 58 is defeated by providing a constant predetermined voltage 62 through a resistor 64 to the output of the integrating peak detector 26 at line 58 by way of illustrative switch IS2. In this way, any changes in the control voltage at line 58 which would be caused by the (L-R) signal processing of BPF 20 and integrating peak detector 26, are "swamped" out by constant voltage 62. Thus, in this arrangement, VCA 18 provides a constant amplification with the amount of said amplification being predetermined by the value of the constant control voltage 62 applied at line 58.

As discussed above, switch 50 switches the input signal for demodulator 52 to bypass LPF 48 when a DBX expander 60 is used. In

the exemplary embodiment, the switching of switch 50 is effectuated by the defeating of the bandpass operation of BPF 20. Such an arrangement will not adversely effect the operation of the system since any control signal generated by the operation of BPF 20 (and  
 5 integrating detector 26) is rendered ineffectual by voltage source 62 and resistor 64. The frequency selective operation of BPF 20 is provided by capacitors 21a and 21b which provide a frequency sensitive network, which will be more fully discussed below. In the exemplary embodiment, capacitor 21a is coupled to a reference  
 10 potential such as ground, and is provided with a DC voltage thereacross. This DC voltage is compared against a reference potential by comparator 66, which has an output 67 to which the switch position of switch 50 is responsive. The DC voltage across capacitor 21a, is of a value above a threshold reference voltage  $V_{REF}$  coupled to the negative  
 15 terminal of comparator 66. In such an arrangement, switch 50 is switched for receiving an input signal from LPF 48. If the DC voltage at line 68 is below  $V_{REF}$ , the output of comparator 66 causes switch 50 to be switched for receiving the input signal from terminal 46, bypassing LPF 48. In the exemplary embodiment, the DC voltage across capacitor  
 20 21a is changed by short circuiting the capacitor 21a to ground by illustrative switch IS3. However, a resistor can be used having a low enough value sufficient to change the voltage at line 68 through  $V_{REF}$  from above  $V_{REF}$  to below  $V_{REF}$ .

The details of BPF 20 are shown in FIGURE 5. The (L-R)  
 25 signal derived from the output of demodulator 52 is provided to unity amplifiers 70, 72 and in turn is fed to a respective pair of frequency sensitive low pass filters comprised of resistors 74, 76, and capacitors 78, 80 to ground for providing low pass filtering. The output signals from the low pass filters are fed to respective unity gain amplifiers 82,  
 30 84 and subsequently to an operational amplifier 86 wherein one of the low pass filtered signals is provided to the non-inverting input terminal and the other low pass filtered signal is provided to the inverting input terminal. In such a case, when the two signals into amplifier 86 are equal, there is no output signal at terminal 88 of  
 35 amplifier 86. If the signal fed to the inverting terminal has a rolloff at a lower frequency than the signal to the non-inverting terminal, the subtraction process is reduced past the rolloff frequency and the signal at the non-inverting terminal will be passed through to terminal 88



until the non-inverting input signal reaches its own rolloff frequency. In this way a bandpass filter is provided.

5 In the exemplary embodiment, the DC voltage across capacitor 21a at line 68 is provided from the the output line 90 of amplifier 72 which is DC coupled and has a DC voltage thereat. Thus, when capacitor 21a is shunted or short circuited to ground through illustrative switch IS3, the operation of that signal path 92 is defeated, and consequently, the operation of the bandpass function of BPF 20 is defeated. The change of the DC voltage at line 68 causes switch 50 to  
10 switch between input signal terminals as discussed above.

This Sheet Has Been Replaced



## Claims:

1. Switching apparatus characterized by:  
filter means (20,21a,21b) including a frequency sensitive network for spectrally filtering a signal, at least one member of the  
5 frequency sensitive network having a DC voltage thereacross,  
comparator means (66) having a threshold voltage and having an output signal responsive to the amplitude of the DC voltage, and  
switch means (50) responsive to the output signal of the  
10 comparator means (66) for switching between at least a first and second terminal.
2. The apparatus of claim 1 characterized in that the  
15 filter means (20,21a,21b) is a bandpass filter.
3. The apparatus of claim 1 characterized in that the  
switch means (50) is actuatable by shunting the member (21a) of the frequency sensitive network to change the DC voltage through the threshold voltage.  
20
4. The apparatus of claim 3 characterized in that the shunting of the member of the frequency sensitive network disables the spectral filtering of the signal by the filter means.



This Sheet Has Been Replaced




ABSTRACT

An expander circuit for decoding audio signals which were encoded in accordance with the BTSC multichannel sound system standard including DBX companding is presented. A wideband expander circuit (44) is utilized and a DBX expander can be accommodated. The wideband expander circuit is provided with a signal path having an input LPF (low pass filter)(48), a stereo difference signal (L-R) demodulator (52), a second LPF (10), and a voltage controlled amplifier (VCA)(18), the gain of which is controlled by a control signal (58) derived from the demodulated difference signal which has been operated on by a bandpass filter (BPF) (20) and an integrating peak detector (54,56). The output of the VCA (18) is provided to a deemphasis network (24) before being fed to a decoder matrix (38) for combining with the sum stereo signal (L+R) for reconstructing the original L and R signals. When a DBX expander (60) is connected, the DBX expander (60) is substituted in place of the deemphasis network (24), the VCA control signal (58), which provides the wideband expansion, is overridden by a predetermined voltage, the BPF (20) is disabled, and the input is switched to bypass the input LPF (48). According to aspects of the present invention, the disablement of the BPF (20) actuates the switching of the input to bypass the input LPF (48).

---

This Sheet Has Been Replaced


1/5



**FIG. 1**  
**PRIOR ART**


This Sheet Has Been Replaced






**FIG. 2**  
**PRIOR ART**



**FIG. 3**  
**PRIOR ART**

This Sheet Has Been Replaced






FIG. 5

This Sheet Has Been Replaced



1-850903E

## REPLACEMENT SHEET

10 JUL 1996

1

SWITCHED SIGNAL PROCESSING CIRCUITField of the Invention

The present application concerns television receivers  
 5 having signal processing circuitry for decoding stereo signals which  
 were encoded in accordance with the DBX<sup>TM</sup> format.

Background of the Invention

The present application relates to wideband expansion of  
 1 0 stereophonic signals as discussed in United States Patent No. 5,091,957  
 of Anderson et al.. The teaching of the '957 patent is expressly  
 incorporated by reference herein. The '957 patent disclosed a  
 wideband expander, and recognized that for practical purposes,  
 satisfactory restoration of an (L-R) audio difference signal companded  
 1 5 according to the DBX format can be achieved without spectral  
 expansion. A decoder according to '957 provides a modified fixed  
 deemphasis and wide-band expansion of the received compressed L-R  
 audio signal, but does not provide spectral expansion. Additionally, it  
 was further recognized in '957 that the relatively complex RMS  
 2 0 detectors of the DBX system can be replaced with simpler, lower cost  
 integrating peak detectors.

It is desirable to design and build television receivers  
 wherein different decoders can be used depending upon model and  
 options.

2 5

SUMMARY OF THE INVENTION

Briefly, the present invention concerns an expander circuit  
 for decoding audio signals which were encoded in accordance with the  
 BTSC multichannel sound system standard including DBX companding.  
 A wideband expander circuit is utilized and a DBX expander can be  
 3 0 accommodated. The wideband expander circuit is provided with a  
 signal path having an input LPF (low pass filter), a stereo difference  
 signal (L-R) demodulator, a second LPF, and a voltage controlled  
 amplifier (VCA), the gain of which is controlled by a control signal  
 derived from the demodulated difference signal which has been  
 3 5 operated on by a bandpass filter (BPF) and an integrating peak  
 detector. The output of the VCA is provided to a deemphasis network  
 before being fed to a decoder matrix for combining with the sum stereo  
 signal (L+R) for reconstructing the original L and R signals. When a DBX  
 expander is connected, the DBX expander is substituted in place of the

✓ Description : page 1.1 to page 1.2..  
 ✓ Claim(s) : page 1.2 to page 1.3..  
 ✓ Drawing(s) : page 1.3 to page 1.4..  
 ✓ Abstract : page 1.1 to page 1.2..

DATE OF RECEIPT 10/1/96

10 JUL 1996

deemphasis network, the VCA control signal, which provides the wideband expansion, is overridden by a predetermined voltage, the BPF is disabled, and the input is switched to bypass the input LPF. According to aspects of the present invention, the disablement of the  
5 BPF actuates the switching of the input to bypass the input LPF.

### BRIEF DESCRIPTION OF THE DRAWINGS

FIGURE 1 shows a block diagram of a DBX expander as known in the prior art.

1 0 FIGURE 2 shows a block diagram of a wideband expander.

FIGURE 3 show a block diagram of a television receiver having BTSC multichannel sound capability.

FIGURE 4 shows a block diagram of a stereophonic difference signal processor according to aspects of the present  
1 5 invention.

FIGURE 5 is a block diagram showing details of the bandpass filter and switching apparatus of Figure 4.

### DETAILED DESCRIPTION OF THE EMBODIMENT

2 0 In the DBX system of Figure 1, a fixed deemphasis is applied to the incoming (L-R) stereo difference signal, by fixed deemphasis unit 10. A spectral expansion is applied to the deemphasized audio signal by variable deemphasis unit 12 in response to a control signal developed by bandpass filter 14 and RMS detector  
2 5 16. Amplitude expansion is applied to the audio signal by variable gain element 18 in response to a control signal developed by bandpass filter 20 and RMS detector 22. A fixed deemphasis (i.e., a fixed amount of low pass filtering) is applied to the expanded audio signal by fixed deemphasis unit 24 in order to attenuate high frequency products  
3 0 which may have been generated in the expansion process.

FIGURE 2 shows a wideband expander. The units of FIGURE 2 having the same numerical designations as corresponding units of the decoder of FIGURE 1, perform the same function as their counterparts. The wideband expansion provided by variable gain element 18 of  
3 5 FIGURE 2 in response to control signals developed by units 20 and 26, substantially restores the dynamic range of the original signal.

Discussion of the significant differences between the arrangements of FIGURES 1 and 2 are stated in the '957 patent. Briefly, these differences are: 1) that the spectral expansion of the compressed

DBX audio signal was found to be not necessary for the reproduction of an acceptable stereo signal, and accordingly, the variable deemphasis unit 12, its associated control path filter 14, and its associated RMS detector 16 were completely eliminated from the arrangement of

5 FIGURE 2; 2) that the rolloff frequency of the fixed deemphasis networks was changed to compensate for some of the lost variable deemphasis caused by elimination of the spectral expansion elements; and 3) that the RMS detector 22 was replaced by a much lower cost and more simply constructed integrating peak detector 26.

10 The expanders of FIGURES 1 and 2 have been used in television receivers known in the prior art. FIGURE 3 shows such a television receiver having BTSC multichannel television sound (MTS) capability. Broadcast television signal are received by an antenna 25 (or coupled to the receiver via a cable television system) and applied to

15 a tuner 28 for channel selection. Tuner 28 converts a selected one of a plurality of received television signals from its respective broadcast frequency to a common intermediate frequency (IF). The IF frequency television signal is applied to a video and sound IF unit 30 which produces a baseband video signal and a frequency modulated (FM) sound carrier. The video and audio signals are separated, and the video signals are applied to video signal processing circuitry, (not shown).

As shown in FIGURE 3, a composite multichannel sound audio signal is detected from the FM sound carrier by an FM detector

25 32 and applied to a stereo decoder 34. Stereo decoder 34 provides an (L+R) stereo sum signal and an (L-R) stereo difference signal. The (L+R) stereo sum signal is deemphasized in a deemphasis unit 36 (i.e., a low pass filter having the appropriate time constant) and applied, to one input of a stereo matrixing unit 38 in which the original left (L) and

30 right (R) stereo signals are reconstructed. The (L-R) stereo difference signal from stereo decoder unit 34 is applied to expander unit 40. Expander unit 40 can correspond to a full DBX expander as shown in FIGURE 1 or to a wideband expander as shown in FIGURE 2. The expanded (L-R) stereo difference signal is applied to the other input of stereo matrix unit 38. The reconstructed left (L) and right (R) stereo signals are applied to stereo audio amplifier unit 42 for amplification and ultimate reproduction in a dual speaker unit 43.


FIGURE 4 shows a wideband expander, generally designated 44, which according to aspects of the present invention, can be adapted

so that a DBX expander can be used. A composite DBX encoded audio signal including a pilot signal is fed to the system at input terminal 46. The composite DBX encoded audio signal is then filtered by an input low pass filter (LPF) 48, which is a notch filter having its maximum  
5 attenuation at a frequency close to but higher than the fifth harmonic (5H) of the pilot signal. This filter is used because it is desirable to remove any SAP signal from the incoming composite signal since the SAP signal can cause interference with the operation of the (L-R) demodulator. This is because an (L-R) demodulator typically uses a  
1 0 phase-locked loop (PLL) and there is a possibility that the PLL will falsely lock onto the 5H center frequency of the SAP signal if the 5H signal is of sufficient amplitude.

The present LPF 48 may be of a twin-T topology (not shown) with the notch tuned to a frequency higher than 5H. In  
1 5 such an arrangement, the SAP signal can be sufficiently attenuated via the filter skirt without requiring close tolerance components to precisely determine the notch frequency. Additionally, placing the notch above the frequency of interest permits smaller capacitance values which are more practical to integrate and assures that R/C value  
2 0 variations will not change the skirt attenuation if a high enough "Q" is used. The present LPF 48 may be configured so as to use a portion of the twin-T arrangement as part of the feedback loop for an operational amplifier to thereby increase the Q of the circuit.

The output signal from LPF 48 is fed to a switch 50 for  
2 5 switching the input terminal of the (L-R) demodulator 52 between the output of LPF 48 and input terminal 46. In the exemplary embodiment, LPF 48 is bypassed when a DBX expander is used. When a DBX expander is used, a third order Sallen-Key LPF (not shown) can be used for providing sharper skirts at the notch frequency. The  
3 0 operation of switch 50 will be discussed in greater detail below.

The signal from switch 50 is fed to LPF 53 for deriving the stereo sum signal (L+R) which is subsequently fed to matrix 38. The signal from switch 50 is also provided to demodulator 52 which is a standard demodulator according to the MTS television standard. The  
3 5 output signal from demodulator 52 is fed to the series coupling of LPF 10 and VCA 18, as well as to the series coupling of BPF 20 and integrating peak detector 26, all of which correspond to similarly designated members of the wideband expander shown in FIGURE 2. Integrating peak detector 26 is comprised of an detector 54 and a



integrating capacitor 56 for providing a integrated peak detected control signal at line 58 to VCA 18. The expanded output signal from VCA 18 is fed to a fixed deemphasis network 24 (see FIGURE 2) which in turn is fed to a stereo matrix 38 for reconstructing the L and R signals.

The members so far described in connection with FIGURE 4 for the (L-R) signal correspond with the wideband expander discussed in FIGURE 2, as shown in the '957 patent. The wideband expander of FIGURE 4 provides amplitude expansion for DBX encoded signals with an expander is not a mirror image of the encoder. However, it is recognized herein that it may be desirable to use selected portions of the present expander, e.g., demodulator 52, LPF 10, and VCA 18, when expansion from a DBX expander is utilized instead of wideband expansion. In such a case, some operations of the present wideband expander would be modified to accommodate the operation of the DBX expander. Such circuitry changes are indicated in FIGURE 4 as illustrative switches IS1, IS2, and IS3. These switches are designated as "illustrative" because it is expected that in practice, that such the alternate connections would be hard wired connections.

A DBX expander 60 would be wired in place of the deemphasis network 24 and such substitution is shown by switch IS1. This substitution is made because the DBX expander 60 provides its own deemphasis and thus, emphasis network 24 is not needed.

In wideband expander 44, BPF 20 and integrating peak detector 26 provide a control voltage at line 58 to VCA 18 to provide amplitude expansion of the (L-R) signal. Since DBX expander 60 provides its own amplitude expansion of the signal, the amplitude expansion provided by the control voltage at line 58 is defeated by providing a constant predetermined voltage 62 through a resistor 64 to the output of the integrating peak detector 26 at line 58 by way of illustrative switch IS2. In this way, any changes in the control voltage at line 58 which would be caused by the (L-R) signal processing of BPF 20 and integrating peak detector 26, are "swamped" out by constant voltage 62. Thus, in this arrangement, VCA 18 provides a constant amplification with the amount of said amplification being predetermined by the value of the constant control voltage 62 applied at line 58.


As discussed above, switch 50 switches the input signal for demodulator 52 to bypass LPF 48 when a DBX expander 60 is used. In

REPLACEMENT SHEET

10 JUL 1996


the exemplary embodiment, the switching of switch 50 is effectuated by the defeating of the bandpass operation of BPF 20. Such an arrangement will not adversely effect the operation of the system since any control signal generated by the operation of BPF 20 (and integrating detector 26) is rendered ineffectual by voltage source 62 and resistor 64. The frequency selective operation of BPF 20 is provided by capacitors 21a and 21b which provide a frequency sensitive network, which will be more fully discussed below. In the exemplary embodiment, capacitor 21a is coupled to a reference potential such as ground, and is provided with a DC voltage thereacross. This DC voltage is compared against a reference potential by comparator 66, which has an output 67 to which the switch position of switch 50 is responsive. The DC voltage across capacitor 21a, is of a value above a threshold reference voltage  $V_{REF}$  coupled to the negative terminal of comparator 66. In such an arrangement, switch 50 is switched for receiving an input signal from LPF 48. If the DC voltage at line 68 is below  $V_{REF}$ , the output of comparator 66 causes switch 50 to be switched for receiving the input signal from terminal 46, bypassing LPF 48. In the exemplary embodiment, the DC voltage across capacitor 21a is changed by short circuiting the capacitor 21a to ground by illustrative switch IS3. However, a resistor can be used having a low enough value sufficient to change the voltage at line 68 through  $V_{REF}$  from above  $V_{REF}$  to below  $V_{REF}$ .

The details of BPF 20 are shown in FIGURE 5. The (L-R) signal derived from the output of demodulator 52 is provided to unity amplifiers 70, 72 and in turn is fed to a respective pair of frequency sensitive low pass filters comprised of resistors 74, 76, and capacitors 78, 80 to ground for providing low pass filtering. The output signals from the low pass filters are fed to respective unity gain amplifiers 82, 84 and subsequently to an operational amplifier 86 wherein one of the low pass filtered signals is provided to the non-inverting input terminal and the other low pass filtered signal is provided to the inverting input terminal. In such a case, when the two signals into amplifier 86 are equal, there is no output signal at terminal 88 of amplifier 86. If the signal fed to the inverting terminal has a rolloff at a lower frequency than the signal to the non-inverting terminal, the subtraction process is reduced past the rolloff frequency and the signal at the non-inverting terminal will be passed through to terminal 88.



until the non-inverting input signal reaches its own rolloff frequency. In this way a bandpass filter is provided.

5 In the exemplary embodiment, the DC voltage across capacitor 21a at line 68 is provided from the the output line 90 of amplifier 72 which is DC coupled and has a DC voltage thereat. Thus, when capacitor 21a is shunted or short circuited to ground through illustrative switch IS3, the operation of that signal path 92 is defeated, and consequently, the operation of the bandpass function of BPF 20 is defeated. The change of the DC voltage at line 68 causes switch 50 to  
10 switch between input signal terminals as discussed above.




THIS SHEET HAS BEEN  
REPLACED

8

Claims:

1. Switching apparatus characterized by:  
filter means (20,21a,21b) including a frequency sensitive  
network for spectrally filtering a signal, at least one member of the  
5 frequency sensitive network having a DC voltage thereacross,  
comparator means (66) having a threshold voltage and  
having an output signal responsive to the amplitude of the DC  
voltage, and  
switch means (50) responsive to the output signal of the  
10 comparator means (66) for switching between at least a first and  
second terminal.
2. The apparatus of claim 1 characterized in that the  
filter means (20,21a,21b) is a bandpass filter.  
15
3. The apparatus of claim 1 characterized in that the  
switch means (50) is actuatable by shunting the member (21a) of the  
frequency sensitive network to change the DC voltage through the  
threshold voltage.  
20
4. The apparatus of claim 3 characterized in that the  
shunting of the member of the frequency sensitive network disables  
the spectral filtering of the signal by the filter means.




This Sheet Has Been Replaced





SWITCHED SIGNAL PROCESSING CIRCUITABSTRACT



An expander circuit for decoding audio signals which were encoded in accordance with the BTSC multichannel sound system standard including DBX companding is presented. A wideband expander circuit (44) is utilized and a DBX expander can be accommodated. The wideband expander circuit is provided with a signal path having an input LPF (low pass filter)(48), a stereo difference signal (L-R) demodulator (52), a second LPF (10), and a voltage controlled amplifier (VCA)(18), the gain of which is controlled by a control signal (58) derived from the demodulated difference signal which has been operated on by a bandpass filter (BPF) (20) and an integrating peak detector (54,56). The output of the VCA (18) is provided to a deemphasis network (24) before being fed to a decoder matrix (38) for combining with the sum stereo signal (L+R) for reconstructing the original L and R signals. When a DBX expander (60) is connected, the DBX expander (60) is substituted in place of the deemphasis network (24), the VCA control signal (58), which provides the wideband expansion, is overridden by a predetermined voltage, the BPF (20) is disabled, and the input is switched to bypass the input LPF (48). According to aspects of the present invention, the disablement of the BPF (20) actuates the switching of the input to bypass the input LPF (48).


FIGURE 4







**FIG. 1**  
**PRIOR ART**





**FIG. 3**  
**PRIOR ART**





10 JUL 1996




FIG. 5



What is claimed is:

1. Switching apparatus comprising:  
filter means including a frequency sensitive network for spectrally filtering a signal, at least one member of the frequency sensitive network having a DC voltage thereacross;  
a comparator having an output signal responsive to a comparison of the amplitude of the DC voltage and a threshold voltage;  
switch means responsive to the output signal of the comparator means for changing the DC voltage across the member of the frequency sensitive network.
2. The apparatus of claim 1 wherein the filter means is a bandpass filter.
3. The apparatus of claim 1 wherein the filter means is a bandpass filter, and changing the DC voltage across the member of the frequency sensitive network disables the bandpass filtering characteristic of the filter means.

REPLACEMENT SHEET

16 AUG 1999