

Description

This invention relates to a camera having an electronic strobe flash unit which charges in response to movement of a shutter release member. More particularly, the invention assures a predetermined minimum amount of charging of the flash unit, prior to an exposure, independently of the actuation of the release member.

Many of today's amateur cameras are designed to maximize the number of acceptable photographs per roll of film. Typical of such cameras are those which incorporate an electronic strobe flash unit and photoelectric circuitry for automatically actuating such unit under those conditions which warrant its use. To avoid a continuous power drain on the camera's battery yet assure that the flash unit is always charged and ready for use, some cameras include circuitry for rapidly charging the flash capacitor in response to pre-exposure movement of the shutter release. A problem with such circuitry, however, is that it can be defeated by a camera operator who, rather than squeezes the shutter release in the recommended manner, »jabs« or »stabs« the release and thereby initiates exposure before the flash capacitor has had time to charge.

As a solution to the above problem it has been proposed that a latching mechanism be used to temporarily delay movement of the shutter release to its shutter-releasing position until the flash capacitor has had time to charge. See, for example, US-A-4 084 167, wherein an electromagnet latches a shutter release member in a pre-exposure position pending sufficient charging of the flash capacitor. Thereafter, the electromagnet frees the shutter release and allows the camera operator to continue moving it toward its shutter-releasing position.

Aside from adding considerably to the manufacturing cost of such cameras, the latching mechanisms disclosed in the above U. S. patent is disadvantageous from the standpoint that an inexperienced camera operator can be misled into thinking an exposure has been made when, in fact, it has not. As indicated above, the operator must continue exerting pressure on the shutter release after it has been latched in its pre-exposure position; otherwise the shutter release would simply return to its rest position without shutter actuation. Since there is a tendency to release the pressure applied to the shutter release after its movement is arrested, photographic opportunities will be lost.

In view of the foregoing, the primary object of this invention is to provide a shutter-release-responsive charging apparatus of the above type which, by virtue of its unique structure suffers neither of the aforementioned disadvantages. Like the prior art apparatus, the charging apparatus of the invention comprises means for delaying shutter release for a variable time interval in the event the shutter release member is moved at a rate which would not allow sufficient time for a charging circuit to adequately charge the

flash unit, prior to shutter release, to a predetermined level sufficient to fire the strobe flash, such time interval being sufficient to provide adequate charging. Unlike the prior art, however, the delaying means of the invention comprises the combination of (a) a first circuit for producing a signal in response to said flash unit being charged to a level sufficient to fire the strobe flash; (b) a second circuit for producing a timing pulse of predetermined duration; and (c) a logic circuit operatively coupled to said first and second circuits, said logic circuit being adapted to produce a shutter-releasing signal in response to said shutter-releasing member having reached its shutter-releasing position and to either (1) receipt of said first circuit signal, or (2) termination of said timing pulse or, whichever occurs first. By virtue of the invention, the operator need not, in contrast with the aforementioned prior art apparatus, remember to further depress the shutter-releasing member after it has been freed from its pre-exposure position by an electromagnetic latch or the like; nor is any such latching mechanism required.

The invention will be better understood from the ensuing detailed description of a preferred embodiment, reference being made to the accompanying drawings.

In a detailed description of a preferred embodiment of the invention presented below, reference is made to the accompanying drawings, in which:

Fig. 1 is a perspective view of a camera having an electronic strobe flash unit;

Fig. 2 is a block diagram of the camera and electronic strobe flash unit of Fig. 1;

Fig. 3 is an exploded view of a switch assembly, which is responsive to a shutter-release member, and

Fig. 4 is a more detailed block diagram of circuitry, according to the invention, for controlling charging of the electronic strobe flash unit of Fig. 1 in response to actuation of the switch assembly of Fig. 3.

Referring to Fig. 1, a camera 10 is provided with an electronic strobe flash unit 12, which may be formed either as an integral part of the camera, as shown, or, alternatively, may be detachable from the camera. A flash or an ambient exposure occurs in response to a camera operator depressing a photographic cycle shutter-release member 13. As will be explained in considerable detail below, the flash unit 12 charges in response to movement of the member 13.

Referring not to Fig. 2, the electronic strobe flash unit 12 comprises a DC to DC converter 14 and a conventional flash trigger circuit 15. By means well known in the electronic strobe flash art, the converter 14 is arranged to charge a flash-firing capacitor 16 to a voltage that is necessary to fire a flash tube 17. A full charge exists when the capacitor 16 is charged to approximately 200 volts. However, the flash tube 17 can

10

be reliably fired when the capacitor 16 is charged to an intermediate voltage, approximately 140 volts. When connected to a low-voltage battery 18, for example, a 6-volt battery, the converter 14 functions to charge the capacitor 16 from the tube's extinguishing voltage (approximately 30 volts) to 140 volts within approximately 7/10 second, and to the full 200 volts within approximately 1.5 seconds.

The camera 10 comprises (a) a bidirectional motor 20 which drives the camera's exposure control apparatus 21 and film advance mechanism 22, (b) logic switching circuitry 23 for controlling both charging of the flash unit 12 and energizing of the motor 20, and (c) a light-level sensing circuit 24 for measuring ambient light intensity.

The exposure control apparatus 21 includes an aperture control mechanism 25 for adjusting the size of an exposure aperture, and a shutter 26 for incovering and covering the exposure aperture to control an exposure interval. The motor 20 sequentially actuates the exposure control apparatus 21 and the film advance mechanism 22, which together constitute a highly automated system for effecting a photographic cycle.

The film advance mechanism 22 includes a film-metering pawl (not shown) for positioning film loaded in the camera 10 for an exposure. A normally open film-metering switch S_4 is held closed by the pawl when it is positioned between adjacent notches located seriatim along an edge portion of the film, and the switch S_4 is open when the pawl is located within a film notch or perforation, i.e. the pawl is registering film for an exposure. The condition of the switch S_4 provides an input to the switching circuit 23 for sequentially controlling the flash unit 12 and the motor 20.

The light-level sensing circuit 24, which includes a photodiode 27 arranged to sense ambient light, produces a logic level 1 output voltage (relatively high voltage) when scene light intensity is above a predetermined level, approximately 125 foot-lamberts, and produces a logic level 0 voltage (relatively low voltage) when scene light intensity is below 125 foot-lamberts. The output voltage of the circuit 24 is another input to the circuit 23 for controlling the flash unit 12 and the motor 20.

To bolster the level to which the flash unit 12 is charged prior to exposure, a highly sensitive "wakeup" switch S_{2A} is provided for commencing flash charging when only very light pressure is applied to the member 13. The pressure required is so slight that an operator may not be aware that the wakeup switch S_{2A} has been actuated. For example, light finger pressure on the release member 13 while the camera 10 is being pointed at a scene or while a scene is being framed in the camera's viewfinder 19 is sufficient to initiate flash charging. Thus, the wakeup switch S_{2A} can extend the pre-exposure time during which charging occurs to include, for example, scene framing time, in addition to the time

used to depress the release member 13 sufficiently, to cause the shutter 26 to open.

The present invention addresses the situation where the pre-exposure actuation time of the member 13 is so brief, that there is insufficient time for the flash capacitor to charge to a level sufficient to fire the strobe flash. Such a situation may arise, for example, when the camera operator jabs or stabs shutter-release member 13 to effect an exposure. In such a case, the apparatus of the invention functions to delay exposure for a variable time interval (up to about 7/10 second) in response to the shutter-release member being moved to a position in which the exposure operation is irreversibly initiated. This delay, although not sufficient in itself to provide a full charge, is long enough to allow the capacitor 16 to charge above a minimum voltage that is necessary to fire the flash tube 17. On the other hand, the full delay is not so long that it disturbs the camera operator to the point that an exposure is adversely affected.

Referring now to Fig. 3, a switch assembly S_2 is located immediately beneath the release member 13 in a switch-receiving pocket formed by a plastic body 28. The assembly S_2 includes three electrically conductive contacts 30, 31 and 32, and an electrically conductive arcuate toggle joint 34. The contacts 30 and 32, and the toggle joint 34 form the highly sensitive wakeup switch S_{2A} (Fig. 2 and 4), and the contacts 31 and 32, and the toggle joint 34 form a shutter-release switch S_{2B} (Fig. 2 and 4).

Each of the contacts 30, 31, and 32 has a projecting portion 30a, 31a, and 32a, respectively, which projects into the switch-receiving pocket through corresponding rectangular-shaped receiving apertures 28a, 28b, and 28c, which are located in the bottom of the body 28. The contacts 30, 31, and 32 are heat sealed in their respective positions to the underside of the body 28 by bosses 28d, 28e, and 28f, respectively.

The member 13 is aligned for limited vertical movement relative to the pocket of the body 28 by means of an opposed pair of depending L-shaped legs 13a and 13b, which are received respectively in apertures 28g and 28h located in the body 28. The member 13 aligns the toggle joint 34 within the top center of the pocket of the body 28 by means of an integral post 13c, which projects downwardly into a circular hole 34a. The hole 34a is located in the centre of an arcuate portion 34b, which forms the knee of the toggle joint 34.

The location of the toggle joint 34 relative to the switch contacts, and the coupling between the toggle joint and the member 13 are important to the proper operation of the wakeup switch S_{2A} , and, thus, to pre-exposure charging of the flash unit 12.

The toggle joint 34 serves as a leaf spring which lightly biases member 13 upwardly in a first position when it is deactuated. In its deactuated position, the member 13 aligns the toggle joint 34 so that its fork-shaped end segments 34c

and 34d remain just out of contact with the projections 30a and 32a, respectively, as shown by the dashed lines of Fig. 3. Additionally, by virtue of its radius of curvature, the knee 34b lies above the projecting portion 31a, somewhat further displaced from the contact 31 than the segments 34c and 34d are displaced respectively from the projections 30a and 32a. Thus, when the member 13 is deactuated, both the wakeup switch S_{2A} and the shutter-release switch S_{2B} are open.

When only slight downward pressure is applied to the member 13, such as when an operator places a finger on the member 13 in anticipation of making an exposure, the knee 34b of the toggle joint 34 depresses slightly, which causes both fork segments 34c and 34d to slide radially outwardly. This causes the forks 34c and 34d to contact respectively the projections 30a and 32a. However, the knee 34b, although closer to the projection 31a, remains out of contact with it. Thus, when only slight pressure is applied to the member 13, to move it to a second, intermediate position, the wakeup switch S_{2A} is closed, but the shutter-release switch S_{2B} is still open. When the switch S_{2A} closes, an exposure operation is reversibly initiated.

When additional pressure is applied to the member 13, i.e. it is more fully actuated, it moves from its intermediate position to a third position, which causes the shutter 26 to open. When the member 13 is in its third position, the knee 34b toggles downwardly, thereby engaging the contact 31a. The forks 34c and 34d remain in contact with the projections 30a and 32a. Thus, when the member 13 is in its third position, the wakeup switch S_{2A} and the shutter-releasing switch S_{2B} are both closed. As described below, once the switch S_{2B} has been closed for a brief interval, the exposure operation is irreversible.

The logic switching circuitry 23 for controlling the camera 10 and the flash unit 12 is shown in greater detail in Fig. 4. It will be readily apparent from the following description that the circuitry 23 is constituted primarily by a variety of conventional low-power digital logic gates, which may be readily manufactured in integrated circuit form.

A voltage and controlled power regulator 46, which is connected to the battery 18 through a normally open power switch S_1 and an external resistor 47, provides controlled operating voltages and currents for the logic gates constituting the switching circuitry 23.

A wakeup circuit 48 constitutes a latch, which is set when battery power is applied to the regulator 46, i.e. when the switch S_1 closes. Additionally, so long as the switch S_1 is closed, the latch is also set when the wakeup switch S_{2A} closes, the shutter-release switch S_{2B} closes, or the film-metering switch S_4 closes.

When the latch is set, the circuit 48 applies a controlled amount of power externally to the light-level sensing circuit 24, as shown in Fig. 4. It also supplies controlled power internally to circuitry 23, to a power-up one-shot multivibrator

49. While controlled power is supplied, a high-level operational current is drawn from the battery 18.

The latch of the circuit 48 is reset when any of a variety of camera and/or flash conditions exist, as described below. When the latch is reset, only a low-level quiescent current is drawn from the battery 18, to conserve its power.

The one-shot 49 is arranged to reset a divider circuit 50, when controlled power is supplied. The divider 50, which is supplied with a 10-khz pulse train by a clock 51, includes seventeen cascaded flip-flops arranged to provide various timing pulses, of different lengths. These pulses are used to enable and/or disable various circuits of switching circuitry 23 in a timed manner.

The timing pulses produced by the divider 50 that are most important to the operation of the flash charging apparatus are a 12.8-ms pulse, a .716-second pulse, and a 2.46-second pulse. The 12.8-ms pulse is used to prevent flash charging immediately after controlled power is supplied, while electrical transients subside. It also establishes an interval during which the light-level sensing circuit 24 measures scene light intensity, for the purpose of controlling a subsequent exposure. The 0.716-second pulse limits the exposure delay provided by the flash charging apparatus of the invention. The 2.46-second pulse limits both the interval used for flash charging when the power switch S_1 closes, and the interval used for flash charging after an exposed film frame is advanced.

An S_4 logic circuit 52 is arranged to drive the motor 20 in a positive direction then the film-metering switch S_4 is closed. When the switch S_4 enables the circuit 52, the motor 20 causes the film drive mechanism 22 to advance camera film.

A flash control logic circuit 56 turns the converter 14 on and off. The circuit 56 produces a FLASH INHIBIT signal, which turns the converter 14 off, while either the 12.8-ms timing pulse produced by the divider 50 is present, the motor 20 is running, or the flash unit 12 is fully charged. Otherwise, the circuit 56 causes the converter 14 to charge the flash unit 12 when controlled power is turned on by the wake-up circuit 48. The circuit 56 also resets the wakeup circuit 48 when both the motor 20 is off and the flash unit 12 is fully charged, so long as at least 12.8 milliseconds have elapsed since the divider 50 was last reset.

A shutter-release logic circuit 62 is arranged to enable an exposure logic circuit 66, reset the divider 50, and set a latch 67, in response to closing of the shutter-release switch S_{2B} . Additionally, the circuit 62 causes the wakeup circuit 48 to hold controlled power on so long as the switch S_{2B} remains closed.

The switch S_{2B} must remain closed for 12.8 milliseconds, otherwise the latch 67 is reset. When the latch 67 has been set for 12.8 milliseconds, it provides a digital logic signal to the circuit 66 corresponding to the scene light intensity sensed by the light-level sensing circuit 24. A

logic level 0 signal corresponds to relatively low ambient light, and a logic level 1 signal corresponds to relatively bright ambient light.

The exposure logic circuit 66, which causes an exposure to occur, is arranged to energize the motor 20, in response to receiving the digital logic signal from the latch 67. The circuit 66 is enabled to cause the motor 20 to be driven in a positive direction, in response to a logic level 0 signal being supplied by the latch 67. In this direction, the motor 20 causes the aperture control mechanism 25 to set an exposure aperture at $f/2.8$, and the shutter 26 operates at $1/100$ second.

The circuit 66 causes the motor 20 to be driven in a negative direction in response to a logic level 1 signal from the latch 67. In this direction, the motor 20 causes the mechanism 25 to set the exposure aperture at $f/8$, and the shutter 26 operates at $1/200$ second.

When scene light is low, the circuit 66 signals the flash control logic circuit 56 to enable the converter 14. According to the invention if the flash unit 12 is not fully charged when the shutter-release member 13 reaches a position to close switch S_{2B} , the circuit 66 temporarily delays the energizing of motor 20 and the resulting shutter-release, to allow for supplementary charging to occur prior to an exposure. When either the 0.716-second pulse, produced by the divider 50, terminates or a FLASH FULLY CHARGED signal is received from the circuit 56, whichever occurs first, the exposure logic circuit 66 then drives the motor 20 to initiate exposure.

As regards the variable time interval during which the exposure is delayed, we have found that, once the exposure operation is irreversibly initiated, delaying an exposure less than $1/5$ second is not noticeable to a camera operator. Once the delay exceeds $3/4$ second, it is generally detectable, although not to the point that exposure quality is adversely affected. The usual reaction of an operator to the delay is to press the release member more forcefully which has no effect on exposure. In our preferred embodiment, we have selected approximately $7/10$ seconds as the maximum delay for charging.

When a dust cover or shield 68 (Fig. 2 and 4) covers a taking lens 70 (Fig. 1), or when a film-loading door 72 (Fig. 1, 2 and 4) is open, a pivot 69 is blocked from moving in the counterclockwise direction under the influence of a bias spring 73. When the pivot 69 is blocked, the switch S_1 is open. When both the cover 68 is moved to a lens-uncovering position and the door 72 is closed, shown by the dashed lines of Fig. 2 and 4, the pivot 69 moves in the counterclockwise direction under the influence of the spring 73, to close the switch S_1 . When the switch S_1 closes, the wakeup circuit 48 is set, and thereby supplies controlled power to the circuitry 23 and the light-level sensing circuit 24.

To simplify the description of the operation of apparatus for charging the flash unit 12 in response to actuation of the shutter-release mem-

ber 13, it is assumed that the lens 70 is uncovered, the door 72 is closed and the camera 10 is loaded with film, and the film-metering pawl is located within a film perforation. Thus, the switch S_1 is closed and the switch S_4 is open.

To initiate an exposure operation, the member 13 is moved from its first, deactuated position to its second, intermediate position so as to close the wakeup switch S_{2A} . It will be readily apparent from the above, closing of the switch S_{2A} can occur as the camera operator merely positions a finger take a picture. In response to closing the wakeup switch S_{2A} , the latch in the wakeup circuit 48 is set, which supplies controlled power to the converter 14, the light-level sensing circuit 24, and the 1-shot 49. The divider 50 initializes the 12.8-ms, 0.716-second, and the 2.46-second timing pulses.

During the 12.8-ms interval immediately following closing of the wakeup switch S_{2A} , the flash logic control circuit 56 is inhibited by the 12.8-ms pulse. At the end of this brief interval, the circuit 56 causes the converter 14 to charge the flash unit 12, if it is charged less than its full charge of 200 volts.

Until the member 13 is moved from its intermediate position into its third position, which closes the shutter-release switch S_{2B} , the flash unit 12 continues to charge so long as it is less than fully charged. If prior to closing the switch S_{2B} , the flash unit 12 becomes fully charged, a zener diode 74 (Fig. 2) conducts. This conduction produces the FLASH FULLY CHARGED signal, at the junction between the diode 74 and the resistor 76. In response to this signal, the circuit 56 produces the FLASH INHIBIT signal, which turns the converter 14 off. Because the motor 20 is off at this time, the circuit 56 also resets the wakeup circuit 48, thereby reducing battery current to a quiescent level.

Whether or not the flash unit 12 becomes fully charged prior to closing the shutter-release switch S_{2B} , when the switch S_{2B} closes, the shutter-release logic circuit 62 sets both the wakeup circuit 48 and the latch 67, resets the divider 50, and enables the exposure logic circuit 66.

During the 12.8-ms interval immediately following closing of the switch S_{2B} , the flash logic control circuit 56 is again inhibited by means of the 12.8-ms timing pulse produced in response to resetting the divider 50. During this time, the light-level sensing circuit 24 measures scene light intensity.

If the camera operator happens to have deactuated the member 13 sufficiently to allow the shutter-release switch S_{2B} to reopen prior to termination of the 12.8-millisecond interval, the latch 67 is reset, and an exposure will not occur. However, if the shutter-release switch S_{2B} is closed for at least 12.8 milliseconds, the exposure operation is now irreversibly initiated, and an exposure is made, as follows, regardless of the state of the switch S_{2B} .

At the end of the 12.8-ms interval, the latch 67 produces a logic level 1 output signal (high vol-

(13)

tage) when the circuit 24 measures scene light intensity above approximately 125 foot-lamberts, and the latch 67 produces a logic level 0 signal (low voltage) when the circuit 24 senses scene light intensity below 125 foot-lamberts.

The latch 67 supplies the logic signal corresponding to ambient light intensity to the exposure logic circuit 66. If ambient light is low, the circuit 66 enables the flash control circuit 56. If the flash unit 12 is not fully charged, the circuit 56 causes the converter 14 to initiate supplemental charging of the flash unit 12.

A race condition develops between fully charging the flash unit 12 and terminating the 0.716-second pulse produced by the divider 50 when the switch S_{28} is closed. If the flash unit 12 becomes fully charged first, the FLASH FULLY CHARGED signal is produced at the junction between the diode 74 and the resistor 76. That signal causes the circuit 56 to turn the converter 14 off, and causes the circuit 56 to enable the exposure logic circuit 66.

If the 0.716-sec. pulse terminates first, that event enables the circuit 66 which causes the circuit 56 to turn the converter 14 off.

In either case, an exposure occurs immediately in response to terminating supplemental flash charging. The exposure logic circuit 66 causes the motor 20 to be driven in the positive direction. This causes the aperture control mechanism 25 to set an exposure aperture at $f/2.8$, then cause the shutter 26 to operate at 1/100 second. At this speed, the shutter 26 closes a normally open flash synchronization switch S_3 , which fires the flash unit 12 during exposure.

In bright ambient light, flash illumination is not used. In this case, the logic level 1 signal produced by the latch 67 causes the circuit 66 to drive the motor 20 in a negative direction, immediately after the latch 67 signals to the circuit 66 that scene light intensity is relatively bright. The aperture control mechanism 25 is set at an $f/6$ exposure aperture, the the shutter 26 is operated at 1/200 second.

To complete the description of an exposure operation, once either an ambient or a flash exposure is completed, the motor 20 causes actuation of the film-metering pawl which closes the switch S_4 . In response to closing the switch S_4 , the wakeup circuit 48 is again set, which causes reinitializing of the timing pulses produced by the divider 50. Additionally, the S_4 logic circuit 52 causes the motor 20 to be driven in the positive direction, thereby advancing film. When film has been advanced one frame, which requires less than about 1/8 second, the metering pawl drops into the next film notch, thus opening the switch S_4 . In response to opening the switch S_4 , the circuit 52 turns the motor 20 off.

When film advance is terminated, the exposure operation is completed. However, the logic switching circuit 23 continues to function to prepare the flash unit 12 for the next exposure. When the motor 20 turns off following film advance, the logic circuit 56 reinitiates charging of

the flash unit 12.

So long as the shutter-release member 13 is not reactivated in anticipation of a subsequent exposure operation, a race condition develops between fully charging the flash unit 12 and terminating the 2.46-second pulse produced by divider 50, when the switch S_4 is closed at the end of an exposure. If the prior exposure was solely in ambient light, most likely little if any additional charging would be necessary to produce the FLASH FULLY CHARGED signal. If the prior exposure occurred with flash light, a longer charging interval would be necessary for restoring the flash charge, to produce the FLASH FULLY CHARGED signal. In either case, flash charging is reinitiated by the circuit 56. The FLASH FULLY CHARGED signal then causes the circuit 56 to turn the converter 14 off.

If, for whatever reason, flash charging is still occurring 2.46 seconds after the switch S_4 is closed after an exposure, terminating the 2.46-second pulse produced by the divider 50 resets the wakeup circuit 48. This decreases the battery current to the aforementioned low-power, quiescent level, which turns the converter 14 off.

The flash charging that occurs after an exposure further assists in providing a full or nearly full flash charge for the next exposure at the time release member 13 causes the shutter-release switch S_{28} to close. This charging, of course, prepares the flash unit 12 for an exposure of all film frames other than the first frame in a film roll or cartridge.

To assist in providing a full flash charge prior to the first exposure, the logic switching circuit 23 provides for automatically charging the flash unit 12 in response to closing the film-loading door 72. So long as the lens 70 is uncovered, the power switch S_1 closes when the film-loading door 72 closes. Thus, when film is loaded into the camera 10 when the lens 70 is already uncovered, the switch S_1 closes in response to closing the door 72. In response to closing the switch S_1 , the wakeup circuit 48 is set, and the divider 50 produces its timing pulses.

When films is loaded in the camera 10, the film-metering pawl may be located between adjacent film notches. Thus, the switch S_4 may be closed when the camera 10 is initially loaded with film. If the switch S_4 is closed, the logic circuit 52 energizes the motor 20, to advance the film. Film is advanced until the metering pawl drops into a film notch, thereby opening the switch S_4 . This switch condition causes the circuit 52 to turn the motor 20 off.

If 12.8 milliseconds have elapsed since the wakeup circuit 48 as set, once the motor 20 is off, the flash control logic circuit 56 turns the converter 14 on. If 12.8 milliseconds have not elapsed, for example, the film-metering pawl was already registering film when the switch S_1 closes, as soon as the 12.8-ms timing pulse produced by the divider 50 has terminated, the circuit 56 turns the converter 14 on.

As was described in regard to charging the flash unit 12 after film advance following an exposure, a race condition develops between fully charging the flash unit 12 and terminating the 2.46-second pulse, so long as the member 13 is not actuated. Assuming the converter 14 is operating in its intended manner, the FLASH FULLY CHARGED signal would be produced first, and thus the converter would turn off as a result of that signal. Thus, the flash unit 12 is charged in response to closing the film-loading door 72, prior to exposing the first film frame.

It will be readily apparent that if a camera operator actuates the member 13 shortly after the switch S₁ closes, or shortly after an exposed film frame is advanced, the flash unit 12 may not be fully charged prior to irreversibly initiating an exposure operation. Consequently, the variable maximum delay of about 7/10 second becomes important in assuring that the flash unit 12 is sufficiently charged for a flash exposure.

A purpose of the 2.46-second timing pulse produced by the divider 50 is to prevent inadvertently draining battery power. It is readily apparent from the above description of the flash charging apparatus that this timing pulse prevents the drawing of controlled power from the battery 18 for longer than 2.46 seconds after the power switch S₁ is closed while the camera 10 is idle. Additionally, if a camera malfunction occurs during an exposure operation, for example, the film becomes bound during film transport, the 2.46-second pulse causes controlled power to be removed from the camera 10.

The invention has been described in detail with particular reference to a preferred embodiment thereof, but it will be understood that variations and modifications can be effected within the scope of the claims. For example, although the camera 10 makes a flash exposure only in low ambient light, it will be understood the invention is also applicable to a camera which fires a flash independently of ambient light.

Claims

1. Apparatus for charging a camera's electronic strobe flash unit (12) in response to movement of the camera's shutter-release member from a rest position toward a shutter-releasing position, said apparatus comprising means for delaying shutter release for a variable time interval in the event said shutter release member is moved at a rate which would not allow sufficient time for a charging circuit to charge said flash unit, prior to exposure, to a level sufficient to fire the strobe flash, said time interval being sufficient to enable charging to said level, characterized in that said delaying means comprises a first circuit (12, 56) for producing a signal in response to said flash unit being charged to a predetermined level; a second circuit (50) for producing a timing pulse of predetermined duration; and a logic circuit (66) operatively coupled to said first and sec-

ond circuits, said logic circuit being adapted to produce a shutter-releasing signal in response to said shutter-releasing member (13) having reached its shutter-releasing position (S_{2a}) and to either (a) termination of said timing pulse, or (b) receipt of said first circuit signal, whichever occurs first.

2. The apparatus as defined in claim 1 wherein said timing pulse is less than approximately 0.75 second.

Patentansprüche

1. Vorrichtung zum Laden eines Elektronenblitzgeräts (12) einer Kamera in Abhängigkeit von der Bewegung eines Kameraverschlußauslösgliedes aus einer Ruhestellung in eine Verschlußauslösestellung, mit Mitteln die die Verschlußauslösung für eine veränderliche Zeitspanne verzögern, wenn das Verschlußauslösglied mit einer solchen Geschwindigkeit bewegt wird, daß für einen Ladestromkreis nicht genügend Zeit vorhanden wäre, das Blitzgerät vor einer Belichtung bis zu einer Höhe aufzuladen, bei der es einen Elektronenblitz abgeben kann, wobei die Zeitspanne für das Aufladen auf eine solche Höhe ausreichend ist, dadurch gekennzeichnet, daß die Verzögerungsmittel eine erste Schaltung (12, 56) umfassen, die in Abhängigkeit von der Aufladung des Blitzgeräts auf eine vorbestimmte Höhe ein Signal erzeugt, eine zweite Schaltung (50), die einen Zeitsteuerimpuls von vorbestimmter Dauer abgibt, sowie eine logische Schaltung (66), die mit der ersten und der zweiten Schaltung wirksam gekoppelt ist, wobei die logische Schaltung ein Verschlußauslösesignal in Abhängigkeit davon abgibt, daß das Verschlußauslösesignal (13) seine Verschlußauslösestellung (S_{2a}) erreicht hat und (a) der Zeitsteuerimpuls beendet ist oder (b) die logische Schaltung das von der ersten Schaltung abgegebene Signal empfangen hat, je nachdem was zuerst eintritt.

2. Vorrichtung nach Anspruch 1, dadurch gekennzeichnet, daß der Zeitsteuerimpuls nicht länger als etwa 0,75 Sekunden dauert.

Revendications

1. Appareil pour charger un dispositif d'éclairage à tube à éclair électronique (12) d'un appareil de prise de vues à la suite du déplacement de l'organe de déclenchement de l'obturateur de l'appareil de prise de vues à partir d'une position de repos en direction d'une position de déclenchement de l'obturateur, cet appareil comprenant des moyens pour retarder la libération de l'obturateur pendant une durée variable pour le cas où cet organe de déclenchement de l'obturateur se déplace à une cadence qui n'allouerait pas une durée suffisante pour permettre à un circuit de charge de charger ce dispositif d'éclairage à éclair, avant une prise de vue, à un niveau

As was described in regard to charging the flash unit 12 after film advance following an exposure, a race condition develops between fully charging the flash unit 12 and terminating the 2.46-second pulse, so long as the member 13 is not actuated. Assuming the converter 14 is operating in its intended manner, the FLASH FULLY CHARGED signal would be produced first, and thus the converter would turn off as a result of that signal. Thus, the flash unit 12 is charged in response to closing the film-loading door 72, prior to exposing the first film frame.

It will be readily apparent that if a camera operator actuates the member 13 shortly after the switch S₁ closes, or shortly after an exposed film frame is advanced, the flash unit 12 may not be fully charged prior to irreversibly initiating an exposure operation. Consequently, the variable maximum delay of about 7/10 second becomes important in assuring that the flash unit 12 is sufficiently charged for a flash exposure.

A purpose of the 2.46-second timing pulse produced by the divider 50 is to prevent inadvertently draining battery power. It is readily apparent from the above description of the flash charging apparatus that this timing pulse prevents the drawing of controlled power from the battery 18 for longer than 2.46 seconds after the power switch S₁ is closed while the camera 10 is idle. Additionally, if a camera malfunction occurs during an exposure operation, for example, the film becomes bound during film transport, the 2.46-second pulse causes controlled power to be removed from the camera 10.

The invention has been described in detail with particular reference to a preferred embodiment thereof, but it will be understood that variations and modifications can be effected within the scope of the claims. For example, although the camera 10 makes a flash exposure only in low ambient light, it will be understood the invention is also applicable to a camera which fires a flash independently of ambient light.

Claims

1. Apparatus for charging a camera's electronic strobe flash unit (12) in response to movement of the camera's shutter-release member from a rest position toward a shutter-releasing position, said apparatus comprising means for delaying shutter release for a variable time interval in the event said shutter release member is moved at a rate which would not allow sufficient time for a charging circuit to charge said flash unit, prior to exposure, to a level sufficient to fire the strobe flash, said time interval being sufficient to enable charging to said level, characterized in that said delaying means comprises a first circuit (12, 56) for producing a signal in response to said flash unit being charged to a predetermined level; a second circuit (50) for producing a timing pulse of predetermined duration; and a logic circuit (66) operatively coupled to said first and sec-

ond circuits, said logic circuit being adapted to produce a shutter-releasing signal in response to said shutter-releasing member (13) having reached its shutter-releasing position (S_{2a}) and to either (a) termination of said timing pulse, or (b) receipt of said first circuit signal, whichever occurs first.

2. The apparatus as defined in claim 1 wherein said timing pulse is less than approximately 0.75 second.

Patentansprüche

1. Vorrichtung zum Laden eines Elektronenblitzgeräts (12) einer Kamera in Abhängigkeit von der Bewegung eines Kameraverschlußauslösegliedes aus einer Ruhestellung in eine Verschlußauslösestellung, mit Mitteln die die Verschlußauslösung für eine veränderliche Zeitspanne verzögern, wenn das Verschlußauslöseglied mit einer solchen Geschwindigkeit bewegt wird, daß für einen Ladestromkreis nicht genügend Zeit vorhanden wäre, das Blitzgerät vor einer Belichtung bis zu einer Höhe aufzuladen, bei der es einen Elektronenblitz abgeben kann, wobei die Zeitspanne für das Aufladen auf eine solche Höhe ausreichend ist, dadurch gekennzeichnet, daß die Verzögerungsmittel eine erste Schaltung (12, 56) umfassen, die in Abhängigkeit von der Aufladung des Blitzgeräts auf eine vorbestimmte Höhe ein Signal erzeugt, eine zweite Schaltung (50), die einen Zeitsteuerimpuls von vorbestimmter Dauer abgibt, sowie eine logische Schaltung (66), die mit der ersten und der zweiten Schaltung wirksam gekoppelt ist, wobei die logische Schaltung ein Verschlußauslösesignal in Abhängigkeit davon abgibt, daß das Verschlußauslösesignal (13) seine Verschlußauslösestellung (S_{2a}) erreicht hat und (a) der Zeitsteuerimpuls beendet ist oder (b) die logische Schaltung das von der ersten Schaltung abgegebene Signal empfangen hat, je nachdem was zuerst eintritt.

2. Vorrichtung nach Anspruch 1, dadurch gekennzeichnet, daß der Zeitsteuerimpuls nicht länger als etwa 0,75 Sekunden dauert.

Revendications

1. Appareil pour charger un dispositif d'éclairage à tube à éclair électronique (12) d'un appareil de prise de vues à la suite du déplacement de l'organe de déclenchement de l'obturateur de l'appareil de prise de vues à partir d'une position de repos en direction d'une position de déclenchement de l'obturateur, cet appareil comprenant des moyens pour retarder la libération de l'obturateur pendant une durée variable pour le cas où cet organe de déclenchement de l'obturateur se déplace à une cadence qui n'allouerait pas une durée suffisante pour permettre à un circuit de charge de charger ce dispositif d'éclairage à éclair, avant une prise de vue, à un niveau



suffisant pour mettre à feu le tube à éclair, cette durée étant suffisante pour permettre cette charge à ce niveau, et étant caractérisé en ce que ce moyens retardateurs comprennent un premier circuit (12, 56) pour émettre un signal à la suite de la charge à un niveau prédéterminé de ce dispositif à éclair; un deuxième circuit (50) pour produire une impulsion de chronométrage de durée déterminée; et un circuit logique (66) qui est associé fonctionnellement à ces premier et deuxième circuits, et qui est conçu pour produire un signal de déclenchement d'obturateur lorsque ce pousier de déclenchement de l'obturateur (13) a atteint sa position de déclenchement d'obturateur (S_{2a}) et soit (a) à l'achèvement de l'impulsion de chronométrage, soit (b) à la réception du signal du premier circuit, suivant lequel se produit le premier. Appareil conforme à la revendication 1 où cette impulsion de chronométrage est inférieure à environ 0,75 s.

5

10

15

20

25

30



35

40

45

50

55

60

65

8