



159159



G00002

COMMUNICATION APPARATUS CONNECTABLE TO A COMMUNICATION DEVICE

Field Of The Invention

5

The present invention is directed to a communications apparatus connectable to a communication device, such as, for example, a modem connectable to a communication device, and a method for enabling data communication, and in particular, to an apparatus and method that detects various communication modes
10 and selects an appropriate communication configuration to establish a communication link between a plurality of communication devices.

Discussion Of Background And Other Information

15 Traditionally, data communication devices, such as, for example, modems (both analog and digital), have been employed over public switched telephone networks (PSTN) to transmit data between a first location and a second location. Such modems typically operate within a conventional voice band (e.g., approximately 0 through 4 kHz bandwidth) of the PSTN. Early modems transmitted data over the
20 PSTN at a speed of approximately 300 bit/second, or less. Over time, and with the increased popularity of the Internet, faster communication schemes (e.g., modems) were demanded and developed. Currently, the fastest analog modem available (referred to as an ITU-T V.34 modem, as defined by the International Telecommunication Union Telecommunication Standardization Sector (ITU-T)),
25 transmits data at a rate of approximately 33,600 bits/second under ideal conditions. Hybrid digital-analog modems, referred to as ITU-T V.90 modems, can achieve data transmission rates up to 56,000 bits/second under ideal conditions. These modems continue to exchange data within the approximate 4 kHz bandwidth of the PSTN.

30 It is not uncommon to transfer data files that are several megabytes (MB) in size. A modem that operates utilizing the V.34 modulation requires a long time to transfer

such a file. As a result, a need has developed for even faster modems and Internet access methods.

Accordingly, many new communication methods are being proposed and/or developed to transmit high speed or broadband data on the local twisted wire pair that uses the spectrum above the traditional 4 kHz band. For example, various "flavors" (variations) of digital subscriber line (DSL) modems have been/are being developed, such as, but not limited to, for example, DSL, ADSL, VDSL, HDSL, SHDSL and SDSL (the collection of which is generally referred to as xDSL).

Each xDSL variation employs a different communication scheme, resulting in different upstream and/or downstream transfer speeds, and utilizes differing frequency bands of a twisted pair communication channel. A wide range of physical and environmental limitations of the various configurations of the twisted pair wires leads to widely varying expectations of a feasible communication capability bandwidth. Depending on, for example, the quality of the twisted wire pair (e.g., CAT3 wire vs. CAT5 wire), a given xDSL scheme may not be able to transmit data at its maximum advertised data transfer rate.

While xDSL technologies exist and offer the promise of solving the high speed data transfer problem, several obstacles exist to the rapid deployment and activation of xDSL equipment.

Several of the various xDSL schemes permit simultaneous communication on a single twisted pair in the voice band and in a frequency band above the voice band. To achieve a simultaneous voice band and above voice band communication, some xDSL variations require filters, including low pass filters, high pass filters and combinations of filters that are sometimes referred to as "splitters". The filters separate the frequency band that carries voice band communication from the frequency band above the voice band carrying data communication. The use and type of filters may differ between installations.

Recently, there has been technology and market motivation to eliminate or reduce the use of those filters. Thus, for a given communication channel, the presence and/or type of filter is often unknown. There is a need for the communication devices to "know" the existence and configuration of such filters before initiating a communication method, as such filters impacts which communication methods are viable.

Many different xDSL and high speed access technologies solutions have been described in public, proprietary, and/or de facto standards. Equipment at each end of a connection may implement one standard (or several standards) that may (or may not) be mutually compatible. In general, startup and initialization methods of the various standards have been heretofore incompatible.

Line environments surrounding the xDSL data communication schemes, such as, for example, their ability to co-exist with a conventional analog modem that communicates within the conventional voice band (e.g., 0 - 4 kHz bandwidth), differences in central office equipment, the quality of the line, etc., are numerous, differ significantly, and are complicated. Accordingly, it is essential to be able to determine the capabilities of the communication channel, in addition to being able to determine the capabilities of the communication equipment, in order to establish an optimum and non-interfering communication link.

User applications can have a wide range of data bandwidth requirements. Although a user could always use the highest capacity xDSL standard contained in a multiple xDSL box, in general, that will be the most expensive service, since communication costs are generally related to the available bandwidth. When a low bandwidth application is used, the user may desire the ability to indicate a preference for a low bandwidth xDSL (and hence, a cheaper communication service), as opposed to using a high bandwidth xDSL service. As a result, it is desirable to have a system that automatically indicates user service and application requirements to the other end of the link (e.g., central office).

In addition to the physical composition of the communication equipment and communication channel, high speed data access complexity is also influenced by regulatory issues. The result has been that possible configuration combinations at each end of a communication channel have grown exponentially.

5

The US Telecommunication Act of 1996 has opened the vast infrastructure of metallic twisted wire pairs to both competitive (CLEC) usage, and the incumbent telephone provider (ILEC) that originally installed the wires. Thus, multiple providers may have differing responsibilities and equipment deployed for a single wire pair.

10

In a given central office termination, a given communication channel (line) may be solely provisioned for voiceband-only, ISDN, or one of the many new xDSL (ADSL, VDSL, HDSL, SDSL, etc.) services. Since the Carterphone court decision, telephone service users (customers) have a wide range of freedom for placing (i.e., installing and utilizing) communication customer premise equipment (e.g., telephones, answering machines, modems, etc.) on voiceband channels. However, customer premise equipment (CPE) associated with leased data circuits has typically been furnished by the service provider. As the high speed communication market continues to evolve, customers will also expect and demand freedom in selecting and providing their own CPE for high speed circuits using the band above the traditional voice band. This will place increased pressure on the service providers to be prepared for a wide range of equipment to be unexpectedly connected to a given line.

25

The customer premise wiring condition/configuration inside of the customer premise (e.g. home, office, etc.) and the range of devices already attached to nodes in the wiring are varied and unspecifiable. For a service provider to dispatch a technician and/or craftsman to analyze the premise wiring and/or make an installation represents a large cost. Accordingly, an efficient and inexpensive (i.e., non-human intervention) method is needed to provide for the initialization of circuits in the

30

situation where a plethora of communication methods and configuration methods exist.

5 Still further, switching equipment may exist between the communication channel termination and the actual communication device. That switching equipment may function to direct a given line to a given type of communication device.

10 Thus, a high speed data access start-up technique (apparatus and method) that solves the various equipment, communication channel, and regulatory environment problems is urgently needed.

In the past, the ITU-T has published recommended methods for initiating data communication over voice band channels. Specifically, two Recommendations were produced:

- 15 1) Recommendation V.8 (09/94) - "Procedures for Starting Sessions of Data Transmission over the General Switched Telephone Network"; and
2) Recommendation V.8bis (08/96) - "Procedures for the Identification and Selection of Common Modes of Operation Between Data Circuit-terminating Equipments (DCEs) and Between Data Terminal Equipments (DTEs) over the
20 General Switched Telephone Network".

Both Recommendations use a sequence of bits transmitted from each modem to identify and negotiate mutually common (shared) operating modes, such as the modulation scheme employed, protocol, etc. However, both startup sequence
25 Recommendations are applicable only to the conventional voice band communication methods. Further, these conventional startup sequences do not test (and/or indicate) the constitution and/or condition of the communication channel between the modems.

30 However, line condition information, such as, for example, frequency characteristics, noise characteristics, presence or absence of a splitter, etc., is useful at the time that plural xDSL modems are negotiating a connection, prior to

actually connecting to each other, if the communications link is to be successfully established.

Voice band line probing techniques are known in the art and can be used to
5 determine voice band line condition information. Such techniques have been used
to optimize a given modulation method, such as, for example, V.34, but have not
been used to optimize startup methods and/or communication selection methods.
In a set of devices with multiple modulation methods, V.8 or V.8bis has been used
to negotiate and then select a particular modulation. After the modulation initiation
10 sequence has started, line probing techniques are used to receive some indication
of the condition of the communication channel. If it is determined at that point that a
given communication channel can not effectively support a chosen modulation
method, time consuming heuristic (i.e., self-learning) fallback techniques are
employed by the prior art to try and find a modulation method that works.

15 In order to establish an improved communication link, a method is required that
observes (examines) the line conditions before attempting to select the most
appropriate communication method. While techniques have been established to
increase the data rate for a given modulation, the prior art does not provide a
20 method for using channel information to aid in the selection of the communication
method.

Unfortunately, in the current state of the art, capability negotiations occur without
knowledge of the prevailing channel configuration. Explicit knowledge of spectrum,
25 splitting, etc. is vital to the selection of the most appropriate communication
mechanism (modulation) decision process.

Definitions

30 During the following discussion, the following definitions are employed:
activating station (calling station) - the DTE, DCE and other associated terminal
equipment which originates an activation of an xDSL service;

answering station - the DTE, DCE and other associated terminal equipment which answers a call placed on a GSTN;

carrier set - a set of one or more frequencies associated with a PSD mask of a particular xDSL Recommendation;

5 **CAT3** - cabling and cabling componenets designed and tested to transmit cleanly to 16 MHZ of communications. Used for voice and data/LAN traffic to 10 megabits per second;

CAT5 - cabling and cabling componenets designed and tested to transmit cleanly to 100 MHZ of communications;

10 **communication method** - form of communication sometimes referred to as modems, modulations, line codes, etc.;

downstream - direction of transmission from the xTU-C to the xTU-R;

errored frame - frame that contains a frame check sequence (FCS) error;

Galf - an octet having the value 81_{16} ; i.e., the ones complement of an HDLC flag;

15 **initiating signal** - signal which initiates a startup procedure;

initiating station - DTE, DCE and other associated terminal equipment which initiates a startup procedure;

invalid frame - frame that has fewer than four octets between flags, excluding transparency octets,

20 **message** - framed information conveyed via modulated transmission;

metallic local loop - communication channel 5, the metallic wires that form the local loop to the customer premise;

responding signal - signal sent in response to an initiating signal;

responding station - station that responds to initiation of a communication transaction from the remote station;

25 **session** - active communications connection, measured from beginning to end, between computers or applications over a network;

signal - information conveyed via tone based transmission;

signaling family - group of carrier sets which are integral multiples of a given carrier spacing frequency;

30 **splitter** - combination of a high pass filter and a low pass filter designed to split a metallic local loop into two bands of operation;

telephony mode - operational mode in which voice or other audio (rather than modulated information-bearing messages) is selected as the method of communication;

transaction - sequence of messages, ending with either a positive acknowledgment [ACK(1)], a negative acknowledgment (NAK), or a time-out;

terminal - station; and

upstream: The direction of transmission from the xTU-R to the xTU-C.

Abbreviations

10

The following abbreviations are used throughout the detailed discussion:

- ACK** - Acknowledge Message;
- ADSL** - Asymmetric Digital Subscriber Line;
- 15 **ANS** - V.25 answer tone;
- ANSam** - V.8 modulated answer tone;
- AOM** - Administration, Operations, and Management;
- CCITT** - International Telegraph and Telephone Consultative Committee;
- CDSL** - Consumer Digital Subscriber Line;
- 20 **CR** - Capabilities Request;
- CL** - Capabilities List;
- CLR** - Capabilities List Request;
- DCME** - Digital Circuit Multiplexing Equipment;
- DPSK** - Differential encoded binary Phase Shift Keying;
- 25 **DIS** - Digital Identification Signal;
- DMT** - Discrete Multi-Tone;
- DSL** - Digital Subscriber Line;
- EC** - Echo canceling;
- EOC** - Embedded Operations channel;
- 30 **ES** - Escape Signal;
- FCS** - Frame Check Sequence;
- FDM** - Frequency Division Multiplexing;

- FSK** - Frequency Shift Keying;
- GSTN** - General Switched Telephone Network (same as PSTN);
- HDSL** - High level Data Link Control;
- HSTU** - Handshake Transceiver Unit;
- 5 **IETF** - Internet Engineering Task Force;
- ISO** - International Organization for Standardization;
- ITU-T** - International Telecommunication Union – Telecommunication Standardization Sector;
- LSB** - Least Significant Bit;
- 10 **LTU** - Line Termination Unit (Central office end);
- MR** - Mode Request,
- MS** - Mode Select;
- MSB** - Most Significant Bit;
- NAK** - Negative Acknowledge Message;
- 15 **NTU** - Network Termination Unit (Customer premise end);
- OGM** - Outgoing Message (recorded voice or other audio);
- ONU** - optical network Unit;
- POTS** - Plain Old Telephone Service
- PSD** - Power Spectral Density;
- 20 **PSTN** - Public Switched Telephone Network;
- RADSL** - Rate Adaptive DSL;
- REQ** - Request Message Type Message;
- RFC** - Request For Comment;
- RTU** - RADSL Terminal Unit;
- 25 **SAVD** - Simultaneous or Alternating Voice and Data;
- SNR** - Signal to Noise Ratio;
- VDSL** - very high speed Digital Subscriber Line;
- xDSL** - any of the various types of Digital Subscriber Lines (DSL).;
- xTU-C** - central terminal unit of an xDSL; and
- 30 **xTU-R** - remote terminal unit of an xDSL.

SUMMARY OF THE INVENTION

There is provided a communication apparatus selectively connectable to a communication device, comprising: a communicator that executes a first communication mode that transmits, to the communication device, a first predetermined signal that designates a specific mode, the communication device responding by issuing a second predetermined signal; the communicator executing a second communication mode to transmit a third predetermined signal that requests a transmission of the first predetermined signal from the communication device, and receives the first predetermined signal from the communication device, the second communication mode thereafter transmitting the second predetermined signal to the communication device; and a controller that executes one of the first communication mode and the second communication mode upon initializing a communication with the communication device.

15

Preferably, the first predetermined signal comprises a MS signal and the third predetermined signal comprises a MR signal. The second predetermined signal preferably comprises one of an ACK signal and a NACK signal.

It is preferable that the communicator executes a third communication mode that transmits a CLR signal to the communication device that informs the communication device of a function list of the communication apparatus and requests a function list of the communication device, the communication device transmitting a CL signal that includes the function list of the communication device to the communication apparatus in response to the CLR signal, after which the third communication mode is executed to transmit one of the ACK signal and the NACK signal to the communication device

25

Preferably, the third communication mode is either executed prior to an execution of the first communication mode or prior to an execution of the second communication mode.

30

Advantageously, the communicator transmits the NACK signal when the communication device requests a non-executable mode and returns the communication apparatus to an initialization state upon an occurrence of a predetermined event. Preferably, the predetermined event comprises a transmission of the NACK signal.

It is preferable that the communicator executes a third communication mode that transmits a CLR signal to the communication device that informs the communication device of a function list of the communication apparatus and requests a function list of the communication device, wherein the communication device transmits a partial function list of the communication device to the communication apparatus in response to the CLR signal, after which the third communication mode is executed to transmit one of the ACK signal and the NACK signal to the communication device.

It is preferred that the third communication mode is executed when the partial function list of the center is received by the communicator a predetermined number of times.

In another embodiment, there is provided a communication apparatus selectively connectable to a communication terminal, comprising: a communicator that executes a first communication mode, associated with the communication apparatus, that transmits a first predetermined signal to the communication terminal that designates a specific mode, and that receives a second predetermined signal from the communication terminal; the communicator executing a second communication mode, associated with the communication apparatus, that transmits a third predetermined signal to the communication terminal requesting a transmission of the first predetermined signal by the communication terminal, the communicator receiving the first predetermined signal from the communication terminal, the communicator executing the second communication mode thereafter to transmit the second predetermined signal to the communication terminal; and a controller that controls the communicator to execute one of the first communication

mode and the second communication mode upon initializing a communication with the remote communication terminal

Preferably, the first predetermined signal comprises a MS signal, the second
5 predetermined signal comprises one of an ACK signal and a NACK signal and the third predetermined signal comprises a MR signal.

Advantageously, the communicator executes a third communication mode that transmits a CLR signal to the communication terminal that informs the
10 communication terminal of a function list of the communication apparatus and requests a function list of the communication terminal, the communication terminal transmitting a CL signal that includes the function list of the communication terminal to the communication apparatus, after which the third communication mode is executed to transmit one of the ACK signal and the NACK signal to the
15 communication terminal.

There is also provided a method for performing a data communication between a communication apparatus and a communication device, comprising: communicating
20 in a first communication mode of the communication apparatus to transmit an MS signal designating a specific mode to the communication device, the communication device receiving the MS signal and transmitting one of an ACK signal and a NACK signal to the first communication mode of the communication apparatus; communicating in a second communication mode of the communication apparatus to transmit an MR signal to the communication device requesting that the
25 communication device transmit the MS signal, the communicating device receiving the MR signal and transmitting the MS signal to the second communication mode of the communication apparatus, and thereafter the second communication mode of the communication apparatus is executed to transmit one of the ACK signal and the NACK signal to the communication device; and executing one of the first
30 communication mode and the second communication mode prior to a communication.

It is preferable that the method further comprises a third communication mode of the communication apparatus that is executed to transmit a CLR signal to the communication device that informs the communication device of a function list of the communication apparatus and requests a function list of the communication device, the communication device responding by transmitting a CL signal that includes the function list of the communication device to the communication apparatus, the execution of the third communication mode transmitting one of the ACK signal and the NACK signal to the communication device prior to executing one of the first communication mode and the second communication mode.

The present disclosure relates to subject matter contained in U.S. Provisional Application Numbers 60/080,310 filed on April 1, 1998; 60/089,850 filed on June 19, 1998; 60/093,669 filed on July 22, 1998; and 60/094,479, filed on July 29, 1998, the disclosures of which are expressly incorporated herein by reference in their entirety.

The present disclosure also refers to the following Recommendations, the subject matter of which is expressly incorporated herein by reference in their entirety:

Recommendation V.8bis (09/94) - "Procedures for Starting Sessions of Data Transmission over the General Switched Telephone Network", published by Telecommunication Standardization Sector of the ITU;

Recommendation V.8 (08/96) - "Procedures for the Identification and Selection of Common Modes of Operation Between Data Circuit-terminating Equipments (DCEs) and Between Data Terminal Equipments (DTEs) over the General Switched Telephone Network", published by Telecommunication Standardization Sector of the ITU;

Recommendation T.35 - "Procedures for the Allocation of CCITT Defined Codes for Non-standard Facilities", published by Telecommunication Standardization Sector of the ITU; and

Recommendation V.34 (10/96) - "a Modem Operating at Data Signaling Rates of up To 33,600 bit/s for Use on the General Switched Telephone Network and on Leased Point-to-point 2-wire Telephone-type Circuits", published by Telecommunication Standardization Sector of the ITU.

5

BRIEF DESCRIPTION OF THE DRAWINGS

The foregoing and other objects, features and advantages of the invention will be apparent from the following more particular description of preferred embodiments, as illustrated in the accompanying drawings, which are presented as a non-limiting example, in which reference characters refer to the same parts throughout the various views, and wherein:

Fig. 1 is a schematic block diagram of a general environment for usage of the present invention;

Fig. 2 is a schematic block diagram of the present invention under an exemplary situation in which Central Office equipment has been provisioned for xDSL service and Remote equipment does not employ a splitter;

Fig. 3 is a schematic block diagrams of a preferred embodiment of the present invention used in connection with two exemplary high speed (xDSL) modems adapted to transmit signals to each other over a communication channel;

Fig. 4 is a state transition diagram for a transaction message sequence of an xTU-R unit;

Fig. 5 is a state transition diagram for a transaction message sequence of an xTU-C unit;

Fig. 6 is a labeling and order format convention for octets in a message;

Fig. 7 is a field mapping convention for data that does not reside in a single octet;

Fig. 8 is a bit order for two octets of a Frame Check Sequence (FCS);

Fig. 9 is the structure of octets in a Frame;

Fig. 10 shows three types of fields of information;

Fig. 11 is a tree structure that links various parameters (NPars and SPars) in an Identification (I) field and a Standard Information (S) field;

Fig. 12 shows a transmission order of NPars and SPars in a message;

Fig. 13 shows the structure of octets in the Identification (I) field;

Fig. 14 shows the structure of Non-Standard information blocks in a Non-Standard information (NS) field; and

Fig. 15 shows the octet structure of data in each Non-Standard information block.

5

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

According to a first embodiment of the present invention, a data communication system comprises a central office system **2** and a remote system **4**, which are interfaced together via a communication channel **5**, as shown in Fig. 1.

10

The central office system **2** includes a main distribution frame (MDF) **1** that functions to interface the central office system **2** to the communication channel **5**. The main distribution frame (MDF) **1** operates to connect, for example, telephone lines (e.g., communication channel **5**) coming from the outside, on one side, and internal lines (e.g., internal central office lines) on the other side.

15

The remote system **4** includes a network interface device (NID) **3** that functions to interface the remote system **4** to the communication channel **5**. The network interface device (NID) **3** interfaces the customer's equipment to the communications network (e.g., communication channel **5**).

20

It is understood that the present invention may be applied to other communications devices without departing from the spirit and/or scope of the invention. Further, while the present invention is described with reference to a telephone communication system employing twisted pair wires, it is understood that the invention is applicable to other transmission environments, such as, but not limited to, cable communication systems (e.g., cable modems), optical communication systems, wireless systems, infrared communication systems, etc., without departing from the spirit and/or scope of the invention.

25

30

Fig. 3 illustrates a detailed block diagram of the first embodiment of the data communication system of Fig. 1. This embodiment represents a typical installation, in which both the central office system **2** and the remote system **4** implement the instant invention.

5

As shown in Fig. 3, the central office system **2** comprises a low pass filter **34** and a high pass filter **38**, a test negotiation block **46**, a high speed data receiving section **68**, a high speed data transmitting section **70**, and a computer **82**. Computer **82** is understood to be a generic interface to network equipment located at the central office. Test negotiation block **46** performs all of the negotiation and examination procedures which takes place prior to the initiation of an actual high speed data communication.

10

The low pass filter **34** and high pass filter **38** function to filter communication signals transferred over the communication channel **5**. The test negotiation block **46** tests and negotiates conditions, capacities, etc. of the central office system **2**, the remote system **4**, and the communication channel **5**. The procedures of the test negotiation block **46** are completed prior to, and initiate the selection of the high speed modem receiving and transmitting sections (e.g., modems) **68** and **70**. The high speed receiving section **68** functions to receive high speed data transmitted from the remote system **4**, while the high speed data transmitting section **70** transmits high speed data to the remote system **4**. The high speed sections **68** and **70** may comprise, but not be limited to, for example, ADSL, HDSL, SHDSL, VDSL, CDSL modems. High speed sections **68** and **70** can be a plurality of high speed transmission devices which "share" the common block **46** during the initial negotiation procedure. The negotiation data receiving section **52** and the high speed data receiving section **68** transmit signals to computer **82**. The negotiation data transmitting section **54** and the high speed data transmitting section **70** receive signals issued from the computer **82**.

20

25

30

In the disclosed embodiment, test negotiation block **46** comprises a negotiation data receiving section **52** and a negotiation data transmitting section **54**. The negotiation

data receiving section **52** receives negotiation data, while the negotiation data transmitting section **54** transmits negotiation data. The operation of the various sections of the central office system **2** will be described, in detail, below.

5 Remote system **4** comprises a low pass filter **36**, a high pass filter **40**, a test negotiation block **48**, a high speed data receiving section **72**, a high speed data transmitting section **66**, and a computer **84**. Computer **84** is understood to be a generic interface to network equipment located at the remote system. Test negotiation block **48** performs all of the negotiation and examination procedures
10 that take place prior to the actual high speed data communication.

The low pass filter **36** and high pass filter **40** operate to filter communication signals transferred over the communication channel **5**. The test negotiation block **48** tests and negotiates conditions, capacities, etc. of the central office system **2**, the remote
15 system **4**, and the communication channel **5**. The high speed receiving section **72** functions to receive high speed data transmitted from the central office system **2**, while the high speed data transmitting section **66** transmits high speed data to the central office system **2**. The negotiation data receiving section **56** and the high speed data receiving section **72** transmit signals to the computer **84**. The
20 negotiation data transmitting section **50** and the high speed data transmitting section **66** receive signals issued from the computer **84**.

In the disclosed embodiment, the test negotiation block **48** comprises a negotiation data receiving section **56** and a negotiation data transmitting section **50**. The
25 negotiation data receiving section **56** receives negotiation data, while the negotiation data transmitting section **50** transmits negotiation data. The operation of the various sections of the remote system **4** will be described, in detail, below.

The negotiation data transmitting section **50** of the remote system **4** transmits the
30 upstream negotiation data to the negotiation data receiving section **52** of the central system **2**. The negotiating data transmitting section **54** of the central system **2**

transmits the downstream negotiating data to the negotiation data receiving section **56** of the remote system **4**.

The central office system **2** includes a plurality of channels **6**, **10**, **14**, **16** and **18** that
5 are used to communicate with a plurality of channels **22**, **26**, **28**, **30** and **32** of the
remote system **4**. In this regard, it is noted that in the disclosed embodiment,
channel **6** comprises a central voice channel that is used to directly communicate
with a corresponding remote voice channel **32** in a conventional voice band (e.g., 0
Hz to approximately 4 kHz), which has been filtered by low pass filters **34** and **36**.
10 Further, a remote voice channel **33** is provided in the remote system **4** that is not
under the control of the central office system **2**. Remote voice channel **33** is
connected in parallel with the communication channel **5** (but prior to the low pass
filter **36**), and thus, provides the same service as the remote voice channel **32**.
However, since this channel is connected prior to the low pass filter **36**, the remote
15 voice channel **33** contains both the high speed data signal and a voice signal.

It is noted that the filters may be arranged to have different frequency
characteristics, so that a communication may take place using other, low band
communication methods, such as, for example, ISDN, between voice channels **6**
20 and **32**. The high pass filters **38** and **40** are selected to ensure a frequency
spectrum above 4 kHz.

Bit streams **10**, **14**, **16** and **18** (in the central office system **2**) and bit streams **22**,
26, **28** and **30** (in the remote system **4**) comprise digital bit streams that are used to
25 communicate between the central computer **82** and the remote computer **84**,
respectively. It is understood that it is within the scope of the present invention that
bit streams **10**, **14**, **16**, and **18** could be implemented as discrete signals (as
shown), or bundled into an interface, or cable, or multiplexed into a single stream,
without changing the scope and/or function of the instant invention. For example,
30 bit streams **10**, **14**, **16** and **18** may be configured as (but are not limited to) an
interface conforming to a RS-232, parallel, FireWire (IEEE-1394), Universal Serial
Bus (USB), wireless, or infrared (IrDA) standard. Likewise, it is understood that bit

streams **22**, **26**, **28** and **30** can be implemented as discrete signals (as shown in the drawings), or bundled into an interface, or cable, or multiplexed into a single stream, as described above.

- 5 Negotiation data (e.g., control information) corresponding to the condition of the communication line (e.g., frequency characteristics, noise characteristics, presence or absence of a splitter, etc.) is exchanged between the negotiation data receiving section **52** and negotiation data transmitting section **54** of the central office system **2**, and the negotiation data receiving section **56** and negotiation data transmitting
10 section **50** of the remote system **4**.

The essential features of the hardware portion of the invention is the functionality contained in the test negotiation blocks **46** and **48**, which test and negotiate the conditions, capabilities, etc. of the central office system **2**, the remote system **4**, and
15 the communication channel **5**. In practice, the configuration of the central office system **2** and the remote system **4** is subject to wide variations. For example, the configuration of the external voice channel **33** is not under the control of the same entities that control the central office system **2**. Likewise, the capabilities and configuration of the communication channel **5** are also subject to wide variation. In
20 the disclosed embodiment, test negotiation blocks **46** and **48** are embedded within modems **42** and **44**. However, the functionality of test negotiation blocks **46** and **48** may, alternatively, be implemented separate and distinct from the modems **42** and **44**. Signals transmitted and received between the test negotiation blocks **46** and **48** are used for testing the environment itself as well as communicating the results of
25 the tests between the central office system **2** and the remote system **4**.

The purpose of each signal path in Fig. 3 will be explained followed by an explanation of the devices used to create the signals. Examples of specific values for the various frequencies will be discussed in detail, below.

30

In the disclosed embodiment, frequency division multiplexing (FDM) is utilized for various communication paths to exchange information between the central office

system **2** and the remote system **4**. However, it is understood that other techniques (such as, but not limited to, for example, CDMA, TDMA, etc.) may be used without departing from the spirit and/or scope of the present invention.

- 5 The range from frequency 0 Hz until frequency 4 kHz is typically referred to as the PSTN voice band. Newer communication methods attempt to use the frequency spectrum above 4 kHz for data communication. Typically, the first frequency where transmission power is allowed occurs at approximately 25 kHz. However, any frequency above 4 kHz may be used. In this regard, it is noted that tone bursts at a
10 frequency of 34.5 kHz are used to initiate T1E1 T1.413 ADSL modems. As a result, if possible, that frequency should be avoided in the spectrum used by precursor negotiation methods.

- The communication paths are defined in pairs, one path for an upstream
15 communication from the remote system **4** to the central office system **2**, and another path for a downstream communication from the central office system **2** to the remote system **4**. The negotiation upstream bits are transmitted by the negotiation data transmitting section **50** of the remote system **4**, and received by the negotiation data receiving section **52** of the central office system **2**. The negotiation
20 downstream bits are transmitted by the negotiation data transmitting section **54** of the central office system **2**, and received by the negotiation data receiving section **56** of the remote system **4**. Once the negotiation and high speed training has been completed, the central office system **2** and the remote system **4** use high speed data transmitting sections **66** and **70**, and high speed data receiving sections **72**
25 and **68** to perform a duplex communication.

- All messages in the present invention are sent with one or more carriers using, for example, a Differential (Binary) Phase Shift Keying (DPSK) modulation. The transmit point is rotated 180 degrees from the previous point if the transmit bit is a
30 1, and the transmit point is rotated 0 degrees from the previous point if the transmit bit is a 0. Each message is preceded by a point at an arbitrary carrier phase. The

frequencies of the carriers, and the procedures for starting the modulation of carriers and messages, will be described below.

Once the remote system **4** begins receiving valid user downstream data, all of the various communication channels have been established and are ready for the negotiation procedures to be described below.

After the remote system **4** has received the spectrum information, it analyzes the equipment capabilities, the application desires, and the channel limitations to make a final decision on the communication method to use.

After the central office system **2** has received the final decision, the transmission of the negotiation downstream data is stopped. When the remote system **4** detects the loss of energy (carrier) from the central office system **2**, the remote system **4** stops transmitting the negotiation upstream data. After a short delay, the negotiated communication method begins its initialization procedures.

In the exemplary system of Fig. 2, the voice channel **6** is often connected to a PSTN switch **300**, and the functionality of the xTU-C **302** is embodied in modem **42**. Central office splitter **304** comprises a low pass filter **34** and high pass filter **38**. In the remote system **4**, multiple telephones **306** are connected to voice channel **32** or **33**, and the xTU-R **308** is implemented in modem **44**.

The present invention goes to great lengths, both before the handshake procedure is performed and during the handshake procedure, to be spectrally polite or as non-obtrusive as possible.

In this regard, the instant invention uses a unique method (criteria) for selecting the transmission and reception carriers (frequency bands), as embodied in a PSD. The spectrum and carrier allocation for the preferred embodiment of the present invention will now be described. The description begins with a review of the upstream and downstream PSD requirements of several different xDSL services

that are co-mingled with POTS or ISDN services. Implications of the xDSL PSDs on the present invention PSD are also discussed.

Downstream carriers are transmitted by the negotiation data transmitting section 54 of the central office system 2, and upstream carriers are transmitted by the negotiation data transmitting section 50 of the remote system 4.

The present invention is used to initiate or activate many types of existing and future xDSL services. The requirements of the various xDSL services have been taken into consideration in the design of present invention. This description addresses two inter-related considerations: spectrum and activation methods. In the present invention, suitable bands were selected for the transmission of the negotiation data channels. The bands were selected based upon several criteria, including considering the existing overall PSDs of the xDSL services and also the activation signals of existing xDSL services.

Examples of various spectra of typical xDSL and existing services that might be negotiated by the present invention are shown in Table 1. For purposes of definition, "upstream" and "downstream" directions using the nomenclature from the various xDSL services are indicated in Table 2. Table 3 lists the initiating activating sequences of several xDSL. Together these tables outline the typical environment in which the present invention must be capable of operating.

Table 1. survey of existing relevant spectra

Nomenclature (Document)	Total Bandwidth		Upstream Bandwidth		Down Stream Bandwidth	
	Lower (kHz)	Upper (kHz)	Lower (kHz)	Upper (kHz)	Lower (kHz)	Upper (kHz)
ITU-T G 992.1 Annex 1	28	1,104	25	138	26	1,104
ITU-T G 992.2 Annex 2 (FDM)	28	1,104	25	138	26	1,104
ITU-T G 992.1 Annex B	138	1,104				
ITU-T G 992.1 Annex C	28	50	28	50	26	50
ITU-T G 992.2 Annex C	28	50	26	50	26	50
T1E1 PSDSL or ITU-T G shdsl			0	400	0	900
VDSL (with European ISDN)	300	10,000	300	10,000	300	10,000
DSX(M-06803-1(draft) V0.6.7 (1998-2)						
Section 8.2 Frequency plan						

TABLE 2. DEFINITIONS OF UPSTREAM AND DOWNSTREAM

Modulation (Document)	Upstream	Downstream
G.992.1	xTU-R to xTU-C	xTU-C to xTU-R
T1.413 Cat 1 w/ Analog filters	ATU-R to ATU-C	ATU-C to ATU-R
G.992.2	xTU-R to xTU-C	xTU-C to xTU-R
DMT with only 64 tones	xTU-R to xTU-C	xTU-C to xTU-R
G.hs1	NTU to LTU	LTU to NTU
HDSL2	NTU to LTU	LTU to NTU
VDSL (with European ISDN)	NT to ONU/LTU	ONU (LT) to NT-R
DTS/TM-06003 (draft) v0.3.7 (1998-2)		
Notes		
xTU-R, NTU, NT indicate customer side		
xTU-C, LTU, ONU indicate network side		

Table 3. Activation signals of existing xDSLs

Modulation (ITU Document Ref No.)	Initiator	Responder	Comment
G.992.1	None - will use handshake procedure		
G.992.2	None - will use handshake procedure		
T1.413 Issue 1	R-ACT-REQ 34.5 kHz sinusoid with envelope of: 125 symbols on 64 symbol @ -2 dBm (-16ms) 64 symbol @ -22 dBm (-16ms) 895 symbols off (-221ms)	C-ACT1 297 kHz (#48) C-ACT2 197 kHz (#44) C-ACT3 224 kHz (#52) C-ACT4 259 kHz (#60)	
T1.413 Issue 2	(same as Issue 1)	(same as Issue 1)	
ETSI: ADSL over ISDN	same as T1.413 but k=42, 18, 125 kHz	C-ACT2m 319 kHz (#74) C-ACT2e 323 kHz (#76)	
RAUSL CAP	NTU-R transmits RS0+trailer (pseudo noise at symbol rate) Using 68 kHz and 85 kHz	Using 282 kHz and 306 kHz	
G.hs1 (DMT)	LTU transmits CS0	NTU transmits CS0	
G.hs1 (CAP - Annex B)	LTU transmits CS0 3150 symbols of pseudo noise at symbol rate	NTU transmits RS0, 3150 symbols of pseudo noise at symbol rate	
HDSL2	TBD		
VDSL			Not defined yet
DTS/TM-06003 (draft)			

With respect to the bands used by ADSL modems, the present invention uses the following detailed criteria to select appropriate carriers for the upstream negotiation channel and the downstream negotiation channel:

- 5 1. Consider all of the services/families known today (e.g., G.992.1/G.992.2 Annex a, Annex B, Annex C, HDSL2);
2. Upstream and downstream negotiations will not use the same frequencies (i.e.; the preferred embodiment does not use echo canceling);
3. FDM filter implementations (with a few non-essential additions) - e.g., avoid
10 upstream/downstream interleaving;
4. Avoid existing T1.413 activation tones (e.g., tone numbers 8, 44, 48, 52, 60);
5. G.992.1 Annex a and G.992.2 Annex a use the same upstream and downstream carriers. G.992.1 Annex C and G.992.2 Annex C use the same upstream and downstream carriers;
- 15 6. At least one carrier associated with G.992.1 Annex a is the same as the carrier used with G.992.1 Annex C. At least one carrier of G.992.2 Annex a is the same as the carrier used with G.992.2 Annex C. (For both upstream and downstream);
7. The ADSL Annex a downstream band is reduced to tones 37 through 68,
20 based on G.992.2;
8. Be reasonably robust against Intermodulation products;
9. a grid for decimation (mainly applicable for Annex a and Annex B). This allow a sample clock that is lower than the Nyquist rate to still extract the required information, because the folded over signals in the spectrum fall
25 directly on top of each other. Since the tones for Annex C have special requirements, they often cannot be aligned on the same grid as the Annex a and Annex B tones;
10. Higher frequency tones should be spaced farther apart to reduce leakage in the filters;
- 30 11. In general, there are 3 tones per Annex (however, Annex C has 2 primary tones each way, and a third borderline tone);

12. Tones between 14 and 64 should not be transmitted in a TCM-ISDN environment; and
13. Avoid (if possible) RADSL activation frequencies. Thus, in the upstream carrier, avoid 68 kHz (~#16) and 85 kHz (~#20). In the downstream carrier, avoid 282 kHz (~#65) and 306 kHz (~#71).

Based on the above discussion, a preferred Embodiment #1 uses the following carriers:

Family / Direction	Tone Index	Comment
4.3 k Upstream	9, 11, 12, 21, 33, 37, 41	(Annex a and B tones use the grid $4N+1$)
4.3 k Downstream	6, 7, (26), 50, 58, 66, 74, 90, 114	(Annex a and B tones use the grid $8N+2$)
4 k family	Reserve Tone area 2-5	

A preferred Embodiment #2 uses the following carriers:

Family / Direction	Tone Index	Comment
4.3 k Upstream	9, 11, 15, 23, 35, 39	(Annex a and B tones use the grid $4N+1$)
4.3 k Downstream	6, 7, (26), 50, 58, 66, 74, 90, 114	(Annex a and B tones use the grid $8N+2$)
4 k family	Reserve Tone area 2-5	

A preferred Embodiment #3 uses the following carriers:

Family / Direction	Tone Index	Comment
4.3 k Upstream	9, 12, 21, 27, 33, 36, 39	(All tones use the grid $3N$)
4.3 k Downstream	6, 7, (26), 50, 58, 66, 74, 90, 114	(Annex a and B tones use the grid $8N+2$)
4 k family	Reserve Tone area 2-5	

A preferred Embodiment #4 uses the following carriers:

Family / Direction	Tone Index	Comment
4.3 k Upstream	7, 9, 17, 25, 37, 45, 53	(Annex a and B tones use the grid $4N+1$)
4.3 k Downstream	13, 14, 40, 56, 64, 72, 88, 96	(Annex a and B tones use the grid $3N$)
4 k Upstream	3	
4 k Downstream	5	

TABLE 4. CARRIER PREFERRED EMBODIMENT #1

Up: Down		Upstream		Downstream	
Up-	8	16	53	7	
Avrds	23				
HDSL2	2-33				
Ann 2	9	13	21		
Ann 3			53	57	41
Ann C	9	13			
On			4	48	52 50
Avrds			Note 7		
HDSL2	(4-5)				
Ann a			2	30	58 66
Ann B			6		
Ann C	6 7		Note 6		
Index	23	43	6	7	8
	9	11	15	16	21
	26	31	33	37	41
	44	48	50	51	58
	60	65	65	66	68
	71	74	90	114	235
	23				
Up-	2	1	3	5	7
HDSL2	2-33				
Ann A	3		31		
Ann B			33		
Ann C	6	12	35		
On-	2	1	3	5	7
HDSL3	2-33				
Ann A			33		
Ann B			65		
Ann C	6	12	13		

- 5 Comments on the selected carriers:
1. The upstream and downstream carriers are completely separated;
 2. The upstream and downstream bands of the existing T1.413 activation tones are preserved;
 3. Annex B allows the optional use of tones below number 33, in which the
- 10 ATU-x may be able to use some but not all of the carriers originally designated for Annex a;

4. Annex B upstream band and Annex a downstream band essentially overlap, so the common band was divided between the two requirements;
5. The tones associated with Annex a and B are set along a common grid;
6. * Tone 26 may optionally be used for downstream transmission, so that a much lower frequency could be used in situations in which high frequency line attenuation exists. However, since it is in the midst of the upstream band, certain filter implementations may preclude it's usage;
7. Tone 74 falls in the null of TCM-ISDN spectrum, so there is some positive SNR there and it is in common with Annex B;
8. Tone 74 was selected as the frequency for Annex B's C-ACT2m; and
9. The band to allocate Annex B upstream tones is very narrow. Using 3 carriers places the two outer carriers very near the band edge. If 2 carriers are sufficient, they could have much better placement. In that case, the appropriate upstream grid is 4N-1 and all of the revised upstream carrier values are shown in Table 5.

TABLE 5. UPSTREAM CARRIER PREFERRED EMBODIMENT #2

	Down	Upstream	Downstream
UP Avoids	8	16 20	
HDSL			
Anx. A		11 13 23	
Anx. B			35 39
Anx. C		9 11	
Index	1	2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000	

TABLE 7. CARRIER PREFERRED EMBODIMENT #4

[illegible]

Although Tables 4 – 7 describe preferred embodiments, it is understood that other sets of frequencies can be used for other environments, while still conforming to the selection criteria described in this invention.

- 5 The frequencies of the carriers are derived by multiplying a base family frequency (e.g., 4.3125 kHz, or 4.000 kHz) by the carrier index. To achieve robustness, multiple carrier symbols are used for each data bit. The 4.0 kHz family, designated as family B, achieves a bit rate of 800 bits/s by dividing the 4000 symbols/sec rate by 5. The 4.3125 kHz family, designated as family a, achieves a bit rate of
 10 539.0625 bits/s by dividing the 4312.5 symbols/sec rate by 8.

In the above carrier selection embodiments for the ADSL bands, several xDSL requirements were simultaneously examined. It is also prudent to be aware of the spectrum used by VDSL modems. However, as of the time of this invention, VDSL
 15 transmission techniques have not been finalized. Thus, it is advisable to consider the following criteria and considerations when selecting carriers for use with VDSL devices (modems):

1. Some VDSL splitter designs begin the HPF roll-off at approximately 600 kHz. As a result, some carriers should be above 600 kHz (e.g., ADSL tone
 20 #140). Other splitter designs roll-off at approximately 300 kHz (e.g., ADSL tone #70). Thus, carriers above those frequencies would be needed;
2. Although there is discussion of an ADSL-compatible mode of VDSL which ensures no interference to ADSL lines, by significantly reducing power in the carriers below 1.1 MHz, a VDSL device can transmit carriers in compliance
 25 with the ADSL PSDs. Thus, care should be taken not to introduce performance degradation to existing services, and in particular, ADSL service;
3. In this regard, current VDSL proposals call for carriers to be spaced at 21.625 kHz and 43.125 kHz. However, it is likely that devices will initiate in
 30 the 43.125 kHz mode, so carriers with a grid of 43.125 kHz is preferred;
4. Carriers should be below 3 MHz (equivalent to ADSL tone #695), so that they can be detected on the longest of VDSL capable lines;

5. Carriers should avoid known HAM radio bands, such as, for example, 1.8-2.0 MHZ (which is equivalent ADSL tones #417 - #464) in North America, or 1.81 - 2.0 MHZ in Europe;
6. Carriers should be selected so as to avoid interference from AM radio stations;
7. VDSL may employ Time Division Duplex (TDD) techniques. Accordingly, upstream and downstream separations need not be so strict;
8. Signals above 1.1 MHZ in the VDSL band should be transmitted in synchronism with the ONU's chosen superframe structure, in order to avoid Near End Crosstalk (NEXT) into the other TDD VDSL lines in the binder; and
9. At least one set of carriers should be inside the VDSL spectrum plan.

Based on the above, preferred carriers for VDSL, according to the present invention, are as follows:

- 15 Downstream Grid = (ADSL downstream grid) x (VDSL grid) = $(8N+2) \times (10)$
 $\rightarrow 100, 180, 260, 340, \text{etc.}$
- Upstream Grid = (ADSL upstream grid) x (VDSL grid) = $(4N-1) \times (10)$
 $\rightarrow 350, 390, 470, 510, 550, \text{etc.}$

- 20 The implicit channel probing feature of the present invention can be used to assess the characteristics of the communication channel while concurrently transmitting information over the communication channel.

Channel probing is performed implicitly by observing all of the initializing carriers sent during the activation sequence, and to verify which carriers were sent, by reading the corresponding bits indicated in Tables 23 and 24. During the reception of unmodulated carriers, the xTU-C, using the negotiation data receiving section 52, and the xTU-R, using the negotiation data receiving section 56, monitor the communication channel (line) to perform a spectrum analysis of the signal to calculate spectrum information. The accuracy of the implicit channel probing need not be precise; it is only necessary to obtain a rough estimate of the SNR in the channel. An xTU-X alters (changes) it's modulation and parameters selections

based on the contents of a CL/CLR message exchange and the SNR from the implicit channel probe.

Another problem addressed by the current invention relates to the use of too many carriers, or the use of too much transmission power, during an initialization procedure. In some environments, it is necessary to reduce the number of carriers used to transmit negotiation information in order to be spectrally polite. In such cases, it is difficult to determine which tones the receiver is actually receiving.

According to a first example of the instant invention for reducing the number of carriers, referred to as a Pair Phase Reversal example, upstream and downstream tones are paired. When an xTU-x receives a tone from a particular pair, it transmits phase reversals on it's corresponding mate (pair) before beginning a modulated carrier.

However, this example exhibits the following limitations:

1. One tone of the pair mate might not be usable because of bridge taps or interference; thus, the other pair mate would be idle; and
2. The carriers cannot always be uniquely paired.

A second example of is referred to as a Modulate Carrier Before Messages example. After sending an unmodulated carrier and before sending a modulated carrier, messages begin with flags, the xTU-X modulates all of it's carriers to indicate which carriers it is receiving. Codes can be created by transmitting concatenated 50% duty cycle patterns of 1's and 0's, with different lengths indicating different carriers. The fixed duty cycle allows reception without octet synchronization.

However, this example exhibits the following limitations:

1. The scheme is not bit or time efficient;
2. It would be preferable to octet-synchronize first and then send the information in a digital message;

3. This scheme increases the time required for the activation sequence; and
4. This coding scheme does not include error correction.

A third example is referred to as a Carriers Used and Request Transmit scheme.

- 5 Based upon the limitations of this scheme (discussed below), example three is the preferred scheme. Carriers to be used in a subsequent session are negotiated via octets in message transactions.

- During an initial state, every applicable carrier transmits CL/CLR messages. a list
10 of transmitted carriers is indicated in Table 23 and Table 24. Parameters in the CL/CLR messages used to determine (negotiate) which carriers to use for subsequent messages are shown in Table 34 and Table 35. The number of transmitted carriers may be reduced in the same transaction, such as, but not limited to, MR, MS, ACK, NAK messages in the same transaction. The number of
15 transmitted carriers may also be reduced in subsequent sessions and transactions that initialize with MS or MR messages. As with MS for MS message contents and states, the xTU-X uses some memory to save the usable carrier information.

- If a channel impediment, such, as but not limited to, an interferer or a bridge tap
20 arises later, an initialization timeout from the initiating xTU-X allows all of the possible tones to be used from the initiating xTU-X.

- In their initial states, the xTU-R and xTU-C are encouraged to transmit as many carriers as possible, in order to determine whether any common carriers exist. a
25 pair of xTU-R and xTU-C negotiate using predetermined procedures, defined above, to specify the transmission of a reduced number of carriers for subsequent messages and subsequent initializations.

- If an xTU-X has been instructed to reduce the number of carriers in the midst of
30 completing a transaction, the xTU-X only reduces the carriers when it is in the process of transmitting flags. After the transmission of a complete flag, the xTU-X

transmits an unmodulated carrier on the redundant carriers for a period of two octet times before stopping transmission on the redundant carriers.

If an xTU-R and xTU-C have negotiated to use a reduced set of initialization carriers by the procedures defined above, the reduced set of carriers shall be used for a subsequent initialization. If an anticipated response is not received within time T_1 , prior instructions from the other xTU-X to reduce the number of carriers are ignored and the initialization scheme re-commences.

10 Either the central office (xTU-C) system **2** or the remote (xTU-R) system **4** may initiate modulation channels. The negotiation data transmitting section **50** of the remote system **4** transmits the upstream negotiation data to the negotiation data receiving section **52** of the central system **2**. The negotiating data transmitting section **54** of the central system **2** transmits the downstream negotiating data to the negotiation data receiving section **56** of the remote system **4**. After the negotiation modulation channels have been established, the remote station is always considered the initiating modem in terms of the transaction messages. Likewise, the central office terminal is thereafter referred to as the responding station.

20 A discussion of the initiation by the xTU-R will now be described, followed by a discussion of the initiation by the xTU-C.

The initiating xTU-R transmits unmodulated carriers selected from either one or both families of the Upstream group, via negotiation data transmitting section **50**.
 25 When the negotiation data receiving section **52** receives the carriers from the xTU-R for a predetermined period of time (at least 200 ms in the preferred embodiment), the responding xTU-C transmits unmodulated carriers, via negotiating data transmitting section **54**, selected from only one family of the Downstream group. After receiving the carriers using negotiation data receiving section **56** from the xTU-C for the predetermined period of time (e.g., at least 200 ms), the xTU-R DPSK modulates, using negotiation data transmitting section **50**,
 30 only one of the family of carriers and transmits a predetermined flag (e.g., $7E_{16}$) as

data. If the xTU-R initiated with carriers selected from both families, the xTU-R stops transmitting carriers from the other family before it begins modulating carriers from the selected family. After receiving the flag, via negotiation data receiving section 52 from the xTU-R, the xTU-C DPSK modulates only one of the family of carriers (using negotiating data transmitting section 54) and transmits flag (e.g., 7E₁₆) as data.

To facilitate the finding of a common set of carriers (if they exist), if an xTU-C receives carriers of a family that it cannot transmit, it nevertheless responds by transmitting carriers from a family it is capable of transmitting. This allows the xTU-R to detect the presence of the xTU-C, and, if it has the capability to do so, attempt an initiating procedure with a different carrier family.

In the disclosed embodiment, the xTU-C and the xTU-R monitor the line for existing services prior to transmitting carriers, to avoid interfering with existing services, using the negotiation data receiving sections 52 and 56, respectively.

The xTU-C transmits identical data, with identical timing on any and all downstream carriers. The xTU-R transmits identical data with identical timing on any and all upstream carriers.

The initiating xTU-C transmits unmodulated carriers selected from either one or both families of the Downstream group using the negotiation data transmitting section 54. After receiving the carriers, using negotiation data receiving section 56, from the xTU-C for (in the preferred embodiment) at least 200 ms, the responding xTU-R transmits unmodulated carriers using the negotiation data transmitting section 50, selected from only one family of the Upstream group. After the carriers are received for at least 200 ms by the negotiation data receiving section 52 of the xTU-R, the xTU-C begins DPSK modulating only one of the family of carriers using the negotiating data transmitting section 54, and transmits ones (FF₁₆) as data. If the xTU-C is initiated with carriers selected from both families, the xTU-C stops transmitting carriers from the other family before it begins modulating carriers from

the selected family. After receiving ones from the xTU-C, the xTU-R DPSK modulates only one of the family of carriers and transmits flags ($7E_{16}$) as data. After the flags are received from the xTU-R, the xTU-C DPSK modulates only one of the family of carriers and transmits flags ($7E_{16}$) as data.

5

In order to facilitate the finding a common set of carriers (if they exist), if the xTU-R receives carriers of a family that it cannot transmit, it nevertheless responds by transmitting carriers from a family it is capable of transmitting. This allows the xTU-C to detect the presence of the xTU-R and attempt an initiation with a different carrier family, if it has the capability to do so.

10

According to the instant invention, the xTU-C and the xTU-R monitor the communication line (using the negotiation data receiving sections 52 and 56, respectively), for existing services prior to transmitting carriers, in order to avoid interfering with existing services.

15

The xTU-C transmits identical data with identical timing on any and all downstream carriers. The xTU-R transmits identical data with identical timing on any and all upstream carriers.

20

In the present invention, an error recovery mechanism comprises (but is not limited to) the transmission of an unmodulated carrier of ones (FF_{16}), or flags ($7E_{16}$) that shall not exceed, for example, a time period of 1 second. An xTU-x may restart the initiation procedure or may optionally start alternative initiation procedures.

25

If only one communication device in the communication link implements the present invention's preferred activation method, a high speed communication may not be possible. The following describes mechanisms to fallback (or escape) to legacy communication systems, such as, but no limited to, legacy DSL systems or voiceband communication systems. Fallback to xDSL systems will be described first, followed by a description of the voiceband fallback procedures:

30

1. Fallback Methods To Legacy xDSL Modulations

Some legacy xDSL systems (examples of which are shown in Table 3) do not implement the present invention. The present invention includes procedures to
5 fallback to a legacy xDSL activation method. The present invention is intended to be a robust mechanism for activating a multiplicity of xDSL modulations in the presence of unknown equipment with unknown transceiver PSDs. The activation of regional standards (i.e., legacy devices) can be handled by two different methods: an implicit method (e.g., activation via escape), or an explicit method (e.g.,
10 activation via nonstandard facilities or standard information). Both methods are used to cover the multitude of initialization methods.

The activation via escape method facilitates the startup of devices prior to the present invention beginning the negotiation modulation. This allows the startup of
15 devices which, for example, implement Annex a, B, or C of a predetermined communication standard (with differing PSDs) and a legacy xDSL system, such as, but not limited to T1.413. The present invention monitors several different frequency bands using xTU-C's data receiving section 52 or xTU-R's data receiving section 56. Thus, a device that also supports a regional standard (such as, for
20 example, T1.413) can concurrently (or nearly concurrently) monitor for the regional standard activation signals while monitoring for the activation signals of the present invention. a procedure for interworking with the ANSI T1.413 protocol is shown in Table 8.

TABLE 8. ESCAPE ACTIVATION WITH T1.413 DEVICES

Device	Capabilities	Algorithm
ATU-C	T1.413	Waits for R-ACT-REQ. Ignores present invention activation signals. Initiates T1.413 when receives R-ACT-REQ.
ATU-C	T1.413 & present invention	Waits for R-ACT-REQ or present invention initiating tone(s). Initiates as appropriate.
ATU-R	T1.413	Transmits R-ACT-REQ and waits for C-TONE or C-ACT. Ignores any present invention activation signals from the ATU-C.
ATU-R	T1.413 & present invention	Transmits present invention activation signals. If no response to present invention activation signals, transmits R-ACT-REQ.

The activation via non-standard facilities or standard information embodiment allows the interworking of devices after the initialization of the handshake modulation, by indicating the legacy communication system in a message. The message may use either a non-standard information (NS) field or a Standard Information (S) field.

The present invention allows the transmission and reception of a non-standard message that indicates a different modulation. Regional standards can be explicitly negotiated through non-standard facilities.

The present invention also provides for the transmission and reception of a standard information message that indicate a different modulation. Regional standards can be explicitly negotiated through a code point in the standard information field.

It is understood that other DSL communication systems, such as, but not limited to, for example, RADSL, can be negotiated using the same explicit and implicit methods discussed above for T1.413, without departing from the spirit and/or scope of this invention.

2. Fallback Methods To Voiceband Modulations

Fallback methods for voiceband modulations are similar to the fallback methods described above for xDSL modulations, that is, both explicit and implicit methods exist.

5

The initial signals for a voiceband modulation are specified in ITU-T Recommendation V.8 and ITU-T Recommendation V.8bis. In the explicit method, after the V.8 or V.8bis code points are selected in an MS message, acknowledged with an ACK(1) message, and the present invention has executed (been
10 completed), the V.8 or V.8bis procedures begins. The xTU-R takes on the roll of a V.8 calling station and the xTU-C takes on the roll of a V.8 answering station.

In the implicit method , if an xTU-X initiates a handshake session by transmitting negotiating tones but does not receive a response from a possible xTU-X at the
15 other end of the communication channel 5, the initiating xTU-X may assume that the other xTU-X does not support a high speed communication, and may then switch to initiating a communication using voiceband procedures such as V.8 and V.8bis.

20 The instant invention also addresses the prior art problem of having long or complicated initialization transactions when either communication device in the communication link needs to transmit data.

In general, the xTU-C is usually always ON, or will have been turned ON before the
25 xTU-R is turned ON. The xTU-R can always remain ON, but it is more likely that there will be periods in which the xTU-R is turned OFF or placed into a "sleep" mode (a mode in which the xTU-R is placed in a standby mode to minimize electrical power consumption). If the xTU-R is in the sleep mode, the central side needs to "wake up" the xTU-R before a data transmission can occur. Four basic
30 transactions for accomplishing this are described in Table 9.

Table 9. Four Basic Transaction Needs

Name	Description	Characteristics
Remote First Time	• very first time initialization of a dedicated circuit • typical initialization by a mobile unit	• ATU-R initiates modulation • full capabilities exchange
Remote Reestablish	• reestablishes a previously negotiated operating mode	• ATU-R initiates modulation • reconfirmation of previous mode through a mutual exchange
Central Push (First Time)	• The network side wishes the ATU-R to activate in order for the network to deliver a "push" service.	• ATU-C initiates modulation • full capabilities exchange
Central Push Reestablish	• Push application desired to reestablish	• ATU-C initiates modulation • typically occurs after a previous full capabilities exchange • minimal exchange

Since the xTU-R will always send the first message of a transaction, and the first message should be as meaningful as possible when the xTU-R initializes the modulation, the present invention uses a preferred initialization protocol scheme shown in Table 10. Alternatively, an initialization protocol scheme illustrated in Table 11 may be used. However, it is understood that variations to these transactions may be made without departing from the spirit and/or scope of the instant invention.

Table 10. Transactions Preferred Scheme #1

Transaction sequence						
#	Name	XTU-R →	XTU-C →	XTU-R →	XTU-C →	XTU-R →
1.	First Time	CLR	CL	MS	ACK/NAK	
2.	Reestablish	MS	ACK/NAK			
3.	Central Push First Time	RC	CLR	CL	MS	ACK/NAK
4.	Central Push Reestablish	RC	MS	ACK/NAK		

Where

CL	Transmit a Capabilities List This message conveys a list of possible modes of operation of the transmitting station
CLR	Transmit a Capabilities List and Request the other unit to also transmit a capabilities list This message conveys a list of possible modes of operation of the transmitting station and also requests the transmission of a capabilities list by the remote station
MS	Mode Select - specify the intended mode This message requests the initiation of a particular mode of operation in the remote station

ACK	Acknowledge the selected mode ACK(1): This message acknowledges receipt of an MS message and terminates a transaction. It may also be used to acknowledge receipt of part of a CL-MS message combination and request transmission of the remainder of the message combination. ACK(2): This message acknowledges receipt of a CL, CLR or MS message and requests the transmission of additional information by the remote station, providing the remote station has indicated that additional information is available.
NAK	Not Acknowledge the selected mode This message indicates that the receiving station is unable to interpret a received message or to invoke the mode requested by the transmitting station. Four NAK messages are defined: - NAK(1) (a.k.a. NAK-EF) indicates that the receiving station is unable to interpret the received message because it is an Errored Frame; - NAK(2) (a.k.a. NAK-NR) indicates that the receiving station is temporarily unable to invoke the mode requested by the transmitting station; - NAK(3) (a.k.a. NAK-NS) indicates that the receiving station either does not support or has disabled the mode requested by the transmitting station; and - NAK(4) (a.k.a. NAK-NL) indicates that the receiving station is unable to interpret a received message.
RC	(a.k.a. REQ) Revert control of the transaction to the xTU-C The message tells the xTU-C to take control.
MR	This message requests the transmission of a mode select message by the remote station.

Although there are names and scenarios associated with the transaction, the names should merely be considered as informational in nature.

5

All messages in a transaction are required.

The RC message contains only one bit of information. Setting the bit to "1" represents that the xTU-C was "surprised" by the push request, or is in a state of confusion. In this situation, it is recommended (but not mandated) that the xTU-C use transaction X instead of W.

10

MS always includes the desired mode.

15 If a xTU-R NAKs in a transaction X but wishes to keep trying, it shall send NAK() and then transaction Z.

On the other hand, if an xTU-C NAKs, the xTU-R should send RC to start transaction X or W.

The following is noted in the situations where the xTU-C has initiated the modulation:

1. If the xTU-R is prepared for the xTU-C to dominate, transaction X or W should be utilized. This should be the typical case when the ATU-C initiates the modulation;
2. However, if the xTU-R is to have equal control, it should use transaction Z;
- 10 3. Although transaction Y could be used, it is overly presumptuous on the part of the xTU-R; and
4. The initiation of modulation by the xTU-C can also be used in conjunction with a power management system

Table 11. Transactions Preferred Scheme #2

Transaction number	xTU-R	ATU-C	xTU-R
A (same as Y)	MS-	ACK/NAK	
B (same as X)	MR-	MS-	ACK/NAK
C (modification of Z and W)	CLR-	CL-	ACK/NAK

15

All permitted transactions will now be described.

Transactions involving the use of messages CL and CLR permit a transfer or exchange of capabilities between the two stations. Transactions involving the use of message MS allow a specific mode to be requested by either station and permit the other station to accept or decline the transition to the requested mode. Transaction a or B are used to select an operating mode without first establishing their common capabilities. Transaction C is used to exchange information about each station's capabilities. Transaction B is intended to allow the responding station to take control of the outcome of the transaction.

25

Figs. 4 and 5 illustrate state transition diagrams for a second transaction embodiment. The state transition diagrams show state information (e.g., the state name and current transmitted message) and transition information (e.g., the received message that caused the state change). In Figs. 4 and 5, message names followed by an asterisk (*) indicate that the state transition may be taken upon the reception of a complete message, or upon the reception of one or more segments of the message.

When a message is received with the "additional information available" parameter set to binary ONE in the identification field, the receiving station may send an ACK(2) message to request that further information be sent. When the ACK(2) message is received, further information is sent. The transmission of signals associated with a selected mode begins immediately after the transmission of ACK(1).

When a station receives an MS message requesting a mode that it is unable to invoke, the station responds by sending a NAK. If an invalid frame is received in any state, the receiving station sends a NAK(1) and immediately returns to an Initial State. If an xTU-X has transmitted a message, but is not receiving flags or valid message data from the other xTU-X, the error recovery procedures (described above) apply. If an xTU-X has transmitted a message and is receiving flags, it waits for a predetermined period of time, for example, 1 second, before re-transmitting the same message. If the xTU-X has transmitted the same message a certain number of times (e.g., 3 times) without receiving a valid message response from the other xTU-x, the transmitting xTU-X transmits a Hangup message and stops transmitting the carrier. If desired, the xTU-x may restart the initiation attempt or start alternative initiation procedures.

The maximum number of octets in any Information Field is 64. If the information exceeds this limit, the remainder of the information may be contained in subsequent messages. To indicate that further information exists, an "Additional Information Available" parameter is set to binary ONE in the identification field of the transmitted

message. This information, however, shall only be sent if, on receiving the message, the remote station sends an ACK(2) message requesting further information.

- 5 Where non-standard information is present in the information field, the standard and non-standard information may be conveyed in separate messages. If the information to be conveyed in the CL message cannot be conveyed in a single message, and the "Additional Information Available" parameter is set to binary ONE, a response is required from the receiving station in order for the transmitting station to complete transmission of the combined CL-MS messages, irrespective of
10 whether the additional information is to be sent. In this case, an ACK(1) shall be sent if no further information is required.

The current invention also addresses the desirability of transmitting information in
15 additional to the equipment capabilities (e.g, channel information, service parameters, regulatory information, etc.) during the negotiation procedure. In this regard, the present invention contains several different and additional types of information, as compared to V.8bis and V.8. The types of information emphasize service requirements instead of "application groups". It is noted that the types of
20 information are merely examples of the types and methodology of parameter exchange, and thus, modifications (variations) may be made without departing from the spirit and/or scope of the invention.

The preferred embodiment of the present invention has the general organizational
25 structure shown in Table 12. Modulation independent information is presented in an "Identification" field, and modulation dependent information is presented in a "Standard Information" field. In general, service parameters and channel capabilities information are independent of the various xDSL modulations. The overall composition of messages according to a first example is shown in Table 13,
30 while Table 14 illustrates a second example.

Table 12. Information Organization Structure

• Identification (Service Parameters/ Channel Capabilities) NPar(1) (No sub-parameters) • Identification (Service Parameters/ Channel Capabilities) SPar(1) (sub-parameters) • Message Type and version • Vendor Identification using T.35 codes • Announce type of bandwidth • number of data channels desired • known splitter information • spectrum usable frequencies - generalization of FDM and overlapped spectrum • carrier families, groups, and tone numbers being transmitted
• Standard Information (Modulations/protocols) NPar(1) • Standard Information (Modulations/protocols) SPar(1) • Which type of xDSL etc. • Reg. anal. considerations (i.e., use of a specific Annex in a Recommendation) • Protocol information: error correction, data compression etc.
• Non-standard Information

5

Table 13. Overall Message Composition (Embodiment #1)

Messages	Identification			Standard Information	Non Standard Information
	Message Type & Version (1 octet)	Country Code Provider Length Provider Code (1+1+L octets)	Service & Channel parameters (7 octets)	Modulations & Protocols available (2 octets)	(3+3+L octets)
RC	Y	Y	-	-	-
CLN	Y	Y	Y	Y	as necessary
CI	Y	Y	Y	Y	as necessary
MS	Y	Y	Y	Y	as necessary
ACK	Y	Y	-	-	-
NACK	Y	Y	Y	Y	-

Notes: * NACK includes the reason for the NACK by setting the bits of the offending parameters

Table 14. Overall Message Composition (Embodiment #2)

Messages	Identification			Standard Information	Non Standard Information
	Message Type & Revision (2 octets)	Vendor ID (8 octets)	Service & Channel parameters	Modulations & Protocols available	$1 + \sum_{i=1}^N (T_i + M_i)$ octets
MR	X	-	-	-	-
CLR	X	X	X	X	as necessary
CL	X	X	X	X	as necessary
MS	X	-	X	X	as necessary
ACK	X	-	-	-	-
NAK	X	-	-	-	-
REQ	X	-	-	-	-

- 5 The following describes the organizational details within each category.

Parameters specific to a given xDSL modulation should always appear under the appropriate modulations category. Of those modulation parameters, some of them might be more general than others, and can have higher positions in the
10 NPars/SPars tree.

Parameters that are negotiated in T1.413 are also negotiated in the present invention (with the exception of Vendor ID, which uses T.35 codes). However, there are a few cases when related parameters need to be negotiated by the
15 present invention:

- If the optionality of the parameters in G.992.1 differ from T1.413;
- If the parameter actually needs to be negotiated instead of just indicated;
or
- If a general preference about a class of parameters needs to be
20 indicated.

If the parameter is very general, it should be negotiated in the Service Parameters octets on the Identification field. If the parameter is fairly closely related to the modulation, it should be negotiated in the 2nd level of the modulation's standard information octets. Even if these modulation parameters are fairly similar among various modulations, they are coded separately for each modulation. Also, other xDSL modulations, such as, for example, VDSL, have some very different parameters, making it very difficult to have one large list of parameters trying to satisfy all of the xDSL requirements and capabilities. As a result, there is some redundancy in the modulation parameters, in much the same way that redundancy exists with V.8bis. Further, many of the parameters under the various applications are identical.

Three types of parameters/options exist; manufacturing, provisioning and negotiated options.

15

1. Manufacturing Options

Manufacturing options are defined as optional portions of a specification that a manufacturer includes/chooses in the product design. An example of a manufacturing option is to employ EC vs. FDM. Manufacturing options must be disclosed and acknowledged in the startup, since a communication would be impossible without commonality between the various devices.

20

2. Provisioning Options

25

Provisioning options are defined as optional capabilities that are in some way fixed a priori. An example of a provisioning option is the Loop timing at the CO that is required to be mastered by either the CO or the CP. The CO capability is normally fixed by a priori decision prior to the negotiation. It is noted that this option can be merged into either the manufacturing or negotiated options. As a result, only a few options are in this category.

30

3. Negotiated Options

Negotiated options are defined as an option in which an item must be selected from a list of (mandatory available) options. An example of a negotiated option is the data transmission rate. In negotiated options, the transmission rate is made peer to peer.

The information coding format for the present invention will now be described with respect to Tables 15-45. The discussion provided with respect to Tables 15-18 are provided as background information. Tables 20-45 are directed to the features of the instant invention.

The basic format convention used for messages is illustrated in Fig. 6. Bits are grouped into octets. The bits of each octet are shown horizontally and are numbered from 1 to 8. Octets are displayed vertically, and are numbered from 1 to N. The octets are transmitted in ascending numerical order. Within an octet, bit 1 is the first bit to be transmitted.

For fields which are contained within a single octet, the lowest numbered bit of the field represents the least significant bit (2^0). When a field spans multiple octets, the lowest numbered bit of the field in the highest numbered octet containing the field represents the least significant bit (2^0). The order of the bit values within each octet increases as the bit number increases. The order of the bit values from octet to octet increases as the octet number decreases. Fig. 7 illustrates a field which spans two octets.

An exception to this convention is the Frame Check Sequence (FCS) field, which spans two octets. In this case, the order of the bit values within the octets is reversed. That is, bit 1 of the first octet is the MSB and bit 8 of the second octet is the LSB (see Fig. 8).

Messages of the instant invention use the frame structure shown in Fig. 9. Messages start and end with a standard HDLC flag octet (01111110₂), as defined in ISO/IEC 3309. The Frame Check Sequence (FCS) field is defined in ISO/IEC 3309. Transparency using the Octet stuffing method is defined in ISO/IEC 3309.

5

The message information field consists of three components; an identification field (I), followed by a standard information field (S); and an optional non-standard information field (NS). The general structure of the message information field is shown in Fig. 10.

10

In both the identification (I) and the standard information (S) fields, most of the information to be conveyed consists of parameters relating to particular modes, features or capabilities associated with the two stations. In order to encode these parameters in accordance with a consistent set of rules; and allow future extension of the parameter list in a way that permits present and future implementations of the present invention to correctly parse the information field, the parameters are linked together in an extensible tree structure. The order in which the parameters in the tree are transmitted and the use of delimiting bits which enable the tree to be reconstructed at the receiver will be described in the rules set out below.

20

Parameters (Pars) are classified as (1) NPars – meaning, parameters which have no subparameters associated with them, and (2) SPars – meaning parameters which have subparameters associated with them. The general structure of this tree is as shown in Fig. 11. At level 1, which is the highest level of the tree, each SPar has a series of Pars (NPars and possibly SPars) at level 2 in the tree associated with it. Similarly, at level 2 in the tree, each SPar has associated with it a series of NPars at level 3 in the tree.

Parameters are binary encoded, and transmitted serially. Parameters of the same type (i.e., level, classification and association) are transmitted sequentially, as a block of data consisting of an integral number of octets. The transmission order of NPars and SPars is specified in Fig. 12. {Par(2)_n} indicates a set of level 2

30

parameters associated with the n 'th level 1 SPar, and consists of $NPar(2)_n$ parameters and possibly $SPar(2)_n$ parameters. $\{NPar(3)_{n,m}\}$ indicates a set of level 3 NPar's associated with the m 'th level 2 SPar, which in turn is associated with the n 'th level 1 SPar. The transmission of parameters begins with the first octet of NPar(1) and ends with the last octet of Par(2)_N.

The use of delimiting bits is illustrated in Fig. 12. At least one bit is defined as a delimiting bit within each octet of an information block. This is used to define the last octet in the block. A binary ZERO in this bit position indicates that there is at least one additional octet in the block. A binary ONE in this bit position indicates the last octet in the block.

Bit 8 is used to delimit the $\{NPar(1)\}$ block, the $\{SPar(1)\}$ block, and each of the Par(2) blocks. There are "N" Par(2) blocks, one for each of the capabilities in the $\{SPar(1)\}$ block that is enabled (e.g., set to binary ONE).

Bit 7 is used to delimit each $\{NPar(2)\}$ block, each $\{SPar(2)\}$ block, and each of the associated $\{NPar(3)\}$ blocks. Fig. 12 indicates that there are "M" $NPar(3)$ blocks, one for each of the capabilities in the $\{SPar(2)_n\}$ block that is enabled (e.g., set to binary ONE). "M" may be different for each of the Par(2) blocks.

A Par(2) block may either contain both $NPar(2)$ and $SPar(2)$ octets, or $NPar(2)$ octets alone. To indicate that a Par(2) block contains only $NPar(2)$ octets, bits 7 and 8 are both set to binary ONE in the last $NPar(2)$ octet. Bits 1 through 7 at level 1 of the tree and bits 1 through 6 at level 2 of the tree may be used to encode parameters. To allow for compatibility with future revisions (developments), receivers shall parse all information blocks and ignore information that is not understood.

In a first embodiment, the identification field consists of three components; a four-bit message type field (see Table 15), followed by a four-bit revision number field (see Table 17), followed by a bit-encoded parameter field.

In a second embodiment, the identification field consists of three components; an eight-bit message type field (see Table 16), followed by an eight-bit revision number field (Table 18), followed by a bit-encoded parameter field. This general structure is shown in Fig. 13.

The message type field identifies the message type of the frame. The revision number field identifies the revision number of the current invention to which the equipment conforms. The identification field encompasses information including, but not limited to: (1) non-modulation specific information, (2) channel capability information, (3) data rate information, (4) data flow characteristics, and (5) splitter Information. The Identification field comprises several octets of NPar(1)s, SPar(1)s, and NPar(2). NPar(1) and SPar(1) octets are always transmitted. NPar(2) octets are transmitted only if the corresponding bit in the SPar(1) is a "1". Octets are transmitted in the order shown in Table 19.

Vendor identification, including, for example, the country code, provider length, and provider code fields, follows the format of ITU-T Recommendation T.35 and is the same as used in the Non-standard field shown in Fig. 15.

Table 15. Message type field format Embodiment #1

Message type	Bit numbers			
	0	1	2	3
MS	0	0	0	1
CL	0	0	1	0
CLR	0	0	1	1
ACK(1)	0	1	0	0
ACK(2)	0	1	0	1
Reserved for ITU-T	0	1	1	0
Reserved for ITU-T	0	1	1	1
NACK(1)	1	0	0	0
NACK(2)	1	0	0	1
NACK(3)	1	0	1	0
NACK(4)	1	0	1	1
RC	1	1	0	0
Language	1	1	0	1
Reserved for ITU-T	1	1	1	0
Reserved for ITU-T	1	1	1	1

Table 16. Message type field format Embodiment #2

Message type	Bit numbers							
	8	7	6	5	4	3	2	1
MS	0	0	0	0	0	0	0	0
MR	0	0	0	0	0	0	0	1
CL	0	0	0	0	0	0	1	0
CLR	0	0	0	0	0	0	1	1
ACK(1)	0	0	0	1	0	0	0	0
ACK(2)	0	0	0	1	0	0	0	1
NAK-EE	0	0	1	0	0	0	0	0
NAK-NR	0	0	1	0	0	0	0	1
NAK-NS	0	0	1	0	0	0	1	0
NAK-NU	0	0	1	0	0	0	1	1
REQ-MS	0	0	1	1	0	1	0	0
REQ-MR	0	0	1	1	0	1	0	1
REQ-CLR	0	0	1	1	0	1	1	1

Table 17. Revision Number field format Embodiment #1

Revision number	Bit numbers			
	3	2	1	0
Revision 1	0	0	0	0

5

Table 18. Revision Number field format Embodiment #2

Revision number	Bit numbers							
	8	7	6	5	4	3	2	1
Revision 1	0	0	0	0	0	0	0	1

Table 19. Identification Field - Order of Octets

Name	N/S Type	Table #
Message type field format	-	Table 15 / Table 16
Version Type field	-	Table 17 / Table 18
Country code	-	
Provider Length	-	
Provider code (L octets)	-	
Identification field - {NPar(1)} coding	NPar(1)	Table 20
Identification field (Capabilities Information)- {SPar(1)} coding - Octet 1	SPar(1)	Table 21
Identification field (Service Requests)- {SPar(1)} coding - Octet 2	SPar(1)	Table 22
Identification Field - (CI) Currently transmitted carriers {NPar(2)} coding - Octet 1	NPar(2)	Table 23
Identification Field - (CI) Currently transmitted carriers {NPar(2)} coding - Octet 2	NPar(2)	Table 24
Identification Field - (CI) Spectrum first usable frequency {NPar(2)} coding	NPar(2)	Table 25
Identification Field - (CI) Spectrum maximum frequency - upstream {NPar(2)} coding	NPar(2)	Table 26
Identification Field - (CI) Spectrum maximum frequency - downstream {NPar(2)} coding	NPar(2)	Table 27
Identification Field - (CI) Spiller Information {NPar(2)} coding - Octet 1	NPar(2)	Table 28
Identification Field - (CI) Spiller Information {NPar(2)} coding - Octet 2	NPar(2)	Table 29
Identification field - (SR) Data rate Amount (Average) {NPar(2)} coding - Octet 1	DS	NPar(2) Table 30
Identification field - (SR) Data rate Amount (Maximum) {NPar(2)} coding - Octet 2	DS	NPar(2) Table 31
Identification field - (SR) Data rate Amount (Minimum) {NPar(2)} coding - Octet 3	DS	NPar(2) Table 32
Identification field - (SR) Data rate Amount (Average) {NPar(2)} coding - Octet 1	US	NPar(2) Table 30
Identification field - (SR) Data rate Amount (Maximum) {NPar(2)} coding - Octet 2	US	NPar(2) Table 31
Identification Field - (SR) Data rate Amount (Minimum) {NPar(2)} coding - Octet 3	US	NPar(2) Table 32
Identification field - (SR) Data rate type {NPar(2)} coding	DS	NPar(2) Table 33
Identification field - (SR) Data rate type {NPar(2)} coding	US	NPar(2) Table 33
Identification field - (SR) Data rate type {NPar(2)} coding	US	NPar(2) Table 33
Identification Field - (SR) Request transmission of carriers {NPar(2)} coding - Octet 1		NPar(2) Table 34
Identification Field - (SR) Request transmission of carriers {NPar(2)} coding - Octet 2		NPar(2) Table 35

C = Capabilities information
 SR = Service requirement
 DS = Downstream
 US = Upstream

- 5 The Identification (I) parameter field is composed of several octets of NPar(1)s, SPAR(1)s, and NPar(2). In the octets, each parameter is assigned a unique bit position (or field). a binary ONE in the assigned bit position indicates that the parameter is valid. The validity of multiple parameters is conveyed by transmitting a binary ONE in each bit position corresponding to a valid parameter. A field is
10 encoded as described in it's table.

NPar(1) and SPar(1) octets are always transmitted. NPar(2) octets are transmitted only if the corresponding bit in the SPar(1) is a "1". Octets are transmitted in the order shown in Table 19. The level 1 NPar is listed in Table 20. The level 1 SPars is described in Table 21 and Table 22. The level 2 NParas are separately described in Table 23 through Table 35.

Table 20. Identification field - {NPar(1)} coding

SPort(s)	8	7	6	5	4	3	2	1
Reserved for ITU-T	x	x	x	x	x	x	x	1
Rec. V 8	x	x	x	x	x	x	1	x
Rec. V 8bis	x	x	x	x	x	1	x	x
Additional information available	x	x	x	x	1	x	x	x
Transmit ACK(1)	x	x	x	1	x	x	x	x
Reserved for ITU-T	x	x	1	x	x	x	x	x
Non-standard field	x	1	x	x	x	x	x	x
No parameters in this octet	x	0	0	0	0	0	0	0

NOTE - Rec. V 8 and Rec. V 8bis are identical to allow escape into voiceband modulation procedures

Table 21. Identification field (Capabilities Information)- {SPar(1)} coding - Octet 1

SPar(1)s	8	7	6	5	4	3	2	1
Currently transmitted carriers	x	x	x	x	x	x	x	1
Spectrum first usable frequency	x	x	x	x	x	x	1	x
Spectrum maximum frequency - upstream	x	x	x	x	x	1	x	x
Spectrum maximum frequency - downstream	x	x	x	x	1	x	x	x
Splitter Information - xTTLR	x	x	x	1	x	x	x	x
Reserved for DUT	x	x	1	x	x	x	x	x
non standard capabilities information	x	1	x	x	x	x	x	x
No parameters in this octet	x	0	0	0	0	0	0	0
NOTE -								

5

Table 22. Identification field (Service Requests)- {SPar(1)} coding - Octet 2

SPar(1)s	8	7	6	5	4	3	2	1
Data rate Amount Downstream	x	x	x	x	x	x	x	1
Data rate Amount Upstream	x	x	x	x	x	x	1	x
Data rate Type Downstream	x	x	x	x	x	1	x	x
Data rate Type Upstream	x	x	x	x	1	x	x	x
Request transmit of carriers	x	x	x	1	x	x	x	x
Reserved for ITU-T	x	x	1	x	x	x	x	x
non standard service request	x	1	x	x	x	x	x	x
No parameters in this octet	x	0	0	0	0	0	0	0

Transmitted carriers and families are indicated above.

10

Table 23. Identification Field – (CI) Currently transmitted carriers {NPar(2)} coding - Octet 1

NPar(2)s	8	7	6	5	4	3	2	1
Currently transmitting 4 >125 kHz family 1a)	x	x	x	x	x	x	x	1
Currently transmitting 4 <125 kHz family 1B)	x	x	x	x	x	x	1	x
Currently transmitting carrier A ₀ x	x	x	x	x	x	1	x	x
Currently transmitting carrier A ₁ x	x	x	x	x	1	x	x	x
Currently transmitting carrier A ₂ x	x	x	x	1	x	x	x	x
Currently transmitting carrier A ₃ x	x	x	1	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

Table 24. Identification Field – (CI) Currently transmitted carriers {NPar(2)} coding - Octet 2

NPar(2)s	8	7	6	5	4	3	2	1
Currently transmitting carrier A ₀ x	x	x	x	x	x	x	x	1
Currently transmitting carrier A ₁ x	x	x	x	x	x	x	1	x
Currently transmitting carrier A ₂ x	x	x	x	x	x	1	x	x
Currently transmitting carrier A ₃ x	x	x	x	x	1	x	x	x
Currently transmitting carrier B ₀ x	x	x	x	1	x	x	x	x
Currently transmitting carrier B ₁ x	x	x	1	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

5

The usable spectrum frequencies of Tables 25 – 27 are useful to indicate the TX/RX capabilities of the xTU-x (such as, for example, an xTU-C that only transmits through tone 68) and can indicate FDM vs. overlapped spectrum operation availability.

10

Table 25. Identification field – (CI) Spectrum
first usable frequency {NPar(2)} coding

NPar(2)s	8	7	6	5	4	3	2	1
Reserved for ITU-T	x	x	1	1	1	1	1	1
Unspecified by terminal	x	x	0	0	0	0	0	0
Spectrum first usable frequency (bits 6-1 x 10 KHz)	x	x	x	x	x	x	x	x

Table 26. Identification field – (CI) Spectrum
maximum frequency - upstream {NPar(2)} coding

NPar(2)s	8	7	6	5	4	3	2	1
Reserved for ITU-T	x	x	1	1	1	1	1	1
Unspecified by terminal	x	x	0	0	0	0	0	0
Spectrum maximum frequency - upstream (bits 5-1 x 1 MHz)	x	x	1	x	x	x	x	x
Spectrum maximum frequency - upstream (bits 5-1 x 10 KHz)	x	x	0	x	x	x	x	x

5

10

15

**Table 27. Identification field – (C1) Spectrum
maximum frequency - downstream {NPar(2)} coding**

NPar(2)s	8	7	6	5	4	3	2	1
Reserved for ITU-T	x	x	1	1	1	1	1	1
Unspecified by terminal	x	x	0	0	0	0	0	0
spectrum maximum frequency - downstream (bits 5-1 x 1 MHz)	x	x	1	x	x	x	x	x
spectrum maximum frequency - downstream (bits 5-1 x 10 MHz)	x	x	0	x	x	x	x	x

**Table 28. Identification Field – (C1) Splitter
Information {NPar(2)} coding - Octet 1**

NPar(2)s	8	7	6	5	4	3	2	1
LPF is voice	x	x	x	x	x	x	x	1
LPF is USA ISDN	x	x	x	x	x	x	1	x
LPF is European ISDN	x	x	x	x	x	1	x	x
Reserved for ITU-T	x	x	x	x	1	x	x	x
Reserved for ITU-T	x	x	x	1	x	x	x	x
Non-standard LPF	x	x	1	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

**Table 29. Identification Field – (C1) Splitter
Information {NPar(2)} coding - Octet 2**

NPar(2)s	8	7	6	5	4	3	2	1
HPF is 25 kHz (voice)	x	x	x	x	x	x	x	1
HPF is 50 kHz USA ISDN	x	x	x	x	x	x	1	x
HPF is 150 kHz (ADSL with European ISDN)	x	x	x	x	1	x	x	x
HPF is 250 kHz (VDSL)	x	x	x	x	1	x	x	x
Reserved for ITU-T	x	x	x	1	x	x	x	x
Non-standard HPF	x	x	1	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

**Table 30. Identification field – (SR) Data Rate
Amount (Average) {NPar(2)} coding - Octet 1**

NPar(2)s	8	7	6	5	4	3	2	1
Reserved for ITU-T	x	x	1	1	1	1	1	1
Unspecified by terminal	x	x	0	0	0	0	0	0
Average bandwidth: It is 5-1 x 5.12 kbps	x	x	1	x	x	x	x	x
Average bandwidth: It is 5-1 x 12.8 kbps	x	x	0	x	x	x	x	x

Table 31. Identification field – (SR) Data Rate Amount (Maximum) {NPar(2)} coding - Octet 2

NPar(2)s	8	7	6	5	4	3	2	1
Reserved for ITU-T	x	x	.	1	1	.	1	1
Unspecified by terminal	x	x	0	0	0	0	0	0
Maximum bandwidth (bits/s : x 512 kbps)	x	x	1	x	x	x	x	x
Maximum bandwidth (bits/s : x 12 kbps)	x	x	0	x	x	x	x	x

Table 32. Identification field – (SR) Data Rate Amount (Minimum) {NPar(2)} coding - Octet 3

NPar(2)s	8	7	6	5	4	3	2	1
Reserved for ITU-T	x	x	1	1	1	1	1	1
Unspecified by terminal	x	x	0	0	0	0	0	0
Minimum bandwidth (bits/s : x 512 kbps)	x	x	1	x	x	x	x	x
Minimum bandwidth (bits/s : x 32 kbps)	x	x	0	x	x	x	x	x

Table 33. Identification field – (SR) Data rate type {NPar(2)} coding

NPar(2)s	8	7	6	5	4	3	2	1
Low latency	x	x	x	x	x	x	x	1
Constant latency	x	x	x	x	x	x	1	x
Bursty	x	x	x	x	x	1	x	x
etc	x	x	x	x	1	x	x	x
	x	x	x	1	x	x	x	x
	x	x	1	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

An xTU-X may request that the other xTU-X transmit only on a certain number of carriers. This permits a reduction in the number of carriers for the rest of the transaction, or for the next initialization, as described above. Note that an xTU-X should only send a request that it knows the other xTU-X can fulfill.

**Table 34. Identification Field – (SR) Request
Transmission of Carriers {NPar(2)} coding – Octet 1**

NPar(2)'s	8	7	6	5	4	3	2	1
Request transmit using 4.515 kHz family (A)	x	x	x	x	x	x	x	1
Request transmit using 4.4Hz family (B)	x	x	x	x	x	x	1	x
Request transmit on carrier A ₀₁ x	x	x	x	x	x	1	x	x
Request transmit on carrier A ₀₂ x	x	x	x	x	1	x	x	x
Request transmit on carrier A ₀₃ x	x	x	x	1	x	x	x	x
Request transmit on carrier A ₀₄ x	x	x	1	x	x	x	x	x
No parameters in this octet	x	x	1	0	0	0	0	0

**Table 35. Identification Field – (SR) Request
Transmission of Carriers {NPar(2)} coding – Octet 2**

NPar(2)'s	8	7	6	5	4	3	2	1
Request transmit on carrier A ₀₁ x	x	x	x	x	x	x	x	1
Request transmit on carrier A ₀₂ x	x	x	x	x	x	x	1	x
Request transmit on carrier A ₀₃ x	x	x	x	x	x	1	x	x
Request transmit on carrier A ₀₄ x	x	x	x	x	1	x	x	x
Request transmit on carrier B ₀₁ x	x	x	x	1	x	x	x	x
Request transmit on carrier B ₀₂ x	x	x	1	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

- 5 The Standard Information field is composed of several octets of NPar(1)'s, SPar(1)'s, and possibly NPar(2), SPar(2), and SPar(3). NPar(1) and SPar(1) octets are specified herein and are always transmitted. NPar(1) octet encoding is described in Table 36, while SPar(1) octets encoding is described in Tables 37 and 38.

10

The contents of NPar(2), SPar(2), and SPar(3) octets are transmitted only if the corresponding bit in SPar(1) is a "1". In general, the contents regard modulation and protocol details specific to respective ITU-T Recommendations. Some illustrative specifications of modulation encoding are given in Tables 39-45.

15

Table 36. Standard Information field - {NPar(1)} coding

SPar(1)s	8	7	6	5	4	3	2	1
Voiceband (Rec. V 8 or V 8bis)	x	x	x	x	x	x	x	1
G.992.1 (clear EOC) channel using present invention	x	x	x	x	x	x	1	x
Reserved for ITU-T	x	x	x	x	x	1	x	x
Reserved for ITU-T	x	x	x	x	1	x	x	x
Reserved for ITU-T	x	x	x	1	x	x	x	x
Reserved for ITU-T	x	x	1	x	x	x	x	x
Reserved for ITU-T	x	1	x	x	x	x	x	x
No parameters in this octet	x	0	0	0	0	0	0	0

Table 37. Standard Information field - {SPar(1)} coding - Octet 1

SPar(1)s	8	7	6	5	4	3	2	1
G.992.1 - Annex A	x	x	x	x	x	x	x	1
G.992.1 - Annex B	x	x	x	x	x	x	1	x
G.992.1 - Annex C	x	x	x	x	x	1	x	x
G.hdsl	x	x	x	x	1	x	x	x
G.992.2	x	x	x	1	x	x	x	x
G.992.2 - (in TCM-(SD) environment)	x	x	1	x	x	x	x	x
Non-standard capabilities (modulations)	x	1	x	x	x	x	x	x
No parameters in this octet	x	0	0	0	0	0	0	0

Table 38. Standard Information field - {SPar(1)} coding - Octet 2

SPar(1)s	8	7	6	5	4	3	2	1
ANSI HDLS2 / G.hdsl2	x	x	x	x	x	x	x	1
ANSI VDSL a / G.vdsl Annex a	x	x	x	x	x	x	1	x
ANSI VDSL B / G.vdsl Annex B	x	x	x	x	x	1	x	x
ANSI T1.413 Issue 2	x	x	x	x	1	x	x	x
Reserved for ITU-T	x	x	x	1	x	x	x	x
Reserved for ITU-T	x	x	1	x	x	x	x	x
Reserved for ITU-T	x	1	x	x	x	x	x	x
No parameters in this octet	x	0	0	0	0	0	0	0

Table 39. Modulation – G.992.1 Annex a {NPar(2)} coding - Octet 1

NPar(2)s	8	7	6	5	4	3	2	1
Specify parameters or profiles for G.992.1 Annex a	x	x	x	x	x	x	x	x
STM=2, ATM=1	x	x	x	x	x	x	x	x
NTR	x	x	x	x	x	x	x	x
etc	x	x	x	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

Table 40. Modulation – G.992.1 Annex a {NPar(2)} coding - Octet 2

NPar(2)s	8	7	6	5	4	3	2	1
AS1 / ATM: downstream	x	x	x	x	x	x	x	x
AS2 downstream	x	x	x	x	x	x	x	x
AS3 downstream	x	x	x	x	x	x	x	x
LS1 downstream	x	x	x	x	x	x	x	x
LS2 downstream	x	x	x	x	x	x	x	x
LS1 / ATM1 upstream	x	x	x	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

Table 41. Modulation – G.992.1 Annex a {NPar(2)} coding - Octet 3

NPar(2)s	8	7	6	5	4	3	2	1
LS2 upstream	x	x	x	x	x	x	x	x
	x	x	x	x	x	x	x	x
	x	x	x	x	x	x	x	x
	x	x	x	x	x	x	x	x
	x	x	x	x	x	x	x	x
	x	x	x	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

Table 42. Modulation – G.992.1 Annex B {NPar(2)} coding - Octet 1

NPar(2)s	8	7	6	5	4	3	2	1
0 = Tones above 32 / 1 = Tones below 33 allowed - NOTE	-	x	x	x	x	x	x	1
	x	x	x	x	x	x	1	x
	x	x	x	x	x	1	x	x
etc	x	x	x	x	1	x	x	x
	x	x	x	1	x	x	x	x
	x	x	1	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

NOTE - When the message is sent by the ATU-C, it indicates its ability to receive tones (0 = RX Tones above 32 / 1 = RX Tones below 33 allowed). When sent by the ATU-C, 1 indicates the ability to transmit tones. (0 = only TX Tones above 32 / 1 = RX Tones 31 to 63 mandatory, RX tones 1 to 32 optional)

Table 43. Modulation – G.992.1 Annex C {NPar(2)} coding - Octet 1

NPar(2)s	8	7	6	5	4	3	2	1
Specify parameters or profiles for G.992.1 Annex C	x	x	x	x	x	x	x	1
	x	x	x	x	x	x	1	x
	x	x	x	x	x	1	x	x
etc	x	x	x	x	1	x	x	x
	x	x	x	1	x	x	x	x
	x	x	1	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

Table 44. Modulation – G.hdsl {NPar(2)} coding

NPar(2)s	8	7	6	5	4	3	2	1
Use G.hdsl Annex B	x	x	x	x	x	x	x	1
	x	x	x	x	x	x	1	x
	x	x	x	x	x	1	x	x
etc	x	x	x	x	1	x	x	x
	x	x	x	1	x	x	x	x
	x	x	1	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

Table 45. Modulation – G.992.2 {NPar(2)} coding - Octet 1

NPar(2)s	8	7	6	5	4	3	2	1
Specify parameters or profiles for G.992.2	x	x	x	x	x	x	x	1
	x	x	x	x	x	x	1	x
	x	x	x	x	x	1	x	x
etc	x	x	x	x	1	x	x	x
	x	x	x	1	x	x	x	x
	x	x	1	x	x	x	x	x
No parameters in this octet	x	x	0	0	0	0	0	0

NOTE - The message may optionally contain a non-standard information

The MS, CL, and CLR messages may optionally contain a non-standard information field to convey information beyond that defined herein. When non-standard
5 information is to be sent, the "Non-standard field" parameter is set to binary ONE in the identification field of the transmitted message. The non-standard information field may optionally be composed of one or more non-standard information blocks (see Fig. 14).

10 Each non-standard information block (see Fig. 15) comprises: (1) a length indicator (one octet) that specifies the length of the remainder of the block; (2) a country code (K octets), as defined in Recommendation T.35; (3) a length indicator (one octet), that specifies the length of the provider code(e.g., the value in octets indicating that L octets follow); (4) a provider code as specified by the country identified in
15 Recommendation T.35; and (5) non-standard information (M octets).

The present invention permits the modulation used by the present invention to continue to be transmitted after the negotiation procedures are complete. According to a feature of the present invention, the modulation can be used as, for
20 example, a clear channel EOC. For example, a standard information NPar(1) bit indicates the availability of CL/CLR messages, and the same bit is used to indicate selection in MS messages. Following the termination of the present invention negotiation protocol with the ACK message, the carrier could remain ON to provide a clear EOC channel

25

In the past, the configuration of an ATU-R Handshake by a Terminal was performed using either AT commands, or other proprietary means. According to the instant invention, an AOM management protocol is used between a Terminal and the ATU-R, and a similar communication path between the ATU-C and the network
30 management systems. In the preferred embodiments, the Terminal uses the SNMP protocol (IETF RFC 1157 published May 1990) to configure and monitor the present invention's handshake procedure in an ATU-R. Since the present invention's

handshake procedure data rate is under 100 bytes/sec, a reasonable time needs to be provided for the Terminal to actively participate in the handshake session.

5 In general, the CL and CLR message parameters can be set before the handshake procedure begins. The present invention enables the Terminal to inquire (of the ATU-R) the status of several of the parameters.

SNMP Traps can be used to indicate critical parts of the received messages that must be acted on by the Terminal if it desires to influence items, such as, for
10 example, MS or ACK/NAK messages.

While the invention has been particularly shown and described with reference to the preferred embodiments thereof, it is understood by those skilled in the art that various alterations in form and/or detail may may be made without departing from
15 the spirit and/or scope of the invention, as defined by the following claims. Although the invention has been described with reference to the particular means, materials and embodiments, it is to be understood that the invention is not limited to the particulars disclosed herein, but extends to all equivalents within the scope of the claims.

20

25

WHAT IS CLAIMED IS:

1. A communication apparatus selectively connectable to a communication device, comprising:

5 a communicator that executes a first communication mode that transmits, to the communication device, a first predetermined signal that designates a specific mode, the communication device responding by issuing a second predetermined signal;

10 said communicator executing a second communication mode to transmit a third predetermined signal that requests a transmission of said first predetermined signal from the communication device, and receives said first predetermined signal from the communication device, the second communication mode thereafter transmitting said second predetermined signal to the communication device; and

15 a controller that executes one of the first communication mode and the second communication mode upon initializing a communication with the communication device.

2. The communication apparatus of claim 1, wherein said first predetermined signal comprises a MS signal.

20

3. The communication apparatus of claim 1, wherein said third predetermined signal comprises a MR signal.

25 4. The communication apparatus of claim 1, wherein said second predetermined signal comprises one of an ACK signal and a NACK signal.

5. The communication apparatus of claim 2, wherein said second predetermined signal comprises one of an ACK signal and a NACK signal.

30 6. The communication apparatus of claim 5, wherein said communicator executes a third communication mode that transmits a CLR signal to the communication device that informs the communication device of a function list of

the communication apparatus and requests a function list of the communication device, the communication device transmitting a CL signal that includes the function list of the communication device to the communication apparatus in response to the CLR signal, after which the third communication mode is executed to transmit one
5 of the ACK signal and the NACK signal to the communication device.

7. The communication apparatus of claim 6, wherein said third communication mode is executed prior to an execution of said first communication mode.

10 8. The communication apparatus of claim 7, wherein said third communication mode is executed prior to an execution of said second communication mode.

9. The communication apparatus of claim 1, wherein said communicator transmits said NACK signal when the communication device requests a non-
15 executable mode.

10. The communication apparatus of claim 9, wherein said communicator returns the communication apparatus to an initialization state upon an occurrence of a predetermined event.

20 11. The communication apparatus of claim 10, wherein said predetermined event comprises a transmission of said NACK signal.

12. The communication apparatus of claim 5, wherein said communicator
25 executes a third communication mode that transmits a CLR signal to the communication device that informs the communication device of a function list of the communication apparatus and requests a function list of the communication device, wherein the communication device transmits a partial function list of the communication device to the communication apparatus in response to the CLR
30 signal, after which the third communication mode is executed to transmit one of the ACK signal and the NACK signal to the communication device.

13. The communication apparatus of claim 12, wherein said third communication mode is executed when said partial function list of the center is received by said communicator a predetermined number of times.

5 14. A communication apparatus selectively connectable to a communication terminal, comprising:

a communicator that executes a first communication mode, associated with the communication apparatus, that transmits a first predetermined signal to the communication terminal that designates a specific mode, and that receives a
10 second predetermined signal from the communication terminal;

said communicator executing a second communication mode, associated with the communication apparatus, that transmits a third predetermined signal to the communication terminal requesting a transmission of said first predetermined signal by the communication terminal, said communicator receiving said first
15 predetermined signal from the communication terminal, said communicator executing said second communication mode thereafter to transmit said second predetermined signal to said communication terminal; and

a controller that controls said communicator to execute one of said first communication mode and said second communication mode upon initializing a
20 communication with the remote communication terminal.

15. The center communication apparatus of claim 14, wherein said first predetermined signal comprises a MS signal.

25 16. The center communication apparatus of claim 14, wherein said second predetermined signal comprises one of an ACK signal and a NACK signal.

17. The center communication apparatus of claim 14, wherein said third predetermined signal comprises a MR signal.

30

18. The center communication apparatus of claim 14, wherein said first predetermined signal comprises a MS signal, said second predetermined signal

comprises one of an ACK signal and a NACK signal, and said third predetermined signal comprises a MR signal.

19. The center communication apparatus of claim 18, wherein said
5 communicator executes a third communication mode that transmits a CLR signal to the communication terminal that informs the communication terminal of a function list of the communication apparatus and requests a function list of the communication terminal, the communication terminal transmitting a CL signal that
10 includes the function list of the communication terminal to the communication apparatus, after which the third communication mode is executed to transmit one of the ACK signal and the NACK signal to the communication terminal.

20. A method for performing a data communication between a communication apparatus and a communication device, comprising:
15 communicating in a first communication mode of the communication apparatus to transmit an MS signal designating a specific mode to the communication device, the communication device receiving the MS signal and transmitting one of an ACK signal and a NACK signal to the first communication mode of the communication apparatus;
20 communicating in a second communication mode of the communication apparatus to transmit an MR signal to the communication device requesting that the communication device transmit the MS signal, the communicating device receiving the MR signal and transmitting the MS signal to the second communication mode of the communication apparatus, and thereafter the second communication mode of
25 the communication apparatus is executed to transmit one of the ACK signal and the NACK signal to the communication device; and
executing one of the first communication mode and the second communication mode prior to a communication.

30 21. The communication method of claim 20, further comprising a third communication mode of the communication apparatus that is executed to transmit a CLR signal to the communication device that informs the communication device of a

function list of the communication apparatus and requests a function list of the communication device, the communication device responding by transmitting a CL signal that includes the function list of the communication device to the communication apparatus, the execution of the third communication mode
5 transmitting one of the ACK signal and the NACK signal to the communication device prior to executing one of the first communication mode and the second communication mode.