

**ANTENNA STEERING FOR AN ACCESS
POINT BASED UPON CONTROL FRAMES**

Field of the Invention

[0001] The present invention relates to the field of wireless local area networks, and in particular, to an antenna steering algorithm for an access point operating within a wireless local area network.

Background of the Invention

[0002] Various standards allow remote stations, such as portable computers, to be moved within a wireless local area network (WLAN) and connect via radio frequency (RF) transmissions to an access point (AP) that is connected to a wired network. The wired network is often referred to as a distribution system. The various standards include the IEEE 802.11 standard and its corresponding letter revisions thereof, such as 802.11b and 802.11g, for example.

[0003] A physical layer in the remote stations and in the access point provides low level transmissions by which the stations and the access point communicate. Above the physical layer is a media access control (MAC) layer that provides services, such as authentication, deauthentication, privacy, association and disassociation, for example.

[0004] In operation, when a remote station comes on-line, a connection is first established between the physical layers in the station and the access point. The MAC layers can then connect. Typically, for the remote stations and the access point, the physical layer RF signals are transmitted and received using monopole antennas.

[0005] A monopole antenna radiates in all directions, generally in a horizontal plane for a vertically oriented element. Monopole antennas are susceptible to effects that degrade the quality of communication between the remote station and the access point, such as reflection or diffraction of radio wave signals caused by intervening objects. Intervening objects include walls, desks and people, for example. These objects create multi-path, normal statistical fading, Rayleigh fading, and so forth. As a result, efforts have been made to mitigate signal degradation caused by these effects.

[0006] One technique for counteracting the degradation of RF signals is to use two antennas to provide diversity. The two antennas are coupled to an antenna diversity switch in one or both of the remote stations and the access point. The theory behind using two antennas for antenna diversity is that, at any given time, at least one of the antennas is likely receiving a signal that is not suffering from the effects of multi-path. Consequently, this antenna is the antenna that the remote station or access point selects via the antenna diversity switch for transmitting/receiving signals. Nonetheless, there is still a need to address the degradation of RF signals

between the remote stations and an access point in a wireless local area network.

Summary of the Invention

[0007] In view of the foregoing background, an object of the present invention is to improve communications between an access point and remote stations within a wireless local area network.

[0008] An improvement over simple diversity is provided through an antenna steering process for access points (i.e., wireless gateways) used in wireless local area networks. Directional antennas improve the throughput of the network, and increase the range between the access point and the remote stations (i.e., wireless user devices). A directional antenna provides a higher signal-to-noise ratio than an omni-directional antenna in most cases, thus allowing the link to operate at higher data rates.

[0009] The antenna steering process may be resident in the media access control (MAC) layer of the access point, and selects a best or preferred directional antenna pattern based on signal quality metrics available from the physical layer upon receiving signals from the remote stations.

[0010] According to the principles of the present invention, during processes such as registration, authentication or subsequent data exchanges between the access point and a selected remote station, a preferred direction for the steered access point antenna is determined. In one embodiment, software or firmware operating at the access point makes this determination. The access point antenna control software/firmware may

build a database that includes the identity of the remote station and the antenna direction associated with that station for achieving optimum communications performance.

[0011] Hardware may be employed to operate with inherent diversity selection circuitry in typical 802.11 equipment for selecting the preferred directional antenna angle. The access point may use signaling to cause the remote stations to transmit a probe response signal, wherein the access point measures the signal quality of the probe response signal. The access point may compare metrics corresponding to signals received from the remote stations in a directional antenna mode against metrics corresponding to signals received from the remote stations in an omni-directional mode to determine if a new antenna scan should be performed. If the access point determines that hidden nodes are present, it may invoke a protection mechanism using request-to-send/clear-to-send (RTS/CTS) messaging as defined in the 802.11 standard, for example.

[0012] The benefits of augmenting the access point with a directional antenna are two-fold: improved throughput to individual remote stations and an ability to support more users in the network. In most RF environments, the signal level received at the remote station can be improved by having the access point transmit using a shaped antenna beam pointed in the direction of the station. The shaped antenna beam may provide a 3-5 dB gain advantage, for example, over the omni-directional antenna typically deployed with an access point. The increased signal level allows the

link between the access point and the remote station to operate at higher data rates, especially at the outer band of the coverage area. The directional antenna steering process is resident in the access point to support operation with the remote stations.

[0013] More particularly, the present invention is directed to a method for operating an access point in a wireless local area network (WLAN), with the access point comprising a directional antenna for communicating with at least one remote station in a forward link based upon an exchange of packet data comprising a plurality of control frames and a data frame. The directional antenna comprising a plurality of antenna patterns. The method comprises receiving a first control frame via a first antenna pattern of the directional antenna from the at least one remote station, transmitting a first data frame to the at least one remote station, and receiving a second control frame via a second antenna pattern of the directional antenna from the at least one remote station.

[0014] The method further comprises measuring a signal quality of the first control frame received via the first antenna pattern and a signal quality of the second control frame received via the second antenna pattern, and comparing the respective measured signal qualities associated with the first and second antenna patterns. The second antenna pattern is selected for transmitting a second data frame to the at least one remote station if the measured signal quality associated with the second antenna pattern exceeds the

measured signal quality associated with the first antenna pattern by a predetermined threshold.

[0015] Transmitting the first data frame may be performed using a preferred antenna pattern of the directional antenna, and wherein the comparing further comprises comparing the respective measured signal qualities associated with the first and second antenna patterns with a signal quality associated with the preferred antenna pattern. The second antenna pattern is selected for transmitting a second data frame to the at least one remote station if the measured signal quality associated with the second antenna pattern exceeds the measured signal qualities associated with the first and preferred antenna patterns by a predetermined threshold.

[0016] The first antenna pattern may comprise an omni angle, and the second antenna pattern may comprise a directional angle. Alternatively, the first antenna pattern may comprise a first directional angle, and the second antenna pattern may comprise a second directional angle. The first control frame received may comprise a clear-to-send message, and the second control frame received may comprise an acknowledgement message.

[0017] Another aspect of the present invention is directed to a method for operating an access point in a WLAN, with the access point comprising a directional antenna for communicating with at least one remote station in a reverse link based upon an exchange of packet data comprising a plurality of control frames and a data frame. The directional antenna comprising a plurality of antenna patterns.

[0018] The method further comprises receiving a first control frame via a first antenna pattern of the directional antenna from the at least one remote station, transmitting a second control frame to the at least one remote station, and receiving a first data frame via a second antenna pattern of the directional antenna from the at least one remote station. A signal quality of the first control frame received via the first antenna pattern and a signal quality of the first data frame received via the second antenna pattern are measured. The respective measured signal qualities associated with the first and second antenna patterns are compared.

[0019] The method further comprises selecting the second antenna pattern for transmitting a second data frame by the access point to the at least one remote station if the measured signal quality associated with the second antenna pattern exceeds the measured signal quality associated with the first antenna pattern by a predetermined threshold.

[0020] The first antenna pattern may comprise an omni angle, and the second antenna pattern may comprise a directional angle. Alternatively, the first antenna pattern may comprise a first directional angle, and the second antenna pattern may comprise a second directional angle. The first control frame received may comprise a request-to-send message, and the second control frame transmitted may comprise a clear-to-send message.

[0021] Yet another aspect of the present invention is directed to an access point for a wireless local area network (WLAN) comprising a directional antenna

comprising a plurality of antenna patterns, and a controller connected to the directional antenna for controller thereof. The controller may be configured for communicating with at least one remote station in a forward link as described above. Alternatively, the controller may be configured for communicating with the least one remote station in a reverse link as also described above.

Brief Description of the Drawings

[0022] The foregoing and other objects, features and advantages of the invention will be apparent from the following more particular description of preferred embodiments of the invention, as illustrated in the accompanying drawings. The drawings are not necessarily to scale, with emphasis instead being placed on illustrating the principles of the invention.

[0023] FIG. 1A is a schematic diagram of a wireless local area network (WLAN) employing the principles of the present invention;

[0024] FIG. 1B is a schematic diagram of an access point in the WLAN of FIG. 1A performing an antenna scan;

[0025] FIG. 2A is a view of an access point of FIG. 1A having an external directive antenna array;

[0026] FIG. 2B is a view of the access point of FIG. 2A having the directive antenna array incorporated in an internal PCMCIA card;

[0027] FIG. 3A is a view of the directive antenna array of FIG. 2A;

[0028] FIG. 3B is a schematic diagram of a switch used to select a state of an antenna element of the directive antenna of FIG. 3A;

[0029] FIG. 4 is a block diagram of an access point of FIG. 1A employing subsystems, layers and an antenna steering process according to the principles of the present invention;

[0030] FIG. 5A is a signal diagram optionally used by the antenna steering process of FIG. 4;

[0031] FIG. 5B is an alternative signal diagram optionally used by the antenna steering process of FIG. 4;

[0032] FIG. 6 is an alternative block diagram of FIG. 4 in which antenna diversity circuits are employed;

[0033] FIG. 7 is a signal diagram using a hidden node technique optionally used by the antenna steering process of FIG. 4;

[0034] FIG. 8 is a top view of the network of FIG. 1 with bi-directional signaling;

[0035] FIG. 9 is a top view of the network of FIG. 1 with indications of the antenna beams;

[0036] FIG. 10 is a flowchart of a method for operating an access point in a WLAN based upon spatial diversity in accordance with the present invention;

[0037] FIG. 11 is a flowchart of a method for operating an access point in a WLAN based upon probe signals in accordance with the present invention;

[0038] FIGS. 12 and 13 are respective flowcharts of a method for operating an access point in a WLAN based upon control frames in forward and reverse links in accordance with the present invention; and

[0039] FIG. 14 is a flowchart of a method for operating an access point in a WLAN based upon hidden node recognition in accordance with the present invention.

Detailed Description of the Preferred Embodiments

[0040] The present invention will be described more fully hereinafter with reference to the accompanying drawings, in which preferred embodiments of the invention are shown. This invention may, however, be embodied in many different forms and should not be construed as limited to the embodiments set forth herein; rather, these embodiments are provided so that this disclosure will be thorough and complete, and will fully convey the scope of the invention to those skilled in the art. Like numbers refer to like elements throughout, and prime notation is used to indicate similar elements in alternate embodiments.

[0041] Referring initially to FIG. 1A, a wireless local area network (WLAN) **100** having a distribution system **105** will initially be discussed. Access points **110a**, **110b** and **110c** are connected to the distribution system **105** via wired connections, such as wired data network connections. Each of the access points **110a**, **110b** and **110c** has a respective zone **115a**, **115b**, **115c** in which it is capable of communicating via radio frequency (RF) signals with the remote stations **120a**, **120b**, **120c**. The remote stations **120a**, **120b**, **120c** are supported with wireless local area network hardware and software to access the distribution system **105**. In the following description, when a general reference is made to the access points, the remote stations and the

zones, the respective reference numerals **110**, **120** and **115** may be used.

[0042] Present technology provides the access points **110** and the remote stations **120** with antenna diversity. Antenna diversity allows the access points **110** and the remote stations **120** to select one of two antennas to provide transmit and receive duties based on the quality of signals being received. One reason for selecting one antenna over the other occurs in the event of multi-path fading, in which a signal taking two different paths causes signal cancellation to occur at one antenna but not the other. Another example is when interference is caused by two different signals received at the same antenna. Yet another reason for selecting one of the two antennas is due to a changing environment, such as when a remote station **120c** is carried from the third zone **115c** to the first or second zones **115a**, **115b** as indicated by arrow **125**.

[0043] FIG. 1B is a block diagram of a subset of the network **100** illustrated in FIG. 1A in which an access point **110b**, employing the principles of the present invention, is shown in greater detail with respect to the directive antenna lobes **130a-130i**. The directive antenna lobes **130a-130i** will also be generally indicated by reference numeral **130**. The access point **110b** sequences through the antenna lobes **130** during a scan of its environment to determine a preferred antenna direction.

[0044] During a scan, the access point **110b** uses a directive antenna, as shown in greater detail in FIGS. 2A and 2B, to scan in search of RF signals transmitted by the remote station **120b**. At each scan direction

(i.e., angle or antenna pattern), the access point **110b** measures a signal or probe response and calculates a respective metric for that scan angle. Examples of the metrics include a received signal strength indication (RSSI), a carrier-to-interference ratio (C/I), an energy-per-bit ratio (Eb/No), or other suitable measures, such as a signal-to-noise ratio (SNR), of the quality of the received signal or signal environment. A combination of these measurements may also be made to determine the best or preferred antenna pattern, as readily appreciated by those skilled in the art. Based on the measured signal quality metrics, the access point **110b** determines the preferred antenna angle or direction for communicating with the remote station **120b**.

[0045] The scans may occur before or after the remote station **110b** has been authenticated and has associated with the distribution system **105**. Thus, the initial antenna scan may be accomplished within the MAC layer. Alternatively, the initial scan may be accomplished external from the MAC layer. Similarly, scans occurring after the remote station **110b** has authenticated and has associated with the distribution system **105** may be accomplished within the MAC layer or by processes occurring external the MAC layer.

[0046] FIG. 2A is a diagram of an access point **110** using an external directive antenna array **200a**. The directive antenna array **200a** includes five monopole passive antenna elements **205a**, **205b**, **205c**, **205d** and **205e** and one monopole, active antenna element **206**. The passive antenna elements **205a**, **205b**, **205c**, **205d** and **205e** are generally referred to below by reference

numeral **205**. The directive antenna element **200a** is connected to the access point **110** via a universal serial bus (USB) port **215**. Other types of connections between the directive antenna array **200a** and the access point **110** are readily acceptable.

[0047] The passive antenna elements **205** in the directive antenna array **200a** are parasitically coupled to the active antenna element **206** to permit scanning. By scanning, it is meant that at least one antenna beam of the directive antenna array **200a** can be rotated, optionally 360 degrees, in increments associated with the number of passive antenna elements **205**.

[0048] A detailed discussion of the directive antenna array **200a** is provided in U.S. Patent Publication No. 2002/0008672, published January 24, 2002, entitled "Adaptive Antenna For Use In Wireless Communications System", the entire disclosure of which is incorporated herein by reference and which is assigned to the current assignee of the present invention. Example methods for optimizing antenna direction based on received or transmitted signals by the directive antenna array **200a** are also discussed therein.

[0049] The directive antenna array **200a** may also be used in an omni-directional mode to provide an omni-directional antenna pattern. The access points **110** may use an omni-directional pattern for transmission or reception. The access points **110** may also use the selected directional antenna when transmitting to and receiving from the remote stations **120**.

[0050] FIG. 2B is an isometric view of an access point **110** with an internal directive antenna **220b**. In

this embodiment, the directive antenna array **200b** is on a PCMCIA card **220**. The PCMCIA card **220** is carried by the access point **110** and is connected to a processor (not shown). The directive antenna array **200b** provides the same functionality as the directive antenna array **200a** illustrated in FIG. 2A.

[0051] It should be understood that various other forms of directive antenna arrays can be used. Examples include the arrays described in U.S. Patent No. 6,515,635 issued February 4, 2003, entitled "Adaptive Antenna For Use In Wireless Communication Systems" and U.S. Patent Publication No. 2002/0036586, published March 28, 2002, entitled "Adaptive Antenna For Use In Wireless Communication System," the entire teachings of which are incorporated herein by reference and which are assigned to the current assignee of the present invention.

[0052] FIG. 3A is a detailed view of the directive antenna array **200a** that includes the passive antenna elements **205** and the active antenna element **206** as discussed above. The directive antenna array **200a** also includes a ground plane **330** to which the passive antenna elements are electrically coupled, as discussed below in reference to FIG. 3B.

[0053] Still referring to FIG. 3A, the directive antenna array **200a** provides a directive antenna lobe **300** angled away from antenna elements **205a** and **205e**. This is an indication that the antenna elements **205a** and **205e** are in a reflective mode, and the antenna elements **205b**, **205c** and **205d** are in a transmission mode. In other words, the mutual coupling between the active antenna element **206** and the passive antenna

elements **205** allows the directive antenna array **200a** to scan the directive antenna lobe **300**, which, in this case, is directed as shown as a result of the modes in which the passive elements **205** are set. Different mode combinations of passive antenna element **205** result in different antenna lobe **300** patterns and angles, as readily understood by those skilled in the art.

[0054] FIG. 3B is a schematic diagram of an example circuit that can be used to set the passive antenna elements **205** in the reflective or transmission modes. The reflective mode is indicated by a representative elongated dashed line **305**, and the transmission mode is indicated by a shortened dashed line **310**. The representative modes **305** and **310** are respectively caused by coupling to a ground plane **330** via an inductive element **320** or a capacitive element **325**. The coupling of the passive antenna element **205a** through the inductive element **320** or capacitive element **325** is performed via a switch **315**. The switch **315** may be a mechanical or electrical switch capable of coupling the passive antenna element **205a** to the ground plane **330**. The switch **315** is set via a control signal **335**.

[0055] Coupled to the ground plane **330** via the inductor **320** is the passive antenna element **205a**, which is effectively elongated as shown by the longer representative dashed line **305**. This can be viewed as providing a "backboard" for an RF signal coupled to the passive antenna element **205a** via mutual coupling with the active antenna element **206**. In the case of FIG. 3A, both passive antenna elements **205a** and **205e** are connected to the ground plane **330** via respective inductive elements **320**. At the same time, in the

example of FIG. 3A, the other passive antenna elements **205b**, **205c** and **205d** are electrically connected to the ground plane **330** via respective capacitive elements **325**.

[0056] The capacitive coupling effectively shortens the passive antenna elements as represented by the shorter representative dashed line **310**. Capacitively coupling all of the passive elements **325** effectively makes the directive antenna array **200a** an omni-directional antenna. It should be understood that alternative coupling techniques may also be used between the passive antenna elements **205** and the ground plane **330**, such as delay lines and lumped impedances, for example.

[0057] Jumping to FIG. 9, an overhead view of the access point **110b** generating an omni-directional antenna pattern **905** and a directional antenna pattern **910** through use of the directive antenna array **200a** or **200b** is provided. The access point **110b** communicates with multiple stations **120a-120d**. Since access points **110** are usually remotely installed without nearby obstructions or moving reflectors (e.g., high on a wall or ceiling), the selection of the preferred antenna pattern direction is likely not going to change throughout the connection with a given remote station **120**.

[0058] The illustrated access point **110b** may make use of a directional antenna **200a** for downlink data frames transmitted to a selected remote station **120c**. For most broadcast and control frames, the access point may use the omni-directional antenna pattern **905** and the lowest available data rate to ensure that all

remote stations **120** receive them. The directional antenna **200a** may not increase the coverage area of the network **100**, but may increase the data rate for data frames sent to the remote stations **120**. The increased downlink rate is useful because the majority of the data transferred over the network **100** appears on the downlink (e.g., web page access, file transfers). One option is to use switched spatial diversity when the access point **110b** is required to receive in the omni mode. The potential added link margin of 5 dB accommodates a throughput increase of 300%, for example.

[0059] Uplink data frames sent from the selected remote station **120c** to the access point **110b** during contention periods (CP) are received using the omni-directional antenna pattern since any remote station may have transmitted the frame. For large frames, the network configuration may require the remote station to use the request-to-send/clear-to-send (RTS/CTS) mechanism to reserve the wireless medium. In this case, the access point **110b** could receive in a directional mode to increase the data rate on the uplink. This is somewhat dependent on the data rate selection algorithm implemented at the remote station **120c**.

[0060] In downlink transmissions, the access point **110b** may decide to transmit small packets during contention periods using the omni-directional pattern and a lower data rate. The reason for this is that a remote station on the "other" side of the coverage area (such as remote station **120e**) may not hear the access point transmission from the directional antenna pattern

910 pointed away from it. This is the familiar "hidden node" problem where two remote stations **120** do not hear each other and end up transmitting at the same time.

In this case the two remote stations are **120c** and **120e**. A method to avoid this problem, especially for large data frames, is described below in reference to FIG. 7.

[0061] The directional antenna patterns at the access point **110** can thus provide higher data rates for downlink and uplink data frame exchanges with the remote stations **120**, which is the bulk of the network traffic. Network connectivity is maintained with the nominal gain of the omni-directional antenna of the access point **110**. That is, the remote stations **120** can associate with the access point **110** and maintain the connection without the use of the directional antenna **200a**.

[0062] A set of rules as provided in TABLE 1 can be defined to take advantage of the omni-directional and directional characteristics of the directional antenna **200a**. TABLE 1 includes addresses of the remote stations **120** currently associated with the access point **110** and their current antenna direction selection. TABLE 1 may delineate example antenna direction selections based on frame sequences from the 802.11 standard (TABLES 21 and 22 therein). In TABLE 1, "Dir" indicates direction, "UL" indicates uplink, and "DL" indicates downlink.

TABLE 1 - Example Antenna Selection Rules

Sequence	Dir	Antenna Selection	
Beacon	DL	Omni	

Data	DL	Dir	See FIG. 5A
RTS-CTS-Data	UL	Omni/Dir	See FIG. 5B

[0063] A process can be described in a set of rules that determine when to select the omni-directional pattern and when to select a directional pattern. For example, the access point **110** may select a directional pattern during time intervals when transmitting or receiving to/from a single remote station **120**.

[0064] A block diagram showing the interfaces of the access point **110** is shown in FIG. 4. The illustrated access point **110** includes various subsystems and layers. An antenna subsystem **405** may include the directional antenna **200b** and supporting circuitry, buses and software to operate the directional antenna. The antenna subsystem **405** interfaces to the physical layer **410** and provides RF signals **412** thereto.

[0065] The physical layer **410** processes the RF signals **412** and determines signal quality measurements **417** to an antenna steering process **420**. The physical layer **410** sends processed signals based upon the RF signals **412** to the MAC layer **415**. The MAC layer **415** generates timing control messages **422**, which are also sent to the antenna steering process **420** in order to switch the antenna to the omni mode or directional mode when required.

[0066] The MAC layer **415** also sends data frames **429** to other processes (not shown). The illustrated physical layer **410**, MAC layer **415** and antenna steering process **420** may reside within a controller **400**. The antenna steering process **420** may be stored within a

memory, for example, which may be a stand-alone memory or an embedded memory within a processor, for example.

[0067] The antenna steering process **420** maintains an "antenna table or database" or a "direction table or database" **425** as a function of the received signal quality measurements **417** made during antenna scans of each remote station **120**. For example, the direction table **425** may store a station ID and a corresponding antenna direction (A, B, C) for directional communications with the remote stations **120**. Once the antenna directions in the direction table **425** have been determined, the antenna steering process **420** is used to provide directional antenna control **427** to the antenna subsystem **405**. If the signal quality measurements **417** are above a predetermined threshold indicating that the highest data rate can be supported in the omni-directional mode, the antenna direction may be held at the omni-directional (O) mode.

[0068] The following paragraphs describe various techniques in accordance with the present invention for determining the preferred direction to point a directional antenna **220b** from an access point **110** to a remote station **120**. The first technique employs a spatial diversity selection mechanism. The second technique uses a sequence of probe signals exchanged between the access point **110** and the remote stations **120**. The third technique uses control messages (e.g., ACK or CTS) to make signal quality measurements of the received antenna directions at the access point **110**. The third technique is applicable in both forward and reverse direction links.

[0069] The first technique assumes that current 802.11 devices incorporate antenna switched diversity scan/control and that future 802.11 devices, such as 802.11a/802.11g/802.11n will also support switched diversity. The first technique is applicable after a remote station **120** has authenticated and associated itself with a network. It is assumed that the initial antenna scan is accomplished within the MAC/network layer protocol. With a directional or multi-element antenna **220a**, the first technique can make use of the diversity protocol to keep the antenna position/selection updated.

[0070] Referring now to FIG. 6, the first technique functions as follows. The illustrated access point **110'** includes a controller **600'** connected to the antenna subsystem **405'**. The controller **600'** comprises a physical layer **410'**, which is given access to the antenna control signals, and a MAC layer (FIG 4). The MAC layer writes antenna selections into register A **605a'** and register B **605b'**. Register A **605a'** contains the selected antenna position, and register B **605b'** contains a candidate antenna position. The physical layer **410'** is also in communications with a multiplexer **610'**. The physical layer **410'** sends a diversity selection switch control signal **607'** to the multiplexer **610'** in a typical diversity selection control manner, but in this case, the diversity selection switch control signal controls whether the contents of register A **605a'** or register B **605b'** are used.

[0071] The selected antenna position is initially chosen during the network authentication/association protocol. The candidate antenna position is any other

antenna position (including an omni-directional mode). The candidate antenna position is changed, in a predetermined sequence, after a valid packet has been received or after not receiving any packets for a predetermined time period.

[0072] After successfully receiving a packet, the physical layer **410'** sends received signal quality metrics (signal strength, signal-to-noise ratio, multi-path/equalizer metrics, etc.) for both antenna positions to the MAC layer. During the packet reception, the physical layer **410'** functions as it does now for 802.11; that is, to switch between the two antenna positions and to use the best antenna position for packet reception. After valid packet reception by the physical layer **410'**, the signal quality metrics for the two antenna positions are sent to the MAC layer. The MAC layer updates both the selected antenna position and the candidate antenna position. The selected antenna position is replaced with the best position based on the data received from the physical layer **410'**. Filtering/hysteresis may be used to keep from "ping-ponging" between two antenna positions.

[0073] As stated previously, this technique takes advantage of the current 802.11 antenna switched diversity methods. It should be understood that this first technique may include hardware, software/firmware or combinations thereof.

[0074] Referring now to FIG. 10, a flowchart of the above described method for operating an access point **110** in a WLAN **100** based upon spatial diversity will be discussed. From the start (Block **1000**), the method comprises communicating with the remote station **120**

using a current angle of the directional antenna **220b** at Block **1010**. Scanning through a plurality of alternate angles of the directional antenna **220b** for communicating with the remote station **120** during the preamble is performed at Block **1020**. Respective signals received via the current angle and the plurality of alternate angles from the remote station **120** are measured at Block **1030**. During the preamble, the current angle or one of the plurality of alternate angles is selected at Block **1040** as a preferred angle based upon the measured signals for continuing communications with the remote station **120**. The method ends at Block **105**.

[0075] The second technique is based upon the transmission by the access point **110** of RTS messages to the remote stations **120**, and the reception of CTS messages transmitted in response by the remote stations to the access point. The 802.11 standard also defines a probe request/probe response exchange, which is typically used by remote stations **120** to determine the quality of the link to other stations **120**.

[0076] When used by the access point **110** to determine the preferred pointing direction to a selected remote station **120**, as illustrated in FIG. 8, the access point **110** transmits a probe request signal **805** in the omni pattern and each of the potential directional patterns **130**, and measures the signal quality of the probe response signal **810** sent back from the remote station **110** while operating in the respective patterns.

[0077] Measurements of these response frames **810** make this a more reliable technique than the diversity

selection technique described above. This second technique is preferably employed at least once immediately after a remote station **120** has associated with the access point **110**. However, there is an impact to network efficiency using additional probe request/probe response signals, but these exchanges may be infrequent.

[0078] Referring now to FIG. 11, a flowchart of the above described method for operating an access point **110** in a WLAN **100** based upon probe signals will be discussed. From the start (Block **1100**), the method comprises selecting a remote station **120** at Block **1110**, transmitting a first probe signal via the omni angle of the directional antenna **220b** to the selected remote station at Block **1120**, and measuring a first probe response signal received via the omni angle from the selected remote station responding to the first probe signal at Block **1130**.

[0079] A respective second probe signal is transmitted at Block **1140** via each one of the plurality of directional angles of the directional antenna **220b** to the selected remote station **120**, and a second probe response signal received via each directional angle from the selected remote station responding to the respective second probe signal is measured at Block **1150**. The measured first probe response signal and the respective measured second probe response signals from the selected remote station **120** are stored in an antenna database at Block **1160**.

[0080] A preferred directional angle for the selected remote station **120** is selected at Block **1170** based upon the measured second probe response signals.

The measured first probe response signal from the omni angle is compared at Block **1180** with the measured second probe response signal from the preferred directional angle. The first probe signal comprises a request-to-send (RTS) message and the first probe response signal comprises a clear-to-send (CTS) message. Similarly, the second probe signal comprises an RTS message and the second probe response signal comprises a CTS message. The omni angle or the preferred directional angle is selected at Block **1190** based upon the comparing for continuing communications with the selected remote station **120**. The method ends at Block **1195**.

[0081] The third technique exploits the control frames used in normal data exchanges between the access point **110** and the remote stations **120**. This technique may be used in both forward link communications and reverse link communications. Since the clear-to-send (CTS) and acknowledge (ACK) messages are sent at the lower data rates, the access point **110** can use these messages to compare the omni pattern **905** to the currently selected directional pattern **130**. This is illustrated in FIG. 5A with the dashed lines on the antenna selection timing. This can serve as a method to determine whether the currently selected direction **130** has maintained its advantage over the omni-directional pattern **905**. This advantage is typically based upon a predetermined threshold to prevent frequent switching between two antenna patterns having similar signal quality metrics.

[0082] For example, during the CTS messages, the omni-directional mode may be used to receive this

message to calculate a first signal quality measurement. During the ACK message, a test antenna direction may be used to receive this message to calculate a second signal quality measurement. Comparison of the first and second signal quality measurements is performed and a determination is made as to whether the test antenna direction should be stored. That is, whether the directional mode provides a higher gain than omni-directional mode. Comparisons may also be performed between two different directional antenna directions.

[0083] The same types of measurements and comparisons may be conducted during a reverse link data transmission, as shown in FIG. 5B. During the ACK message, the access point **110** may calculate a signal quality measurement and compare it to an omni-directional mode measurement or other directional mode measurement. Comparisons may be conducted over several communications with the selected remote station **110** before scanning a different antenna direction.

[0084] The direction table **425** in FIG. 4 may be augmented with signal quality measurements from the process or processes described above for the omni and selected directional antenna pattern. If the advantage drops below a predetermined threshold, the access point **110** reverts back to the omni selection and performs an antenna search using one of the first two techniques described above.

[0085] In cases where the remote station **120** goes into a power-save mode or has long idle periods with no data transfers, the access point **110** reverts back to the omni pattern selection. When the remote station

120 becomes active again, the access point **110** may perform another antenna search.

[0086] Referring now to FIGS. 12 and 13, respective flowcharts of a method for operating an access point **120** in a WLAN **100** based upon control frames in forward and reverse links will be discussed. From the start (Block **1200**), the method comprises receiving in the forward link a first control frame via a first antenna pattern of the directional antenna **220b** from the remote station **120** at Block **1210**, and transmitting a first data frame to the remote station at Block **1220**, and receiving a second control frame via a second antenna pattern of the directional antenna from the remote station at Block **1230**. A signal quality of the first control frame received via the first antenna pattern and a signal quality of the second control frame received via the second antenna pattern are measured at Block **1240**. The respective measured signal qualities associated with the first and second antenna patterns are compared at Block **1250**. The second antenna pattern for transmitting a second data frame to the remote station **120** is selected at Block **1260** if the measured signal quality associated with the second antenna pattern exceeds the measured signal quality associated with the first antenna pattern by a predetermined threshold. The first control frame received comprises a clear-to-send message, and the second control frame received comprises an acknowledgement message. The method ends at Block **1270**.

[0087] The method for operating an access point **120** in a WLAN **100** based upon control frames in the reverse link comprises from the start (Block **1300**), receiving a

first control frame via a first antenna pattern of the directional antenna **220b** from the remote station at Block **1310**, transmitting a second control frame to the remote station at Block **1320**, and receiving a first data frame via a second antenna pattern of the directional antenna from the remote station at Block **1330**. A signal quality of the first control frame received via the first antenna pattern and a signal quality of the first data frame received via the second antenna pattern are measured at Block **1340**. The respective measured signal qualities associated with the first and second antenna patterns are compared at Block **1350**. The second antenna pattern for transmitting a second data frame by the access point **110** to the remote station **120** is selected at Block **1360** if the measured signal quality associated with the second antenna pattern exceeds the measured signal quality associated with the first antenna pattern by a predetermined threshold. The first control frame received comprises a request-to-send message, and the second control frame transmitted comprises a clear-to-send message. The method ends at Block **1370**.

[0088] The fourth techniques is a hidden node protection technique that provides a protection mechanism when employing a directional antenna **220b** at the access point **110** to reduce or eliminate the occurrence of hidden nodes. Hidden nodes occur when not all of the remote stations **120** in the network **100** can hear communications between the access point **110** and a selected remote station **120**, and therefore, those that cannot hear can transmit when the medium is in

use. This causes collisions, particularly at the access point **110**.

[0089] When the access point **110** has data for transmission to a remote station **120**, the control process sets the selected antenna direction by scanning the direction table **425** in FIG. 4 to determine if there are potential hidden nodes. For example, the access point **110** may look for remote stations **120** in the opposite direction from the selected antenna direction.

[0090] Referring to the timing diagram of FIG. 7, if the control software determines that a potential for hidden nodes exists, the access point **110** first transmits a CTS message to a known unused MAC address using the omni-directional mode of the antenna **220a**. This process serves to tell all of the remote stations **120** in the network that an exchange is to occur and not to transmit until the exchange is finished. The access point **110** then switches to the selected antenna direction for the intended remote station **120** and communications proceed. Another approach to preventing the hidden node problem is to perform a four-way frame exchange protocol (RTS, CTS, data and ACK) with a desired remote station **120**.

[0091] If the control software determines that there is no potential for a hidden node, the access point **110** may not send the CTS message and communications may start immediately with the access point **110** antenna set to the proper direction. If required by the network protocol, the RTS message can be addressed to the intended receiver, resulting in a CTS message back to the access point **110** as an acknowledgement, as shown in FIG. 5A.

[0092] Note that in the process described in reference to FIG. 7, efficiency is improved since the RTS message is not transmitted by the access point 110 since the CTS message is all that is necessary to cause the remote stations 120 to halt transmissions. The remote station 120 indicated in the ID section of the standard 802.11 protocol header ensures the specified remote station receives the data frame.

[0093] Referring now to FIG. 14, a flowchart for operating an access point 120 in a WLAN 100 based upon hidden node recognition will be discussed. From the start (Block 1400), the method comprises creating an antenna database by associating between the access point 110 and each remote station 120 a respective measured signal quality corresponding to the plurality of antenna patterns at Block 1410. The respective measured signal qualities are determined by the access point 110 based upon communications with each remote station 120. For each remote station 120 a preferred antenna pattern based upon the antenna database is determined at Block 1420, and a remote station and the corresponding preferred antenna pattern to communicate with are selected at Block 1430. Based upon the antenna database and prior to communicating with the selected remote station, it is determined at Block 1440 if any non-selected remote stations have the potential of not being aware when such communications actually occurs. This is determined by comparing the measured signal quality associated with the preferred antenna pattern for the selected remote station with the respective signal qualities associated with the non-selected remote stations when using the same preferred

antenna pattern.

[0094] If there is a potential for a hidden node, then a message is broadcast at Block **1450** indicating that the access point **110** and the selected remote station **120** are to communicate with one another. As noted above, this broadcast may be in the form of an unsolicited clear-to-send message via the omni antenna pattern to the remote stations **120**. The CTS has an unused address that does not correspond to any of the remote stations **120**. Alternatively, a four-way frame exchange protocol (RTS, CTS, data and ACK) is performed with the selected remote station **120** to prevent the hidden node problem. The method ends at Block **1460**.

[0095] While this invention has been particularly shown and described with references to preferred embodiments thereof, it will be understood by those skilled in the art that various changes in form and details may be made therein without departing from the scope of the invention encompassed by the appended claims. For instance, the access point is not limited to the IEEE 802.11 standard. The antenna algorithm for an access point as discussed above is applicable to other types of local area networks, as readily appreciated by those skilled in the art, such as those defined by the IEEE 802.16 standard.

THAT WHICH IS CLAIMED IS:

1. A method for operating an access point in a wireless local area network (WLAN), the access point comprising a directional antenna for communicating in a forward link with at least one remote station based upon an exchange of packet data comprising a plurality of control frames and a data frame, the directional antenna comprising a plurality of antenna patterns, the method comprising:

receiving a first control frame via a first antenna pattern of the directional antenna from the at least one remote station;

transmitting a first data frame to the at least one remote station;

receiving a second control frame via a second antenna pattern of the directional antenna from the at least one remote station;

measuring a signal quality of the first control frame received via the first antenna pattern and a signal quality of the second control frame received via the second antenna pattern; and

comparing the respective measured signal qualities associated with the first and second antenna patterns.

2. A method according to Claim 1 further comprising selecting the second antenna pattern for transmitting a second data frame to the at least one remote station if the measured signal quality associated with the second antenna pattern exceeds the

measured signal quality associated with the first antenna pattern by a predetermined threshold.

3. A method according to Claim 1 wherein transmitting the first data frame is performed using a preferred antenna pattern of the directional antenna; and wherein the comparing further comprises comparing the respective measured signal qualities associated with the first and second antenna patterns with a signal quality associated with the preferred antenna pattern.

4. A method according to Claim 3 further comprising selecting the second antenna pattern for transmitting a second data frame to the at least one remote station if the measured signal quality associated with the second antenna pattern exceeds the measured signal qualities associated with the first and preferred antenna patterns by a predetermined threshold.

5. A method according to Claim 1 wherein the first antenna pattern comprises an omni angle, and the second antenna pattern comprises a directional angle.

6. A method according to Claim 1 wherein the first antenna pattern comprises a first directional angle, and the second antenna pattern comprises a second directional angle.

7. A method according to Claim 1 wherein the first control frame received comprises a clear-to-send message, and the second control frame received comprises an acknowledgement message.

8. A method according to Claim 1 further comprising creating an antenna database including the respective measured signal qualities associated with the first and second antenna patterns.

9. A method according to Claim 1 further comprising selecting the first antenna pattern and the second antenna pattern, and wherein the selecting are performed at the media access control (MAC) layer of the access point.

10. A method according to Claim 1 wherein measuring the respective signal qualities comprises determining at least one of a received signal strength indication, a carrier to interference ratio, an energy per bit ratio and a signal to noise ratio.

11. A method according to Claim 1 wherein the access point is operating based upon at least one of an IEEE 802.11 standard and an IEEE 802.16 standard.

12. A method according to Claim 1 wherein the directional antenna comprises at least one active element and a plurality of passive elements.

13. A method for operating an access point in a wireless local area network (WLAN), the access

point comprising a directional antenna for communicating with at least one remote station in a reverse link based upon an exchange of packet data comprising a plurality of control frames and a data frame, the directional antenna comprising a plurality of antenna patterns, the method comprising:

receiving a first control frame via a first antenna pattern of the directional antenna from the at least one remote station;

transmitting a second control frame to the at least one remote station;

receiving a first data frame via a second antenna pattern of the directional antenna from the at least one remote station;

measuring a signal quality of the first control frame received via the first antenna pattern and a signal quality of the first data frame received via the second antenna pattern; and

comparing the respective measured signal qualities associated with the first and second antenna patterns.

14. A method according to Claim 13 further comprising selecting the second antenna pattern for transmitting a second data frame by the access point to the at least one remote station if the measured signal quality associated with the second antenna pattern exceeds the measured signal quality associated with the first antenna pattern by a predetermined threshold.

15. A method according to Claim 13 wherein the first antenna pattern comprise an omni angle, and

the second antenna pattern comprises a directional angle.

16. A method according to Claim 13 wherein the first antenna pattern comprises a first directional angle, and the second antenna pattern comprises a second directional angle.

17. A method according to Claim 13 wherein the first control frame received comprises a request-to-send message, and the second control frame transmitted comprises a clear-to-send message.

18. A method according to Claim 13 further comprising creating an antenna database including the respective measured signal qualities associated with the first and second antenna patterns.

19. A method according to Claim 13 wherein the directional antenna comprises at least one active element and a plurality of passive elements.

20. An access point for a wireless local area network (WLAN) comprising:

a directional antenna comprising a plurality of antenna patterns; and

a controller connected to said directional antenna for control thereof, said controller communicating with at least one remote station in a forward link based upon an exchange of packet data comprising a plurality of control frames and a data frame, said controller

receiving a first control frame via a first antenna pattern of said directional antenna from the at least one remote station,

transmitting a first data frame to the at least one remote station,

receiving a second control frame via a second antenna pattern of said directional antenna from the at least one remote station,

measuring a signal quality of the first control frame received via the first antenna pattern and a signal quality of the second control frame received via the second antenna pattern, and

comparing the respective measured signal qualities associated with the first and second antenna patterns.

21. An access point according to Claim 20 wherein said directional antenna comprises at least one active element and a plurality of passive elements.

22. An access point according to Claim 20 wherein said controller selects the second antenna pattern for transmitting a next data frame to the at least one remote station if the measured signal quality associated with the second antenna pattern exceeds the measured signal quality associated with the first antenna pattern by a predetermined threshold.

23. An access point according to Claim 20 wherein transmitting the data frame is performed by

said controller using a preferred antenna pattern of said directional antenna; and wherein the comparing by said controller further comprises comparing the respective measured signal qualities associated with the first and second antenna patterns with a signal quality associated with the preferred antenna pattern.

24. An access point according to Claim 23 wherein said controller selects the second antenna pattern for transmitting a second data frame to the at least one remote station if the measured signal quality associated with the second antenna pattern exceeds the measured signal qualities associated with the first and preferred antenna patterns by a predetermined threshold.

25. An access point according to Claim 20 wherein the first antenna pattern comprise an omni angle, and the second antenna pattern comprises a directional angle.

26. An access point according to Claim 20 wherein the first antenna pattern comprise a first directional angle, and the second antenna pattern comprises a second directional angle.

27. An access point according to Claim 20 wherein the first control frame received comprises a clear-to-send message, and the second control frame transmitted comprises an acknowledgement message.

28. An access point according to Claim 20 wherein said controller creates an antenna database including the respective measured signal qualities associated with the first and second antenna patterns, and stores the antenna database.

29. An access point according to Claim 20 wherein said controller comprises a physical layer and a media access control (MAC), and selection of the first antenna pattern and the second antenna pattern are performed at the MAC layer.

30. An access point according to Claim 20 wherein said controller measures the respective signal qualities based upon determining at least one of a received signal strength indication, a carrier-to-interference ratio, an energy-per-bit ratio and a signal-to-noise ratio.

31. An access point for a wireless local area network (WLAN) comprising:

a directional antenna comprising a plurality of antenna patterns; and

a controller connected to said directional antenna for control thereof, said controller communicating with at least one remote station in a reverse link based upon an exchange of packet data comprising a plurality of control frames and a data frame, said controller

receiving a first control frame via a first antenna pattern of said directional antenna from the at least one remote station,

transmitting a second control frame to the at least one remote station,
receiving a first data frame via a second antenna pattern of said directional antenna from the at least one remote station,
measuring a signal quality of the first control frame received via the first antenna pattern and a signal quality of the first data frame received via the second antenna pattern, and
comparing the respective measured signal qualities associated with the first and second antenna patterns.

32. An access point according to Claim 31 wherein said directional antenna comprises at least one active element and a plurality of passive elements.

33. An access point according to Claim 31 wherein said controller selects the second antenna pattern for transmitting a second data frame to the at least one remote station if the measured signal quality associated with the second antenna pattern exceeds the measured signal quality associated with the first antenna pattern by a predetermined threshold.

34. An access point according to Claim 31 wherein the first antenna pattern comprise an omni angle, and the second antenna pattern comprises a directional angle.

35. An access point according to Claim 31 wherein the first antenna pattern comprise a first directional angle, and the second antenna pattern comprises a second directional angle.

36. An access point according to Claim 31 wherein the first control frame received comprises a request-to-send message, and the second control frame transmitted comprises a clear-to-send message.