

Description

This invention relates to a tone signal generation device suitable for simulating a damper pedal effect of a piano or the like musical instrument.

US-A-4 383 462 discloses an electronic musical instrument capable of generating a tone with a piano tone color is one in which a tone of a piano in a damper pedal (loud pedal) OFF state is picked up and stored in a memory and a tone waveform thus stored in this memory is subsequently read out to generate a tone with a piano tone color.

It is known that, in this type of electronic musical instrument, the envelope of a tone which is being produced is controlled in such a manner that, when a damper pedal attached to the instrument is not ON, the tone is attenuated fast upon key-off whereas when the damper pedal is ON, the tone is attenuated gradually.

In the above described prior art electronic musical instrument, it is not possible to simulate an impression of expansion of a tone which is peculiar to a piano tone being played in a damper pedal ON state. When a piano is played in the damper pedal ON state in which the damper is released from strings of all piano keys, strings other than a string which has been struck by a hammer vibrate due to resonance with resulting generation of an acoustic effect which imparts the impression of expansion to the tone being played. In the prior art electronic musical instrument, however, pressing of the damper pedal into an ON state brings about change in the envelope shape of a depressed key only and fails to produce such acoustic effect of tone expansion.

US-A-4 067 253 describes a tone-generating system for an electronic musical instrument, comprising a damper pedal to resemble the expanding effect of a natural piano. The damper pedal is coupled to a switch which, upon actuation of the damper pedal, causes a damper circuit to produce a damper control signal which is applied to a variable rate clock for changing the control clock signal applied to an envelope control counter. Accordingly, upon actuation of the damper pedal, the counting rate of the envelope control counter is decreased so that the tone produced is damped less and, therefore, produced as a sustained tone. However, only the shape of the envelope is changed according to the actuation of the damper pedal. This does not cause the same effect as in case of a natural piano.

A tone signal generation device capable of producing a reverberation effect in response to a key depression is disclosed in JP-A-60-68 387. In this electronic musical instrument, normal waveshape data are read out from a normal waveshape memory and reverberation data are

read out from a reverberation waveshape memory. Normal envelope shape data and reverberation envelope shape data having smaller peak levels and longer decay times are generated respectively. Both envelope data are intermixed. The reverberation waveshape memory stores a waveshape having a fixed characteristics. The reverberation effect of this electronic musical instrument varies only with the tone pitch of the normal tone but not with the frequency spectrum of the normal tone.

A tone signal generation device having the features of the precharacterizing part of claim 1 is disclosed in EP 0 167 847. This device comprises a waveshape memory storing the waveshape of a tone. The tone waveshape signal obtained by reading this waveshape memory is applied to a tone colour circuit where its tone colour is changed. The tone wave signal whose tone colour has been changed and the tone wave signal whose tone colour has not been changed are both multiplied with respective coefficients whereby these tone wave signals are weighted. The weighted tone wave signals are added together to provide a mixed tone signal. The coefficients for the tone colour control may be provided in accordance with the operation states of control knobs. With this instrument, tone signals exhibiting a variety of tone colour changes may be obtained by using only one waveshape memory. A damper pedal effect is not disclosed.

It is an object of the invention to obtain an acoustic effect imparting the impression of expansion of a tone similar to the one obtained by playing a piano in the damper pedal ON state.

This object is solved by the features of claim 1.

In such construction, one value and another value of the detection output may be used as values corresponding to the presence and absence of operation of the operator and an amplitude level of the resonance tone information in the output means may be gradually increased from start of operation of the operator.

The detection means may generate a detection output in accordance with the amount of operation of the operator while first and second level control means may be provided in lieu of the output means. In this case, the first level control means controls the level of the read out output of waveform information in one direction (e.g., decreasing direction) in accordance with increase of the amount of operation exhibited by the detection output whereas the second level control means controls the amplitude level of the resonance tone information in a direction which is opposite to the one direction (e.g., increasing direction) in accordance with increase in the amount of operation exhibited by the detection output. The outputs of the first and second level control means are deliv-

ered out as the first and second tone signals.

According to the invention, a desired tone can be generated in accordance with stored waveform information during a non-operation mode of the operator and a tone imparting the impression of expansion can be generated in accordance with resonance tone information during operation of the operator whereby the damper pedal effect of a piano or the like musical instrument can be simulated with high fidelity.

By gradually increasing the amplitude level of resonance tone information from start of the operation of the operator, the gradually increasing expansion of a tone due to resonance caused by releasing of a damper from strings of a piano occurring when the damper pedal is pressed ON in the piano can be simulated.

Further, as described above, by changing the level of the read out output of waveform information and the amplitude level of resonance tone information in opposite directions in accordance with increase in the amount of operation of the operator, the impression of expansion of a tone can be controlled as desired within an operable range of the operator.

The tone signal generation device according to the invention comprises memory means for storing first waveform information corresponding to a waveform of a desired tone and second waveform information corresponding to a mixed waveform of the tone and a resonance tone thereof, the operator, the detection means, and tone signal generation means for generating a first tone signal in accordance with the first waveform information when the detection output exhibits one value and second tone signal in accordance with the second waveform information when the detection output exhibits another value.

As the first and second waveform information, data representing a tone waveform in a damper pedal OFF state and data representing a tone waveform in a damper pedal ON state respectively picked up from a piano, for example, may be employed.

As the tone generation means, there may be employed one which comprises readout means for reading out the first waveform information and the second waveform information in parallel from the memory means at a desired speed, and selection means for selecting the read out output of the first waveform information and delivering it out as the first tone signal when the operator is not operated and selecting the read out output of the second waveform information and delivering it out as the second tone signal when the operator is operated, the selection means gradually decreasing the level of the read out output of the first waveform information from start of operation of the operator

while gradually increasing the level of the read out output of the second waveform information.

When the readout means is provided, the detection means may generate a detection output in accordance with an amount of operation of the operator and there may be provided first level control means for controlling the level of the read out output of the first waveform information for changing it in one direction in accordance with increase in the amount of operation exhibited by the detection output and second level control means for controlling the level of the read out output of the second waveform information for changing it in a direction which is opposite to the one direction in accordance with increase in the amount of operation exhibited by the detection output, and the outputs of the first and second level control means may be delivered out as the first and second tone signals.

According to the invention, a desired tone can be generated in accordance with the first waveform information when the operator is not operated while a tone including a resonance tone and thereby imparting an impression of expansion of a the tone is generated in accordance with the second waveform information when the operator is operated whereby the damper pedal effect of a piano or the like musical instrument can be simulated with high fidelity.

Further, by gradually decreasing the level of the read out output of the first waveform information and gradually increasing the level of the read out output of the second waveform information from start of operation of the operator, the gradually increasing expansion of a tone due to resonance caused by releasing of a damper from strings of a piano occurring when the damper pedal is pressed ON in the piano can be simulated.

Further, as described above, by changing the level of the read out outputs of the first and second waveform information in accordance with increase in the amount of operation of the operator in opposite directions, the feeling of expansion of a tone can be controlled as desired within an operable range of the operator.

The electronic musical instrument according to the invention comprises tone pitch designation means for designating a tone pitch of a tone to be generated, tone signal generation means for generating a tone signal in accordance with the tone pitch designated by the tone pitch designation means, an operator for controlling a tone, and resonance tone adding means responsive to operation of the operator for adding a resonance tone to the tone signal to be generated by the tone signal generation means.

When the operator is operated, a resonance tone is added to a tone signal by the resonance

tone adding means. A tone including a resonance tone and imparting an impression of expansion of the tone can be generated.

In this electronic musical instrument, in a known manner, envelope switching means may be further provided for switching a decay rate of amplitude envelope of the tone signal to be generated by the tone signal generation means.

With reference to the accompanying drawings, embodiments of the invention will be described.

In the accompanying drawings,

Fig. 1 is a block diagram showing a circuit construction of an electronic musical instrument not incorporating the invention;

Fig. 2 is a waveform diagram showing an example of a piano tone waveform;

Fig. 3 is a signal waveform diagram for explaining the envelope shape generation operation;

Fig. 4 is a signal waveform diagram for explaining the cross-fade control operation;

Fig. 5 is a circuit diagram showing an example of a resonance tone generation circuit;

Figs. 6 and 7 are block diagrams showing the second and third embodiments and

Fig. 8 is a block diagram showing a circuit construction of an electronic musical instrument incorporating the invention.

Circuit Construction of the Electronic Musical Instrument (Fig. 1)

Fig. 1 shows a circuit construction of an electronic musical instrument not incorporating the invention. This electronic musical instrument is so constructed that it can produce plural tones simultaneously by a time division multiplexing processing in plural channels (e.g., eight channels).

Keys of a keyboard 12 are divided into plural groups each consisting of, e.g., keys of half octave (six keys) and waveform data for one key representing each group is stored in a waveform memory 10 with respect to respective levels of key touch strength in plural stages (e.g., three levels of "weak", "middle" and "strong"). The reason for storing waveform data for each key group is that a key scaling control can thereby be performed for producing different tone elements such as different tone colors depending upon the key group. The reason for storing waveform data for each key touch strength level is that a touch response control can thereby be performed for producing different tone color, tone volume or the like depending upon the key touch strength level.

Each waveform data stored in the waveform memory 10 is obtained, for example, by picking up a tone from a piano (as a natural musical instrument) being played in a damper pedal (i.e., loud pedal) OFF state, sampling its tone waveform at a

predetermined time interval and converting amplitude values at respective sample points to digital data (i.e., PCM recording). In actual recording, piano keys are divided into groups in correspondence to key groups of the keyboard 12 of Fig. 1, one key representing each group is played at different touch levels of weak, middle and strong touches in a damper pedal OFF state to produce piano tones and waveform data for each tone is written in the waveform memory 10 by the PCM recording.

Fig. 2 shows an example of a waveform of a picked up piano tone. In the waveform memory 10, waveform data for a section W1 + W2 from rising of the tone to some point of decay thereof for each tone is written, the portion of decay after W2 being discarded. In reading out waveform data from the waveform memory 10, the waveform data from W1 to W2 is read out first and then the waveform data of W2 is repeatedly read out.

In storing data in the waveform memory 10, the amplitude level of each picked up tone waveform may be standardized to a constant level L0, e.g., maximum level, as shown in Fig. 2 and this standardized level may be stored in the waveform memory 10. By this arrangement, the amplitude value can be expressed digitally with high precision even in a low amplitude portion. Since an amplitude envelope is imparted by envelope imparting means 22 and 24 as will be described later, no adverse effect will be produced by adopting such arrangement.

A depressed key detection and key assigning circuit 14 detects a depressed key in the keyboard 12 and assigns key code data KC representing the key code (i.e., tone pitch) of the detected key and a key-on signal KON indicating that there is a depressed key to one of empty channels so that they are provided at the timing of this channel.

A touch detection circuit 16 detects which level among the weak, middle and strong levels the key touch strength of the depressed key in the keyboard 12 corresponds to and provides touch level data TD representing the detected touch level in synchronism with the timing of the channel to which the key code KC and the key-on signal KON have been assigned.

As described above, the circuits 14 and 16 are operated on a time shared basis and posterior circuits responsive to outputs of these circuits 14 and 16 are also operated on a time shared basis. For convenience of explanation, however, an operation for one channel only will be described below.

A waveform selection control circuit 18 generates waveform designation data WS in response to the key code data KC and the touch level data TD. In the waveform memory 10, a waveform to be read out is designated in response to the waveform

designation data WS. If, for example, a key code represented by the key code data KC belongs to the first key group, waveform data corresponding to the touch level data TD among waveform data belonging to the first key group is designated for reading.

An address signal generation circuit 20 generates an address signal AD in response to the key code data KC and the key-on signal KON. The waveform data which has been designated by the waveform designation data WS is read out from the waveform memory 10 in response to the address signal AD. In this case, the designation of address by the address signal AD is performed at a speed corresponding to the key code (tone, pitch) represented by the key code data KC and the tone pitch of the generated tone is determined in accordance with this reading speed. For plural keys belonging to the same key group, the same waveform data is read out at different reading speeds for the respective keys so long as the keys are depressed at a constant key touch level.

The waveform data WD read out from the waveform memory 10 is supplied to a multiplier 22 in which it is multiplied with envelope shape data ED.

An envelope signal generation circuit 24 generates envelope shape data ED in response to the key-on signal KON in such a manner that different envelope shapes are produced depending upon whether a damper pedal signal DP is "0" or "1" as shown in Fig. 3. The damper pedal signal DP is detected from a damper pedal 26 through a switch or the like means. When the damper pedal 26 is OFF and the signal DP = "0", the envelope shape decays gradually after rising and decays rapidly after key-off. When the damper pedal 26 is ON and the signal DP = "1", the envelope shape decays gradually even after key-off. Parameters such as attack time, attack level, decay time etc. of the envelope shape are controlled key group by key group in response to the key code data KC and also controlled touch level by touch level in response to the touch level data TD.

As a result of multiplication in the multiplier 22, waveform data EWD imparted with an envelope shape in accordance with tone pitch, touch response and damper pedal state is provided and this waveform data EWD is supplied to an accumulator 28.

The accumulator 28 is provided for mixing waveform data for plural channels. Its output waveform data SWD is supplied to a multiplier 30A in which it is multiplied with a cross-fade control signal CF1. The waveform data SWD is supplied also to a resonance tone generation circuit 32 in which it is converted to resonance tone data RWD. The resonance tone data RWD from the resonance

tone generation circuit 32 is supplied to a multiplier 30B in which it is multiplied with a cross-fade control signal CF2.

The resonance tone generation circuit 32 is constructed, e.g., as shown in Fig. 5, of digital delay circuits 31 (shown by square blocks), coefficient multipliers 33 (shown by triangular blocks) and adders 35 (shown by circular blocks with "+" signs therein). By properly determining delay amounts D11 - D1n in a delay circuit group DIL receiving an input signal IN, coefficients a11 - a1n, delay amounts D21 - D2n in a comb-filter group CFL and coefficients a21 - a2n, a digital signal having a resonance or reverberation effect can be obtained as an output signal OUT. Accordingly, by inputting the waveform data SWD as the input signal IN, tone waveform data imparting an impression of expansion of a tone which is similar to a tone produced when a damper pedal is ON, i.e., resonance tone data, can be obtained as the output signal OUT.

A cross-fade control signal generation circuit 34 generates the cross-fade control signals CF1 and CF2 in response to the damper pedal signal DP. An example of the cross-fade control signals is shown in Fig. 4. The cross-fade control signal CF1 is generated in such a manner that its level falls gradually from maximum value 1 to minimum value 0 taking about one second when the damper pedal signal DP has been turned from "0" to "1" (i.e., the damper pedal 26 has been turned ON from the OFF state), maintains the minimum value "0" as long as the signal DP maintains "1" and rises from the minimum value "0" to the maximum value "1" taking about 0.2 second when the signal DP has been turned from "1" to "0" (i.e., the damper pedal 26 has been turned OFF from the ON state). The cross-fade control signal CF2 is generated in the form of inverted cross-fade control signal CF1.

The above described arrangement in which the level changes more gradually when the damper pedal 26 is turned ON from the OFF state than when it is turned OFF from the ON state is convenient for simulating the increasing expansion of a tone due to resonance occurring when the damper has been released from all strings in playing a piano.

As a result of multiplications in the multipliers 30A and 30B, the waveform SWD is supplied to an adder 36 when the damper pedal 26 is OFF whereas the resonance tone data RWD is supplied to the adder 36 when the damper pedal 26 is ON. In this case, during the periods of about one second and about 0.2 second shown in Fig. 4, there is provided mixed data of the data SWD and RWD which are mixed in the adder 36 at a mixing ratio determined by the values of the cross-fade control signals CF1 and CF2.

The waveform data as the output of the adder 36 is supplied to a sound system 38 including a digital-to-analog converter, an amplifier and loudspeakers and is sounded therefrom as a tone.

The Second Embodiment (Fig. 6)

Fig. 6 shows the second embodiment in which the resonance tone adding portion used in the circuit of Fig. 1 is modified. In Fig. 6, the same component parts as in Fig. 1 are designated by the same reference characters.

The second embodiment which is a modification of the embodiment of Fig. 1 is different from the embodiment of Fig. 1 in the following two points. Firstly, waveform data SWD from the accumulator 28 is supplied to the adder 36 without passing through the multiplier 30A. Secondly, the multiplier 30B is provided in a prior stage to the resonance tone generation circuit 32. In this case, a similar signal to the cross-fade control signal CF2 of Fig. 4 is supplied as a level control signal LC to the multiplier 30B.

In this construction, waveform data SWD is obtained as the output of the adder 36 when the damper pedal 28 is OFF. When the damper pedal 26 is ON, the waveform data SWD is supplied to the resonance tone generation circuit 32 through the multiplier 30B so that the resonance tone data RWD is provided from the circuit 32. Accordingly, mixed data of the waveform data SWD and the resonance tone data RWD is supplied as the output of the adder 36. In this case, during the periods of about one second and about 0.2 second shown in Fig. 4, the mixing ratio of the resonance tone data RWD to the waveform data SWD is controlled in response to the level control signal LC (corresponding to the cross-fade control signal CF2).

According to the construction of Fig. 6, when a desired key is depressed in the damper pedal ON state, waveform data which is a mixture of waveform data having the tone pitch corresponding to the depressed key and resonance tone data generated on the basis of this waveform data is obtained. This waveform data has a greater ratio of tone component of the depressed key than in a case where, as shown in Fig. 1, resonance tone data alone is provided so that this construction is advantageous when it is desired to emphasize the tone of a depressed key. The multiplier 30B may be provided in a posterior stage to the resonance tone generation circuit 32.

The Third Embodiment (Fig. 7)

Fig. 7 shows the third embodiment of the invention in which the mixing ratio control portion used in the circuit of Fig. 1 is modified. The same

component parts as in Fig. 1 are designated by the same reference characters.

A feature of this embodiment is that a depression amount detection circuit 40 for detecting an amount of depression of the damper pedal 26 is provided and a detection output A of this detection circuit 40 is supplied to the multiplier 30B as a signal A2 instead of the cross-fade control signal CF2 while a signal A1 obtained by inverting the detection output A by an inverting circuit 42 (i.e., "1 - A") is supplied to the multiplier 30A instead of the cross-fade control signal CF1.

According to this construction, in the process of increasing of the value of the detection output A from the minimum value 0 to the maximum value 1 by depression of the damper pedal 26, the waveform data SWD from the accumulator 28 is controlled by the multiplier 30A to decrease in its amplitude level while the resonance tone data RWD from the resonance tone generation circuit 32 is controlled by the multiplier 30B to increase in its amplitude level. Thus, the adder 36 provides waveform data which is a mixture of the data SWD and RWD at a mixing ratio determined by the values of the signals A1 and A2. If the damper pedal 26 is not depressed, the adder 36 provides the waveform data SWD and, if the damper pedal 26 is depressed most deeply, the adder 36 provides the resonance tone data RWD.

According to the construction of Fig. 7, the performer can set the mixing ratio of the waveform data SWD and the resonance tone data RWD as desired by properly adjusting the amount of depression of the damper pedal 26 whereby a tone color change can be obtained in addition to the damper pedal ON/OFF effect as described with reference to Fig. 1.

Circuit Construction of Electronic Musical Instrument of the Invention (Fig. 8)

Fig. 8 shows a circuit construction of an embodiment of the electronic musical instrument according to the invention. In the same manner as in the above described embodiment, this electronic musical instrument can produce plural tones simultaneously by a time division multiplexing processing in plural channels (e.g., eight channels). In Fig. 8, the same component parts as in Fig. 1 are designated by the same reference characters.

A damper pedal OFF waveform memory 10A is of a similar construction to the waveform memory 10 in Fig. 1, storing waveform data for each key group in a damper pedal OFF state with respect to each of plural stages of touch levels.

A damper pedal ON waveform memory 10B stores waveform data sampled from a piano as a natural musical instrument for each key group with

respect to each of plural stages of touch levels in the same manner as in the waveform memory 10A except that the damper pedal is not in an OFF state but in an ON state. Since a key has been depressed in the damper pedal ON state in this case, each waveform data represents a mixed waveform of a tone produced by vibration of a string corresponding to the depressed key and tones produced by vibration of other strings due to resonance.

In the same manner as in the above described embodiment, in the waveform memories 10A and 10B, a waveform to be read out is designated in response to waveform designation data WS from the waveform selection control circuit 18.

In the same manner as in the above described embodiment, waveform data designated by the waveform designation data WS are read out in parallel from the waveform memories 10A and 10B in response to the address signal AD from the address generation circuit 20.

The waveform data WD read out from the waveform memory 10A is supplied to a multiplier 21A in which it is multiplied with the cross-fade control signal CF1. The waveform data WDB read out from the waveform memory 10B is supplied to a multiplier 21B in which it is multiplied with the cross-fade control signal CF2.

The cross-fade control signals CF1 and CF2 are, in the same manner as in the above described embodiment, generated by the cross-fade control signal generation circuit 34. An example of these cross-fade control signals are shown in Fig. 4.

As a result of multiplications in the multipliers 21A and 21b, the waveform data WDA is supplied to the adder 23 when the damper pedal 26 is OFF and the waveform data WDB is supplied to the adder 23 when the damper pedal 26 is ON. In this case, during the periods of about one second and about 0.2 second shown in Fig. 4, a mixture of the waveform data WDA and WDB which are mixed together by the adder 23 at a mixing ratio determined by values of the cross-fade control signals CF1 and CF2.

The waveform data as the output of the adder 23 is supplied to a multiplier 25 in which it is multiplied with the envelope shape data ED which is generated from the envelope shape generation circuit 24 as shown in Fig. 3.

As a result of the multiplication in the multiplier 25, waveform data EWD which has been imparted with envelope in accordance with tone pitch, touch level and damper pedal state is obtained. This waveform data EWD is supplied to the sound system 38.

In the embodiment of Fig. 8 also, the construction of the mixing ratio control portion can be modified as shown in Fig. 7. In this case, the

output A2 of the depression amount detection circuit 40 is applied to the multiplier 21B instead of the cross-fade control signal CF2 and the output A1 of the inversion circuit 42 is applied to the multiplier 21A instead of the cross-fade control signals CF1. By this arrangement, in the same manner as in the above described embodiment, the performer can set the mixing ratio of the waveform data WDB including resonance tone to the waveform data WDA as desired by properly adjusting the amount of depression of the damper pedal 26 whereby a tone color change according to the mixing ratio can be obtained in addition to the damper pedal ON/OFF effect shown in Fig. 8.

Modifications

The present invention is not limited to the above described embodiments but can be carried out in various other forms. For example, the following modifications are possible:

(1) As to storing and reading of tone waveforms, as shown in US-P 4,633,749, a waveform of plural periods of attack portion and subsequent several segment waveforms (partial waveforms) may be stored in a memory and the waveform of plural periods of the attack portion may be read out and then the segment waveforms may be read out, performing a smooth interpolation between them.

(2) As to recording and reproducing of a tone, a system by which data compression is possible may be employed. Such system includes, for example, a differential pulse code modulation (DPCM) system, an adaptive differential pulse code modulation (ADPCM) system, a delta modulation (DM) system, an adaptive delta modulation (ADM) system, a linear predictive coding (LPC) system or a combination of these systems (e.g., combination of LPC and ADPCM).

(3) As to controlling of touch response and key scaling, a system of processing data read out from a waveform memory by a digital filter as disclosed by US-P 4,738,179 or a system of controlling a mixing ratio of data read out from two waveform memories as disclosed by Japanese Preliminary Patent Publication No. 60-55398, for example, may be employed.

(4) In the above described embodiments, waveform data designated by the waveform selection control circuit 18 is read out in response to the address signal from the address generation circuit 20. Alternatively, the function of the waveform selection control circuit 18 may be provided to the address signal generation circuit 20.

(5) This invention is applicable also to a monophonic electronic musical instrument.

(6) In the above described embodiments, a piano tone is employed. The invention is applicable also to other tone colors.

(7) In the embodiment of Fig. 1, read out waveform data for plural channels are mixed by the accumulator 28 and thereafter are supplied to the resonance tone generation circuit 32. Alternatively, a resonance tone generation circuit may be provided independently for each channel and read out waveform data of a corresponding channel may be supplied to each resonance tone generation circuit. In this case, in each resonance tone generation circuit, it is preferably to properly control internal connection, coefficients etc. in accordance with the tone pitch.

(8) the cross-fade control as shown in the embodiment of Fig. 1 may be omitted and the read out waveform data and the resonance tone data may be simply switched.

(9) In the embodiment of Fig. 1, tone signals of two systems consisting of the read out waveform data and the resonance tone data may be supplied to separate sound systems and sounded after being mixed in space instead of being sounded from a single sound system after mixing.

(10) In the embodiment of Fig. 8, in reading out the designated waveform data from the waveform memories 10A and 10B, these data may be read out on a time shared basis instead of being read out in parallel.

(11) The cross-fade control as shown in the embodiment of Fig. 8 may be omitted. In this case, the waveform memory 10A or 10B may be selected in response to the damper pedal signal DP and waveform data may be read out from the selected waveform memory.

(12) In the embodiment of Fig. 8, tone signals of two systems based on read out data from the waveform memories 10A and 10B may be supplied to separate sound systems and sounded after being mixed in space instead of being sounded from a single sound system after being mixed.

According to the invention, a desired tone or a resonance tone corresponding to this tone can be generated as desired and, accordingly, simulation of a damper pedal effect as in a piano can be achieved with high fidelity.

By performing the cross-fade control so that the amplitude level of resonance tone data increases gradually from start of operation of the operator as shown in the embodiment of Fig. 1 or Figs. 6 and 8, a closer simulation of the damper pedal effect can be realized.

By controlling the mixing ratio of tone signals of two systems in accordance with the operation

amount of the operator as shown in the embodiment of Fig. 7, the feeling of expansion of a tone can be controlled as desired.

Claims

1. A tone signal generation device comprising:
 - pitch designation means (12) for designating a pitch of a tone to be generated;
 - tone generation means (10A) for generating waveform information corresponding to a waveform of a desired tone in accordance with a pitch designated by the pitch designation means (12), said tone generation means (10A) comprising:
 - a) memory means (10A) for storing the waveform information corresponding to the desired tone waveform; and
 - b) reading means (20) for reading out the waveform information (WDA) from said memory means in accordance with a pitch designated by the pitch designation means;
 - operator means (26) that is operable independently of the pitch designation means;
 - detection means for detecting the state of operation of said operator means (26) and delivering out a detection output indicative of the state of operation of said operator means; and
 - output means (21A, 21B, 23) for outputting the waveform information (WDA) as a first tone signal and as a second tone signal in response to said detection output;

characterized in that it further comprises:

 - memory means (10B) for storing resonance tone waveform information (WDB) corresponding to a mixed waveform of the desired tone and the resonance tone thereof; and
 - reading means (20) for reading out the resonance tone waveform information (WDB) from said memory means (10B) in accordance with a pitch designated by the pitch designation means (12), said second tone signal being said resonance tone waveform information (WDB).
2. A tone signal generation device as defined in claim 1, which further comprises cross-fade control means (34) for performing such a control that the waveform information (WDA) and the resonance tone information (WDB) are output in cross-fade manner when said operator means (26) has been operated.
3. A tone signal generation device as defined in claim 1, which further comprises control means for performing such a control that, when said operator means (26) has been operated, the resonance tone information (WDB) to be output



(6) In the above described embodiments, a piano tone is employed. The invention is applicable also to other tone colors.

(7) In the embodiment of Fig. 1, read out waveform data for plural channels are mixed by the accumulator 28 and thereafter are supplied to the resonance tone generation circuit 32. Alternatively, a resonance tone generation circuit may be provided independently for each channel and read out waveform data of a corresponding channel may be supplied to each resonance tone generation circuit. In this case, in each resonance tone generation circuit, it is preferably to properly control internal connection, coefficients etc. in accordance with the tone pitch.

(8) the cross-fade control as shown in the embodiment of Fig. 1 may be omitted and the read out waveform data and the resonance tone data may be simply switched.

(9) In the embodiment of Fig. 1, tone signals of two systems consisting of the read out waveform data and the resonance tone data may be supplied to separate sound systems and sounded after being mixed in space instead of being sounded from a single sound system after mixing.

(10) In the embodiment of Fig. 8, in reading out the designated waveform data from the waveform memories 10A and 10B, these data may be read out on a time shared basis instead of being read out in parallel.

(11) The cross-fade control as shown in the embodiment of Fig. 8 may be omitted. In this case, the waveform memory 10A or 10B may be selected in response to the damper pedal signal DP and waveform data may be read out from the selected waveform memory.

(12) In the embodiment of Fig. 8, tone signals of two systems based on read out data from the waveform memories 10A and 10B may be supplied to separate sound systems and sounded after being mixed in space instead of being sounded from a single sound system after being mixed.

According to the invention, a desired tone or a resonance tone corresponding to this tone can be generated as desired and, accordingly, simulation of a damper pedal effect as in a piano can be achieved with high fidelity.

By performing the cross-fade control so that the amplitude level of resonance tone data increases gradually from start of operation of the operator as shown in the embodiment of Fig. 1 or Figs. 6 and 8, a closer simulation of the damper pedal effect can be realized.

By controlling the mixing ratio of tone signals of two systems in accordance with the operation

amount of the operator as shown in the embodiment of Fig. 7, the feeling of expansion of a tone can be controlled as desired.

Claims

1. A tone signal generation device comprising:
 - pitch designation means (12) for designating a pitch of a tone to be generated;
 - tone generation means (10A) for generating waveform information corresponding to a waveform of a desired tone in accordance with a pitch designated by the pitch designation means (12), said tone generation means (10A) comprising:
 - a) memory means (10A) for storing the waveform information corresponding to the desired tone waveform; and
 - b) reading means (20) for reading out the waveform information (WDA) from said memory means in accordance with a pitch designated by the pitch designation means;
 - operator means (26) that is operable independently of the pitch designation means;
 - detection means for detecting the state of operation of said operator means (26) and delivering out a detection output indicative of the state of operation of said operator means; and
 - output means (21A, 21B, 23) for outputting the waveform information (WDA) as a first tone signal and as a second tone signal in response to said detection output;

characterized in that it further comprises:

 - memory means (10B) for storing resonance tone waveform information (WDB) corresponding to a mixed waveform of the desired tone and the resonance tone thereof; and
 - reading means (20) for reading out the resonance tone waveform information (WDB) from said memory means (10B) in accordance with a pitch designated by the pitch designation means (12), said second tone signal being said resonance tone waveform information (WDB).
2. A tone signal generation device as defined in claim 1, which further comprises cross-fade control means (34) for performing such a control that the waveform information (WDA) and the resonance tone information (WDB) are output in cross-fade manner when said operator means (26) has been operated.
3. A tone signal generation device as defined in claim 1, which further comprises control means for performing such a control that, when said operator means (26) has been operated, the resonance tone information (WDB) to be output



by the output means is gradually increased or decreased while the waveform information (WDA) is being output by the output means.

4. A tone signal generation device as defined in claim 1, which further comprises control means for performing such a control that, the waveform information (WDA) and the resonance tone information (WDB) are output in combination at a variable combination ratio corresponding to said detection output. 10
5. A tone signal generation device as defined in any one of claims 1 - 4, which further comprises envelope control means (24) for controlling an envelope of a tone generated in said tone signal generation device in response to said detection output. 15
6. A tone signal generation device as defined in any one of claims 1 - 5, wherein said detection means detects an ON/OFF state of operation of the operator means. 20
7. A tone signal generation device as defined in any one of claims 1 - 5, wherein said detection means detects an amount of operation of the operator means within a range from a minimum amount to a maximum amount. 25
8. A tone signal generation device as defined in claim 7, wherein said output means comprises:
 - first level control means (42, 21A) for controlling the amplitude level of the waveform information (WDA) to change it in accordance with a first changing characteristic corresponding to the detected amount by the detection means, and 30
 - second level control means (40, 21B) for controlling the amplitude level of the resonance tone information (WDB) to change it in accordance with a second changing characteristic corresponding to the detected amount by the detection means which is different from said first changing characteristic. 35
9. A tone signal generation device as defined in any one of claims 1 - 8 wherein said operator means comprises a damper pedal. 40
10. A tone signal generation device as defined in any one of claims 1 - 9, wherein one of said memory means (10A) stores said waveform information (WDA) having a feature of a tone waveform of a natural piano being played with non-activated damper pedal, and the other of said memory means (10B) stores said resonance tone waveform information (WDB) hav-

ing a feature of a tone waveform of a natural piano being played with activated damper pedal.

5 Patentansprüche

1. Tonsignalerzeugungsvorrichtung mit:
 - einer Tonhöhenbestimmungseinrichtung (12) zum vorgeben der Tonhöhe eines zu erzeugenden Tones;
 - einer Tonerzeugungseinrichtung (10A) zum Erzeugen von Wellenforminformationen, die einer Wellenform eines gewünschten Tones entsprechen, entsprechend einer durch die Tonhöhenbestimmungseinrichtung (12) bestimmten Tonhöhe, wobei die Tonerzeugungseinrichtung (10A) aufweist:
 - a) eine Speichereinrichtung (10A) zum Speichern der der gewünschten Wellenform entsprechenden Wellenforminformationen; und
 - b) eine Leseeinrichtung (20) zum Auslesen der Wellenforminformationen (WDA) aus der Speichereinrichtung entsprechend der von der Tonhöhenbestimmungseinrichtung bestimmten Tonhöhe;
 - einer unabhängig von der Tonhöhenbestimmungseinrichtung betätigbaren Bedienungseinrichtung (26);
 - einer Erkennungseinrichtung zum Erkennen des Betätigungszustands der Betätigungseinrichtung (26) und zum Ausgeben eines Erkennungsausgangssignals, das den Betätigungszustand der Betätigungseinrichtung angibt; und
 - einer Ausgabereinrichtung (21A, 21B, 23) zum Ausgeben der Wellenforminformationen (WDA) als ein erstes Tonsignal und als zweites Tonsignal in Reaktion auf das Erkennungsausgangssignal; dadurch gekennzeichnet, daß sie ferner aufweist:
 - eine Speichereinrichtung (10B) zum Speichern von Resonanztonwellenforminformationen (WDB), die einer gemischten Wellenform des gewünschten Tons und dessen Resonanztones entsprechen; und
 - eine Leseeinrichtung (20) zum Auslesen der Resonanztonwellenforminformationen (WDB) aus der Speichereinrichtung (10B) entsprechend einer von der Tonhöhenbestimmungseinrichtung (12) bestimmten Tonhöhe, wobei das zweite Tonsignal durch die Resonanztonwellenforminformationen (WDB) gebildet ist.



2. Tonsignalerzeugungsvorrichtung nach Anspruch 1, die ferner eine Überblendsteuereinrichtung (34) zum Durchführen einer derartigen Steuerung aufweist, daß sie Wellenforminformationen (WDA) und die Resonanztoninformationen (WDB) überblendet ausgegeben werden, wenn die Betätigungseinrichtung (26) betätigt worden ist. 5
3. Tonsignalerzeugungsvorrichtung nach Anspruch 1, die ferner eine eine Steuereinrichtung zum Durchführen einer derartigen Steuerung aufweist, daß, wenn die Betätigungseinrichtung (26) betätigt worden ist, die von der Ausgabeeinrichtung auszugebenden Resonanztoninformationen (WDB) allmählich erhöht oder verringert werden, während die Wellenforminformationen (WDA) von der Ausgabeeinrichtung ausgegeben werden. 10
4. Tonsignalerzeugungsvorrichtung nach Anspruch 1, die ferner eine eine Steuereinrichtung zum Durchführen einer derartigen Steuerung aufweist, daß die Wellenforminformationen (WDA) und die Resonanztoninformationen (WDB) mit variablen Kombinationsverhältnissen entsprechend dem Erkennungsausgangssignal kombiniert ausgegeben werden. 15
5. Tonsignalerzeugungsvorrichtung nach einem der Ansprüche 1-4, die ferner eine Hüllkurven-Steuereinrichtung (24) zum Steuern einer Hüllkurve eines Tones, der der Tonsignalerzeugungsvorrichtung in Reaktion auf das Erkennungsausgangssignal erzeugt wurde, aufweist. 20
6. Tonsignalerzeugungsvorrichtung nach einem der Ansprüche 1-5, bei der die Erkennungseinrichtung einen EIN/AUS-Betätigungsstatus der Betätigungseinrichtung erkennt. 25
7. Tonsignalerzeugungsvorrichtung nach einem der Ansprüche 1-5, bei der die Erkennungseinrichtung den Betätigungsbetrag der Betätigungseinrichtung innerhalb eines Bereichs von einem Mindestbetrag bis zu einem Höchstbetrag erkennt. 30
8. Tonsignalerzeugungsvorrichtung nach Anspruch 7, bei der die Ausgabeeinrichtung aufweist: 35
 - eine erste Pegelsteuereinrichtung (42, 21A) zum Steuern des Amplitudenpegels der Wellenforminformationen (WDA), um diesen entsprechend einer ersten Veränderungscharakteristik, die dem durch die Erkennungseinrichtung erkannten Betrag entspricht, zu verändern, und 40

- eine zweite Pegelsteuereinrichtung (40, 21B) zum Steuern des Amplitudenpegels der Resonanztoninformationen (WDB), um diesen entsprechend einer dem durch die Erkennungseinrichtung erkannten Betrag entsprechenden zweiten Veränderungscharakteristik, die von der ersten Veränderungscharakteristik verschieden ist, zu verändern. 45

9. Tonsignalerzeugungsvorrichtung nach einem der Ansprüche 1-8, bei der die Betätigungseinrichtung ein Dämpferpedal aufweist. 50

10. Tonsignalerzeugungsvorrichtung nach einem der Ansprüche 1-9, bei der eine der Speichereinrichtungen (10A) die Wellenforminformationen (WDA) speichert, die einer Wellenform eines natürlichen Pianos, das mit nicht betätigtem Dämpferpedal gespielt wird, entsprechen und die andere Speichereinrichtung (10B) die Resonanztonwellenforminformationen (WDB) speichert, die einer Wellenform eines natürlichen Pianos entsprechen, das mit betätigtem Dämpferpedal gespielt wird. 55

Revendications

1. Un dispositif générateur de son, comprenant:
 - un moyen de désignation de hauteur (12), destiné à désigner une hauteur d'un son à générer.
 - un moyen de génération de son (10A), destiné à générer des informations de forme d'onde correspondant à une forme d'onde d'un son désiré selon une hauteur désignée par le moyen de désignation de hauteur (12), ledit moyen de génération de son (10A) comprenant:
 - a) un moyen de mémoire (10A), destiné à mémoriser les informations de forme d'onde correspondant à la forme d'onde de son désirée, et
 - b) un moyen de lecture (20), destiné à lire les informations de forme d'onde (WDA) dudit moyen de mémoire selon une hauteur désignée par le moyen de désignation de hauteur,
 - un moyen d'actionnement (26) qui peut être actionné indépendamment du moyen de désignation de hauteur,
 - un moyen de détection, destiné à détecter l'état d'actionnement dudit moyen d'actionnement (26) à fournir une sortie de détection indiquant l'état d'actionnement dudit moyen d'actionnement, et
 - un moyen de sortie (21A, 21B, 23), destiné à sortir les informations de forme d'onde



(WDA) comme premier signal sonore et comme second signal sonore en réponse à ladite sortie de détection,

caractérisé en ce qu'il comprend, en outre:
un moyen de mémoire (10B), destiné à mémoriser les informations de forme d'onde de son résonant (WDB) correspondant à une forme d'onde mixte du son désiré et du son résonant de celui-ci, et

un moyen de lecture (20), destiné à lire les informations de forme d'onde de son résonant (WDB) dudit moyen de mémoire (10B) selon une hauteur désignée par le moyen de désignation de hauteur (12), ledit second signal sonore étant lesdites informations de forme d'onde de son résonant (WDB).

2. Un dispositif générateur de son suivant la revendication 1, qui comprend, en outre, un moyen de commande de fondu enchaîné (34), destiné à réaliser une commande telle que les informations de forme d'onde (WDA) et les informations de son résonant (WDB) sont sorties en fondu enchaîné lorsque ledit moyen d'actionnement (26) a été actionné.
3. Un dispositif générateur de son suivant la revendication 1, qui comprend, en outre, un moyen de commande destiné à réaliser une commande telle que, lorsque ledit moyen d'actionnement (26) a été actionné, les informations de son résonant (WDB) à sortir par le moyen de sortie sont progressivement augmentées ou diminuées tandis que les informations de forme d'onde (WDA) sont sorties par le moyen de sortie.
4. Un dispositif générateur de son suivant la revendication 1, qui comprend, en outre, un moyen de commande destiné à réaliser une commande telle que les informations de forme d'onde (WDA) et les informations de son résonant (WDB) sont sorties en combinaison selon un taux de combinaison variable correspondant à ladite sortie de détection.
5. Un dispositif générateur de son suivant l'une quelconque des revendications 1 à 4, qui comprend, en outre, un moyen de réglage de courbe enveloppe (24) destiné à régler une courbe enveloppe d'un son généré dans ledit dispositif générateur de son en réponse à ladite sortie de détection.
6. Un dispositif générateur de son suivant l'une quelconque des revendications 1 à 5, dans lequel ledit moyen de détection détecte un état d'actionnement MARCHE/ARRET du moyen

d'actionnement.

7. Un dispositif générateur de son suivant l'une quelconque des revendications 1 à 5, dans lequel ledit moyen de détection détecte une quantité d'actionnement du moyen d'actionnement dans une plage allant d'une quantité minimale à une quantité maximale.
8. Un dispositif générateur de son suivant la revendication 7, dans lequel ledit moyen de sortie comprend:
un premier moyen de réglage de niveau (42, 21A), destiné à régler le niveau d'amplitude des informations de forme d'onde (WDA) pour le modifier selon une première caractéristique de modification correspondant à la quantité détectée par le moyen de détection, et
un second moyen de réglage de niveau (40, 21B), destiné à régler le niveau d'amplitude des informations de son résonant (WDB) pour le modifier selon une seconde caractéristique de modification correspondant à la quantité détectée par le moyen de détection qui est différente de ladite première caractéristique de modification.
9. Un dispositif générateur de son suivant l'une quelconque des revendications 1 à 8, dans lequel ledit moyen d'actionnement comprend une pédale de sourdine.
10. Un dispositif générateur de son suivant l'une quelconque des revendications 1 à 9, dans lequel l'un desdits moyens de mémoire (10A) mémorise lesdites informations de forme d'onde (WDA) ayant une caractéristique d'une forme d'onde de son d'un piano naturel joué avec la pédale de sourdine non-actionnée, et l'autre desdits moyens de mémoire (10B) mémorise lesdites informations de forme d'onde de son résonant (WDB) ayant une caractéristique d'une forme d'onde de son d'un piano naturel joué avec la pédale de sourdine actionnée.