

Voltage Sources

5 This invention relates to voltage sources and particularly to circuits which provide specific voltages which are dependent on the threshold voltage of transistors used in the circuit.

10 Such circuits are particularly useful in the field of CMOS IC's where it is advantageous to provide specific voltages whose values are proportional to the threshold voltage V_T of the transistors used therein. Such transistors may be either n- or p-channel field-effect transistors. One application is in logic circuits where threshold voltage
15 dependent voltages are required in order to switch the transistors in the circuit so that logical decisions are made by the circuit. Another application is in sensing amplifiers in which lines connected to the inputs of the amplifier are precharged by voltages proportional to the threshold voltage
20 in order to improve the sensitivity of the amplifier.

 Therefore it is an object of the invention to provide a circuit which generates voltages whose values are proportional to the threshold voltage of the transistors used in the circuit.

25 Accordingly, the invention provides a voltage source circuit for generating a voltage proportional to a threshold voltage of the circuit at an output thereof, the voltage source circuit comprising a current mirror having an input and an output and coupled to a first reference potential
30 line;

 a reference current source coupled to the current mirror input for generating a reference current which is dependent on the threshold voltage; and

 a bias transistor having a first current electrode
35 coupled to the current mirror output, a second current electrode coupled to a second reference potential line and a control electrode coupled so as to produce at its first

current electrode a voltage dependent on the reference current,

5 wherein said current mirror output forms the output of the voltage source circuit.

Preferably the reference current source comprises a transistor having a first current electrode coupled to said current mirror input, a second current electrode coupled to
10 said second reference potential line and a control electrode for receiving an input reference voltage.

As will be more fully described below, the control electrode of the bias transistor may be coupled to receive either the input reference voltage or the voltage level at
15 the current mirror output, depending on the required output from the voltage source circuit.

The invention will now be more fully described by way of example with reference to the drawings of which:

Figure 1 shows a circuit diagram of a basic embodiment
20 of a voltage source circuit according to the invention; and

Figure 2 shows a circuit diagram of an improved embodiment of a voltage source circuit according to the invention.

Thus, Figure 1 shows a circuit diagram of a voltage
25 source circuit providing voltages which are dependent on the threshold voltage of n-channel transistors. It comprises a current mirror composed of p-channel transistors M_2 and M_3 each having one current electrode coupled to a voltage supply line V_{DD} . Transistor M_2 is diode-coupled with its second
30 current electrode coupled to its gate electrode

which is also coupled to the gate electrode of transistor M_3 . The input to the current mirror comprises the second current electrode of transistor M_2 which is coupled to the first current electrode of an n-channel transistor M_1 . This transistor has its second current electrode coupled to a ground reference potential line and its gate electrode coupled to receive an input reference voltage V_{REF} .

In this embodiment of the voltage source circuit, the input reference voltage V_{REF} is arranged to be twice the threshold V_T of the n-channel transistors. Thus:

$$V_{REF} = 2 V_T \quad (0)$$

Since the current I through a transistor having a threshold voltage V_T and biased by a voltage V is described by

$$I = K (V - V_T)^2$$

where K is the transistor gain constant, the current through transistor M_1 is

$$I_1 = K_1 (2V_T - V_T)^2 = K_1 V_T^2 \quad (1)$$

This is the current input to the current mirror and the current output from the mirror through transistor M_3 is:

$$I_3 = x I_1 = x K_1 V_T^2 \quad (2)$$

where x is a constant determined by the geometry ratios of transistors M_2 and M_3 .

The output of the current mirror is coupled to the drain of an n-channel bias transistor M_4 , this drain forming the output of the voltage source circuit. The source of transistor M_4 is coupled to the ground reference potential line and the gate of transistor M_4 is connected either to its own drain or the gate electrode of transistor M_1 depending on the output voltage required from the voltage source circuit.

If the gate electrode of transistor M_4 is coupled to its drain, its drain source voltage V_4 is determined by:

$$I_3 = K_4 (V_4 - V_T)^2 \quad (3)$$

Rearranging this, gives:

$$V_4 = V_T + \sqrt{I_3 / K_4} \quad (4)$$

Substituting for I_3 from equation (2) gives:

$$\begin{aligned} V_4 &= V_T + \sqrt{xK_1 V_T^2 / K_4} \\ &= V_T (1 + \sqrt{xK_1 / K_4}) \end{aligned} \quad (5)$$

Thus the output voltage V_4 can be made to be any predetermined ratio of V_T greater than one by appropriately choosing xK_1 / K_4 .

Similarly, if the gate electrode of transistor M_4 is coupled to the gate electrode of transistor M_1 , the transistor M_4 can be made to operate in the triode region. In this case, the output voltage V_4 is given by:

$$I_3 = K_4 [2(2V_T - V_T)V_4 - V_4^2]$$

5

$$= K_4 (2V_T V_4 - V_4^2) \quad (6)$$

Substituting for I_3 from equation (2) gives:

10

$$V_4^2 - 2V_T V_4 + xK_1 V_T^2 / K_4 = 0 \quad (7)$$

whose solution is:

15

$$V_4 = V_T (1 - \sqrt{1 - xK_1/K_4}) \quad (8)$$

From this it can be seen that the output voltage V_4 can now be made to be lower than the threshold voltage V_T by appropriate choices of x , K_1 and K_4 .

20

Thus, by coupling the gate of transistor M_4 to the gate of the transistor M_1 , the ratio V_4/V_T is less than one and by coupling the gate of transistor M_4 to the drain of transistor M_4 , the ratio V_4/V_T is greater than one.

25

Although the above calculations were performed for $V_{REF} = 2V_T$, it will be appreciated that a similar result will be obtained for V_{REF} being any value $(n+1) \cdot V_T$. In this case:

30

$$I_1 = K_1 ((n+1) V_T - V_T)^2 = K_1 (nV_T)^2 \quad (9)$$

so that for the gate of the transistor M_4 being coupled to its drain we have, similarly to equations (2) and (3):

35

$$\begin{aligned} I_3 &= xI_1 = x K_1 (nV_T)^2 \\ &= K_4 (V_4 - V_T)^2 \end{aligned}$$

Thus:
$$\frac{xK_1}{K_4} (nV_T)^2 = (V_4 - V_T)^2$$

5 giving:
$$\sqrt{xK_1/K_4} nV_T = V_4 - V_T$$

so that
$$V_4 = V_T [1 + n\sqrt{xK_1/K_4}] \quad (10)$$

To generate a current in transistor M_1 , n must be greater than zero. However when V_{REF} is generated by diode-connected transistors connected in series to realise ratios V_{REF}/V_T larger than two i.e. three or four or more, requires higher values of the supply voltage V_{DD} . Therefore a useful compromise is to set $V_{REF} = 2V_T$.

15 One circuit in which a voltage V_{REF} with a value of approximately $2V_T$ is generated is shown in Figure 2. In this figure transistors M_1-M_4 are equivalent to those in Figure 1 and the output voltage is V_4 . The reference voltage $V_{REF} = V_1$ is generated by resistor R and by transistors M_{01} , M_{02} ,
20 connected in series between voltage supply line V_{DD} and reference potential line. However, the reference voltage V_{REF} will not be exactly $2V_T$ because of transistors M_{01} and M_{02} which are diode-coupled, across which the voltage will be:

25
$$V_1 = 2V_T + 2\sqrt{I_0/K_0} \quad (11)$$

where I_0 is the current through the transistors M_{01} and M_{02} and K_0 is their gain constant.

30 However neither I_0 nor K_0 can be considered as having constant values since I_0 depends on the supply voltage V_{DD} and K_0 is a function of process parameters and temperature. In the circuit of Figure 1 and referring to equation (0) the current I_3 controlled by voltage V_1 would be:

35
$$I_3 = xK_1 (V_T + 2\sqrt{I_0/K_0})^2$$

$$= xK_1 (V_T^2 + 4V_T\sqrt{I_0/K_0} + 4I_0/K_0) \quad (12)$$

This current will be fed to transistor M_4 .

To obtain I_4 equal to $xK_1V_T^2$ the current I_3 must
5 therefore be lowered by a value equal to:

$$xK_1 (4V_T\sqrt{I_0/K_0} + 4 I_0/K_0)$$

As shown in Figure 2, a current of this value can be
10 subtracted from I_3 using additional transistors M_5 , M_6 and
 M_7 . Transistors M_5 and M_7 are coupled in series between the
ground reference potential line and the output of the current
mirror composed of transistors M_2 and M_3 . The gate of
transistor M_5 is coupled to the gate of transistor M_1 and the
15 gate of transistor M_7 is coupled to the junction between
transistors M_{01} and M_{02} . Transistor M_6 is coupled between
the ground reference potential line and the input of the
current mirror with its gate coupled to the gate of
transistor M_7 .

20 Transistor M_7 has a wide channel and acts as a voltage
follower. Its output voltage V_5 is given by:

$$V_5 \approx \sqrt{I_0/K_0} \quad (13)$$

The current I_5 through transistor M_5 operating in the triode
25 region is:

$$I_5 = K_5 [2(V_T + 2\sqrt{I_0/K_0}) V_5 - V_5^2]$$

which gives from equation (13):

30

$$I_5 = K_5 (2V_T\sqrt{I_0/K_0} + 3I_0/K_0) \quad (14)$$

By setting:

35

$$K_5 = 2xK_1$$

gives:

5
$$I_5 \approx 2xK_1 (2V_T \sqrt{I_0/K_0} + 3I_0/K_0) \quad (15)$$

Now subtracting I_5 from I_3 gives:

10
$$I_3 - I_5 \approx xK_1 (V_T^2 - 2I_0/K_0) \quad (16)$$

This is close to the required value of $xK_1 V_T^2$ but still requires the cancellation of the $2 I_0/K_0$ term in order to achieve very high precision for the ratio V_4/V_T .

This can be achieved by adding to current I_1 a current I_6 flowing through transistor M_6 . By setting $K_6 = 2K_1$ then:

15
$$I_4 \approx x[I_1 + I_6] - I_5 \approx xK_1 V_T^2 \quad (17)$$

20 Current I_4 flowing through transistor M_4 now has the required value and generates a voltage:

$$V_4 = V_T (1 + \sqrt{xK_1/K_4}) \geq V_T$$

if its gate is connected to its drain or:

25
$$V_4 = V_T (1 - \sqrt{1 - xK_1/K_4}) \leq V_T$$

if its gate is connected to the gate of the transistor M_1 .

The above description refers to an embodiment of the circuit according to the invention in which voltages are generated whose value is proportional to the threshold voltage of the n-channel transistors. To generate voltages proportional to the threshold voltage of the p-channel transistors a circuit complementary to that described above may be used.

10

15

20

25

30

35



CLAIMS

- 5 1. A voltage source circuit for generating a voltage proportional to a threshold voltage of the circuit at an output thereof, the voltage source circuit comprising:
a current mirror having an input and an output and coupled to a first reference potential line;
10 a reference current source coupled to the current mirror input for generating a reference current which is dependent on the threshold voltage of the circuit; and
a bias transistor having a first current electrode coupled to the current mirror output, a second current
15 electrode coupled to a second reference potential line and a control electrode coupled so as to produce at its first current electrode a voltage dependent on the reference current,
wherein said current mirror output forms the output of
20 the voltage source circuit.
2. A voltage source circuit according to claim 1 wherein said reference current source comprises a transistor having a first current electrode coupled to said current mirror input,
25 a second current electrode coupled to said second reference potential line and a control electrode for receiving an input reference voltage which is dependent on the threshold voltage of the transistor.
- 30 3. A voltage source circuit according to claim 2 wherein said input reference voltage has a value of substantially twice the threshold voltage of the transistor forming the reference current source.
- 35 4. A voltage source circuit according to either claim 2 or claim 3 wherein the control electrode of said bias transistor is coupled to receive said input reference voltage.



5. A voltage source circuit according to either claim 2 or claim 3 wherein the control electrode of said bias transistor is coupled to said current mirror output.

6. A voltage source circuit according to claim 3 wherein said input reference voltage is produced at the gate electrode of a first diode-coupled transistor coupled via a second diode-coupled transistor to said second reference potential line.

7. A voltage source circuit according to claim 6 further comprising means for adjusting the currents at the input and output of the current mirror in order to correct the voltage at the output of the voltage source circuit.

8. A voltage source circuit according to claim 7 wherein the adjusting means comprises a first adjusting transistor coupled in series between said current mirror output and the first current electrode of a second adjusting transistor, the second adjusting transistor having a second current electrode coupled to said second reference potential line, and a gate electrode coupled to receive said input reference voltage and the gate electrode of the first adjusting transistor being coupled to the gate electrode of said second diode-coupled transistor, so as to subtract an adjusting current from the current produced at the output of the current mirror.



9. A voltage source circuit according to claim 8 wherein the adjusting means further comprises a third adjusting
5 transistor coupled between the current mirror input and the second reference potential line and whose gate electrode is coupled to the gate electrode of said second diode-coupled transistor so as to add an adjusting current to the current produced by the reference current source.

10

10. A voltage source circuit substantially as hereinbefore described by way of example with reference to the drawings.

15

20

25

30

35