

INPUT CONVERTER FOR A HEARING AID AND SIGNAL CONVERSION METHOD

This application relates to hearing aids. More specifically, it relates to analog-to-digital
5 input signal converters in digital hearing aids. The invention further relates to a method of
converting an analog signal to a digital signal in a hearing aid.

An analog-to-digital converter, denoted an A/D converter in the following, converts a
varying current or voltage into a digital data format. Several different A/D converter
10 topologies exist, each having benefits and tradeoffs in terms of conversion speed,
accuracy, quantization noise, current consumption, word length, linearity and circuit
complexity. In contemporary, digital hearing aid designs, the delta-sigma A/D converter
type is the preferred converter type due to a number of important factors such as easy
aliasing filter implementation, conversion noise being controllable by design,
15 comparatively low power consumption and relatively easy implementation due to a low
component count when compared to existing A/D converter designs.

By definition, noise inherent in a signal processing device is unwanted signals introduced
by the signal processing device itself. Inherent noise may e.g. originate from inadequate
20 operating conditions, poor design or variations in component values. These circumstances
have to be taken into account in designing the signal processing device. In A/D
converters, several different types of noise may be observed. Among these are conversion
noise, quantization noise, thermal noise, flicker noise, recombination noise, and noise due
to various physical limitations in the gain-producing elements. In order to provide a
25 distinction between the sources of these different noise types, the most important noise
types will be discussed briefly in the following.

Quantization noise originates from the process of quantifying a continuous input voltage
span into a finite set of voltage levels that may be represented by discrete, binary levels
30 according to the expression:

$$L_N = 2^n$$

where L_N is the number of discrete levels possible and n is the number of bits used to represent a single sample in the digital domain. Quantization noise may be thought of as the difference between the actual input voltage of a single sample and the discrete voltage used to represent it. This type of noise may thus be minimized, e.g. by increasing the number of bits representing the signal arbitrarily, and will therefore not be discussed further here.

Thermal noise originates from the random Brownian motion of electrons in a resistive medium. Given a resistance, a bandwidth and a temperature, the rms thermal noise V_{nt} is given by:

$$V_{nt} = \sqrt{4k_b T \Delta f R}$$

where k_b is Boltzmann's constant, $1,38065 \cdot 10^{-23}$ J/K, T the absolute temperature in K, Δf the bandwidth of interest in Hz and R the resistance in Ω of the circuit element considered.

Flicker noise, or $1/f$ noise, is predominant in the noise spectrum at low frequencies. It has been observed in electronic devices since the era of vacuum tubes, and is also present in contemporary semiconductor devices.

Shot noise is the result of stochastic phenomena caused by an electric current crossing a potential barrier, such as the barrier found between P-doped and N-doped material in a semiconductor element. Current shot noise I_n is a temperature-independent quantity, and may be described by the expression:

$$I_n = \sqrt{2qI}$$

where q is the electron charge, $1,602 \cdot 10^{-19}$ coulombs, and I the bias current for the semiconductor element. The unit of the spectral density of shot noise is $A/\sqrt{\text{Hz}}$.

In order to provide a hearing aid capable of working uninterrupted for several days without a need for replacing the battery, one design goal for the hearing aid is that the current drawn from the battery by the electronic circuit is reduced as much as possible,

preferably to a value below 1 mA. A semiconductor element providing amplification in the order of between one hundred times to perhaps a thousand times the signal present at its input uses a considerable percentage of this current as its bias current in order to handle the large gain within its operating limits. From the foregoing it is evident that shot
5 noise is dependent on the current flowing through the semiconductor element, this fact providing further motivation for reducing the bias current for the amplifier in the A/D converter as much as possible.

Delta-sigma A/D converters are well known in the art. Their purpose is to convert a
10 varying, analog input voltage into a binary bit stream for further processing in the digital domain. Delta-sigma A/D converters have significant advantages over other A/D converter designs. They have a relatively low component count, and they feature various signal processing advantages above other A/D converter designs. In order to reduce conversion noise, oversampling is used. By measuring each discrete voltage many times,
15 e.g. 64, errors due to statistical variations in the input signal are leveled out, and the conversion noise spectrum is pushed far beyond the Nyquist limit, thus making conversion noise very easy to filter out from the signal. One drawback is that the converter clock rate in this example has to be 64 times the desired sample clock rate.

20 In its essence, a delta-sigma A/D converter comprises a delta-sigma modulator and a low-pass filter. This may be made with an integrator, a comparator and a D-flip-flop. The output signal of the flip-flop is fed back through a feedback loop comprising a one-bit D/A converter, and is subtracted from the input signal upstream of the integrator. The subtracted feedback signal provides an error signal to the input of the delta-sigma
25 modulator.

The error signal from the feedback loop of the A/D converter is used to ensure that, on average, the output signal level of the converter is always equal to the input signal level. If no signal is present on the converter input, a symmetric output bit stream of binary ones
30 and zeroes is generated by the A/D converter. When the input signal voltage changes to a more positive voltage, more binary ones will be present in the output bit stream, and when the input signal voltage changes to a more negative voltage, more binary zeroes will be present in the output bit stream. The delta-sigma A/D converter thus converts an analog input signal into a balance between ones and zeroes in the output bit stream.

The invention, in a first aspect, provides an input converter as recited in claim 1. The invention, in a second aspect, provides a method as recited in claim 9.

5 In order to overcome the above shortcomings, the input converter according to the invention comprises a first voltage transformer placed in the input converter upstream of the input stage and having a transformation ratio such that it provides an output voltage larger than the input voltage. When the input signal voltage is transformed up prior to being amplified by the amplifier stage, less amplification is needed in order to bring the
10 input signal up to an acceptable level, and the relative amplifier noise contribution to the amplified signal is lower, and the same is the case when the feedback signal voltage is transformed up prior to being presented to the amplifier input.

According to the invention, both the input transformer and the feedback transformer are
15 implemented as voltage transformers. Voltage transformers are easily implemented in synchronized (clock-controlled) digital networks, and may be designed so as to optimize their impedance to the impedance of the amplifier and the subsequent stages of the A/D converter.

20 Further features and advantages are evident from the dependent claims.

The invention will now be described in further detail with respect to the drawings, where

fig. 1 is a schematic of a prior art delta-sigma A/D converter,
25

fig. 2 is a more detailed schematic of the prior art delta-sigma converter in fig. 1,

fig. 3 is an equivalent schematic illustrating the noise level voltage V_n of an amplifier of the delta-sigma converter in fig. 2,
30

fig. 4 is a schematic illustrating the principle of equivalent transformation of the input signal to the amplifier in fig. 3,

fig. 5 is a schematic illustrating a first phase of a prior art sampled capacitor integrator,

fig. 6 is a schematic illustrating a second phase of a prior art sampled capacitor integrator,

fig. 7 is a schematic illustrating a first phase of the sampled capacitor integrator according
5 to the invention,

fig. 8 is a schematic illustrating a second phase of the sampled capacitor integrator
according to the invention,

10 fig. 9 is a schematic of an implementation of an input transformer in a first phase
according to the invention,

fig. 10 is a schematic of an implementation of an input transformer in a second phase
according to the invention,

15

fig. 11 is a schematic of an embodiment of a delta-sigma analog-to-digital converter
according to the invention,

fig. 12 is a schematic of a preferred embodiment of a delta-sigma analog-to-digital
20 converter according to the invention, and

fig. 13 is a schematic of a hearing aid having four delta-sigma converters according to the
invention.

25 Fig. 1 shows a block schematic of a prior art delta-sigma A/D converter comprising an
input terminal IN, a subtraction point 1, an integrator 2, a comparator 3, a D-flip-flop 4, a
1-bit digital-analog converter 5, a clock generator 6, and an output terminal OUT. An
analog signal presented to the input terminal IN is fed to the subtraction point 1 where the
output signal from the 1-bit D/A converter 5 is subtracted from the input signal,
30 generating an error signal. The difference signal from the subtraction point 1 is fed to the
input of the integrator 2 for generating an integral of the difference signal from the
subtraction point 1. The output signal from the integrator 2 is presented to the input of the
comparator 3 for generating a logical “one”-level whenever the integral signal exceeds a
predetermined threshold limit set by the comparator 3, and a logical “zero”-level

whenever the output signal from the integrator 2 falls below the predetermined threshold. This logical signal then feeds the data input of the flip-flop 4.

5 The clock generator 6 controls the flip-flop 4 in such a way that the output signal from the comparator 3 is quantized in time and synchronized to the clock signal, the flip-flop 4 working as a latch, thus creating a bit stream representing the input signal. The bit stream from the output of the flip-flop 4 is split between the output terminal OUT and the input of the 1-bit D/A converter 5 to the subtraction point 1 and subtracted from the input signal. The 1-bit D/A converter 5 converts the logical ones and zeroes in the bit stream
10 into a positive or negative voltage with respect to the input signal for subtraction from the input signal in the subtraction point 1.

This arrangement, in essence, creates a feedback loop, making the bit stream represent the changes in the input signal over time, i.e. when the input signal level is zero, an equal
15 number of digital ones and zeroes will be present in the bit stream, whenever the input signal goes positive, more ones than zeroes will be present in the bit stream in a proportion to the input signal level, and whenever the signal goes negative, more zeroes than ones will be present in the bit stream in a proportion to the input signal level. The bit stream may then be converted into a suitable, digital format for further processing in the
20 digital domain.

A delta-sigma A/D converter design for a hearing aid should have a small noise figure and a low current consumption. However, if the current consumption of the input amplifier of the A/D converter is decreased without any alterations to the design, the
25 noise figure of the amplifier will increase correspondingly. This problem, and a possible solution, will be explained in further detail in the following.

Fig. 2 shows a more detailed schematic of a prior art delta-sigma A/D converter. The converter comprises an input IN, a first resistor R1, a second resistor R2, an amplifier A, a capacitor C, a residual loop filter RLF, a D-flip-flop DFF, and a clock generator CLK
30 generating a clock signal. The amplifier A and the capacitor C forms the integrator 2 of the converter topology shown in fig. 1, and the residual loop filter RLF comprises subsequent low-pass filter stages present in second- or higher-order delta-sigma converters. The converter receives an analog input signal in the form of a voltage U at the

input terminal IN and presents a bit stream representing a digital output signal Y at the output terminal OUT. It should be noted that the signals in the converter are time-continuous until the generation of the bit stream from the output Q of the flip-flop DFF.

- 5 The amplifier A and the residual loop filter RLF comprises the loop filter of the converter, and the frequency transfer function of the loop filter, i.e. the frequency transfer function of both A and RLF, determines the converter's ability to suppress frequency-dependent quantization noise. The gain of the amplifier A also suppresses the noise from RLF because the filter RLF is positioned in the feedback loop of the converter. In this
10 discussion, the reason for distinguishing between the amplifier loop filter, respectively, is to isolate the noise contribution from the amplifier A from other noise sources in the feedback loop. All other things being equal, the noise level of the amplifier A thus constitutes the main noise component of the converter apart from quantization noise. This is the reason that the contribution from this particular noise source should be minimized,
15 as mentioned in the foregoing.

- If the amplifier A were to have infinite gain, the signal level on the input terminal of the amplifier would be zero. Instead it may be assumed that the total gain of A and RLF combined is sufficiently large throughout the desired frequency bandwidth of the
20 converter for the converter quantization noise to be neglected. Given an input voltage U and a resulting output voltage Y, the transfer function H of the complete converter in fig. 2 in the ideal case may thus be estimated as:

$$H = \frac{Y}{U} = \frac{-R_2}{R_1}$$

25

In order to address the problem of the noise contribution from the input stage of the converter, this particular noise source has to be isolated. This is illustrated in the schematic in fig. 3.

- 30 In fig. 3, an ideal, noise-free amplifier A and a noise voltage source V_n is substituting the amplifier A in fig. 2, and the configuration of C, R1, R2 and A is sketched out together with the input voltage U, the output voltage Y, and the amplifier noise voltage source V_n , while the remaining components from fig. 2 are left out from the schematic for clarity. If the total amplification from A and RLF (not shown in fig. 3) is assumed to be sufficient

for the desired bandwidth of the converter, the noise contribution Y_n to the output voltage Y may be written as:

$$Y_n = \left(1 + \frac{R_2}{R_1}\right) \cdot V_n$$

5

The noise voltage contribution U_n with reference to the input voltage U may then be calculated by combining the two expressions thus:

$$U_n = \frac{Y_n}{H} = -\left(1 + \frac{R_1}{R_2}\right) \cdot V_n$$

10

This implies that the input noise U_n is dependent on the amplifier noise V_n . In other words, if it is possible to decrease V_n , the input noise U_n will decrease, too.

The amplifier noise voltage V_n has three primary origins. Noise due to the fact that the amplifier A has finite gain, intermodulation products originating from nonlinearities in the amplifier A , and thermal noise produced by the input stage of the amplifier A . Multi-stage amplifiers with large gain values have traditionally been used in order to minimize thermal noise. Likewise, noise may also be reduced by supplying the semiconductor elements in the amplifier with sufficiently large currents in order to keep the total noise in the output signal at an acceptable level.

However, none of these approaches are especially attractive in a converter design for a hearing aid, where current consumption and component count has to be kept to a minimum in order to prolong battery life. An alternative way of reducing the noise sensitivity of the amplifier in the converter is thus desired.

In theory, the noise voltage V_n may be downscaled, e.g. by transforming the input signal U and the output signal Y by placing ideal transformers between the input terminal U and R_1 and between the output terminal and R_2 with a given transformation factor N . Fig. 4 shows an equivalent schematic of the converter in fig. 3 with ideal transformers T_1 and T_2 in the input branch and the output branch of the converter, respectively. The input transformer T_1 transforms the input voltage by the ratio $1:N$, (i.e. the voltage on the

30

transformer output is N times the voltage on the transformer input), and the feedback transformer T2 transforms the feedback voltage by the ratio $1:N$ (i.e. the voltage presented to the amplifier is N times the voltage present at the output node Y). The values of the resistors R1 and R2 are each scaled with a factor of N^2 in order to preserve the

5 current load of the input and the output, respectively. Likewise, the value of the integrator capacitor C is scaled by the factor N^2 . It may be shown that the resulting amplifier noise voltage V_n is scaled correspondingly by the factor V_n/N . In theory, it is possible to scale the noise contribution from the amplifier stage down by an arbitrary amount, providing the amplifier stage is capable of handling the increased input voltage without being

10 saturated. The current demands for the converter are also smaller due to the impedance transformation.

Real transformers are non-ideal and therefore impossible to use in practical hearing aids due to their size, weight, current consumption and power losses. The inventor has realized

15 that the equivalent of an ideal transformer may be applied as a solution to the problem with satisfactory results. Such an equivalent is described in further detail in the following. The starting point of this discussion is a delta-sigma A/D converter utilizing a topology based on sampled capacitors. Sampled-capacitor stages are considered to be well-known in the art, and the working principle of such a sampled-capacitor A/D converter is

20 described in further detail in the following with reference to fig. 5 and fig. 6.

Fig. 5 is a schematic illustrating a first phase of a sampling clock control signal in a prior art sampled-capacitor delta-sigma A/D converter comprising an input terminal U, a first sampling capacitor C_s , a first switch S_I , a second switch S_E , a hold capacitor C_h , an

25 amplifier A, a feedback loop capacitor C_s' , a feedback loop terminal Q and an output terminal Y. The feedback loop terminal Q carries the feedback signal from the output of the D-flip-flop (not shown). The switches S_I and S_E are controlled by a sampling clock (not shown). In a first phase of the sampling clock control signal, shown in fig. 5, the sampling capacitor C_s is charged by the input voltage presented on the input terminal U

30 during a first, specific period of time, via the switch S_I . The second switch S_E is open in the first phase.

In a second phase of the sampling clock control signal, shown in the schematic in fig. 6, the switch S_I disconnects the sampling capacitor C_s from the input terminal U and

- connects it to the input of the amplifier A and the hold capacitor C_h , whereby the sampling capacitor C_s is discharged for a second, specific period of time via the switch S_I , transferring its charge to the hold capacitor C_h . The switch S_E is closed in the second phase, and connects the feedback loop capacitor C_s' to the input of the amplifier A. The
- 5 voltage on the input terminal of the amplifier A is now equal to the voltage on the input terminal U during the first period of time minus the error voltage present on the feedback terminal Q. When the second phase ends, the switches S_I and S_E are returned to their initial positions shown in fig. 5, and the process is repeated periodically.
- 10 If the position of the switch S is controlled by a periodical signal having the frequency f_s , the impedance Z_s of the sample capacitor C_s may be described as:

$$Z_h = \frac{1}{(C_s \cdot f_s)}$$

- 15 Consider the sampling capacitor C_s of the sampled-capacitor delta-sigma A/D converter in the first phase shown in fig. 5 split into two capacitors, each having a capacitance of $C_s/2$. A voltage transformation may then be implemented by changing the sampled-capacitor design to look like the schematic in fig. 7 and fig. 8, respectively. The sampled-capacitor circuit design shown in fig. 7 and fig. 8 comprise two controlled switches S_I and
- 20 S_E , an amplifier A, a hold capacitor C_h , and four capacitors C_a and C_b , C_c and C_d , each of the four capacitors having a capacitance of $C_s/2$. In fig. 7, the switch S_I connect the two capacitors C_a and C_b to the input terminal IN in parallel in the first phase, in a manner similar to that shown in fig. 5, and in fig. 8, the switch S_I connect the two capacitors C_a and C_b to the amplifier A in series in the second phase in a manner similar to that shown
- 25 in fig. 6.

- Likewise, the feedback capacitors C_c and C_d are charged in parallel to the voltage present on the feedback loop terminal Q with reference to ground via the switch S_E in the first phase in fig. 7, and in the second phase, shown in fig. 8, the feedback capacitors C_c and
- 30 C_d are connected in series between the feedback loop terminal Q and the amplifier A via the switch S_E during discharge of the feedback capacitors C_c and C_d , whereby the voltage drop between the feedback loop terminal Q and the hold capacitor C_h is doubled. The

voltage present at the input of the amplifier A in the second phase is then $V_U - V_Q$, i.e. the doubled input voltage minus the doubled feedback voltage.

The effect of this arrangement is that the input node of the amplifier A is isolated from the input terminal U and the feedback loop terminal Q by the voltage transformers formed by the capacitors C_a , C_b , C_c and C_d , respectively. The net result of doubling the input voltage and the feedback loop voltage is that the intrinsic noise level V_n of the amplifier A becomes comparatively smaller, and the signal-to-noise ratio thus is improved, while maintaining both the input impedance and the output impedance of the amplifier stage A as seen from outside the circuit shown in fig. 7 and fig. 8, respectively.

With the capacitors C_a , C_b , C_c and C_d having values of $C_s/2$, respectively, this configuration is equivalent to a voltage transformation with a transformation factor of 1:2 for the input transformer, respectively 2:1 for the feedback transformer, as the impedance Z_s of the hold capacitor C_s now becomes:

$$Z_s = \frac{4}{(C_s \cdot f_s)}$$

This arrangement thus effectively quadruples the input impedance of the amplifier A. By changing the configuration of the circuit in synchronization with the two phases of the sampling clock frequency f_s of the sampled-capacitor delta-sigma A/D converter, by means of the switches S_I and S_E as shown in fig. 7 and 8, the input voltage U presented to the input terminal of the amplifier A is then doubled to 2U.

Consider the amplifier A having unity gain, and an error signal of 0 V being present on the feedback loop terminal Q. Then the output signal downstream of the second voltage transformer C_c and C_d is:

$$\frac{2 \cdot U + V_n}{2} = U + \frac{V_n}{2}$$

30

This is based on the imperative that the capacitors C_c and C_d are shifted between the parallel configuration in the first phase shown in fig. 7 and the serial configuration in the second phase shown in fig. 8. By isolating the input of the amplifier A of the input stage

of the A/D-converter from the rest of the circuitry with first and second voltage transformers in this way, an effective, comparative noise figure of $V_n/2$ may be obtained in a simple and effective manner.

- 5 A schematic illustrating a first and a second phase of the function of the input voltage transformer circuit of fig. 7 and 8 is described in the following with reference to fig. 9 and fig. 10. In fig. 9 and fig. 10, a voltage transformer circuit comprises an input terminal U, an output terminal V_A , five controlled switches S1, S2, S3, S4, and S5, and two sampling capacitors C_a and C_b , both having a capacitance of $C_s/2$ with respect to the schematic of
 10 the circuit shown in fig. 5 and 6. The output terminal V_A of the voltage transformer circuit is to be connected to an amplifier (not shown) as illustrated in fig. 7 and 8.

In the first phase of the voltage transformer, shown in fig. 9, the switches S1, S3, and S5 are closed, and the switches S2 and S4 are open. The two capacitors are thus connected in
 15 parallel to the input terminal U in fig. 9. A voltage present on the input terminal U will thus charge the capacitors C_a and C_b to the same voltage.

In the second phase of the voltage transformer, shown in fig. 10, the switches S1, S3, and S5 are now open, and the switches S2 and S4 are now closed. The two capacitors C_a and
 20 C_b are now connected in series, thus doubling their total charge voltage while reducing the total capacitance to $C_s/4$, and connected to the output terminal V_A . The combined charge collected by the capacitors C_a and C_b is now presented as a voltage to the output terminal V_A . This voltage is double the voltage of U due to the altered configuration of the capacitors C_a and C_b .

25 Considering the output terminal V_A of the input voltage transformer shown in fig. 9 and fig. 10 connected to the input stage of an amplifier A in the way shown in fig. 7 and fig. 8. If the amplifier A has an amplification gain β , then the input voltage U is both doubled and multiplied by β , but the noise voltage V_n is just multiplied by β . For a given input
 30 voltage U, the voltage output V_Y from the amplifier A will be:

$$V_Y = 2 \cdot \beta \cdot U + \beta \cdot V_n \Leftrightarrow V_Y = \beta(2 \cdot U + V_n)$$

The noise voltage contribution V_n to the output voltage V_Y is then half the noise voltage contribution of the untransformed input voltage in this case, provided that the amplifier is capable of handling the transformed input voltage of $2U$.

- 5 The voltage contribution from the feedback loop signal of the delta-sigma A/D converter is doubled in a similar way by the second voltage transformer C_c and C_d as indicated in fig. 7 and fig. 8.

The principle of voltage transformation is extensible to an arbitrary number N of
 10 sampling capacitors each having the capacitance of C_s/N , in effect reducing the apparent noise figure of the amplifier equally to V_n/N . It is not essential for operation of the invention that the input transformer and the feedback transformer have the same transformation ratio. This principle permits implementation of the input amplifier in a much simpler way due to the reduced demands on its performance with regard to
 15 amplification gain, thermal noise, intermodulation noise, and errors due to finite gain of the amplifier.

The amplifier in the input stage of the A/D converter according to the invention may consequently be implemented as a simple, single-stage amplifier comprising one single
 20 semiconductor element, such as a BJT, FET, or other amplifying element having sufficient gain. Single-stage amplifiers inherently have a very attractive relationship between thermal voltage noise and current consumption. The voltage transformation further reduces the bias current demands of the amplifier and thus the current consumption of the complete A/D converter, of which the bias current for the input
 25 amplifier constitutes a substantial part.

Fig. 11 shows a delta-sigma A/D converter ADC according to the invention. The A/D converter ADC comprises an input terminal IN, an input transformer stage IT, an amplifier stage Q_A , a hold capacitor C_h , a constant current generator I_c , a feedback
 30 transformer stage OT, a residual loop filter RLF, a comparator CMP, a flip-flop DFF, and an output terminal OUT. The flip-flop DFF is controlled by a system clock source (not shown). The amplifier stage Q_A is fed a constant current from the constant current source I_c powered by a connection to the reference voltage source V_{ref} . This current controls the

operating point of the amplifier Q_A in order for it to be able to provide the desired gain to the input signal.

The input transformer stage IT comprises switching transistors Q_1 , Q_2 , Q_3 , Q_4 , and Q_5 , and capacitors C_a and C_b . The feedback transformer stage OT comprises switching transistors Q_6 , Q_7 , Q_8 , Q_9 and Q_{10} , and capacitors C_c and C_d . For simplicity, these four capacitors are considered to be of equal capacitance, i.e. $C_a = C_b = C_c = C_d$.

The switching transistors Q_1 , Q_2 , Q_3 , Q_4 and Q_5 of the input transformer stage IT are controlled by a sampling clock generator (not shown) in such a manner that when the signal edge of the sampling clock generator goes positive in a first phase, the switching transistors Q_1 , Q_3 , and Q_5 close (i.e. they allow an electrical current to pass), and Q_2 and Q_4 open (i.e. they block an electrical current). This is illustrated in fig. 11 by an open or a filled circle, respectively, on the base terminal of the respective switching transistors. In the first phase of the signal edge of the sampling clock generator, a filled circle denotes a closed transistor and an open circle denotes an open transistor.

When the signal edge of the sampling clock generator goes negative in a second phase, the switching transistors Q_1 , Q_3 , and Q_5 of the input transformer IT open, and the switching transistors Q_2 and Q_4 close. In the second phase of the signal edge of the sampling clock generator, an open circle denotes a closed transistor and a filled circle denotes an open transistor. This configuration is equivalent to the schematics shown in figs. 9 and 10, respectively, where the transistors Q_1 , Q_2 , Q_3 , Q_4 , and Q_5 substitute the switches S_1 , S_2 , S_3 , S_4 , and S_5 , respectively, retaining the essential function of the circuit shown in figs. 9 and 10. The clock frequency of the sampling clock generator (not shown) is of the magnitude of 30 kHz, and the clock frequency of the system clock generator (not shown) is of the magnitude 1-2 MHz. This gives an oversampling ratio of the converter of from 30 to 60 times oversampling.

In the first phase, where Q_1 , Q_3 and Q_5 are closed and Q_2 and Q_4 are open, the capacitors C_a and C_b are connected in parallel to the input terminal IN, and each capacitor is charged to the voltage present on the input terminal IN. In the second phase, where Q_1 , Q_3 and Q_5 are open and Q_2 and Q_4 are closed, the capacitors C_a and C_b are connected in series to the input of Q_A , delivering their combined charge to the input of Q_A and the hold capacitor

C_h . Due to this arrangement, the input voltage fed to the input transformer IT will be doubled at its output, as explained above.

The switching transistors Q_6 , Q_7 , Q_8 , Q_9 and Q_{10} of the feedback transformer OT are also controlled by the sampling clock generator (not shown) in such a way that when the signal edge of the sampling clock generator goes positive in the first phase, the switching transistors Q_6 , Q_8 and Q_{10} close and Q_7 and Q_9 open. This is also illustrated by an open or a filled circle, respectively, on the base terminal of the respective switching transistors, where a filled circle denotes a closed transistor and an open circle denotes an open transistor. This implies that the capacitors C_c and C_d are connected in parallel to the input of the amplifier Q_A in the first phase, delivering their combined charge to the input of the amplifier Q_A .

In the second phase, when the signal edge of the sampling clock generator goes negative, the switching transistors Q_6 , Q_8 and Q_{10} open, and Q_7 and Q_9 close. In this case, an open circle on the base terminal of the respective transistor denotes a closed transistor and a filled circle denotes an open transistor. This implies that the capacitors C_c and C_d are connected in series to the output terminal OUT in the second phase and charged by the error voltage from the flip-flop DFF. The capacitors C_c and C_d are essentially placed in the feedback loop of the amplifier Q_A , doubling the feedback voltage from the output of the flip-flop DFF before presenting the error voltage to the input of the amplifier Q_A .

The residual loop filter RLF outputs the integral of the signal from Q_A , and the comparator CMP outputs a logical zero value whenever the integral is below a predetermined threshold, and a logical one value whenever the integral is above a predetermined threshold. The flip-flop DFF converts the binary integral signal from the comparator CMP into a bit stream controlled by the clock signal CLK and fed to both the output terminal OUT and the input of the feedback transformer OT as a feedback signal.

By doubling the voltage present at the input of the amplifier Q_A with the voltage transformers IT and OT respectively, the input voltage is increased by a factor two, and the relative noise voltage level V_n is reduced as a consequence without the need for increasing the supply current to the amplifier Q_A .

A preferred embodiment of the A/D converter according to the invention is shown in fig. 12. The general configuration of the input terminal IN, the input transformer IT, the feedback transformer OT, the constant current generator I_c , the amplifier Q_A , the hold capacitor C_h , the residual loop filter RLF, the comparator CMP, the flip-flop DFF, and the output terminal OUT is similar to the configuration shown in fig. 11, but the topologies of the input transformer IT and the feedback transformer OT differs from the embodiment shown in fig. 11.

The input transformer IT comprises switching transistors, Q_1 , Q_2 , Q_3 , Q_4 , and Q_5 , and capacitors C_a and C_b , and the feedback transformer OT comprises switching transistors, Q_6 , Q_7 , Q_8 , Q_9 , Q_{10} , and Q_{11} , one capacitor C_c , and two AND gates AG_1 and AG_2 . In this preferred embodiment, the feedback transformer OT has one capacitor less than the embodiment shown in fig. 11.

All the switching transistors of the input transformer IT and some of the switching transistors of the feedback transformer OT are controlled by a sampling clock generator (not shown) in such a way that when the sampling clock signal goes positive in a first phase, the transistors Q_1 , Q_2 , Q_5 , Q_7 , and Q_{10} close, i.e. they allow an electric current to pass, and the transistors Q_3 and Q_4 open, i.e. they block an electric current. When the clock signal goes negative, in a second phase, the transistors Q_1 , Q_2 , Q_5 , Q_7 , and Q_{10} open, and the transistors Q_3 and Q_4 close.

The switching transistors Q_6 , Q_8 , Q_9 and Q_{11} are controlled by first and second AND gates AG_1 and AG_2 , respectively. The first AND gate AG_1 outputs a logical high level when the logical flip-flop output $\overline{Q}$ is logically high and the inverted system clock signal $\overline{CLK}$ is logically high. The second AND gate AG_2 outputs a logically high level when the flip-flop output Q is logically high and the system clock signal CLK is logically high. The logical flip-flop output signals $\overline{Q}$ and Q are mutually exclusive, and $\overline{CLK}$ and CLK are also mutually exclusive, so only one of the two AND gates AG_1 and AG_2 may output a logically high level at any one time. When a logical zero is present in the bit stream, AG_1 is logically high on every negative clock pulse, and when a logical one is present in the bit stream, AG_2 is logically high on every positive clock pulse.

When the first AND gate AG_1 outputs a logically high level, the switching transistors Q_6 and Q_8 close, while the switching transistors Q_9 and Q_{11} open. This has the effect of the first node of the capacitor C_c being connected to ground through Q_8 , and the second node of the capacitor C_c being connected to the input of the amplifier Q_A , and whatever voltage present on the first node of the capacitor C_c is mirrored as a negative voltage at the input of the amplifier Q_A . In the first phase of the sampling period, the switching transistors Q_7 and Q_{10} are closed. They provide the voltage V_{ref} to the first node of the capacitor C_c , and connects the second node of C_c to ground, while V_{ref} gets added to the voltage already present on the first node of C_c . In the second phase of the sampling period, the switching transistors Q_7 and Q_{10} are open. The first node of the capacitor C_c is now connected to the output of AG_1 , and the second node of C_c is connected to the input of the amplifier Q_A .

When the second AND gate AG_2 outputs a logically high level, the switching transistors Q_9 and Q_{11} are closed, while the switching transistors Q_6 and Q_8 are open. Consequently, the first node of the capacitor C_c is connected to the input of the amplifier Q_A , and the second node of the capacitor C_c is connected to V_{ref} through Q_8 . In the first phase of the sampling period, the switching transistors Q_7 and Q_{10} are closed. They provide the voltage V_{ref} to the first node of the capacitor C_c , and connect the second node of C_c to ground while V_{ref} gets added to the voltage already present on the first node of C_c . In the second phase of the sampling period, the switching transistors Q_7 and Q_{10} are open. The first node of the capacitor C_c is now connected to the input of the amplifier Q_A , and the second node of C_c is connected to the output of AG_1 .

The result of this arrangement is that whenever a logical one is present in the bit stream to the output terminal OUT, the voltage contribution from OT is equal to $2V_{ref}$, and whenever a logical zero is present in the bit stream, the voltage contribution from OT is equal to $-V_{ref}$. For a bit stream comprised of an equal number of ones and zeroes, the mean value of the error signal from OT is thus equal to $\frac{1}{2}V_{ref}$.

The delta-sigma A/D converter according to the invention accomplishes two goals at the same time. Firstly, the single-stage input amplifier design implies that the current consumption of the input amplifier may be reduced considerably, and secondly, the signal-to-noise ratio is improved by transforming up the signal level before it reaches the input stage. The application of sample-clock controlled voltage transformers for isolating

the input stage from the input and the error feedback loop, respectively, provides the solution to the signal-to-noise ratio problem arising from using a single-stage input amplifier without a significant increase in power consumption. This design is preferred in a battery-powered circuit such as a hearing aid, and as a result, more than one delta-sigma
5 A/D converter may be implemented on the circuit chip comprising the main part of the electronic circuit of a hearing aid.

Fig. 13 is a schematic of a hearing aid 20 comprising a plurality of A/D converters according to the invention. The hearing aid 20 comprises a first microphone 21, a second
10 microphone 22, a telecoil 23, an antenna 24, a wireless receiver 25, a first A/D converter 26, a second A/D converter 27, a third A/D converter 28, a fourth A/D converter 29, a digital signal processor 30 and a loudspeaker 31. All the components of the hearing aid 20 are fed from a battery cell (not shown) disposed within the hearing aid.

15 When in use, the first microphone 21 and the second microphone 22 pick up acoustical signals from the surroundings and convert them into continuously varying electrical signals for use by the hearing aid 20. The continuously varying electrical signal from the first microphone 21 is fed to the first A/D converter 26, which converts the variations in the electrical signal into a first digital bit stream suitable for being processed by the digital
20 signal processor 30. In a similar way, the continuously varying electrical signal from the second microphone 22 is fed to the second A/D converter 27, which converts the variations in the electrical signal into a third digital bit stream suitable for being processed by the digital signal processor 30. As the first and the second A/D converters 26 and 27 are independent entities, they generate individual bit streams for independent processing
25 by the digital signal processor 30.

The digital signal processor 30 may combine the individual bit streams from the first and the second A/D converters 26 and 27, representing the signals from the first and the second microphone 21 and 22, respectively, in such a way that directional information
30 inherent in the acoustical signals picked up by the microphones is retained for processing in the digital signal processor 30 and subsequent reproduction by the speaker 31.

In situations where a suitable wireless signal is available, the wireless receiver 25 may be engaged for receiving and demodulating the wireless signal for reproduction by the

hearing aid 20. The wireless signal is received by the antenna 24, demodulated by the wireless receiver 25, and presented as a varying electrical signal to the third A/D converter 28, which converts the variations in the electrical signal into a third digital bit stream suitable for being processed by the digital signal processor 30. The third A/D
5 converter 28 operates independently of the first A/D converter 26 and the second A/D converter 27, and the signal from the wireless receiver 25 may thus be selected even if both the first and the second microphone 21 and 22 are engaged simultaneously.

If the hearing aid user is at a location where a telecoil loop system is present, it may be
10 advantageous to use the signal from the telecoil 23. In this case, signals from the loop system (not shown) is picked up by the telecoil 23 and presented to the input of the fourth A/D converter 29, which converts the variations in the electrical signal into a fourth digital bit stream suitable for being processed by the digital signal processor 30. The fourth A/D converter 29 operates independently of the first, the second and the third A/D
15 converters 26, 27 and 28, respectively, and the signal may be selected even if both the first microphone 21, the second microphone 22, and the wireless receiver 25 are engaged at the same time.

The digital signal processor 30 comprises means (not shown) for selecting up to four
20 individual bit streams from the four A/D converters 26, 27, 28 and 29, respectively. The bit streams are preferably interleaved by the digital signal processor 30 and mutually weighted in order to generate a preferred balance between the signals from the four signal sources feeding the four A/D converters 26, 27, 28 and 29 for reproduction to a hearing aid user.

25
The digital signal processor 30 performs a series of calculations on the individual bit streams in order to process the digital representations of the audio signals according to an individual prescription for the hearing aid user. The balance between the signals from the four signal sources feeding the four A/D converters 26, 27, 28 and 29 may be determined
30 when fitting the hearing aid to the user, and subsets of different signal source balances may be stored in the hearing aid as programs for later recall by the user.

CLAIMS

1. An input converter for a hearing aid, said converter comprising a first voltage transformer and an analog-to-digital converter of the delta-sigma type, the analog-to-digital converter having an input stage and an output stage, a connection from the output of the input stage to the input of the output stage, and a feedback loop between the input of the input stage and the output of the output stage, said input stage comprising an amplifier and an integrator, wherein the first voltage transformer has a transformation ratio such that it provides an output voltage larger than the input voltage and is placed in the input converter upstream of the input stage.
2. The input converter according to claim 1, characterised in that a second voltage transformer is placed in the feedback loop in such a way that it provides a feedback voltage larger than the input voltage.
3. The input converter according to claim 1, characterised in that at least one of the first and the second voltage transformers is a switched capacitor voltage transformer.
4. The input converter according to claim 3, characterized in that at least one of the first and the second voltage transformers comprises at least two capacitors arranged to be charged in a parallel configuration and to be discharged in a serial configuration and means for controlling the charging and discharging of the capacitors in the respective configurations.
5. The input converter according to claim 4, characterized in that at least one of the first and the second voltage transformers is controlled by a sampling clock generator.
6. The input converter according to claim 5, characterized in that at least one of the voltage transformers is controlled by a system clock generator.

7. The input converter according to claim 1, characterized in that the amplifier comprises a single amplifying semiconductor element.
8. The input converter according to claim 3, characterized in that each of the output
5 voltages of the first and the second voltage transformer are larger than the respective input voltage.
9. A method of converting an analog signal into a digital signal in a hearing aid comprising a digital signal processor, a sampling clock generator and a system
10 clock generator, said method comprising the steps of transforming an input signal voltage, amplifying the transformed input signal voltage, integrating the transformed, amplified voltage, digitizing the amplified, integrated voltage, transforming the digitized, integrated voltage into a higher voltage, subtracting the transformed, digitized voltage from the transformed input voltage, and using the
15 digitized, integrated voltage for generating a digital output bit stream representing the input signal voltage to subsequent stages of the digital signal processor in the hearing aid.
10. The method according to claim 9, wherein the step of transforming the input
20 signal voltage into a higher voltage involves the steps of charging at least two capacitors in a parallel configuration to an instantaneous value of the input voltage in a first phase of the signal from the sampling clock generator and discharging the at least two capacitors in a serial configuration in a second phase of the signal from the sampling clock generator, thereby multiplying the combined discharge
25 voltage of the capacitors by the number of capacitors.
11. The method according to claim 9, wherein the step of digitizing the amplified, integrated voltage involves the steps of comparing the amplified, integrated voltage to a predetermined voltage and generating a discrete, logical signal in
30 dependence of the value of the amplified, integrated voltage and the signal from the system clock generator.
12. The method according to claim 9, wherein the step of transforming the digitized, integrated signal voltage involves the steps of charging at least two capacitors in a

parallel configuration to an instantaneous value of the digitized, integrated signal voltage in a first phase of the signal from the sampling clock generator and discharging the at least two capacitors in a serial configuration in a second phase of the signal from the sampling clock generator, thereby multiplying the combined
5 discharge voltage of the capacitors by the number of capacitors.

13. The method according to claim 12, wherein the step of transforming the digitized, integrated signal voltage involves the steps of charging one capacitor in a first phase of the signal from the sampling clock generator and applying the digitized,
10 integrated signal voltage and the signal from the system clock generator in such a manner that the mean value of the transformed, digitized voltage to be subtracted from the transformed input voltage is equal to zero minus the maximum voltage of the digital output bit stream.

14. The method according to claim 12, wherein the step of transforming the digitized, integrated signal voltage involves the steps of charging one capacitor in a first phase of the signal from the sampling clock generator and applying the digitized,
15 integrated signal voltage and the signal from the system clock generator in such a manner that the mean value of the transformed, digitized voltage to be subtracted from the transformed input voltage is equal to N times the maximum voltage of
20 the digital output bit stream, where N is the number of capacitors.