

Transmission system for correlated signals.

FIELD OF THE INVENTION

The invention relates to a signal transmission system comprising processing means for isolating an estimate for at least one wanted signal contained in at least one mixed signal, at least one sensor for detecting the mixed signal, the mixed signal
5 comprising at least the wanted signal and at least two correlated interference signals which are produced by two sources of the system in response respectively to two correlated electric signals.

This may relate to an audio signal broadcasting system present, for example, in a motor car or in a room. The system comprises a sound source formed, for
10 example, by a car radio, a compact disc reader, a television receiver, a hifi system or by other stereophonic sound sources. The system may include voice recognition which permits a user to give voiced commands for controlling notably the sound source.

This may relate to a teleconference system which comprises a transmitting station which communicates with a receiving station for which stations the conversations
15 captured in the transmitting station are to be recovered in the receiving station without degradation.

This may also relate to systems for which radio broadcast signals arrive by radio link in the form of mixtures on antennas, the radio broadcast signals being locally interfered by noise sources.

20

BACKGROUND OF THE INVENTION

By way of example, let us consider the case where the wanted signal is a speech signal coming from a person.

A first situation appears in the case of the transmission of conversations
25 via teleconferencing. A microphone installed in a transmitting station captures the voices as well as the ambient noise and all the sounds thus captured are transmitted to the receiving station. Evidently, the sounds broadcast by loudspeakers situated in the transmitting station and coming from the receiving station, will also be captured and then broadcast to the receiving station and cause undesirable echoes. A solution restricted to certain types of

signals is revealed in the document entitled: "Stereophonic Acoustic Echo Cancellation - An Overview of the Fundamental Problem" by M.M. Sondhi, D.R. Morgan, J.L. Hall, IEEE Signal Processing Letters, Vol. 2, No. 8, 1995, pp. 148-151.

None the less, when the loudspeakers broadcast stereophonic sounds, no
5 satisfactory technique is known which permits of correctly isolating the person's voice expressed in the microphone.

Another situation occurs in the case where the voice to be captured is that
of a driver who expresses himself in a microphone installed in a motor car. The past few
years there have been developed possibilities for the driver to have voice control of
10 equipment inside a motor car. The object of this is to set the driver free from movements he
has to make to effect certain settings or to have certain controls in the motor car itself. It is
thus necessary in a first period to recognize the voice message pronounced by the driver and
then, in a second period, to decode this voice message and extract therefrom commands
intended to influence the equipment. By placing several microphones inside the driver's
15 compartment, there is achieved that the driver's voice is isolated and the commands it
contains are decoded to take appropriate action. But the motor car is a considerably noisy
environment where known techniques are not satisfactory, notably when the driver's
compartment contains loudspeakers which broadcast stereophonic sounds. Each time mixed
signals contain mutually correlated signals, it is very difficult to separate them and also to
20 separate other signals that form the mixed signal.

It is a main object of the invention to propose a signal transmission
system which is suitable for separating signals contained in mixed signals comprising
correlated signals and which is more robust to interference than prior-art techniques.

A particular object of the invention is to check the sound volume returned
25 to the user of the system on the basis of voice messages pronounced by the user.

SUMMARY OF THE INVENTION

This main object is achieved with a system in which the processing means
receive on the input the detected mixed signal and the two correlated electric signals
30 wherefrom the processing means extract the estimate of the wanted signal contained in the
detected mixed signal by decorrelating via multiple shifts the estimate relative respectively to
the correlated electric signals.

The voice message is thus correctly separated from all the other sound
signals present in the sound environment, which other signals may come from whatever

sound source present in the vehicle. The invention provides an effective solution to the processing of stereophonic signals, that is to say, correlated signals, which is impossible with known processings.

The correlated electric signals which give rise to correlated interference
5 signals may be obtained from the loudspeakers of a car radio, a television receiver, a hifi system or other sound sources.

In the cases where the sensor is a microphone, where the mixed signal is an ambient sound signal captured at the listening end by the microphone, where the wanted signal is a voice message sent by a speaker at the listening end, where the voice message is
10 interfered by stereophonic signals broadcast by loudspeakers which form the sources, the system is such that the processing means extract the estimate of the voice message contained in the ambient sound signal by decorrelating the estimate of the voice message relative respectively to the stereophonic signals.

According to a particular embodiment, converting means permit to
15 convert the estimate of the voice message into at least one voice control. The voice controls may be used for controlling in return the sound source from which the correlated signals come. Thus, a voice control may request the modification of the sound volume produced by the car radio. When the system detects such a voice control, it subsequently applies this control to the car radio.

But the use of voice controls is not restricted to the control of the sound
20 source from which the correlated signals are taken. The voice controls may also be used for controlling the other sound sources or for acting on actuators at the listening end, in the motor car or in the room, for example. Thus, a first voice control may request a lowering of the sound volume broadcast by the car radio, after which a second voice control may request
25 the windows of the motor car to be closed. The means producing the voice controls are therefore connected to the respective actuators via the voice controls provided to this effect.

In the case of a teleconference system comprising a transmitting station and a receiving station interconnected by at least an up and at least a down channel, the stations comprising each at least two microphones and at least two loudspeakers broadcasting
30 two stereophonic signals, the system is characterized in that the processing means eliminate undesirable echoes generated by the stereophonic signals arriving at the transmitting station coming from the receiving station, the transmitting station transmitting in stereo only the estimates of the local voice message to the loudspeakers of the receiving station.

The speech signals pronounced by the speaker may thus be perfectly

separated from the correlated signals broadcast by the loudspeakers and coming from the other station. The transmitting station can thus transmit solely the speaker's signals from the transmitting station to the receiving station. This makes it possible to avoid the phenomena of echoes which manifest themselves if the signals produced by the loudspeakers were retransmitted in a loop to the station that has broadcast them.

In the case where the sensor is an antenna which receives a radio broadcast signal, the system permits of separation of the radio broadcast signal by clearing it of all the correlated signals coming from sources that transmit interference signals.

These and other aspects of the invention will be apparent from and elucidated with reference to the embodiments described hereinafter.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 shows a diagram of an audio system for extracting the voice message of a single speaker, which system further comprises voice recognition means,

Fig. 2 represents a diagram of an embodiment for adaptive filter processing means for decorrelating the signals,

Fig. 3 represents a diagram of an embodiment for source separation processing means for decorrelating the signals,

Fig. 4 represents a diagram of an embodiment for adaptive filter means,

Fig. 5 represents a diagram of an audio system for extracting the voice messages of two speakers, which system further comprises voice recognition means, and

Fig. 6 represents a diagram of a teleconference system comprising processing means for decorrelating the signals.

DESCRIPTION OF PREFERRED EMBODIMENTS

Fig. 1 represents a voice recognition audio system 5 according to the invention for recognizing a single speaker L. By way of example, let us consider the case of sound sources situated in a motor car, the possibility being given to the speaker, for example, to the driver of the vehicle, to express voice messages to control various actions in the driver's compartment. The driver's messages are captured by a microphone Ma which also captures all the sound signals which occur in the driver's compartment. These sound signals may comprise any kind of noise, but also, notably, stereophonic sounds broadcast by a car radio.

The sound signals which occur at the listening end are captured and

converted by the microphone into an electric signal E_a . The signal E_a is a mixed signal which comprises the wanted signal X_L sent by the speaker, as well as interference signals P_a and P_b coming from the loudspeakers LS_a , LS_b . The sound signals broadcast by the loudspeakers are stereophonic signals, that is to say, correlated signals obtained on the basis of correlated electric signals CR_a and CR_b which excite the loudspeakers. Because of the correlation between the signals, the separation of the wanted signal X_L from the interference signals CR_a and CR_b was impossible to realize with known techniques. Thanks to the invention it is possible to separate the wanted signal X_L correctly as an estimate I_L of the wanted signal X_L .

10 The estimate I_L is obtained by processing means SEPAR 10 which implement an adaptive method that decorrelates the estimate I_L relative to correlated electric signals CR_a and CR_b .

Fig. 2 is a diagram of an embodiment of processing means SEPAR 10. The interference signals CR_a , CR_b enter adaptive filter means FILT1 90a and FILT2 90b, respectively. A summing means $\Sigma 95$, for example a summator, receives the mixed signal E_a from which it subtracts the outputs of the filter means FILT1 and FILT2. The output of the summator produces the estimate I_L . The processing means 10 are adaptive, that is to say, they adapt themselves to variations of the characteristics of the input signals. Adapting means ADAP1 and ADAP2 determine the updates which are to be applied to the filters FILT1 and FILT2, so that they permit the summator of producing a reliable estimate of the wanted signal X_L , which estimate is still reliable when the characteristics of the input signals follow a normal course.

Each adaptive filter has a structure known per se (Fig. 4) comprising, for example, a bank of delay cells, which cells deliver each the signal CR_a delayed by k samples, each delayed signal being weighted with a respective weighting factor $h_a(k)$. The summation of all the weighted delayed signals produces the output signal of the filter (connections 91a, 91b).

In a general manner, the decorrelation of the signals I_L relative to the signals CR_a or CR_b shifted by an integral number of samples k may be expressed (for CR_a , for example) by:

$$(1) \quad E[I_L(t) \cdot CR_a(t-k)] = 0$$

in which the variable t corresponds to time and forms the integer index of the current sample. The term E represents the mathematic expectation of the expression in brackets with respect to time. Thus, by canceling the set of contributions determined by equation (1)

applied to the signal samples for $0 \leq k \leq M$, the decorrelation provided in the case of the filter FILT1 is effected, while M are the number of cells of the filter.

In a particular manner, the weighting factors $h_a(k)$ may be adapted according to the equation:

$$(2) \quad h_a(k)(t+1) = h_a(k)(t) + \eta \cdot I_L(t) \cdot CRa(t-k),$$

in which the variable t is time.

For effecting the decorrelation according to the equation (1) or (2), the adapting means ADAP1 receive the interference signal CRa and its delayed versions and the output signal I_L of the summator 95 and all the factors $h_a(k)$ (bus 96a). Similar operations are carried out by the adapting means ADAP2 which act on the interference signal CRb to obtain the total decorrelation of the estimate $I_L(t)$ relative to the two interference signals. With each updating, new weighting factors are fed to the filter means 90a, 90b (bus 96a, 96b).

Fig. 4 represents a diagram of the processing which corresponds to, for example, the processing of signal CRa via an example restricted to four weighting factors. The signal CRa passes through three delay cells $70_1, 70_2, 70_3$. The signal on the input of the first cell and the output signals of the three cells are multiplied by the respective weighting factors $h_a(0), h_a(1), h_a(2), h_a(3)$ in multiplier means $72_0, 72_1, 72_2, 72_3$. Storage means 78_0 to 78_3 store the weighting factors. The results obtained are added together in a summator 77. The adapting means 92a adapt the weighting factors in accordance with equation (2). Let us consider the adaptation of the factor $h_a(0)$ performed at time t . A multiplier cell 73_0 performs the multiplication of the signal CRa by the estimate I_L . The result obtained is multiplied by an adaptation gain η in a multiplier cell 74_0 . The adaptation gain is stored in a means 75_0 . The result obtained is increased by the previous value of $h_a(0)$ so as to obtain the new weighting factor $h_a(0)$ at time $t+1$. An analogous process is carried out for the other weighting factors. The weighting factors of the filter means FILT2 are adapted similarly.

According to a particular embodiment it is possible to realize the adaptation not directly from the interference signals CRa, CRb and from the estimate I_L , but from the modified versions of these signals. The adaptation may thus be carried out in accordance with:

$$(3) \quad E[f\{I_L(t)\} \cdot g\{CRa(t-k)\}] = 0,$$

or, more particularly, in accordance with:

$$(4) \quad h_a(k)(t+1) = h_a(k)(t) + \eta \cdot f[I_L(t)] \cdot g[CRa(t-k)],$$

in which at least one of the functions $f(\cdot)$ or $g(\cdot)$ is a non-linear function. Similar equations

are applied to the filter FILT2.

For applying these functions, the diagram of Fig. 4 is modified by incorporating a means 69 for applying the non-linear function $g(\cdot)$ to the interference signal CRa and to each of its delayed versions and by incorporating a means 71 for applying the non-linear function $f(\cdot)$ to the estimate I_L before they are fed to the multiplier means 73₀. The means 69 and 71 are indicated in dashed lines in this Figure, because they may be omitted. The importance of these non-linear functions resides in the fact that this allows of obtaining a better speed and a better adaptation precision of the filters FILT1 and FILT2 by choosing functions $f(\cdot)$ and $g(\cdot)$ adapted to the signals to be processed either totally for all the coefficients or specifically for each coefficient.

The processing means 10 have been described on the basis of adaptive filter means which realize the described decorrelation. It is alternatively possible to carry out this decorrelation by utilizing adaptive source-separation means. In that case the interference signals are not regarded as unmixed signals, but processed as any signal.

Fig. 3 describes a recursive structure intended for producing three estimate signals: $I_{L1} = \langle X_L \rangle$, I_{L2} , I_{L3} . The processing means are thus source-separation means which comprise a plurality of adaptive filter units 111, 211, 311, 113, 213, 313. This structure comprises a first summator 112 which has an input 110 connected to the mixed signal Ea and an output 115 which produces the estimate signal I_{L1} . A second summator 212 has an input connected to the signal CRa and an output which produces the estimate signal I_{L2} . A third summator 312 has an input connected to the signal CRb and an output which produces the estimate signal I_{L3} . A second input of the first summator 112 is connected to the output of the second summator 212 via the adaptive filter unit 111 which filters the output signal of the second summator. A third input of the first summator 112 is connected to the output of the third summator 312 via the adaptive filter unit 113 which filters the output signal of the third summator.

Similarly, a second and a third input of the second summator 212 are connected to the output of the first summator 112 and of the third summator 312 respectively, via the respective filter units 211 and 213 which filter the output signal of the first and of the third summator, respectively.

Similarly, the third summator 312 is connected to the outputs of the other summators 112 and 212 via the filter units 311 and 313 which filter the output signal of the first and of the second summator, respectively.

The filter coefficients of the filter units are adapted in adapting means

ADAPT 105 to which the estimate signals I_{L1} , I_{L2} , I_{L3} are applied. Therefore, the adapting means 105 decorrelate the signals I_{L1} , I_{L2} , I_{L3} in accordance with the equations (1) to (4) in a manner described previously. Therefore, the signals CRa, CRb are replaced by one of the signals I_{L1} , I_{L2} , I_{L3} , that is to say, by the signal that is connected to the input of the
5 respective filter. Likewise, I_L is replaced by one of the signals I_{L1} , I_{L2} , I_{L3} , that is to say, by the output signal of the summator which receives on the input the output of the respective filter.

A person skilled in the art may conceive source separation means which have a direct structure or a mixed, recursive/direct structure.

10 The summators, the multiplier cells and the filter units may form part of a calculator, microprocessor or digital processing unit of the signal, which unit is programmed for carrying out the described functions.

Fig. 5 relates to the case where two speakers L1 and L2 may simultaneously send voice messages at the same location. To separate two speakers, or, more
15 generally, two signal sources, it is necessary to utilize two sensors which receive each different mixed signals Ea and Eb which are linked with the position of the speakers relative to the microphones. The mixed signals are formed by the same signals, only the mixtures are different. The same operating principles as those developed in the case of Fig. 1 are implemented. In the case where the interference signals are processed as non-mixed
20 interference signals, the processing means SEPAR 10 thus have two channels, each one comprising the means described with respect to Fig. 2. None the less, it is necessary to connect to the output two-input-source-separation means for separating the two speakers in accordance with the diagram shown in Fig. 3 reduced to two inputs. In the case where the interference signals are processed as mixed interference signals, the processing means
25 SEPAR 10 are thus formed in accordance with the diagram of Fig. 3 to which is added an additional channel for processing the mixed signal Eb by an adaptation of the diagram for processing the four input signals based on the same principle.

Fig. 6 relates to the case of an adapted processing system for processing signals exchanged in a teleconference over two-way channels 1, 2. A transmitting station ST1
30 transmits stereophonic signals I_{La} and I_{Lb} to two loudspeakers LS_{2a} and LS_{2b} of a receiving station ST2. The estimated signals of a station become the correlated electric signals which generate interference for the other station. Evidently, either station is alternately the transmitter and the receiver. In the transmitting station a speaker L2 utters a message. For transmitting a stereophonic message to the other station it is necessary to have two

microphones. The microphones M_{2a} and M_{2b} capture the message of the speaker as well as the sound broadcast by the loudspeakers. If there were no processing, the sound coming from the loudspeakers would continuously circulate between the two stations causing phenomena of echoes to occur which are very annoying for understanding the speakers.

- 5 To solve the stereophonic signal problem that has not been solved so far, processing means SEPAR1 and SEPAR2 which decorrelate the estimated signals relative to the stereophonic signals arriving from the loudspeakers are arranged in each station. A microphone, for example M_{1a} will be capable of receiving the message X_{La} coming from the speaker as well as the interference signals P_{aa} and P_{ba} coming from the respective
- 10 loudspeakers LS_{1a} and LS_{1b} . The microphone will then apply a mixed signal to the processing means SEPAR1. The two correlated electric signals which arrive at the loudspeakers are tapped before the loudspeakers and are fed to the separation means SEPAR1. An estimate of the speaker's message is made for each microphone by the processing means in the same manner as described previously with respect to one mixed
- 15 input signal and two interference signals. For two microphones, the means of Fig. 2 or Fig. 3 are doubled. Each station can thus isolate two estimates which are transmitted without echoes to the other station along the transmission channels 1 and 2.

- That which has been developed previously relates to the production of a correct estimate of the speaker's message. This message may itself contain multiple
- 20 information signals which have to be decoded. The situation is represented in the Figs. 1 and 5 in the case where, for example, a system is present in a motor car. Therefore, the estimate I_L is decoded in converter means VOCCD which decode controls contained in the speaker's message. A message may contain various controls C_L , C_J , C_K intended to act on various pieces of equipment of the system or on parts of the vehicle. More particularly, the control
- 25 C_L may request to control in return the equipment that produces the stereophonic signals. This may be, for example, a request by the speaker to lower the sound volume of the car radio that produces the stereophonic signals.

Another control C_J may call for varying another sound source S_J which forms part of the system, S_J being subjected to a similar processing.

- 30 Another control C_K may relate not to a sound signal source, but to the vehicle itself, for example, to driving an actuator S_K to set the wind screen wipers into operation.

CLAIMS:

1. A signal transmission system comprising processing means (SEPAR) for isolating an estimate (I_L) for at least one wanted signal (X_L) contained in at least one mixed signal (E_a), at least one sensor (M_a) for detecting the mixed signal, the mixed signal comprising at least the wanted signal (X_L) and at least two correlated interference signals
5 (Pa, Pb) which are produced by two sources (LSa, LSb) of the system in response to two respective correlated electric signals (CRa, CRb), characterized in that the processing means (SEPAR) receive on the input the detected mixed signal (E_a) and the two correlated electric signals (CRa, CRb) wherefrom the processing means extract the estimate (I_L) of the wanted signal (X_L) contained in the detected mixed signal by decorrelating via multiple shifts the
10 estimate (I_L) relative respectively to the correlated electric signals (CRa, CRb).
2. The system as claimed in Claim 1 in which the sensor is a microphone, the mixed signal is an ambient sound signal captured at the listening end by the microphone, the wanted signal is a voice message sent by a speaker (L) at the listening end, the voice message is interfered by stereophonic signals broadcast by loudspeakers which form the
15 sources, characterized in that the processing means extract the estimate of the voice message contained in the ambient sound signal by decorrelating the estimate of the voice message relative respectively to the stereophonic signals.
3. The system as claimed in Claim 2, characterized in that the processing means are followed by means (VOCCD) for converting the estimate of the voice message
20 into a voice control (C_L).
4. The system as claimed in Claim 3, characterized in that the voice control (C_L) acts in return on the stereophonic signal sources (LSa, LSb).
5. The system as claimed in Claim 2, the system being a teleconference system comprising a transmitting station (ST1) and a receiving station (ST2) interconnected
25 by at least an up (1) and at least a down channel (2), the stations comprising each at least two microphones (M) and at least two loudspeakers (LS) broadcasting two stereophonic signals (CRa, CRb), characterized in that the processing means (SEPAR) eliminate undesirable echoes generated by the stereophonic signals arriving at the transmitting station (ST1) coming from the receiving station, the transmitting station transmitting in stereo only

the estimates (I_{La} , I_{Lb}) of the local voice message to the loudspeakers of the receiving station.

6. The system as claimed in Claim 1 in which the sensor is an antenna, the mixed signal captured by the antenna comprises the wanted signal formed by a radio broadcast signal and correlated interference signals coming from interference sources, characterized in that the processing means extract the estimate of the radio broadcast signal contained in the mixed signal by decorrelating via various shifts the estimate of the radio broadcast signal relative to correlated electric signals.

7. The system as claimed in one of the Claims 1 to 6, characterized in that the processing means comprise a plurality of adaptive filter means (90a, 90b) for respectively filtering each correlated electric signal (CRa, CRb) and a plurality of adapting means (92a, 92b) for adapting each respective adaptive filter means, the adapting means decorrelating via various shifts the estimate signal relative to each correlated electric signal.

8. The system as claimed in one of the Claims 1 to 6, characterized in that the processing means comprise source separation means (111, 112, 113) (211, 212, 213) (311, 312, 313) for separating the wanted signals contained in a plurality of mixed signals, the source separation means producing respective estimate signals for the wanted signals contained in the mixed signals, the source separation means comprising a plurality of adapting means (105) for adapting the source separation means by decorrelating via various shifts each estimate of each source relative to the plurality of estimates of the other sources.

9. The system as claimed in Claim 7 or 8, characterized in that the estimates (I_L) (I_{L1} , I_{L2} , I_{L3}) and/or the correlated electric signals (CRa, CRb) are subjected to a preliminary action of non-linear functions.

