

Capacitive sensor circuit

This Sheet Has Been Replaced



The invention relates to a capacitive sensor circuit comprising: a sensor electrode forming a first plate of a sensing capacitor; a first inverting amplifier, having an input connected to the sensor electrode and having an output; a second amplifier, having an input coupled to the output of the first inverting amplifier and having an output; a feedback resistor connected between the output and the input of the first inverting amplifier.

Such a sensor circuit is known from European Patent Application No. EP 0,524,708, where the circuit is used to turn on a personal-care apparatus when it is lifted by the user of the apparatus and to turn off the apparatus when the apparatus is put down. The sensor electrode, the first inverting amplifier and the feedback resistor form an oscillator, also referred to as an astable multivibrator, whose oscillation frequency is dictated *inter alia* by the value of the feedback resistor and by the magnitude of the capacitance between the sensor electrode and the signal earth terminal of the capacitive sensor circuit. The oscillation frequency decreases as the capacitance increases. When the user picks up the apparatus the capacitance relative to earth is comparatively high and the frequency is comparatively low. If the apparatus has been put down the capacitance relative to earth is comparatively low and the frequency is comparatively high. The frequency difference or the frequency ratio between the comparatively low and the comparatively high oscillator frequency is measured by means of a frequency-to-voltage converter and is converted into a voltage difference, which energises a switch to turn on the apparatus. The second amplifier then serves as a buffer between the oscillating first inverting amplifier and the frequency-to-voltage converter. This known capacitive sensor circuit is fairly susceptible to spreads in properties and values of the components used. It is known, *inter alia* from European Patent Specification EP 0,104,422, to compare the oscillation frequency with that of a second oscillator which comprises a reference capacitance relative to earth. The capacitance of the sensor electrode is compared with the capacitance of the reference capacitor by means of a frequency measurement. A gate circuit provides a signal which

E-158022

is a measure of the oscillation frequencies. This known solution can be accurate but requires the use of a gate circuit or some other coincidence circuit.

It is an object of the invention to provide a capacitive sensor circuit which is accurate but does not require such a coincidence circuit, so that it is possible to save
5 components.

To this end, according to the invention, a capacitive sensor circuit of the type defined in the opening paragraph is characterised in that a series resistor is connected between the output of the first inverting amplifier and the input of the second amplifier, which series resistor has a resistance value substantially equal to the
10 resistance value of the feedback resistor; a reference capacitor is connected between the input of the second amplifier and a reference terminal, which reference capacitor has a capacitance value substantially equal to a predetermined value of the capacitance of the capacitive sensor electrode relative to the reference terminal; and in that the first inverting amplifier and the second amplifier are constructed as Schmitt triggers having
15 substantially the same low and high input threshold voltages.

By means of these steps it is achieved that a d.c. level appears on the output of the second amplifier when the capacitance of the sensor electrode is smaller than the reference capacitance and that an alternating voltage of the same frequency as the oscillating first inverting amplifier appears on the output of the second amplifier in
20 the opposite case. The change from direct voltage to alternating voltage is hardly susceptible to tolerances and can be detected reliably by means of a frequency-to-voltage converter, which converter now merely serves to detect whether a signal is a direct voltage of zero frequency or an alternating voltage of non-zero frequency. In order to minimise the influence of component spreads the first and the second amplifier are
25 preferably identical NAND Schmitt triggers accommodated in one semiconductor body.

The capacitive sensor circuit is suitable for turning on and turning off all kinds of electrical apparatuses having a handle, such as electric toothbrushes, shavers, irons, hair driers, drills, vacuum cleaners, and for turning on and turning off electrical equipment having touch controls, such as audio and video equipment, ovens, cook-tops
30 and the like.

These and other aspects of the invention will now be described and elucidated with reference to the accompanying drawings, in which





Figure 1 shows a circuit diagram of a capacitive sensor circuit in accordance with the invention,

Figure 2 shows a circuit diagram of an electrical apparatus comprising a capacitive sensor circuit in accordance with the invention, and

5 Figure 3 shows a hair drier having a capacitive sensor circuit in accordance with the invention built into its handle.

In these Figures parts having the same function or purpose bear the same reference numerals.

Figure 1 shows a capacitive sensor circuit in accordance with the invention. A first inverting amplifier 2, in the form of a Schmitt trigger, has its input 4 connected to its output 6 via a feedback resistor 8. Two capacitors are situated between the input 4 and a reference terminal 10, which functions as signal earth for the sensor circuit. A first capacitor is formed by a parasitic input capacitor 12 having a value C_{p1} and a second capacitor is formed by the capacitance C_s of a sensing capacitor 14, having a first plate formed by a sensor electrode 16 connected to the input 4. The second plate is formed by the reference terminal 10 which, if desired, may also be connected to a second sensor electrode 18. For mains-powered apparatuses having a handle it is adequate to build only the sensor electrode 16 into the handle. The reference terminal 10 is then coupled to the mains earth via the power supply of the sensor circuit. The capacitance C_s relative to earth changes when the user takes hold of the handle. Now it is also possible to detect a hum voltage V_m of mains frequency, which hum voltage is symbolised by an alternating voltage source 20 between the second sensor electrode 18, if present, and the reference terminal 10. The inverting amplifier 2, the feedback resistor 8 and the two capacitors 12 and 14 form an oscillator whose oscillation frequency F_s decreases as the overall capacitance $C_{p1} + C_{p2}$ of the capacitors 12 and 14 increases. In the afore-mentioned apparatus with a sensor electrode 16 in the handle the oscillation frequency F_s will be comparatively low if the apparatus is held by the handle and it will be comparatively high if the apparatus is put aside. When the detected hum voltage V_m is very high there will no longer be a free oscillation and the oscillation frequency F_s will be pulled to the mains frequency. The output of the first inverting amplifier 2 is connected to the input 24 of a second inverting amplifier 26, also formed by a Schmitt trigger, via a series resistor 22. The

input 24 is connected to the reference terminal 10 via a parasitic capacitor 28 of a value C_{p2} and a reference capacitor 30 of a value C_r .

In order to simplify a rough calculation of the oscillation frequency F_s it will be assumed, although this is not essential for the operation of the capacitive sensor circuit, that the average value of the low threshold voltage V_l and the high threshold voltage V_h lies halfway the supply voltage V_{cc} and that their difference voltage is V_n :

$$V_h = 1/2 * (V_{cc} + V_n); V_l = 1/2 * (V_{cc} - V_n) \quad (1)$$

During oscillation the voltage $V(t)$ across the overall capacitance at the input 4 will vary between the low threshold voltage V_l and the high threshold voltage V_h within one period T . The voltage across the overall capacitance will vary in accordance with:

$$V(t) = V_0 * \exp(-t/\tau) \quad (2)$$

15

Here, V_0 is the initial voltage, $\tau = R_l * (C_s + C_{p1})$ and R_l is the value of the feedback resistor 8. When $t = T/2$, $V(T/2) = V_l$ and $V_0 = V_h$ the following will be valid for one half period:

$$T/2 = \tau * \ln \{(V_{cc} + V_n)/(V_{cc} - V_n)\} = \tau * \ln \{(1+\alpha)/(1-\alpha)\} \quad (3)$$

where $\alpha = V_n/V_{cc}$. For a small value of α equation (3) can be reduced to the following approximation:

$$T = 4 * \tau * \alpha = 4 * R_l * (C_s + C_{p1}) * V_n/V_{cc} \quad (4)$$

This Sheet Has Been Replaced



The oscillation frequency F_s is therefore approximately equal to:

$$F_s = V_{cc} / \{4 * V_n * R_l * (C_s + C_{p1})\} \quad (5)$$

30

At the output 6 a squarewave voltage appears which charges and discharges the capacitors 28 and 30 via the series resistor 22. This results in a ripple voltage across the capacitors 28 and 30, whose peak-peak voltage V_{pp} is approximately equal to:



$$V_{pp} = V_{cc} / \{4 * F_s * R_2 * (C_r + C_{p2})\} \quad (6)$$

If R_2 is now selected to be equal to R_1 and equation (5) is substituted in equation (6) it follows that:


5

$$V_{pp} = V_n * (C_s + C_{p1}) / (C_r + C_{p2}) \quad (7)$$

If now for the second inverting amplifier 26 a Schmitt trigger is used having the same voltage difference V_n between the high and the low threshold voltage as for the first inverting amplifier 2 the following is achieved. V_{pp} is smaller than V_n if C_s is smaller than C_r , so that the two trigger thresholds V_n and V_h of the second inverting amplifier 26 are not exceeded and a d.c. level appears on the output 32 of this amplifier. V_{pp} is larger than V_n if C_s is larger than C_r , so that the two trigger thresholds V_n and V_h are exceeded periodically and an a.c. signal with the oscillation frequency F_s appears on the output 32. The voltage difference V_n is substantially equal for the inverting amplifiers 2 and 26 if the amplifiers are identical and are integrated on one semiconductor body. This has the additional advantage that the parasitic capacitors C_{p1} and C_{p2} are then also substantially equal and the influence of these parasitic capacitors on the amplitude of V_{pp} is eliminated. The resistors 8 and 22 have equal values. A parasitic capacitance parallel to these resistors will then neither have any effect on the ripple voltage V_{pp} because a strictly symmetrical load is seen from the output 6 to reference terminal 10.

Thus, it is achieved that the output 32 supplies an a.c. signal if C_s is larger than C_r and a d.c. signal if C_s is smaller than C_r , inaccuracies as a result component spreads being largely eliminated owing to the symmetry of the circuit.

25 Detection whether the output 32 carries an a.c. or a d.c. signal is possible by means of a comparator 34, which is also formed by an inverting Schmitt trigger and which has an input 36 and an output 38, which input 36 receives a signal from the output 32 of the second inverting amplifier 26 via a charge pump 40. The charge pump 40 comprises a first capacitor 42 connected between the output 32 and a node 44, a first diode 46, 30 having its cathode connected to the node 44 and its anode to the reference terminal 10, a second diode 48, having its anode connected to the node 44 and its cathode to the input 36, and a resistor 50 and a capacitor 52, which are connected between the input 36 and the reference terminal 10.



The charging current i through the capacitor 42 per oscillation period $1/F$ is approximately equal to:

$$i = C_1 * (V_{cc} - 2*V_j - V_2) * F = V_2 / R_3 \quad (8)$$

5 In this equation C_1 is the value of the capacitor 42, V_j is the junction voltage of the diodes 46 and 48, V_2 is the voltage across the capacitor 52, and R_3 is the value of the resistor 50. If the threshold voltages of the comparator 34 lie approximately halfway the supply voltage V_{cc} the voltage V_2 must be equal to $V_{cc}/2$ at the minimum frequency F_1 10 and the following equation is valid:

$$F_1 = V_{cc} / \{R_3 * C_1 * (V_{cc} - 4*V_j)\} \quad (9)$$

As stated hereinbefore the oscillation frequency may be equal to the detected mains 15 frequency. When $F_1 = 20$ Hz, $V_{cc} = 5$ V and $V_j = 0.7$ V it follows from equation (9) that the time constant R_3*C_1 has a value of approximately 114 ms. The capacitor 52 provides some delay in the change-over of the comparator 34.

Figure 2 shows the capacitive sensor circuit of Figure 1 used in an electrical apparatus. The inverters 2, 26 and 34 are implemented by means of dual input 20 Schmitt trigger NANDs. The output 38 of the inverter 34 drives the base of an NPN switching transistor 56 via a fourth dual input Schmitt trigger NAND 54 and a current limiting resistor 74, the emitter of said switching transistor being connected to the reference terminal 10 via a light-emitting diode (LED) 58 and the collector of this transistor driving the energising coil 62 of a relay 64 via an interrupter switch 60. The 25 relay and the NANDs receive their supply voltage from a supply voltage source, not shown, which may comprise a rectifier circuit, not shown. The relay actuates a switch 66, which is arranged in series with a load 72 between mains voltage terminals 68 and 70. The load 72 may be, for example, a motor, a heating element, a lamp or any other device to be turned on and turned off.

30 At comparatively low oscillation frequencies, *i.e.* when the sensor electrode 16 is approached as in the case that the apparatus is taken hold of, an a.c. signal appears on the output 32, so that the input 36 is high. The output 38 is then low and the transistor 56 is turned on via the inverter 54. The energising coil 62 of the relay

64 is energised, the switch 66 is closed and the load 72 receives mains voltage. By means of the interrupter switch 60 the power supply to the energising coil 62 can be interrupted to render the electrical apparatus inoperative. The LED 58 signals that the load is connected to the mains *via* the switch 66. When the apparatus is put aside the oscillation frequency is comparatively high, the output 32 is then continually high and the input 36 is low, so that the output 38 is high and the transistor 56 receives no base current. Now the relay 64 is not energised, the LED 58 is turned off and the load 72 is disconnected from the mains voltage. Thus, the relay is energised in response to the a.c./d.c. signal on the output 32 of the second inverting amplifier 26.

10 The second amplifier 26 may alternatively be non-inverting because this is irrelevant for the decision whether an a.c. signal or a d.c. signal is present on the output 32. The value C_r of the reference capacitor 30 depends on the envisaged values of the sensing capacitor 14.


15 Figure 3 shows an electric hair drier having a handle 74, in which the sensor electrode 16 is mounted. The capacitive sensor circuit and the other electronic devices of Figure 2 are accommodated on a p.c. board 76, which is also mounted in the handle 74.

This Sheet Has Been Replaced



Claims

This Sheet Has Been Replaced



1. A capacitive sensor circuit comprising: a sensor electrode (16) forming a first plate of a sensing capacitor (14); a first inverting amplifier (2), having an input (4) connected to the sensor electrode (16) and having an output (6); a second amplifier (26), having an input (24) coupled to the output (6) of the first inverting amplifier (2) and
5 having an output (32); a feedback resistor (8) connected between the output (6) and the input (4) of the first inverting amplifier (2), characterised in that a series resistor (22) is connected between the output (6) of the first inverting amplifier (2) and the input (24) of the second amplifier (26), which series resistor (22) has a resistance value substantially equal to the resistance value of the feedback resistor (8); a reference
10 capacitor (30) is connected between the input (24) of the second amplifier (26) and a reference terminal (10), which reference capacitor (30) has a capacitance value substantially equal to a predetermined value of the capacitance of the capacitive sensor electrode (16) relative to the reference terminal (10); and in that the first inverting amplifier (2) and the second amplifier (26) are constructed as Schmitt triggers having
15 substantially the same low and high input threshold voltages.
2. A capacitive sensor circuit as claimed in Claim 1, characterised in that the first amplifier (2) and the second amplifier (26) are identical NAND Schmitt triggers accommodated in one semiconductor body.
3. A capacitive sensor circuit as claimed in Claim 1 or 2, characterised in
20 that the capacitive sensor circuit further comprises: a comparator (34) having an input (36) and an output (38); and a charge pump (40) comprising a first capacitor (42) connected between the output (32) of the second amplifier (26) and a node (44), a first diode (46) connected between the node (44) and the reference terminal (10), a second diode (48) connected between the node (10) and the input (36) of the comparator (34),
25 one (48) of said first (46) and second (48) diodes having its anode connected to the node (44) and the other one (46) of said first (46) and second (48) diodes having its cathode connected to said node (44), a resistor (50) and a second capacitor (52), both connected between the input (36) of the comparator (34) and the reference terminal (10).

4. A capacitive sensor circuit as claimed in Claim 3, characterised in that the comparator (34) is a Schmitt trigger having threshold voltages which lie substantially halfway the supply voltage of the Schmitt trigger.
5. An electrical apparatus comprising a load (72) and a controllable switch (56, 62, 64, 66) having a main current path (66) arranged in series with the load (72) and having a main current path (56, 62) for receiving a control signal for turning on and turning off the controllable switch (56, 62, 64, 66) in response to a signal from the output (32) of the second amplifier (26) of a capacitive sensor circuit as claimed in Claim 1, 2, 3 or 4.
- 10 6. An electrical apparatus as claimed in Claim 5, characterised in that the electrical apparatus has a handle (74) which accommodates the sensor electrode (16).



This Sheet Has Been Replaced

