


REPLACED SHEETS		SG
☐ Description	: paged 1 to paged 7	
☐ Claim(s)	: paged 8 to paged 9	
☐ Drawing(s)	: paged 43 to paged 3/3A	
☐ Abstract	: paged 10 to paged -	
DATE OF RECEIPT		

9602639-8 IPOS

1

DUPLICATE

This Sheet Has Been Replaced



DETECTOR CIRCUIT FOR USE IN A VCR

The subject application concerns the field of videocassette recorders (VCRs) and apparatus for programming them.

- 5 The subject application is related to U.K. Patent applications entitled "VCR Control of a Cable Converter Unit", "An IR LED Assembly for VCR Control of a Cable Converter Unit", "ON/OFF Control of a Cable Converter Unit by a VCR", "Automatic Detection of Kind of Cable Converter Unit Coupled to a VCR", and "VCR Control of Cable Converter Unit", all filed on even date claiming priority from U.S. Patent applications Nos: 807,472; 806,916; 806,551; 806,918; and 807,068 respectively.

- 15 When a television set owner is a subscriber to a cable television system and also possesses a videocassette recorder (VCR), he may be required to connect to the cable system via a cable decoder box (also called a CATV converter, or a set-top converter). This connection may be required, because in these systems, many cable channels (i.e., the so-called premium channels) are scrambled (i.e., encoded or encrypted) and must be descrambled (i.e., decoded or decrypted) in the cable box. The cable box descrambles the premium channel and converts its RF carrier frequency from its assigned cable channel frequency to a cable box output frequency, normally that of channel 2, 3, 4, or 5 for reception and recording by the VCR, or display by the television receiver. In such an arrangement the viewer may have as many as three remote control units for controlling the video equipment (i.e., one each for a television set, a VCR, and the cable box).

- 30 Recently, a programming simplification system known as VCR PLUS™, manufactured by Gemstar Development Corporation, Pasadena, California, has become available. Briefly, the apparatus of the VCR PLUS™ system resembles a standard remote control handunit. The handunit is preprogrammed with the codes for controlling the VCRs and cable control boxes of many manufacturers. The handunit is then programmed by the user with a unique code comprising 1 to 8 digits, which code corresponds to a particular television show broadcast on a given channel, at a given time and date, and having a given duration. A



television show which is broadcast at the most popular viewing time (for example, 7 pm) may have a code which comprises only 1 digit. Conversely, a television show which is broadcast at the least popular viewing time (for example, 3 am) may have a code which comprises the full 8 digits. These codes are printed in the channel guide section of the viewer's local newspaper along with the normal time and channel information. After entering the unique 1 to 8 digit code for a particular television show to be recorded, the user places the handunit in a cradle mounted on his VCR to ensure that the handunit is in the proper orientation for transmitting data to the IR (infrared) receiver of the VCR and to the cable box. At the proper time, the VCR PLUS™ handunit transmits IR codes to the cable box to turn it on and tune it to the desired channel, and to the VCR to turn it on and program it to record the desired television show.

Unfortunately, the stand alone VCR PLUS™ handunit operates in an "open-loop" mode. That is, the VCR PLUS™ handunit has no way of knowing if its commands were actually received and executed by either the VCR or by the cable box because no feedback signal to the VCR PLUS™ handunit exists.

Apparatus in accordance with the subject invention controls a cable box (i.e., the source of its own video input signals), and monitors the television signals received from the cable box, in a "closed loop" manner. By monitoring an appropriate signal the controller of the VCR can detect perturbations of signal level which indicate that the cable box has changed channels. It is herein recognized that such an appropriate signal can be taken across the filter capacitor of a sync/AGC portion of a video processor of the VCR.

An exemplary embodiment of the invention will now be described with reference to the following figures:

FIGURE 1 shows, in block diagram form, a VCR incorporating the subject invention.

FIGURES 2a and 2b are views of a VCR incorporating the invention.

FIGURE 3 is a detailed view of the SYNC/AGC detector of FIGURE 1.



Referring to FIGURE 1, radio frequency (RF) signals are applied to an RF input terminal of a tuner assembly 102. Tuner assembly 102 selects a particular RF signal under control of a tuner control unit 104 which applies a tuning control signal to tuner assembly 102 via a wire 103, and applies bandswitching signals via a control bus 103'. Tuner control unit 104 is controlled by a controller 110. Controller 110, which may be a microprocessor or microcomputer, includes a central processing unit (CPU) 112, a read-only memory (ROM) 114, a random access memory 116, and an external electrically-erasable read only memory (EEPROM) 117. Controller 110 generates a control signal for causing tuner control unit 104 to control tuner 102 to select a particular RF signal, in response to user-entered control signals from a local keyboard 120 and from an infrared (IR) receiver 122. IR receiver 122 receives and decodes remote control signals transmitted by a remote control unit 125.

Tuner 102 produces a signal at an intermediate frequency (IF) and applies it to a processing unit 130 comprising a video IF (VIF) amplifying stage, an AFT circuit, a video detector, and a sound IF (SIF) amplifying stage. Processing unit 130 produces a first baseband composite video signal (TV), and a sound carrier signal. The sound carrier signal is applied to an audio signal processor unit 135 which includes an audio detector and may include a stereo decoder. Audio signal processor unit 135 produces a first baseband audio signal and applies it to a signal switch unit 137. Second baseband composite video signals and second baseband audio signals may be applied to VIDEO IN and AUDIO IN terminals from an external source.

The first and second baseband video signals (TV) are coupled to a video processor unit 155 (having a selection circuit not shown) and is also applied to signal switch unit 137. Video and audio signals are also applied to a tape recorder unit 165 which causes the signals to be recorded onto video tape. Tape recorder unit 165 has a control input and operates under control of a tape recorder unit controller 160, which may be a microprocessor. Tape recorder unit controller 160 is in turn controlled by control signals from controller 110. Under control



of controller 110, an on-screen display processor 140 generates character signals, and applies them to a second input of video signal processor 155, for inclusion in the processed video signal. Signal switch unit 137 is controlled by controller 110 via a control input terminal C to select audio and video signals from audio signal processor 135 and video signal processor 155, or from the output terminals of tape recording unit 165 in the playback mode, and to apply the selected signals to a modulator 139 for modulation onto a particular channel frequency carrier, typically that of channel 3 or channel 4. That portion of the circuitry shown in FIGURE 1 which has been described thus far is known from RCA videocassette recorder model VR520.

Unlike the RCA VR520, which has as its main programming feature a TIMER PROGRAM mode of operation, apparatus according to the subject invention may include both a TIMER PROGRAM programming feature and a VCR PLUS™ programming feature. The control program for the above-mentioned features resides in ROM 114 of controller 110. Electrically-erasable programmable read only memory (EEPROM) 117 is coupled to controller 110, and serves as a non-volatile storage element for storing autoprogramming channel data, user-entered channel data, and VCR PLUS™ channel mapping data.

An IR LED driver circuit, generally, designated 100, is coupled to controller 110, for providing IR signals to external units, such as a cable box for a cable TV service. IR LED driver circuit comprises a filter capacitor C102, a current-limiting resistor R102, three series-connected IR LEDs (infrared light emitting diodes) D101, D102, and D103, a darlington-connected transistor switch Q101, a base resistor R101, and a speed-up capacitor C101.

Processing unit 130 also produces an IF AGC signal which is coupled to controller 110 via a wire 131, for detection of variation of the signal strength of signals of currently-tuned channels, the changes being indicative of channel changes. Alternatively, video signal processor 155 produces a valid sync detection signal (or a video AGC signal) which is coupled to controller 110 from a SYNC/AGC DETECTOR 156 via a wire 151, for



detection of valid TV sync, changes in the detection of valid TV sync being indicative of channel changes.

It is herein recognized that it is a clear advantage for the unit which contains the VCR PLUS™ control code (in the subject case, the VCR) for controlling the cable box, to be coupled to the television antenna line, so that the controller can determine whether or not the cable box is actually responding to transmitted IR commands. Copending U.S. patent application bearing attorney docket number RCA 86,660 concerns the problem that there are about 44 different cable box IR remote control command formats. With an "open loop" type of system, such as implemented in the VCR PLUS™ handunit, the controller has no way of knowing if the cable box responds to the transmitted command or not. Thus, if the cable box is inadvertently switched to select the wrong cable box command code format, the desired channel change will not be accomplished, and the desired program will not be recorded. In contrast, apparatus according to U.K. Patent Application entitled "Automatic Detection of Kind of Cable Converter by a VCR" controls the cable box (i.e., the source of its own video input signals), and monitors the television signals received from the cable box, in a "closed loop" manner. By monitoring the SYNC/AGC signal from video processor 155 of FIGURE 1, controller 110 can detect perturbations of the signal level which indicate that the cable box is, in fact, receiving and executing commands as indicated by the fact that it can change channels.

Advantageously, if a signal which tracks a characteristic of the baseband video signal (such as Valid Sync Detect or baseband video AGC) is used for detecting loss of signal during channel change, then the subject invention is applicable to use with cable boxes which produce decoded cable television signals at baseband rather than remodulating them to a particular television channel frequency.

The present invention will be further described with reference to FIGURES 2a and 2b, and 3.

FIGURE 2a is a perspective view of a cable box placed VCR 200 having a , In FIGURE 2b, VCR 200 is shown coupled to the RF input via cable box 210. Tuner 102 of FIGURE 2b is the same tuner unit 102 previously described with respect



to FIGURE 1. It is common practice for cable television services to encode (i.e., scramble) at least their "Premium" channels. FIGURE 2b is a configuration which may be used when some or all of the television channels provided by the cable television service are encoded in some fashion (i.e., a cable box is required for decoding). In such a configuration, the VCR will be set to record all television programs on the cable box output channel (typically, channel 2, 3, or 4). Cable box 210 of FIGURES 2a and 2b includes a window 212 for admitting an IR (infrared) remote control signal for turning the cable box on and off, and for causing the tuner of the cable box to change channels. VCR 200 of FIGURE 2a includes a window 204 for admitting an IR (infrared) remote control signal for turning the VCR on and off, for causing the tuner 102 of the VCR to change channels, and for controlling the recording and playback of videotapes. VCR 200 also includes a window 214 through which IR signals generated by the VCR are transmitted to external units such as cable box 210. Note from FIGURE 2b that cable box 210 preferably receives IR signals from window 214 of VCR 200 along a rearward directed path 216, and from a "bounce" path 218 in which the IR signals may be reflected from a wall or other object 220. The rearward direction of the IR light provides more assurance that the VCR-generated IR commands will reach the cable box. It is important to note that because the "bounce" IR light path 218 is always longer than the more direct rearward path 216, more IR power is required to ensure remote control signal reception at the cable box. For this reason, two IR LEDs are directed along the longer bounce path. The two generally forward-facing LEDs may also be angled outward from each other (i.e., along diverging paths) in order to cover more area and increase the chance of reflecting a signal back to the cable box. The "bounce" path is provided for the case in which the user chooses not to place the cable box on top of the VCR.


Referring to FIGURE 3, a video processor integrated circuit 155, which may be an AN3248NK manufactured by Toshiba, includes a terminal to which an external filter capacitor C300 is to be connected. Heretofore, no external circuitry has been connected across external filter capacitor C300. It is herein recognized that when an external source of television signals such



as a cable box, changes channels a large and rapid signal level change is developed across filter capacitor C300, and that the large signal change can be detected, amplified, and applied to controller 110 as a feedback signal for channel change commands transmitted to the cable box.

Normally, there is only a small ripple on the signal level across filter capacitor C300. When there is a large change in television signal level, such as what happens between channels when the tuner of the cable box is changing, the ripple in the voltage across filter capacitor C300 increases to approximately 2 volts peak-to-peak. Coupling capacitor C301 removes the DC component from the "ripple" signal and applies the signal to a common emitter configured transistor amplifier Q301 via a base current limiting resistor R301. Positive-going transitions of the ripple signal turn Q301 on. The output signal is taken at the junction of the collector of Q301 and its collector resistor R302. The output signal comprises negative-going signals having pulse widths from 0.1 milliseconds to 5 milliseconds, and averaging about 1 millisecond in duration. Diode D301 and resistor R301 form a clamp circuit which clamps the negative-going transitions of the ripple signal. Capacitor C302 is optional, but has been found to limit some of the high frequencies, and reduce false triggering.

Although the VCR PLUS™ system is referred to in the subject specification, it is herein recognized that the subject invention does not require the use of the VCR PLUS™ system and is extremely useful with standard timer recording.

CLAIMS

1. A videocassette recorder, comprising:
a radio frequency (RF) signal input terminal, for receiving a group of RF signals;
tuner means coupled to said RF signal input terminal for receiving said group of RF signals, said tuner means selecting a particular RF signal from said group of RF signals in response to a control signal, said tuner means being capable of tuning to a predetermined number of channels;
video processing means coupled to said tuner means for processing received video signals;
control means for generating said control signal for causing said tuner means to select said particular RF signal;
means, coupled to said control means, for entering data in response to operation by a user; and
means coupled to said control means for transmitting a remote control signal for controlling an external source of said particular RF signal;
said control means in response to data entered by said user generates said remote control signals and applies said remote control signals to said remote control signal transmitting means; and
means for detecting perturbations of signal level at a SYNC/AGC output filter terminal of said video processor means, producing a detection signal in response thereto, and applying said detection signal to said control means;
said perturbation serving as a feedback signal to ensure that commands corresponding to said remote control signals are executed.

2. The videocassette recorder of claim 1, wherein said means for transmitting is an IR LED assembly, and said remote control signals are IR signals.



This Sheet Has Been Replaced



9

3. The videocassette recorder of claims 1 or 2, wherein said means for detecting perturbations of signal level comprises an amplifier.
4. The videocassette recorder of claim 3, wherein said amplifier is an AC-coupled amplifier.
5. The videocassette recorder of any preceding claim, further comprising:
 - a baseband video signal input terminal, for receiving a baseband video signal;
 - said video processing means being coupled to said baseband video signal input terminal, for processing received video signals;
 - said means for transmitting a remote control signal controlling an external source of said baseband video signal.
6. A videocassette recorder comprising means for receiving a signal from a cable box, means for controlling the cable box, and means for detecting perturbations in the signal level and signalling the means for controlling in response to a signal perturbation.
7. A videocassette recorder substantially as herein described with reference to the accompanying drawings.