

ELECTRONIC MAGNETORESISTIVE SENSOR BIASING

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to magnetoresistive (MR) sensor biasing. More particularly, the present invention relates to magnetoresistive sensor biasing methods and circuits.

2. Description of the Related Art

For the purpose of this disclosure, the terms "magnetoresistive (MR) sensor" and "MR head" both encompass any magnetoresistive element used for detecting a varying magnetic field by detecting a change in resistance ΔR_s of the element resistance R_s caused by variations in the magnetic field. Also for purposes of this disclosure, the terms MR sensor and MR head are both not limited to magnetic recording elements only. Examples of embodiments of MR sensors that are contemplated to be within the scope of these two terms include, but are not limited to, barber pole MRs, dual MRs, soft adjacent layer MRs, differential MRs, spin valve MRs, tunnel junction MRs and giant MRs.

An MR sensor is an energetically passive sensor that uses a sense current (or voltage) for detecting a change in sensor resistance in the form of a signal voltage or signal current. The sense current may also be used for providing all or part of a magnetic bias for the sensor that is needed for proper MR sensor

operation. This disclosure does not distinguish between sense and bias current (or voltage). The terms (MR sensor) bias current and voltage are used interchangeably throughout this disclosure. The biasing and readout electronics associated with an MR sensor are generally referred to as an arm electronic (AE) module.

The physical characteristics of an MR sensor are determined by the properties of the materials used, the MR sensor sandwich configuration, and the sensor dimensions, that is, the thickness, height and length of the sensor. The dimension having the greatest tolerance in externally exposed MR sensors used for magnetic recording is the sensor height h . The tolerance on this dimension is for compensating for head wear and lapping for tape heads, and for ABS lapping for disk drive heads.

Figure 1(a) shows the physical relationships between the different resistances forming the total MR head resistance R_H . Figure 1(b) shows a schematic diagram for an electrical model of resistance R_H . The total MR head resistance R_H is measured at terminals 10 and 11 of the AE module. The MR head and the AE module are shown as part of a disk drive 12 in Figure 1(a). The portion of the total MR head resistance that varies in accordance with a varying magnetic field is the sensor resistance R_s , with the resulting change in resistance being indicated as ΔR_s . Resistance R_s varies inversely proportional to the sensor height h . The total head lead resistance R_l is the resistance of the wires to the pre-amplifier of the AE module and the resistance of

the back-leads BL-inside the MR head. Lastly, the total front-lead resistance of the MR head is indicated as R_f . Resistance R_f also varies inversely proportional to the sensor height h . However, R_f shows no signal variations for varying magnetic field. Equations (1)-(4) represent these principles in symbolic notation.

$$R_H = R_l + R_f + R_s \quad (1)$$

$$R_f, R_s \propto 1/h, \quad (2)$$

$$h = \text{sensor height}, \quad (3)$$

and

$$R_s = R_{s0} \pm \Delta R_s \text{ (signal induced)}. \quad (4)$$

In Figures 1(a) and 1(b) and throughout the following disclosure, bias current I_B equals head bias current I_H . The voltage V_H is the bias voltage appearing across the total MR head resistance R_H . Voltage V_b is the bias voltage appearing across sensor resistance R_s and front lead resistance R_f . Voltage V_s is the bias voltage appearing across sensor resistance R_s . Height h is the physical height of the sensor.

There are three conventional approaches for providing MR sensor biasing: a constant bias current scheme; a constant bias voltage scheme; and an adjusted bias current scheme for attaining constant bias voltage. The term "constant" as used when referring to biasing schemes indicates a biasing invariability

from sensor to sensor in view of manufacturing tolerances. For a conventional constant bias current scheme, the same bias/sense DC current is applied to all MR heads by AE modules during manufacturing of a product regardless of the respective head resistances, sensor heights, etc., of the MR heads. Figures 2(a) and 2(b) illustrate an example of biasing conditions for an MR head for different sensor resistances R_H for a conventional constant bias current I_B scheme. If I_B in Figure 2(a) is 10 mA, for example, Figure 2(b) shows that the head bias voltage V_H varies accordingly between 200 mV and 500 mV as R_H varies between 20 and 50 Ohms.

For a conventional constant bias voltage scheme, the same bias/sense DC voltage is applied to all MR heads in a product by an AE module. Figures 2(c) and 2(d) illustrate exemplary bias conditions for an MR head for different sensor resistances R_H for a conventional constant bias voltage V_B scheme. If the bias voltage V_B appearing across the sensor resistance R_S in Figure 2(d) is 500 mV, for example, Figure 2(c) shows that the bias current I_H through the MR head varies inversely proportional to the total head resistance R_H .

U.S. 5,309,294 to Cahalan, issued May 3, 1994, discloses voltage biasing circuit that provides a constant bias voltage for an MR head. According to Cahalan, voltage biasing circuit includes a nulling circuit that adjusts the output of the voltage biasing circuit. The nulling circuit effectively increases the output of the voltage biasing circuit by an amount that is

THIS SHEET HAS BEEN
REPLACED

5

approximately equal to a cable drop across any parasitic cable resistances that are present. The Cahalan circuit uses a resistive element having a resistance that is an estimate of the parasitic cable resistance for generating the nulling voltage. This approach, however, does not compensate for any voltage drop appearing across the back-leads inside an MR head.

In the conventional adjusted bias current scheme for attaining a constant bias voltage, the bias current through the MR head is adjusted during manufacturing to be inversely proportional to the MR head resistance R_H , achieving an essentially constant MR head bias voltage. The resistance R_H must be measured during the manufacturing process.

None of these conventional MR head biasing scheme compensate for variations in physical characteristics of the MR head that occur during the manufacturing process, specifically, the sensor dimension tolerances. Consequently, operation of an MR head biased by a conventional biasing scheme is typically not at or near the operational optimum for the head. Further, uniform magnetic performance from MR head to MR head of a product, that is, less variability in magnetic performance from head to head regardless of manufacturing tolerances, is not typically achieved.

SUMMARY OF THE INVENTION

It is an object of the present invention to provide an MR head biasing scheme that generally allows for variations in the

This Sheet Has Been Replaced



physical characteristics of an MR sensor occurring during manufacturing, specifically for the physical tolerances of the head occurring during manufacturing. In this regard, the present invention allows for operation of an MR head at or closer to the operational optimum of the MR sensor, and achieves a more uniform magnetic performance from sensor to sensor regardless of physical variations within manufacturing tolerances than conventional biasing schemes.

It is another object of the present invention to provide a sensor biasing scheme that does not rely on head resistance R_H measurements. Consequently, it is an object of the present invention to make use of a "head model" that is based on the head lead resistance R_L and the bias voltage V_b appearing across the sensor resistance R_s portion of the total head resistance R_H that is proportional to the sensor height h and that is varying with the magnetic data signal. Additionally, it is an object of the present invention to use a controlled current source to achieve constant current density J_s in an MR sensor and a constant temperature rise of an MR sensor, regardless of sensor height h . Consequently, maximum allowable bias is provided for all heads in a product with respect to limits set in accordance with electromigration and interdiffusion. It is an object of the present invention for the MR sensor biasing schemes of the invention to be used in conjunction with a signal current sensing (low input impedance) readback amplifier ($|Z_{in}| \ll R_H$), as well as

This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED

7

with a signal voltage sensing high input impedance readback amplifier ($|Z_{in}| \gg R_H$).

To achieve these and other objects, one embodiment of the present invention provides a bias circuit that generates a bias current I_B and a bias voltage V_H for a magnetoresistive (MR) transducer. The bias voltage V_H is a voltage produced by the bias current I_B flowing through a total resistance R_H of the MR transducer, where the total resistance R_H is the sum of a sensor resistance R_s , a total head lead resistance R_l , and a total front-lead resistance R_f . This embodiment of the present invention includes a multiplier, a comparator, a controller and a current generator. The multiplier has first and second inputs in which the first input receives a first signal that is related to the bias current I_B and the second input receives a second signal that is related to the bias voltage V_H . The multiplier generates a product signal that is proportional to a product of the first and second signals. The comparator compares the product signal to a reference signal that is proportional to a predetermined bias power P_b dissipated by the MR transducer, and generates a control signal. The controller is responsive to the control signal by controlling one of the bias current I_B and the bias voltage V_H or both I_B and V_H , and as a result controls the bias power P_b dissipated by the MR transducer to a predetermined value. Preferably, the controller is responsive to the control signal by controlling the current generator to generate the bias current I_B .

AM9-96-032

This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED

According to the invention, the multiplier includes a current sink circuit and a differential amplifier. An input of the current sink circuit receives the second signal and, in response, the current sink circuit generates an output current that is proportional to the bias voltage V_H . The differential amplifier has an input and an output, and is biased by the output current of the current sink circuit. The differential amplifier input receives the first signal and the output of the differential amplifier output is therefore proportional to a product of the bias current I_b and the bias voltage V_H . More specifically, the current sink circuit includes a first transistor having first, second and third nodes; and a first resistor. The second signal is coupled to the first node of the first transistor. The first resistor is coupled between the second node of the first transistor and a first power supply node. The differential amplifier includes second and third transistors, and second and third resistors. The second and third transistors each have first, second and third nodes, where the first signal is coupled between the first node of each of the second and third transistors. The second node of each of the second and third transistors are coupled to the third node of the first transistor. The second resistor is coupled between the third node of the second transistor and the second power supply node, while the third resistor is coupled between the third node of the third transistor and the second power supply node. The output of the differential amplifier appears between the third

This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED

9

node of the second transistor and the third node of the third transistor. Preferably, the comparator is an adder circuit coupled to the third node of the second transistor and the third node of the third transistor. The adder circuit adds to the output of the differential amplifier a predetermined current signal that is related to the reference signal.

Another embodiment of the present invention provides a biasing circuit for a magnetoresistive (MR) transducer, where the transducer is defined as having a total resistance R_H . Resistance R_H includes a sensor resistance R_s , a lead resistance R_l and a front-lead resistance R_f . The biasing circuit includes a transducer equivalent circuit, a difference sensing circuit, and first and second current sources. The transducer equivalent circuit includes a voltage source and an input resistance. The voltage source has a predetermined voltage and the input resistance has a resistance that is related to the lead resistance R_l of the MR transducer. The difference sensing circuit has first and second inputs, with the first input being coupled to the MR transducer and the second input being coupled to the transducer equivalent circuit. The difference sensing circuit senses a voltage difference between the first and second inputs. The first current source is responsive to the difference sensing circuit by generating a bias current I_b for the MR transducer. Similarly, the second current source is responsive to the difference sensing circuit by generating a control current that is coupled to the transducer equivalent circuit. According

This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED

10

to the invention, the control current is proportional to the MR transducer bias current I_b so that the predetermined voltage of the voltage source equals a predetermined voltage V_b appearing across the sensor resistance R_s in series with the front lead resistance R_f .

Since both R_s and R_f are inversely proportional to the sensor height h , the constant voltage appearing across R_s and R_f also provides a constant (i.e. sensor height independent) voltage across R_s .

In one configuration of the second embodiment, the difference sensing circuit includes first and second transistors each having first, second and third nodes. The first node of first transistor is coupled to the first and third nodes of the second transistor. The second node of the first transistor is coupled to the MR transducer. The second node of the second transistor is coupled to the transducer equivalent circuit. The first current source includes a third transistor having first, second and third nodes. Similarly, the second current source includes a fourth transistor having first, second and third nodes. The first and third nodes of the third transistor are coupled to the first node of the fourth transistor to form a current mirror. The third node of the third transistor is coupled to the third node of the first transistor, and the third node of the fourth transistor is coupled to the third node of the second transistor. For power considerations, an area ratio of the first transistor to the second transistor is preferably $N:1$

This Sheet Has Been Replaced



and, similarly, an area ratio of the third transistor to the fourth transistor is preferably $N:1$.

In another configuration of the second embodiment, the first current source includes a first transistor having first, second and third nodes, and, likewise, the second current source includes a second transistor having first, second and third nodes. The first node of the first transistor and the first node of the second transistor are each coupled to an output of the difference sensing circuit. The third node of the first transistor is coupled to the MR transducer, and the third node of the second transistor is coupled to the MR transducer equivalent circuit. The biasing circuit of this embodiment also includes an output circuit that has first and second input nodes and an output node. The first input node of the output circuit is coupled to the third node of the first transistor and the second input node of the output circuit is coupled to the third node of the second transistor.

In yet another configuration of the second embodiment of the present invention, the difference sensing circuit includes first and second transistors each having first, second and third nodes. The first node of first transistor is coupled to the first and third nodes of the second transistor. The second node of the first transistor is coupled to the MR transducer and the second node of the second transistor is coupled to the transducer equivalent circuit. The first current source includes third and fourth transistors each having first, second and third nodes.

This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED

The second node of each of the third and fourth transistors are coupled to the third node of the first transistor. The second current source includes a fifth transistor having first, second and third nodes. The first node of the third transistor is coupled to the first and third node of the fifth transistor to form a current mirror, while the second node of the fifth transistor is coupled to the third node of the second transistor. Preferably, an area ratio of the first transistor to the second transistor is $N:1$, and a current ratio of current flowing in the second node of the fourth transistor to the current flowing in the second node of the third transistor to the current flowing in the second node of the fifth transistor $K:L:1$, where $K + L$ equals N .

Still another configuration of the second embodiment includes a current sensing circuit and a third current source. The current sensing circuit senses the bias current I_b generated by the first current source for the predetermined bias voltage V_s appearing across the sensor resistance R_s . The third current source is responsive to the current sensing circuit by generating an output current when the bias current I_b generated by the first current source for the predetermined bias voltage V_s is less than a predetermined sensor bias current. The output current generated by the third current source is coupled to the transducer equivalent circuit and combined with the control current generated by the second current source to form a combined control current. The combined control current is related to the

This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED

MR transducer bias current I_b such that a predetermined MR transducer bias current I_b flows through the sensor resistance R_s producing a predetermined effective magnetic bias of the sensor resistance R_s .

Preferably for this configuration, the difference sensing circuit includes first and second transistors each having first, second and third nodes. The first node of first transistor is coupled to the first and third nodes of the second transistor. The second node of the first transistor is coupled to the MR transducer, and the second node of the second transistor is coupled to the transducer equivalent circuit. The first current source includes a third transistor having first, second and third nodes, and the second current source includes a fourth transistor having first, second and third nodes. The first and third nodes of the third transistor is coupled to the first node of the fourth transistor to form a current mirror. The third node of the third transistor is coupled to the third node of the first transistor, and the third node of the fourth transistor is coupled to the third node of the second transistor.

The current sensing circuit includes a fifth transistor, a fourth current source, and an amplifier circuit. The fifth transistor has first, second and third nodes, with the first node being coupled to the third node. The fourth current source is coupled to the third node of the fifth transistor. The amplifier circuit has a first input, a second input and an output. The first input of the amplifier is coupled to the third node of the

This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED

third transistor. The second input is coupled to the third node of the fifth transistor and the amplifier output is coupled to the third current source.

A third embodiment of the present invention provides a circuit for magnetically biasing a magnetoresistive (MR) transducer. The biasing circuit includes a transducer equivalent circuit, a difference sensing circuit, and first and second current sources. The difference sensing circuit has first and second inputs, with the first input being coupled to the MR transducer and the second input being coupled to the transducer equivalent circuit. The difference sensing circuit senses a voltage difference between the first and second inputs. The first current source is responsive to the difference sensing circuit by generating a bias current I_b for the MR transducer. The second current source is responsive to the difference sensing circuit by generating a control current that is coupled to the transducer equivalent circuit. According to the invention, the control current is proportional to the MR transducer bias current I_b so that the bias current I_b through the MR transducer produces a predetermined effective magnetic bias of a sensor portion of the MR transducer.

The biasing circuit also includes a current sensing circuit and a third current source. The current sensing circuit senses the bias current I_b generated by the first current source for the predetermined effective magnetic bias of the sensor portion of the MR transducer. The third current source is responsive to the

This Sheet Has Been Replaced



THIS SHEET HAS BEEN REPLACED

current sensing circuit by generating an output current when the bias current I_b generated by the first current source for the predetermined effective magnetic bias of the sensor portion of the MR transducer is less than a predetermined sensor bias current. The output current generated by the third current source is then coupled to the transducer equivalent circuit and combined with the control current generated by the second current source to form a combined control current. The combined control current is related to the MR transducer bias current I_b so that a predetermined MR transducer bias current I_b flows through the MR transducer producing the predetermined effective magnetic bias of the sensor portion of the MR transducer.

Preferably, the difference sensing circuit includes first and second transistors each having first, second and third nodes. The first node of the first transistor is coupled to the first and third nodes of the second transistor. The second node of the first transistor is coupled to the MR transducer, and the second node of the second transistor being coupled to the transducer equivalent circuit. The first current source includes a third transistor having first, second and third nodes. Similarly, the second current source includes a fourth transistor having first, second and third nodes. The first and third nodes of the third transistor are coupled to the first node of the fourth transistor forming a current mirror. The third node of the third transistor is coupled to the third node of the first transistor. The third

This Sheet Has Been Replaced



THIS SHEET HAS BEEN REPLACED

node of the fourth transistor is coupled to the third node of the second transistor.

The current sensing circuit includes a fifth transistor, a fourth current source and an amplifier circuit. The fifth transistor has first, second and third nodes, with the first node being coupled to the third node. The fourth current source is coupled to the third node of the fifth transistor. The amplifier circuit has a first input, a second input and an output. The first input is coupled to the third node of the third transistor. The second input is coupled to the third node of the fifth transistor. The amplifier output is coupled to the third current source.

The biasing circuits of the present invention can be part of an MR/AE circuit which is part of a disk drive.

BRIEF DESCRIPTION OF THE DRAWINGS

The present invention is illustrated by way of example and not limitation in the accompanying figures in which like reference numerals indicate similar elements and in which:

Figure 1(a) shows the physical relationship between the different resistances forming the total MR head resistance R_H ;

Figure 1(b) shows a schematic diagram for an electrical model of resistance R_H ;

Figures 2(a) and 2(b) illustrate exemplary bias conditions for different sensor resistances R_H for an MR head for a conventional constant bias current I_b approach;

This Sheet Has Been Replaced



Figures 2(c) and 2(d) illustrate exemplary bias conditions for different sensor resistances R_H for an MR head for a conventional constant bias voltage V_H approach;

Figures 3(a) and 3(b) show exemplary bias conditions for varying sensor resistance R_H for a constant bias power P_B approach according to the present invention;

Figure 4(a) shows a schematic block diagram of an MR head connected to an arm electronics module;

Figure 4(b) shows an equivalent circuit for an MR head according to the present invention;

Figures 4(c) and 4(d) show equivalent circuits according to the present invention for a bias voltage source V_s having a negative input resistance;

Figures 5(a)-5(c) show schematic block diagrams of equivalent circuits for the biasing circuit of Figure 3(d);

Figures 6(a) and 6(b) show exemplary biasing conditions for an MR head for a constant sensor temperature rise biasing approach according to the present invention;

Figure 7(a) shows theoretical biasing conditions for achieving a constant effective magnetic bias;

Figures 7(b) and 7(c) show biasing conditions for a practical approximation for achieving a constant effect magnetic bias according to the present invention;

Figures 8(a) and 8(b) show schematic block diagrams for illustrating the general concept of constant MR head power biasing according to the present invention;

Figure 9 shows a schematic block diagram of a bias circuit providing a constant bias power circuit for an MR head according to the present invention.

Figure 10(a) shows a schematic block diagram of a circuit providing a constant voltage bias for the sensor resistance of an MR head according to the present invention;

Figure 10(b) shows a network equivalent circuit for the schematic block diagram of Figure 9(a);

Figure 11 shows an alternative schematic block diagram of a circuit providing a constant voltage across the sensor resistance portion of an MR head according to the present invention;

Figure 12 shows a schematic block diagram of another circuit providing a constant voltage across the sensor resistance portion of an MR head according to the present invention;

Figure 13 shows a schematic block diagram of an input stage for a single-ended MR preamplifier circuit using sensor biasing according to the present invention;

Figure 14 shows another schematic block diagram of an input stage of a single-ended MR preamplifier circuit using sensor biasing according to the present invention;

Figure 15 shows a schematic block diagram of a circuit providing a constant effective magnetic bias for an MR head according to the present invention; and

Figures 16(a) and 16(b) show head biasing conditions for a constant effective magnetic biasing according to the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

The present invention provides an MR head biasing scheme that compensates for physical variations from head to head within manufacturing tolerances of the head using one of five related approaches. The first approach is to electrically bias an MR head so that the (electrical) power dissipation in the head is kept constant from head to head, regardless of variations in total head resistance R_H due to manufacturing tolerances. This is accomplished by keeping the product of the DC voltage across the head V_H and the DC current through the head I_H constant. That is,

$$V_H I_H = P_B = a \text{ constant} \quad (5)$$

where, P_B is the bias power.

Figures 3(a) and 3(b) show exemplary bias conditions for varying total head resistance R_H for a constant bias power P_B approach according to the invention. Figure 3(a) shows variations in head current I_H for variations in total head resistance R_H for a constant bias P_B . Figure 3(b) shows corresponding variations in voltage across the head V_H for variations in total head resistance R_H for the same constant bias P_B . An advantage of a constant bias power scheme over a conventional constant bias voltage approach is that increases in head current I_H caused by larger sensor heights are less dramatic with a constant bias power scheme. Additionally, a constant power biasing technique is useful for avoiding magnetic underbiasing of low sensor height heads (high R_H) due to a sensor

demagnetization effect. This is because the head voltage V_H does not remain constant for constant P_s bias, but increases slightly for higher resistance heads.

A second biasing approach of the present invention is a constant MR sensor current density scheme. With this bias technique, the current density J_s in the MR sensor is held constant. This allows operation of all MR sensors in a product as close as possible to the electro-migration limits. The electro-migration depends on current density,

$$J_s = V_s \frac{1}{\rho l} = I_s \frac{1}{ht} = \text{constant} \quad (6)$$

where ρ = sensor resistivity,

l = sensor length,

h = sensor height,

t = sensor thickness,

V_s = the voltage across the sensor, that is, the portion of the MR head corresponding to resistance R_s and responsive to the magnetic data, and

I_s = the current through the sensor (which equals the current through the entire MR head I_H).

The sensor resistance is given by

$$R_s = \rho \frac{l}{ht} \quad (7)$$

The (electrical) power dissipation in the sensor is therefore

$$P_s = J_s^2 \rho l t h \quad (8)$$

The temperature rise ΔT_s of the sensor due to the electrical power dissipation is

$$\Delta T_s = P_s \times R_{thermal} \quad (9)$$

where $R_{thermal}$ is the thermal resistance of the sensor to ambient.

The sensor cools by heat diffusing away from the sensor through the two-side surfaces facing the shields. The thermal resistance resulting from this facial cooling is inversely proportional to the sensor height h . Another cooling mechanism is by heat diffusion into the leads of the sensor. The thermal resistance associated with this cooling mechanism is also inversely proportional to the sensor height h . Hence, the total thermal resistance $R_{thermal}$ in equation (9) is inversely proportional to the sensor height h .

$$R_{thermal} = \frac{K}{h} \quad (10)$$

where K is an arbitrary constant. Therefore,

$$\Delta T_s = J_s^2 \rho l t K \quad (11)$$

is no longer a function of the sensor height h . Consequently, if the biasing circuitry of an MR sensor is designed to bias at a constant current density J_s , all MR sensors in a product will be operating at the same temperature rise ΔT_s above ambient.

A third biasing approach of the present invention provides a constant MR sensor bias voltage V_s . For this scheme, the voltage V_s across the sensor, that is the portion of the MR head

corresponding to-resistance R_s and responsive to the magnetic data, is held constant for all MR heads in a product.

Rewriting equation (12) with:

$$P_s = V_s^2 \frac{1}{R_s} = V_s^2 \frac{th}{\rho l} \quad (12)$$

results in

$$\Delta T_s = V_s^2 \frac{t}{\rho l} K \quad (13)$$

It also follows that for constant sensor voltage biasing, the sensor temperature rise is the same for all sensors in a product.

With

$$I_s = J_s h t = \frac{V_s}{R_s},$$

the current density of the sensor J_s is

$$J_s = V_s / \rho l. \quad (15)$$

Hence, if V_s is held constant for all heads within a product, J_s is also held constant for heads within the same product. Thus, both the constant MR sensor current density bias scheme of the invention and the constant MR sensor bias voltage scheme of the present invention are identical. It should be understood that constant voltage biasing of an MR sensor is not the same as conventional constant voltage biasing of an entire MR head, which does not produce the advantages of constant temperature rise and constant current density.

A fourth MR sensor biasing approach of the present invention is a constant MR sensor temperature rise bias scheme. This MR sensor biasing technique leads to the same sensor temperature rise (resulting from the electrical bias power dissipation in the sensor) of all heads in a product. Naturally, this biasing approach is the same as the two previous biasing approaches of the present invention. Since constant sensor temperature rise biasing, constant sensor current density biasing, and constant sensor bias voltage biasing are all independent of sensor height h , these three biasing approaches of the present invention can all be treated as the same case. Since

$$R_H = R_I + R_f + R_s \quad (16)$$

and

$$R_f, R_s \propto 1/h, \quad (17)$$

a constant voltage bias across the front-lead resistance R_f and the sensor resistance R_s , that is across $R_f + R_s$, will also produce a constant current density in the sensor and provide a constant temperature rise for all sensors in a product, regardless of sensor height h . Therefore, a constant sensor temperature rise can be obtained in principle as indicated by the schematic block diagrams of Figures 4(a)-4(d).

Figure 4(a) shows a schematic block diagram of an MR head, an AE module and wires W connected between the MR head and AE module. Figure 4(b) shows an equivalent circuit for an MR head with leads and wires. According to the invention, the MR head

"sees" a bias voltage source having a negative input resistance at the input terminals of the AE module. Figure 4(c) shows an equivalent bias circuit where a voltage V_s is developed across the sensor resistance R_s of the MR sensor. Figure 4(d) shows an equivalent bias circuit where a voltage V_b is developed across the sensor resistance R_s and the lead front-end resistance R_f . The equivalent circuit shown in Figure 4(c), where the input resistance is $-(R_f + R_1)$, is relatively difficult to realize because $R_f \propto 1/h$ and is dependent on each individual head. R_1 , on the other hand, is relatively constant. Consequently, the equivalent circuit shown in Figure 4(d), having a bias voltage V_b and an input resistance $-R_1$, is the preferred implementation for a biasing circuit that provides biasing for the second, third and fourth biasing schemes of the present invention. The negative resistance $-R_1$ of the equivalent circuit in Figure 4(d) cancels R_1 of the MR head wiring and leads, and effectively applies the bias voltage V_b across $R_s + R_f$ of the MR head.

Figures 5(a)-5(c) are equivalent circuit models for the circuit of Figure 4(d). In Figure 5(c), the current source I and the negative input impedance $-R_1$ result in a constant bias voltage V_b across $(R_s + R_f)$ of the MR head, shown in Figure 4(b), when $I = V_b/R_1$. Figures 6(a) and 6(b) show exemplary biasing conditions for a constant sensor temperature rise biasing scheme according to the present invention. In Figure 6(a), sensor current I_H is shown for varying total MR head resistance R_H for a constant sensor temperature rise biasing. Figure 6(b) shows a

graph of head bias voltage V_H for varying MR head resistance R_H for the same conditions. The curves of Figures 6(a) and 6(b) are described by:

$$I_H = V_B / (R_S + R_H), \quad (18)$$

and

$$V_H = V_B + I_H R_L. \quad (19)$$

The effective magnetic bias caused by a constant current density J_s in a sensor becomes progressively less as the sensor height decreases due to a demagnetization effect on the top and bottom edges of the sensor. To obtain a constant effective magnetic bias in sensors having a relative smaller height, a fifth biasing approach according to the present invention provides a progressively larger sensor current density J_s and which is given by the following polynomial approximation

$$J_s = (J_{h0} - J_0) \left(\frac{h_0}{h} \right)^2. \quad (20)$$

Figure 7(a) shows a theoretical curve for J_s . Figures 7(b) and 7(c) show biasing conditions providing a practical approximation for a constant current density J_s biasing according to the fifth biasing scheme of the present invention. Below a head resistance R_{h0} , corresponding to a sensor height h_0 , a head is biased with a constant bias voltage yielding a constant current density J_s . Above resistance R_{h0} , a head is biased with a constant current I_B , resulting in an increase in a sensor current

density that is inversely proportional to the sensor height h and is proportional to the sensor resistance R_s .

Figures 8(a) and 8(b) show schematic block diagrams for illustrating the general concept of the constant MR head power biasing scheme according to the present invention. Each electronic circuit shown in Figures 8(a) and 8(b) includes a multiplying device 81, for example, a well-known transconductance multiplier having a first input signal that is proportional to I_B and a second input signal that is proportional to V_H . I_B and V_H are signals available at the input terminals of an AE module. The product signal output 82 from multiplier 81 is compared by a comparator 83 to a reference signal 84. Signal 84 is proportional to the desired bias power P_B dissipated by MR head resistance R_H . Comparator 83 outputs a control signal 85 that is proportional to the difference of the product signal 82 and reference signal 84 and is used for controlling the bias current I_B (Figure 8(a)) or for controlling the head voltage V_H (Figure 8(b)) such that the product $I_B V_H$ is constant. In Figure 8(a), the controlled variable is I_B and variable V_H is automatically linked to I_B through the equation $V_H = R_H I_B$. The head resistance R_H need not be a known value, that is, it may vary from head to head. For Figure 8(b), the controlled variable is V_H and the variable I_B is linked to V_H .

Figure 9 shows a schematic block diagram of a bias circuit 900 that provides a constant bias power to an MR head. Bias circuit 900 includes a current sink formed by amplifier 901,

transistor 902 and resistor 903. The output current of the current sink is proportional to head voltage V_H . As shown, the output of amplifier 901 is coupled to the base of transistor 902. The emitter of transistor 902 is coupled to the inverting input of amplifier 901 and to a first power source V_{s1} through resistor 903. The non-inverting input of amplifier 901 is connected to input terminal 804 of bias circuit 900. Input terminal 905 of circuit 900 is coupled to power source V_{s1} . MR head (R_H) is connected across input terminals 904 and 905. Thus, the magnitude of the voltage V_H appearing across R_H is connected across the current sink and controls the magnitude of the collector current of transistor 902.

Transistors 906 and 907 are connected to form a first differential amplifier. That is, the emitters of transistors 906 and 907 are connected together and coupled to the collector of transistor 902. The bases of transistors 906 and 907 are coupled to opposite sides of a resistor 917. Resistor 917 is connected so that the current flowing through resistor 917 is the bias current I_B that flows through terminal 904 and through R_H . The collector of transistor 906 is connected to a second power source V_{s2} through resistor 908, while the collector of transistor 907 is connected to second power source V_{s2} through resistor 909. The differential collector current of transistors 906 and 907 is proportional to $I_B V_H$.

A second differential amplifier is formed by transistors 910 and 911, and current source 913. The emitters of transistors 910

and 911 are connected together and coupled to one terminal of current source 913. The other terminal of current source 913 is connected to first power source V_{s1} . Current source 913 outputs current I_3 that is used for biasing transistors 910 and 911. The collector of transistor 910 is coupled to the collector of transistor 906, and the collector of transistor 911 is coupled to the collector of transistor 907. A reference voltage V_{ref} , which has a magnitude that is proportional to the desired bias power P_B , is applied between the bases of transistors 910 and 911 causing a constant differential current at the collectors of transistors 910 and 911 to be subtracted from the differential current output of transistors 906 and 907. The constant amount can be varied by varying V_{ref} . While Figure 9 shows that V_{ref} is externally applied to circuit 900, V_{ref} can alternatively be made to have a constant magnitude, that is, internal to circuit 900, and I_3 can be made to be varied externally in proportion to the desired bias power P_B for accommodating a wide range of products having different P_B requirements.

The collector of transistor 906 is coupled to the inverting input to a control amplifier 914, and the collector of transistor 907 is coupled to the non-inverting input of control amplifier 914. The output of amplifier 914 controls a current source formed by transistor 916 and resistor 915. Transistor 916 and resistor 915 generate bias current I_B that flows through resistor 917 and through head resistance R_H . With resistor $917 \ll kT/qI_B$ and $V_{ref} \ll kT/q$, it follows that

$$P_B = V_H I_B = I_3 V_{ref} \frac{R_1}{R_5} \quad (21)$$

where R_1 and R_5 are the resistance of resistors 903 and 917, respectively.

For a constant MR sensor bias voltage approach according to the present invention, only the resistance R_s of the total MR head resistance R_H is biased with a constant voltage. As demonstrated above, this biasing scheme also achieves a constant current density J_s in the sensor in addition to a constant temperature rise of the sensor above ambient temperature. As indicated by Figures 4(a)-4(d), a constant sensor biasing can be implemented by compensating for the non-sensor resistance part of the head resistance, that is, the lead resistance R_l and the front-lead resistance R_f , or more easily by compensating only for the lead resistance R_l (see Figure 4(d)). A simple and elegant way to achieve this is shown by Figures 10(a) and 10(b). Figure 10(a) shows a schematic block diagram of a circuit 1000 providing a constant sensor voltage bias according to the present invention and Figure 10(b) shows a network equivalent circuit 1010 for the schematic block diagram of Figure 10(a).

In Figure 10(a), the network equivalent circuit 1010 of Figure 10(b) having a negative input resistance $-R_l$ with a voltage source V_b is created by a bridge-like circuit 1000. Circuit 1000 includes an amplifier 1002 that senses a voltage difference between the total head resistance R_H and the model or equivalent circuit 1001 for the MR transducer, that is, a circuit

AM9-96-032

having a NR_1 in series. Amplifier 1002 adjusts two current sources 1003 and 1004 until the voltage difference sensed at the input to amplifier 1002 equals zero. Preferably, current source 1003 supplies current I_b and current source 1004 supplies current I_b/N , where N is chosen to be greater than 1 for power savings considerations. However, N may be chosen other considerations in mind. Practical values for N are in the range from 5-20.

Figure 11 shows a schematic block diagram of a circuit 1100 providing a constant voltage V_b across the sensor resistance R_s portion of an MR head. Circuit 1100 includes a transistor 1101 connected as an emitter follower. The base-emitter voltage of transistor 1001 is cancelled by the base-emitter voltage of transistor 1002, which has an area preferably N times smaller than T_1 transistor 1101 for power saving considerations. The resistance NR_1 of equivalent circuit 1001 is scaled accordingly by N . Transistor 1101 is preferably the input transistor of the readback amplifier of an AE module. Although not shown in Figure 11, the readback signal is detected at the collector transistor 1101. Capacitor 1105 is connected between the bases of transistors 1101 and 1102 and power source V_{s2} for providing filtering. NR_1 and V_b can be provided off-chip for greater flexibility. A current mirror is formed by transistors 1103 and 1104, and is connected in any well-known current mirror configuration (double FET mirror, etc.), and is also scaled by a factor N . This current mirror forces the currents through

transistors 1101 and 1102, and also through R_H and model 1001 to be scaled by N .

Figure 12 shows a schematic block diagram of another circuit 1200 providing a constant voltage V_b across the sensor resistance R_s portion of an MR head. Circuit 1200 is configured for detecting an MR head readback signal directly from the MR head signal voltage. Circuit 1200 includes MR equivalent circuit 1001. Amplifier 1201 is connected to detect a voltage difference between the voltage V_H appearing across the MR head and the voltage appearing across equivalent circuit 1001. In that regard, the non-inverting input of amplifier 1201 is coupled to the MR head, while the inverting input of amplifier 1201 is coupled to the equivalent circuit 1001. The output of amplifier 1201 is connected to the bases of transistors 1202 and 1204, which are both configured as controllable current sources. The area ratio of transistor 1202 to transistor 1204 is preferably $N:1$ for power savings considerations, but may also be chosen for other considerations. Capacitor 1206 is coupled between the output of amplifier 1201 and a power supply voltage V_{s2} for providing filtering of the control signal output from amplifier 1201.

The emitter of transistor 1202 is coupled to power supply voltage V_{s2} through resistor 1203. Similarly, the emitter of transistor 1204 is coupled to supply voltage V_{s2} through resistor 1205. The collector of transistor 1202 is coupled to the MR head, while the collector of transistor 1204 is coupled to

equivalent circuit 1001 through diodes 1208 and 1209. Capacitor 1207 is connected to the collector of transistor 1204 for filtering purposes.

Circuit 1200 includes an output stage formed by transistors 1211 and 1212. The base of transistor 1212 is coupled to the collector of transistor 1202. Similarly, the base of transistor 1211 is coupled to the collector of transistor 1204. The collector of transistor 1211 is coupled to power supply V_{s2} through resistor 1210. The detected readback signal from the MR head is generated across resistor 1210 between terminals 1213 and 1214.

Figure 13 shows a schematic block diagram of an input stage circuit 1300 for a single-ended MR preamplifier using sensor biasing according to the present invention. Circuit 1300 includes circuit 1100 that is shown in Figure 11. Additionally, a current source 1304 having a current I_{comp} equal to $2I_B/\beta$, where β is the current gain of transistor 1103, is connected between a voltage source V_{s2} (+5 V for example) and the bases of transistors 1103 and 1104. The MR head signal V_{out} is available between terminals 1310 and 1311, and is described by the following equation:

$$V_{out} = \frac{\Delta R_h}{R_h} V_B \frac{R_C}{(r_{e1} + r_{e2})} \quad (22)$$

A current source containing an amplifier 1305, a capacitor 1306, a compensation diode 1307, a resistor 1308 and a transistor 1309 is used for "bleeding off" part of the bias current I_B .

around resistor 1303, so that resistor 1303 can have a larger resistive value, for example, 450 Ohms, for providing more gain without causing transistor head-room problems. For a resistive value of 450 Ohms for resistor 1303, resistor 1308 should preferably have a resistive value of 194 Ohms so that 70% of I_B is sourced through transistor 1309. Preferably, capacitor 1306 is 470 pF. To mirror the current through resistor 1303, which is, for example, 30% of the bias current I_B , a series diode 1301 (self-biased transistor) is used with transistor 1302. This circuit configuration, however, can result in signal distortion, offset, etc., despite compensation diode 1307 in the bleed-off current source.

The problems of circuit 1300 associated with signal distortion are avoided by circuit 1400, shown in Figure 14. Circuit 1400 is an input stage of a single-ended MR preamplifier using sensor biasing, and includes circuit 1100 (Figure 11), and the bleed-off current source (circuit 1300). For circuit 1400, though, diodes 1301 and 1307 of circuit 1300 have been eliminated. Resistors 1303 and 1308 are chosen to be equal, for example, 450 Ohms, so that 50% of I_B flows through transistor 1103 and 50% flows through transistor 1309. An amplifier 1401 is coupled to the emitters of the current mirror formed by transistors 1103 and 1104. The output of amplifier 1401 is coupled to the gate of a transistor 1304. The source of transistor 1404 is coupled to power source V_{S2} through resistor 1403. The drain of transistor 1404 is coupled to the collector

of transistor 1104. Capacitor 1402 is used for filtering purposes.

In circuit 1400, the magnitude of the compensation current in the right-most vertical branch containing head equivalent circuit 1001 is derived from the base-emitter of the cascode transistor 1103 above input transistor 1101. Amplifier 1401 controls the FET current source, that is, transistor 1404, so that the compensation current in the right-most branch is 1/10 times, for example, the input bias current I_b through the MR head.

In the constant effective magnetic bias scheme of the present invention, an MR sensor having a relatively lower sensor height is biased at a higher current density than would be provided by the second, third or fourth biasing schemes of the present invention. The ideal curve for increasing current density is difficult to realize (Figure 7(a)), therefore the approximation of Figure 7(b) is provided by the present invention. The approximation realizes constant voltage bias for low resistance heads (Figure 7(b)) and constant current bias for higher resistance heads (Figure 7(c)). The cross-over point between constant V_b and constant I_b is between the minimum head resistance $R_{H \min}$ and the maximum head resistance $R_{H \max}$ as encountered in a product, and corresponds to a given sensor height h_0 .

Figure 15 shows a schematic block diagram of a circuit 1500 providing a constant effective magnetic bias according to the

present invention. Circuit 1500 includes circuit 1100 of Figure 11. Circuit 1500 provides a constant sensor voltage for relatively low values of R_H for which the head bias current through R_H and transistor 1101 is sufficiently large to turn off a controllable current source formed by transistor 1502 and resistor 1503. For a relatively higher value of head resistance R_H , the bias current I_B becomes sufficiently small that amplifier 1501, which compares the voltage drop across transistor 1504 with the voltage drop across transistor 1103 (both shown connected as diodes), applies a forward voltage to the base of transistor 1502. Transistor turns on accordingly and circuit 1500 supplies a constant current bias to the MR head. Figures 16(a) and 16(b) show exemplary MR head biasing conditions for constant effective magnetic biasing circuit 1500. The cross-over point is determined by the value of the (reference) current I_0 and the transistor area ratio N .

So, for head resistance R_H sufficiently large that

$$I_B > V_B / (R_H - R_I), \quad (23)$$

the head bias current I_B is kept constant at the value, $I_B = NI_0$.

For lower values of head resistance R_H , the bias current I_B is determined by

$$I_B = V_B / (R_H - R_I). \quad (24)$$

The cross-over point occurs at the value of R_H given by

$$R_{ho} = \frac{V_B}{NI_0} + R_I \quad (25)$$

and can be located anywhere within the product head resistance interval

$$R_{h \min} \leq R_{ho} \leq R_{h \max}. \quad (26)$$

All of the disclosed embodiments and configurations of the bias circuit of the present invention can be made part of circuitry in an MR/AE module which is part of a disk drive.

While the present invention has been described in connection with the illustrated embodiments, it will be appreciated and understood that modifications may be made without departing from the true spirit and scope of the invention.

CLAIMS

What is claimed is:

1. A circuit generating a bias current I_B and a bias voltage V_H for a magnetoresistive (MR) transducer, the circuit comprising:

a multiplier having first and second inputs, the first input receiving a first signal that is related to the bias current I_B and the second input receiving a second signal that is related to the bias voltage V_H , the multiplier generating a product signal that is proportional to a product of the first and second signals;

a comparator comparing the product signal to a reference signal and generating a control signal, the reference signal being proportional to a predetermined bias power P_B that is dissipated by the MR transducer; and

a controller responsive to the control signal by controlling one of the bias current I_B and the bias voltage V_H , and by generating the predetermined bias power P_B that is dissipated by the MR transducer.

2. The circuit according to claim 1, wherein the bias voltage V_H is a voltage produced by the bias current I_B flowing through a total resistance R_H of the MR transducer, the total resistance R_H being the sum of a sensor resistance R_S , a total head lead resistance R_L , and a total front-lead resistance R_F .



3. The circuit according to claim 2, wherein the controller controls both the bias current I_b and the bias voltage V_H .

4. The circuit according to claim 2, further comprising a current generator, and wherein the controller is responsive to the control signal by controlling the current generator to generate the bias current I_b .

5. The circuit according to claim 4, wherein the circuit is part of an MR head/arm electronics (AE) circuit.

6. The circuit according to claim 5, wherein the MR head/AE circuit is part of a disk drive.

7. The circuit according to claim 4, wherein the multiplier includes,

a current sink circuit having an input and an output, the input of the current sink circuit receiving the second signal and generating an output current that is proportional to the bias voltage V_H ; and

a differential amplifier having an input and an output, the differential amplifier being biased by the output current of the current sink circuit, the input of the differential amplifier receiving the first signal and the output of the differential



amplifier being proportional to a product of the bias current I_b and the bias voltage V_R .

8. The circuit according to claim 7, further comprising a first power supply node and a second power supply node,

wherein the current sink circuit includes,

a first transistor having first, second and third nodes, the second signal being coupled to the first node of the first transistor, and

a first resistor coupled between the second node of the first transistor and the first power supply node;

wherein the differential amplifier includes,

second and third transistors each having first, second and third nodes, the first signal being coupled between the first node of each of the second and third transistors, the second node of each of the second and third transistors being coupled to the third node of the first transistor,

a second resistor coupled between the third node of the second transistor and the second power supply node, and

a third resistor coupled between the third node of the third transistor and the second power supply node,

the output of the differential amplifier appearing between the third node of the second transistor and the third node of the third transistor; and

wherein the comparator is an adder circuit, the adder circuit being coupled to the third node of the second transistor



THIS SHEET HAS BEEN
REPLACED

and the third node of the third transistor, the adder circuit adding a predetermined current signal to the output of the differential amplifier, the predetermined current signal being related to the reference signal.

9. A biasing circuit for a magnetoresistive (MR) transducer having a total resistance R_H , the total MR transducer resistance R_H including a sensor resistance R_s , a lead resistance R_l and a front-lead resistance R_f , the biasing circuit comprising:

a transducer equivalent circuit including a voltage source and an input resistance, the voltage source having a predetermined voltage and the input resistance having a resistance that is related to the lead resistance R_l of the MR transducer;

a difference sensing circuit having first and second inputs, the first input being coupled to the MR transducer and the second input being coupled to the transducer equivalent circuit, the difference sensing circuit sensing a voltage difference between the first and second inputs;

a first current source responsive to the difference sensing circuit by generating a bias current I_b for the MR transducer; and

a second current source responsive to the difference sensing circuit by generating a control current that is coupled to the transducer equivalent circuit, the control current being

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

proportional to the MR transducer bias current I_b so that the predetermined voltage of the voltage source equals a predetermined voltage V_b appearing across the sensor resistance R_s .

10. The biasing circuit according to claim 9, wherein the biasing circuit is part of an MR head/arm electronics (AE) circuit.

11. The biasing circuit according to claim 10, wherein the MR head/AE circuit is part of a disk drive.

12. The biasing circuit according to claim 9, wherein the difference sensing circuit includes first and second transistors each having first, second and third nodes, the first node of first transistor being coupled to the first and third nodes of the second transistor, the second node of the first transistor being coupled to the MR transducer, and the second node of the second transistor being coupled to the transducer equivalent circuit, and

wherein the first current source includes a third transistor having first, second and third nodes, and the second current source includes a fourth transistor having first, second and third nodes, the first and third nodes of the third transistor being coupled to the first node of the fourth transistor to form a current mirror, the third node of the third

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

transistor being coupled to the third node of the first transistor, and the third node of the fourth transistor being coupled to the third node of the second transistor.

13. The biasing circuit according to claim 12, wherein an area ratio of the first transistor to the second transistor is $N:1$, and an area ratio of the third transistor to the fourth transistor is $N:1$.

14. The biasing circuit according to claim 9, wherein the difference sensing circuit further including an output,

wherein the first current source includes a first transistor having first, second and third nodes, and the second current source includes a second transistor having first, second and third nodes,

the first node of the first transistor and the first node of the second transistor each being coupled to the output of the difference sensing circuit, the third node of the first transistor being coupled to the MR transducer, and the third node of the second transistor being coupled to the MR transducer equivalent circuit,

the biasing circuit further comprising:

an output circuit having first and second input nodes and an output node, the first input node of the output circuit being coupled to the third node of the first transistor, the

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

second input node of the output circuit being coupled to the third node of the second transistor.

15. The biasing circuit according to claim 9, wherein the difference sensing circuit includes first and second transistors each having first, second and third nodes, the first node of first transistor being coupled to the first and third nodes of the second transistor, the second node of the first transistor being coupled to the MR transducer, and the second node of the second transistor being coupled to the transducer equivalent circuit,

wherein the first current source includes third and fourth transistors each having first, second and third nodes, the second node of each of the third and fourth transistors being coupled to the third node of the first transistor, and

wherein the second current source includes a fifth transistor having first, second and third nodes,

the first node of the third transistor being coupled to the first and third node of the fifth transistor to form a current mirror, and the second node of the fifth transistor being coupled to the third node of the second transistor.

16. The biasing circuit according to claim 15, wherein an area ratio of the first transistor to the second transistor is $N:1$, and a current ratio of current flowing in the second node of the fourth transistor to the current flowing in the second node

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

of the third transistor to the current flowing in the second node of the fifth transistor K:L:1, where $K + L$ equals N.

17. The biasing circuit according to claim 9, further comprising:

a current sensing circuit sensing the bias current I_b generated by the first current source for the predetermined bias voltage V_s appearing across the sensor resistance R_s ; and

a third current source responsive to the current sensing circuit by generating an output current when the bias current I_b generated by the first current source for the predetermined bias voltage V_s is less than a predetermined sensor bias current, the output current generated by the third current source being coupled to the transducer equivalent circuit and combining with the control current generated by the second current source to form a combined control current, the combined control current being related to the MR transducer bias current I_b so that a predetermined MR transducer bias current I_b flows through the sensor resistance R_s producing a predetermined effective magnetic bias of the sensor resistance R_s .

18. The biasing circuit according to claim 17, wherein the difference sensing circuit includes first and second transistors each having first, second and third nodes, the first node of first transistor being coupled to the first and third nodes of the second transistor, the second node of the first transistor

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

being coupled to the MR transducer, and the second node of the second transistor being coupled to the transducer equivalent circuit, and

wherein the first current source includes a third transistor having first, second and third nodes, and the second current source includes a fourth transistor having first, second and third nodes, the first and third nodes of the third transistor being coupled to the first node of the fourth transistor to form a current mirror, the third node of the third transistor being coupled to the third node of the first transistor, and the third node of the fourth transistor being coupled to the third node of the second transistor.

19. The biasing circuit according to claim 18, wherein the current sensing circuit includes,

a fifth transistor having first, second and third nodes, the first node being coupled to the third node;

a fourth current source coupled to the third node of the fifth transistor; and

an amplifier circuit having a first input; a second input and an output, the first input being coupled to the third node of the third transistor, the second input being coupled to the third node of the fifth transistor and the output being coupled to the third current source.

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

20. A circuit for magnetically biasing a magnetoresistive (MR) transducer, the MR transducer including a sensor portion having a sensor resistance R_s , a lead portion having a lead resistance R_l and a front-lead portion having a front-lead resistance R_f , the biasing circuit comprising:

a transducer equivalent circuit;

a difference sensing circuit having first and second inputs, the first input being coupled to the MR transducer and the second input being coupled to the transducer equivalent circuit, the difference sensing circuit sensing a voltage difference between the first and second inputs;

a first current source responsive to the difference sensing circuit by generating a bias current I_b for the MR transducer; and

a second current source responsive to the difference sensing circuit by generating a control current that is coupled to the transducer equivalent circuit, the control current being proportional to the MR transducer bias current I_b so that the bias current I_b through the MR transducer produces a predetermined effective magnetic bias of the sensor portion of the MR transducer.

21. The circuit according to claim 20, wherein the circuit is part of an MR head/arm electronics (AE) circuit.

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

22. The circuit according to claim 21, wherein the MR head/AE circuit is part of a disk drive.

23. The circuit according to claim 20, further comprising:
a current sensing circuit sensing the bias current I_b generated by the first current source for the predetermined effective magnetic bias of the sensor portion of the MR transducer; and

a third current source responsive to the current sensing circuit by generating an output current when the bias current I_b generated by the first current source for the predetermined effective magnetic bias of the sensor portion of the MR transducer is less than a predetermined sensor bias current, the output current generated by the third current source being coupled to the transducer equivalent circuit and combining with the control current generated by the second current source to form a combined control current, the combined control current being related to the MR transducer bias current I_b so that a predetermined MR transducer bias current I_b flows through the MR transducer producing the predetermined effective magnetic bias of the sensor portion of the MR transducer.

24. The circuit according to claim 23, wherein the difference sensing circuit includes first and second transistors each having first, second and third nodes, the first node of first transistor being coupled to the first and third nodes of

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

the second transistor, the second node of the first transistor being coupled to the MR transducer, and the second node of the second transistor being coupled to the transducer equivalent circuit, and

wherein the first current source includes a third transistor having first, second and third nodes, and the second current source includes a fourth transistor having first, second and third nodes, the first and third nodes of the third transistor being coupled to the first node of the fourth transistor to form a current mirror, the third node of the third transistor being coupled to the third node of the first transistor, and the third node of the fourth transistor being coupled to the third node of the second transistor.

25. The circuit according to claim 24, wherein the current sensing circuit includes,

a fifth transistor having first, second and third nodes, the first node being coupled to the third node;

a fourth current source coupled to the third node of the fifth transistor; and

an amplifier circuit having a first input, a second input and an output, the first input being coupled to the third node of the third transistor, the second input being coupled to the third node of the fifth transistor and the output being coupled to the third current source.

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

26. A magnetoresistive (MR) head/arm electronics (AE) circuit comprising:

a magnetoresistive transducer, the magnetoresistive transducer having a bias current I_b flowing through the transducer and a bias voltage V_H appearing across the transducer;

a multiplier having first and second inputs, the first input receiving a first signal that is related to the bias current I_b and the second input receiving a second signal that is related to the bias voltage V_H , the multiplier generating a product signal that is proportional to a product of the first and second signals;

a comparator comparing the product signal to a reference signal and generating a control signal, the reference signal being proportional to a predetermined bias power P_b that is dissipated by the MR transducer; and

a controller responsive to the control signal by controlling one of the bias current I_b and the bias voltage V_H , and by generating the predetermined bias power P_b that is dissipated by the MR transducer.

27. The circuit according to claim 26, wherein the bias voltage V_H is a voltage produced by the bias current I_b flowing through a total resistance R_H of the MR transducer, the total resistance R_H being the sum of a sensor resistance R_s , a total head lead resistance R_l , and a total front-lead resistance R_f .

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

28. The circuit according to claim 27, wherein the controller controls both the bias current I_b and the bias voltage V_H .

29. The circuit according to claim 27, further comprising a current generator, and wherein the controller is responsive to the control signal by controlling the current generator to generate the bias current I_b .

30. The circuit according to claim 29, wherein the MR head/AE circuit is part of a disk drive.

31. The circuit according to claim 29, wherein the multiplier includes,

a current sink circuit having an input and an output, the input of the current sink circuit receiving the second signal and generating an output current that is proportional to the bias voltage V_H ; and

a differential amplifier having an input and an output, the differential amplifier being biased by the output current of the current sink circuit, the input of the differential amplifier receiving the first signal and the output of the differential amplifier being proportional to a product of the bias current I_b and the bias voltage V_H .

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

32. The circuit according to claim 31, further comprising a first power supply node and a second power supply node,

wherein the current sink circuit includes,

a first transistor having first, second and third nodes, the second signal being coupled to the first node of the first transistor, and

a first resistor coupled between the second node of the first transistor and the first power supply node;

wherein the differential amplifier includes,

second and third transistors each having first, second and third nodes, the first signal being coupled between the first node of each of the second and third transistors, the second node of each of the second and third transistors being coupled to the third node of the first transistor,

a second resistor coupled between the third node of the second transistor and the second power supply node, and

a third resistor coupled between the third node of the third transistor and the second power supply node,

the output of the differential amplifier appearing between the third node of the second transistor and the third node of the third transistor; and

wherein the comparator is an adder circuit, the adder circuit being coupled to the third node of the second transistor and the third node of the third transistor, the adder circuit adding a predetermined current signal to the output of the

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

52

differential amplifier, the predetermined current signal being related to the reference signal.

33. A magnetoresistive (MR) head/arm electronics (AE) circuit comprising:

a magnetoresistive transducer, the magnetoresistive transducer having a total resistance R_H , the total MR transducer resistance R_H including a sensor resistance R_s , a lead resistance R_l and a front-lead resistance R_f ;

a transducer equivalent circuit including a voltage source and an input resistance, the voltage source having a predetermined voltage and the input resistance having a resistance that is related to the lead resistance R_l of the MR transducer;

a difference sensing circuit having first and second inputs, the first input being coupled to the MR transducer and the second input being coupled to the transducer equivalent circuit, the difference sensing circuit sensing a voltage difference between the first and second inputs;

a first current source responsive to the difference sensing circuit by generating a bias current I_b for the MR transducer; and

a second current source responsive to the difference sensing circuit by generating a control current that is coupled to the transducer equivalent circuit, the control current being proportional to the MR transducer bias current I_b so that the

This Sheet Has Been Replaced





* C L M S *

THIS SHEET HAS BEEN
REPLACED

predetermined voltage of the voltage source equals a predetermined voltage V_b appearing across the sensor resistance R_s .

34. The circuit according to claim 33, wherein the MR head/AE circuit is part of a disk drive.

35. The biasing circuit according to claim 33, wherein the difference sensing circuit includes first and second transistors, each having first, second and third nodes, the first node of first transistor being coupled to the first and third nodes of the second transistor, the second node of the first transistor being coupled to the MR transducer, and the second node of the second transistor being coupled to the transducer equivalent circuit, and

wherein the first current source includes a third transistor having first, second and third nodes, and the second current source includes a fourth transistor having first, second and third nodes, the first and third nodes of the third transistor being coupled to the first node of the fourth transistor to form a current mirror, the third node of the third transistor being coupled to the third node of the first transistor, and the third node of the fourth transistor being coupled to the third node of the second transistor.

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

36. The biasing circuit according to claim 35, wherein an area ratio of the first transistor to the second transistor is $N:1$, and an area ratio of the third transistor to the fourth transistor is $N:1$.

37. The biasing circuit according to claim 33, wherein the difference sensing circuit further including an output,

wherein the first current source includes a first transistor having first, second and third nodes, and the second current source includes a second transistor having first, second and third nodes,

the first node of the first transistor and the first node of the second transistor each being coupled to the output of the difference sensing circuit, the third node of the first transistor being coupled to the MR transducer, and the third node of the second transistor being coupled to the MR transducer equivalent circuit,

the biasing circuit further comprising:

an output circuit having first and second input nodes and an output node, the first input node of the output circuit being coupled to the third node of the first transistor, the second input node of the output circuit being coupled to the third node of the second transistor.

38. The biasing circuit according to claim 33, wherein the difference sensing circuit includes first and second transistors

This Sheet Has Been Replaced





* C L M S *

THIS SHEET HAS BEEN
REPLACED

each having first, second and third nodes, the first node of first transistor being coupled to the first and third nodes of the second transistor, the second node of the first transistor being coupled to the MR transducer, and the second node of the second transistor being coupled to the transducer equivalent circuit,

wherein the first current source includes third and fourth transistors each having first, second and third nodes, the second node of each of the third and fourth transistors being coupled to the third node of the first transistor, and

wherein the second current source includes a fifth transistor having first, second and third nodes,

the first node of the third transistor being coupled to the first and third node of the fifth transistor to form a current mirror, and the second node of the fifth transistor being coupled to the third node of the second transistor.

39. The biasing circuit according to claim 38, wherein an area ratio of the first transistor to the second transistor is $N:1$, and a current ratio of current flowing in the second node of the fourth transistor to the current flowing in the second node of the third transistor to the current flowing in the second node of the fifth transistor $K:L:1$, where $K + L$ equals N .

40. The biasing circuit according to claim 33, further comprising:

This Sheet Has Been Replaced





* C L M S *

THIS SHEET HAS BEEN
REPLACED

a current sensing circuit sensing the bias current I_b generated by the first current source for the predetermined bias voltage V_s appearing across the sensor resistance R_s ; and

a third current source responsive to the current sensing circuit by generating an output current when the bias current I_b generated by the first current source for the predetermined bias voltage V_s is less than a predetermined sensor bias current, the output current generated by the third current source being coupled to the transducer equivalent circuit and combining with the control current generated by the second current source to form a combined control current, the combined control current being related to the MR transducer bias current I_b so that a predetermined MR transducer bias current I_b flows through the sensor resistance R_s producing a predetermined effective magnetic bias of the sensor resistance R_s .

41. The biasing circuit according to claim 40, wherein the difference sensing circuit includes first and second transistors each having first, second and third nodes, the first node of first transistor being coupled to the first and third nodes of the second transistor, the second node of the first transistor being coupled to the MR transducer, and the second node of the second transistor being coupled to the transducer equivalent circuit, and

wherein the first current source includes a third transistor having first, second and third nodes, and the second

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

current source includes a fourth transistor having first, second and third nodes, the first and third nodes of the third transistor being coupled to the first node of the fourth transistor to form a current mirror, the third node of the third transistor being coupled to the third node of the first transistor, and the third node of the fourth transistor being coupled to the third node of the second transistor.

42. The biasing circuit according to claim 41, wherein the current sensing circuit includes,

a fifth transistor having first, second and third nodes, the first node being coupled to the third node;

a fourth current source coupled to the third node of the fifth transistor; and

an amplifier circuit having a first input, a second input and an output, the first input being coupled to the third node of the third transistor, the second input being coupled to the third node of the fifth transistor and the output being coupled to the third current source.

43. A magnetoresistive (MR) head/arm electronics (AE) circuit comprising:

a magnetoresistive transducer, the magnetoresistive transducer having a total resistance R_H , the total MR transducer resistance R_H including a sensor resistance R_s , a lead resistance R_l and a front-lead resistance R_f ;

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

a transducer equivalent circuit;

a difference sensing circuit having first and second inputs, the first input being coupled to the MR transducer and the second input being coupled to the transducer equivalent circuit, the difference sensing circuit sensing a voltage difference between the first and second inputs;

a first current source responsive to the difference sensing circuit by generating a bias current I_b for the MR transducer; and

a second current source responsive to the difference sensing circuit by generating a control current that is coupled to the transducer equivalent circuit, the control current being proportional to the MR transducer bias current I_b so that the bias current I_b through the MR transducer produces a predetermined effective magnetic bias of the sensor portion of the MR transducer.

44. The circuit according to claim 43, wherein the MR head/AE circuit is part of a disk drive.

45. The circuit according to claim 43, further comprising: —

a current sensing circuit sensing the bias current I_b generated by the first current source for the predetermined effective magnetic bias of the sensor portion of the MR transducer; and

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

a third current source responsive to the current sensing circuit by generating an output current when the bias current I_b generated by the first current source for the predetermined effective magnetic bias of the sensor portion of the MR transducer is less than a predetermined sensor bias current, the output current generated by the third current source being coupled to the transducer equivalent circuit and combining with the control current generated by the second current source to form a combined control current, the combined control current being related to the MR transducer bias current I_b so that a predetermined MR transducer bias current I_b flows through the MR transducer producing the predetermined effective magnetic bias of the sensor portion of the MR transducer.

46. The circuit according to claim 45, wherein the difference sensing circuit includes first and second transistors each having first, second and third nodes, the first node of first transistor being coupled to the first and third nodes of the second transistor, the second node of the first transistor being coupled to the MR transducer, and the second node of the second transistor being coupled to the transducer equivalent circuit, and

wherein the first current source includes a third transistor having first, second and third nodes, and the second current source includes a fourth transistor having first, second and third nodes, the first and third nodes of the third

This Sheet Has Been Replaced





transistor being coupled to the first node of the fourth transistor to form a current mirror, the third node of the third transistor being coupled to the third node of the first transistor, and the third node of the fourth transistor being coupled to the third node of the second transistor.

47. The circuit according to claim 46, wherein the current sensing circuit includes,

a fifth transistor having first, second and third nodes, the first node being coupled to the third node;

a fourth current source coupled to the third node of the fifth transistor; and

an amplifier circuit having a first input, a second input and an output, the first input being coupled to the third node of the third transistor, the second input being coupled to the third node of the fifth transistor and the output being coupled to the third current source.

THIS SHEET HAS BEEN
REPLACED

This Sheet Has Been Replaced

