

Description

This invention relates to a raster size regulating circuit.

In many television receivers or video display monitors, a combined scan and high voltage generator is utilized. Typically, an energy storage system is provided that includes a trace switch, a retrace capacitor, an S-shaping capacitor, and a horizontal deflection winding. During the retrace interval the switch is opened, forming a resonant retrace circuit that develops a large amplitude retrace pulse across the deflection winding. During the trace interval, the deflection winding generates a sawtooth shaped current which is used to deflect the electron beams horizontally across the screen of the picture tube. The deflection retrace pulse may be used in conjunction with an integrated high voltage transformer (IHVT) to generate the ultor voltage that accelerates the electron beams to the phosphor screen of the picture tube.

The IHVT includes a high voltage winding which is segmented into several winding sections. A high voltage diode is coupled in series with each winding segment. The large amplitude retrace pulse voltage is applied to the primary winding of the IHVT, stepped up by the high voltage winding, and rectified by the high voltage diodes to develop an ultor voltage of illustratively 24 to 29 kilovolts.

The low-AC end of the IHVT may be used to sample the beam current being drawn by the picture tube anode electrode that is coupled to the ultor terminal. Sampling is performed at a current resupply terminal of the high voltage winding remote from the ultor terminal. The current resupply terminal is interposed in the DC current path between a relatively low DC voltage source and the low-AC end of the high voltage winding.

The voltage at the resupply terminal will vary in accordance with picture tube loading on the ultor terminal. As more beam current is drawn from the anode of the picture tube due to increased video drive on the cathode, the voltage at the resupply terminal will decrease. This voltage is monitored by an automatic beam current limiter circuit. At a certain design threshold voltage, the automatic beam limiter circuit will limit the drive at the cathode and thus limit the current being supplied by the IHVT.

The IHVT has a typical source impedance of, illustratively, 1 megohm, and delivers ultor current of 1 to 2 milliamperes average, depending upon the desired picture power of the television receiver. Short duration, peak ultor current may reach a value of 10 milliamperes. As beam current is drawn by the picture tube anode, the ultor voltage will drop because of the IHVT impedance and because of the relatively low ultor terminal capacitance

formed by the inner and outer conductive coatings of the picture tube. The ultor terminal capacitance may equal 1400 picofarad in a 20 inch picture tube, and 2700 picofarad in a 26 inch picture tube. The lower the ultor capacitance, the greater the variation in ultor voltage with beam current loading.

Deflection sensitivity and thus raster size is a function of ultor voltage. Variations in ultor voltage produced by variations in beam current loading may produce undesirable variations in raster size that distort the picture displayed on the picture tube screen.

A most severe type of beam current loading is produced by the video signal drive of a block pattern picture illustrated in FIGURE 2A. The block pattern consists of high brightness, rectangular, white blocks B1 and B2, positioned on either side of a white vertical line VL0 that is positioned in the center of the picture. The rectangular blocks B1 and B2 are positioned only in the upper half of the picture. White vertical lines VL1 and VL2 are positioned at the left and right edges, respectively, of the picture.

During the first half of vertical scan, when the video signal of blocks B1 and B2 drive the cathode of the picture tube, the ultor terminal experiences heavy beam current loading and the ultor voltage decreases. The increased deflection sensitivity caused by the decrease in ultor voltage results in increased width of the raster lines scanned during the first half of vertical scan. This produces a distorted display of the block pattern.

As illustrated in FIGURE 2B, during the time of increased beam loading, during the first half of vertical scan, the raster will bend outwardly in a symmetrical manner with respect to the center vertical line VL0. The center line VL0, however, remains undistorted. Especially noticeable and objectionable are the outwardly bent sections S1 and S2 of respective vertical lines VL1 and VL2.

The block pattern of FIGURE 2A exhibits severe picture distortion due to beam current loading effects. Similar distortions may be observed when the displayed picture includes large blocks of lettering or includes computer generated block-like patterns.

US-A-4 645 984 discloses a compensation circuit which eliminates such distortions.

In accordance with an aspect of the invention, a raster size regulating circuit counters the picture distorting tendencies, described above, that may be attributed to beam current loading of the ultor terminal. A high voltage generator includes a high voltage transformer having a first winding to which first voltage pulses are coupled. A high voltage winding is coupled to a picture tube ultor terminal via a high voltage rectifying means and generates thereat an ultor voltage. A source of supply voltage

is coupled to a current resupply terminal of the high voltage winding at a point remote from the ultor terminal. Second voltage pulses are produced at the resupply terminal and have amplitudes which vary in accordance with loading on the ultor voltage. An envelope detector is coupled to the resupply terminal for envelope detecting the amplitude variations of the second voltage pulses to develop a size control signal which follows the loading induced variations in ultor voltage. The size control signal is coupled to a scanning current modulator that modulates the scanning current in a manner that regulates raster size.

In the Drawing:

FIGURE 1 illustrates a raster size regulating circuit, according to the invention;

FIGURE 2A illustrates a picture of a block pattern that is to be displayed on the screen of a picture tube;

FIGURE 2B illustrates a distorted block pattern picture that may be produced by beam current loading effects on the ultor terminal; and

FIGURES 3A-3D and FIGURE 4 illustrate waveforms useful in explaining the operation of the circuit of FIGURE 1.

In FIGURE 1, a B+ voltage is applied to the primary winding W1 of a flyback transformer T1. Primary winding W1 is coupled to a horizontal deflection output stage 20 comprising a horizontal output transistor Q1, a deflection damper diode D1, a deflection retrace capacitor CRH and a horizontal deflection winding L_H coupled in a series relationship with an S-shaping capacitor C_s. A horizontal oscillator and driver, not illustrated in FIGURE 1, provides horizontal rate switching of transistor Q1 to generate horizontal scanning current i_h in deflection winding L_H and a retrace pulse voltage v_R at the collector of transistor Q1.

A diode modulator 30 provides a means for modulating scanning current i_h to provide side pincushion correction of the raster scanned on the phosphor screen of a picture tube, not shown in FIGURE 1. Diode modulator 30 includes a modulator inductor L_m, a modulator trace capacitor C_m, a modulator damper diode D2, and a modulator retrace capacitor CRM. The modulator voltage v_m developed across modulator capacitor C_m is modulated by an amplifier U2 to provide the required side pincushion correction.

A vertical deflection circuit 40 includes an amplifier U1 that generates vertical scanning current i_v in a vertical deflection winding L_v. A current sampling resistor R_s and a DC-blocking capacitor C_v are coupled in series with vertical deflection winding L_v. A vertical parabola voltage v_v developed by vertical deflection circuit 40 is first AC coupled by a capacitor C4, then attenuated and filtered by a T-network comprising resistors R4 and R5, a variable

resistor R6, and a capacitor C5, and then applied to a terminal 32.

The attenuated vertical parabola voltage is summed at terminal 32 with an adjustable DC voltage that is developed at the wiper arm of a potentiometer R8 and coupled to terminal 32 via a resistor R7. The voltage developed at terminal 32 is applied to the inverting input terminal of amplifier U2. Adjustment of variable resistor R6 controls the pincushion correction amplitude. Adjustment of potentiometer R8 controls static raster width. An RC network 31 is coupled between the output terminal of amplifier U2 and the inverting input terminal for providing negative feedback and stable amplifier operation. A reference voltage developed by a zener diode Z1 is coupled to the noninverting input terminal of amplifier U2. Zener diode biasing is provided by a +24V voltage source that is coupled to the zener diode via a resistor R11.

Flyback transformer T1 functions as a high voltage transformer of a high voltage generator 50 that generates an ultor voltage V_{hv} at an ultor terminal 52. To generate ultor voltage V_{hv}, retrace pulse voltage v_R is applied to primary winding W1, stepped up by the segmented high voltage winding W2, rectified by corresponding high voltage diodes D3, and filtered by an ultor capacitance C_o to develop the DC ultor voltage V_{hv}. The ultor capacitance may be provided by the capacitance formed between the inner and outer conductive coatings of the picture tube.

The DC current path to ultor terminal 52 begins at a +24V supply terminal, goes through resistors R9 and R10 to a resupply terminal 51 that is coupled to the low-AC end of high voltage winding W2. An automatic beam current limiter circuit 53 is coupled to the junction of resistors R9 and R10 for limiting video drive to the picture tube when beam current loading on ultor terminal 52 reaches a predetermined value.

In accordance with an aspect of the invention, the voltage v_{rs} developed at resupply terminal 51 is coupled to an envelope detector 10 to generate a raster size control signal that is coupled to terminal 32 of the diode modulator for regulating raster size as a function of beam current loading.

Envelope detector 10 includes the series arrangement of a rectifier CR1 and a resistor R1. The series arrangement is coupled between current resupply terminal 51 and a terminal 11, with the anode of rectifier CR1 being coupled to terminal 11. A capacitor C2 is coupled between terminal 11 and ground. A resistor R2 is coupled across capacitor C2.

The current supplied to high voltage winding W2 by way of the +24V supply is in the form of relatively sharp, horizontal rate, current pulses flowing into resupply terminal 51. As illustrated in FIG-

FIGURE 4 by the voltage v_{rs} , the current pulses generate corresponding negative going voltage pulses 54, repeating at the horizontal rate $1/T_H$, where T_H equals the horizontal deflection interval. Higher frequency ringing due to tuning of the flyback transformer is superimposed on the positive going portions of voltage pulses 54. A high frequency bypass capacitor C1 is coupled between terminal 51 and ground.

The amplitude of the negative going, horizontal rate pulses 54 varies as a function of beam current loading on ultor terminal 52. As more beam current is drawn by the anode of the picture tube due to increased video drive on the cathode, voltage pulses 54 will become even more negative, with the negative peaks of the pulses following the beam current loading.

Consider a situation where the video signal driving the picture tube cathode represents the block pattern picture of FIGURE 2A. The resulting severe vertical rate beam current loading of ultor terminal 52 causes ultor voltage V_{HV} to drop each vertical interval, T_V , when blocks B1 and B2 are displayed on the picture tube screen, as illustrated in FIGURE 3A by the waveform portion 12a of ultor voltage V_{HV} . The decrease in ultor voltage produces an increased deflection sensitivity which tends to cause the raster width to increase, thereby tending to produce the outwardly bent segments S1 and S2 of vertical lines VL1 and VL2 in FIGURE 2B.

In accordance with a feature of the invention, envelope detector 10 of FIGURE 1 counters the tendency of the raster width to vary under beam current loading. Voltage v_{rs} developed at current resupply terminal 51 is coupled to envelope detector 10. Voltage v_{rs} is illustrated in FIGURE 3B. The time scale of FIGURE 3 is the larger vertical interval time scale as opposed to the horizontal interval time scale of FIGURE 4. The negative going horizontal rate pulses 54 occurring in FIGURE 4 near time t_1 are only shown schematically in FIGURE 3B by means of closely spaced vertical lines.

Because the negative going peaks of voltage pulses 54 of FIGURE 4 closely follow beam current loading on ultor terminal 52, the envelope 12 of the negative pulses also closely follows the beam current loading. At the vertical interval time scale of FIGURE 3B, it is noted that envelope 12 of the negative voltage pulses of voltage v_{rs} closely follows, in waveshape, the waveshape of voltage V_{HV} of FIGURE 3A. Thus, the sagging portion 12a of ultor voltage has a corresponding sagging portion 12b in envelope 12 of voltage v_{rs} .

Rectifier CR1 of envelope detector 10 is poled to conduct current during the negative-going excursions of voltage pulses 54 of FIGURE 4. Capacitor C2 is charged each horizontal interval via resistor

R1 and rectifier CR1 to a negative voltage that depends on the amplitudes of the negative going portions of voltage pulses 54. Resistor R2 allows capacitor C2 to slightly discharge within each horizontal interval when rectifier CR1 is blocked. This enables the voltage v_{ed} developed at terminal 11 to closely follow the envelope of the voltage pulses of voltage V_{rs} . As illustrated in FIGURES 3B and 3C, the waveshape of voltage portion 12c of envelope detector voltage v_{ed} closely follows in waveshape portion 12b of the envelope 12 of voltage V_{rs} . Advantageously, as a result of the envelope detection, the portion 12c of envelope detector voltage v_{ed} closely follows in waveshape the sagging voltage portion 12a of ultor voltage V_{HV} , as illustrated in FIGURES 3A and 3C.

The operation of envelope detector 10 is analogous to that of a diode detector of an amplitude modulated carrier signal. The horizontal rate voltage pulses 54 of FIGURE 4 provide the function of a carrier signal at the horizontal frequency. The carrier signal is then amplitude modulated by a signal having a waveshape similar to that of ultor voltage V_{HV} of FIGURE 3A. The result of the amplitude modulation is an amplitude modulated signal v_{rs} of FIGURE 3B, wherein at least the lower envelope 12 closely follows the waveshape of the modulating signal.

The time constants associated with the RC network in envelope detector 10, when rectifier CR1 is conducting or when blocked, are selected on the basis of filtering out large horizontal rate components from envelope detector voltage v_{ed} , while enabling the voltage v_{ed} to follow the negative going amplitude variations of the voltage pulses of voltage V_{rs} . The ratio of resistors R1 and R2 is selected to attenuate voltage v_{ed} to the proper amplitude required by the control circuitry of diode modulator 30.

Envelope detector voltage v_{ed} is AC coupled via a capacitor C3, further attenuated by a resistor R3, and summed at terminal 32 with the other diode modulator control voltages. In an alternative configuration, attenuating resistor R3 may be omitted. To achieve the same attenuation level at terminal 32 for envelope detector voltage v_{ed} , a voltage divider, not shown in FIGURE 2, may be coupled between resupply terminal 51 and ground. The input to envelope detector 10 will then be located at an intermediate point in the voltage divider.

To achieve raster size regulation with ultor terminal beam current loading, the AC coupled envelope detector voltage v_{ed} is subtracted from the AC coupled parabola voltage v_v . The resultant voltage is inverted at the output of amplifier U2 to develop modulator voltage v_m , illustrated in FIGURE 3D. FIGURE 3D omits from illustration any horizontal rate ripple component of voltage v_m .

During heavy beam current loading by blocks B1 and B2 of FIGURE 2A, during the first half of vertical scan, the amplitude of negative going parabola voltage v_m is modified in accordance with envelope detector voltage v_{ed} . Voltage portion 12d of modulator v_m is made more positive. The more positive modulator voltage v_m produces a decreased deflection trace voltage across S-shaping capacitor C_s , a decreased amplitude of scanning current i_h , and a decreased raster width. The decreased raster width counters the tendency of the raster to expand during the interval within vertical scan when blocks B1 and B2 are displayed. In this way, a dynamic raster width regulation capability is provided that compensates for rapid fluctuations in beam current levels that occur within as short a time interval as a vertical deflection interval.

Envelope detector 10 has the further advantage of following ultor voltage fluctuations across the entire range of average brightness levels, from high brightness levels down to minimal brightness levels. Even low levels of beam current loading will be detected by envelope detector 10 because of the nature of the current pulses that flow to resupply terminal 51 during each horizontal interval.

As a still further advantage, by supplying voltage v_{ed} as a size control signal to a side pincushion correction circuit such as a diode modulator, the ultor voltage remains unaffected by the size control signal modulation of the scanning current. Had it been otherwise, the concurrent modulation of the ultor voltage would have tended to cancel the size regulating effects of the modulation of the scanning current.

Claims

1. A raster size regulating circuit, comprising: a high voltage generator including a high voltage transformer having a first winding to which first voltage pulses are applied and a high voltage winding coupled to an ultor terminal of a picture tube via a high voltage rectifying means for generating an ultor voltage, wherein variation in loading on said ultor terminal due to variation in picture content produces a corresponding variation in ultor voltage;

a source of supply voltage coupled to a current resupply terminal of said high voltage winding remote from said ultor terminal and producing thereat second voltage pulses having amplitudes which vary in accordance with said ultor terminal loading;

a deflection winding;

a deflection output stage for generating scanning current in said deflection winding;

means coupled to said deflection winding for modulating said scanning current; charac-

terized by

an envelope detector (10) coupled to said resupply terminal (51) for envelope detecting amplitude variation of said second voltage pulses (V_{rs}) to develop a size control signal (V_{ed}) which follows the variation in ultor voltage, said size control signal (V_{ed}) being coupled to said modulating means (30) for modulating said scanning current (i_h) in a manner that regulates said raster size.

2. A circuit according to Claim 1 characterized in that said envelope detector (10) includes a rectifier (CR1) that is poled to conduct current during negative-going excursions of said second voltage pulses (V_{rs}).
3. A circuit according to Claim 1 characterized in that said envelope detector (10) has a response characteristic which enables said detector (10) to follow an ultor voltage variation that occurs within a vertical deflection interval.
4. A circuit according to Claim 1 characterized in that said modulating means (30) comprises a side pincushion modulator responsive to a side pincushion correction signal (V_v) for providing a side pincushion corrected scanning current.
5. A circuit according to Claim 4 characterized in that said side pincushion correction signal (V_v) and said size control signal (V_{ed}) are summed at a control terminal (32) of said side pincushion modulator.
6. A circuit according to Claim 4 characterized in that said high voltage transformer (T1) comprises a flyback transformer, with said first winding (W1) being coupled to said deflection output stage (20), and said side pincushion modulator (30) comprises a diode modulator that modulates said scanning current (i_h) in accordance with said size control signal (V_{ed}) without thereby producing significant modulation of said ultor voltage (V_{hv}).
7. A circuit according to either of Claims 3 or 6 characterized in that said envelope detector (10) includes a first resistor (R1) coupled to said resupply terminal (51) in a series relationship with a rectifier (CR1), a capacitor (C2) coupled to an electrode (anode) of said rectifier (CR1) remote from said resupply terminal (51), and a resistor (R2) coupled in a parallel relationship with said capacitor (C2) for developing said size control signal (V_{ed}) in said capacitor (C2).



During heavy beam current loading by blocks B1 and B2 of FIGURE 2A, during the first half of vertical scan, the amplitude of negative going parabola voltage v_m is modified in accordance with envelope detector voltage v_{ed} . Voltage portion 12d of modulator v_m is made more positive. The more positive modulator voltage v_m produces a decreased deflection trace voltage across S-shaping capacitor C_s , a decreased amplitude of scanning current i_h , and a decreased raster width. The decreased raster width counters the tendency of the raster to expand during the interval within vertical scan when blocks B1 and B2 are displayed. In this way, a dynamic raster width regulation capability is provided that compensates for rapid fluctuations in beam current levels that occur within as short a time interval as a vertical deflection interval.

Envelope detector 10 has the further advantage of following ultor voltage fluctuations across the entire range of average brightness levels, from high brightness levels down to minimal brightness levels. Even low levels of beam current loading will be detected by envelope detector 10 because of the nature of the current pulses that flow to resupply terminal 51 during each horizontal interval.

As a still further advantage, by supplying voltage v_{ed} as a size control signal to a side pincushion correction circuit such as a diode modulator, the ultor voltage remains unaffected by the size control signal modulation of the scanning current. Had it been otherwise, the concurrent modulation of the ultor voltage would have tended to cancel the size regulating effects of the modulation of the scanning current.

Claims

1. A raster size regulating circuit, comprising: a high voltage generator including a high voltage transformer having a first winding to which first voltage pulses are applied and a high voltage winding coupled to an ultor terminal of a picture tube via a high voltage rectifying means for generating an ultor voltage, wherein variation in loading on said ultor terminal due to variation in picture content produces a corresponding variation in ultor voltage;

a source of supply voltage coupled to a current resupply terminal of said high voltage winding remote from said ultor terminal and producing thereat second voltage pulses having amplitudes which vary in accordance with said ultor terminal loading;

a deflection winding;

a deflection output stage for generating scanning current in said deflection winding;

means coupled to said deflection winding for modulating said scanning current; charac-

terized by

an envelope detector (10) coupled to said resupply terminal (51) for envelope detecting amplitude variation of said second voltage pulses (V_{rs}) to develop a size control signal (V_{ed}) which follows the variation in ultor voltage, said size control signal (V_{ed}) being coupled to said modulating means (30) for modulating said scanning current (i_h) in a manner that regulates said raster size.

2. A circuit according to Claim 1 characterized in that said envelope detector (10) includes a rectifier (CR1) that is poled to conduct current during negative-going excursions of said second voltage pulses (V_{rs}).

3. A circuit according to Claim 1 characterized in that said envelope detector (10) has a response characteristic which enables said detector (10) to follow an ultor voltage variation that occurs within a vertical deflection interval.

4. A circuit according to Claim 1 characterized in that said modulating means (30) comprises a side pincushion modulator responsive to a side pincushion correction signal (V_v) for providing a side pincushion corrected scanning current.

5. A circuit according to Claim 4 characterized in that said side pincushion correction signal (V_v) and said size control signal (V_{ed}) are summed at a control terminal (32) of said side pincushion modulator.

6. A circuit according to Claim 4 characterized in that said high voltage transformer (T1) comprises a flyback transformer, with said first winding (W1) being coupled to said deflection output stage (20), and said side pincushion modulator (30) comprises a diode modulator that modulates said scanning current (i_h) in accordance with said size control signal (V_{ed}) without thereby producing significant modulation of said ultor voltage (V_{hv}).

7. A circuit according to either of Claims 3 or 6 characterized in that said envelope detector (10) includes a first resistor (R1) coupled to said resupply terminal (51) in a series relationship with a rectifier (CR1), a capacitor (C2) coupled to an electrode (anode) of said rectifier (CR1) remote from said resupply terminal (51), and a resistor (R2) coupled in a parallel relationship with said capacitor (C2) for developing said size control signal (V_{ed}) in said capacitor (C2).



Patentansprüche

1. Rastergrößenregelschaltung, enthaltend:
einen Hochspannungsgenerator, der einen Hochspannungstransformator mit einer ersten Wicklung enthält, an die erste Spannungsimpulse angelegt werden und eine Hochspannungswicklung, die zur Erzeugung einer Endanodenspannung an einen Endanodenanschluß einer Bildröhre über ein Hochspannungsgleichrichtmittelangeschlossen ist, in der Schwankungen der Last am genannten Endanodenanschluß aufgrund des Bildinhaltes eine entsprechende Schwankung der Endanodenspannung bewirken:

eine Versorgungsspannungsquelle, die an einen vom genannten Endanodenanschluß getrennten Stromrückspeisungsanschluß der genannten Hochspannungswicklung angeschlossen ist und dort zweite Spannungsimpulse erzeugt, die Amplituden aufweisen, die mit der Last am genannten Endanodenanschluß schwanken;

eine Ablenkwicklung;

eine Ablenkausgangsstufe zur Erzeugung eines Abtaststromes in der genannten Ablenkwicklung;

ein an die genannte Ablenkwicklung geschaltetes Mittel zur Modulation des genannten Stromes;

gekennzeichnet durch

einen mit dem genannten Stromrückspeisungsanschluß verbundenen Hüllkurvendetektor (10) zur Erfassung der Hüllkurve von Amplitudenschwankungen der genannten zweiten Spannungsimpulse (V_{rs}) zur Erzeugung eines Größensteuerungssignals (V_{ed}), das den Schwankungen der Endanodenspannung folgt, wobei das genannte Größensteuerungssignal (V_{ed}) zur Modulation des genannten Abtaststromes (I_h) in einer Weise, die die genannte Rastergröße regelt, an das genannte Modulationsmittel angelegt wird.

2. Schaltung gemäß Patentanspruch 1, dadurch gekennzeichnet, daß der genannte Hüllkurvendetektor (10) einen Gleichrichter (CR1) enthält, der derart gepolt ist, daß er während negativ verlaufender Auslenkungen der genannten zweiten Spannungsimpulse (V_{rs}) leitend ist.

3. Schaltung gemäß Patentanspruch 1, dadurch gekennzeichnet, daß der genannte Hüllkurvendetektor (10) einen Frequenzgang aufweist, der dem genannten Detektor (10) erlaubt, Schwankungen der Endanodenspannung zu folgen, die innerhalb eines Vertikalablenkintervalls auftreten.

4. Schaltung gemäß Patentanspruch 1, dadurch gekennzeichnet, daß das genannte Modulationsmittel (30) einen Modulator zur Korrektur der seitlichen Kissenverzerrung enthält, der auf ein Signal (V_v) zur Korrektur der seitlichen Kissenverzerrung reagiert, um einen bezüglich der seitlichen Kissenverzerrung korrigierten Abtaststrom zu liefern.

5. Schaltung gemäß Patentanspruch 4, dadurch gekennzeichnet, daß das genannte Korrektursignal für die seitliche Kissenverzerrung (V_v) und das Größensteuerungssignal (V_{ed}) an einem Steueranschluß (32) des genannten Modulators zur Korrektur der seitlichen Kissenverzerrung addiert werden.

6. Schaltung gemäß Patentanspruch 4, dadurch gekennzeichnet, daß der genannte Hochspannungstransformator (T1) einen Zeilenendtrafo enthält, wobei die erste Windung (W1) an die genannte Ablenkausgangsstufe (20) angeschlossen ist, und daß der genannte Modulator zur Korrektur der seitlichen Kissenverzerrung (30) einen Diodenmodulator enthält, der den genannten Abtaststrom (I_h) entsprechend dem genannten Größensteuerungssignal (V_{ed}) moduliert, ohne dabei eine erhebliche Modulation der genannten Endanodenspannung (V_{hv}) zu bewirken.

7. Schaltung gemäß irgendeinem der Patentansprüche 3 oder 6, dadurch gekennzeichnet, daß der genannte Hüllkurvendetektor (10) einen ersten Widerstand (R1) enthält, der in Reihe mit einem Gleichrichter (CR1) am genannten Rückspeisungsanschluß (51) angeschlossen ist, einen Kondensator (C2), der getrennt vom genannten Rückspeisungsanschluß (51) an eine Elektrode (Anode) des genannten Gleichrichters (CR1) angeschlossen ist, und einen Widerstand (R2), der mit dem genannten Kondensator (C2) parallel geschaltet ist, um das genannte Größensteuerungssignal (V_{ed}) im genannten Kondensator (C2) zu erzeugen.

Revendications

1. Circuit de réglage de format de trame comprenant :
un générateur haute tension comprenant un transformateur haute tension ayant un premier enroulement, auquel sont appliquées des premières impulsions de tension, et un enroulement haute tension couplé à une borne d'anode terminale d'un tube image par un organe de redressement de haute tension pour générer une tension d'anode terminale, dans lequel



la variation de la charge sur ladite borne d'anode terminale, d'oue à une variation du contenu d'image, produit une variation correspondante de la tension d'anode terminale ;

une source de tension de secteur coupée à une borne de réalimentation en courant de l'enroulement haute tension mentionné éloigné de ladite borne d'anode terminale et y produisant des secondes impulsions de tension qui ont des amplitudes qui varient selon ladite charge de la borne d'anode terminale ;

un enroulement de déviation ;

un étage de sortie de déviation pour générer le courant de balayage dans ledit enroulement de déviation ;

un organe couplé à l'enroulement de déviation mentionné pour moduler ledit courant de balayage ;

caractérisé par

un détecteur d'enveloppante (10) coupé à ladite borne de réalimentation (51) pour détection d'enveloppante de la variation en amplitude des secondes impulsions de tension mentionnées (V_{ns}) pour produire un signal de contrôle de format (V_{ed}) qui suit la variation de tension d'anode terminale, ledit signal de contrôle de format (V_{ed}) étant couplé à l'organe de modulation mentionné (30) pour moduler ledit courant de balayage (i_h) d'une manière qui règle ledit format de trame.

2. Circuit selon la revendication 1, **caractérisé en ce que** ledit détecteur d'enveloppante (10) comprend un redresseur (CR1) qui est polarisé pour conduire le courant pendant les excursions de sens négatif des secondes impulsions de tension mentionnées (V_{ns}).

3. Circuit selon la revendication 1, **caractérisé en ce que** ledit détecteur d'enveloppante (10) a une courbe de réponse qui permet au détecteur mentionné (10) de suivre une variation de tension d'anode terminale qui intervient à l'intérieur d'un intervalle de déviation verticale.

4. Circuit selon la revendication 1, **caractérisé en ce que** ledit organe de modulation (30) comprend un modulateur de coussin latéral sensible à un signal de correction de coussin latéral (V_v) pour fournir un courant de balayage à coussin latéral corrigé.

5. Circuit selon la revendication 4, **caractérisé en ce que** le dit signal de correction de coussin latéral (V_v) et ledit signal de contrôle de format (V_{ed}) sont additionnés à une borne de contrôle (32) du modulateur de coussin latéral mentionné.

6. Circuit selon la revendication 4, **caractérisé en ce que** ledit transformateur haute tension (T1) comprend un transformateur de retour de balayage horizontal avec ledit premier enroulement (W1) couplé à l'étage de sortie de déviation mentionné (20), et ledit modulateur de coussin latéral (30) comprend un modulateur à diode qui module ledit courant de balayage (i_h) en accord avec ledit signal de contrôle de format (V_{ed}) sans produire en même temps de modulation significative de ladite tension d'anode terminale (V_{hv}).

7. Circuit selon l'une ou l'autre des revendications 3 ou 6, **caractérisé en ce que** ledit détecteur d'enveloppante (10) comprend une première résistance (R1) couplée à ladite borne de réalimentation (51) en série avec un redresseur (CR1), un condensateur (C2) couplé à une électrode (anode) du redresseur mentionné (CR1) éloignée de la borne de réalimentation mentionnée (51) et une résistance (R2) couplée en parallèle avec ledit condensateur (C2) pour produire ledit signal de contrôle de format (V_{ed}) dans ledit condensateur (C2).