

SENSOR SYSTEMS FOR MEASURING AN INTERFACE LEVEL IN A MULTI-PHASE FLUID COMPOSITION

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] This application is related to concurrently filed application Ser. No. 13/630,739, titled SYSTEMS AND METHODS FOR MEASURING AN INTERFACE LEVEL IN A MULTI-PHASE FLUID COMPOSITION, filed jointly in the names of Cheryl Surman, William Platt, William Morris, Steven Go, Jon Dieringer and Radislav A. Potyrailo, assigned to General Electric Company, the assignee of the present invention.

TECHNICAL FIELD

[0002] The subject matter disclosed herein generally relates to sensors, and more particularly to level sensors to determine the interface level of a multi-phase fluid composition.

BACKGROUND

[0003] Measurement of the composition of emulsions and the interface level of immiscible fluids is important in many applications. For example, it is important to characterize emulsions in oil field management. The measurement of the water and oil content of emulsions from individual oil wells may vary over the life of an oil field and may indicate the overall health of a field. In the case of injection wells, it is critical to control water quality to reduce hydrate formation and corrosion. Characterization of the composition of the oil and water mixture (e.g., measurement of the relative proportions of oil and water in the mixture) helps the operator improve well productivity and capacity. The information obtained is also useful to reduce back-pressure of wells, flowline size and complexity, and thermal insulation requirements.

[0004] Characterization of emulsions is also important in the operation of systems that contain fluids in a vessel (vessel systems) such as fluid processing systems. Vessel systems may include storage tanks, reactors, separators and desalters. Vessel

systems are used in many industries and processes, such as the oil and gas, chemical, pharmaceutical, food processing industries, among others. For example, separation of water from raw oil is important to establishing production streams of oil and gas. Crude oil leaving the wellhead is both sour (contains hydrogen sulfide gas) and wet (contains water). The crude leaving the wellhead must be processed and treated to make it economically viable for storage, processing and export. One way of treating the raw oil is through the use of a separator. Most separators are driven by gravity and use the density differences between individual fluid phases of oil, water, gas, and solids to accomplish the separation. Identification of the interface levels of these layers is critical to the control of the separation process. Another fluid processing system where characterization of emulsions and measurement of the interface level is important is a desalter. Desalters are used in a refinery to control overhead corrosion downstream. In a desalter water and crude oil are mixed, inorganic salts are extracted into the water, and water is then separated and removed.

[0005] Finally, it is important to accurately characterize the water and salinity in the crude oil itself at various stages of the life of the product from a cost standpoint. Oil is a valuable commodity and underestimation of the water content in a typical tanker load can have significant cost consequences.

[0006] Wastewater management is another application where measurement and characterization of emulsion is important. Large quantities of oily wastewater are generated in the petroleum industry from both recovery and refining. A key factor in controlling the oil discharge concentrations in wastewater is improved instrumentation for monitoring the oil content of emulsions.

[0007] Many types of level and interface instruments have been contemplated over the years and a subset of those have been commercialized. Among those are gamma-ray sensors, guided wave sensors, magnetostrictive sensors, microwave sensors, ultrasonic sensors, single plate capacitance/admittance sensors, segmented capacitance sensors, inductive sensors, and computed tomography sensors. Each of the sensors has advantages and disadvantages. Some of the sensors are prohibitively expensive for many users. Some of the sensors may require a cooling jacket to

perform at operating temperatures (above 125° C). Some interface instruments require a clear interface to work, which can be problematic when working with diffuse emulsions. Some are susceptible to fouling. Other sensors do not have the ability to provide a profile of the tank, but rather monitor discrete points in the desalting process. Systems using electrodes are susceptible to the shorting of electrodes in high salinity applications and are susceptible to fouling. Finally, many of these systems are complex and difficult to implement.

[0008] Some existing sensor systems have used individual capacitive elements to measure fluid levels. A key limitation of those sensor systems is their inability to simultaneously quantify several components in the liquid. Capacitance methods have been used to measure dielectric constant of a liquid using specially designed electrodes for capacitance measurements. These designs are limited by the need for separate types of electrodes for capacitance measurements and for conductivity measurements. Inductor capacitor circuits also have been used to monitor the fluid level in a container using an electromagnetic resonator where change in capacitance was related to fluid level and fluid type. However, it has been the consensus of those of ordinary skill in the art that the filling of the resonator by a conducting liquid increased the uncertainties and noise in measurements by about one order of magnitude as compared to the values in a non-conducting fluid such as in air. However, these methods do not provide accurate measurements of concentrations of individual analytes at the limits of their minimum and maximum concentrations in the mixture.

[0009] With existing sensor systems, no one system is capable of delivering a combination of low cost, high sensitivity, favorable signal-to-noise ratio, high selectivity, high accuracy, and high data acquisition speeds. Additionally no existing system has been described as capable of accurately characterizing or quantifying fluid mixtures where one of the fluids is at a low concentration (i.e. at their minimum and maximum limits).

BRIEF DESCRIPTION OF THE INVENTION

[0010] The disclosure provides a technical solution to the expense, reliability and accuracy problems of existing level sensor systems. An electrically resonant transducer (resonant transducer) provides a combination of low cost, high sensitivity, favorable signal-to-noise ratio, high selectivity, high accuracy, and high data acquisition speeds. The resonant transducer is incorporated in a robust sensor without the need for a clear interface. The solution also provides a sensor that is less susceptible to fouling, particularly in applications involving emulsions.

[0011] In accordance with one exemplary non-limiting embodiment, the disclosure relates to a sensor having a resonant transducer configured to determine a composition of an emulsion and includes a sampling assembly and an impedance analyzer.

[0012] In another embodiment, the disclosure relates to a system including a fluid processing system; a fluid sampling assembly; and a resonant sensor system coupled to the fluid sampling assembly.

[0013] In another embodiment, the disclosure relates to a method for measuring a level of a mixture of fluids in a vessel. The method includes the steps of detecting a signal from a resonant sensor system at a plurality of locations in the vessel; converting each signal to values of the complex impedance spectrum for the plurality of locations; storing the values of the complex impedance spectrum and frequency values; and determining a fluid phase inversion point from the values of the complex impedance spectrum.

[0014] In another embodiment, the disclosure relates to a method for determining a composition of a mixture of oil and water in a vessel. The method includes the step of determining values of the complex impedance spectrum of the mixture of oil and water as a function of a height in the vessel with a resonant transducer. The method also includes the step of determining a fluid phase inversion point from the values of the complex impedance spectrum; applying an oil phase model to the values of the complex impedance spectrum and conductivity values above the fluid phase inversion

point, and applying a water phase model to the values of the complex impedance spectrum below the fluid phase inversion point.

[0015] In another embodiment, the disclosure relates to a sensor comprising a resonant transducer configured to simultaneously determine concentration of a first and a second component of an emulsion.

[0016] In another embodiment, the disclosure relates to a sensor having a resonant transducer configured to determine a composition of an emulsion.

[0017] In another embodiment, the disclosure relates to a sensor system having a resonant transducer configured to determine a composition of an emulsion. The sensor system includes a sampling assembly and an impedance analyzer.

[0018] In another embodiment, the disclosure relates to a method for determining a composition of a mixture of a first fluid and a second fluid in a vessel. The determination of the composition is accomplished by determining, with a sensor system, a set of complex impedance spectrum values of the mixture of the first fluid and the second fluid as a function of a height in the vessel. The method includes the step of determining a fluid phase inversion point from the set of complex impedance spectrum values. The method also includes the steps of applying a phase model of the first fluid to the set of complex impedance spectrum values above the fluid phase inversion point, and applying a phase model of the second fluid to the set of complex impedance spectrum values below the fluid phase inversion point.

BRIEF DESCRIPTION OF THE DRAWINGS

[0019] Other features and advantages of the present disclosure will be apparent from the following more detailed description of the preferred embodiment, taken in conjunction with the accompanying drawings which illustrate, by way of example, the principles of certain aspects of the disclosure.

[0020] Figure 1 is a schematic of a non-limiting embodiment of a resonant sensor system.

[0021] Figure 2 is a non-limiting illustration of the operation of a resonant transducer.

[0022] Figure 3 is an example of a measured complex impedance spectrum used for multivariate analysis.

[0023] Figure 4 illustrates an embodiment of a two-dimensional resonant transducer.

[0024] Figure 5 illustrates an embodiment of a three-dimensional resonant transducer.

[0025] Figure 6 is a schematic electrical diagram of the equivalent circuit of a three-dimensional resonant transducer.

[0026] Figure 7 is a chart illustrating the R_p response of a resonant transducer to varying mixtures of oil and water.

[0027] Figure 8 is a chart illustrating the C_p response of a resonant transducer to varying mixtures of oil and water.

[0028] Figure 9 is a partial cutaway side view of an embodiment of a resonant transducer assembly.

[0029] Figure 10 is a schematic diagram of an embodiment of a fluid processing system.

[0030] Figure 11 is a schematic diagram of an embodiment of a desalter.

[0031] Figure 12 is a schematic diagram of an embodiment of a separator.

[0032] Figure 13 is a chart illustrating the frequency (F_p) response of a three-dimensional resonant transducer to increasing concentrations of oil-in-water and water-in-oil emulsions.

[0033] Figure 14 is a chart illustrating the frequency (F_p) response of a two-dimensional resonant transducer to increasing concentrations of oil-in-water and water-in-oil emulsions.

[0034] Figure 15 is a flow chart of an embodiment of a method for determining the composition of an oil and water mixture as a function of height.

[0035] Figure 16 is a chart illustrating data used to determine a fluid phase inversion point and conductivity.

[0036] Figure 17 is a chart illustrating the results of an analysis of the experimental data of an embodiment of a resonant sensor system.

[0037] Figure 18 is a chart illustrating test results of a resonant sensor system in a simulated desalter.

[0038] Figure 19 is an embodiment of a display of a data report from a resonant sensor system.

[0039] Figure 20 is a flowchart of an embodiment of a method for determining the level of a fluid in a vessel.

[0040] Figure 21 is a block diagram of a non-limiting representative embodiment of a processor system for use in a resonant sensor system.

DETAILED DESCRIPTION OF THE INVENTION

[0041] As discussed in detail below, embodiments of the present invention provide low cost systems for reliably and accurately measuring the fluid level in a fluid processing vessel. A resonant sensor system provides effective and accurate measurement of the level of the transition or emulsion layer through the use of a resonant transducer such as an inductor-capacitor-resistor structure (LCR) multivariable resonant transducer and the application of multivariate data analysis applied to the signals from the transducer. The resonant sensor system also provides the ability to determine the composition of water and oil mixtures, oil and water mixtures and, where applicable, the emulsion layer.

[0042] The resonant transducer includes a resonant circuit and a pick up coil. The electrical response of the resonant transducer immersed in a fluid is translated into simultaneous changes to a number of parameters. These parameters may include the complex impedance response, resonance peak position, peak width, peak height and peak symmetry of the impedance response of the sensor antenna, magnitude of the real part of the impedance, resonant frequency of the imaginary part of the impedance, antiresonant frequency of the imaginary part of the impedance, zero-reactance frequency, phase angle, and magnitude of impedance, and others as described in the definition of the term sensor "spectral parameters." These spectral parameters may change depending upon the dielectric properties of the surrounding fluids. The typical configuration of a resonant transducer may include an LCR resonant circuit and an antenna. The resonant transducer may operate with a pickup coil connected to the detector reader (impedance analyzer) where the pickup coil provides excitation of the transducer and detection of the transducer response. The resonant transducer may also operate when the excitation of the transducer and detection transducer response is performed when the transducer is directly connected to the detector reader (impedance analyzer).

[0043] A resonant transducer offers a combination of high sensitivity, favorable signal-to-noise ratio, high selectivity, high accuracy, and high data acquisition speeds in a robust sensor without the need for optical transparency of the analyzed fluid and the measurement flow path. Instead of conventional impedance spectroscopy that scans across a wide frequency range (from a fraction of Hz to tens of MHz or GHz) a resonant transducer is used to acquire a spectrum rapidly and with high signal-to-noise across only a narrow frequency range. The sensing capability is enhanced by putting the sensing region between the electrodes that constitute a resonant circuit. As implemented in a fluid processing system such as a desalter or a separator, the resonant sensor system may include a sampling assembly and a resonant transducer coupled to the fluid sampling assembly. The resonant sensor system implements a method for measuring the level of a mixture of fluids in a vessel, and may also implement a method for determining the composition of a mixture of oil and water in a vessel. The resonant transducers are capable of accurately quantifying individual

analytes at their minimum and maximum limits. The resonant sensor system is able to determine the composition of fluid mixtures even when one of the fluids is at a low concentration.

[0044] A nonlimiting examples of fluid processing systems include reactors, chemical reactors, biological reactors, storage vessels, containers, and others known in the art.

[0045] Illustrated in Figure 1 is a schematic of an embodiment of a resonant sensor system 11. The resonant sensor system 11 includes a resonant transducer 12, a sampling assembly 13, and an impedance analyzer (analyzer 15). The analyzer 15 is coupled to a processor 16 such as a microcomputer. Data received from the analyzer 15 is processed using multivariate analysis, and the output may be provided through a user interface 17. Analyzer 15 may be an impedance analyzer that measures both amplitude and phase properties and correlates the changes in impedance to the physical parameters of interest. The analyzer 15 scans the frequencies over the range of interest (i.e., the resonant frequency range of the LCR circuit) and collects the impedance response from the resonant transducer 12.

[0046] As shown in Figure 2, resonant transducer 12 includes an antenna 20 disposed on a substrate 22. The resonant transducer may be separated from the ambient environment with a dielectric layer 21. In some embodiments, the thickness of the dielectric layer 21 may range from 2 nm to 50 cm, more specifically from 5 nm to 20 cm; and even more specifically from 10 nm to 10 cm. In some applications the resonant transducer 12 may include a sensing film deposited onto the transducer. In response to environmental parameters an electromagnetic field 23 may be generated in the antenna 20 that extends out from the plane of the resonant transducer 12. The electromagnetic field 23 may be affected by the dielectric property of an ambient environment providing the opportunity for measurements of physical parameters. The resonant transducer 12 responds to changes in the complex permittivity of the environment. The real part of the complex permittivity of the fluid is referred to as a "dielectric constant". The imaginary part of the complex permittivity of the fluid is

referred to as a "dielectric loss factor". The imaginary part of the complex permittivity of the fluid is directly proportional to conductivity of the fluid.

[0047] Measurements of fluids can be performed using a protecting layer that separates the conducting medium from the antenna 20. Response of the resonant transducer 12 to the composition of the fluids may involve changes in the dielectric and dimensional properties of the resonant transducer 12. These changes are related to the analyzed environment that interacts with the resonant transducer 12. The fluid-induced changes in the resonant transducer 12 affect the complex impedance of the antenna circuit through the changes in material resistance and capacitance between the antenna turns.

[0048] For selective fluid characterization using a resonant transducer 12, the complex impedance spectra of the sensor antenna 20 are measured as shown in Figure 3. At least three data points of impedance spectra of the emulsion are measured. Better results may be achieved when at least five data points of the impedance spectra of the emulsion are measured. Non limiting examples of number of measured data points are 8, 16, 32, 64, 101, 128, 201, 256, 501, 512, 901, 1024, 2048 data points. Spectra may be measured as a real part of impedance spectra or an imaginary part of impedance spectra or both parts of impedance spectra. Non-limiting examples of LCR resonant circuit parameters include impedance spectrum, real part of the impedance spectrum, imaginary part of the impedance spectrum, both real and imaginary parts of the impedance spectrum, frequency of the maximum of the real part of the complex impedance (F_p), magnitude of the real part of the complex impedance (Z_p), resonant frequency (F_1) and its magnitude (Z_1) of the imaginary part of the complex impedance, and anti-resonant frequency (F_2) and its magnitude (Z_2) of the imaginary part of the complex impedance.

[0049] Additional parameters may be extracted from the response of the equivalent circuit of the resonant transducer 12. Non-limiting examples of the resonant circuit parameters may include quality factor of resonance, zero-reactance frequency, phase angle, and magnitude of impedance of the resonance circuit response of the resonant transducer 12. Applied multivariate analysis reduces the dimensionality of the multi-

variable response of the resonant transducer 12 to a single data point in multidimensional space for selective quantitation of different environmental parameters of interest. Non-limiting examples of multivariate analysis tools are canonical correlation analysis, regression analysis, nonlinear regression analysis, principal components analysis, discriminate function analysis, multidimensional scaling, linear discriminate analysis, logistic regression, and/or neural network analysis. By applying multivariate analysis of the full complex impedance spectra or the calculated spectral parameters, quantitation of analytes and their mixtures with interferences may be performed with a resonant transducer 12. Besides measurements of the complex impedance spectra parameters, it is possible to measure other spectral parameters related to the complex impedance spectra. Examples include, but are not limited to, S-parameters (scattering parameters) and Y-parameters (admittance parameters). Using multivariate analysis of data from the sensor, it is possible to achieve simultaneous quantitation of multiple parameters of interest with a single resonant transducer 12.

[0050] A resonant transducer 12 may be characterized as one-dimensional, two-dimensional, or three-dimensional. A one-dimensional resonant transducer 12 may include two wires where one wire is disposed adjacent to the other wire and may include additional components.

[0051] Shown in Figure 4 is a two-dimensional resonant transducer 25 having a transducer antenna 27. The two-dimensional resonant transducer 25 is a resonant circuit that includes an LCR circuit. In some embodiments, the two-dimensional resonant transducer 25 may be coated with a sensing film 21 applied onto the sensing region between the electrodes. The transducer antenna 27 may be in the form of coiled wire disposed in a plane. The two-dimensional resonant transducer 25 may be wired or wireless. In some embodiments, the two-dimensional resonant transducer 25 may also include an IC chip 29 coupled to transducer antenna 27. The IC chip 29 may store manufacturing, user, calibration and/or other data. The IC chip 29 is an integrated circuit device and it includes RF signal modulation circuitry that may be fabricated using a complementary metal-oxide semiconductor (CMOS) process and a nonvolatile memory. The RF signal modulation circuitry components may include a

diode rectifier, a power supply voltage control, a modulator, a demodulator, a clock generator, and other components.

[0052] Sensing is performed via monitoring of the changes in the complex impedance spectrum of the two-dimensional resonant transducer 25 as probed by the electromagnetic field 23 generated in the transducer antenna 27. The electromagnetic field 23 generated in the transducer antenna 27 extends out from the plane of the two-dimensional resonant transducer 25 and is affected by the dielectric property of the ambient environment, providing the opportunity for measurements of physical, chemical, and biological parameters.

[0053] Shown in Figure 5 is a three-dimensional resonant transducer 31. The three-dimensional resonant transducer 31 includes a top winding 33 and a bottom winding 35 coupled to a capacitor 37. The top winding 33 is wrapped around an upper portion of a sampling cell 39 and the bottom winding 35 is wrapped around a lower portion of the sampling cell 39. The sampling cell 39 may, for example, be made of a material resistant to fouling such as Polytetrafluoroethylene (PTFE), a synthetic fluoropolymer of tetrafluoroethylene.

[0054] The three-dimensional resonant transducer 31 utilizes mutual inductance of the top winding 33 to sense the bottom winding 35. Illustrated in Figure 6 is an equivalent circuit 41, including a current source 43, R0 resistor 45, C0 capacitor 47, and L0 inductor 49. The equivalent circuit 41 also includes L1 inductor 51, R1 resistor 53 and C1 capacitor 55. The circuit also includes Cp capacitor 57 and Rp resistor 59. The circled portion of the equivalent circuit 41 shows a sensitive portion 61 that is sensitive to the properties of the surrounding test fluid. A typical Rp response and Cp response of resonant a transducer 12 to varying mixtures of oil and water are shown in Figures 7 and 8 respectively.

[0055] The three-dimensional resonant transducer 31 may be shielded as shown in Figure 9. A resonant transducer assembly 63 includes a radio frequency absorber (RF absorber layer 67) surrounding the sampling cell 39, top winding 33, and bottom winding 35. A spacer 69 may be provided surrounded by a metal shield 71. The

metal shield 71 is optional, and is not part of the transducer 31. The metal shield 71 allows operation inside or near metal objects and piping, reduces noise, and creates a stable environment such that any changes in the sensor response is directly due to changes in the test fluid. In order to successfully encapsulate the sensor in a metal shield 71 the RF absorber layer 67 may be placed between the sensor and the metal shield 71. This prevents the RF field from interacting with the metal and quenching the response of the sensor. The metal shield 71 may be wrapped with a cover 73 of suitable material. The RF absorber layer 67 can absorb electromagnetic radiation in different frequency ranges with non-limiting examples in the kilohertz, megahertz, gigahertz, terahertz frequency ranges depending on the operation frequency of the transducer 31 and the potential sources of interference. The absorber layer 67 can be a combination of individual layers for particular frequency ranges so the combinations of these individual layers provide a broader spectral range of shielding.

[0056] Fouling of the resonant sensor system 11 may be reduced by providing the resonant transducer 12 with a geometry that enables resonant transducer 12 to probe the environment over the sample depth perpendicular to the transducer ranging from 0.1 mm to 1000 mm. Signal processing of the complex impedance spectrum reduces the effects of fouling over the sample depth.

[0057] As shown in Figure 10, the resonant sensor system 11 may be used to determine the level and composition of fluids in a fluid processing system 111. Fluid processing system 111 includes a vessel 113 with a sampling assembly 115 and a resonant sensor system 11. The resonant sensor system 11 includes at least one resonant transducer 12 coupled to the sampling assembly 115. Resonant sensor system 11 also includes an analyzer 15 and a processor 16.

[0058] In operation, a normally immiscible combination of fluids enters the vessel through a raw fluid input 123. The combination of fluids may include a first fluid and a second fluid normally immiscible with the first fluid. As the combination of fluids is processed, the combination of fluids is separated into a first fluid layer 117, and a second fluid layer 119. In between the first fluid layer 117 and second fluid layer 119, there may be a rag layer 121. After processing, a first fluid may be extracted

through first fluid output 125, and a second fluid may be extracted through second fluid output 127. The resonant sensor system 11 is used to measure the level of the first fluid layer 117, the second fluid layer 119 and the rag layer 121. The resonant sensor system 11 may also be used to characterize the content of the first fluid layer 117, the second fluid layer 119 and the rag layer 121.

[0059] An embodiment of a fluid processing system 111 is a desalter 141 illustrated in Figure 11. The desalter 141 includes a desalter vessel 143. Raw oil enters the desalter 141 through crude oil input 145 and is mixed with water from water input 147. The combination of crude oil and water flows through mixing valve 149 and into the desalter vessel 143. The desalter 141 includes a treated oil output 151 and a wastewater output 153. Disposed within the desalter vessel 143 are an oil collection header 155 and a water collection header 157. Transformer 159 and transformer 161 provide electricity to top electrical grid 163 and bottom electrical grid 165. Disposed between top electrical grid 163 and bottom electrical grid 165 are emulsion distributors 167.

[0060] In operation, crude oil mixed with water enters the desalter vessel 143 and the two fluids are mixed and distributed by emulsion distributors 167 thereby forming an emulsion. The emulsion is maintained between the top electrical grid 163 and the bottom electrical grid 165. Salt containing water is separated from the oil/water mixture by the passage through the top electrical grid 163 and bottom electrical grid 165 and drops towards the bottom of the desalter vessel 143 where it is collected as waste water.

[0061] Control of the level of the emulsion layer and characterization of the contents of the oil-in-water and water-in-oil emulsions is important in the operation of the desalter 141. Determination of the level of the emulsion layer may be accomplished using a sampling assembly such as a try-line assembly 169 coupled to the desalter vessel 143 and having at least one resonant transducer 12 disposed on try-line output conduit 172. The resonant transducer 12 may be coupled to a data collection component 173. In operation, the resonant transducer 12 is used to measure the level of water and the oil and to enable operators to control the process.

The try-line assembly 169 may be a plurality of pipes open at one end inside the desalter vessel 143 with an open end permanently positioned at the desired vertical position or level in the desalter vessel 143 for withdrawing liquid samples at that level. There are generally a plurality of sample pipes in a processing vessel, each with its own sample valve, with the open end of each pipe at a different vertical position inside the unit, so that liquid samples can be withdrawn from a plurality of fixed vertical positions in the unit. Another approach to measuring the level of the emulsion layer is to use a swing arm sampler. A swing arm sampler is a pipe with an open end inside the desalter vessel 143 typically connected to a sampling valve outside the unit. It includes an assembly used to change the vertical position of the open end of the angled pipe in the desalter 141, by rotating it, so that liquid samples can be withdrawn (or sampled) from any desired vertical position.

[0062] Another method to measure the level of the oil and water is to dispose at least one resonant transducer 12 on a dipstick 175. A dipstick 175 may be a rod with a resonant transducer 12 that is inserted into the desalter vessel 143. Measurements are made at a number of levels. Alternately, the dipstick 175 may be a stationary rod having a plurality of multiplexed resonant transducers 12. The resonant transducer 12 may be coupled to a data collection component 179 that collects data from the various readings for further processing.

[0063] Another embodiment of a fluid processing system 111 is a separator 191 illustrated in Figure 12. The separator 191 includes a separator vessel 193 having an input conduit 195 for crude oil. Crude oil flowing from input conduit 195 impacts an inlet diverter 197. The impact of the crude oil on the inlet diverter 197 causes water particles to begin to separate from the crude oil. The crude oil flows into the processing chamber 199 where it is separated into a water layer 201 and an oil layer 203. The crude oil is conveyed into the processing chamber 199 below the oil/water interface 204. This forces the inlet mixture of oil and water to mix with the water continuous phase in the bottom of the vessel and rise through the oil/water interface 204 thereby promoting the precipitation of water droplets which are entrained in the oil. Water settles to the bottom while the oil rises to the top. The oil is skimmed over a weir 205 where it is collected in oil chamber 207. Water may be withdrawn from

the system through a water output conduit 209 that is controlled by a water level control valve 211. Similarly oil may be withdrawn from the system through an oil output conduit 213 controlled by an oil level control valve 215. The height of the oil/water interface may be detected using a try-line assembly 217 having at least one resonant transducer 12 disposed in a try-line output conduit 218 and coupled to a data processor 221. Alternately a dip stick 223 having at least one resonant transducer 12 coupled to a processor 227 may be used to determine the level of the oil/water interface 204. The determined level is used to control the water level control valve 211 to allow water to be withdrawn so that the oil/water interface is maintained at the desired height.

[0064] The following examples are given by way of illustration only and are not intended as a limitation of the scope of this disclosure. A model system of heavy mineral oil, tap water and detergent was used to carry out static tests for various designs of resonant transducer 12. The level of detergent was kept constant for all of the mixtures.

[0065] Example 1. In the case of the three-dimensional resonant transducer 31 disposed on a try-line or swing arm sampling assembly 13, different compositions of oil and water were poured into a sample cell with the three-dimensional resonant transducer 31 wound around the outside of the sample cell. Figure 13 shows the try-line/swing arm response in terms of F_p (frequency shift of the real impedance) as oil concentration increases. The calculated detection limit of the composition of oil in oil-in-water emulsions (Figure 13 part A) is 0.28% and of oil in water-in-oil emulsions (Figure 13 part B) is 0.58%.

[0066] Example 2. In the case of the two-dimensional resonant transducer 25, the two-dimensional resonant transducer 25 was immersed in different compositions of oil and water. Figure 14 shows the response of a two-dimensional resonant transducer 25 (2 cm circular) in terms of F_p (frequency shift of the real impedance) as oil concentration increases. The calculated detection limit of the composition of oil in oil-in-water emulsions (Figure 14 part A) is 0.089% and of oil in water-in-oil emulsions (Figure 14 part B) is 0.044%. This example illustrates that small

concentrations of one fluid mixed large concentrations of another fluid can be measured with a high degree of accuracy.

[0067] Example 3. The model system was loaded with 250 mL of mineral oil and treated with detergent at a concentration of 1 drop per 50 mL (5 drops). The mineral oil was stirred and injected through the sensor and the impedance spectra are recorded. Small additions of water were added with constant salinity and same detergent treatment. After the water volume exceeded 66% or 500 mL of water, the system was cleaned and the experiment is repeated with different salinity waters. The multivariate response of the two-dimensional resonant transducer 25 was sensitive to changes in composition and conductivity at all levels in the test vessel of the model system. Although the effect of conductivity and composition are somewhat convoluted, the fact that the sensor monitors a composition gradient allows the data analysis procedure to deconvolute these effects.

[0068] Figure 15 is a generalized process diagram illustrating a method 261 for determining the composition of an oil and water mixture as a function of height.

[0069] In step 263 data (a set of LCR resonant circuit parameters) is collected as a function of height from top to bottom (in the lab, this is simulated by starting with 100% oil and gradually adding water).

[0070] In step 265 the conductivity of water using calibration is determined. At 100% water, the multivariate response is compared to a calibration for water conductivity.

[0071] In step 267 the fluid phase inversion point is determined using Z parameters.

[0072] In step 269 the Z parameters are combined with conductivity and fluid phase data.

[0073] In step 271 an oil phase model is applied. The oil phase model is a set of values correlating measured frequency values, impedance values and conductivity values to oil content in an oil and water mixture.

[0074] In step 273 a water phase model is applied. The water phase model is a set of values correlating measured frequency values, impedance values and conductivity values to water content in a water and oil mixture.

[0075] In step 275 the composition as a function of height is determined using the conductivity and the fluid phase inversion point as input parameters in the multivariate analysis and a report is generated.

[0076] Figure 16 shows the raw impedance (Z_p) vs. frequency (F_p) data for a profile containing 0-66% water from right to left. At approximately 8.12 MHz, the water content is high enough (~25%) to induce fluid phase inversion from oil to water continuous phase. This is apparent from the drastic change in Z_p due to the increased conductivity of the test fluid in water continuous phase. An oil continuous phase model is applied to any data points to the right of the fluid phase inversion and a water model to the left. Additionally, a calibration is applied to the endpoint to determine the conductivity of the water, which in this case was 2.78 mS/cm.

[0077] Figure 17 shows the results of an analysis of the experiment data from an embodiment of a three-dimensional resonant sensor system illustrated the correlation between the actual and predicted values of oil in water and water in oil and the residual errors of prediction based on developed model. Part A of the chart plots the actual and predicted values of oil in water. Part B of the chart plots the actual and predicted values of water in oil. In part A, the data points were modeled separately from the data points in part B (water continuous phase). Parts C and D of the chart plot the residual error between the actual and predicted values of oil in water and water in oil respectively. Generally, the residual error was less than 0.5% when the actual percentage of oil is between 0% to 60%. The residual error was less than 0.04% when the actual percentage of oil is between 70% to 100%. At the fluid phase inversion the residual error increases up to 10% where prediction capability is difficult due to fluctuations in the composition of the test fluid in the dynamic test rig. The prediction capability of the sensor will improve at compositions >66% water with more training data.

[0078] Figure 18 illustrates the results obtained in a simulated desalter. The chart shows a profile developed by plotting the composition as a function of time. To simulate the sampling using a swing arm that is slowly rotated through the rag layer, a test rig was operated such that the composition of the test fluid was slowly modulated with time by adding small additions of water.

[0079] Figure 19 is an illustration of the expected level of reporting from the sensor data analysis system. The end user will be shown a plot that displays a representation of the composition as a function of height in the desalter, the level of fluid phase inversion, and the width of the rag layer. On the left are fluid phase indicators (black --- oil, gray --- oil continuous, cross hatched -- water continuous, white - water) that indicate the percent water/height curve. The height of the rag layer is the sum of the water continuous and oil continuous regions. The level of detail indicated will allow the operator of the desalter to optimize the feed rate of chemicals into the process, provide more detailed feedback on the performance of a fluid processing system, and highlight process upsets that may cause damage to downstream process infrastructure.

[0080] Illustrated in Figure 20 is a method 281 for measuring the level of a mixture of fluids in a vessel 113.

[0081] In step 283, the method 281 may detect signals (a set of signals) from a resonant sensor system 11 at a plurality of locations in a vessel. The signals are generated by a resonant transducer 12 immersed in the mixture of fluids. The resonant transducer 12 generates a set of transducer signals corresponding to changes in dielectric properties of the resonant transducer 12, and the signals are detected by an analyzer 15.

[0082] In step 285, the method 281 may convert the signals to a set of values of the complex impedance spectrum for the plurality of locations. The conversion is accomplished using multivariate data analysis.

[0083] In step 287, the method 281 may store the values of the complex impedance spectrum.

[0084] In step 289, the method 281 may determine if a sufficient number of locations have been measured.

[0085] In step 291, the method 281 may change the resonant transducer 12 being read (or the location of the resonant transducer 12) if an insufficient number of locations have been measured.

[0086] In step 293, the method 281 may determine the fluid phase inversion point if a sufficient number of locations has been measured. The fluid phase inversion point is determined from the values of the complex impedance spectrum by identifying a drastic change in the impedance values.

[0087] In step 295, the method 281 may assign a value for the interface level based on the fluid phase inversion point.

[0088] Figure 21 is a block diagram of non-limiting example of a processor system 810 that may be used to implement the apparatus and methods described herein. As shown in Figure 21, the processor system 810 includes a processor 812 that is coupled to an interconnection bus 814. The processor 812 may be any suitable processor, processing unit or microprocessor. Although not shown in Figure 21, the processor system 810 may be a multi-processor system and, thus, may include one or more additional processors that are identical or similar to the processor 812 and that are communicatively coupled to the interconnection bus 814.

[0089] The processor 812 of Figure 21 is coupled to a chipset 818, which includes a memory controller 820 and an input/output (I/O) controller 822. As is well known, a chipset typically provides I/O and memory management functions as well as a plurality of general purpose and/or special purpose registers, timers, etc. that are accessible or used by one or more processors coupled to the chipset 818. The memory controller 820 performs functions that enable the processor 812 (or processors if there are multiple processors) to access a system memory 824 and a mass storage memory 825.

[0090] The system memory 824 may include any desired type of volatile and/or non-volatile memory such as, for example, static random access memory (SRAM), dynamic random access memory (DRAM), flash memory, read-only memory (ROM), etc. The mass storage memory 825 may include any desired type of mass storage device including hard disk drives, optical drives, tape storage devices, etc.

[0091] The I/O controller 822 performs functions that enable the processor 812 to communicate with peripheral input/output (I/O) devices 826 and 828 and a network interface 830 via an I/O bus 832. The I/O devices 826 and 828 may be any desired type of I/O device such as, for example, a keyboard, a video display or monitor, a mouse, etc. The I/O devices 826 and 828 also may be The network interface 830 may be, for example, an Ethernet device, an asynchronous transfer mode (ATM) device, an 802.11 device, a DSL modem, a cable modem, a cellular modem, etc. that enables the processor system 810 to communicate with another processor system. Data from analyzer 15 may be communicated to the processor 812 through the I/O bus 832 using the appropriate bus connectors.

[0092] While the memory controller 820 and the I/O controller 822 are depicted in Figure 21 as separate blocks within the chipset 818, the functions performed by these blocks may be integrated within a single semiconductor circuit or may be implemented using two or more separate integrated circuits.

[0093] Certain embodiments contemplate methods, systems and computer program products on any machine-readable media to implement functionality described above. Certain embodiments may be implemented using an existing computer processor, or by a special purpose computer processor incorporated for this or another purpose or by a hardwired and/or firmware system, for example. Certain embodiments include computer-readable media for carrying or having computer-executable instructions or data structures stored thereon. Such computer-readable media may be any available media that may be accessed by a general purpose or special purpose computer or other machine with a processor. By way of example, such computer-readable media may comprise RAM, ROM, PROM, EPROM, EEPROM, Flash, CD-ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other

medium which can be used to carry or store desired program code in the form of computer-executable instructions or data structures and which can be accessed by a general purpose or special purpose computer or other machine with a processor. Combinations of the above are also included within the scope of computer-readable media. Computer-executable instructions comprise, for example, instructions and data which cause a general purpose computer, special purpose computer, or special purpose processing machines to perform a certain function or group of functions.

[0094] Generally, computer-executable instructions include routines, programs, objects, components, data structures, etc., that perform particular tasks or implement particular abstract data types. Computer-executable instructions, associated data structures, and program modules represent examples of program code for executing steps of certain methods and systems disclosed herein. The particular sequence of such executable instructions or associated data structures represent examples of corresponding acts for implementing the functions described in such steps.

[0095] Embodiments of the present disclosure may be practiced in a networked environment using logical connections to one or more remote computers having processors. Logical connections may include a local area network (LAN) and a wide area network (WAN) that are presented here by way of example and not limitation. Such networking environments are commonplace in office-wide or enterprise-wide computer networks, intranets and the Internet, and may use a wide variety of different communication protocols. Those skilled in the art will appreciate that such network-computing environments will typically encompass many types of computer system configurations, including personal computers, handheld devices, multi-processor systems, microprocessor-based or programmable consumer electronics, network PCs, minicomputers, mainframe computers, and the like. Embodiments of the disclosure may also be practiced in distributed computing environments where tasks are performed by local and remote processing devices that are linked (either by hardwired links, wireless links, or by a combination of hardwired or wireless links) through a communications network. In a distributed computing environment, program modules may be located in both local and remote memory storage devices.

[0096] Monitoring changes of the complex impedance of the circuit and applying chemometric analysis of the impedance spectra allows for the composition and continuous phase of oil-in-water and water-in-oil mixtures to be predicted with a standard error of 0.04% in 0-30% water and 0.26% in 30-100% water.

[0097] Multivariate analysis tools in combination with data-rich impedance spectra allow for elimination of interferences, and transducers designed for maximum penetration depth decreases the impact of fouling. As the penetration depth of the resonator is extended further into the bulk of the fluid, surface fouling becomes less significant.

[0098] The term "analyte" includes any desired measured environmental parameter.

[0099] The term "environmental parameters" is used to refer to measurable environmental variables within or surrounding a manufacturing or monitoring system. The measurable environmental variables comprise at least one of physical, chemical and biological properties and include, but are not limited to, measurement of temperature, pressure, material concentration, conductivity, dielectric property, number of dielectric, metallic, chemical, or biological particles in the proximity or in contact with the sensor, dose of ionizing radiation, and light intensity.

[0100] The term "fluids" includes gases, vapors, liquids, and solids.

[0101] The term "interference" includes any undesired environmental parameter that undesirably affects the accuracy and precision of measurements with the sensor. The term "interferent" refers to a fluid or an environmental parameter (that includes, but is not limited to temperature, pressure, light, etc.) that potentially may produce an interference response by the sensor.

[0102] The term "transducer" means a device that converts one form of energy to another.

[0103] The term "sensor" means a device that measures a physical quantity and converts it into a signal which can be read by an observer or by an instrument.

[0104] The term “multivariate data analysis” means a mathematical procedure that is used to analyze more than one variable from a sensor response and to provide the information about the type of at least one environmental parameter from the measured sensor spectral parameters and/or to quantitative information about the level of at least one environmental parameter from the measured sensor spectral parameters.

[0105] The term “resonance impedance” or “impedance” refers to measured sensor frequency response around the resonance of the sensor from which the sensor “spectral parameters” are extracted.

[0106] The term “spectral parameters” is used to refer to measurable variables of the sensor response. The sensor response is the impedance spectrum of the resonance sensor circuit of the resonant transducer 12. In addition to measuring the impedance spectrum in the form of Z-parameters, S-parameters, and other parameters, the impedance spectrum (both real and imaginary parts) may be analyzed simultaneously using various parameters for analysis, such as, the frequency of the maximum of the real part of the impedance (F_p), the magnitude of the real part of the impedance (Z_p), the resonant frequency of the imaginary part of the impedance (F_1), and the anti-resonant frequency of the imaginary part of the impedance (F_2), signal magnitude (Z_1) at the resonant frequency of the imaginary part of the impedance (F_1), signal magnitude (Z_2) at the anti-resonant frequency of the imaginary part of the impedance (F_2), and zero-reactance frequency (F_z , frequency at which the imaginary portion of impedance is zero). Other spectral parameters may be simultaneously measured using the entire impedance spectra, for example, quality factor of resonance, phase angle, and magnitude of impedance. Collectively, “spectral parameters” calculated from the impedance spectra, are called here “features” or “descriptors”. The appropriate selection of features is performed from all potential features that can be calculated from spectra. Multivariable spectral parameters are described in U.S. Patent Application, Serial No. 12/118,950 entitled “Methods and systems for calibration of RFID sensors”, which is incorporated herein by reference.

[0107] The terminology used herein is for the purpose of describing particular embodiments only and is not intended to be limiting of the invention. Where the

definition of terms departs from the commonly used meaning of the term, applicant intends to utilize the definitions provided herein, unless specifically indicated. The singular forms "a", "an" and "the" are intended to include the plural forms as well, unless the context clearly indicates otherwise. It will be understood that, although the terms first, second, etc. may be used to describe various elements, these elements should not be limited by these terms. These terms are only used to distinguish one element from another. The term "and/or" includes any, and all, combinations of one or more of the associated listed items. The phrases "coupled to" and "coupled with" contemplates direct or indirect coupling.

[0108] This written description uses examples to disclose the invention, including the best mode, and also to enable any person skilled in the art to practice the invention, including making and using any devices or systems and performing any incorporated methods. The patentable scope of the invention is defined by the claims, and may include other examples that occur to those skilled in the art. Such other examples are intended to be within the scope of the claims if they have structural elements that do not differ from the literal language of the claims, or if they include equivalent structural elements.

Claims

1. A sensor comprising:
an electrically resonant transducer comprised of a top winding and a bottom winding, said bottom winding coupled at opposite ends across a capacitor, wherein said top winding provides excitation and detection of the bottom winding, wherein mutual inductance of the top winding is used to sense the bottom winding, said mutual inductance used to measure values of real and imaginary parts of an impedance spectra of the bottom winding across said capacitor and said top winding, said impedance spectra determined from an electrical response of the bottom winding to the top winding of the electrically resonant transducer while said bottom winding is proximate to an emulsion and said measured values of real and imaginary parts of the impedance spectra of the bottom winding are each independently used to determine a composition of the emulsion.
2. The sensor of claim 1 further comprising a sampling cell, wherein the top winding of the electrically resonant transducer is disposed around an upper portion of the sampling cell; and the bottom winding of the electrically resonant transducer is disposed around a lower portion of the sampling cell.
3. The sensor of claim 2, further comprising a radio frequency absorber disposed around the top winding and the bottom winding.
4. The sensor of claim 3 further comprising a metal shield disposed around the radio frequency absorber.
5. The sensor of claim 4 further comprising a cover disposed around the metal shield.
6. The sensor of claim 2 further comprising an absorber of electromagnetic radiation disposed around the top winding and the bottom winding where the absorber absorbs electromagnetic radiation in kilohertz, megahertz, gigahertz, and terahertz frequency ranges depending on the operation frequency of the electrically resonant transducer and a source of interferences.

7. The sensor of claim 2 further comprising an absorber of electromagnetic radiation disposed around the top winding and the bottom winding where the absorber is a combination of individual layers for particular frequency ranges.
8. The sensor of claim 1, wherein the measured values for the real and the imaginary parts of the impedance spectra are each independently used to simultaneously determine a concentration of a first and a second component of the emulsion.
9. The sensor of claim 8 wherein the electrically resonant transducer measures at least three data points of the real and the imaginary parts of the impedance spectra of the electrically resonant transducer.
10. The sensor of claim 8 wherein the electrically resonant transducer comprises a sensitive portion that detects changes in capacitance and resistance of the electrically resonant transducer.
11. The sensor of claim 8 wherein the electrically resonant transducer comprises a sensitive portion that detects changes in capacitance, resistance, inductance of the electrically resonant transducer.
12. The sensor of claim 8 where the electrically resonant transducer probes an environment over a sample depth perpendicular to the electrically resonant transducer of between 0.1 mm to 1,000 mm.
13. The sensor of claim 1, wherein the electrically resonant transducer measures a set of LCR resonant circuit parameters, said set of LCR resonant circuit parameters comprise at least one of an impedance spectrum, a real part of the impedance spectrum, an imaginary part of the impedance spectrum, both a real part and an imaginary part of the impedance spectrum, a frequency associated with a maximum of the real part of a complex impedance, a magnitude of the real part of the complex impedance, a resonant frequency, a magnitude of imaginary part of the complex

impedance, and an anti-resonant frequency and a magnitude of the imaginary part of the complex impedance.