

Description

The present invention relates to a method for controlling two or more video display devices by a computer and, also to an adapter circuit.

The personal computer industry has three basic graphics display standards. The "monochrome" display standard allows crisp text on a monochrome display using a 720 X 350 format, or 720 dots or pixels in each horizontal line and 350 horizontal lines on the display. The "color graphics adapter" (CGA) standard supports 16 different colors on a display using a 640 X 200 format. The 640 X 200 format is adequate for graphics and supports text modes, but the text is so coarse that it is not very useful. A third standard is known as the "enhanced graphics adapter" (EGA). The EGA has monochrome modes (720 X 350 text and 640 X 350 graphics) and color modes (640 X 350 text and graphics as well as 640 X 200 text and graphics). The multiple modes allow the EGA to drive the original monochrome monitor, the original color monitor, and the new enhanced color display having both 640 X 200 and 640 X 350 modes.

A dual scan monitor (DSM) has been developed which has a low scan mode which is the same as the industry standard color monitor and a high scan mode which is unique to a particular application. The low scan mode has a horizontal scan frequency of 15.7 KHz and a 60 Hz frame rate. The high scan mode has a horizontal scan rate of 18.5 KHz and a 50 Hz frame rate.

The horizontal and vertical scan rates in the 640 X 200 resolution mode of the enhanced color display, the standard color monitor, and the dual scan monitor are the same. As a result, a display controller can drive an enhanced color display and a dual scan monitor or a standard color monitor and a dual scan monitor in the 640 X 200 resolution mode at the same time.

However, the horizontal and vertical scan rates in the 640 X 350 resolution mode of the enhanced color display and the dual scan monitor are not the same. As a result, a single display controller cannot drive both an enhanced color display and a dual scan monitor in the 640 X 350 resolution mode at the same time.

EP-A-0 195 163 discloses a video converter device converting video data from low resolution format to another format of a display device that is attached to the system. Video control parameters are permanently written into a ROM device. Only one display device is attached to the system at any given time.

IBM Technical Disclosure Bulletin, vol. 30, no. 1, June 1987, pages 440-441 discloses a "self-initializing CRT adaptor for multiple CRT types". This adaptor also allows only one display device to be connected to a controller at a time.

The present invention enables a computer and a single display device, or CRT, controller to drive and control two or more display devices, each of which requires different control parameters. The control parameters for the CRT controller are typically provided from the computer according to software instructions. One embodiment of the present invention utilizes a memory device in conjunction with the CRT controller for storing control parameters which are used to program the CRT controller. Switches are used to indicate to the CRT controller the types of display devices connected to the computer. A control device, utilizing input from the switches, determines the monitor type which is being driven by the CRT controller at any particular time. A substitution device receives input from the control device and the storage device and, depending upon the type of monitor being driven, modifies the control parameters as they are read from the storage device or received from the computer and written to the CRT controller. A control signal generated from the computer keyboard triggers the control device to switch from one monitor type to another and, in response to that control signal, the CRT controller is reprogrammed with the appropriate control parameters as read from the storage device and modified by the substitution device.

FIG. 1 is a block diagram showing a computer, an adapter circuit according to the present invention, a CRT controller, and two display devices, each of which may be driven by the CRT controller.

FIG. 2 is a schematic diagram of an adapter circuit according to the present invention.

FIG. 1 shows a block diagram of a system utilizing an adapter circuit 10 according to the present invention. The adapter circuit 10 is interposed between the processor 11 and the CRT controller 12 and contains buffers, a memory device, and programmable logic devices. CRT control data is written by the processor 11 into the adapter circuit 10 which, in turn, either transmits those data directly to the CRT controller 12 or first modifies the data before transmitting them to the CRT controller 12. The processor 11 also sends display data through the adapter circuit 10 to the CRT controller 12 for display on the video display devices 13 and 14. The processor 11 may read data which is stored in the CRT controller 12 video data memory and that is accomplished through the adapter circuit 10.

FIG. 2 is a schematic diagram showing an adapter circuit according to the present invention. The data bus 21 connects the processor with the adapter circuit and provides a path for transfer of data between the processor and the adapter circuit. It is a bidirectional bus. Buffer U53 interconnects the data bus 21 with a bidirectional adapter board bus 22 and, when enabled, allows data to pass from the board bus 22 to the data bus

21. In this way, data can be read from the CRT controller, through the adapter circuit, to the processor. Buffer U54 interconnects the data bus 21 with a memory device U52 and a substitution device U51 and, when enabled, allows data to pass from the processor to the memory device U52 and the substitution device U51. As will become more clear below, the buffers U53 and U54 each allow uni-directional passage of data to the bi-directional data bus 21 and adapter board bus 22.

Also connected to the data bus 21 is an index register U55. The index register U55 is used in conjunction with the memory device U52 and with a control device U47. The use of the index register U55 will be explained in greater detail later.

Appendix B sets forth parts information for different components illustrated in FIG. 2. Appendix B is incorporated by reference as if set forth in full.

Switches SW2 are manually set switches which are used to indicate to the adapter circuit the types of monitors connected to the CRT controller. Four different monitor types are normally possible and each monitor type may be uniquely identified using two binary signals. Accordingly, a pair of switches and a pair of lines may be used to identify a single monitor type. In the embodiment shown in FIG. 2, two different monitors are connected to the CRT controller and four switches in SW2 and four independent lines are used to indicate the two monitor types. A "pull-up" circuit 30 consisting of resistors is used in conjunction with the switches to provide "high" and "low" signals on the individual lines in response to the open or closed status of the individual switches.

A control mode register U27 accepts inputs to select which monitor(s) enable/disable and provides four output signals which are utilized in the present invention. Two of the signals are used to enable/disable the two monitors connected to the CRT controller. A third signal is a "tie breaker" if there are two monitors attached to the controller that can display in the programmed mode but not at the same time. The fourth signal, "RE-STORE", is used whenever the CRT controller is to be switched from one monitor to another. That operation will be explained in more detail below.

Device U28 accepts input from the switches SW2 and from the control mode register U27 and generates signals which will, in part, determine the type of modifications to the video control parameters which might be necessary. For example, the device U28 generates signals which enable and disable the two monitors and it generates signals specifying whether any modification is needed for a color or monochrome mode. This will also be explained in more detail below.

Memory device U52 is a random access memory (RAM) which may be written to or read from and is used to store the display control parameters for later modification and transfer to the CRT controller. The memory device U52 receives its data input from the computer via the data bus 21 and the buffer U54. When the computer processor provides video control parameters for possible modification and transfer to the CRT controller, those parameters are simultaneously stored in the memory device U52 and written to a substitution device U51. This writing to the memory device will occur when the "write enable" signal is active to the memory device U52. As will be seen below, the "write enable" signal will be inactive when the CRT controller is being switched from one monitor to another. Otherwise, whenever the application program being executed by the processor calls for new display control parameters, the "write enable" signal will be active and those parameters will be written to the memory device U52 through the data bus 21 and the buffer U54.

The substitution device U51 receives input from the processor by way of the buffer U54. The substitution device U51 is a programmed logic device which contains instructions for modifying the display control parameters so that the desired monitor may be driven in the desired mode. The device U51 is connected to the buffer U54 and the memory device U52 such that its input may come from the buffer U54 or the memory device U52. Under conditions which will be more particularly specified below, the input to the substitution device U51 will be read from the memory device U52 and will not be transmitted from the processor through the buffer U54.

The index register U55 is also connected to the data bus 21 and is used in conjunction with the memory device U52 to address individual values stored in the memory device U52. The index register U55 also supplies address information to a control device U47 for use in generating modification signals.

The control device U47 accepts input from the device U28 and the index register U55, as well as other signals. Its output is used to control reading from and writing to the memory device U52 and to provide modification control signals to the substitution device U54. An "enable" signal for controlling the buffer U54 is also generated by the control device U47. The control device U47 is a programmed logic device.

The CRT controller typically has a number of programmable registers. These registers determine things such as the size of the character cell, the total number of horizontal lines, the horizontal blank time, the horizontal retrace time, the vertical blank time, the vertical retrace time, the size of the cursor and the location of the cursor.

The values programmed in these registers and the clock frequency selected determine the actual timing of the signals that drive the displays or monitors. Using a monitor that has different timing requirements than

that expected by the software requires changing the drivers in the software or having the controller change the values as needed for the different monitor.

When the computer is initially powered up, the CRT controller is programmed according to the type of monitor expected by the software based on the clock frequency selected and the I/O address decode selected.

5 When the controller is programmed, the values in the software for the CRT controller are stored in the memory device U52 and the CRT controller is programmed.

The switches SW2 are selectively opened and closed to indicate to the adapter circuit the monitor types connected to the CRT controller. The device U28 receives input from the switches SW2 as well as clock select signals and generates signals indicating whether modification of the display control parameters will be necessary. Those signals, as well as others, will provide inputs for use by the control device U47 as will be explained below.

10

The control mode register U27 receives input regarding the monitor(s) to be selected. Device U28 uses the outputs from U27 and generates signals which enable/disable each of the individual monitors. The control mode register U27 also receives a control signal as generated from the computer keyboard and, in response to the signal, activates the RESTORE bit at the output of the control mode register U27. The control device

15 U47 receives as input the RESTORE bit signal from the control mode register U27. In addition, the device U47 monitors the outputs of the device U28, the direction control line, whether a 40-column or an 80-column mode is being programmed, the least significant address line and lines indicating CRT controller reads and writes. The control device U47 uses this information for a number of purposes. First, the control device U47 provides a write enable signal to the buffer U54 to turn on the buffer to enable data from the CPU to pass through the buffer. Secondly, U47 generates control signals to the memory device U52 to allow the writing of data into the memory device or the reading of data from the memory device. Third, the control device U47 provides control signals to the substitution device U51. These control signals are used by the substitution device U51 to modify the display control data which it receives from the processor or the memory device U52 and which it then passes to the CRT controller.

20

25

Application software which may be executed by a computer typically contains display control data which is used to program a CRT controller to appropriately control the monitor. Although these values may be changed during the course of the execution of the program, for purposes of explaining the operation of the present invention, it will be assumed that a program is run in which these control parameters are specified initially in the program and remain the same throughout.

30

When the application program is initiated in the processor, the video control parameters are output to the CRT controller through the adapter circuit. The "write enable" signal from the control device U47 enables the buffer U54 to pass the display control parameters from the processor into the adapter circuit. In addition, as the appropriate memory addresses appear in the index register U55, a "write enable" signal is applied to the memory device U52 to enable the data being passed to be written into the memory device U52. As the control parameter data is passed through the buffer U54 and stored in the memory device U52, it also passes to the substitution device U51. The switches SW2 having been set to indicate the monitor types attached to the CRT controller and device U28 having specified whether a parameter substitution is for a color mode or a monochrome mode, the control device U47 generates control signals CTRLA, CTRLB, CTRLC, and CTRLD as inputs to the substitution device U51. The device U51 modifies the parameter data received from the buffer U54 in accordance with the control signals received from the control device U47. Attached hereto as Appendix A is a table showing the various combinations of the control signals A through D, the values typically written by the application software, and the resulting modified value which is transmitted from the substitution device U51 to the CRT controller. Appendix A is incorporated by reference as if fully set forth.

35

40

The index register U55 is used to address the individual storage locations in the memory device U52. The transfer of the control parameters, and other data, from the processor to the adapter circuit is a two-step process. First, a register location is identified and that information is stored in the index register U55. Next, the data to be stored in the register is passed from the processor to the adapter circuit and is transmitted through the buffer U54. Continuing, a new register is identified and the data for that register is passed. This process continues until all the necessary data have been transferred.

45

50

As the control parameters are being transferred from the processor to the adapter circuit, the register identifications are being monitored by the control device U47. In response to those identifications and certain other inputs, the control device initiates the CTRLA through CTRLD signals to the substitution device U51. Those control signals are then used, as needed, to modify the data being transmitted from the processor through the data bus, through the buffer U54 to the substitution device U51. The data modification which occurs in the substitution device U51 is specified in Appendix A.

55

While the control parameter data is being processed by the adapter circuit, it is also being stored in the memory device U52. The index register signals are used to store the parameter signals in the proper locations

in the memory device U52. After initial programming of the CRT controller and during operation of the application program, should the computer operator desire to transfer visual output to a second, different monitor, he will generate a control signal at the keyboard which will activate the RESTORE signal at the control mode register U27. This RESTORE signal is input to the control device U47 and a RAM "output enable" signal is generated by the control device U47 and applied to the memory device U52. At the same time, the "write enable" signal supplied from the control device U47 to the buffer U54 is deactivated to block the passage of data through the buffer U54.

The control device U47 then causes the parameter data stored in the memory device U52 to be output to the substitution device U51, one storage location at a time. The index register U55 is sequenced through the various registers which must be accessed and the control device U47 operates as though the application program were being originally initiated. That is, it generates the CTRLA through CTRLD signals and inputs them to the substitution device U51 as the device U51 is receiving the parameter data from the memory device U52. Because a different monitor is being accessed and it may need different control parameters, the CTRLA through CTRLD signals are likely to differ from those originally generated. Likewise, the modifications performed in the substitution device U51 will likely result in different control parameters being transferred to the CRT controller.

The computer operator can switch between the various monitors by generating the appropriate control signals at the keyboard. Each time this occurs, the RESTORE bit signal will be activated at the control mode register U27 and the reprogramming of the CRT controller will be performed by the sequential readout of control data from the memory device U52 as modified by the substitution device U51.

While the present invention has been described in terms of one specific embodiment, it will be understood by those of skill in the art that the invention may assume numerous different embodiments.

APPENDIX A

5	DISPLAY PARAMETERS	INDEX REGISTER	CTRL				STD. VALUE	SUBST. VALUE
			A	B	C	D		
10	COLOR; 40 COL.	R00	0	0	0	1	2DH	37H
	COLOR; 40 COL.	R03	0	0	1	0	2DH	13H
	COLOR; 40 COL.	R04	0	0	1	1	28H	30H
	COLOR; 40 COL.	R05	0	1	0	0	6DH	54H*
15	COLOR; 40 COL.	R06	0	1	0	1	6CH	70H
	COLOR; 80 COL.	R00	1	0	0	1	5BH	70H
	COLOR; 80 COL.	R03	1	0	1	0	37H	03H
20	COLOR; 80 COL.	R04	1	0	1	1	51H	60H
	COLOR; 80 COL.	R05	1	1	0	0	5BH	08H
	COLOR; 80 COL.	R06	1	1	0	1	6CH	70H
	MONO	R00	0	0	0	1	60H	70H
25	MONO	R03	0	0	1	0	3AH, 1AH	3EH**
	MONO	R04	0	0	1	1	51H, 50H	5CH
	MONO	R05	0	1	0	0	60H, E0H	64H***
30								
35	* (Bit 7 unchanged) ** (Bits 7-5 unchanged) *** (Bit 7 unchanged)							
40								

Claims

- 45
1. A method for controlling two or more video display devices (13, 14) using an adapter circuit (10) interposed between a processor and a single display controller (12), wherein display control data is written by the processor into the adapter circuit which, in turn, either transmits those data directly to the display controller or first modifies the data before transmitting them to the display controller, comprising the steps of:
- 50
- transferring the display control data to a memory device (U52) and to a substitution means (U47, U51) of the adapter circuit;
 - generating type signals (INTMON0, INTMON1, EXTMON0, EXTMON2) indicative of the types of display devices (13, 14) to be controlled;
 - 55 - generating first modification signals as determined by the type of a first display device (13) to be controlled and indicative of possibly necessary modifications of the display control data;
 - modifying the display control data in the substitution means (U47, U51) in response to the first modification signals;



APPENDIX A

	<u>DISPLAY PARAMETERS</u>	<u>INDEX REGISTER</u>	<u>CTRL</u>				<u>STD. VALUE</u>	<u>SUBST. VALUE</u>
			A	B	C	D		
5								
10	COLOR; 40 COL.	R00	0	0	0	1	2DH	37H
	COLOR; 40 COL.	R03	0	0	1	0	2DH	13H
	COLOR; 40 COL.	R04	0	0	1	1	28H	30H
	COLOR; 40 COL.	R05	0	1	0	0	6DH	54H*
15	COLOR; 40 COL.	R06	0	1	0	1	6CH	70H
	COLOR; 80 COL.	R00	1	0	0	1	5BH	70H
	COLOR; 80 COL.	R03	1	0	1	0	37H	03H
20	COLOR; 80 COL.	R04	1	0	1	1	51H	60H
	COLOR; 80 COL.	R05	1	1	0	0	5BH	08H
	COLOR; 80 COL.	R06	1	1	0	1	6CH	70H
	MONO	R00	0	0	0	1	60H	70H
25	MONO	R03	0	0	1	0	3AH, 1AH	3EH**
	MONO	R04	0	0	1	1	51H, 50H	5CH
	MONO	R05	0	1	0	0	60H, E0H	64H***
30								

* (Bit 7 unchanged)

** (Bits 7-5 unchanged)

*** (Bit 7 unchanged)

Claims

1. A method for controlling two or more video display devices (13, 14) using an adapter circuit (10) interposed between a processor and a single display controller (12), wherein display control data is written by the processor into the adapter circuit which, in turn, either transmits those data directly to the display controller or first modifies the data before transmitting them to the display controller, comprising the steps of:
 - transferring the display control data to a memory device (U52) and to a substitution means (U47, U51) of the adapter circuit;
 - generating type signals (INTMON0, INTMON1, EXTMON0, EXTMON2) indicative of the types of display devices (13, 14) to be controlled;
 - generating first modification signals as determined by the type of a first display device (13) to be controlled and indicative of possibly necessary modifications of the display control data;
 - modifying the display control data in the substitution means (U47, U51) in response to the first modification signals;



- programming the display controller (12) using the modified display control data as modified in response to the first modification signals (output of U28);
 - generating a user control signal (keyboard trigger);
 - 5 - generating a switch signal (RESTORE) in response to said user control signal to change control from the first display device (13) to be controlled to a second display device (14) to be controlled by said display controller;
 - reading the display control data from the memory device (U52) into the substitution means (U47, U51);
 - 10 - generating second modification signals as determined by the type of the second display device (14) to be controlled;
 - modifying the display control data in the substitution means (U47, U51) in response to the second modification signals; and
 - re-programming the controller (12) using the modified display control data as modified in response to the second modification signals.
- 15 2. An adapter circuit (10) interposed between a processor (11) and a single display controller (12) enabling the controller to drive and control two or more video display devices (13, 14), each of which requires different control parameters, comprising:
- 20 - a memory (U52) for storing the display control parameters transmitted from said processor for said display controller (12);
 - means (SW2) for indicating types of display devices to be controlled by the display controller (12);
 - means for providing a user control signal;
 - means (U27) responsive to said user control signal for selecting a display device to be controlled and generating a change signal (RESTORE);
 - 25 - a control device utilizing input from said indicating means for producing display device data depending upon the selected type of display;
 - a substitution means (U47, U51) responsive to the change signal (RESTORE) to receive said display device data and to read said display control parameters from the memory (U52) and operative to modify the display control parameters in accordance with the display device data and operative to
 - 30 program the display controller (12) to control the selected display device.
- 35 3. The adapter circuit according to claim 2, wherein said substitution means (U47, U51) comprises a first programmable device (U51) having inputs coupled to said memory (U52) to receive said display control parameters and having outputs for producing modified display control parameters for programming the display controller (12).
- 40 4. The adapter circuit according to claim 2 or 3, wherein the means (SW2) for indicating types of display devices comprises switches (SW2) that can be selectively opened and closed to generate binary signals.
- 45 5. The adapter circuit according to any one of claims 2 to 4, wherein the means (U27) for selecting a display device and for generating a change signal also generates a monitor signal, the adapter circuit further comprising a second programmable device (U28) having inputs for receiving said binary signals and said monitor signal, said second programmable device (U28) generating a modification signal for input to said substitution means (U47, U51).
- 50 6. The adapter circuit according to any one of claims 2 to 5, wherein the substitution means (U47, U51) further comprises a third programmable device (U47) having inputs for receiving the modification signal and the change signal (RESTORE), said third programmable device (U47) having outputs for producing control signals (CTRLA - CTRLD) for input to the first programmable device (U51).
- 55 7. The adapter circuit according to any of claims 2 to 6, further comprising a buffer (U54) having inputs for receiving data from a data bus (DATA) and having outputs coupled to said memory (U52) and to said first programmable device (U51), said buffer (U54) controlling input of display control parameters from the data bus (DATA) to the memory (U52) and to the substitution means (U47, U51).
8. The adapter circuit according to any of claims 2 to 7, further comprising an index register (U55) producing output signals received by said memory (U52) for controlling the storage of said display control parameters in selected locations in said memory (U52).



Patentansprüche

1. Verfahren zum Steuern von zwei oder mehr Videoanzeigevorrichtungen (13, 14) unter Verwendung einer Adapterschaltung (10), die zwischen einem Prozessor und einem einzelnen Anzeigecontroller (12) angeordnet ist, wobei Anzeigesteuerdaten durch den Prozessor in die Adapterschaltung geschrieben werden, die ihrerseits entweder diese Daten direkt zu dem Anzeigecontroller überträgt oder zuerst die Daten modifiziert, bevor sie sie zu dem Anzeigecontroller überträgt, das die Schritte aufweist:
 - Übertragen der Anzeigesteuerdaten zu einer Speichervorrichtung (U52) und zu einer Substitutionseinrichtung (U47, U51) der Adapterschaltung;
 - Erzeugen von Typsignalen (INTMON0, INTMON1, EXTMON0, EXTMON2), die die Typen der Anzeigevorrichtung (13, 14) anzeigen, die gesteuert werden sollen;
 - Erzeugen von ersten Modifikationssignalen wie durch den Typ einer ersten Anzeigevorrichtung (13) bestimmt ist, die gesteuert werden soll, und die mögliche notwendige Modifikationen der Anzeigesteuerdaten anzeigen;
 - Modifizieren der Anzeigesteuerdaten in der Substitutionseinrichtung (U47, U51) in Antwort auf die ersten Modifikationssignale;
 - Programmieren des Anzeigecontrollers (12) unter Verwendung der modifizierten Anzeigesteuerdaten, wie sie in Antwort auf die ersten Modifikationssignale modifiziert sind (Ausgabe von U28);
 - Erzeugen eines Benutzersteuersignales (Tastaturtrigger);
 - Erzeugen eines Umschaltsignals (RESTORE) in Antwort auf das Benutzersteuersignal, um die Steuerung von der ersten Anzeigevorrichtung (13), die gesteuert werden soll, zu einer zweiten Anzeigevorrichtung (14), die gesteuert werden soll, durch den Anzeigecontroller zu ändern;
 - Lesen der Anzeigesteuerdaten von der Speichervorrichtung (U52) in die Substitutionsvorrichtung (U47, U51);
 - Erzeugen von zweiten Modifikationssignalen wie durch den Typ der zweiten Anzeigevorrichtung (14) bestimmt, die gesteuert werden soll;
 - Modifizieren der Anzeigesteuerdaten in der Substitutionseinrichtung (U47, U51) in Antwort auf die zweiten Modifikationssignale; und
 - Neuprogrammieren des Controllers (12) unter Verwendung der modifizierten Anzeigesteuerdaten, wie sie in Antwort auf die zweiten Modifikationssignale modifiziert sind.
2. Adapterschaltung (10), die zwischen einem Prozessor (11) und einem einzelnen Anzeigecontroller (12) angeordnet ist, die dem Controller ermöglicht, zwei oder mehr Videoanzeigevorrichtungen (13, 14) anzusteuern und zu steuern, wobei jede unterschiedliche Steuerparameter erfordert, die aufweist:
 - einen Speicher (U52) zum Speichern der Anzeigesteuerparameter, die von dem Prozessor für den Anzeigecontroller (12) übertragen worden sind;
 - eine Einrichtung (SW2) zum Anzeigen von Typen der Anzeigevorrichtung, die durch den Anzeigecontroller (12) gesteuert werden sollen;
 - eine Einrichtung zum Bereitstellen eines Benutzersteuersignals;
 - eine Einrichtung (U27), die auf das Benutzersteuersignal zum Auswählen einer Anzeigevorrichtung, die gesteuert werden soll, reagiert und ein Änderungssignal (RESTORE) erzeugt;
 - eine Steuervorrichtung, die die Eingabe von der Anzeigeeinrichtung zum Erzeugen der Anzeigevorrichtungsdaten abhängig von dem ausgewählten Typ der Anzeige verwendet;
 - eine Substitutionseinrichtung (U47, U51), die auf das Änderungssignal (RESTORE) reagiert, um die Anzeigevorrichtungsdaten zu empfangen und die Anzeigesteuerparameter von dem Speicher (U52) zu lesen, und die arbeitet, um die Anzeigesteuerparameter in Übereinstimmung mit den Anzeigevorrichtungsdaten zu modifizieren, und die arbeitet, um den Anzeigecontroller (12) so zu programmieren, daß er die ausgewählte Anzeigevorrichtung steuert.
3. Adapterschaltung gemäß Anspruch 2, wobei die Substitutionseinrichtung (U47, U51) eine erste programmierbare Vorrichtung (U51) aufweist, die Eingänge hat, die mit dem Speicher (U52) gekoppelt sind, um die Anzeigesteuerparameter zu empfangen, und die Ausgänge hat, um modifizierte Anzeigesteuerparameter zum Programmieren des Anzeigecontrollers (12) zu erzeugen.
4. Adapterschaltung gemäß Anspruch 2 oder 3, wobei die Einrichtungen (SW2) zum Anzeigen der Typen der Anzeigevorrichtungen Schalter (SW2) aufweist, die selektiv geöffnet und geschlossen werden können, um binäre Signale zu erzeugen.



5. Adapterschaltung gemäß einem der Ansprüche 2 bis 4, wobei die Einrichtung (U27) zum Auswählen einer Anzeigevorrichtung und zum Erzeugen eines Änderungssignales auch ein Überwachungssignal erzeugt, wobei die Adapterschaltung weiter eine zweite programmierbare Vorrichtung (U28) mit Eingängen zum Empfangen der binären Signale und des Überwachungssignales aufweist, wobei die zweite programmierbare Vorrichtung (U28) ein Modifikationssignal zur Eingabe zu der Substitutionseinrichtung (U47, U51) erzeugt.
6. Adapterschaltung gemäß einem der Ansprüche 2 bis 5, wobei die Substitutionseinrichtung (U47, U51) weiter eine dritte programmierbare Vorrichtung (U47) mit Eingängen zum Empfangen des Modifikationssignales und des Änderungssignales (RESTORE) aufweist, wobei die dritte programmierbare Vorrichtung (U47) Ausgänge zum Erzeugen von Steuersignalen (CTRLA-CTRLD) zur Eingabe zu der ersten programmierbaren Vorrichtung (U51) aufweist.
7. Adapterschaltung gemäß einem der Ansprüche 3 bis 6, die weiter einen Puffer (U54) aufweist, der Eingänge zum Empfangen von Daten von einem Datenbus (DATA) und Ausgänge hat, die mit dem Speicher (U52) und der ersten programmierbaren Vorrichtung (U51) gekoppelt sind, wobei der Puffer (U54) die Eingabe der Anzeigesteuerparameter von dem Datenbus (DATA) zu dem Speicher (U52) und zu der Substitutionseinrichtung (U47, U51) steuert.
8. Adapterschaltung gemäß einem der Ansprüche 2 bis 7, die weiter ein Indexregister (U55) aufweist, das Ausgangssignale erzeugt, die durch die Speichereinrichtung (U52) zum Steuern des Speicherns der Anzeigesteuerparameter in ausgewählten Stellen in dem Speicher (U52) empfangen werden.

Revendications

1. Procédé pour la commande de deux ou plus de deux dispositifs à écran cathodique ou affichage vidéo (13, 14) ayant recours à un circuit adaptateur (10) intercalé entre un processeur et une unité simple de commande du visuel (12), dans laquelle les données de commande d'affichage sont écrites par le processeur dans le circuit adaptateur qui, à son tour, transmet ces données directement à l'unité de commande du visuel ou modifie d'abord les données avant de les transmettre à l'unité de commande du visuel, comprenant les étapes consistant à :
 - transférer les données de commande d'affichage à un dispositif mémoire (U52) et à des moyens de substitution (U47, U51) du circuit adaptateur ;
 - produire des signaux de type (INTMON0, INTMON1, EXTMON0, EXTMON2) indicatif des types de dispositifs d'affichage (13, 14) à commander ;
 - produire des premiers signaux de modification comme cela est déterminé par le type d'un premier dispositif d'affichage (13) à commander et indicatif de modifications éventuellement nécessaires des données de commande du visuel ;
 - modifier les données de commande de visuel dans les moyens de substitution (U47, U51) en réponse aux premiers signaux de modification ;
 - programmer l'unité de commande du visuel (12) en utilisant les données de commande d'affichage telles que modifiées en réponse aux premiers signaux de modification (signal de sortie de U28) ;
 - produire un signal de commande utilisateur (actionnement clavier) ;
 - produire un signal de commutation (RESTORE) en réponse au signal de commande de l'utilisateur pour modifier la commande provenant du premier dispositif d'affichage (13) à commander vers un second dispositif d'affichage (14) à commander par l'unité de commande du visuel ;
 - emmagasiner les données de commande du visuel provenant du dispositif mémoire (U52) dans les moyens de substitution (U47, U51) ;
 - produire des seconds signaux de modification tels que déterminés par le type du second dispositif d'affichage (14) à commander ;
 - modifier les données de commande d'affichage dans les moyens de substitution (U47, U51) en réponse aux seconds signaux de modification ; et
 - reprogrammer l'unité de commande (12) en utilisant les données de commande d'affichage modifiées telles qu'elles sont modifiées en réponse aux seconds signaux de modification.
2. Circuit adaptateur (10) intercalé entre un processeur (11) et une unité simple de commande de visuel (12) permettant à l'unité de commande d'entraîner et de commander deux ou plus de deux dispositifs d'affi-



chage vidéo dont chacun nécessite des paramètres de commande différents, comprenant :

- une mémoire (U52) pour stocker les paramètres de commande d'affichage transmis par le processeur pour l'unité de commande de visuel (12) ;
- des moyens (SW2) pour indiquer les types de dispositifs d'affichage à commander par l'unité de commande de visuel (12) ;
- des moyens pour fournir un signal de commande utilisateur ;
- des moyens (U27) sensibles au signal de commande utilisateur pour choisir un dispositif d'affichage à commander et produire un signal de modification (RESTORE) ;
- un dispositif de commande utilisant le signal d'entrée provenant des moyens indicateurs pour produire des données de dispositif d'affichage en fonction du type choisi d'affichage ;
- des moyens de substitution (U47, U51) sensibles au signal de modification (RESTORE) pour recevoir les données du dispositif d'affichage et pour lire les paramètres de commande de visuel provenant de la mémoire (U52) et opérant pour modifier les paramètres de commande d'affichage en fonction des données du dispositif d'affichage et opérant pour programmer l'unité de commande de visuel (12) pour commander le dispositif d'affichage sélectionné.

3. Circuit adaptateur selon la revendication 2, dans lequel les moyens de substitution (U47, U51) comprennent un premier dispositif programmable (U51) comportant des entrées couplées à la mémoire (U52) pour recevoir les paramètres de commande de visuel et comportant des sorties pour produire les paramètres de commande de visuel modifiés pour programmer l'unité de commande du visuel (12).

4. Circuit adaptateur selon la revendication 2 ou 3, dans lequel les moyens (SW2) pour indiquer les types de dispositifs d'affichage comprennent des commutateurs (SW2) pouvant être ouverts et fermés sélectivement pour produire des signaux binaires.

5. Circuit adaptateur selon l'une quelconque des revendications 2 à 4, dans lequel les moyens (U27) pour sélectionner un dispositif d'affichage et pour produire un signal de modification produisent également un signal de contrôle, le circuit adaptateur comprend de plus un second dispositif programmable (U28) comportant des entrées pour recevoir les signaux binaires et le signal de contrôle, le second dispositif programmable (U28) produisant un signal de modification pour l'entrée dans les moyens de substitution (U47, U51).

6. Circuit adaptateur selon l'une quelconque des revendications 2 à 5, dans lequel les moyens de substitution (U47, U51) comprennent de plus un troisième dispositif programmable (U47) comportant des entrées pour recevoir le signal de modification et le signal de changement (RESTORE), ce troisième dispositif programmable (U47) comportant des sorties pour produire des signaux de commande (CTRLA-CTRLD) pour l'entrée au premier dispositif programmable (U51).

7. Circuit adaptateur selon l'une quelconque des revendications 2 à 6, comprenant de plus un tampon (U54) comportant des entrées pour recevoir les données provenant d'un bus de données (DATA) et comportant des sorties couplées à la mémoire (U52) et au premier dispositif programmable (U51), le tampon (U54) commandant l'entrée des paramètres de commande d'affichage provenant du bus de données (DATA) vers la mémoire (U52) et vers les moyens de substitution (U47, U51).

8. Circuit adaptateur selon l'une quelconque des revendications 2 à 7, comprenant de plus un registre d'index (U55) produisant des signaux de sortie reçus par la mémoire (U52) pour commander le stockage des paramètres de commande de visuel dans des emplacements sélectionnés de la mémoire (U52).