

☒ Description : paged to paged
☒ Claim(s) : paged to paged
☒ Drawing(s) : paged to paged
☒ Abstract : paged to paged

- 1 -

RADIO COMMUNICATION DEVICES

The present invention relates to radio communication
 devices which have simple conversation with others by
 5 radio.

So-called remote control devices which control the
 operation of electronic devices such as television sets or
 video tape recorders, using an infrared control signal, are
 sold as commodities. Infrared signals are used not only to
 10 control the operation of the electronic devices, but also
 to send and/or receive information composed of character
 data and/or numerical data between two electronic devices.

In order to send and/or receive information such as
 character data and numerical data using an infrared radio
 15 signal, the information is required to be set by the
 operation of keys of a device on the side of the
 transmission and a circuit which decodes all the characters
 and numerical data received from the other party must be
 provided on the side of the transmission. Thus, the
 20 structure of the device of the transmission side is
 complicated undesirably. When image information different
 from the character and numerical data is sent and/or
 received, a more complicated structure is required.

It is therefore an object of the present invention to
 25 provide a radio communication device which has a very
 simple structure and requires only a very simple operation
 to send and/or receive information.

It is another object of the present invention to
 provide a radio communication device which has a very
 30 simple structure to send and/or receive image information,
 in addition to character data and/or numerical data.

In order to achieve the above objects, according to
 the present invention, there is provided a radio
 communication device which sends and/or receives data to
 35 and/or from the other party's radio communication device,
 comprising:

conversation sentence data storage means for storing a



plurality of conversation sentence data items;

conversation sentence selecting means for selecting one of the plurality of conversation sentence data items stored in said conversation data storage means;

5 sending means for sending to the other party's radio communication device radio data corresponding to the conversation sentence data selected by said conversation sentence selecting means;

10 receiving means for receiving radio data from the other party's radio communication device;

determining means for determining which of the conversation data items of the plurality stored in said conversation sentence data storing means the radio data received by said receiving means corresponds to; and

15 display means for displaying conversation sentence data corresponding to the received data determined by said determining means.

FIG. 1 is a block diagram of an internal circuit of a radio communication device as one embodiment of the present invention.

20 FIG. 2 shows the appearance of a key-in unit of the device.

FIG. 3 shows data on the basic part patterns of a face stored in a ROM (Read Only Memory) of the device.

25 FIGS. 4A, 4B, and 4C show data on expression change patterns stored in the ROM.

FIG. 5 is a table of question/response data stored in the ROM.

30 FIG. 6 shows the internal structure of a RAM (Random Access Memory) of the device.

FIG. 7 is a general flowchart indicative of the operation of the device.

FIG. 8 is a flowchart indicative of a montage creation process performed in the device.

35 FIG. 9 is a flowchart indicative of a montage synthesis process performed in the device.

FIG. 10 is a flowchart indicative of other key-in



processes performed in the device.

FIG. 11 is a flowchart indicative of other key-in processes performed in the device and combined with the flowchart of FIG. 10.

5 FIG. 12 is a flowchart indicative of a transmission process performed in the device.

FIG. 13 is a flowchart indicative of a reception process performed in the device.

10 FIGS. 14A and 14B illustrate user's and the other party's montage data.

FIGS. 15 illustrates communication made between the user's device and the other party's device.

An embodiment of the present invention will be described next with reference to the accompanying drawings.

15 FIG. 1 is a block diagram of the internal circuit of a radio communication device as one embodiment of the present invention.

In FIG. 1, a central processing unit (CPU) 1 which includes a microprocessor or the like controls the whole operation of the radio communication device on the basis of a microprogram stored in a built-in ROM (not shown).

20 CPU 1 is connected to a key-in unit 2, a ROM 3, a RAM 4, an image synthesis RAM 5, a display driver 6, a display 7 connected to the display driver 6, and a
25 transmitter/receiver unit 8.

The key-in unit 2 includes a keyboard with many kinds of depression-type switches where a depressed switch outputs a key-in signal to CPU 1.

30 ROM 3 stores face pattern data and questions/answer data, as shown in FIGS. 3-5, which will be described later in more detail.

RAM 4 is composed of registers which store predetermined data. CPU 1 reads/writes data from/in the RAM 4.

35 The synthesis RAM 5 is a bit image memory on which a face montage is synthesized from face pattern data items designated by input data or from which the synthesized



montage data is read.

The display driver 6 is composed of a decoder, driver, etc., and decodes display data received from CPU 1, produces and outputs a display drive voltage signal to the display 7, which is composed of a dot matrix type liquid crystal display which makes predetermined display on the display in accordance with the voltage signal from the display driver 6.

The transmitter/receiver unit 8 is composed of a transmitter circuit (not shown) which includes a LED (Light Emitting Diode) and a switching FET (Field Effect Transistor); and a receiver circuit (not shown) which includes a photodiode or a phototransistor, an amplifier, and a low pass filter. The transmitter circuit converts a parallel signal from CPU 1 to a serial high-low electric signal, which turns on/off the switching FET and hence the LED to thereby output an infrared optical signal including predetermined data. In the receiver circuit, its photodiode (or phototransistor) is turned on/off in response to an optical signal from an LED of a transmitter circuit of the other party to convert the optical signal to an electric signal, amplifies this signal, extracts only the frequency components of the LED emission signal from the amplified electric signal, converts the frequency signal to a parallel digital signal, and outputs this signal to CPU 1.

FIG. 2 shows the structure of the keyboard of key-in unit 2. The keyboard is composed of a designating key unit 21 composed of 9 (3 x 3) designating keys disposed vertically and horizontally in an upper portion of the keyboard, a select key unit 22 composed of 4 cursor keys with upward, downward, rightward and leftward arrows thereon and provided in the middle portion of the keyboard, and two select keys with upward and downward triangular key pads; and a data key-in unit 23 composed of data input numerical keys and character keys disposed in a lower portion of the keyboard.



5 An M key 21A of the designating unit 21 is an operation mode designating key. Each time it is operated, the operation mode is switched alternately between a normal mode in which calculation and data transmission/reception are performed and a data producing mode where a montage is created or calling or visiting card data is input.

10 An F key 21B is a user's/the other party's mode designating key. Each time it is operated in the data creation mode, the operation mode is switched alternately between a user's montage creation mode in which the user creates his portrait montage and a data bank (DB) data/montage creation mode in which a portrait montage of a person different from the user is created.

15 A montage creation key 21C is an input mode designating key. Each time it is operated in the data creation mode, the operation mode is switched alternately between the montage creation mode and the character (numerical) data input mode.

20 A Q1 key 21D, a Q2 key 21E and a Q3 key 21F each are a question designating key which is operated to select a corresponding one of three kinds of questions to be described later in more detail.

25 An "OK" key 21G and a "NO" key 21H are respective response designating keys which are operated to select two corresponding kinds of responses YES and NO.

 A transmission key 21I is a transmission commanding key which is operated to send transmission data designated by the respective designating keys from the transmitter/receiver unit 8 of FIG. 1 to the outside.

30 The two upward and downward triangular basic pattern select keys 22A and 22B disposed in the right-hand middle portion of the keyboard are each operated to select a basic type of basic part patterns of a montage to be described later in the montage creation mode of the data creation mode. The four upward, downward, rightward and leftward arrowed cursor keys 22C, 22D, 22E and 22F disposed to the left of the two select keys 22A, 22B are part select

35



keys which are operated to select part data items of the basic type of the selected basic part pattern of the montage.

The numerical keys and character keys of the input unit 23 disposed in the lower portion of the keyboard are operated to input character data such as the first name, second name, and address of a person and numerical data such as his telephone numbers to the device in the character (numeral) input mode of the data creation mode. The input unit 23 further includes a record key 23A which is operated to record question data and response data designated by the corresponding designating keys and basic part pattern data items selected by the corresponding select keys.

FIG. 3 shows data on basic part patterns of a face stored in a first storage area 3A of ROM 3. In FIG. 3, the basic part patterns includes 50 patterns numbered "1"-"50" disposed from left to right for each of a "contour" part 3A-1, a "hair style" part 3A-2, an "eyes" part 3A-3, a "nose" part 3A-4, and a "mouth" part 3A-5 of a face. The number of part patterns may be more or less than 50 depending on the capacity of the ROM. Any ones of those patterns may be selected and combined using the select keys 22A, 22B disposed in the middle portion of the keyboard of FIG. 2. The 50th "eyes" part 3A-3 and the 50th "mouth" part 3A-5 each have a usual or calm expression.

FIGS. 4A, 4B, 4C each show part pattern data stored in a second storage area 3B of ROM 3 and related to change part patterns corresponding to "eyes" part 3A-3 and "mouth" part 3A-5 of the basic part pattern Nos. "1", "2", "3", ... FIG. 4A shows patterns of an "eyes" part 3B-1A and a "mouth" part 3B-2A each indicative of a delightful expression. FIG. 4B shows patterns of an "eyes" part 3B-1B and a "mouth" part 3B-2B each indicative of a sad expression. FIG. 4C shows patterns of an "eyes" part 3B-1C and a "mouth" part 3B-2C each indicative of an angry expression.



FIG. 5 shows a storage table of conversation sentence data composed of question sentence data and response sentence, data and expression change data stored in a third storage area 3C of ROM 3.

5 First question sentence data "let's play ?" is stored along with a specified code X in a storage area 3C-1. By depression of the question designating key Q1 of FIG. 2, the stored specified code X and "Let's play ?" question sentence data are addressed and read. Second question
10 sentence data "Please tell me an answer to our assignment ?" is stored along with a specified code Y in a storage area 3C-2. By the operation of the designating key Q2 of FIG. 2, the stored specified code Y and "Pease tell me an answer to our assignment are addressed and read. Third
15 sentence data "Please forgive me ?" is stored along with a specified code Z in a storage area 3C-3. By depression of the question designating key Q3 of FIG. 2, the stored specified code Z and "Please forgive me ?" question sentence data are addressed and read.

20 The response sentence data items "OK", "NO" are stored along with specified codes S and T in storage areas 3C-4, 3C-5, respectively. By depression of "OK" key 21G and "NO" key 21H, the corresponding specified codes S and T are addressed and read.

25 The specified codes X, Y, Z, S and T are each composed of 3 bits and differ one from the other.

Storage areas 3C-6, 3C-7 are provided in correspondence to the storage area 3C-1. Storage areas 3C-8, 3C-9 are provided in correspondence to the storage area
30 3C-2. Storage areas 3C-10, 3C-11 are provided in correspondence to the storage area 3C-3. These storage areas 3C-6 to 3C-11 store change data indicating which of change patterns stored in the ROM of FIGS. 4A, 4B, 4C or that no change patterns are selected. The storage areas
35 3C-6, 3C-8 store data items which select the ROM of FIG. 4A. The storage are 3C-7 stores data which select the ROM of FIG. 4B. The storage areas 3C-9 stores data which



selects the ROM of FIG. 4C. The storage areas 3C-10, 3C-11 store data items which select no ROMs.

5 The data in the storage areas 3C-6, 3C-8, 3C-10 is read when the "OK" 21G is operated. The data in the storage areas 3C-7, 3C-9, 3C-11 is read when the "NO" 21H is operated.

FIG. 6 shows the internal structure of RAM 4. In FIG. 6, a display register 61 stores data displayed on the display 7 of FIG. 1.

10 A register n is a flag register which designates an operation mode. The data stored in the register n is changed to another in the sequence of "0"→"1"→"0" each time the M key 21A of the designating unit 21 of the FIG. 2 keyboard is operated for inputting purposes. "0"

15 designates a normal mode in which calculation or transmission/reception can be performed. "1" designates a data creation mode in which montage creation or a calling or visiting card data inputting operation can be performed.

A register f is a flag register which designates a user mode or a different person mode. The data stored in the register f is changed alternately between "0" and "1" each time the F key 21B of the designating unit 21 of the FIG. 2 keyboard is operated for inputting purposes. "1" designates a user' montage creation mode. "0" designates a

25 DB data/montage creation mode.

A register l is a flag register indicative of a transmission/reception mode. It stores "1" for the time interval from when the transmitter/receiver unit 8 of FIG. 1 receives question data from the other party's device to the time when the transmitter/receiver unit 8 sends

30 response data to the other party, and stores "0" if otherwise.

A user's montage data register 62 stores user's montage data similar to DB montage data.

35 DB registers 63-1, 63-2, 63-3,... each store montage data on each of user's friends along with his name, telephone number, and address, etc. The storage area for



the montage data is divided into five data subareas for "contour", "hair", "eyes", "nose" and "mouth" which store corresponding numbers indicative of the basic part patterns of FIG. 3 selected by the keying-in operation.

5 The processing operation of CPU 1 of FIG. 1 will be described with reference to flowcharts of FIGS. 7-13.

FIG. 7 is a general flowchart indicative of the whole flow of the program. In FIG. 7, first, at step A1 it is determined whether the transmitter/receiver unit 8 of FIG. 10 1 has received data sent by the other party. If so, control passes to step A2, where a reception process to be described later is performed and the process is terminated.

If not at step A1, it is determined at step A3 whether a key is operated for inputting purposes at the keyboard of 15 the key-in unit 2 of FIG. 2. If not, the processing is terminated at once. If so at step A3, control passes to step A4, where it is determined whether the key-in operation has been performed by the transmission key 21I.

If so at step A4, control passes to step A5, where a 20 transmission process to be described later in more detail is performed and the process is terminated.

If not at step A4, control passes to step A6, where other key-in operations are performed and the process is terminated.

25 A montage creation process by keys among the other key-in operations at step A6 will be described with reference to a flowchart of FIG. 8. This process is started on the basis of a key-in operation by the montage creation key 21C at the keyboard of FIG. 2. Before this 30 operation, the user's montage creation mode or the DB data/montage creation mode is beforehand designated by the operation of the F key 21B to thereby select any one of the user's montage data register 62 or DB registers 63-1, 63-2, 63-3, ... of the FIG. 6 RAM and its corresponding montage 35 area is used.

First, at step M1 of the FIG. 8 flowchart, "contour", "hair", "eyes", "nose", and "mouth" part patterns shown by



No. 1 in the FIG. 3 ROM are selected as a basic type and the "contour" is then set initially as a changeable part. At step M2 a montage synthesis process to be described later in more detail is performed. At step M3 the
5 resulting montage is displayed on the display 7 through the FIG. 1 display driver 6 on the basis of the processed montage data. Thus, at the beginning, the montage composed of the basic part patterns No. 1 is displayed and the "contour" of the montage is displayed "going-on-off or
10 inverted as a change starting part.

At step M4 it is determined whether the triangular select key 22A or 22B is operated for inputting purposes at the selection unit 22 of the FIG. 2 keyboard. If not, it is determined at step M6 whether the cursor key 22C or 22D
15 at the keyboard select unit 22 of FIG. 2 is operated for inputting purposes. If not at step M6, it is determined at step M8 whether the cursor key 22E or 22F is operated for inputting purposes at the selection unit 22 of the FIG. 2 keyboard. If not, it is determined at step M10 whether the
20 record key is operated for inputting purposes and control returns to step M4 to iterate the determination of the key-in operations at steps M4-M8.

If the selection key 22A or 22B is operated for inputting purposes at step M4, control passes to step M5,
25 where the set basic type is changed and then control returns to step M2 for montage synthesis. Thus, the basic patterns now in display are changed and displayed. At this time, if
30 the upward triangular select key 22A is operated for inputting purposes, the basic part pattern number of the montage displayed at present is changed to a basic part pattern number larger by one than the former one. If the downward triangular selection key 22B is operated for
35 inputting purposes, the basic part pattern number of the montage displayed at present is changed to a basic part pattern number smaller by one than the former one.

When the upward or downward arrowed cursor key 22C or



22D is operated for inputting purposes at step M6, control passes to step M7, where the kind of the part is changed and control returns to step M2 for montage synthesis process. Thus, one of the "contour", "hair", "eyes", "nose" and "mouth" which are the kinds of the parts of the basic part patterns displayed at present is displayed, for example, in a going-on-off manner on the display screen. Each time the upward arrowed cursor key 22C is operated for inputting purposes at this time, the montage displayed at present moves in a going-on-off manner sequentially in the sequence of "mouth"→"nose"→"eyes"→"hair"→"contour"→"mouth". If the downward arrowed cursor key 22D is operated for inputting purposes, the part of the montage displayed at present changes to another in a going on-off manner sequentially in the sequence of "contour"→"hair"→"eyes"→"nose"→"mouth"→"contour" each time that key is operated for inputting purposes.

If it is determined at step M8 that the leftward or rightward arrowed cursor key 22E or 22F has been operated for inputting purposes control passes to step M9, where the pattern of the part is changed and control then returns to step M2 for montage synthesis. Thus, that of the currently displayed basic part patterns and displayed in a going-on-off manner is changed in accordance with the key-in operation. At this time, if the leftward arrowed cursor key 22E is operated for inputting purposes, the part of the montage displayed at present in the going-on-off manner changes to another sequentially in the sequence of the No. 50 part → the No. 49 part... → the No. 3 part→ the No. 2 part → the No. 1 part → the No. 50 part.

If the rightward arrowed cursor key 22F has been operated for inputting purposes, the part of the montage displayed at present in the going-on-off manner changes to another sequentially in the sequence of the No. 1 part→the No. 2 part→ the No. 3 part →... →the No. 50 part → the No. 1 part each time the key 22F is operated.

If the record key is operated for inputting purposes



at step M10, control passes to step M11, where the kind of the part is changed. A montage is then synthesized at step M2, the data on the montage displayed at step M3 is recorded in a predetermined montage data area and the process is terminated.

Subsequently, the montage synthesis at step M2 will be described with reference to a flowchart of FIG. 9.

First, at step D1 the "contour" No. (a basic part pattern No. of the "contour" part 3A-1 of FIG. 3) set in the predetermined montage area is read. Data on the "contour" part 3A-1 indicated by the read basic part pattern number is read from the first storage area 3A in ROM 3 and stored in a predetermined area in the synthesis RAM 5.

Then at step D3 a "hair" No. (the basic part pattern No. of the "hair" part 3A-2 of FIG. 3) is read. At step D4 and data on a "hair" part 3A-2 indicated by the read basic part pattern number is read from the first storage area 3A in ROM 3, and stored in a predetermined area in the synthesis RAM 5.

Then at step D5 the "eyes", "nose", and "mouth" basic part pattern Nos. are read and data items on the "eyes", "nose", and "mouth" part patterns 3A-3, 3A-4, and 3A-5 indicated by the corresponding read basic part pattern numbers Nos. are read from the first storage area 3A in ROM 3, and stored in predetermined areas in the synthesis RAM 5. Thus, a montage image created in the synthesis RAM 5 is displayed on the display 7 of FIG. 1 at step D6.

Key-in processes of the other key-in processes at step A6 of FIG. 7 other than the montage creation will be described with reference to the flowcharts of FIGS. 10 and 11 which are connected to each other at (1) and (2) of FIGS. 10 and 11.

At step A7 it is determined whether the M key 21A is operated for inputting purposes. If so, it is determined at step A8 whether the value (flag) of the flag register n is "0". If so, control passes to step A9, where "1" is set



in the flag register n to terminate the process. If the flag register is "1", control passes to step A10, where the "0" is set in the flag register n to terminate the process. Thus, each time the M key 21A is operated for inputting purposes, the flag of the flag register n is switched alternately between "0" and "1", so that the operation mode is switched alternately between the normal mode and the data creation mode.

10 If the M key 21A is not operated at step A7, control passes to A11, where it is determined whether the F key 21B is operated for inputting purposes. If so, control passes to step A12, where the flag of the flag register n is referred to, thereby determining whether the F key 21B is operated in the data creation mode.

15 If the flag of the flag register n is "1" at step A12, it is determined that the F key 21B is operated for inputting purposes in the data creation mode. In this case, control passes to step A13, where it is determined whether the flag of the flag register f is "0". If so, control passes to step A14, where "1" is set in the flag register f to terminate the process. If the flag of the flag register is "1" at step A13, control passes to step A15, where "0" is set in the flag register f to terminate the process. Thus, the flag of the flag register f is switched alternately between "0" and "1" each time the F key 21B is operated for inputting purposes in the data creation mode. Thus, the user's/other party's mode is switched alternately between the DB data montage creation mode and the user's montage creation mode.

30 If the flag of the flag register n is "0" at step A12, it is determined that the F key 21B is operated in the normal mode to thereby terminate the process at once. Thus, in the normal mode, the key-in operation of the F key 21B is ignored.

35 If the key-in operation of the F key 21B is not performed at step A11, control passes to step A16, where it is determined whether the montage creation key 21C is



operated for inputting purposes. If so, control passes to step A17, where the flag of the flag register n is referred to, thereby determining whether the montage creation key 21C is operated in the data creation mode.

5 If the flag of the flag register n is "1" at step A17, it is determined that the montage creation key 21C is operated in the data creation mode. In this case, at step A18 the flag of the flag register f is referred to, thereby determining which of the user's and other party's modes is set.

10 If the flag of the flag register f is "0", it is determined that the DB data montage creation mode is set now. In this case, control passes to step A19, where the DB data is input and the DB montage creation described in the flowchart of FIG. 8 is performed to thereby terminate the process.

15 If the flag is "1" at step A18, it is determined that the user's montage creation mode is set. In this case, control passes to step A20, where the user's montage creation described with reference to the FIG. 8 flowchart is performed and process is terminated.

20 Thus, for example, as shown in FIG. 14A, selected "contour", "hair", "nose", "eyes", and "mouth" parts having basic part pattern Nos. "2", "3", "1", "1" and "2", respectively, and a user's montage synthesized from those parts in the user's montage creation mode of the user's device are recorded in the user's montage data register 62 of FIG. 6. In the other party's device which, for example, a girl has, selected "contour", "hair", "nose", "eyes", and "mouth" parts having basic part pattern Nos. "1", "2", "2", "2" and "1", respectively, and a girl's montage synthesized from those parts are recorded in a girl's montage data register such as 62, as shown in FIG. 14B.

25 If the flag of the flag register n is "0" in the determination at step A17, the process is terminated at once. Thus, the key-in operation of the montage creation key 21C performed in the normal mode is ignored.



If no montage creation key 21C is determined to be operated at step A16, control passes to step A21, where it is determined whether the "OK" key 21G is operated for inputting purposes. If so, control passes to step A22,
5 where the flag of the flag register 1 is referred to, thereby determining whether the "OK" key 21G is operated in the transmission/reception mode during transmission of the response data.

If the flag of the flag register 1 is "1", it is
10 determined that it is now in a response data transmission interval after question data is received from the other party to be described later. Thus, control passes to step A23, where response data "OK" is set in the display register 61 and also is displayed on the display 7.

15 If at step A22 the flag of the flag register 1 is "0", the process is terminated at once. Thus, the key-in operation of the "OK" key 21G is ignored except in the response data transmission interval.

If at step A21 the key-in operation of "OK" key 21G is
20 not performed, control passes to step A24, where it is determined whether the "NO" key 21H is operated for inputting purposes. If so, control passes to step A25, where the flag of the flag register 1 is referred to, thereby determining whether the "NO" key 21H is operated in
25 the transmission/reception mode during the response data transmission interval.

If the flag of the flag register 1 is "1", it is determined whether it is now in the response data transmission interval and control passes to step A26, where
30 "NO" data is set and "NO" is displayed on the display 7.

If at step A25 the flag of the flag register 1 is "0", the process is terminated at once. Thus, the key-in operation of the "NO" key 21H is ignored except in the response data transmission interval.

35 If at step A24 the key-in operation of the "NO" key 21H is not performed, control passes to step A27, where it is determined whether any one of Q1 key 21D, Q2 key 21E and



Q3 key 21F is operated for inputting purposes. If so, control passes to step A28, where the flag of the flag register 1 is referred to, thereby determining whether the key-in operation of that key is performed in the question data transmission interval.

If the flag of the flag register 1 is "0", it is determined that it is now in the question data transmission interval. Control then passes to step A29, where, as shown in FIG. 5, "Let's play ?" data, "Please tell me an answer to our assignment ?" data, and "forgive me" data are displayed on the display register 61 when the Q1 key 21D, Q2 key 21E, and Q3 key 21F, respectively, are operated for inputting purposes.

If at step 28 the flag of the flag register 1 is "1", the process is terminated at once. Thus, the key-in operation of the Q1 key 21D, Q2 key 21E or Q3 key 21F is ignored except in the question data transmission interval.

The transmission at step A5 of FIG. 7 for transmission of the montage, question or response data, set as mentioned above, will be described with reference to the flowchart of FIG. 12. First, at step A30 it is determined whether the flag of the flag register 1 is "0". If so, it is determined that it is now in the question data transmission interval. Control then passes to step A31, where specified code data corresponding to the question data set in the display register 61 by the Q1 key 21D, Q2 key 21E or Q3 key 21F and displayed on the display 7 is read from ROM 3. If, for example, the question sentence "Let's play ?" is displayed by the operation of the Q1 key 21D, a specified code X is read from a third storage area 3C-1 of ROM 3. If "Please tell me an answer to our assignment ?" or "Please forgive me ?" has been displayed by the operation of the Q2 key 21E or Q3 key 21F, a specified code Y or Z is read. The read specified code is transmitted along with corresponding number data stored in the user's montage data register 62.

The sent specified code and montage number data are



processed by a reception process to be described later and displayed as a question sentence and a montage on the display of the other party.

5 If at step A30 the flag of the flag register 1 is "1", it is determined that it is now in the response data transmission interval. Thus, control passes to step A32, where a specified code S or T corresponding to a response sentence set and displayed by the "OK" key 21G or the "NO" key 21H is read from the third storage area 3C-4 or 3C-5.
10 Data in one of the storage areas 3C-6 to 3C-11 is read depending on the answer to that of the question sentences for which the "OK" key 21G or "NO" key 21H is operated, and sent along with its number data stored in the user's montage data register 62.

15 If at step A30 the flag of the flag register 1 is "1", it is determined that it is now in the response data transmission interval. Thus, control passes to step A32, where a specified code for the response data set by the "OK" 21G or "NO" key 21H and displayed on the display 7 is
20 sent along with the user's montage data.

Subsequent to step A32, control passes to step A33, where the flag of the flag register 1 is set at "0" to thereby set the end of the response interval.

25 Subsequently, the reception process at step A2 of FIG. 7 performed when the sent data is received will be described with reference to the flowchart of FIG. 13.

First, at step A34 it is determined whether the flag of the flag register 1 is "0". If so, it is determined that it is now in the reception interval in the
30 transmission/reception mode. Thus, control passes to step A35, where it is determined whether the received data is a specified code for the question data. If so, control passes to step A36, where the storage area where the specified code received from one of the third storage areas
35 3C-1, 3C-2 and 3C-3 of ROM 3 is stored is retrieved and the question sentence data stored in that area is displayed on the display 7. Pattern data is read from the first storage



area 3A on the basis of the number data for the received montage data and displayed on the display 7.

Subsequently, at step A37 the flag of the flag register 1 is set at "1" to thereby terminate the process. Thus, a transmission interval for the response data to the received question data is set.

When at step A35 the received specified code data is determined to be not for a specified code corresponding to the question data, control passes to step A38, where it is determined whether the received data is for a specified code corresponding to the response sentence. If so, control passes to step A39, where response characters for the corresponding response sentence data are read from the storage area 3C-4 or 3C-5 and displayed on the display 7, and number data on the "eyes" part 3A-3 and "mouth" part 3A-5 of the received montage number data are converted to "eyes" expression change pattern data and "mouth" expression change pattern data corresponding to the changed data received at the same time, and displayed on the display 7.

Subsequent to step A39, the ending process is performed at step A40 to terminate the process. This process involves display of the received response data for a predetermined interval of time and then erasure of the display.

By the above processing, for example, as shown in FIG. 15A, "Let's play" data is selected by the Q1 key 21-4 in the user's device and subsequent operation of the transmission key 21I is performed, the specified code X is sent along with the number data of the user's montage data of FIG. 14A to the other party's device. By the reception process in the other party's device, the sentence "Let's play" and the montage are displayed on the display of the other party's device. As shown in FIG. 15C, when the data "Please tell me an answer to our assignment ?" is set by the Q2 key 21-5, and transmission key 21I is operated in the other party's device, the specified code Y in the



storage area 3C-1 of FIG. 5 is sent along with the other party's montage data to the user's device, so that by the reception process the "Please tell me an answer to our assignment ?" and the other party's montage are displayed on the user's display 7.

When the "OK" key 21G or "NO" key 21H is operated to set response data and the transmission key is operated in the state where the question sentence from the other party and the other party's montage are displayed on the display 7, the specified code corresponding to the response data and the user's montage data are sent.

For example, as shown by F in FIG. 15, the user's montage data of FIG. 14A is sent by his device to the other party's device along with the specified code S for the "OK" data set by the "OK" key 21G as a response to the reception of the "Please tell me an answer to our assignment" data. By the reception process in the other party device, "OK" and the user's montage are displayed on the display of the other party's device. In this case, since the response "OK" to the question "Please tell me an answer to our assignment" is received, change data stored in the area 3C-8 of FIG. 5 is read and the expressions of "eyes" and "mouth" of the montage the data of which is received are replaced with the read change data to a delightful montage expression on the display. For example, as shown by C in FIG. 15, when a specified code T corresponding to "NO" set by the "NO" key of the other party device as a response to receipt of the "Let's play" data is sent along with the girl's montage data, "NO" and a montage having a "sad" expression change pattern of FIG. 4B are displayed on the user's display 7, as shown by D in FIG. 15.

As described above, in the present embodiment, even if no conversation sentence data itself is sent by radio, satisfactory communication is achieved. Data on an image such as a montage is sendable or the contents of the image are changeable in accordance with the contents of the conversation sentences so that the user can inform the



other party of his feeling by using his image.

While in the present embodiment one of three kinds of questions is illustrated as being selected or designated, the number of questions selectable is not limited to three.

- 5 More kinds of questions may be prepared such that any one of them can be selected by a key. While one of the two kinds of responses is illustrated as being selected or designated, three or more kinds of responses may be prepared such that any one of them may be selected. While
- 10 the receiving end converts the "eyes" and "mouth" part patterns to other part patterns depending on the kind of the responses, the sending end may change the "eyes" and "mouth" part pattern data to other part pattern data depending on the kinds of the response and then send the
- 15 changed data to the receiving end.

This Sheet Has Been Replaced





CLAIMS:

1. A radio communication device which sends and/or receives data to and/or from the other party's radio communication device, comprising:

5 conversation sentence data storage means (3C) for storing a plurality of conversation sentence data items;

10 conversation sentence selecting means (Q1, Q2, Q3, 21G, 21H) for selecting one of the plurality of conversation sentence data items stored in said conversation data storage means;

15 sending means (8) for sending to the other party's radio communication device radio data corresponding to the conversation sentence data selected by said conversation sentence selecting means;

receiving means (8) for receiving radio data from the other party's radio communication device;

20 determining means (X, Y, Z, S, T) for determining which of the conversation data items of the plurality stored in said conversation sentence data storing means the radio data received by said receiving means corresponds to; and

display means (7) for displaying conversation sentence data corresponding to the received data determined by said determining means.

25 2. A radio communication device according to claim 1, wherein said conversation sentence selecting means comprises operation keys (Q1, Q2, Q3, 21G, 21H) provided for the respective conversation sentence data items of the plurality to select one of the conversation sentence data items.

30 3. A radio communication device according to claim 1, wherein said sending means and said receiving means comprises an infrared data sending circuit and an infrared receiving circuit, respectively.

35 4. A radio communication device according to claim 1, further comprising image data storage means (3A, 3B, 62) for storing image data, and image data transmission control




means (A31, A32 in FIG. 12) for sending image data stored in said image data storage means from said sending means.

5. A radio communication device according to claim 5, wherein said image data storage means comprises part
5 pattern data storage means (3A) for storing a plurality of data items on the patterns of parts of a face of a montage, and image data selecting means (22A-22F) for selecting any part pattern data item of a plurality of part pattern data items stored in said part pattern data storage means to
10 obtain image data on the montage.

6. A radio communication device according to claim 1, wherein the plurality of conversation sentence data stored in said conversation sentence data storage means comprises
15 question conversation data and response conversation data to the question conversation data.

This Sheet Has Been Replaced



* C L N S *

ABSTRACT: (FIG. 1)

"RADIO COMMUNICATION DEVICES"

5 Data on various conversation sentences are
sent/received by radio between radio communication devices
remote from one another. Many conversation sentence data
items and different code data items are beforehand stored
10 in corresponding relationship in a conversation sentence
data storage ROM 3. When one of the conversation sentence
data items is selected by operation of a select switch, a
corresponding code data item is sent to a receiving end,
which is provided with a ROM having the same contents of
storage as the ROM 3. A conversation sentence is read from
the ROM in accordance with the received code data and
15 displayed on a display 7.

This Sheet Has Been Replaced






FIG.1

This Sheet Has Been Replaced






FIG.2

This Sheet Has Been Replaced



BASIC PART PATTERNS IN ROM

	PART \ NO.	NO.				50	
		1	2	3			
3A-1 →	CONTOUR						
3A-2 →	HAIR STYLE						
3A-3 →	EYES						
3A-4 →	NOSE						
3A-5 →	MOUTH						

FIG.3

This Sheet Has Been Replaced



EXPRESSION CHANGE
PATTERNS IN ROM

FIG.4A

		1	2	3	
3B-1A	EYES				
3B-2A	MOUTH				

FIG.4B

		1	2	3	
3B-1B	EYES				
3B-2B	MOUTH				

FIG.4C

		1	2	3	
3B-1C	EYES				
3B-2C	MOUTH				


This Sheet Has Been Replaced



	3C-1	3C-2	3C-8	3C-6	3C-7
X	Let's play ?			HAPPY	SAD
Y	Please tell me an answer to our assignment ?			HAPPY	ANGRY 3C-9
Z	Please forgive me ?			BASIC	BASIC 3C-11
S	OK !				3C-10
T	NO !				
	3C-5	3C-4	3C-3		

FIG.5

This Sheet Has Been Replaced



61

DISPLAY REGISTER						
n	f	ℓ				
USER'S MONTAGE DATA						
NAME	TEL	ADDRESS	CON-TOUR	HAIR	EYES	NOSE MOUTH
TARO YAMADA		..., TOKYO	1	2	3	1

62

63-1

63-2

63-3

FIG.6

This Sheet Has Been Replaced






FIG.7

This Sheet Has Been Replaced






FIG.8

This Sheet Has Been Replaced






FIG.9

This Sheet Has Been Replaced






FIG.10

This Sheet Has Been Replaced






FIG.11

This Sheet Has Been Replaced






FIG.12

This Sheet Has Been Replaced






FIG.13

This Sheet Has Been Replaced



(USER'S MONTAGE)

CONTOUR	HAIR	NOSE	EYES	MOUTH
NO.2	NO.3	NO.1	NO.1	NO.2



FIG.14A

(THE OTHER'S
MONTAGE DATA)

CONTOUR	HAIR	NOSE	EYES	MOUTH
NO.1	NO.2	NO.2	NO.2	NO.1



FIG.14B

This Sheet Has Been Replaced



(ILLUSTRATIVE MONTAGE
COMMUNICATION)




FIG.15

This Sheet Has Been Replaced



RADIO COMMUNICATION DEVICES

The present invention relates to radio communication devices which have simple conversation with others by radio.

So-called remote control devices which control the operation of electronic devices such as television sets or video tape recorders, using an infrared control signal, are sold as commodities. Infrared signals are used not only to control the operation of the electronic devices, but also to send and/or receive information composed of character data and/or numerical data between two electronic devices.

In order to send and/or receive information such as character data and numerical data using an infrared radio signal, the information is required to be set by the operation of keys of a device on the side of the transmission and a circuit which decodes all the characters and numerical data received from the other party must be provided on the side of the transmission. Thus, the structure of the device of the transmission side is complicated undesirably. When image information different from the character and numerical data is sent and/or received, a more complicated structure is required.

It is therefore an object of the present invention to provide a radio communication device which has a very simple structure and requires only a very simple operation to send and/or receive information.

It is another object of the present invention to provide a radio communication device which has a very simple structure to send and/or receive image information, in addition to character data and/or numerical data.

In order to achieve the above objects, according to the present invention, there is provided a radio communication device which sends and/or receives data to and/or from the other party's radio communication device, comprising:

conversation sentence data storage means for storing a

This is the replacement sheet

Date: - 9 SEP 1996

plurality of conversation sentence data items;

conversation sentence selecting means for selecting one of the plurality of conversation sentence data items stored in said conversation data storage means;

5 sending means for sending to the other party's radio communication device radio data corresponding to the conversation sentence data selected by said conversation sentence selecting means;

10 receiving means for receiving radio data from the other party's radio communication device;

determining means for determining which of the conversation data items of the plurality stored in said conversation sentence data storing means the radio data received by said receiving means corresponds to; and

15 display means for displaying conversation sentence data corresponding to the received data determined by said determining means.

FIG. 1 is a block diagram of an internal circuit of a radio communication device as one embodiment of the present invention.

20 FIG. 2 shows the appearance of a key-in unit of the device.

FIG. 3 shows data on the basic part patterns of a face stored in a ROM (Read Only Memory) of the device.

25 FIGS. 4A, 4B, and 4C show data on expression change patterns stored in the ROM.

FIG. 5 is a table of question/response data stored in the ROM.

30 FIG. 6 shows the internal structure of a RAM (Random Access Memory) of the device.

FIG. 7 is a general flowchart indicative of the operation of the device.

FIG. 8 is a flowchart indicative of a montage creation process performed in the device.

35 FIG. 9 is a flowchart indicative of a montage synthesis process performed in the device.

FIG. 10 is a flowchart indicative of other key-in

This is the replacement sheet

Date: - 9 SEP 1996

processes performed in the device.

FIG. 11 is a flowchart indicative of other key-in processes performed in the device and combined with the flowchart of FIG. 10.

5 FIG. 12 is a flowchart indicative of a transmission process performed in the device.

FIG. 13 is a flowchart indicative of a reception process performed in the device.

10 FIGS. 14A and 14B illustrate user's and the other party's montage data.

FIGS. 15 illustrates communication made between the user's device and the other party's device.

An embodiment of the present invention will be described next with reference to the accompanying drawings.

15 FIG. 1 is a block diagram of the internal circuit of a radio communication device as one embodiment of the present invention.

In FIG. 1, a central processing unit (CPU) 1 which includes a microprocessor or the like controls the whole operation of the radio communication device on the basis of a microprogram stored in a built-in ROM (not shown).

20 CPU 1 is connected to a key-in unit 2, a ROM 3, a RAM 4, an image synthesis RAM 5, a display driver 6, a display 7 connected to the display driver 6, and a transmitter/receiver unit 8.

25 The key-in unit 2 includes a keyboard with many kinds of depression-type switches where a depressed switch outputs a key-in signal to CPU 1.

30 ROM 3 stores face pattern data and questions/answer data, as shown in FIGS. 3-5, which will be described later in more detail.

RAM 4 is composed of registers which store predetermined data. CPU 1 reads/writes data from/in the RAM 4.

35 The synthesis RAM 5 is a bit image memory on which a face montage is synthesized from face pattern data items designated by input data or from which the synthesized

montage data is read.

The display driver 6 is composed of a decoder, driver, etc., and decodes display data received from CPU 1, produces and outputs a display drive voltage signal to the display 7, which is composed of a dot matrix type liquid crystal display which makes predetermined display on the display in accordance with the voltage signal from the display driver 6.

The transmitter/receiver unit 8 is composed of a transmitter circuit (not shown) which includes a LED (Light Emitting Diode) and a switching FET (Field Effect Transistor); and a receiver circuit (not shown) which includes a photodiode or a phototransistor, an amplifier, and a low pass filter. The transmitter circuit converts a parallel signal from CPU 1 to a serial high-low electric signal, which turns on/off the switching FET and hence the LED to thereby output an infrared optical signal including predetermined data. In the receiver circuit, its photodiode (or phototransistor) is turned on/off in response to an optical signal from an LED of a transmitter circuit of the other party to convert the optical signal to an electric signal, amplifies this signal, extracts only the frequency components of the LED emission signal from the amplified electric signal, converts the frequency signal to a parallel digital signal, and outputs this signal to CPU 1.

FIG. 2 shows the structure of the keyboard of key-in unit 2. The keyboard is composed of a designating key unit 21 composed of 9 (3 x 3) designating keys disposed vertically and horizontally in an upper portion of the keyboard, a select key unit 22 composed of 4 cursor keys with upward, downward, rightward and leftward arrows thereon and provided in the middle portion of the keyboard, and two select keys with upward and downward triangular key pads; and a data key-in unit 23 composed of data input numerical keys and character keys disposed in a lower portion of the keyboard.

This is the replacement sheet

Date: - 9 SEP 1996

5 An M key 21A of the designating unit 21 is an operation mode designating key. Each time it is operated, the operation mode is switched alternately between a normal mode in which calculation and data transmission/reception are performed and a data producing mode where a montage is created or calling or visiting card data is input.

10 An F key 21B is a user's/the other party's mode designating key. Each time it is operated in the data creation mode, the operation mode is switched alternately between a user's montage creation mode in which the user creates his portrait montage and a data bank (DB) data/montage creation mode in which a portrait montage of a person different from the user is created.

15 A montage creation key 21C is an input mode designating key. Each time it is operated in the data creation mode, the operation mode is switched alternately between the montage creation mode and the character (numerical) data input mode.

20 A Q1 key 21D, a Q2 key 21E and a Q3 key 21F each are a question designating key which is operated to select a corresponding one of three kinds of questions to be described later in more detail.

25 An "OK" key 21G and a "NO" key 21H are respective response designating keys which are operated to select two corresponding kinds of responses YES and NO.

A transmission key 21I is a transmission-commanding key which is operated to send transmission data designated by the respective designating keys from the transmitter/receiver unit 8 of FIG. 1 to the outside.

30 The two upward and downward triangular basic pattern select keys 22A and 22B disposed in the right-hand middle portion of the keyboard are each operated to select a basic type of basic part patterns of a montage to be described later in the montage creation mode of the data creation mode. The four upward, downward, rightward and leftward arrowed cursor keys 22C, 22D, 22E and 22F disposed to the left of the two select keys 22A, 22B are part select

35

This is the replacement sheet

9 SEP 1996

Date:

keys which are operated to select part data items of the basic type of the selected basic part pattern of the montage.

5 The numerical keys and character keys of the input unit 23 disposed in the lower portion of the keyboard are operated to input character data such as the first name, second name, and address of a person and numerical data such as his telephone numbers to the device in the character (numeral) input mode of the data creation mode. 10 The input unit 23 further includes a record key 23A which is operated to record question data and response data designated by the corresponding designating keys and basic part pattern data items selected by the corresponding select keys.

15 FIG. 3 shows data on basic part patterns of a face stored in a first storage area 3A of ROM 3. In FIG. 3, the basic part patterns includes 50 patterns numbered "1"- "50" disposed from left to right for each of a "contour" part 3A-1, a "hair style" part 3A-2", an "eyes" part 3A-3", a 20 "nose" part 3A-4, and a "mouth" part 3A-5" of a face. The number of part patterns may be more or less than 50 depending on the capacity of the ROM. Any ones of those patterns may be selected and combined using the select keys 22A, 22B disposed in the middle portion of the keyboard of FIG. 2. The 50th "eyes" part 3A-3 and the 50th "mouth" 25 part 3A-5 each have a usual or calm expression.

FIGS. 4A, 4B, 4C each show part pattern data stored in a second storage area 3B of ROM 3 and related to change part patterns corresponding to "eyes" part 3A-3 and "mouth" 30 part 3A-5 of the basic part pattern Nos. "1", "2", "3",... FIG. 4A shows patterns of an "eyes" part 3B-1A and a "mouth" part 3B-2A each indicative of a delightful expression. FIG. 4B shows patterns of an "eyes" part 3B-1B and a "mouth" part 3B-2B each indicative of a sad 35 expression. FIG. 4C shows patterns of an "eyes" part 3B-1C and a "mouth" part 3B-2C each indicative of an angry expression.

This is the replacement sheet

Date: - 9 SEP 1996

FIG. 5 shows a storage table of conversation sentence data composed of question sentence data and response sentence, data and expression change data stored in a third storage area 3C of ROM 3.

5 First question sentence data "let's play ?" is stored along with a specified code X in a storage area 3C-1. By depression of the question designating key Q1 of FIG. 2, the stored specified code X and "Let's play ?" question sentence data are addressed and read. Second question
10 sentence data "Please tell me an answer to our assignment ?" is stored along with a specified code Y in a storage area 3C-2. By the operation of the designating key Q2 of FIG. 2, the stored specified code Y and "Pease tell me an answer to our assignment are addressed and read. Third
15 sentence data "Please forgive me ?" is stored along with a specified code Z in a storage area 3C-3. By depression of the question designating key Q3 of FIG. 2, the stored specified code Z and "Please forgive me ?" question sentence data are addressed and read.

20 The response sentence data items "OK", "NO" are stored along with specified codes S and T in storage areas 3C-4, 3C-5, respectively. By depression of "OK" key 21G and "NO" key 21H, the corresponding specified codes S and T are addressed and read.

25 The specified codes X, Y, Z, S and T are each composed of 3 bits and differ one from the other.

Storage areas 3C-6, 3C-7 are provided in correspondence to the storage area 3C-1. Storage areas 3C-8, 3C-9 are provided in correspondence to the storage area
30 3C-2. Storage areas 3C-10, 3C-11 are provided in correspondence to the storage area 3C-3. These storage areas 3C-6 to 3C-11 store change data indicating which of change patterns stored in the ROM of FIGS. 4A, 4B, 4C or that no change patterns are selected. The storage areas
35 3C-6, 3C-8 store data items which select the ROM of FIG. 4A. The storage are 3C-7 stores data which select the ROM of FIG. 4B. The storage areas 3C-9 stores data which

This is the replacement sheet

Date: - 9 SEP 1996

selects the ROM of FIG. 4C. The storage areas 3C-10, 3C-11 store data items which select no ROMs.

The data in the storage areas 3C-6, 3C-8, 3C-10 is read when the "OK" 21G is operated. The data in the storage areas 3C-7, 3C-9, 3C-11 is read when the "NO" 21H is operated.

FIG. 6 shows the internal structure of RAM 4. In FIG. 6, a display register 61 stores data displayed on the display 7 of FIG. 1.

A register n is a flag register which designates an operation mode. The data stored in the register n is changed to another in the sequence of "0"→"1"→"0" each time the M key 21A of the designating unit 21 of the FIG. 2 keyboard is operated for inputting purposes. "0" designates a normal mode in which calculation or transmission/reception can be performed. "1" designates a data creation mode in which montage creation or a calling or visiting card data inputting operation can be performed.

A register f is a flag register which designates a user mode or a different person mode. The data stored in the register f is changed alternately between "0" and "1" each time the F key 21B of the designating unit 21 of the FIG. 2 keyboard is operated for inputting purposes. "1" designates a user' montage creation mode. "0" designates a DB data/montage creation mode.

A register l is a flag register indicative of a transmission/reception mode. It stores "1" for the time interval from when the transmitter/receiver unit 8 of FIG. 1 receives question data from the other party's device to the time when the transmitter/receiver unit 8 sends response data to the other party, and stores "0" if otherwise.

A user's montage data register 62 stores user's montage data similar to DB montage data.

DB registers 63-1, 63-2, 63-3,... each store montage data on each of user's friends along with his name, telephone number, and address, etc. The storage area for

This is the replacement sheet

Date: 9 SEP 1996

the montage data is divided into five data subareas for "contour", "hair", "eyes", "nose" and "mouth" which store corresponding numbers indicative of the basic part patterns of FIG. 3 selected by the keying-in operation.

5 The processing operation of CPU 1 of FIG. 1 will be described with reference to flowcharts of FIGS. 7-13.

10 FIG. 7 is a general flowchart indicative of the whole flow of the program. In FIG. 7, first, at step A1 it is determined whether the transmitter/receiver unit 8 of FIG. 1 has received data sent by the other party. If so, control passes to step A2, where a reception process to be described later is performed and the process is terminated.

15 If not at step A1, it is determined at step A3 whether a key is operated for inputting purposes at the keyboard of the key-in unit 2 of FIG. 2. If not, the processing is terminated at once. If so at step A3, control passes to step A4, where it is determined whether the key-in operation has been performed by the transmission key 21I.

20 If so at step A4, control passes to step A5, where a transmission process to be described later in more detail is performed and the process is terminated.

 If not at step A4, control passes to step A6, where other key-in operations are performed and the process is terminated.

25 A montage creation process by keys among the other key-in operations at step A6 will be described with reference to a flowchart of FIG. 8. This process is started on the basis of a key-in operation by the montage creation key 21C at the keyboard of FIG. 2. Before this operation, the user's montage creation mode or the DB data/montage creation mode is beforehand designated by the operation of the F key 21B to thereby select any one of the user's montage data register 62 or DB registers 63-1, 63-2, 63-3, ... of the FIG. 6 RAM and its corresponding montage area is used.

35 First, at step M1 of the FIG. 8 flowchart, "contour", "hair", "eyes", "nose", and "mouth" part patterns shown by

This is the replacement sheet

Date: 2 9 SEP 1996

No. 1 in the FIG. 3 ROM are selected as a basic type and the "contour" is then set initially as a changeable part. At step M2 a montage synthesis process to be described later in more detail is performed. At step M3 the
5 resulting montage is displayed on the display 7 through the FIG. 1 display driver 6 on the basis of the processed montage data. Thus, at the beginning, the montage composed of the basic part patterns No. 1 is displayed and the "contour" of the montage is displayed "going-on-off or
10 inverted as a change starting part.

At step M4 it is determined whether the triangular select key 22A or 22B is operated for inputting purposes at the selection unit 22 of the FIG. 2 keyboard. If not, it is determined at step M6 whether the cursor key 22C or 22D
15 at the keyboard select unit 22 of FIG. 2 is operated for inputting purposes. If not at step M6, it is determined at step M8 whether the cursor key 22E or 22F is operated for inputting purposes at the selection unit 22 of the FIG. 2 keyboard. If not, it is determined at step M10 whether the
20 record key is operated for inputting purposes and control returns to step M4 to iterate the determination of the key- in operations at steps M4-M8.

If the selection key 22A or 22B is operated for inputting purposes at step M4, control passes to step M5,
25 where the set basic type is changed and then control returns to step M2 for montage synthesis. Thus, the basic patterns now in display are changed and displayed. At this time, if
the upward triangular select key 22A is operated for
30 inputting purposes, the basic part pattern number of the montage displayed at present is changed to a basic part pattern number larger by one than the former one. If the downward triangular selection key 22B is operated for
inputting purposes, the basic part pattern number of the
35 montage displayed at present is changed to a basic part pattern number smaller by one than the former one.

When the upward or downward arrowed cursor key 22C or

This is the replacement sheet

Date: - 9 SEP 1996

22D is operated for inputting purposes at step M6, control passes to step M7, where the kind of the part is changed and control returns to step M2 for montage synthesis process. Thus, one of the "contour", "hair", "eyes",
5 "nose" and "mouth" which are the kinds of the parts of the basic part patterns displayed at present is displayed, for example, in a going-on-off manner on the display screen. Each time the upward arrowed cursor key 22C is operated for inputting purposes at this time, the montage displayed at
10 present moves in a going-on-off manner sequentially in the sequence of "mouth"→"nose"→"eyes"→"hair"→"contour"→"mouth". If the downward arrowed cursor key 22D is operated for inputting purposes, the part of the montage displayed at present changes to another in a going on-off manner
15 sequentially in the sequence of "contour"→"hair"→"eyes"→"nose"→"mouth"→"contour" each time that key is operated for inputting purposes.

If it is determined at step M8 that the leftward or rightward arrowed cursor key 22E or 22F has been operated
20 for inputting purposes control passes to step M9, where the pattern of the part is changed and control then returns to step M2 for montage synthesis. Thus, that of the currently displayed basic part patterns and displayed in a going-on-off manner is changed in accordance with the key-
25 in operation. At this time, if the leftward arrowed cursor key 22E is operated for inputting purposes, the part of the montage displayed at present in the going-on-off manner changes to another sequentially in the sequence of the No.
50 part → the No. 49 part... → the No. 3 part → the No. 2
30 part → the No. 1 part → the No. 50 part.

If the rightward arrowed cursor key 22F has been operated for inputting purposes, the part of the montage displayed at present in the going-on-off manner changes to another sequentially in the sequence of the No. 1 part→the
35 No. 2 part→ the No. 3 part →... →the No. 50 part → the No. 1 part each time the key 22F is operated.

If the record key is operated for inputting purposes

This is the replacement sheet

Date: 9 SEP 1996

at step M10, control passes to step M11, where the kind of the part is changed. A montage is then synthesized at step M2, the data on the montage displayed at step M3 is recorded in a predetermined montage data area and the process is terminated.

Subsequently, the montage synthesis at step M2 will be described with reference to a flowchart of FIG. 9.

First, at step D1 the "contour" No. (a basic part pattern No. of the "contour" part 3A-1 of FIG. 3) set in the predetermined montage area is read. Data on the "contour" part 3A-1 indicated by the read basic part pattern number is read from the first storage area 3A in ROM 3 and stored in a predetermined area in the synthesis RAM 5.

Then at step D3 a "hair" No. (the basic part pattern No. of the "hair" part 3A-2 of FIG. 3) is read. At step D4 and data on a "hair" part 3A-2 indicated by the read basic part pattern number is read from the first storage area 3A in ROM 3, and stored in a predetermined area in the synthesis RAM 5.

Then at step D5 the "eyes", "nose", and "mouth" basic part pattern Nos. are read and data items on the "eyes", "nose", and "mouth" part patterns 3A-3, 3A-4, and 3A-5 indicated by the corresponding read basic part pattern numbers Nos. are read from the first storage area 3A in ROM 3, and stored in predetermined areas in the synthesis RAM 5. Thus, a montage image created in the synthesis RAM 5 is displayed on the display 7 of FIG. 1 at step D6.

Key-in processes of the other key-in processes at step A6 of FIG. 7 other than the montage creation will be described with reference to the flowcharts of FIGS. 10 and 11 which are connected to each other at (1) and (2) of FIGS. 10 and 11.

At step A7 it is determined whether the M key 21A is operated for inputting purposes. If so, it is determined at step A8 whether the value (flag) of the flag register n is "0". If so, control passes to step A9, where "1" is set

This is the replacement sheet

Date: 2 9 SEP 1996

in the flag register n to terminate the process. If the flag register is "1", control passes to step A10, where the "0" is set in the flag register n to terminate the process. Thus, each time the M key 21A is operated for inputting purposes, the flag of the flag register n is switched alternately between "0" and "1", so that the operation mode is switched alternately between the normal mode and the data creation mode.

5 If the M key 21A is not operated at step A7, control passes to A11, where it is determined whether the F key 21B is operated for inputting purposes. If so, control passes to step A12, where the flag of the flag register n is referred to, thereby determining whether the F key 21B is operated in the data creation mode.

10 If the flag of the flag register n is "1" at step A12, it is determined that the F key 21B is operated for inputting purposes in the data creation mode. In this case, control passes to step A13, where it is determined whether the flag of the flag register f is "0". If so, control passes to step A14, where "1" is set in the flag register f to terminate the process. If the flag of the flag register is "1" at step A13, control passes to step A15, where "0" is set in the flag register f to terminate the process. Thus, the flag of the flag register f is switched alternately between "0" and "1" each time the F key 21B is operated for inputting purposes in the data creation mode. Thus, the user's/other party's mode is switched alternately between the DB data montage creation mode and the user's montage creation mode.

20 If the flag of the flag register n is "0" at step A12, it is determined that the F key 21B is operated in the normal mode to thereby terminate the process at once. Thus, in the normal mode, the key-in operation of the F key 21B is ignored.

25 If the key-in operation of the F key 21B is not performed at step A11, control passes to step A16, where it is determined whether the montage creation key 21C is

This is the replacement sheet

Date: 9 SEP 1996

operated for inputting purposes. If so, control passes to step A17, where the flag of the flag register n is referred to, thereby determining whether the montage creation key 21C is operated in the data creation mode.

5 If the flag of the flag register n is "1" at step A17, it is determined that the montage creation key 21C is operated in the data creation mode. In this case, at step A18 the flag of the flag register f is referred to, thereby determining which of the user's and other party's modes is

10 set.
If the flag of the flag register f is "0", it is determined that the DB data montage creation mode is set now. In this case, control passes to step A19, where the DB data is input and the DB montage creation described in the flowchart of FIG. 8 is performed to thereby terminate

15 the process.
If the flag is "1" at step A18, it is determined that the user's montage creation mode is set. In this case, control passes to step A20, where the user's montage creation described with reference to the FIG. 8 flowchart is performed and process is terminated.

20 Thus, for example, as shown in FIG. 14A, selected "contour", "hair", "nose", "eyes", and "mouth" parts having basic part pattern Nos. "2", "3", "1", "1" and "2", respectively, and a user's montage synthesized from those

25 parts in the user's montage creation mode of the user's device are recorded in the user's montage data register 62 of FIG. 6. In the other party's device which, for example, a girl has, selected "contour", "hair", "nose", "eyes", and

30 "mouth" parts having basic part pattern Nos. "1", "2", "2", "2" and "1", respectively, and a girl's montage synthesized from those parts are recorded in a girl's montage data register such as 62, as shown in FIG. 14B.

35 If the flag of the flag register n is "0" in the determination at step A17, the process is terminated at once. Thus, the key-in operation of the montage creation key 21C performed in the normal mode is ignored.

This is the replacement sheet

Date: 7 9 SEP 1996

If no montage creation key 21C is determined to be operated at step A16, control passes to step A21, where it is determined whether the "OK" key 21G is operated for inputting purposes. If so, control passes to step A22, where the flag of the flag register 1 is referred to, thereby determining whether the "OK" key 21G is operated in the transmission/reception mode during transmission of the response data.

If the flag of the flag register 1 is "1", it is determined that it is now in a response data transmission interval after question data is received from the other party to be described later. Thus, control passes to step A23, where response data "OK" is set in the display register 61 and also is displayed on the display 7.

If at step A22 the flag of the flag register 1 is "0", the process is terminated at once. Thus, the key-in operation of the "OK" key 21G is ignored except in the response data transmission interval.

If at step A21 the key-in operation of "OK" key 21G is not performed, control passes to step A24, where it is determined whether the "NO" key 21H is operated for inputting purposes. If so, control passes to step A25, where the flag of the flag register 1 is referred to, thereby determining whether the "NO" key 21H is operated in the transmission/reception mode during the response data transmission interval.

If the flag of the flag register 1 is "1", it is determined whether it is now in the response data transmission interval and control passes to step A26, where "NO" data is set and "NO" is displayed on the display 7.

If at step A25 the flag of the flag register 1 is "0", the process is terminated at once. Thus, the key-in operation of the "NO" key 21H is ignored except in the response data transmission interval.

If at step A24 the key-in operation of the "NO" key 21H is not performed, control passes to step A27, where it is determined whether any one of Q1 key 21D, Q2 key 21E and

Q3 key 21F is operated for inputting purposes. If so, control passes to step A28, where the flag of the flag register 1 is referred to, thereby determining whether the key-in operation of that key is performed in the question data transmission interval.

If the flag of the flag register 1 is "0", it is determined that it is now in the question data transmission interval. Control then passes to step A29, where, as shown in FIG. 5, "Let's play ?" data, "Please tell me an answer to our assignment ?" data, and "forgive me" data are displayed on the display register 61 when the Q1 key 21D, Q2 key 21E, and Q3 key 21F, respectively, are operated for inputting purposes.

If at step 28 the flag of the flag register 1 is "1", the process is terminated at once. Thus, the key-in operation of the Q1 key 21D, Q2 key 21E or Q3 key 21F is ignored except in the question data transmission interval.

The transmission at step A5 of FIG. 7 for transmission of the montage, question or response data, set as mentioned above, will be described with reference to the flowchart of FIG. 12. First, at step A30 it is determined whether the flag of the flag register 1 is "0". If so, it is determined that it is now in the question data transmission interval. Control then passes to step A31, where specified code data corresponding to the question data set in the display register 61 by the Q1 key 21D, Q2 key 21E or Q3 key 21F and displayed on the display 7 is read from ROM 3. If, for example, the question sentence "Let's play ?" is displayed by the operation of the Q1 key 21D, a specified code X is read from a third storage area 3C-1 of ROM 3. If "Please tell me an answer to our assignment ?" or "Please forgive me ?" has been displayed by the operation of the Q2 key 21E or Q3 key 21F, a specified code Y or Z is read. The read specified code is transmitted along with corresponding number data stored in the user's montage data register 62.

The sent specified code and montage number data are

This is the replacement sheet
This is the

Date: 7 9 SEP 1996

processed by a reception process to be described later and displayed as a question sentence and a montage on the display of the other party.

5 If at step A30 the flag of the flag register 1 is "1", it is determined that it is now in the response data transmission interval. Thus, control passes to step A32, where a specified code S or T corresponding to a response sentence set and displayed by the "OK" key 21G or the "NO" key 21H is read from the third storage area 3C-4 or 3C-5.
10 Data in one of the storage areas 3C-6 to 3C-11 is read depending on the answer to that of the question sentences for which the "OK" key 21G or "NO" key 21H is operated, and sent along with its number data stored in the user's montage data register 62.

15 If at step A30 the flag of the flag register 1 is "1", it is determined that it is now in the response data transmission interval. Thus, control passes to step A32, where a specified code for the response data set by the "OK" 21G or "NO" key 21H and displayed on the display 7 is
20 sent along with the user's montage data.

Subsequent to step A32, control passes to step A33, where the flag of the flag register 1 is set at "0" to thereby set the end of the response interval.

25 Subsequently, the reception process at step A2 of FIG. 7 performed when the sent data is received will be described with reference to the flowchart of FIG. 13.

First, at step A34 it is determined whether the flag of the flag register 1 is "0". If so, it is determined that it is now in the reception interval in the
30 transmission/reception mode. Thus, control passes to step A35, where it is determined whether the received data is a specified code for the question data. If so, control passes to step A36, where the storage area where the specified code received from one of the third storage areas
35 3C-1, 3C-2 and 3C-3 of ROM 3 is stored is retrieved and the question sentence data stored in that area is displayed on the display 7. Pattern data is read from the first storage

area 3A on the basis of the number data for the received montage data and displayed on the display 7.

Subsequently, at step A37 the flag of the flag register 1 is set at "1" to thereby terminate the process. Thus, a transmission interval for the response data to the received question data is set.

When at step A35 the received specified code data is determined to be not for a specified code corresponding to the question data, control passes to step A38, where it is determined whether the received data is for a specified code corresponding to the response sentence. If so, control passes to step A39, where response characters for the corresponding response sentence data are read from the storage area 3C-4 or 3C-5 and displayed on the display 7, and number data on the "eyes" part 3A-3 and "mouth" part 3A-5 of the received montage number data are converted to "eyes" expression change pattern data and "mouth" expression change pattern data corresponding to the changed data received at the same time, and displayed on the display 7.

Subsequent to step A39, the ending process is performed at step A40 to terminate the process. This process involves display of the received response data for a predetermined interval of time and then erasure of the display.

By the above processing, for example, as shown in FIG. 15A, "Let's play" data is selected by the Q1 key 21-4 in the user's device and subsequent operation of the transmission key 21I is performed, the specified code X is sent along with the number data of the user's montage data of FIG. 14A to the other party's device. By the reception process in the other party's device, the sentence "Let's play" and the montage are displayed on the display of the other party's device. As shown in FIG. 15C, when the data "Please tell me an answer to our assignment?" is set by the Q2 key 21-5, and transmission key 21I is operated in the other party's device, the specified code Y in the

This is the replacement sheet

Date: 9 SEP 1996

storage area 3C-1 of FIG. 5 is sent along with the other party's montage data to the user's device, so that by the reception process the "Please tell me an answer to our assignment ?" and the other party's montage are displayed on the user's display 7.

When the "OK" key 21G or "NO" key 21H is operated to set response data and the transmission key is operated in the state where the question sentence from the other party and the other party's montage are displayed on the display 7, the specified code corresponding to the response data and the user's montage data are sent.

For example, as shown by F in FIG. 15, the user's montage data of FIG. 14A is sent by his device to the other party's device along with the specified code S for the "OK" data set by the "OK" key 21G as a response to the reception of the "Please tell me an answer to our assignment" data. By the reception process in the other party device, "OK" and the user's montage are displayed on the display of the other party's device. In this case, since the response "OK" to the question "Please tell me an answer to our assignment" is received, change data stored in the area 3C-8 of FIG. 5 is read and the expressions of "eyes" and "mouth" of the montage the data of which is received are replaced with the read change data to a delightful montage expression on the display. For example, as shown by C in FIG. 15, when a specified code T corresponding to "NO" set by the "NO" key of the other party device as a response to receipt of the "Let's play" data is sent along with the girl's montage data, "NO" and a montage having a "sad" expression change pattern of FIG. 4B are displayed on the user's display 7, as shown by D in FIG. 15.

As described above, in the present embodiment, even if no conversation sentence data itself is sent by radio, satisfactory communication is achieved. Data on an image such as a montage is sendable or the contents of the image are changeable in accordance with the contents of the conversation sentences so that the user can inform the

This is the replacement sheet

Date: 7 9 SEP 1996

other party of his feeling by using his image.

While in the present embodiment one of three kinds of questions is illustrated as being selected or designated, the number of questions selectable is not limited to three.

- 5 More kinds of questions may be prepared such that any one of them can be selected by a key. While one of the two kinds of responses is illustrated as being selected or designated, three or more kinds of responses may be prepared such that any one of them may be selected. While
- 10 the receiving end converts the "eyes" and "mouth" part patterns to other part patterns depending on the kind of the responses, the sending end may change the "eyes" and "mouth" part pattern data to other part pattern data depending on the kinds of the response and then send the
- 15 changed data to the receiving end.

This is the replacement sheet

Date: 4 9 SEP 1996

CLAIMS:

1. A radio communication device which sends and/or receives data to and/or from the other party's radio communication device, comprising:

5 conversation sentence data storage means (3C) for storing a plurality of conversation sentence data items; conversation sentence selecting means (Q1, Q2, Q3, 21G, 21H) for selecting one of the plurality of conversation sentence data items stored in said conversation data storage means;

10 sending means (8) for sending to the other party's radio communication device radio data corresponding to the conversation sentence data selected by said conversation sentence selecting means;

15 receiving means (8) for receiving radio data from the other party's radio communication device; determining means (X, Y, Z, S, T) for determining which of the conversation data items of the plurality stored in said conversation sentence data storing means the radio data received by said receiving means corresponds to; and

20 display means (7) for displaying conversation sentence data corresponding to the received data determined by said determining means.

25 2. A radio communication device according to claim 1, wherein said conversation sentence selecting means comprises operation keys (Q1, Q2, Q3, 21G, 21H) provided for the respective conversation sentence data items of the plurality to select one of the conversation sentence data items.

30 3. A radio communication device according to claim 1, wherein said sending means and said receiving means comprises an infrared data sending circuit and an infrared receiving circuit, respectively.

35 4. A radio communication device according to claim 1, further comprising image data storage means (3A, 3B, 62) for storing image data, and image data transmission control

This is the replacement sheet

Date: 9 SEP 1996



* C L M S *

means (A31, A32 in FIG. 12) for sending image data stored in said image data storage means from said sending means.

5. A radio communication device according to claim 5, wherein said image data storage means comprises part
5 pattern data storage means (3A) for storing a plurality of data items on the patterns of parts of a face of a montage, and image data selecting means (22A-22F) for selecting any
10 part pattern data item of a plurality of part pattern data items stored in said part pattern data storage means to obtain image data on the montage.

6. A radio communication device according to claim 1, wherein the plurality of conversation sentence data stored in said conversation sentence data storage means comprises
15 question conversation data and response conversation data to the question conversation data.



* C L M S *

This is the replacement sheet

Date: 9 SEP 1996

ABSTRACT: (FIG. 1)

"RADIO COMMUNICATION DEVICES"

5 Data on various conversation sentences are
sent/received by radio between radio communication devices
remote from one another. Many conversation sentence data
items and different code data items are beforehand stored
in corresponding relationship in a conversation sentence
data storage ROM 3. When one of the conversation sentence
data items is selected by operation of a select switch, a
10 corresponding code data item is sent to a receiving end,
which is provided with a ROM having the same contents of
storage as the ROM 3. A conversation sentence is read from
the ROM in accordance with the received code data and
displayed on a display 7.

15

This is the replacement sheet

Date: 9 SEP 1996




FIG.1

This is the replacement sheet

Date: 9 SEP 1996




FIG.2

This is the replacement sheet

Date: 9 SEP 1996

BASIC PART PATTERNS IN ROM

PART	NO.						
		1	2	3			50
3A-1 →	CONTOUR	U	U	U			U
3A-2 →	HAIR STYLE						
3A-3 →	EYES						
3A-4 →	NOSE						
3A-5 →	MOUTH						

FIG.3

This is the replacement sheet

Date: 9 SEP 1996

EXPRESSION CHANGE PATTERNS IN ROM

FIG.4A

		1	2	3	
3B-1A	EYES				
3B-2A	MOUTH				

FIG.4B

		1	2	3	
3B-1B	EYES				
3B-2B	MOUTH				

FIG.4C

		1	2	3	
3B-1C	EYES				
3B-2C	MOUTH				

This is the replacement sheet

Date: 9 SEP 1996

	3C-1	3C-2	3C-8	3C-6	3C-7
X	Let's play ?			HAPPY	SAD
Y	Please tell me an answer to our assignment ?			HAPPY	ANGRY 3C-9
Z	Please forgive me ?			BASIC	BASIC 3C-11
S	OK !				3C-10
T	NO !				
	3C-5	3C-4	3C-3		

FIG.5

This is the replacement sheet

Date:

9 SEP 1996

61

DISPLAY REGISTER										
n	f	l	USER'S MONTAGE DATA							
			62							
			NAME	TEL	ADDRESS	CON-TOUR	HAIR	EYES	NOSE	MOUTH
			TARO YAMADA		..., TOKYO	1	2	3	2	1

63-1

63-2

63-3

FIG.6

This is the replacement sheet

Date: 9 SEP 1996




FIG.7




FIG.8

This is the replacement sheet

Date: 9 SEP 1996

9/15




FIG.9

This is the replacement sheet

Date: 9 SEP 1996




FIG.10

This is the replacement sheet

Date: 20 SEP 1996




FIG.11

This is the replacement sheet

Date: - 9 SEP 1996




FIG.12




FIG.13

14/15

(USER'S MONTAGE)

CONTOUR	HAIR	NOSE	EYES	MOUTH
NO.2	NO.3	NO.1	NO.1	NO.2



FIG.14A

(THE OTHER'S
MONTAGE DATA)

CONTOUR	HAIR	NOSE	EYES	MOUTH
NO.1	NO.2	NO.2	NO.2	NO.1



FIG.14B

This is the replacement sheet

Date: 7-9 SEP 1996




FIG.15

This is the replacement sheet

Date: 9 SEP 1996