

Improvements in or relating to Coded
Information Arrangements

5 The present invention relates to coded information arrangements. The arrangement may be similar to those disclosed in our co-pending Application No. 81/15288, published under No. G.B. 2077556.

10 The present invention seeks to provide an improved coded information arrangement.

15 According to the present invention there is provided an active device having first and second input circuits, a frequency division circuit connected to the first input circuit, a memory for storing and supplying coded information, further data supply means and a transmitter arranged to transmit an output signal including said coded information and said further data, the second input circuit being connected to a clock
20 input of the memory, wherein an output of the frequency division circuit is connected to a coding input of the memory.

25 Preferably the output is from an intermediate part of the frequency division circuit.

30 The device may comprise signal input means and a memory protection circuit for preventing undesired changing of the coded information stored in the memory wherein when it is desired to change the stored information a predetermined series of pulses must be applied via the signal input means to the memory protection circuit and wherein the memory protection circuit includes means for comparing both the number and the timing of pulses
35 actually applied to the input means with the number and

the timing of the predetermined series. The device may comprise further signal input means connected to signal processing circuitry which, upon the applications of a signal to said further input means, automatically
 5 supplies the memory protection circuit with said predetermined series of pulses.

The predetermined series of pulses may define a corresponding series of windows during which the actual
 10 pulses must occur, and the memory protection circuit may include means for checking that no pulses occur between the windows, and/or means for checking that at least one pulse appears in each window, and/or means for checking that no more than one pulse appears in
 15 each window.

The device may comprise frequency division circuitry, the division ratio of which is adjustable.

In one preferred embodiment, the active device comprises a memory for storing information, transmitter means for transmitting an output signal including said information, a battery, and means for detecting when the battery voltage falls below a predetermined level,
 20 the battery voltage detecting means being arranged to modify said output signal when the battery voltage falls below said predetermined level. The detecting means may be arranged to alter the value of a single bit in the output signal. Alternatively the detecting
 25 means may be used to convert the output signal to a signal of constant value. In a preferred arrangement there are two battery-voltage detecting means, a first of which alters the value of a single bit in the output signal when the voltage falls below a first
 30 predetermined level, and the second of which converts
 35

3
the output signal to a constant data value when the voltage falls below a second predetermined level which is itself below said first predetermined level.

5 In another preferred embodiment, the active device comprises means for receiving an input signal including coded information from a programming unit, a memory comprising means for storing said information, and means for directly receiving further information
10 independently of said programming unit. Said further information may comprise one or more bits, each indicating an "on/off" or, "yes/no" condition, for example the output of an alarm device. Alternatively or in addition, the further information may comprise
15 digital values representing one or more variable parameters.

The device according to the present invention is preferably an active transponder device which may
20 comprise first signal input means, second signal input means and an output which, in response to signals received by said first input means, transmits output signals including the coded information stored in the memory. When storing information in the memory of the
25 device, coded signals containing said information are supplied to said second input means. Uncoded signals are supplied to said first input means simultaneously with the coded signals being supplied to said second input means. Said uncoded signals may be regular pulse
30 train and said coded signals may be irregular coding pulses and the bits of information successively stored in the memory may correspond to successive values derived from within the transponder device of said uncoded signal when a coding pulse is supplied to said
35 input means.

Coded information is preferably supplied to the memory of the active device by means of a programming unit. The memory preferably comprises at least two groups of bits of information and the coded information is supplied to only one of said groups, the information in the remaining group(s) remaining unaltered. To prevent undesired changing of the information stored in the



memory of an active device by a programming unit, the contents of a part of said memory are read by the programming unit and the unit then determines whether it is allowed to change said information.

Where the device is an active transponder it may comprise a first circuit for supplying regular pulse trains and a second circuit for supplying spaced pulses, the first and second circuits having a single input for receiving modulated signals, and the second circuit being connected to the input via a demodulator. The demodulator may be an amplitude, phase or frequency demodulator. The spaced pulses may be programming clock pulses.

A coded information detecting system may comprise:

- (i) a plurality of active transponder devices according to the present invention, each comprising a receiver, and a transmitter for transmitting in response to an input signal received by the receiver an output signal including said coded information and said further information,
- (ii) an interrogator unit which is arranged to provide said input signal and detect said output signal, and which includes decoding means, and
- (iii) a polling unit which is arranged to supply said input signal from said interrogator unit successively to each one of a plurality of aerial units at separate sites, and to return any received output signal from a transponder to the interrogator unit, wherein the decoding means includes means for detecting whether an initial transponder output signal is received from an aerial unit and means responsive to said detecting means which, in the presence of a transponder output signal, allows the polling unit to supply the coded information from the memory of the transponder to the

interrogator unit and which, in the absence of a transponder output signal, instructs the polling unit to skip immediately to the next aerial unit.

A preferred embodiment of the present invention will now be described by way of example only with reference to the accompanying drawings of which:

Figure 1 shows a block diagram of a programmable coded tag in accordance with the present invention;

Figure 2 shows a block diagram of frequency division circuitry forming part of the tag of Figure 1;

Figure 3 shows a block diagram of memory protection circuitry forming part of the tag of Figure 1;

Figure 4 shows a block diagram of a modification of the tag;

Figure 5 shows an interrogator terminal unit for use in connection with coded tags; and

Figure 6 shows a modification of the input circuitry of the tag.

Referring now to Figure 1 there is shown the circuitry of a coded tag. Many components are the same as described in connection with Figure 1 of the above-mentioned co-pending application and thus will be described only briefly. 132 KHz signals are supplied from an interrogator unit to an input 21. In the absence of such signals, the input circuitry generates a reset signal R for the tag circuitry. The 132 KHz signals pass to a frequency translator (divide-by-two counter) 22 connected to an AND gate 23, the output of

which is connected to a transmitter output 24. The 132 KHz signals are also supplied to frequency division circuitry 134, which is shown in greater detail in Figure 2.

The circuit 134 comprises a divide-by-3 counter 135 and a divide-by-2 counter 136, the output of one of which is selected by a data selector 137 whose set-input is connected to a terminal 190. The output division selector is connected to a frequency division chain comprising divide-by-2 counters 138-141, the output of one of which is selected by a data selector 142. Selector 142 has two set inputs S_0 , S_1 and its output is connected to a further frequency division chain comprising divide-by-2 counters 143-146. The output W of one of the counters is supplied to the coding input of register 31.

Referring again to Figure 1, the signal from counter 146 constitutes the output of circuit 134 and is supplied to an index counter 33 and to one input of a half-bit (or HABIT) former 36, which is an exclusive-OR gate. The index counter comprises seven divide-by-two counters, six of which supply respective signals A1-A6 to inputs of a data selector 32 and the seventh of which, counter 331, supplies a signal A7 to memory protection circuitry 410.

The data selector 32 has a first data input D_L , a second data input D_B and N data inputs corresponding to a code stored in an N-bit memory register 31. Input D_L is strapped to the value logic '1' or logic '0' depending on whether it is required that the information arrangement is intended to detect the presence of programmable tags using the presence sensing system as described in Patent Application

The second input D_B is connected to the output of a battery voltage detector circuit 161 which is arranged to give a logic '1' signal when the battery voltage is low.

The output of (N+2)-bit data selector 32 is supplied to a first signal input of a 2-bit data selector 163. The input D_L is connected to the second signal input of a selector 163, and the output of a second battery voltage detector circuit 162 is connected to the selecting input. Detector 162 is arranged to select D_L when the battery voltage reaches a low level. The output of selector 163 is connected to the second input of the half-bit former 36. The output of half-bit former 36 is connected to the first input of an OR gate 91. The second input of OR gate 91 is connected to a terminal 90, which is preferably constituted by an external pin of the tag chip. The pin is normally down-bonded to the logic value '0' so that the OR gate 91 functions as a straight through connection from half-bit former 36 to the second input of AND gate 23. If terminal 90 is strapped to logic value '1', the tag behaves as an uncoded, presence-sensing device.

Clocking signals for the register 31 are supplied by a clock receiver input 41. Before being fed to the register, the clock signals pass through a memory protection circuit 410, which prevents accidental and/or unauthorised changes to the code held by the register.

Circuit 410 is shown in greater detail in Fig.3. Clock pulses from a programming unit (not shown) arrive at input 41 and are supplied to:

- (i) a first input of an AND gate 173;
- (ii) a first input of an AND gate 174;
- (iii) a first input of an AND gate 42; and
- (iv) a clock input of a 2-bit counter 178.

Connected to the second input of AND gate 173 is the output of a further AND gate 171. The inputs of gate 171 are signals derived from the frequency division circuitry 134. The output of AND circuit 171 is also supplied, via an inverter 172, to, the second input of AND gate 174.

The output of AND gate 173 is connected to the counting input of an M-bit counter 175. Counter 175 has all its outputs connected to an AND gate 177. It also has a reset input which is the output of an OR gate 176. A first input of OR gate 176 is the reset signal R from the input circuitry of the tag and a second input signal is the output of AND gate 174.

The output of AND gate 177 is connected to the D-input of a D-type flip-flop circuit 45. The clock input of circuit 45 receives the signal A_7 from counter 331 of the index counter, and its output is connected to the second input of AND gate 42. The output of AND gate 42 constitutes the clock input to register 31.

The output of inverter 172 is also supplied to the reset input of 2-bit counter 178. The counter has a blind first output Q_1 and a second output Q_2 which forms a further input signal for the OR gate 176 which resets counter 175. During the first phase of the programming sequence in which a new code is entered in register 31, a 132 KHz signal is supplied at 21 for a time corresponding to approximately two interrogation

cycles. This automatically produces L shift pulse windows. The programming unit, which includes means duplicating the frequency division circuitry of the tag, produces one clock or shift pulse within each of the shift pulse windows, and at the end of the first phase signal A7 attains the logic '1' level. This clocks flip-flop 45 which opens AND gate 42 of the memory protection circuitry to pass clock pulses to register 31.

During the second phase of the programming sequence, N shift pulses are applied to the register at intervals determined by the desired code. This phase is described in greater detail below. At the end of the second phase, the 132 KHz is removed which has the effect of resetting the circuitry of the tag, and in particular signal A7 and the memory protection circuit 410.

During the third phase of the programming sequence, two (or more) interrogation cycles are performed on the tag, the results are compared with the desired code, and if the entered code is correct a data valid signal is given by the programming unit.

Various aspects of the operation of the coded information arrangement described above will now be discussed in greater detail.

1. Battery Status Indication

Prevention of faulty operation of the tag due to run down of its battery will now be described. The first battery-voltage -detector 161 normally supplies a logic '0' signal to input D_B of data selector 32 (corresponding to bit 2 of the code of the tag). When the voltage of the battery falls below a first level the output of detector 161 changes to logic '1'. The

tag is still fully operational at this stage. When its code is read by the decoder of the interrogator, the presence of a logic '1' at bit 2 is used to activate means to indicate that the voltage of the battery is low and that it should be replaced.

If the battery voltage falls below a second level, which is itself below the first level, this is detected by the second battery-voltage-detector 162. The output of detector 162 changes and triggers data selector 163 so that instead of supplying coded signals to half-bit former 36 the selector supplies continuous '0s' or continuous '1s' to the transmitter 24 depending on the value of inputs D_L . Thus when the tag is interrogated it is immediately apparent that the battery has run-down.

An advantage of this arrangement is that degraded or incorrect coded information cannot be supplied to the interrogator for processing; this could occur if the circuitry of the tag was allowed to continue to function in its normal fashion as the battery ran down. The two-stage indication permits replacement of the battery before the tag stops working correctly. Of course, if desired, either of the stages could be used on its own.

2. Direct Programming

It may be arranged that some of the bits in the code may be directly programmed via external terminal pins of the tag itself, without the need for a programming unit. Such an arrangement is depicted in Fig.4 where there is direct parallel axis to the leading 8 bits of the code supplied to data selector 32 via terminal pins Bo-B7. For normal use, as described previously, pins Bo-B7 and select input 319 are 'down-bonded' so that

the first eight outputs Do-D7 from register 31 are supplied to selector 32 via data selectors 310-317. When the select input 319 for selectors 310-317 is made logic '1'. the signals, if any, from inputs Bo-B7 are supplied to selector 32. Signals at these inputs may represent the automatically updated values of parameters such as temperature, voltage, pressure etc., which may be converted to a digital word for direct inclusion in the code data stream when the tag is interrogated. Thus part of the coded information can be changed in real time. Alternatively one or more inputs may be used to indicate whether a particular parameter has exceeded a predetermined value, and may for example indicate an alarm condition. More than one select input 319 may be provided if desired.

As shown in Figure 4 the direct programming feature is combined with the battery-voltage indication feature; the latter feature, however, may be omitted.

3. Programming the Tag

In the arrangement disclosed in G.B. 2077556 the tag 20 was coded or programmed by a coded data stream from a separate programming unit. The coded signal was supplied to input 21 and was clocked into register 31 by signals supplied by a clock receiver input 41. In the arrangement according to the present invention an uncoded 132KHz signal is supplied to input 21 and to the programming unit.

The 132KHz signal is supplied to frequency division circuitry 134. An output from a counter inside circuitry 134 is used to supply data pulses W to the input of register 31.

As stated above the programming unit includes frequency

division means which corresponds to the circuitry of the tag, and which may be hardware or software. The data pulse W alternately has logic values '1' and '0'. If, when coding the tag, the next bit of the code to be encoded is logic '1', the unit supplies a clock or shift pulse to detector 41 only when the data pulse W has the value '1'. This arrangement has the advantage that the detector circuitry 29 of the earlier arrangement is not required. It is only necessary that a clock pulse occurs during the window defined by the interval that the data pulse W has the desired value. In addition great precision in the timing of the clock pulse is not required.

4. Memory Protection Circuitry

As disclosed in the above-mentioned co-pending application, coding of the tag is preceded by an interval corresponding preferably to two full interrogation transmission times. During this interval, it is checked that the correct number of clock pulses arrive at input 41. Only the total number of clock pulses is counted, however, and their timing is not checked. The way in which the memory protection circuit of the present invention functions will become apparent from the following description of programming the tag.

During the set-up interval before the tag is coded, L clock or shift pulses are applied via input 41 to a first input of AND gate 173. To the second input of gate 173 are applied pulses defining the windows in which the clock pulses must occur for programming to proceed. The shift pulse windows are defined by outputs taken from selected points of the frequency division circuitry. Since the frequency division circuitry is reproduced in the programming unit, the unit can supply the clock pulses precisely within the windows.

The output of AND gate 173 is supplied to the counting input of an M-bit counter 175 whose outputs are connected to AND gate 177. When the L pulses have been correctly counted, gate 177 supplies an output logic '1' to the input of D-type flip-flop 45.

The output of gate 171 is also supplied via an inverter 172 to a first input of AND gate 174, the output of which is connected to an OR gate 176 connected to the reset input of counter 175. The clock pulses from input 41 are supplied to the second input of gate 174. Thus should a clock pulse appear which is not simultaneous with a window pulse, counter 175 will be reset, flip-flop 45 will not be actuated and recoding of the tag will be prevented.

The output of inverter 172 is also supplied to a reset input of 2-bit counter 178. Thus at the end of each window pulse, counter 178 is reset to zero. The clock pulses are supplied to a count input of counter 178. If the correct clock-pulses are supplied, only one pulse will be supplied to counter 178 between each reset operation thereof, and logic '1' will appear only at the blind output Q_1 of the counter. If, on the other hand, two clock pulses are supplied between successive reset operations of the counter, a logic '1' will appear at output Q_2 of counter 178 which is connected to OR gate 176 to reset the counter 175. Thus should an incorrect extra clock pulse occur, counter 175 will reset and recoding of the tag will be prevented even if the extra clock pulse occurs along with a correct pulse within a 'window' set by the pulses from gate 171.

If no clock pulse appears at input 41 within the interval set by the window pulse, counter 175 will not

be actuated and thus will not be able to count up to the correct number of L pulses. Thus flip-flop 45 will not be actuated and recoding of the tag will be prevented.

Thus during the set-up period immediately preceding coding, the memory protection circuit of the present invention requires that clock pulses are supplied at the correct instant, that only one clock pulse is supplied at a time, and that no extra pulses are supplied between the correct instants.

During the set-up interval a 132KHz signal is applied to input 21 and thus after a time equivalent to two interrogation cycles, the end counter 331 of the index counter 33 gives a logic '1' output A7, which is supplied to the clock input of flip-flop 45. Providing flip-flop 45 has been actuated by counter 175 a logic '1' signal will be applied to a first input of AND gate 42. Subsequent clock pulses are supplied to the second input of AND gate 42 at points in time corresponding to the new code that it is desired to insert into register 31. When the code has been stored, the 132KHz signal is removed from input 21, which has the effect of applying a reset signal to all the counters in the frequency division chain (including counter 331), flip-flop 45 and OR gate 176. Thus signal A7 becomes logic '0' and AND gate 42 no longer passes clock pulses to the register 31. Two interrogation cycles are then effected, the signals transmitted by the tag are compared with the correct code, and if the information has been coded correctly, means on the programming unit is activated to indicate satisfactory coding and that the data is valid.

5. Selectable Division Ratio

The frequency division ratio of circuitry 134 (i.e. between frequency divider 22 and index counter 33) may be arranged to be selected to have one of a plurality of values. For example in an electrically noisy environment it may be required to have a slower bit rate, which corresponds to a higher division ratio. To this end data selectors 137 and 142 are provided.

A set input of selector 137 is coupled to a terminal 190 of the tag. Terminal 190 is preferably constituted by an external pin of the tag chip. The pin is preferably down-bonded that is it applies a logic signal '0' to select input X1 of selector 137. This connects divide-by-3 counter 135 into the frequency division circuitry. To change the division ratio terminal 190 may alternatively be connected to give a logic '1' signal which selects input X0 and divide-by-2 counter 136. Data selector has two set inputs S_1 , so corresponding to four counter inputs X0-X3. Inputs S_1 , S_0 are connected to respective terminal pins 192, 193 which are both preferably down-bonded to select input X1 and the output from divide-by-2 counter 140, thus excluding counter 141 from the frequency division chain. To select another counter input of selector 142 pin 192 and/or pin 193 are connected to give a logic '1' signal. With counter input X1 selected for both selectors 137, 142 a division ratio of 384 is achieved, that is the same as in the above-mentioned co-pending application.

6. Selective Coding

If desired, a part only of the register 31 may be coded during a programming cycle. Thus it may be arranged that a particular programming unit is only able to recode, say, the first 16 bits of information or

predetermined groups within the first 16 bits. The other (N-16) bits may be fixed at the stage of manufacture or may be coded and re-coded only by a master programming unit. It will be clear that there can be a hierarchy of programming units each with the authority to change the code of a different number of bits.

The presence of 'fixed' bits in the register permits recoding of the tag to be restricted to one particular user. Before recoding is permitted it may be arranged that the tag is interrogated and that the coded signal transmitted by the tag is checked by the programming unit to determine whether the user of that particular unit is authorised to recode that particular tag. If the user is not so authorised, recoding of the tag is prevented; this provides a further memory-protection feature.

7. Presence-sensing Role

Figure 5 indicates an arrangement in which a single interrogator circuit is used with a plurality of aerials. An interrogator circuit 210 is associated with a polling circuit 211 and a signal processor 212. The interrogator comprises a transmitter circuit 221, a receiver circuit 222, a decoder 223, a timing circuit 224 and an output circuit 225. The polling unit selectively connects the circuits 221, 222 to successive aerial pairs 231-234. Although only four sets are shown in practice a larger number of pairs may be used.

Unit 211 which may be under the control of processor 212, first connects aerial pair 231 to interrogate 210. Circuit 221 emits an interrogating pulse and circuit 222 receives the coded signal from any tag in the

region of the aerial pair. Thus if a tag is present, circuit 222 receives two bits in habit format, the first bit D_L indicating that a coded tag is present and the second bit D_B indicating the condition of the battery. If decoder 223 detects that these two bits have not been received by circuit 222 it causes the polling unit to immediately stop the interrogation cycle. The next aerial pair 232 is then connected to circuit 210 and the interrogation cycle recommenced.

Since the interrogation cycle takes a relatively long time, the provision of this skipping feature enables a large number of aerial pairs to be scanned by a single unit. The waste of time involved in interrogating empty sites is avoided.

8. Tag with single input

Although the tags described above and in the above mentioned co-pending application have separate interrogating and clocking inputs, these may be replaced by a single input as indicated in Fig.6. A demodulator 250 is connected to a convenient point of the input circuitry 21. The output of the demodulator is connected to point P, Fig.3 of the memory protection circuitry and the separate clocking input 41 is omitted.

The demodulator may be an amplitude demodulator, a phase demodulator or even a frequency demodulator providing the frequency shift is small enough so as not to upset the timings of the system. When it is desired to code the tag, suitable modulation of the 132KHz signals is provided.

The features 3 to 8 above may be used in any desired combination with one or both of the features 1 and 2.

35

Alternatively features 1 and/or 2 may be used with the rest of the coded information arrangement being as described in G.B. 2077556.

Claims

1. An active device having first and second input circuits, a frequency division circuit connected to the first input circuit, a memory for storing and supplying
5 coded information, further data supply means and a transmitter arranged to transmit an output signal including said coded information and said further data, the second input circuit being connected to a clock
10 input of the memory, wherein an output of the frequency division circuit is connected to a coding input of the memory.
2. An active device according to claim 1 wherein the
15 output is from an intermediate part of the frequency division circuit.
3. An active device according to claim 1 or 2 comprising a memory protection circuit for preventing
20 undesired changing of the coded information stored in the memory, the memory protection circuit being connected to the second input circuit, wherein, when it is desired to change the stored information, a predetermined series of pulses must be applied via the
25 second input circuit to the memory protection circuit and wherein the memory protection circuit includes means for comparing both the number and the timing of pulses actually applied to the second input circuit with the number and the timing of the predetermined
30 series.
4. An active device according to claim 2, wherein logic means of the memory protection circuit are connected to selected points of the frequency division
35 circuit whereby to determine said predetermined series.



5. An active device according to any preceding claim, wherein the division ratio of the frequency division circuit is adjustable.
- 5 6. An active device according to any preceding claim, wherein the first and second input circuits have a single input for receiving modulated signals, and the second input circuit is connected to the input via a demodulator.
- 10 7. An active device according to any preceding claim, wherein the outputs of the memory and further data supply means are connected to corresponding inputs of data selector means.
- 15 8. An active device according to claim 7, said further data supply means comprising one or more input connections connected to means for providing signals representing the updated values of one or more parameters, said values constituting said further data.
- 20 9. An active device according to claim 7 and 8 wherein said input connections are connected to respective inputs of said data selector means via respective further data selector means, said further data selector means also being connected to respective outputs of the memory, and select input means being provided for said further data selector means whereby said inputs of said first mentioned data selector means receive information either from said input connections or from said respective outputs of the memory.
- 25 10. An active device according to any preceding claim and comprising a battery, wherein said further data relates to the battery voltage level.
- 30 35



22

11. An active device according to claim 10 comprising means for detecting that the battery voltage has fallen below a predetermined level and altering a part of said further data.

5

12. An active device according to claim 11 comprising means for detecting that the battery voltage has fallen below a predetermined level and means, connected to said detecting means, for preventing coded information in the memory from being transmitted.

10

13. An active device according to any of claims 10 to 12 comprising first means for detecting that the battery voltage has fallen below a first predetermined level and second means for detecting that the battery voltage has fallen below a second predetermined level, said second level being lower than said first level.

15

14. An active device according to any preceding claim which constitutes a transponder.

20

15. An active device substantially as herein described with reference to the accompanying drawings.

16. A system comprising an active device as claimed in any preceding claim and a programming unit which comprises clock signal supply means and a frequency division means, the frequency division means controlling the timing of signals from the supply means to the second input circuit of the active device.

25

30

17. A system according to claim 16 wherein the frequency division means duplicates the frequency division circuit of the active device.



23

18. A coded information detecting system comprising:
(i) a plurality of active devices according to any of
claims 1 to 15, each comprising a receiver, and a
transmitter for transmitting in response to an input
5 signal received by the receiver an output signal
including the contents of the memory,
(ii) an interrogator unit which is arranged to provide
said input signal and detect said output signals, and
which includes decoding means, and
10 (iii) a polling unit which is arranged to supply said
input signal from said interrogator unit successively
to each one of a plurality of aerial units at separate
sites, and to return any received output signal from a
transponder to the interrogator unit, wherein the
15 decoding means includes means for detecting whether an
initial transponder output signal is received from an
aerial unit and means responsive to said detecting
means which, in the presence of a transponder output
signal, allows the polling unit to supply the coded
20 information from the memory of the transponder to the
interrogator unit and which, in the absence of a
transponder output signal, instructs the polling unit
to skip immediately to the next aerial unit.

25 19. A coded information detecting system substantially
as herein described with reference to the accompanying
drawings.

20. A method of supplying coded information to the
30 memory of an active device according to any preceding
claim, comprising supplying an uncoded signal to the
first input circuit and supplying signals to the second
input circuit at respective times when the signal at
said output of the frequency decision circuit has the
35 same logic value as the next bit of code to be encoded.



24

21. A method according to claim 20, wherein the uncoded signal is also supplied to a programming unit which supplies said signals to the second input circuit at said respective times.

5

22. A method according to claim 21 wherein the logic signal is derived in the active device from the first input circuit by frequency division, and the programming unit includes means duplicating the
10 frequency division means of the active device to determine said respective times.

23. A method of supplying coded information to the memory of an active device substantially as herein
15 described with reference to the accompanying drawings.
