

DESCRIPTION

Title of Invention: WIRELESS POWER TRANSMISSION DEVICE, HEAT GENERATION CONTROL METHOD FOR WIRELESS POWER TRANSMISSION DEVICE, AND PRODUCTION METHOD FOR WIRELESS POWER TRANSMISSION DEVICE

[Technical Field]

[0001]

The present invention relates to: a wireless power transmission apparatus in which heat generation is controllable; a thermal control method for the wireless power transmission apparatus; and a manufacturing method for the wireless power transmission apparatus.

[Background Art]

[0002]

Portable electronic devices such as laptop PCs, tablet PCs, digital cameras, mobile phones, portable gaming devices, earphone-type music players, wireless headsets, hearing aids, recorders, which are portable while being used by the user have rapidly increased in recent years. Many of these portable electronic devices have therein a rechargeable battery, which requires periodical charging. To facilitate the work for charging the rechargeable battery of an electronic device, there are an increasing number of devices for charging rechargeable batteries by using a power-supplying technology that performs wireless power transmission between a power-supplying device and a power-receiving device mounted in an electronic device (wireless

power transmission technology performing power transmission by varying the magnetic field).

[0003]

Examples of the wireless power transmission technology include a technology that performs power transmission by means of electromagnetic induction between coils (e.g. see Patent Literature 1), a technology that performs power transmission by magnetic field coupling utilizing a resonance phenomenon (magnetic field resonant state) between resonators (coils) provided to the power-supplying device and the power-receiving device (e.g. see Patent Literature 2).

[0004]

Further, a constant current/constant voltage charging system has been known as a system of charging a rechargeable battery (e.g., lithium ion secondary battery). However, when a lithium ion secondary battery is charged with the constant current/constant voltage charging system using a wireless power transmission apparatus that performs the above wireless power transmission, the load impedance value of a power-supplied device (the rechargeable battery, a stabilizer circuit, a charging circuit, and the like) including the rechargeable battery increases because the value of the current supplied to the rechargeable battery decreases when a transition from constant current charging to constant voltage charging occurs.

[0005]

With this, the input impedance of the entire wireless power transmission apparatus including the power-supplied device varies. In this regard, if it is possible to increase the amount of change in input impedance value of the wireless power transmission apparatus for a predetermined period of charging time in the constant voltage charging, the amount of change in the value of the current input to the wireless power transmission apparatus for the predetermined period of charging time can be increased. This prevents excessive input of power after the transition from the constant current charging to the constant voltage charging, thereby preventing excessive heat generation in the wireless power transmission apparatus. That is, to prevent the excessive heat generation in the wireless power transmission apparatus after the transition from the constant current charging to the constant voltage charging, it is required to make it possible to adjust a load change characteristic, which is represented by an amount of change in the input impedance value of the wireless power transmission apparatus for a predetermined period of charging time in the constant voltage charging.

[0006]

To make the load change characteristic adjustable, it is conceivable to provide an impedance matching box additionally.

[Citation List]

[Patent Literature]

[0007]

Patent Literature 1: Japanese Patent No. 4624768

Patent Literature 2: Japanese Unexamined Patent Publication No.
239769/2010

[Summary of Invention]

[Technical Problem]

[0008]

However, additionally providing such an impedance matching box causes an increase in the number of components, and is inconvenient in portable electronic devices for which portability, compactness, and cost-efficiency are required.

[0009]

In other words, it is desirable to adjust the load change characteristic without adding another member in a wireless power transmission apparatus (power-supplying device and power-receiving device).

[0010]

It is therefore an object of the present invention is to provide a thermal control method and the like which makes it possible to control heat generation in the wireless power transmission apparatus without a need of an additional device, by adjusting the load change characteristic, which is represented by an amount of change in the input impedance value of the wireless power transmission apparatus for a predetermined period of charging time after a transition from constant current charging to constant voltage charging.

[Solution to Problem]

[0011]

An aspect of the present invention to solve the problem above is a thermal control method for a wireless power transmission apparatus configured to supply power, by changing a magnetic field, from a power-supplying module to a power-receiving module connected to a power-supplied device including a secondary battery rechargeable using a constant current/constant voltage charging system, the method including adjusting a load change characteristic, which is represented by an amount of change in input impedance value of the wireless power transmission apparatus for a predetermined period of charging time in constant voltage charging, by adjusting a value of a coupling coefficient between coils each included in the power-supplying module or the power-receiving module.

[0012]

With the above method, in the case where the secondary battery rechargeable using the constant current/constant voltage charging system is charged with the wireless power transmission apparatus configured to supply power by changing a magnetic field, it is possible to adjust the load change characteristic, which is represented by an amount of change in the input impedance value of the wireless power transmission apparatus for a predetermined period of charging time after a transition from the constant current charging to the constant voltage charging, by changing

the value of a coupling coefficient between coils each included in the power-supplying module or the power-receiving module. As the load change characteristic is increased in this way, an amount of change in the input impedance value of the wireless power transmission apparatus for a predetermined period of charging time after the transition from the constant current charging to the constant voltage charging increases, which increases an amount of change in the value of the current input to the wireless power transmission apparatus for the predetermined period of charging time. The increase in the amount of change in the value of the current input to the wireless power transmission apparatus prevents excessive input of power after the transition from the constant current charging to the constant voltage charging, thereby preventing excessive heat generation in the wireless power transmission apparatus (the power-supplying module and the power-receiving module).

To the contrary, as the load change characteristic is decreased, an amount of change in the input impedance value of the wireless power transmission apparatus for a predetermined period of charging time after the transition from the constant current charging to the constant voltage charging decreases, which decreases an amount of change in the value of the current input to the wireless power transmission apparatus for the predetermined period of charging time. The decrease in the amount of change in the value of the current input to the wireless power

transmission apparatus prevents a rapid change in temperature of the wireless power transmission apparatus (the power-supplying module and the power-receiving module) in a short time after the transition from the constant current charging to the constant voltage charging.

[0013]

Another aspect of the present invention to solve the above problem is a thermal control method for a wireless power transmission apparatus, the wireless power transmission apparatus configured to supply power, by means of resonance phenomenon, from a power-supplying module having at least a power-supplying coil and a power-supplying resonator to a power-receiving module having at least a power-receiving resonator and a power-receiving coil, the power-receiving module being connected to a power-supplied device including a secondary battery rechargeable using a constant current/constant voltage charging system, the method including

adjusting a load change characteristic, which is represented by an amount of change in input impedance value of the wireless power transmission apparatus for a predetermined period of charging time in constant voltage charging, by adjusting at least one of coupling coefficients which are a coupling coefficient between the power-supplying coil and the power-supplying resonator, a coupling coefficient between the power-supplying resonator and the power-receiving resonator, and a coupling coefficient between

the power-receiving resonator and the power-receiving coil.

[0014]

With the above method, in the case where the secondary battery rechargeable using the constant current/constant voltage charging system is charged with the wireless power transmission apparatus configured to supply power by means of a resonance phenomenon, it is possible to adjust the load change characteristic, which is represented by an amount of change in input impedance value of the wireless power transmission apparatus for a predetermined period of charging time after the transition from the constant current charging to the constant voltage charging, by changing at least one of the coupling coefficients which are the coupling coefficient between the power-supplying coil and the power-supplying resonator, the coupling coefficient between the power-supplying resonator and the power-receiving resonator, and the coupling coefficient between the power-receiving resonator and the power-receiving coil.

As the load change characteristic is increased in this way, an amount of change in the input impedance value of the wireless power transmission apparatus for a predetermined period of charging time after the transition from the constant current charging to the constant voltage charging increases, which increases an amount of change in the value of the current input to the wireless power transmission apparatus for the predetermined period of

charging time. Such an increase in the amount of change in the value of the current input to the wireless power transmission apparatus prevents excessive input of power after the transition from the constant current charging to the constant voltage charging, and thereby it is possible to prevent excessive heat generation in the wireless power transmission apparatus (the power-supplying coil, the power-supplying resonator, the power-receiving resonator, and the power-receiving coil).

To the contrary, as the load change characteristic is decreased, an amount of change in the input impedance value of the wireless power transmission apparatus for a predetermined period of charging time after the transition from the constant current charging to the constant voltage charging decreases, which decreases an amount of change in the value of the current input to the wireless power transmission apparatus for the predetermined period of charging time. Such a decrease in the amount of change in the value of the current input to the wireless power transmission apparatus suppresses rapid variation, for a short time, in temperature of the wireless power transmission apparatus (the power-supplying coil, the power-supplying resonator, the power-receiving resonator, and the power-receiving coil) after the transition from the constant current charging to the constant voltage charging.

[0015]

According to another aspect of the invention to solve the above

problem, the above thermal control method is arranged such that the load change characteristic is increased by increasing the coupling coefficient between the power-supplying coil and the power-supplying resonator.

[0016]

With the above method, it is possible to increase the load change characteristic by increasing the coupling coefficient between the power-supplying coil and the power-supplying resonator.

[0017]

According to another aspect of the invention to solve the above problem, the above thermal control method is arranged such that the load change characteristic is increased by increasing the coupling coefficient between the power-receiving resonator and the power-receiving coil.

[0018]

With the above method, it is possible to increase the load change characteristic by increasing the coupling coefficient between the power-receiving resonator and the power-receiving coil.

[0019]

According to another aspect of the invention to solve the above problem, the above thermal control method is arranged such that the load change characteristic is increased by increasing the coupling coefficient between the power-supplying coil and the power-supplying resonator and the coupling coefficient between the power-receiving resonator and the power-receiving coil.

[0020]

With the above method, it is possible to increase the load change characteristic by increasing the coupling coefficient between the power-supplying coil and the power-supplying resonator and the coupling coefficient between the power-receiving resonator and the power-receiving coil.

[0021]

According to another aspect of the invention to solve the above problem, the above thermal control method is arranged such that the value of the coupling coefficient between the power-supplying coil and the power-supplying resonator is adjusted by changing a distance between the power-supplying coil and the power-supplying resonator, the value of the coupling coefficient between the power-supplying resonator and the power-receiving resonator is adjusted by changing a distance between the power-supplying resonator and the power-receiving resonator, and the value of the coupling coefficient between the power-receiving resonator and the power-receiving coil is adjusted by changing a distance between the power-receiving resonator and the power-receiving coil.

[0022]

With the above method, the value of the coupling coefficient between the power-supplying coil and the power-supplying resonator is adjusted by changing the distance between the power-supplying coil and the power-supplying resonator, the value

of the coupling coefficient between the power-supplying resonator and the power-receiving resonator is adjusted by changing the distance between the power-supplying resonator and the power-receiving resonator, and the value of the coupling coefficient between the power-receiving resonator and the power-receiving coil is adjusted by changing the distance between the power-receiving resonator and the power-receiving coil. Thus, by a simple operation of physically changing the distance between the power-supplying coil and the power-supplying resonator; the distance between the power-supplying resonator and the power-receiving resonator; and the distance between the power-receiving resonator and the power-receiving coil, it is possible to change the respective coupling coefficients between the corresponding coils. That is, by the simple operation of physically changing the distance between the power-supplying coil and the power-supplying resonator; the distance between the power-supplying resonator and the power-receiving resonator; and the distance between the power-receiving resonator and the power-receiving coil, it is possible to adjust the load change characteristic.

[0023]

According to another aspect of the invention to solve the above problem, the thermal control method further including setting variable parameters configuring the power-supplying module and the power-receiving module so that values of a transmission

characteristic relative to a driving frequency of power supplied to the power-supplying module have a double-hump characteristic having a peak in a lower driving frequency band which is lower than a resonance frequency of the power-supplying module and the power-receiving module, and a peak in a higher driving frequency band which is higher than the resonance frequency, thereby enabling control of a variation tendency of input impedance values of the wireless power transmission apparatus in the constant voltage charging, by adjusting the driving frequency.

[0024]

In the above method, the wireless power transmission apparatus is set to have the double-hump characteristic. With this, by adjusting the driving frequency of power supplied to the wireless power transmission apparatus thus set to have the double-hump characteristic, it is possible to set the variation tendency of the input impedance values of the wireless power transmission apparatus in the constant voltage charging and thus adjusting the variation tendency in the input current to the wireless power transmission apparatus, thereby controlling heat generation in the wireless power transmission apparatus.

[0025]

According to another aspect of the invention to solve the above problem, the thermal control method is arranged such that the driving frequency of the power supplied to the power-supplying module is set in a band corresponding to a peak value of the

transmission characteristic appearing in the lower driving frequency band lower than the resonance frequency of the power-supplying module and the power-receiving module, or in a band corresponding to a peak value of the transmission characteristic appearing in the higher driving frequency band higher than the resonance frequency of the power-supplying module and the power-receiving module, thereby making adjustment so that the input impedance values of the wireless power transmission apparatus in the constant voltage charging show an increasing tendency.

[0026]

With the above method, the driving frequency of the power supplied to the power-supplying module is set in the band corresponding to the peak value of the transmission characteristic appearing in the lower driving frequency band lower than the resonance frequency of the power-supplying module and the power-receiving module, or in the band corresponding to the peak value of the transmission characteristic appearing in the higher driving frequency band higher than the resonance frequency of the power-supplying module and the power-receiving module, and thereby adjustment is made so that the input impedance values of the wireless power transmission apparatus in the constant voltage charging show the increasing tendency. This reduces the input current to the wireless power transmission apparatus in the constant voltage charging, consequently reducing heat generation

in the wireless power transmission apparatus.

[0027]

According to another aspect of the invention to solve the above problem, the thermal control method is arranged such that the driving frequency of the power supplied to the power-supplying module is set in a band corresponding to a valley between peak values of the transmission characteristic respectively appearing in the lower drive frequency band and the higher frequency band which are respectively lower and higher than the resonance frequency of the power-supplying module and the power-receiving module, thereby making adjustment so that the input impedance values of the wireless power transmission apparatus in the constant voltage charging show a maintaining tendency or a decreasing tendency.

[0028]

With the above method, the driving frequency of the power supplied to the power-supplying module is set in the band corresponding to the valley between peak values of the transmission characteristic respectively appearing in the lower drive frequency band and the higher frequency band which are respectively lower and higher than the resonance frequency of the power-supplying module and the power-receiving module, and thereby adjustment is made so that the input impedance values of the wireless power transmission apparatus in the constant voltage charging show a maintaining tendency or a decreasing tendency.

This maintains or increases the input current to the wireless power transmission apparatus in the constant voltage charging.

[0029]

Another aspect of the present invention to solve the above problem is a wireless power transmission apparatus adjusted by the above-described thermal control method.

[0030]

With the above structure, it is possible to control heat generation in the wireless power transmission apparatus by adjusting the value of a coupling coefficient between coils each included in the power-supplying module or the power-receiving module. In other words, control of heat generation in the wireless power transmission apparatus is possible without a need of an additional component in the wireless power transmission apparatus.

[0031]

An aspect of the present invention to solve the problem above is a manufacturing method for a wireless power transmission apparatus configured to supply power, by changing a magnetic field, from a power-supplying module to a power-receiving module connected to a power-supplied device including a secondary battery rechargeable using a constant current/constant voltage charging system, the method including a process of adjusting a load change characteristic, which is represented by an amount of change in input impedance value of the wireless power transmission apparatus for a predetermined

period of charging time in constant voltage charging, by adjusting a value of a coupling coefficient between coils each included in the power-supplying module or the power-receiving module.

[0032]

With the above structure, it is possible to manufacture the wireless power transmission apparatus capable of controlling heat generation in the wireless power transmission apparatus by adjusting the value of a coupling coefficient between coils each included in the power-supplying module or the power-receiving module. In other words, it is possible to manufacture the wireless power transmission apparatus capable of controlling heat generation without a need of an additional component in the wireless power transmission apparatus.

[Advantageous Effects of Invention]

[0033]

There is provided a thermal control method and the like which makes it possible to control heat generation in a wireless power transmission apparatus without a need of an additional device, by adjusting a load change characteristic, which is represented by an amount of change in the value of the input impedance of the wireless power transmission apparatus for a predetermined period of charging time after a transition from constant current charging to constant voltage charging.

[Brief Description of Drawings]

[0034]

[FIG. 1] FIG. 1 is a schematic explanatory diagram of a wireless power transmission apparatus.

[FIG. 2] FIG. 2 is an explanatory diagram of an equivalent circuit of the wireless power transmission apparatus.

[FIG. 3] FIG. 3 is a graph indicating charging characteristics of a lithium ion secondary battery.

[FIG. 4] FIG. 4 is an explanatory diagram illustrating transmission characteristic "S21" varying as a function of a driving frequency.

[FIG. 5] FIG. 5 is a graph illustrating input impedance Z_{in} varying as a function of the driving frequency.

[FIG. 6] FIG. 6 is a graph showing measurement results related to Measurement Experiment 1-1.

[FIG. 7] FIG. 7 is a graph showing measurement results related to Measurement Experiment 1-2.

[FIG. 8] FIG. 8 is a graph showing measurement results related to Measurement Experiment 1-3.

[FIG. 9] FIG. 9 includes graphs respectively showing measurement results related to Measurement Experiments 2-1 and 2-2.

[FIG. 10] FIG. 10 includes graphs respectively showing measurement results related to Measurement Experiments 2-3 and 2-4.

[FIG. 11] FIG. 11 is a graph showing measurement results related to Measurement Experiment 2-5.

[FIG. 12] FIG. 12 shows measurement results for the surface

temperature of a power-supplying coil related to Measurement Experiment 2-5.

[FIG. 13] FIG. 13 is a graph showing a relation between the distance between coils and a coupling coefficient in wireless power transmission.

[FIG. 14] FIG. 14 is an explanatory diagram illustrating a manufacturing method of the wireless power transmission apparatus.

[FIG. 15] FIG. 15 is a flowchart explaining a method for designing a wireless headset and a charger, including the wireless power transmission apparatus.

[Description of Embodiments]

[0035]

(Embodiment)

The following describes embodiments of a wireless power transmission apparatus, a thermal control method for the wireless power transmission apparatus, and a manufacturing method for the wireless power transmission apparatus, which are related to the present invention. First, a wireless power transmission apparatus 1 used in the present embodiment is described.

[0036]

(Structure of Wireless Power Transmission Apparatus 1)

The wireless power transmission apparatus 1 includes: a power-supplying module 2 having a power-supplying coil 21 and a power-supplying resonator 22; and a power-receiving module 3 having a power-receiving coil 31 and a power-receiving resonator

32, as shown in FIG. 1. The power-supplying coil 21 of the power-supplying module 2 is connected to an AC power source 6 having an oscillation circuit configured to set the driving frequency of power supplied to the power-supplying module 2 to a predetermined value. The power-receiving coil 31 of the power-receiving module 3 is connected to a lithium ion secondary battery 9 via a stabilizer circuit 7 configured to rectify the AC power received, and via a charging circuit 8 configured to prevent overcharge. It should be noted that, in the present embodiment, the stabilizer circuit 7, the charging circuit 8, and the lithium ion secondary battery 9 correspond to a power-supplied device 10.

[0037]

The power-supplying coil 21 plays a role of supplying power obtained from the AC power source 6 to the power-supplying resonator 22 by means of electromagnetic induction. As shown in FIG. 2, the power-supplying coil 21 is constituted by an RLC circuit whose elements include a resistor R_1 , a coil L_1 , and a capacitor C_1 . The coil L_1 is formed by winding a copper wire material (coated by an insulation film) with its coil diameter set to 15 mm ϕ . The total impedance of a circuit element constituting the power-supplying coil 21 is Z_1 . In the present embodiment, the Z_1 is the total impedance of the RLC circuit (circuit element) constituting the power-supplying coil 21, which includes the resistor R_1 , the coil L_1 , and the capacitor C_1 . Further,

the current that flows in the power-supplying coil 21 is I_1 . The current I_1 is identical with an input current I_{in} input to the wireless power transmission apparatus 1.

[0038]

The power-receiving coil 31 plays roles of receiving the power having been transmitted as magnetic field energy from the power-supplying resonator 22 to the power-receiving resonator 32, by means of electromagnetic induction, and supplying the power received to the lithium ion secondary battery 9 via the stabilizer circuit 7 and the charging circuit 8. As shown in FIG. 2, the power-receiving coil 31, similarly to the power-supplying coil 21, is constituted by an RLC circuit whose elements include a resistor R_4 , a coil L_4 , and a capacitor C_4 . The coil L_4 is formed by winding a copper wire material (coated by an insulation film) with its coil diameter set to 11 mm ϕ . The total impedance of a circuit element constituting the power-receiving coil 31 is Z_4 . In the present embodiment, the Z_4 is the total impedance of the RLC circuit (circuit element) constituting the power-receiving coil 31, which includes the resistor R_4 , the coil L_4 , and the capacitor C_4 . The total impedance of the power-supplied device 10 connected to the power-receiving coil 31 is Z_L . Further, the current that flows in the power-receiving coil 31 is I_4 . While the total impedance of the power-supplied device 10 is Z_L , this may be substituted by R_L for the sake of convenience.

[0039]

As shown in FIG. 2, the power-supplying resonator 22 is constituted by an RLC circuit whose elements include a resistor R_2 , a coil L_2 , and a capacitor C_2 . Further, as shown in FIG. 2, the power-receiving resonator 32 is constituted by an RLC circuit whose elements include a resistor R_3 , a coil L_3 , and a capacitor C_3 . The power-supplying resonator 22 and the power-receiving resonator 32 each serves as a resonance circuit and plays a role of creating a magnetic field resonant state. The magnetic field resonant state (resonance phenomenon) here is a phenomenon in which two or more coils resonate with each other at a resonance frequency. The total impedance of a circuit element constituting the power-supplying resonator 22 is Z_2 . In the present embodiment, the Z_2 is the total impedance of the RLC circuit (circuit element) constituting the power-supplying resonator 22, which includes the resistor R_2 , the coil L_2 , and the capacitor C_2 . The total impedance of a circuit element constituting the power-receiving resonator 32 is Z_3 . In the present embodiment, the Z_3 is the total impedance of the RLC circuit (circuit element) constituting the power-receiving resonator 32, which includes the resistor R_3 , the coil L_3 , and the capacitor C_3 . The current flowing in the power-supplying resonator 22 is I_2 , whereas the current flowing in the power-receiving resonator 32 is I_3 .

[0040]

In the RLC circuit which is the resonance circuit in each of the power-supplying resonator 22 and the power-receiving resonator

32, the resonance frequency is f which is derived from (Formula 1) below, where the inductance is L and the capacity of capacitor is C . In the present embodiment, the resonance frequency of the power-supplying coil 21, the power-supplying resonator 22, the power-receiving coil 31, and the power-receiving resonator 32 is set to 970 kHz.

$$f = \frac{1}{2\pi\sqrt{LC}}$$

... (Formula 1)

[0041]

The power-supplying resonator 22 is a solenoid coil made of a copper wire material (coated by an insulation film) with its coil diameter being 15 mmφ. The power-receiving resonator 32 is a solenoid coil made of a copper wire material (coated by an insulation film) with its coil diameter being 11 mmφ. The resonance frequency of the power-supplying resonator 22 and that of the power-receiving resonator 32 are matched with each other. Each of the power-supplying resonator 22 and the power-receiving resonator 32 may be a spiral coil or a solenoid coil as long as it is a resonator using a coil.

[0042]

In regard to the above, the distance between the power-supplying coil 21 and the power-supplying resonator 22 is denoted as d_{12} , the distance between the power-supplying resonator 22 and the power-receiving resonator 32 is denoted as d_{23} , and the distance

between the power-receiving resonator 32 and the power-receiving coil 31 is denoted as d_{34} (see FIG. 1).

[0043]

Further, as shown in FIG. 2, a mutual inductance between the coil L_1 of the power-supplying coil 21 and the coil L_2 of the power-supplying resonator 22 is M_{12} , a mutual inductance between the coil L_2 of the power-supplying resonator 22 and the coil L_3 of the power-receiving resonator 32 is M_{23} , and a mutual inductance between the coil L_3 of the power-receiving resonator 32 and the coil L_4 of the power-receiving coil 31 is M_{34} . Further, in the wireless power transmission apparatus 1, a coupling coefficient between the coil L_1 and the coil L_2 is denoted as K_{12} , a coupling coefficient between the coil L_2 and the coil L_3 is denoted as K_{23} , a coupling coefficient between the coil L_3 and the coil L_4 is denoted as K_{34} .

[0044]

The resistance values, inductances, capacities of capacitors of R_1 , L_1 , and C_1 of the RLC circuit of the power-supplying coil 21, R_2 , L_2 , and C_2 of the RLC circuit of the power-supplying resonator 22, R_3 , L_3 , and C_3 of the RLC circuit of the power-receiving resonator 32, and R_4 , L_4 , and C_4 of the RLC circuit of the power-receiving coil 31, and the coupling coefficients K_{12} , K_{23} , and K_{34} are parameters variable at the stage of designing and manufacturing, and are preferably set so as to satisfy the relational expression of (Formula 4) which is described later.

[0045]

FIG. 1 shows at its bottom a circuit diagram of the wireless power transmission apparatus 1 (including the stabilizer circuit 7, the charging circuit 8, and the lithium ion secondary battery 9) having the structure as described above. In the figure, the entire wireless power transmission apparatus 1 is shown as a single input impedance Z_{in} . Further, the voltage applied to the wireless power transmission apparatus 1 is indicated as voltage V_{in} , and the current input to the wireless power transmission apparatus 1 is indicated as current I_{in} .

[0046]

To be more specific about the input impedance Z_{in} of the wireless power transmission apparatus 1, the structure of the wireless power transmission apparatus 1 is expressed in an equivalent circuit as shown in FIG. 2. Based on the equivalent circuit in FIG. 2, the input impedance Z_{in} of the wireless power transmission apparatus 1 is expressed as (Formula 2).

$$Z_{in} = Z_1 + \frac{(\omega M_{12})^2}{Z_2 + \frac{(\omega M_{23})^2}{Z_3 + \frac{(\omega M_{34})^2}{Z_4 + Z_L}}}$$

$$M_{12} = k_{12} \sqrt{L_1 L_2} \quad M_{23} = k_{23} \sqrt{L_2 L_3} \quad M_{34} = k_{34} \sqrt{L_3 L_4}$$

k_{ij} is a coupling coefficient between L_i and L_j

... (Formula 2)

[0047]

Further, the impedances Z_1 , Z_2 , Z_3 , Z_4 , and Z_L of the power-supplying coil 21, the power-supplying resonator 22, the power-receiving resonator 32, and the power-receiving coil 31 in the wireless power transmission apparatus 1 of the present embodiment are expressed as (Formula 3).

$$Z_1 = R_1 + j \left(\omega L_1 - \frac{1}{\omega C_1} \right)$$

$$Z_2 = R_2 + j \left(\omega L_2 - \frac{1}{\omega C_2} \right)$$

$$Z_3 = R_3 + j \left(\omega L_3 - \frac{1}{\omega C_3} \right)$$

$$Z_4 = R_4 + j \left(\omega L_4 - \frac{1}{\omega C_4} \right)$$

$$Z_L = R_L$$

... (Formula 3)

[0048]

Introducing the (Formula 3) into the (Formula 2) makes the (Formula 4).

$$Z_{in} = R_1 + j \left(\omega L_1 - \frac{1}{\omega C_1} \right) + \frac{(\omega M_{12})^2}{R_2 + j \left(\omega L_2 - \frac{1}{\omega C_2} \right) + \frac{(\omega M_{23})^2}{R_3 + j \left(\omega L_3 - \frac{1}{\omega C_3} \right) + \frac{(\omega M_{34})^2}{R_4 + j \left(\omega L_4 - \frac{1}{\omega C_4} \right) + R_L}}$$

... (Formula 4)

[0049]

With the wireless power transmission apparatus 1, when the resonance frequency of the power-supplying resonator 22 and the

resonance frequency of the power-receiving resonator 32 are matched with each other, a magnetic field resonant state is created between the power-supplying resonator 22 and the power-receiving resonator 32. When the magnetic field resonant state is created between the power-supplying resonator 22 and the power-receiving resonator 32 by having these resonators resonating with each other, power is transmitted from the power-supplying resonator 22 to the power-receiving resonator 32 as magnetic field energy. Then, the power received by the power-receiving resonator 32 is supplied to the lithium ion secondary battery 9 thus charging the same via the power-receiving coil 31, the stabilizer circuit 7, and the charging circuit 8.

[0050]

(Thermal Control Method for Wireless Power Transmission Apparatus)

The following describes a thermal control method for the wireless power transmission apparatus 1, based on the above-described structure of the wireless power transmission apparatus 1.

[0051]

First described is the mechanism of the temperature increase in the wireless power transmission apparatus 1 and its counter measure, based on the charging characteristic of the lithium ion secondary battery 9 at the time of charging, the lithium ion secondary battery 9 being a target to which power is supplied using the wireless power transmission apparatus 1 of the present

embodiment.

[0052]

In the present embodiment, the lithium ion secondary battery 9 is used as one of members collectively referred to as the power-supplied device 10 to which the power is supplied. To charge the lithium ion secondary battery 9, a constant current/constant voltage charging system is used in general. In such charging of the lithium ion secondary battery 9 using the constant current/constant voltage charging system, the lithium ion secondary battery 9 is charged with a constant current (I_{ch}) (CC: Constant Current) for a while after the charging is started, as indicated by the charging characteristic of the lithium ion secondary battery 9 shown in FIG. 3. Then, the voltage (V_{ch}) applied to the lithium ion secondary battery 9 increases to a predetermined upper limit voltage (4.2 V in the present embodiment), while the battery 9 is charged with the constant current. After the voltage (V_{ch}) increases to the upper limit voltage, charging is performed at a constant voltage (CV: Constant Voltage), while the upper limit voltage is maintained. During the constant voltage charging (CV), the value of the current (I_{ch}) input to the lithium ion secondary battery 9 decreases. The charging is completed when the value of the current reaches a predetermined value, or after a predetermined time has been elapsed.

[0053]

With the decrease of the value of the current (I_{ch}) input to the lithium ion secondary battery 9, the value of the load impedance of the power-supplied device 10 including the lithium ion secondary battery 9 increases.

[0054]

Then, the input impedance Z_{in} of the entire wireless power transmission apparatus 1 including the power-supplied device 10 also varies.

[0055]

Assuming that a voltage V_{in} is applied to the wireless power transmission apparatus 1 and the current I_{in} flows therein for t seconds (sec.), the thermal energy J generated (amount of heat generated) in the wireless power transmission apparatus 1 is derived from (Formula 5) (Joule's law).

$$J = I_{in} \times V_{in} \times t(\text{sec})$$

... (Formula 5)

[0056]

(Formula 6) is an expression for the current I_{in} described using the voltage V_{in} , and input impedance Z_{in} (see FIG. 1).

$$I_{in} = \frac{V_{in}}{Z_{in}}$$

... (Formula 6)

[0057]

Since, in the present embodiment, the voltage V_{in} applied by the AC power source 6 to the wireless power transmission apparatus 1 is kept constant (effective value in the present embodiment is 5 V), substituting (Formula 6) to (Formula 5) makes a relational expression of (Formula 7).

$$J = \frac{V_{in}^2}{Z_{in}} \times t(\text{sec})$$

... (Formula 7)

[0058]

An increase in the amount of the thermal energy J generated in the wireless power transmission apparatus 1 leads to reduction of the life of electronic components structuring the wireless power transmission apparatus 1. Thus, it is required to reduce the amount of the thermal energy J generated in the wireless power transmission apparatus 1.

[0059]

According to (Formula 7), if the value of the input impedance Z_{in} in the constant voltage charging is increased, the value of the current I_{in} input to the wireless power transmission apparatus 1 decreases (see Formula 6). As a result, the amount of heat generated in the wireless power transmission apparatus 1 (the thermal energy J generated in the wireless power transmission apparatus 1) after the transition from the constant current charging (CC) to the constant voltage charging (CV) is reduced,

which consequently restrains an increase in the temperature of the wireless power transmission apparatus 1.

[0060]

Further, if the load change characteristic, which is represented by an amount of change in the value of the input impedance Z_{in} of the wireless power transmission apparatus 1 for a predetermined period of charging time in the constant voltage charging (CV), can be increased, the amount of change in the value of the current I_{in} input to the wireless power transmission apparatus 1 for a predetermined period of charging time is increased. This prevents excessive input of power after a transition from the constant current charging to the constant voltage charging, thereby preventing excessive heat generation in the wireless power transmission apparatus 1.

Meanwhile, if the load change characteristic, which is represented by an amount of change in the value of the input impedance Z_{in} of the wireless power transmission apparatus 1 for a predetermined period of charging time in the constant voltage charging (CV), can be decreased, the amount of change in the value of the current I_{in} input to the wireless power transmission apparatus 1 for a predetermined period of charging time is decreased. This prevents rapid change of the temperature of the wireless power transmission apparatus 1 in a short time.

[0061]

(Setting of Variation Tendency in Input Impedance Z_{in} in Constant

Voltage Charging)

In the present embodiment, to increase the value of the input impedance Z_{in} in the constant voltage charging (CV) of the constant current/constant voltage charging of the lithium ion secondary battery 9 using the wireless power transmission apparatus 1, variable parameters configuring the power-supplying module 2 and the power-receiving module 3 are set so that the later-described transmission characteristic "S21" of the wireless power transmission apparatus 1 relative to the driving frequency of the power supplied to the wireless power transmission apparatus 1 has a double-hump characteristic. Such variable parameters include: the resistance values, inductances, and capacities of capacitors of the R_1 , L_1 , and C_1 of the RLC circuit of the power-supplying coil 21, the R_2 , L_2 , and C_2 of the RLC circuit of the power-supplying resonator 22, the R_3 , L_3 , and C_3 of the RLC circuit of the power-receiving resonator 32, and the R_4 , L_4 , and C_4 of the RLC circuit of the power-receiving coil 31; and the coupling coefficients K_{12} , K_{23} , and K_{34} . After setting is made so that the transmission characteristic "S21" of the wireless power transmission apparatus 1 relative to the driving frequency of the power supplied to the wireless power transmission apparatus 1 has the double-hump characteristic, the driving frequency of the power supplied to the wireless power transmission apparatus 1 is adjusted, and thereby setting the variation tendency (e.g., to an increasing or decreasing tendency) of input impedance values

of the wireless power transmission apparatus 1 in the constant voltage charging, to reduce the amount of heat generated in the wireless power transmission apparatus 1.

[0062]

(Measurement Experiments 1-1 to 1-3)

The following describes, with reference to Measurement Experiments 1-1 to 1-3, what kind of variation tendency the input impedance values of the wireless power transmission apparatus 1 in the constant voltage charging show when the driving frequency of the power supplied to the wireless power transmission apparatus 1 is adjusted in the situation where setting is made so that the transmission characteristic "S21" of the wireless power transmission apparatus 1 relative to the driving frequency of the power supplied to the wireless power transmission apparatus 1 has the double-hump characteristic.

[0063]

In the wireless power transmission apparatus 1 used in Measurement Experiments 1-1 to 1-3, the power-supplying coil 21 is constituted by an RLC circuit whose elements include a resistor R_1 , a coil L_1 , and a capacitor C_1 , and the coil diameter is set to 15 mm ϕ . Similarly, the power-receiving coil 31 is constituted by an RLC circuit whose elements include a resistor R_4 , a coil L_4 , and a capacitor C_4 , and the coil diameter is set to 11 mm ϕ . Further, the power-supplying resonator 22 is constituted by an RLC circuit whose elements include a resistor R_2 , a coil L_2 , and a capacitor

C_2 , and a solenoid coil with a coil diameter of 15 mm ϕ is adopted as the coil L_2 . Further, the power-receiving resonator 32 is constituted by an RLC circuit whose elements include a resistor R_3 , a coil L_3 , and a capacitor C_3 , and a solenoid coil with a coil diameter of 11 mm ϕ is adopted as the coil L_3 . The values of R_1 , R_2 , R_3 , and R_4 in the wireless power transmission apparatus 1 used in Measurement Experiments 1-1 to 1-3 were set to 0.65 Ω , 0.65 Ω , 2.47 Ω , and 2.0 Ω , respectively. Further, the values of L_1 , L_2 , L_3 , and L_4 were set to 3.1 μH , 3.1 μH , 18.4 μH , and 12.5 μH , respectively. Further, the coupling coefficients K_{12} , K_{23} , and K_{34} were set to 0.46, 0.20, and 0.52, respectively. The resonance frequency of the power-supplying resonator 22 and the power-receiving resonator 32 was 970 kHz.

[0064]

In Measurement Experiments 1-1 to 1-3, after the wireless power transmission apparatus 1 was set as described above so as to have the double-hump characteristic, the current I_{in} and the input impedance Z_{in} during charging (power supply) of the lithium ion secondary battery 9 were measured in three different modes of the driving frequency of the AC power supplied to the power-supplying module 2: an inphase resonance mode (f_L), an antiphase resonance mode (f_H), and a resonance frequency mode (f_0), which will be described later (see FIG. 4 and FIG. 5). In Measurement Experiments 1-1 to 1-3, the current I_{in} and the input impedance Z_{in} were measured each as a function of charging time (min.), under

the condition that the input voltage V_{in} from the AC power source 6 to the wireless power transmission apparatus 1 is 5V.

[0065]

(Double-hump Characteristic)

In Measurement Experiments, used is the wireless power transmission apparatus 1 arranged so that the transmission characteristic "S21" of the wireless power transmission apparatus 1 relative to the driving frequency of the power supplied to the wireless power transmission apparatus 1 has the double-hump characteristic. The transmission characteristic "S21" is formed of signals measured by a network analyzer (e.g., E5061B produced by Agilent Technologies, Inc.) connected to the wireless power transmission apparatus 1, and is indicated in decibel. The greater the value is, the higher the power transmission efficiency is. The transmission characteristic "S21" of the wireless power transmission apparatus 1 relative to the driving frequency of the power supplied to the wireless power transmission apparatus 1 may have either single-hump or double-hump characteristic, depending on the strength of coupling (magnetic coupling) by the magnetic field between the power-supplying module 2 and the power-receiving module 3. The single-hump characteristic means the transmission characteristic "S21" relative to the driving frequency has a single peak which occurs in the resonance frequency band (around f_0) (see dotted line 51 FIG. 4). The double-hump characteristic on the other hand means the

transmission characteristic S21 relative to the driving frequency has two peaks, one of the peaks occurring in a drive frequency band lower than the resonance frequency (around f_L), and the other occurring in a drive frequency band higher than the resonance frequency (around f_H) (see solid line 52 in FIG. 4). The double-hump characteristic, to be more specific, means that the reflection characteristic "S11" measured with the network analyzer connected to the wireless power transmission apparatus 1 has two peaks. Therefore, even if the transmission characteristic S21 relative to the driving frequency appears to have a single peak, the transmission characteristic "S21" has a double-hump characteristic if the reflection characteristic "S11" measured has two peaks. It should be noted that the power transmission efficiency is a ratio of power received by the power-receiving module 3 to the power supplied to the power-supplying module 2.

[0066]

In the wireless power transmission apparatus 1 having the single-hump characteristic, the transmission characteristic "S21" is maximized (the power transmission efficiency is maximized) when the driving frequency is at the resonance frequency f_0 , as indicated by the dotted line 51 of FIG. 4.

[0067]

On the other hand, in the wireless power transmission apparatus 1 having the double-hump characteristic, the transmission

characteristic "S21" is maximized in the driving frequency band (around f_L) lower than the resonance frequency f_0 , and in the driving frequency band (around f_H) higher than the resonance frequency f_0 , as indicated by the solid line 52 of FIG. 4.

[0068]

It should be noted that, in general, if the distance between the power-supplying resonator and the power-receiving resonator is the same, the maximum value of the transmission characteristic "S21" having the double-hump characteristic (the value of the transmission characteristic "S21" at f_L or f_H) is lower than the maximum value of the transmission characteristic "S21" having the single-hump characteristic (the value of the transmission characteristic "S21" at f_0) (See graph in FIG. 4).

[0069]

Specifically, when the driving frequency of the AC power to the power-supplying module 2 is set to the frequency f_L nearby the peak on the low frequency side in the of double-hump characteristic (in the inphase resonance mode), the power-supplying resonator 22 and the power-receiving resonator 32 are resonant with each other in inphase, and the current in the power-supplying resonator 22 and the current in the power-receiving resonator 32 both flow in the same direction. As the result, as shown in the graph of FIG. 4, the value of the transmission characteristic "S21" is made relatively high, even though the driving frequency does not match the resonance

frequency of the power-supplying resonator 22 of the power-supplying module 2 and the power-receiving resonator 32 of the power-receiving module 3, although the value still may not be as high as that of the transmission characteristic "S21" in wireless power transmission apparatuses in general aiming at maximizing the power transmission efficiency (see dotted line 51). It should be noted that the resonance state in which the current in the coil (power-supplying resonator 22) of the power-supplying module 2 and the current in the coil (power-receiving resonator 32) of the power-receiving module 3 both flow in the same direction is referred to as an inphase resonance mode.

[0070]

Further, in the inphase resonance mode, because the magnetic field generated on the outer circumference side of the power-supplying resonator 22 and the magnetic field generated on the outer circumference side of the power-receiving resonator 32 cancel each other out, a magnetic field space having a lower magnetic field strength than the magnetic field strengths in positions not on the outer circumference side of the power-supplying resonator 22 and the power-receiving resonator 32 (e.g., the magnetic field strength on the inner circumference side of the power-supplying resonator 22 and the power-receiving resonator 32) is formed on the outer circumference side of the power-supplying resonator 22 and the power-receiving resonator 32, as the influence of the magnetic fields is lowered. When the stabilizer circuit 7, the

charging circuit 8, the lithium ion secondary battery 9, and the like which are desired to be less influenced by the magnetic field are placed in this magnetic field space, occurrence of eddy current attributed to the magnetic field in these components is reduced or prevented. This restrains negative effects due to generation of heat.

[0071]

On the other hand, when the driving frequency of the AC power to the power-supplying module 2 is set to the frequency f_H nearby the peak on the high frequency side in the double-hump characteristic (in the antiphase resonance mode), the power-supplying resonator 22 and the power-receiving resonator 32 resonate with each other in antiphase, and the current in the power-supplying resonator 22 and the current in the power-receiving resonator 32 flow opposite directions to each other. As the result, as shown in the graph of FIG. 4, the value of the transmission characteristic "S21" is made relatively high, even though the driving frequency does not match the resonance frequency of the power-supplying resonator 22 of the power-supplying module 2 and the power-receiving resonator 32 of the power-receiving module 3, although the value still may not be as high as that of the transmission characteristic "S21" in wireless power transmission apparatuses in general aiming at maximizing the power transmission efficiency (see dotted line 51). The resonance state in which the current in the coil

(power-supplying resonator 22) of the power-supplying module 2 and the current in the coil (power-receiving resonator 32) of the power-receiving module 3 flow opposite directions to each other is referred to as an antiphase resonance mode.

[0072]

Further, in the antiphase resonance mode, because the magnetic field generated on the inner circumference side of the power-supplying resonator 22 and the magnetic field generated on the inner circumference side of the power-receiving resonator 32 cancel each other out, a magnetic field space having a lower magnetic field strength than the magnetic field strengths in positions not on the inner circumference side of the power-supplying resonator 22 and the power-receiving resonator 32 (e.g., the magnetic field strengths on the outer circumference side of the power-supplying resonator 22 and the power-receiving resonator 32) is formed on the outer circumference side of the power-supplying resonator 22 and the power-receiving resonator 32, as the influence of the magnetic fields is lowered. When the stabilizer circuit 7, the charging circuit 8, the lithium ion secondary battery 9, and the like which are desired to be less influenced by the magnetic field are placed in this magnetic field space, occurrence of eddy current attributed to the magnetic field in these components is reduced or prevented. This restrains negative effects due to generation of heat. Further, since the magnetic field space formed in this antiphase resonance mode is

formed on the inner circumference side of the power-supplying resonator 22 and the power-receiving resonator 32, arranging the electronic components such as the stabilizer circuit 7, the charging circuit 8, the lithium ion secondary battery 9, and the like within this space makes the wireless power transmission apparatus 1 itself more compact, and improves the freedom in designing.

[0073]

When the driving frequency of the AC power supplied to the power-supplying module 2 is set to the inphase resonance mode (f_L) or to the antiphase resonance mode (f_H) in the situation where the transmission characteristic "S21" of the wireless power transmission apparatus 1 relative to the driving frequency of the power supplied to the wireless power transmission apparatus 1 has the double-hump characteristic, the value of the input impedance Z_{in} of the wireless power transmission apparatus 1 is maximized while the power transmission efficiency is kept at a high level, as shown in FIG. 5 (see the solid line 55). Meanwhile, when the driving frequency of the AC power to the power-supplying module 2 is set to the resonance frequency (f_0), the value of the input impedance Z_{in} of the wireless power transmission apparatus 1 is minimized, as shown in FIG. 5 (see the solid line 55). In Measurement Experiments 1-1 to 1-3, the current I_{in} and the input impedance Z_{in} during charging (power supply) of the lithium ion secondary battery 9 were measured in the three modes of the driving

frequency of the AC power supplied to the power-supplying module 2: the inphase resonance mode (f_L), the antiphase resonance mode (f_H), and the resonance frequency mode (f_0).

[0074]

In the present embodiment, as long as the transmission characteristic "S21" of the wireless power transmission apparatus 1 relative to the driving frequency of the power supplied to the wireless power transmission apparatus 1 has the double-hump characteristic, the settings and combinations of the variable parameters configuring the power-supplying module 2 and the power-receiving module 3 fall within design matters and are freely modifiable, the variable parameters including: the resistance values, inductances, and capacities of capacitors of the R_1 , L_1 , and C_1 of the RLC circuit of the power-supplying coil 21, the R_2 , L_2 , and C_2 of the RLC circuit of the power-supplying resonator 22, the R_3 , L_3 , and C_3 of the RLC circuit of the power-receiving resonator 32, and the R_4 , L_4 , and C_4 of the RLC circuit of the power-receiving coil 31, and the coupling coefficients K_{12} , K_{23} , and K_{34} .

[0075]

(Measurement Experiment 1-1: Driving Frequency set in Inphase Resonance Mode)

In Measurement Experiment 1-1, the driving frequency of the AC power to the power-supplying module 2 was set to the frequency f_L nearby the peak on the low frequency side (inphase resonance

mode: $f_L = 870$ kHz) of the double-hump characteristic. Then, the input current I_{in} and the input impedance Z_{in} were measured as a function of the charging time (min.) in this setting. The measurement results are shown in FIG. 6. It should be noted that the input voltage V_{in} was 5V (constant).

[0076]

The measurement results in FIG. 6 show that the values of the input impedance Z_{in} after the transition from constant current charging (CC) to constant voltage charging (CV) show an increasing tendency. It can be seen that along with the increasing tendency of the values of the input impedance Z_{in} , the values of the input current Input current I_{in} show a decreasing tendency (see Formula 6).

[0077]

According to the results of Measurement Experiment 1-1, when the driving frequency of the AC power supplied to the power-supplying module 2 is set to the frequency f_L nearby the peak on the low frequency side of the double-hump characteristic after setting is made so that the transmission characteristic "S21" of the wireless power transmission apparatus 1 relative to the driving frequency of the power to the wireless power transmission apparatus 1 has the double-hump characteristic, the values of the input impedance Z_{in} after the transition from the constant current charging (CC) to the constant voltage charging (CV) show the increasing tendency. This reduces the input current I_{in} to the wireless power transmission apparatus 1 in the constant voltage

charging (CV), consequently reducing heat generation in the wireless power transmission apparatus 1.

[0078]

(Measurement Experiment 1-2: Driving Frequency Set in Antiphase Resonance Mode)

In Measurement Experiment 1-2, the driving frequency of the AC power to the power-supplying module 2 was set to the frequency f_H nearby the peak on the high frequency side (antiphase resonance mode: $f_H = 1070$ kHz) of the double-hump characteristic. Then, the input current I_{in} and the input impedance Z_{in} were measured as a function of the charging time (min.) in this setting. The measurement results are shown in FIG. 7. It should be noted that the input voltage V_{in} was 5V (constant).

[0079]

The measurement results in FIG. 7 show that the values of the input impedance Z_{in} after the transition from constant current charging (CC) to constant voltage charging (CV) show an increasing tendency. It can be seen that along with the increasing tendency of the values of the input impedance Z_{in} , the values of the input current Input current I_{in} show a decreasing tendency (see Formula 6).

[0080]

According to the results of Measurement Experiment 1-2, when the driving frequency of the AC power supplied to the power-supplying module 2 is set to the frequency f_H nearby the peak on the high frequency side of the double-hump characteristic after setting

is made so that the transmission characteristic “S21” of the wireless power transmission apparatus 1 relative to the driving frequency of the power to the wireless power transmission apparatus 1 has the double-hump characteristic, the values of the input impedance Z_{in} after the transition from the constant current charging (CC) to the constant voltage charging (CV) show the increasing tendency. This reduces the input current I_{in} to the wireless power transmission apparatus 1 in the constant voltage charging (CV), consequently reducing heat generation in the wireless power transmission apparatus 1.

[0081]

(Measurement Experiment 1-3: Driving Frequency Set to Resonance frequency)

In Measurement Experiment 1-3, the driving frequency of the AC power to the power-supplying module 2 was set to the resonance frequency f_0 (the resonance frequency $f_0 = 970$ kHz) of the double-hump characteristic. Then, the input current I_{in} and the input impedance Z_{in} were measured as a function of the charging time (min.). The measurement results are shown in FIG. 8. It should be noted that the input voltage V_{in} was 5V (constant).

[0082]

The measurement results in FIG. 8 show that the values of the input impedance Z_{in} after the transition from constant current charging (CC) to constant voltage charging (CV) show a decreasing tendency. It can be seen that along with the decreasing tendency of the values

of the input impedance Z_{in} , the values of the input current Input current I_{in} show an increasing tendency (see Formula 6).

[0083]

According to the results of Measurement Experiment 1-3, when the driving frequency of the AC power supplied to the power-supplying module 2 is set to the resonance frequency f_0 of the double-hump characteristic after setting is made so that the transmission characteristic "S21" of the wireless power transmission apparatus 1 relative to the driving frequency of the power to the wireless power transmission apparatus 1 has the double-hump characteristic, the values of the input impedance Z_{in} after the transition from the constant current charging (CC) to the constant voltage charging (CV) show the decreasing tendency .

[0084]

The above Measurement Experiment 1-1 to 1-3 show that by adjusting the driving frequency of the AC power supplied to the power-supplying module 2 after setting is made so that the transmission characteristic "S21" of the wireless power transmission apparatus 1 relative to the driving frequency of the power to the wireless power transmission apparatus 1 has the double-hump characteristic, it is possible to set the variation tendency of the values of the input impedance Z_{in} of the wireless power transmission apparatus 1 in the constant voltage charging and thus adjusting the variation tendency of the input current I_{in} to the wireless power transmission apparatus 1, thereby

controlling heat generation in the wireless power transmission apparatus 1. It should be noted that, according to the Measurement Experiments 1-1 to 1-3, if the driving frequency of the AC power supplied to the power-supplying module 2 is set to a predetermined value between the frequency f_L of the inphase resonance mode and the resonance frequency f_0 , or between the resonance frequency f_0 and frequency f_H of the antiphase resonance mode, it is possible to maintain a constant value of the input impedance Z_{in} of the wireless power transmission apparatus 1 during the constant voltage charging.

[0085]

Further, by setting the driving frequency of the power supplied to the power-supplying module 2 in a band corresponding to a peak value (f_L) of the transmission characteristic appearing in the lower driving frequency band lower than the resonance frequency (f_0) of the power-supplying module 2 and the power-receiving module 3, it is possible to make adjustment so that the values of the input impedance Z_{in} of the wireless power transmission apparatus 1 in the constant voltage charging show an increasing tendency. This reduces the input current I_{in} to the wireless power transmission apparatus 1 in the constant voltage charging, consequently reducing heat generation in the wireless power transmission apparatus 1.

[0086]

Further, by setting the driving frequency of the power supplied

to the power-supplying module 2 in a band corresponding to a peak value (f_H) of the transmission characteristic appearing in the higher driving frequency band higher than the resonance frequency (f_0) of the power-supplying module 2 and the power-receiving module 3, it is possible to make adjustment so that the values of the input impedance Z_{in} of the wireless power transmission apparatus 1 in the constant voltage charging show an increasing tendency. This reduces the input current I_{in} to the wireless power transmission apparatus 1 in the constant voltage charging, consequently reducing heat generation in the wireless power transmission apparatus 1.

[0087]

Further, by setting the driving frequency of the power supplied to the power-supplying module 2 in a band corresponding to valley between the peak value (f_L) and the peak value (f_H) of the transmission characteristic respectively appearing in the lower driving frequency band and the higher driving frequency band which are respectively lower and higher than the resonance frequency (f_0) of the power-supplying module 2 and the power-receiving module 3, it is possible to make adjustment so that the values of the input impedance Z_{in} of the wireless power transmission apparatus 1 in the constant voltage charging show a maintaining tendency (tendency to stay the same) or a decreasing tendency. This maintains or increases the input current I_{in} to the wireless power transmission apparatus 1 in the constant voltage charging.

[0088]

(Setting of Load Change Characteristic)

In the situation where, for example, the variation tendency of the input impedance values of the wireless power transmission apparatus 1 in the constant voltage charging (CV) is set to the increasing tendency as is in Measurement Experiment 1-1, if the load change characteristic, which is represented by an amount of change in the value of the input impedance Z_{in} of the wireless power transmission apparatus 1 for a predetermined period of the charging time in the constant voltage charging (CV), can be increased, an amount of change in the value of the current I_{in} input to the wireless power transmission apparatus 1 for a predetermined period of charging time is increased. This prevents excessive input of power after the transition from the constant current charging to the constant voltage charging, thereby preventing excessive heat generation in the wireless power transmission apparatus 1 with readiness.

[0089]

Now, the load change characteristic is represented by an amount of change in the input impedance Z_{in} of the wireless power transmission apparatus 1 for a predetermined period of charging time in the constant voltage charging. That is, assuming that the X coordinate represents the charging time in the constant voltage charging (CV) and the Y coordinate represents the input impedance Z_{in} (see the input impedance Z_{in} in FIG. 6), the load change

characteristic is the ratio of the amount of change in the Y coordinate (ΔY) to a given amount of change in the X coordinate (ΔX), i.e., the slope (note that the absolute value of the slope is used as the load change characteristic). Thus, as the load change characteristic increases, an amount of change in the value of the input impedance Z_{in} of the wireless power transmission apparatus 1 for a predetermined period of charging time in the constant voltage charging increases. That is, the slope is large. In other words, when the load change characteristic is increased, the current I_{in} input to the wireless power transmission apparatus 1 is decreased in a short time. This prevents excessive input of power after the transition from the constant current charging (CC) to the constant voltage charging (CV), thereby preventing excessive heat generation in the wireless power transmission apparatus with readiness.

[0090]

(Adjustment of Load Change Characteristic with Coupling Coefficient)

In the present embodiment, the load change characteristic is adjusted by changing the coupling coefficient(s) k_{12} , k_{23} , and/or k_{34} . The following will describes how the load change characteristic changes by changing the coupling coefficient(s) k_{12} , k_{23} , and/or k_{34} and its ways, with reference to Measurement Experiments 2-1 to 2-5.

[0091]

(Measurement Experiment 2-1)

The values of R_1 , R_2 , R_3 , and R_4 in the wireless power transmission apparatus 1 used in Measurement Experiments 2-1 were set to $0.65\ \Omega$, $0.65\ \Omega$, $2.47\ \Omega$, and $2.0\ \Omega$, respectively. Further, the values of L_1 , L_2 , L_3 , and L_4 were set to $3.1\ \mu\text{H}$, $3.1\ \mu\text{H}$, $18.4\ \mu\text{H}$, and $12.5\ \mu\text{H}$, respectively. The resonance frequency of the power-supplying resonator 22 and the power-receiving resonator 32 was $970\ \text{kHz}$.
[0092]

In Measurement Experiment 2-1, after the wireless power transmission apparatus 1 was set as described above so as to have the double-hump characteristic, the driving frequency of the AC power to the power-supplying module 2 was set to the antiphase resonance mode (fH). Then, while the coupling coefficients k_{23} and k_{34} were fixed to 0.20 and 0.52 respectively, the input impedance Z_{in} at the time of charging (power-supplying to) the lithium ion secondary battery 9 was measured for the case where the coupling coefficient k_{12} was set to 0.3 and for the case where the coupling coefficient k_{12} was set to 0.46 . In Measurement Experiment 2-1, the input impedance Z_{in} was measured as a function of the charging time (min.), under the condition that the input voltage V_{in} from the AC power source 6 to the wireless power transmission apparatus 1 was $5\ \text{V}$.

[0093]

According to the measurement results of Measurement Experiment 2-1 shown in FIG. 9, in the case where the coupling coefficient

k_{12} was 0.3, an amount of change in the value of the input impedance Z_{in} for a predetermined period of charging time in the constant voltage charging (CV) was approximately 10 Ω . Meanwhile, in the case where the coupling coefficient k_{12} was 0.46, an amount of change in the value of the input impedance Z_{in} for the predetermined period of charging time in the constant voltage charging (CV) was approximately 20 Ω . Thus, the load change characteristic is larger in the case where the coupling coefficient k_{12} was 0.46 than in the case where the coupling coefficient k_{12} was 0.3.

[0094]

(Measurement Experiment 2-2)

The wireless power transmission apparatus 1 used in Measurement Experiments 2-2 is identical to that used in Measurement Experiment 2-1. In Measurement Experiment 2-2, after the wireless power transmission apparatus 1 was set to have the double-hump characteristic, the driving frequency of the AC power to the power-supplying module 2 was set to the resonance frequency (f_0) of the power-supplying resonator 22 and the power-receiving resonator 32. Then, while the coupling coefficients k_{23} and k_{34} were fixed to 0.20 and 0.52 respectively, the input impedance Z_{in} at the time of charging (power-supplying to) the lithium ion secondary battery 9 was measured for the case where the coupling coefficient k_{12} was set to 0.3 and for the case where the coupling coefficient k_{12} was set to 0.46. In Measurement Experiment 2-2, the driving frequency of the AC power supplied to the

power-supplying module 2 was set to the resonance frequency (f_0) of the power-supplying resonator 22 and the power-receiving resonator 32, to cause the value of the input impedance Z_{in} after the transition from the constant current charging (CC) to the constant voltage charging (CV) to have the decreasing tendency.

[0095]

According to the measurement results of Measurement Experiment 2-2 shown in FIG. 9, in the case where the coupling coefficient k_{12} was 0.3, an amount of change in the value of the input impedance Z_{in} for a predetermined period of charging time in the constant voltage charging (CV) was approximately 3 Ω . Meanwhile, in the case where the coupling coefficient k_{12} was 0.46, an amount of change in the value of the input impedance Z_{in} for the predetermined period of charging time in the constant voltage charging (CV) was approximately 6 Ω . Thus, the load change characteristic is larger in the case where the coupling coefficient k_{12} was 0.46 than in the case where the coupling coefficient k_{12} was 0.3. Note that, the slope, which is the ratio of the amount of change in the input impedance Z_{in} of the wireless power transmission apparatus 1 to the predetermined period of charging time in the constant voltage charging, is negative (-) in the above case. However, as described above, because the absolute value of the slope is used as the load change characteristic is, it is determined that the load change characteristic is larger in the case where the coupling coefficient k_{12} was 0.46, also in Measurement Experiment 2-2.

[0096]

(Measurement Experiment 2-3)

The wireless power transmission apparatus 1 used in Measurement Experiments 2-3 is identical to that used in Measurement Experiment 2-1. In Measurement Experiment 2-2, after the wireless power transmission apparatus 1 was set to have the double-hump characteristic, the driving frequency of the AC power to the power-supplying module 2 was set to the antiphase resonance mode (fH). Then, while the coupling coefficients k_{12} and k_{23} were fixed to 0.46 and 0.20 respectively, the input impedance Z_{in} at the time of charging (power-supplying to) the lithium ion secondary battery 9 was measured for the case where the coupling coefficient k_{34} was set to 0.25 and for the case where the coupling coefficient k_{34} was set to 0.52.

[0097]

According to the measurement results of Measurement Experiment 2-3 shown in FIG. 10, in the case where the coupling coefficient k_{34} was 0.25, an amount of change in the value of the input impedance Z_{in} for a predetermined period of charging time in the constant voltage charging (CV) was approximately 15 Ω . Meanwhile, in the case where the coupling coefficient k_{34} was 0.52, an amount of change in the value of the input impedance Z_{in} for the predetermined period of charging time in the constant voltage charging (CV) was approximately 20 Ω . Thus, the load change characteristic is larger in the case where the coupling coefficient k_{34} was 0.52 than in

the case where the coupling coefficient k_{34} was 0.25.

[0098]

(Measurement Experiment 2-4)

The wireless power transmission apparatus 1 used in Measurement Experiments 2-4 is identical to that used in Measurement Experiment 2-1. In Measurement Experiment 2-4, after the wireless power transmission apparatus 1 was set to have the double-hump characteristic, the driving frequency of the AC power to the power-supplying module 2 was set to resonance frequency (f_0) of the power-supplying resonator 22 and the power-receiving resonator 32. Then, while the coupling coefficients k_{12} and k_{23} were fixed to 0.46 and 0.20 respectively, the input impedance Z_{in} at the time of charging (power-supplying to) the lithium ion secondary battery 9 was measured for the case where the coupling coefficient k_{34} was set to 0.25 and for the case where the coupling coefficient k_{34} was set to 0.52. In Measurement Experiment 2-4, in same way as in Measurement Experiment 2-2, the driving frequency of the AC power supplied to the power-supplying module 2 was set to the resonance frequency (f_0) of the power-supplying resonator 22 and the power-receiving resonator 32, to cause the value of the input impedance Z_{in} after the transition from the constant current charging (CC) to the constant voltage charging (CV) to have the decreasing tendency.

[0099]

According to the measurement results of Measurement Experiment

2-4 shown in FIG. 10, in the case where the coupling coefficient k_{34} was 0.25, an amount of change in the value of the input impedance Z_{in} for a predetermined period of charging time in the constant voltage charging (CV) was approximately 1.5 Ω . Meanwhile, in the case where the coupling coefficient k_{34} was 0.52, an amount of change in the value of the input impedance Z_{in} for the predetermined period of charging time in the constant voltage charging (CV) was approximately 6 Ω . Thus, the load change characteristic is larger in the case where the coupling coefficient k_{34} was 0.52 than in the case where the coupling coefficient k_{34} was 0.25.

[0100]

(Measurement Experiment 2-5)

The values of R_1 , R_2 , R_3 , and R_4 in the wireless power transmission apparatus 1 used in Measurement Experiments 2-5 were set to 0.7 Ω , 0.7 Ω , 2.5 Ω , and 2.0 Ω , respectively. Further, the values of L_1 , L_2 , L_3 , and L_4 were set to 3.1 μH , 3.1 μH , 18.4 μH , and 12.5 μH , respectively. Further, the values of C_1 , C_2 , C_3 , and C_4 were set to 8.7 nF, 8.7 nF, 1.5 nF, and 2.3 nF, respectively. The resonance frequency of the power-supplying resonator 22 and the power-receiving resonator 32 was 970 kHz.

[0101]

In Measurement Experiment 2-5, after the wireless power transmission apparatus 1 was set to have the double-hump characteristic by the above arrangement, the driving frequency of the AC power to the power-supplying module 2 was set to the

antiphase resonance mode (fH). Then, while the coupling coefficient k_{23} was fixed to 0.20, the input impedance Z_{in} and the input current I_{in} (I_1) at the time of charging (power-supplying to) the lithium ion secondary battery 9 were measured for the case where the coupling coefficient k_{12} was set to 0.38 and the coupling coefficient k_{34} was set to 0.37 and for the case where the coupling coefficient k_{12} was set to 0.46 and the coupling coefficient k_{34} was set to 0.52. Also in Measurement Experiment 2-5, the input impedance Z_{in} and the input current I_{in} were measured as a function of the charging time (min.), under the condition that the input voltage V_{in} from the AC power source 6 to the wireless power transmission apparatus 1 was 5 V.

[0102]

According to the measurement results of Measurement Experiment 2-5 shown in FIG. 11, in the case where the coupling coefficient k_{12} was 0.38 and the coupling coefficient k_{34} was 0.37, an amount of change in the value of the input impedance Z_{in} for a predetermined period of charging time in the constant voltage charging (CV) was approximately 12 Ω (41 Ω - 29 Ω). Meanwhile, in the case where the coupling coefficient k_{12} was set to 0.46 and the coupling coefficient k_{34} was set to 0.52, an amount of change in the value of the input impedance Z_{in} for the predetermined period of charging time in the constant voltage charging (CV) was approximately 17 Ω (47 Ω - 30 Ω). Thus, the load change characteristic is larger in the case where the coupling

coefficient k_{12} was set to 0.46 and the coupling coefficient k_{34} was set to 0.52 than in the case where the coupling coefficient k_{12} was 0.38 and the coupling coefficient k_{34} was 0.37.

[0103]

Further, according to the measurement results for the input current I_{in} in Measurement Experiment 2-5 shown in FIG. 11, in the case where the coupling coefficient k_{12} was 0.38 and the coupling coefficient k_{34} was 0.37, an amount of change in the value of the input current I_{in} to the wireless power transmission apparatus 1 for the predetermined period of charging time in the constant voltage charging was approximately 0.050 A (0.170 A - 0.120 A). Meanwhile, in the case where the coupling coefficient k_{12} was set to 0.46 and the coupling coefficient k_{34} was set to 0.52, an amount of change in the value of the input current I_{in} to the wireless power transmission apparatus 1 for the predetermined period of charging time in the constant voltage charging was approximately 0.058 A (0.164 A - 0.106 A). Thus, the amount of change in the input current I_{in} to the wireless power transmission apparatus 1 for the predetermined period of charging time in the constant voltage charging is larger in the case where the coupling coefficient k_{12} was set to 0.46 and the coupling coefficient k_{34} was set to 0.52 than in the case where the coupling coefficient k_{12} was 0.38 and the coupling coefficient k_{34} was 0.37.

[0104]

Further, in Measurement Experiment 2-5, the surface temperature

of the power-supplying coil 21 in the constant current constant voltage charging was measured for the case where the coupling coefficient k_{12} was 0.38 and the coupling coefficient k_{34} was 0.37, and for the case where the coupling coefficient k_{12} was set to 0.46 and the coupling coefficient k_{34} was set to 0.52. The thus measured values and a graph in which the measured values are plotted are shown in FIG. 12.

[0105]

According to the measurement results of the surface temperature of the power-supplying coil 21 in FIG. 12, in the case where the coupling coefficient k_{12} was 0.38 and the coupling coefficient k_{34} was 0.37, the surface temperature of the power-supplying coil 21 around the transition from the constant current charging (CC) to the constant voltage charging (CV) (a point between 30 min. and 40 min. of charging time) was approximately 39.4 degrees centigrade, and the surface temperature of the power-supplying coil 21 measured approximately 40 minutes after the transition to the constant voltage charging (CV) (corresponding to 80 min. of charging time) was approximately 39.2 degrees centigrade. That is, the surface temperature of the power-supplying coil 21 dropped merely by 0.2 degrees centigrade (39.4 - 39.2).

Meanwhile, in the case where the coupling coefficient k_{12} was 0.46 and the coupling coefficient k_{34} was 0.52, the surface temperature of the power-supplying coil 21 around the transition from the constant current charging (CC) to the constant voltage charging

(CV) (a point between 30 min. and 40 min. of charging time) was approximately 39.1 degrees centigrade, and the surface temperature of the power-supplying coil 21 measured approximately 40 minutes after the transition to the constant voltage charging (CV) (corresponding to 80 min. of charging time) was approximately 37.6 degrees centigrade. That is, the surface temperature of the power-supplying coil 21 dropped by 1.5 degrees centigrade (39.1 - 37.6).

[0106]

Thus, by setting the coupling coefficients k_{12} and k_{34} to larger values, the load change characteristic is increased, which increases an amount of change in the value of the current I_{in} input to the wireless power transmission apparatus 1 for a predetermined charging time. This prevents excessive input of power after the transition from the constant current charging (CC) to the constant voltage charging (CV), thereby further preventing excessive heat generation in the wireless power transmission apparatus 1 (the power-supplying coil 21 in Measurement Experiment 2-5).

[0107]

(Method for Adjusting Coupling coefficients)

The following describes a method for adjusting the coupling coefficients, which are parameters to adjust the above-described load change characteristic.

[0108]

As shown in FIG. 13, in wireless power transmission, the

relationship between a distance between coils and the corresponding coupling coefficient k is as follows: the coupling coefficient k increases with a decrease (reduction) in the distance between the coils. Now, let us apply the above to the wireless power transmission apparatus 1 of the present embodiment. With a decrease in the distance d_{12} between the power-supplying coil 21 and the power-supplying resonator 22, the coupling coefficient k_{12} between the power-supplying coil 21 (coil L_1) and the power-supplying resonator 22 (coil L_2) increases; with a decrease in the distance d_{23} between the power-supplying resonator 22 and the power-receiving resonator 32, the coupling coefficient k_{23} between the power-supplying resonator 22 (coil L_2) and the power-receiving resonator 32 (coil L_3) increases; and with a decrease in the distance d_{34} between the power-receiving resonator 32 and the power-receiving coil 31, the coupling coefficient k_{34} between the power-receiving resonator 32 (coil L_3) and the power-receiving coil 31 (coil L_4) increases. To the contrary, with an increase in the distance d_{12} between the power-supplying coil 21 and the power-supplying resonator 22, the coupling coefficient k_{12} between the power-supplying coil 21 (coil L_1) and the power-supplying resonator 22 (coil L_2) decreases; with an increase in the distance d_{23} between the power-supplying resonator 22 and the power-receiving resonator 32, the coupling coefficient k_{23} between the power-supplying resonator 22 (coil L_2) and the power-receiving resonator 32 (coil L_3) decreases; and

with an increase in the distance d_{34} between the power-receiving resonator 32 and the power-receiving coil 31, the coupling coefficient k_{34} between the power-receiving resonator 32 (coil L_3) and the power-receiving coil 31 (coil L_4) decreases.

[0109]

Based on the above method for adjusting the coupling coefficients and Measurement Experiments 2-2 to 2-5 where the load change characteristic is adjusted by adjusting the coupling coefficients, the following is derived: while the distance d_{23} between the power-supplying resonator 22 and the power-receiving resonator 32 and the distance d_{34} between the power-receiving resonator 32 and the power-receiving coil 31 are fixed, it is possible to increase the value of the coupling coefficient k_{12} between the power-supplying coil 21 and power-supplying resonator 22 by decreasing the distance d_{12} between the power-supplying coil 21 and power-supplying resonator 22, thereby to increase the load change characteristic. To the contrary, it is possible to decrease the value of the coupling coefficient k_{12} between the power-supplying coil 21 and the power-supplying resonator 22 by increasing the distance d_{12} between the power-supplying coil 21 and the power-supplying resonator 22, thereby to decrease the load change characteristic.

[0110]

Further, while the distance d_{12} between the power-supplying coil 21 and power-supplying resonator 22 and the distance d_{23} between

the power-supplying resonator 22 and the power-receiving resonator 32 are fixed, it is possible to increase the value of the coupling coefficient k_{34} between the power-receiving resonator 32 and the power-receiving coil 31 by decreasing the distance d_{34} between the power-receiving resonator 32 and the power-receiving coil 31, thereby to increase the load change characteristic. To the contrary, it is possible to decrease the value of the coupling coefficient k_{34} between the power-receiving resonator 32 and the power-receiving coil 31 by increasing the distance d_{34} between the power-receiving resonator 32 and the power-receiving coil 31, thereby to decrease the load change characteristic.

[0111]

Further, while the distance d_{23} between the power-supplying resonator 22 and the power-receiving resonator 32 is fixed, it is possible to increase the values of the coupling coefficient k_{12} between the power-supplying coil 21 and power-supplying resonator 22 and the coupling coefficient k_{34} between the power-receiving resonator 32 and the power-receiving coil 31 by respectively decreasing the distance d_{12} between the power-supplying coil 21 and the power-supplying resonator 22 and the distance d_{34} between the power-receiving resonator 32 and the power-receiving coil 31, thereby to increase the load change characteristic. To the contrary, it is possible to decrease the values of the coupling coefficient k_{12} between the power-supplying

coil 21 and the power-supplying resonator 22 and the coupling coefficient k_{34} between the power-receiving resonator 32 and the power-receiving coil 31 by respectively increasing the distance d_{12} between the power-supplying coil 21 and the power-supplying resonator 22 and the distance d_{34} between the power-receiving resonator 32 and the power-receiving coil 31, thereby to decrease the load change characteristic.

[0112]

With the above method, in the case where the lithium ion secondary battery 9 rechargeable using a constant current/constant voltage charging system is charged using the wireless power transmission apparatus 1 configured to supply power by means of a resonance phenomenon, it is possible to adjust the load change characteristic, which is represented by an amount of change in the value of the input impedance Z_{in} of the wireless power transmission apparatus 1 for a predetermined period of charging time after the transition from the constant current charging (CC) to the constant voltage charging (CV), by changing at least one of the coupling coefficients which are the coupling coefficient k_{12} between the power-supplying coil 21 and the power-supplying resonator 22, the coupling coefficient k_{23} between the power-supplying resonator 22 and the power-receiving resonator 32, and the coupling coefficient k_{34} between the power-receiving resonator 32 and the power-receiving coil 31. As the load change characteristic is increased in this way, an amount of change in

the value of the input impedance Z_{in} of the wireless power transmission apparatus 1 for a predetermined period of charging time after the transition from the constant current charging (CC) to the constant voltage charging (CV) increases, which increases an amount of change in the value of the current I_{in} input to the wireless power transmission apparatus 1 for a predetermined period of charging time. Such an increase in the amount of change in the value of the current I_{in} input to the wireless power transmission apparatus 1 prevents excessive input of power after the transition from the constant current charging (CC) to the constant voltage charging (CV), and thereby it is possible to prevent excessive heat generation in the wireless power transmission apparatus 1 (the power-supplying coil 21, the power-supplying resonator 22, the power-receiving resonator 32, and the power-receiving coil 31).

To the contrary, as the load change characteristic is decreased, an amount of change in the value of the input impedance Z_{in} of the wireless power transmission apparatus 1 for a predetermined period of charging time after the transition from the constant current charging (CC) to the constant voltage charging (CV) decreases, which decreases an amount of change in the value of the current I_{in} input to the wireless power transmission apparatus 1 for a predetermined period of charging time. Such a decrease in the amount of change in the value of the current I_{in} input to the wireless power transmission apparatus 1 suppresses rapid

variation, for a short time, in temperature of the wireless power transmission apparatus 1 (the power-supplying coil 21, the power-supplying resonator 22, the power-receiving resonator 32, and the power-receiving coil 31) after the transition from the constant current charging (CC) to the constant voltage charging (CV).

[0113]

Furthermore, with the above method, it is possible to increase the load change characteristic by increasing the coupling coefficient k_{12} between the power-supplying coil 21 and the power-supplying resonator 22.

[0114]

Furthermore, with the above method, it is possible to increase the load change characteristic by increasing the coupling coefficient k_{34} between the power-receiving resonator 32 and the power-receiving coil 31.

[0115]

Furthermore, with the above method, it is possible to increase the load change characteristic by increasing the coupling coefficient k_{12} between the power-supplying coil 21 and the power-supplying resonator 22 and the coupling coefficient k_{34} between the power-receiving resonator 32 and the power-receiving coil 31.

[0116]

With the above method, it is possible to change the value of the

coupling coefficient k_{12} between the power-supplying coil 21 and the power-supplying resonator 22 by changing the distance d_{12} between the power-supplying coil 21 and the power-supplying resonator 22; it is possible to change the value of the coupling coefficient k_{23} between the power-supplying resonator 22 and the power-receiving resonator 32 by changing the distance d_{23} between the power-supplying resonator 22 and the power-receiving resonator 32; and it is possible to change the value of the k_{34} between the power-receiving resonator 32 and the power-receiving coil 31 by changing the distance d_{34} between the power-receiving resonator 32 and the power-receiving coil 31. Thus, by a simple operation of physically changing the distance d_{12} between the power-supplying coil 21 and the power-supplying resonator 22; the distance d_{23} between the power-supplying resonator 22 and the power-receiving resonator 32; and the distance d_{34} between the power-receiving resonator 32 and the power-receiving coil 31, it is possible to change the respective coupling coefficients between the corresponding coils. That is, it is possible to adjust the load change characteristic by the simple operation of physically changing at least one of the distances between coils.

[0117]

(Manufacturing Method)

Next, the following describes with reference to FIG. 14 and FIG. 15 a design method (design process) which is a part of the manufacturing process of the wireless power transmission

apparatus 1. In the following description, a wireless headset 200 having an earphone speaker unit 200a, and a charger 201 are described as an example of a portable device having the wireless power transmission apparatus 1 (see FIG. 14).

[0118]

The wireless power transmission apparatus 1 to be designed in this design method is mounted in the wireless headset 200 and the charger 201 shown in FIG. 14, in the form of a power-receiving module 3 (the power-receiving coil 31 and the power-receiving resonator 32) and a power-supplying module 2 (the power-supplying coil 21 and the power-supplying resonator 22), respectively. For the sake of convenience, FIG. 14 illustrates the stabilizer circuit 7, the charging circuit 8, and the lithium ion secondary battery 9 outside the power-receiving module 3; however, these are actually disposed on the inner circumference side of the power-receiving coil 31 and the power-receiving resonator 32, which is a solenoid coil. That is, the wireless headset 200 includes the power-receiving module 3, the stabilizer circuit 7, the charging circuit 8, and the lithium ion secondary battery 9, and the charger 201 includes the power-supplying module 2. While in use, the power-supplying coil 21 of the power-supplying module 2 is connected to the AC power source 6.

[0119]

(Design Method)

First, as shown in FIG. 15, a power reception amount in the

power-receiving module 3 is determined based on the capacity of the lithium ion secondary battery 9, and the charging current required for charging the lithium ion secondary battery 9 (S1).

[0120]

Next, the distance between the power-supplying module 2 and the power-receiving module 3 is determined (S2). The distance is the distance d23 between the power-supplying resonator 22 and the power-receiving resonator 32 in the situation where the wireless headset 200 having therein the power-receiving module 3 is placed on the charger 201 having therein the power-supplying module 2, i.e., during the charging state. To be more specific, the distance d23 between the power-supplying resonator 22 and the power-receiving resonator 32 is determined, taking into account the shapes and the structures of the wireless headset 200 and the charger 201.

[0121]

Further, based on the shape and the structure of the wireless headset 200, the coil diameters of the power-receiving coil 31 and the coil of the power-receiving resonator 32 which are in the power-receiving module 3 are determined (S3).

[0122]

Further, based on the shape and the structure of the charger 201, the coil diameters of the power-supplying coil 21 and the coil of the power-supplying resonator 22 which are in the power-supplying module 2 are determined (S4).

[0123]

Through the steps of S2 to S4, the coupling coefficient K_{23} between the power-supplying resonator 22 (coil L_2) and the power-receiving resonator 32 (coil L_3) of the wireless power transmission apparatus 1; and the power transmission efficiency are determined.

[0124]

Based on the power reception amount in the power-receiving module 3 determined in S1 and on the power transmission efficiency determined through S2 to S4, the minimum power supply amount required for the power-supplying module 2 is determined (S5).

[0125]

Then, a range of design values of the input impedance Z_{in} in the wireless power transmission apparatus 1 is determined, taking into account the power reception amount in the power-receiving module 3, the power transmission efficiency, and the minimum power supply amount required for the power-supplying module 2 (S6).

[0126]

Further, there is determined a range of design values in which the transmission characteristic "S21" of the wireless power transmission apparatus 1 relative to the driving frequency of power supplied to the wireless power transmission apparatus 1 has the double-hump characteristic (S7).

[0127]

Then, final parameters related to the power-supplying coil 21, the power-supplying resonator 22, the power-receiving resonator

32, and the power-receiving coil 31 are determined so as to satisfy: the design values of the input impedance Z_{in} determined in S6; the design values for the double-hump characteristic determined in S7; and a desired load change characteristic (S8). The parameters related to the power-supplying coil 21, the power-supplying resonator 22, the power-receiving resonator 32, and the power-receiving coil 31 include: the resistance values, inductances, and capacities of capacitors in the R_1 , L_1 , and C_1 of the RLC circuit of the power-supplying coil 21, the R_2 , L_2 , and C_2 of the RLC circuit of the power-supplying resonator 22, the R_3 , L_3 , and C_3 of the RLC circuit of the power-receiving resonator 32, and the R_4 , L_4 , and C_4 of the RLC circuit of the power-receiving coil 31; the coupling coefficients K_{12} , K_{23} , and K_{34} ; and the distance d_{12} between the power-supplying coil 21 and the power-supplying resonator 22, and the distance d_{34} between the power-receiving resonator 32 and the power-receiving coil 31. [0128]

The above-described manufacturing method of the wireless power transmission apparatus 1 including the above design method enables manufacturing of a wireless power transmission apparatus 1 that allows control of heat generation in the wireless power transmission apparatus 1 by adjusting the value of at least one coupling coefficient between coils each included in the power-supplying module 2 or the power-receiving module 3. In other words, it is possible to manufacture the wireless power

transmission apparatus 1 capable of controlling heat generation therein without a need of an additional component in the wireless power transmission apparatus 1.

[0129]

(Other Embodiments)

Although the above description of the manufacturing method deals with the wireless headset 200 as an example, the method is applicable to any devices having a secondary battery: e.g., tablet PCs, digital cameras, mobile phones, earphone-type music players, hearing aids, and sound collectors.

[0130]

Although the above description deals with the wireless power transmission apparatus 1 configured to perform power transmission by means of magnetic coupling using a resonance phenomenon (magnetic field resonant state) between resonators (coils) provided to the power-supplying module 2 and the power-receiving module 3, the present invention is applicable to a wireless power transmission apparatus 1 configured to perform power transmission by using electromagnetic induction between coils.

[0131]

Further, although the above description assumes the wireless power transmission apparatus 1 is mounted in a portable electronic device, the use of such an apparatus is not limited to small devices. For example, with a modification to the specifications according to the required power amount, the wireless power transmission

apparatus 1 is mountable to a relatively large system such as a wireless charging system for an electronic vehicle (EV), or to an even smaller device such as a wireless endoscope for medical use.

[0132]

Although the above descriptions have been provided with regard to the characteristic parts so as to understand the present invention more easily, the invention is not limited to the embodiments and the examples as described above and can be applied to the other embodiments and examples, and the applicable scope should be construed as broadly as possible. Furthermore, the terms and phraseology used in the specification have been used to correctly illustrate the present invention, not to limit it. In addition, it will be understood by those skilled in the art that the other structures, systems, methods and the like included in the spirit of the present invention can be easily derived from the spirit of the invention described in the specification. Accordingly, it should be considered that the present invention covers equivalent structures thereof without departing from the spirit and scope of the invention as defined in the following claims. In addition, it is required to sufficiently refer to the documents that have been already disclosed, so as to fully understand the objects and effects of the present invention.

[Reference Signs List]

[0133]

1: Wireless Power Transmission Apparatus
2: Power-Supplying Module
3: Power-Receiving Module
6: AC power source
7: Stabilizer Circuit
8: Charging Circuit
9: Lithium Ion Secondary Battery
10: Power-Supplied Device
21: Power-Supplying Coil
22: Power-Supplying Resonator
31: Power-Receiving Coil
32: Power-Receiving Resonator
200: Wireless Headset
201: Charger

CLAIMS

[Claim 1]

A thermal control method for a wireless power transmission apparatus configured to supply power, by changing a magnetic field, from a power-supplying module to a power-receiving module connected to a power-supplied device including a secondary battery rechargeable using a constant current/constant voltage charging system, the method comprising
adjusting a load change characteristic, which is represented by an amount of change in input impedance value of the wireless power transmission apparatus for a predetermined period of charging time in constant voltage charging, by adjusting a value of a coupling coefficient between coils each included in the power-supplying module or the power-receiving module.

[Claim 2]

The thermal control method according to claim 1, wherein the wireless power transmission apparatus is configured to supply power, by means of resonance phenomenon, from the power-supplying module having at least a power-supplying coil and a power-supplying resonator to the power-receiving module having at least a power-receiving resonator and a power-receiving coil, the power-receiving module being connected to a power-supplied device including a secondary battery rechargeable using a constant current/constant voltage charging system, and the load change characteristic, which is represented by an amount

of change in input impedance value of the wireless power transmission apparatus for a predetermined period of charging time in constant voltage charging, is adjusted by adjusting at least one of coupling coefficients which are a coupling coefficient between the power-supplying coil and the power-supplying resonator, a coupling coefficient between the power-supplying resonator and the power-receiving resonator, and a coupling coefficient between the power-receiving resonator and the power-receiving coil.

[Claim 3]

The thermal control method according to claim 2, wherein the load change characteristic is increased by increasing the coupling coefficient between the power-supplying coil and the power-supplying resonator.

[Claim 4]

The thermal control method according to claim 2, wherein the load change characteristic is increased by increasing the coupling coefficient between the power-receiving resonator and the power-receiving coil.

[Claim 5]

The thermal control method according to claim 2, wherein the load change characteristic is increased by increasing the coupling coefficient between the power-supplying coil and the power-supplying resonator and the coupling coefficient between the power-receiving resonator and the power-receiving coil.

[Claim 6]

The thermal control method according to any one of claims 2 to 5, wherein the value of the coupling coefficient between the power-supplying coil and the power-supplying resonator is adjusted by changing a distance between the power-supplying coil and the power-supplying resonator, the value of the coupling coefficient between the power-supplying resonator and the power-receiving resonator is adjusted by changing a distance between the power-supplying resonator and the power-receiving resonator, and the value of the coupling coefficient between the power-receiving resonator and the power-receiving coil is adjusted by changing a distance between the power-receiving resonator and the power-receiving coil.

[Claim 7]

The thermal control method according to any one of claims 1 to 6, further comprising
setting variable parameters configuring the power-supplying module and the power-receiving module so that values of a transmission characteristic relative to a driving frequency of power supplied to the power-supplying module have a double-hump characteristic having a peak in a lower driving frequency band which is lower than a resonance frequency of the power-supplying module and the power-receiving module, and a peak in a higher driving frequency band which is higher than the resonance frequency, thereby

enabling control of a variation tendency of input impedance values of the wireless power transmission apparatus in the constant voltage charging, by adjusting the driving frequency.

[Claim 8]

The thermal control method according to claim 7, wherein the driving frequency of the power supplied to the power-supplying module is set in a band corresponding to a peak value of the transmission characteristic appearing in the lower driving frequency band lower than the resonance frequency of the power-supplying module and the power-receiving module, or in a band corresponding to a peak value of the transmission characteristic appearing in the higher driving frequency band higher than the resonance frequency of the power-supplying module and the power-receiving module, thereby making adjustment so that the input impedance values of the wireless power transmission apparatus in the constant voltage charging show an increasing tendency.

[Claim 9]

The thermal control method according to claim 7, wherein the driving frequency of the power supplied to the power-supplying module is set in a band corresponding to a valley between peak values of the transmission characteristic respectively appearing in the lower drive frequency band and the higher frequency band which are respectively lower and higher than the resonance frequency of the power-supplying module and the power-receiving

module, thereby making adjustment so that the input impedance values of the wireless power transmission apparatus in the constant voltage charging show a maintaining tendency or a decreasing tendency.

[Claim 10]

A wireless power transmission apparatus adjusted by the thermal control method recited in any one of claims 1 to 9.

[Claim 11]

A manufacturing method for a wireless power transmission apparatus configured to supply power, by changing a magnetic field, from a power-supplying module to a power-receiving module connected to a power-supplied device including a secondary battery rechargeable using a constant current/constant voltage charging system, the method comprising
a process of adjusting a load change characteristic, which is represented by an amount of change in input impedance value of the wireless power transmission apparatus for a predetermined period of charging time in constant voltage charging, by adjusting a value of a coupling coefficient between coils each included in the power-supplying module or the power-receiving module.