

Description

This invention relates to television image display apparatus. Embodiments of the invention may be used for controlling the video output of a television receiver to achieve a desired image quality for each field.

In a video output circuit of a television receiver, a variety of output signal control devices are provided, for example, for adjusting the luminance level (brightness and contrast), colour level, sharpness and the like of an image on a display screen, and such control devices are normally adjusted by the user.

The image state on the display screen continuously changes depending on the content of each video programme, so that, even if the described control devices are adequately adjusted for one programme so as to attain the best image quality thereof, it does not ensure that the image quality will remain optimum for a different programme. Thus, for example, since visual impressions of displayed images vary significantly with regard to extremely light and dark scenes, maintaining a proper luminance level is difficult. Therefore, if a luminance adjustment is performed during a light video output, the luminance level normally tends to be adjusted by the user towards a slightly darker image. After such luminance adjustment has been completed and fixed by the user, the contrast and so forth are thereafter controlled on the basis of such fixed luminance level. Such a fixed luminance level produces an image with "black deformation" or "black separation", which is unsatisfactory, when the video output changes from a light to a dark video output. Thus, maintaining the best state of the displayed image is difficult.

According to the present invention there is provided a television image display apparatus in which an input video signal is processed to form an output image signal for display on a display screen, said apparatus comprising:

sampling means for dividing a field of said input video signal into a plurality of areas and for sampling image information in each of said areas;
memory means for storing preset adjustment data; and
arithmetic processing means for receiving the sampled image information and said preset adjustment data and, on the basis thereof, generating a video control signal for controlling the output image signal to be displayed.

According to the present invention there is also provided a colour television receiver in which an input video signal is processed to form an output image signal, the receiver comprising:

sampling means for dividing a field of said input video signal into a predetermined number of areas and for sampling image information in each of said areas;
memory means for storing preset adjustment data;

and

arithmetic processing means for receiving the sampled image information and said preset adjustment data, and generating a control signal on the basis of said sampled image information and said preset adjustment data for controlling a colour level of said output image signal

According to the present invention there is also provided a television receiver in which an input video signal is processed to form an output image signal, the receiver comprising:

sampling means for dividing a field of said input video signal into a predetermined number of areas and for sampling image information in each of said areas;
memory means for storing preset adjustment data; and

arithmetic processing means for receiving the sampled image information and said stored preset adjustment data, and generating a control signal on the basis of said sampled image information and said preset adjustment data for controlling the sharpness of said output image signal.

Embodiments of the present invention can provide an improved television image display apparatus which automatically maintains a proper luminance level notwithstanding substantial changes in the brightness thereof. Generally, in accordance with an embodiment of this invention, one field of an input video signal is divided into a predetermined number of areas and a typical luminance signal in each of the divided areas is sampled to provide image information in respect of each field. Adjustment data are also obtained on the basis of such sample image information, and a signal for controlling the luminance signal is provided in accordance with the adjustment data, whereby a desired adjustment of the output video signal can be achieved for each field. The brightness, contrast, colour saturation, sharpness and so forth of the image can be automatically controlled by real-time processing in conformity with the video content of each field.

The invention will now be described by way of example with reference to the accompanying drawings, throughout which like parts are referred to by like references, and in which:

Figure 1 is a block diagram of a television image display apparatus according to the present invention;

Figure 2 is a more detailed block diagram of a first embodiment of the invention;

Figure 3 illustrates signal sampling timing;

Figures 4 and 5 are flow charts for explaining the operating procedure of the embodiment of Figure 2;

Figures 6A and 6B illustrate graphically an operation for setting adjustment data;

Figure 7 illustrates graphically another operation for setting adjustment data;

Figure 8 graphically illustrates an example of luminance signal control;

Figure 9 is a circuit diagram of a sample value totalizer;

Figure 10 is a block diagram of a known chrominance signal processor;

Figure 11 is a block diagram of a second embodiment of the invention;

Figure 12 is a flow chart schematically showing the operating procedure of the embodiment of Figure 11;

Figure 13 is a circuit diagram of a known sharpness controller;

Figure 14 is a block diagram of a third embodiment of the invention; and

Figure 15 is a flow chart showing the operating procedure of the third embodiment.

As shown in Figure 1, a television image display apparatus according to the present invention generally comprises a control signal generator 1, a luminance-chrominance (Y-C) processor 5 and a cathode ray tube (CRT) display unit 6. The control signal generator 1 includes a sampling device 2, an arithmetic device 3 and a memory device 4, and samples a signal from the processor 5 and supplies an output control signal S to the processor 5. The operation of the apparatus shown in Figure 1 will be apparent from the following detailed description of the preferred embodiments.

The first embodiment is shown on Figure 2, and is provided for controlling a luminance signal in conformity with the state of each field.

The television image display apparatus shown in Figure 2 comprises a television tuner 10, an intermediate frequency (IF) amplifier 11, a switch 14, a video signal or Y-C processor 12, a cathode ray tube (CRT) display unit 13 and a luminance control signal circuit 15. A composite video television signal is received through the tuner 10 and is supplied to the amplifier 11 wherein the signal is amplified and supplied to one input terminal of the switch 14. An input signal T from a video tape recorder (VTR) or similar device is coupled to the other input terminal of the switch 14. The switch 14 is coupled to the processor 12 and supplies one of either the amplified signal from the amplifier 11 or the reproduced signal from the VTR to the processor 12. The processor 12 is coupled to the display unit 13 and supplies red, green and blue (R, G, B) video signals thereto. The processor 12 further supplies a video luminance signal (Y) to the luminance control signal circuit 15 as hereinafter described.

As shown in Figure 2, the luminance control signal circuit 15 includes a sampling circuit 16, an A-D converter 17, an arithmetic processor 18, a read only memory (ROM) 19, a random access memory (RAM) 20 and a D-A converter 21. The sampling circuit 16 is connected to the processor 12 and samples, at a pre-

determined timing, one field of video luminance data so as to obtain luminance data corresponding to the luminance data presented to the display unit 13. The sampling circuit 16 is connected to the A-D converter 17 which digitizes the sampled luminance information and supplies such digitized information to the arithmetic processor 18. The arithmetic processor 18 may include a microcomputer and receives the digitized luminance information and generates a control signal for adjusting the luminance signal level. The ROM 19 contains previously stored adjustment data selectively supplied to the arithmetic processor 18 and utilized by the latter in providing the control signal for adjusting the luminance signal level. The rewritable RAM 20 stores user selected adjustment data which are also supplied to the arithmetic processor 18 for use in the control signal. The digital control signal from the arithmetic processor 18 is supplied to the D-A converter 21 which provides a corresponding analogue control signal Sb to a luminance controller 12A. In response thereto, the luminance controller 12A adjusts the luminance level of the signal supplied to the display unit 13 by adjusting either the respective R G B signal levels or the Y signal level. A manual control 22 is connected to the processor 18 and allows the user manually to adjust the luminance level. Although not shown, the output of the manual control 22 may be directly supplied to the luminance controller 12A rather than to the arithmetic processor 18.

The sampling performed by the sampling circuit 16 will now be described with reference to Figure 3. Voltage values of a video signal in one field are sampled at n points, Sp1 to Spn, as shown. The sampled information obtained from each of the n points represents a typical value in a respective one of n individual areas. If more precise image information is required, the number of data sampling points can be increased. An optimum number of sampling points may be determined by taking into consideration the processing speed of the arithmetic processor 18 and the additional time that would be required for processing additional sampled data.

The operation of the arithmetic processor 18 will now be described below with reference to the flow charts in Figures 4 and 5.

Processing begins, in the arithmetic processor 18, upon receipt of one sample of luminance signal data from the sampling circuit 16 through the A-D converter 17. As previously mentioned, n samples of luminance signal data are acquired in each field. These n samples are inputted sequentially through A-D conversion, thereby executing data processing steps 100(1) to 100(n) in Figure 4.

The operation shown in Figure 5 is performed in each of the steps 100(1) to 100(n) so as to decide in which group, as classified by the luminance signal level (IRE level), the input sample of luminance signal data belongs. Such grouped data are then totalled.

The IRE level groups are formed by dividing the IRE range, that is 0(IRE) to 100(IRE), into several stages. In the present embodiment, eight stages are utilized. More specifically, data in the 0 to 12 IRE range are defined as being in ① IRE group; data in 13 to 24 IRE range are defined as being in ② IRE group; ...; and data in 88 to 100 IRE range are defined as being in ⑧ IRE group. It should be noted that the invention is not limited to the use of eight stages or groups. Thus, the sampled data are grouped or classified by the operations indicated in steps 102(1) to 102(8), whereupon the total data in each of the individual groups ① to ⑧ are obtained upon completion of the processing of the n sample data of one field.

In other words, when one sample of data is inputted in step 101, a determination is made in steps 102(1) to 102(8) as to the group in which the sample data belong, that is, to identify the corresponding IRE level of the sample data signal. Afterwards, in one of steps 103(1) to 103(8), one point is added to each IRE group to which a sample of data is found to belong.

Accordingly, it is to be appreciated that upon completion of the steps 100(1) to 100(n) in Figure 4, which involves repeating the operations in Figure 5 n times, each sampled datum in the entire field has been grouped into a corresponding IRE group and the number of sampled data in each IRE group has been totalled. Arithmetic processing is executed according to the totalled IRE group data, which readily allows determination of the distribution of the luminance levels, including the areas of the individual luminance levels, the lightness and darkness of the entire image and so forth, as displayed on the display unit 13.

In a step 110 following the step 100(n), a constant B is set on the basis of the data in the low IRE groups, that is, the total data in the ① to ④ IRE groups. The constant B is a reference value which represents the "darkness" of the image as shown on the display unit 13. Such value can be obtained by computation of the total data in the ① to ④ IRE groups according to a predetermined rule, or by reading out one of the previously stored adjustment datum from the ROM 19 on the basis of such total data. An alternate procedure for setting the constant B involves weighing the data in the darkest ① IRE group through the relatively lighter ④ IRE group and summing up the values thereof. For example, the calculation involving the ① to ④ IRE groups is executed so that $B = (① \times ④) + (② \times ②) + (③ + ④)$, where the level "B", represents the entire "darkness" of the displayed image.

A constant W is next set in step 111 on the basis of the data in the high IRE groups, that is, the total data in the ⑤ to ⑧ IRE groups. The constant W represents the "lightness" value of the image shown on the display unit 13 and is obtained by a procedure similar to that previously described for step 110.

After determining the constants B and W, which represent the darkness and lightness values, respec-

tively, a luminance level control signal is determined in step 112 on the basis of such two constants B and W. In other words, predetermined calculations are executed utilizing constants B, W and the adjustment data selected from the ROM 19 and/or the RAM 20, so as to obtain reference data f(B) and f(W). The reference data f(B) and f(W) are added to a signal value N, where N represents a signal control led to the pre-adjusted luminance or average luminance level, and the resultant value $N + f(B) + f(W)$ is outputted in step 113 as a control signal SB.

The calculations for obtaining the values f(B) and f(W) may be achieved by storing in the ROM 19 arithmetic coefficients for the constants B and W as represented by the curves shown in Figures 6(a) and 6(b), respectively; or by storing in the ROM 19 the values f(B) and f(W) which correspond to the constants B and W, respectively, and which arranged in the form of a data table, thereby enabling direct access of the values f(B) and f(W).

An alternative procedure for setting or determining the control signal SB in step 112 involves first computing the ratio of the constant B to the constant W which is utilized as data representative of the dark area in the displayed image, and then storing, as an adjustment data group, in ROM 19 a plurality of conversion curves, arithmetic coefficient group or data tables, with various B/W ratios, as shown in Figure 7. The value f(B) is obtained from both the constant B and the B/W ratio or dark area data. The control signal is set to have the sum of the value f(B) and the value N, which is the normal or nominal luminance level control signal. For example, as in Figure 7, when the constant B equals BA and the ratio B/W corresponds to the curve b2, a value f(BA) is obtained as the adjustment data, so that the luminance control signal SB becomes $f(BA) + N$.

Alternatively, data corresponding to the conversion curves shown in Figures 6(a) and 6(b) or Figure 7 are prepared. Such conversion curve data for corresponding groups can be stored in multiple memory devices, respectively, and utilized by merely exchanging one memory device for another. Additional selection is also possible by switching the operation modes, that is, switching between using the video constant or the user's personal selection. The RAM 20 may be configured to allow the user to write a personalized adjustment data group therein.

The luminance level control signal SB outputted from the arithmetic processor 18 is converted into an analogue signal by the D-A converter 21, as previously mentioned, and is supplied to the luminance controller 12A included within the processor 12 as shown in Figure 2. The video luminance level is controlled by the luminance controller 12A on the basis of the control signal SB.

It is to be appreciated that the above operations, including the sampling timing control, arithmetic proc-

essing control, memory device control and so forth can be controlled by a system control device (not shown) in the microcomputer.

As the above operations are performed in each vertical synchronizing period, the luminance control signal SB is outputted for each field so as to adjust the luminance signal level on a field-by-field basis, hence each displayed image contains the proper luminance level. Therefore, automatic control is maintained so as to lower the luminance level in the case of a light image and to raise the luminance level in the case of a dark image, thereby preventing "black deformation" or "black separation" regardless of the video content of each image. Furthermore, proper contrast is similarly maintained.

Since such adjustment is effected in consideration of the black level and white level areas, the luminance level may be adjusted so that the DC transmission factor or brightness control level is lowered when the amount of the data in the low IRE group is either small or large, as graphically shown in Figure 8, and the DC transmission factor is raised when the data predominantly lies in an intermediate IRE group. A similar adjustment may also be effected in respect to the contrast, and an acceptable result can be obtained by executing such control for both brightness and contrast simultaneously.

In an alternate approach, the luminance signal need not be sampled in each field, but may be sampled in one out of several fields in a group of fields or vertical synchronizing periods. Furthermore, the luminance control may be executed not only during the vertical synchronizing period, but also in the middle of a field. For example, control may be carried out to raise the luminance level in the upper half of the field while lowering the luminance level in the lower half thereof. This can be accomplished by changing the totalization unit of the aforementioned sample data.

In a preferred embodiment, the luminance level control circuit is designated to change with the hysteresis characteristic so that, upon occurrence of over a predetermined level difference, the luminance level is controlled to shift to another level.

A field memory may be provided which successively holds the sampled data therein, so as to make it possible to determine, with high accuracy, both information as to the position of the light or dark areas in the image, and also the state of the present field as compared with that of the preceding field. Therefore, by taking such data in to consideration at the time of setting the constants, further enhanced luminance control can be achieved. For example, an adjustment can be performed for each area in accordance with the lightness distribution in one field.

The operation of totalizing the luminance distribution, that is, the operation of acquiring the total data in the IRE groups, as performed by the processor 18 with reference to the flow chart of Figure 5, can be al-

ternatively performed by the circuit shown in Figure 9.

In the circuit of Figure 9, the luminance signal inputted at each sampling timing is distributed through one of the comparators CP1 to CP8 and stored in a respective one of the capacitors C1 to C8 which corresponds to a respective one of the IRE groups. Such action is repeated for one vertical synchronizing period, whereafter the integrated voltage value stored in one of the capacitors C1 to C8 is read out therefrom at the instant a vertical synchronizing signal is fed to a respective one of transistors T1 to T8. The voltage value thus obtained is A-D converted in one of a group 171 to 178 of A-D converters, and the resulting digital value is supplied as a total value of the respective IRE group to the arithmetic processor 18.

In a second embodiment of the present invention, the latter is applied to a chrominance signal processor. However, in order that the problems overcome by this embodiment may be fully understood, a known chrominance signal processor will be initially described in detail with reference to Figure 10.

In such known chrominance signal processor, a composite video signal is first separated into a luminance signal Y and a colour or chrominance signal C in a Y-C separator 50, as shown in Figure 10. The colour signal is thereafter inputted to an automatic gain-control (AGC) circuit 51 where the amplitude of a burst signal is controlled. The output signal from the circuit 51 is supplied to an automatic phase control (APC) circuit 52 and to a voltage controlled oscillator (VCO) circuit 53 which produces two colour sub-carrier signals having a 90° phase difference with respect to each other. A hue controller 54 is coupled to the VCO 53 so as to adjust the hue by changing the phase between the colour sub-carrier signal and the burst signal. The output signal from the circuit 51 is further supplied to a colour controller 55 which is capable of adjusting the colour density by changing the amplitude of the colour signal. The output signals of the VCO circuit 53 and the colour control circuit 55 are supplied to a colour demodulator 56. A demodulated colour difference signal from the demodulator 56, and the luminance signal from the Y-C separator 50 are supplied to an R-G-B matrix circuit 57 from which colour signals R, G, B are obtained.

In the circuit of Figure 10, adjustment of the colour saturation level in the colour controller 55 is normally performed by a user or operator, and thereafter, the colour state or density is retained at such fixed set level. However, the video state including lightness, darkness and so forth in the displayed image changes continuously depending upon the video content so that it is difficult to maintain a proper colour image in each video scene by the usual manual control of the colour saturation level. Furthermore, in the case of a dark image or a video signal obtained from a received wave having a low electric field strength,

the noise associated with the colour signal is noticeable, and it is generally assumed that a more acceptable result is achieved by lowering the colour level in such case. On the other hand, when the image is light, colour insufficiency occurs, so that a better result is achieved by raising the colour level. The optimum colour level also varied depending on the video content. For example, in the case of a scene containing a snow mountain or the like where the white level is high, the colour level needs to be lowered; whereas, in a scene containing a lake or the like, the colour level needs to be raised. Also, in a colourful scene, for example, one showing various fruits or the like, the colour level needs to be raised.

Therefore, the proper or desired colour level for each field varies depending on the lightness or darkness of the respective image content, the total level of the chrominance signals in the field, the field strength or received wave level and so forth. Hence, it is impossible continuously to maintain the proper colour level merely by setting a fixed control level as in the known technique. For example, if a certain control level is set by adjustment when a light video image is displayed, colour noise becomes noticeable when the image changes to a dark one.

A second embodiment of the present invention which eliminates the aforementioned problems will now be described with reference to Figure 11.

The apparatus shown in Figure 11 comprises a tuner 10, an IF amplifier 11, a switch 14, a Y-C processor 12, CRT display unit 13, sampling circuits 16, 23 and 25, A-D converters 17, 24 and 26, an arithmetic processor 27, ROM 28, a RAM 29, a D-A converter 30 and a manual control 31. The elements 10 to 17 in Figure 11 are connected similarly to the elements identified by the same reference numerals in Figure 2 and operate in a similar manner.

In Figure 11, the three sampling circuits 16, 23 and 25 are provided. In the sampling circuit 16, a luminance signal supplied to the video signal processor 12 is sampled at a predetermined timing in each field. Similarly, in the sampling circuit 25, a colour signal supplied to the processor 12 is sampled in the same manner. Thus, samples of the luminance and colour information displayed on the display unit 13 are obtained and supplied to the arithmetic processor 27. To obtain information on the received wave level, or electric field strength, an AGC voltage from the IF amplifier 11 is sampled at predetermined timing by the sampling circuit 23.

The three A-D converters 17, 24 and 26 are coupled to the sampling circuits 16, 23 and 25, respectively, and digitize the signals outputted from the respective sampling circuits; and the arithmetic processor 27, consisting of a microcomputer, receives the digital image data signals from the A-D converters 17, 24 and 26 and produces, as its output, a colour level control signal resulting from computations performed

on the received digital image data signals.

The D-A converter 30, which is connected to the arithmetic processor 27, converts into an analogue signal SC the colour level control signal determined by the operation of the arithmetic processor 27. The analogue control signal SC is supplied to a colour controller 12B included in the processor 12, by which the colour level is adjusted in accordance with the control signal SC.

The manual control 31 is connected to the arithmetic processor 27 and enables the user to adjust the colour saturation level manually.

The operation of arithmetic processor 27 in setting the colour level control signal for each field will now be described with reference to the flow chart in Figure 12.

Upon receipt by the arithmetic processor 27 of a sample of the luminance signal through the A-D converter 17 from the sampling circuit 16, the arithmetic processor 27 executes a procedure similar to that hereinbefore described with reference to Figures 4 and 5. As previously described, n data samples are obtained per field, and data totalization and so forth are performed upon the n data samples so as to obtain information on the "lightness" level in the image. Simultaneous arithmetic processing is executed by the arithmetic processor 27 with respect to n data samples of the colour signal obtained through the A-D converter 26 from the sampling circuit 25, whereby colour information regarding the colour signal distribution and colour level is obtained.

Furthermore, in an operation similar to that described above, samples of the AGC voltage data from the sampling circuit 23 are supplied to the arithmetic processor 27 in an initial step 200 (Figure 12) and are processed to acquire information on the received wave level or electric field strength. Thereafter, in steps 201 to 207, a colour level control signal is set so as to obtain an optimum colour level in accordance with the lightness and darkness of the image, the colour stage and the received wave level. The operations of steps 201 to 207 will now be further described.

Utilizing the electric field strength data input in step 200, it is determined in step 201 whether or not the input video data is from a weak electric field. If the answer is affirmative, the routine proceeds to step 202 in which the processor 27 provides a control signal which lowers the colour level. If the answer to step 201 is negative, signifying that the video data is not from a weak electric field, the routine proceeds to step 203 in which the colour state of the image is judged according to the total level of the chrominance signal samples from the sampling circuit 25. If the resulting total level is high, indicating that the respective field contains a colourful image, the routine proceeds to step 204 in which a control signal is set to raise the colour level. When the image is judged not to be rel-

atively colourful in step 203, the routine proceeds to step 205 in which the lightness and darkness of the image are judged according to the luminance signal samples from the sampling circuit 16. If the image is judged to be light in step 205, the control signal is set in the step 206 so as to raise the colour level. Conversely, if the image is judged to be dark in step 205, the program proceeds to step 207 in which the control signal is set to lower the colour level.

An operation for thus setting the control signal may be performed on the basis of a lightness reference value (constant A) obtained by totalizing or computing the luminance data samples for one field, a colour state reference value (constant B) obtained by totalizing the chrominance data samples for one field, and another value (constant C) similarly obtained from the AGC voltage data samples. Using the constants A, B and C as parameters, a control signal is determined by selectively reading out preset adjustment data from the ROM 28 and computing the general colour level control value therefrom.

In an alternative method, the control signal is determined by recalling previously stored arithmetic coefficients, which correspond to the above constants, from the ROM 28 and then computing the constants A, B and C directly from the coefficients that are read out.

As another alternative, a plurality of adjustment data can be stored in the ROM 28 so as to enable a control signal to be set on the basis of the information obtained from the luminance signal, colour signal and AGC voltage value, that is, constants A, B and C. An optimum colour level control signal can be supplied by various methods by the use of a suitable software program and the microcomputer of the arithmetic processor 27.

The RAM 29 enables, a user to write therein desired adjustment data by which personalized colour level control may be achieved. The ROM 28 and/or the RAM 29 may utilize replaceable cartridges.

Since the above operation is performed in each vertical synchronizing period, a colour level control signal is provided for each field so as to adjust the colour level of the video signal on a field-by-field basis, and thereby maintain the video output image at a proper colour level state. Thus, automatic video control is performed so that the colour level is reduced when the received wave level is low or the image is dark, and the colour level is emphasized or increased in the case of a colourful or light image. By reason of the foregoing, noticeable noise resulting from the colour signal is avoided whether due to the video content, that is, a dark image or a dark portion, or the received wave level or electric field strength. Even in the case of an image where noise is not otherwise noticeable, the embodiment achieves significant enhancement of the colour display.

It will be appreciated that the D-A converter 30 in

Figure 11 may be omitted, in which case the control signal SC outputted from the arithmetic processor 27 in digital form is directly applied to the colour controller 12B for adjusting the colour level.

Further, a field memory (not shown) may be provided for holding the successive data samples therein. In such case, it is possible to determined both the relatively light and dark portions of the field, as well as the colour state of the image with higher accuracy and also the state of the present field as compared with that of a preceding field. Therefore, by taking such data into consideration at the time of setting of the constants A, B and C or the execution of the various calculations, further enhanced colour level control can be achieved. For example, an adjustment can be performed for each area of the image in accordance with the lightness distribution in the respective field.

Furthermore, in sampling the colour signals, the respective signals R, G and B may be sampled individually.

The above described operation of acquiring a certain constant from the information signal for one field which is inputted to the microcomputer in the arithmetic processor 27, for example, the totalization of the luminance signal distribution, can also be performed by the circuit of Figure 9, as in the first described embodiment.

For the purpose of improving the image quality in a television receiver, a sharpness control device is frequently provided, as illustrated in Figure 13, which enhances the sharpness of the image by adding pre-shoot and over-shoot to the signal waveform.

In the sharpness control circuit of Figure 13, a video signal is supplied through a transistor Q to a coil L and a capacitor C1, by which a high-frequency component of the video signal is emphasized thus obtaining a relatively high order differential waveform. The signal component of such waveform is then supplied to a terminal a at one end of a variable resistor VR so that the edge of the video signal as supplied to a slider or intermediate terminal b is emphasized. In such sharpness control device, the image quality is rendered sharp or soft by displacing the slider b of the variable resistor VR towards the terminal a or the terminal c at the opposite end, respectively. Hence, the user can adjust the sharpness to conform with his taste. However, such sharpness control has a disadvantage in that, once adjusted, the sharpness level is generally kept fixed, so that the image quality is deteriorated when the video content is thereafter changed.

Moreover, it is generally believed that image definition is enhanced by raising the sharpness in the case of a light image or lowering the sharpness in the case of either a dark image or an image received with a small electric field strength, that is, a low wave level, since the pre-shoot and over-shoot of the video

signal for raising the sharpness of the image emphasize the noise so as to make it noticeable. Thus, a preferred sharpness level varies depending upon the lightness and darkness of the image content, so that the proper sharpness is not attainable by merely setting a fixed sharpness level with a variable resistor or the like.

A third embodiment of the present invention which will be described with reference to Figure 14 eliminates the aforementioned problem by controlling the sharpness of a video signal for each field in accordance with a control signal determined on the basis of sampled image data for the respective field. Furthermore, the optimum adjustment level of the sharpness controller is set automatically for each field to conform with the video content.

The apparatus in Figure 14 is shown to comprise elements identified by reference numerals 10 to 17, 23 and 24 which correspond to the similarly numbered elements in Figure 11, and which are similarly connected and operate in a similar manner.

In Figure 14, the A-D converters 17 and 24 digitize the output signals from the sampling circuits 16 and 23, respectively, and an arithmetic processor 32, which may be constituted by a microcomputer, executes arithmetic calculations, in a manner similar to that previously described with reference to Figure 11, on the basis of the image data and the field strength data supplied in digital signal form from the A-D converters 17 and 24, and outputs a control signal for performing optimum sharpness control.

Also included in the circuit of Figure 14 is a D-A converter 35 which is connected to the arithmetic processor 32 and converts the digital control signal obtained from the arithmetic processor 32 into a corresponding analogue signal SS. The analogue control signal SS is supplied to a sharpness controller 12C included in the processor 12 and in which the sharpness level is adjusted by the control signal SS either directly or indirectly.

A manual control 36 is also connected to the arithmetic processor 27, and enables the user to adjust the sharpness level manually.

The operation of the arithmetic processor 32 for setting the sharpness level for each field will now be described with reference to the flow chart in Figure 15.

In an initial step 300, the arithmetic processor 32 receives samples of the luminance signal supplied from the sampling circuit 16 through the A-D converter 17 and a processing procedure similar to that described with reference to Figure 12 is executed. More specifically n data samples are obtained for each field, and data totalization and so forth are performed upon the n data samples, whereby information on the "lightness" or "darkness" of the image is obtained. Furthermore, data samples of the AGC voltage level are supplied from the sampling circuit 23 and proc-

essed to produce information on the level of the received wave or electric field strength. Thereafter, a control signal is set to obtain the optimum sharpness in accordance with the lightness of the image and the received wave level.

More specifically, in a step 301 following the step 300, it is determined whether or not the sampled data for a field represents a "dark" image. If the answer to step 301 is affirmative, the program proceeds to a step 302 in which the sharpness level is lowered for accommodating the dark image. On the other hand, in the case of a light image, that is, when step 301 has a negative answer, the program proceeds to a step 303 in which it is determined whether or not the received video signal had a weak electric field. If the answer to step 303 is affirmative, the sharpness level is lowered in the next step 304. On the other hand, if the electric field was strong, the sharpness level is raised in a step 305.

An operation for setting the control signal produced by the arithmetic processor 32 in accordance with the program of Figure 15 may be performed on the basis of a lightness reference value (constant A) obtained by either totalizing the samples of the luminance signal for one field or by computing such sample values, and also on the basis of another reference value (constant C) obtained from the AGC voltage. The control signal is determined by reading out adjustment data from a ROM 33 with the constant A initially used as a parameter and then with the constant C used as a parameter in a manner similar to that previously described.

The control signal may be obtained directly from the values of such constants A and C. In such a case, arithmetic coefficients corresponding to the constants A and C are stored as table data in the ROM 33 so as to enable direct access thereof and are subsequently combined to form the control signal as previously described.

As an alternative, a plurality of adjustment data may also be previously stored in the ROM 33 so that a desired control signal can be set on the basis of the information obtained from both the luminance signal and the AGC voltage value, that is, constants A and C.

The provision of a RAM 34 enables the user to write therein desired adjustment data for attaining personally desired sharpness characteristics.

The above described operations are performed in each vertical synchronizing period so as to provide a sharpness control signal for each field, thereby adjusting the sharpness of the video signal on a field-by-field basis and producing a video output image with its properly maintained sharpness. It will be appreciated that automatic control is executed such that, for example, when the received wave level or field strength is high and the image is light, a sharp video output can be obtained with the addition of over-shoot

and pre-shoot. On the other hand, when the image is dark or the received wave level is low, a soft video output can be obtained with a signal having a gentle rise in its waveform.

Thus, it becomes possible to eliminate the noticeable noise that otherwise appears depending upon the video content, that is, in any dark image or dark image portion, or when the received wave level is low or weak. Furthermore, enhanced sharpness can be ensured in any image where noise is not noticeable.

In an embodiment of television image display apparatus as described above, any of the luminance, chrominance and sharpness can be automatically controlled for each field in accordance with the video signal or the image state so as to maintain the video display in the optimum state. In particular, in the case of a dark image or a weak electric field signal, the appearance of noise can be easily avoided while realizing an improvement in the image quality.

Claims

1. A television image display apparatus in which an input video signal is processed to form an output image signal for display on a display screen, said apparatus comprising:
sampling means (2) for dividing a field of said input video signal into a plurality of areas and for sampling image information in each of said areas;
memory means (4) for storing preset adjustment data; and
arithmetic processing means (3) for receiving the sampled image information and said preset adjustment data and, on the basis thereof, generating a video control signal for controlling the output image signal to be displayed.
2. Apparatus according to claim 1 wherein said image information which is sampled includes a luminance signal, and said control signal controls the brightness of said output image signal to be displayed.
3. Apparatus according to claim 1 wherein said image information which is sampled includes a chrominance signal, and said control signal controls a colour level of said output image signal to be displayed.
4. Apparatus according to claim 1 wherein said image information which is sampled includes data representing the electrical field strength of said input video signal, and said control signal controls a colour level of said output image signal to be displayed.
5. Apparatus according to claim 1 wherein said im-

age information which is sampled includes data representing the electrical field strength of said input video signal, and data representing a luminance component and a chrominance component of said input video signal; and wherein said control signal controls a colour level of said output image signal so as to increase said colour level in response to a high level of said chrominance component and also in response to a light image represented by said luminance component, and so as to decrease said colour level in response to a weak electrical field of said input video signal and a dark image represented by said luminance component.

6. Apparatus according to claim 1 wherein said video control signal is determined field-by-field.
7. Apparatus according to claim 1 wherein said image information which is sampled includes data representing the electrical field strength of said input video signal, and data representing a luminance component of said input video signal and from which the lightness of a respective image can be determined; and wherein said control signal controls sharpness of said output image signal so as to increase said sharpness in response to a luminance component corresponding to a light image and a strong electrical field, and so as to decrease said sharpness in response to a luminance component corresponding to a dark image and a weak electrical field.
8. A colour television receiver in which an input video signal is processed to form an output image signal, the receiver comprising: sampling means (2) for dividing a field of said input video signal into a predetermined number of areas and for sampling image information in each of said areas; memory means (4) for storing preset adjustment data; and
arithmetic processing means (3) for receiving the sampled image information and said preset adjustment data, and generating a control signal on the basis of said sampled image information and said preset adjustment data for controlling a colour level of said output image signal.
9. A receiver according to claim 8 wherein said sampled image information includes data representing an electric field strength of said input video signal.
10. A television receiver in which an input video signal is processed to form an output image signal, the receiver comprising:
sampling means (2) for dividing a field of said input video signal into a predetermined number of



and pre-shoot. On the other hand, when the image is dark or the received wave level is low, a soft video output can be obtained with a signal having a gentle rise in its waveform.

Thus, it becomes possible to eliminate the noticeable noise that otherwise appears depending upon the video content, that is, in any dark image or dark image portion, or when the received wave level is low or weak. Furthermore, enhanced sharpness can be ensured in any image where noise is not noticeable.

In an embodiment of television image display apparatus as described above, any of the luminance, chrominance and sharpness can be automatically controlled for each field in accordance with the video signal or the image state so as to maintain the video display in the optimum state. In particular, in the case of a dark image or a weak electric field signal, the appearance of noise can be easily avoided while realizing an improvement in the image quality.

Claims

1. A television image display apparatus in which an input video signal is processed to form an output image signal for display on a display screen, said apparatus comprising:
sampling means (2) for dividing a field of said input video signal into a plurality of areas and for sampling image information in each of said areas;
memory means (4) for storing preset adjustment data; and
arithmetic processing means (3) for receiving the sampled image information and said preset adjustment data and, on the basis thereof, generating a video control signal for controlling the output image signal to be displayed.
2. Apparatus according to claim 1 wherein said image information which is sampled includes a luminance signal, and said control signal controls the brightness of said output image signal to be displayed.
3. Apparatus according to claim 1 wherein said image information which is sampled includes a chrominance signal, and said control signal controls a colour level of said output image signal to be displayed.
4. Apparatus according to claim 1 wherein said image information which is sampled includes data representing the electrical field strength of said input video signal, and said control signal controls a colour level of said output image signal to be displayed.
5. Apparatus according to claim 1 wherein said im-
- age information which is sampled includes data representing the electrical field strength of said input video signal, and data representing a luminance component and a chrominance component of said input video signal; and wherein said control signal controls a colour level of said output image signal so as to increase said colour level in response to a high level of said chrominance component and also in response to a light image represented by said luminance component, and so as to decrease said colour level in response to a weak electrical field of said input video signal and a dark image represented by said luminance component.
6. Apparatus according to claim 1 wherein said video control signal is determined field-by-field.
7. Apparatus according to claim 1 wherein said image information which is sampled includes data representing the electrical field strength of said input video signal, and data representing a luminance component of said input video signal and from which the lightness of a respective image can be determined; and wherein said control signal controls sharpness of said output image signal so as to increase said sharpness in response to a luminance component corresponding to a light image and a strong electrical field, and so as to decrease said sharpness in response to a luminance component corresponding to a dark image and a weak electrical field.
8. A colour television receiver in which an input video signal is processed to form an output image signal, the receiver comprising: sampling means (2) for dividing a field of said input video signal into a predetermined number of areas and for sampling image information in each of said areas; memory means (4) for storing preset adjustment data; and
arithmetic processing means (3) for receiving the sampled image information and said preset adjustment data, and generating a control signal on the basis of said sampled image information and said preset adjustment data for controlling a colour level of said output image signal.
9. A receiver according to claim 8 wherein said sampled image information includes data representing an electric field strength of said input video signal.
10. A television receiver in which an input video signal is processed to form an output image signal, the receiver comprising:
sampling means (2) for dividing a field of said input video signal into a predetermined number of



areas and for sampling image information in each of said areas;
memory means (4) for storing preset adjustment data; and
arithmetic processing means (3) for receiving the sampled image information and said stored preset adjustment data, and generating a control signal on the basis of said sampled image information and said preset adjustment data for controlling the sharpness of said output image signal.

11. A receiver according to claim 10 wherein said sampled image information includes data representing an electric field strength of said input signal.

12. A colour receiver according to claim 11 wherein said sampled image information further includes data representing luminance and colour components of said input video signal.

13. A receiver according to claim 11 wherein said sampled image information further includes data representing a luminance component of said input video signal.

Patentansprüche

1. Fernsehbildanzeigevorrichtung, in der ein Eingangsvideosignal verarbeitet wird, damit es ein Ausgangsbildsignal zur Anzeige auf einem Anzeigeschirm bildet, wobei die Vorrichtung aufweist:
eine Abtasteinrichtung (2) zum Unterteilen eines Halbbildes des Eingangsvideosignals in mehrere Bereiche und zum Abtasten der Bildinformation in jedem der Bereiche;
eine Speichereinrichtung (4) zum Speichern voreingestellter Einstelldaten; und
eine Rechenverarbeitungseinrichtung (3) zum Empfangen der abgetasteten Bildinformation und der voreingestellten Einstelldaten, und zum Erzeugen eines Videosteuersignals auf dieser Grundlage, um das anzuzeigende Ausgangsbildsignal zu steuern.

2. Vorrichtung nach Anspruch 1, wobei die Bildinformation, die abgetastet wird, ein Luminanzsignal enthält, und das Steuersignal die Helligkeit des anzuzeigenden Ausgangsbildsignals steuert.

3. Vorrichtung nach Anspruch 1, wobei die Bildinformation, die abgetastet wird, ein Chrominanzsignal enthält, und das Steuersignal einen Farbpegel des anzuzeigenden Ausgangsbildsignals steuert.

4. Vorrichtung nach Anspruch 1, wobei die Bildinformation, die abgetastet wird, Daten enthält, die die elektrische Feldstärke des Eingangsvideosignals darstellen, und das Steuersignal einen Farbpegel des anzuzeigenden Ausgangsbildsignals steuert.

5. Vorrichtung nach Anspruch 1, wobei die Bildinformation, die abgetastet wird, Daten enthält, die die elektrische Feldstärke des Eingangsvideosignals darstellen, und Daten, die eine Luminanzkomponente und eine Chrominanzkomponente des Eingangsvideosignals darstellen; und wobei das Steuersignal einen Farbpegel des Ausgangsbildsignals so steuert, daß dieser Farbpegel bei einem hohen Pegel der Chrominanzkomponente und ebenfalls bei einem hellen Bild, das durch die Luminanzkomponente dargestellt wird, ansteigt, und daß der Farbpegel bei einem schwachen elektrischen Feld des Eingangsvideosignals und einem dunklen Bild, das durch die Luminanzkomponente dargestellt wird, vermindert wird.

6. Vorrichtung nach Anspruch 1, wobei das Videosteuersignal halbbildweise bestimmt wird.

7. Vorrichtung nach Anspruch 1, wobei die Bildinformation, die abgetastet wird, Daten enthält, die die elektrische Feldstärke des Eingangsvideosignals darstellen, und Daten, die eine Luminanzkomponente des Eingangsvideosignals darstellen, und aus denen die Helligkeit eines entsprechenden Bildes bestimmt werden kann; und wobei dieses Steuersignal die Schärfe des Ausgangsbildsignals so steuert, daß die Schärfe bei einer Luminanzkomponente, die einem hellen Bild und einem starken elektrischen Feld entspricht, ansteigt, und daß die Schärfe bei einer Luminanzkomponente vermindert wird, die einem dunklen Bild und einem schwachen elektrischen Feld entspricht.

8. Farbfernsehempfänger, in welchem ein Eingangsvideosignal verarbeitet wird, um ein Ausgangsbildsignal zu bilden, wobei der Empfänger aufweist:

eine Abtasteinrichtung (2) zur Unterteilung eines Halbbildes des Eingangsvideosignals in eine vorgegebene Anzahl von Bereichen und zum Abtasten der Bildinformation in jedem dieser Bereiche;

eine Speichereinrichtung (4) zum Speichern voreingestellter Einstelldaten; und

eine Rechenverarbeitungseinrichtung (3) zum Empfang der abgetasteten Bildinformation und der voreingestellten Einstelldaten, und zum Erzeugen eines Steuersignals auf der Grundlage

5

10

15

20

25

30

35

40

45

50

55

10



der abgetasteten Bildinformation und der voreingestellten Einstelldaten zum Steuern eines Farbpegels des Ausgangsbildsignals.

9. Empfänger nach Anspruch 8, wobei die abgetastete Bildinformation Daten enthält, die eine elektrische Feldstärke des Eingangsvideosignals darstellen. 5
10. Fernsehempfänger, in dem ein Eingangsvideosignal verarbeitet wird, um ein Ausgangsbildsignal zu bilden, wobei der Empfänger aufweist: 10
 - eine Abtasteinrichtung (2) zur Unterteilung eines Halbbildes des Eingangsvideosignals in eine vorgegebene Anzahl von Bereichen und zum Abtasten der Bildinformation in jedem dieser Bereiche; 15
 - eine Speichereinrichtung (4) zum Speichern voreingestellter Einstelldaten; und
 - eine Rechenverarbeitungseinrichtung (3) zum Empfang der abgetasteten Bildinformation und der gespeicherten, voreingestellten Einstelldaten, und zum Erzeugen eines Steuersignals auf der Grundlage der abgetasteten Bildinformation und der voreingestellten Einstelldaten zum Steuern der Schärfe des Ausgangsbildsignals. 20 25
11. Empfänger nach Anspruch 10, wobei die abgetastete Bildinformation Daten enthält, die eine elektrische Feldstärke des Eingangssignals darstellen. 30
12. Farbempfänger nach Anspruch 11, wobei die abgetastete Bildinformation weiter Daten enthält, die die Luminanz- und Farbkomponenten des Eingangsvideosignals darstellen. 35
13. Empfänger nach Anspruch 11, wobei die abgetastete Bildinformation weiter Daten enthält, die eine Luminanzkomponente des Eingangsvideosignals darstellen. 40

Revendications

1. Appareil d'affichage d'images de télévision, dans lequel un signal vidéo d'entrée est traité pour former un signal d'image de sortie pour affichage sur un écran d'affichage, ledit appareil comprenant: 45
 - des moyens d'échantillonnage (2) pour diviser une trame dudit signal vidéo d'entrée en une pluralité de zones et pour échantillonner les informations d'image dans chacune desdites zones; 50
 - des moyens formant mémoire (4) pour mémoriser des données de réglage préétablies; et 55

- des moyens de traitement arithmétique (3) pour recevoir les informations d'image échantillonnées et lesdites données de réglage préétablies et, sur la base de celles-ci, produire un signal de commande vidéo pour commander le signal d'image de sortie à afficher.

2. Appareil selon la revendication 1, dans lequel lesdites informations d'image qui sont échantillonnées comprennent un signal de luminance, et ledit signal de commande commande la luminosité dudit signal d'image de sortie à afficher.
3. Appareil selon la revendication 1, dans lequel lesdites informations d'image qui sont échantillonnées comprennent un signal de chrominance, et ledit signal de commande commande un niveau de couleur dudit signal d'image de sortie à afficher.
4. Appareil selon la revendication 1, dans lequel lesdites informations d'image qui sont échantillonnées comprennent des données représentant l'intensité du champ électrique dudit signal vidéo d'entrée, et ledit signal de commande commande un niveau de couleur dudit signal d'image de sortie à afficher.
5. Appareil selon la revendication 1, dans lequel lesdites informations d'image à afficher comprennent des données représentant l'intensité du champ électrique dudit signal vidéo d'entrée, et des données représentant une composante de luminance et une composante de chrominance dudit signal vidéo d'entrée; et dans lequel ledit signal de commande commande un niveau de couleur dudit signal d'image de sortie de manière à augmenter ledit niveau de couleur en réponse à un haut niveau de ladite composante de chrominance et également en réponse à une image claire représentée par ladite composante de luminance, et de manière à diminuer ledit niveau de couleur en réponse à un champ électrique faible dudit signal vidéo d'entrée et à une image sombre représentée par ladite composante de luminance.
6. Appareil selon la revendication 1, dans lequel ledit signal de commande vidéo est déterminé trame par trame.
7. Appareil selon la revendication 1, dans lequel lesdites informations d'image qui sont échantillonnées comprennent des données représentant l'intensité du champ électrique dudit signal vidéo d'entrée, et des données représentant une composante de luminance dudit signal vidéo



- d'entrée et à partir desquelles la clarté d'une image respective peut être déterminée; et dans lequel ledit signal de commande commande la netteté dudit signal d'image de sortie de manière à augmenter ladite netteté en réponse à une composante de luminance correspondant à une image claire et un champ électrique intense, et de manière à diminuer ladite netteté en réponse à une composante de luminance correspondant à une image sombre et un champ électrique faible.
8. Récepteur de télévision en couleurs, dans lequel un signal vidéo d'entrée est traité pour former un signal d'image de sortie, le récepteur comprenant:
- des moyens d'échantillonnage (2) pour diviser une trame dudit signal vidéo d'entrée en un nombre prédéterminé de zones et pour échantillonner les informations d'image dans chacune desdites zones;
 - des moyens formant mémoire (4) pour mémoriser des données de réglage préétablies; et
 - des moyens de traitement arithmétique (3) pour recevoir les informations d'image échantillonnées et lesdites données de réglage préétablies, et produire un signal de commande sur la base desdites informations d'image échantillonnées et desdites données de réglage préétablies pour commander un niveau de couleur dudit signal d'image de sortie.
9. Récepteur selon la revendication 8, dans lequel lesdites informations d'image échantillonnées représentent l'intensité de champ électrique dudit signal vidéo d'entrée.
10. Récepteur de télévision, dans lequel un signal vidéo d'entrée est traité pour former un signal d'image de sortie, le récepteur comprenant:
- des moyens d'échantillonnage (2) pour diviser une trame dudit signal vidéo d'entrée en un nombre prédéterminé de zones et pour échantillonner les informations d'image dans chacune desdites zones.
 - des moyens formant mémoire (4) pour mémoriser des données de réglage préétablies; et
 - des moyens de traitement arithmétique (3) pour recevoir les informations d'image échantillonnées et lesdites données de réglage préétablies mémorisées, et produire un signal de commande sur la base desdites informations d'image échantillonnées et desdites données de réglage préétablies pour commander la netteté dudit signal d'image de sortie.
11. Récepteur selon la revendication 10, dans lequel lesdites informations d'image échantillonnées comprennent des données représentant l'intensité du champ électrique dudit signal d'entrée.
12. Récepteur couleur selon la revendication 11, dans lequel lesdites informations d'image échantillonnées comprennent en outre des données représentant des composantes de luminance et de chrominance dudit signal vidéo d'entrée.
13. Récepteur selon la revendication 11, dans lequel lesdites informations d'image échantillonnées comprennent en outre des données représentant une composante de luminance dudit signal vidéo d'entrée.