

[0001] METHOD AND APPARATUS FOR IMPLEMENTING
 SPACE FREQUENCY BLOCK CODING

[0002] FIELD OF INVENTION

[0003] The present invention is related to wireless communication systems. More particularly, the present invention is related to a method and apparatus for implementing space frequency block coding (SFBC) in an orthogonal frequency division multiplexing (OFDM) wireless communication system.

[0004] BACKGROUND

[0005] OFDM is a data transmission scheme where data is split into a plurality of smaller streams and each stream is transmitted using a sub-carrier with a smaller bandwidth than the total available transmission bandwidth. The efficiency of OFDM depends on choosing these sub-carriers orthogonal to each other. The sub-carriers do not interfere with each other while each carrying a portion of the total user data.

[0006] OFDM system has advantages over other wireless communication systems. When the user data is split into streams carried by different sub-carriers, the effective data rate on each subcarrier is much smaller. Therefore, the symbol duration is much larger. A large symbol duration can tolerate larger delay spreads. In other words, it is not affected by multipath as severely. Therefore, OFDM symbols can tolerate delay spreads without complicated receiver designs. However, typical wireless systems need complex channel equalization schemes to combat multipath fading.

[0007] Another advantage of OFDM is that the generation of orthogonal sub-carriers at the transmitter and receiver can be done by using inverse fast Fourier transform (IFFT) and fast Fourier transform (FFT) engines. Since the IFFT and FFT implementations are well known, OFDM can be implemented easily and does not require complicated receivers.

[0008] Multiple-input multiple-output (MIMO) refers to the type of wireless transmission and reception scheme where both a transmitter and a receiver employ more than one antenna. A MIMO system takes advantage of the spatial diversity or spatial multiplexing and improves signal-to-noise ratio (SNR) and increases throughput.

[0009] SFBC is a scheme for transmitting symbols of a space diversity coding on neighboring subcarriers rather than on the same subcarrier in the successive time slots. The SFBC avoids the problem of fast time variations in space time block coding. However, the channel needs to be constant over the subcarriers that combining takes place.

[0010] SUMMARY

[0011] The present invention is related to a method and apparatus for implementing space frequency block coding (SFBC) in an orthogonal frequency division multiplexing (OFDM) wireless communication system. The present invention is applicable to both a closed loop mode and an open loop mode. In the closed loop mode, power loading and eigen-beamforming are performed based on channel state information (CSI). A channel coded data stream is multiplexed into two or more data streams. Power loading is performed based on the CSI on each of the multiplexed data streams. SFBC encoding is performed on the data streams for each of the paired subcarriers. Then, eigen-beamforming is performed based on the CSI to calculate eigenbeams over multiple transmit antennas. The power loading may be performed on two or more SFBC encoding blocks or on each eigenmodes. Additionally, the power loading may be performed across subcarriers or subcarrier groups for weak eigenmodes.

[0011a] According to the first aspect of the present invention, there is provided a base station comprising: a plurality of antennas; and circuitry configured to receive information including at least one channel quality indicator and at least one indication of a precoding matrix from a wireless transmit/receive unit (WTRU); wherein the channel quality indicator indicates modulation and coding information; wherein the circuitry is further configured based on the received information to process first data using a first modulation and coding and to process second data using a second modulation and coding; and wherein the circuitry is further configured to substantially simultaneously transmit the first data and the second data using orthogonal frequency division multiplexing (OFDM) spatial multiplexing over the plurality of antennas to the WTRU.

[0011b] According to the second aspect of the present invention, there is provided a wireless transmit/receive unit (WTRU) comprising: circuitry configured to wirelessly transmit information including at least one channel quality indicator and at least one indication of a precoding matrix to a base station; wherein the channel quality indicator indicates modulation and coding information; wherein the circuitry is further configured to wirelessly substantially simultaneously receive orthogonal

frequency division multiplexing (OFDM) spatially multiplexed first data processed using a first modulation and coding and second data processed using a second modulation and coding; wherein the circuitry is further configured to recover the first data and the second data.

[0011c] According to the third aspect of the present invention, there is provided a method comprising: wirelessly transmitting, by a wireless transmit/receive unit (WTRU), information including at least one channel quality indicator and at least one indication of a precoding matrix to a base station; wherein the channel quality indicator indicates modulation and coding information; and wirelessly substantially simultaneously receiving, by the WTRU, orthogonal frequency division multiplexing (OFDM) spatially multiplexed first data processed using a first modulation and coding and second data processed using a second modulation and coding; and recovering, by the WTRU, the first data and the second data from the received OFDM spatially multiplexed first data and second data.

[0011d] According to the fourth aspect of the present invention, there is provided a transmitter comprising: a plurality of transmit antennas; circuitry configured to generate a first channel coded data stream; wherein the circuitry is further configured to perform space frequency block coding (SFBC) encoding on the first channel coded data stream producing SFBC encoded data; wherein the circuitry is further configured to apply a precoding matrix to the SFBC encoded data to map the SFBC encoded data to the transmit antennas; wherein the precoding matrix applies weights to the SFBC encoded data; and wherein the circuitry is further configured to transmit the mapped SFBC encoded data over a plurality of subcarriers as an orthogonal frequency division multiplexed (OFDM) signal.

[0011e] According to the fifth aspect of the present invention, there is provided a transmitter comprising: a plurality of transmit antennas; a channel coder configured to generate a channel coded data stream; a multiplexer coupled to the channel coder, the multiplexer configured to multiplex the channel coded data stream into a plurality of data streams; a plurality of space frequency block coding (SFBC) encoders, each SFBC encoder configured to encode a respective one of the data streams over sub-carriers for each data rate that is transmitted; and circuitry configured to map each sub-carrier to a respective one of the transmit antennas using a preprocessing matrix.

[0012] In accordance with embodiments of the present invention, a robust channel estimation can be provided in all channel conditions, with or without channel information feedback, and low complexity is achieved at both transmitter and receiver. In addition, scalable solution can be used with any antenna configuration and backward compatibility is provided with enhanced

performance with 802.11a/g.

[0013] BRIEF DESCRIPTION OF THE DRAWINGS

[0014] Figure 1 is a block diagram of an OFDM-MIMO system implementing a closed loop mode.

[0015] Figure 2 is a block diagram of a system implementing open loop.

[0016] Figure 3 is a block diagram of a transmitter for depicting power loading.

[0017] Figure 4 is a diagram of an exemplary power loading and adaptive modulation and coding mapping between two pairs of modes.

[0018] Figure 5 shows an example of pairing of subcarrier groups for power/bit loading.

[0019] DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0020] Hereafter, the terminology "station" (STA) includes but is not limited to a user equipment, a wireless transmit/receive unit, a fixed or mobile subscriber unit, a pager, or any other type of device capable of operating in a wireless environment. When referred to hereafter, the terminology "access point" (AP) includes but is not limited to a Node-B, a base station, a site controller or any other type of interfacing device in a wireless environment.

[0021] The present invention will be described with reference to the drawing figures wherein like numerals represent like elements throughout. It should be noted that figures provided in the present invention are high level functional block diagrams and the functions implemented by the functional blocks may be implemented by more or less blocks. The features of the present invention may be incorporated into an integrated circuit (IC) or be configured in a circuit comprising a multitude of interconnecting components.

[0022] Embodiments of the present invention provide a transmitter implementing SFBC MIMO coding and receiver matched filter. Embodiments also provide transmitter channel precoding and receiver antenna processing as well as channel decomposition functions.

[0023] There are two modes of operation of the system: a closed loop and an open loop. The closed loop is used when channel state information (CSI) is available to the transmitter. The open loop is used when CSI is not available. A variant may be used for transmission to legacy STA where it provides diversity benefits.

[0024] In the closed loop mode, CSI is used to create virtual independent channels by decomposing and diagonalizing the channel matrix and by precoding at the transmitter. Given the eigenvalue spread of TGn channels the present invention employs a space-frequency orthogonal MIMO coding in the transmitter at the input to the channel precoder to increase robustness at the cost of decreasing data rate. Any coding scheme in MIMO has to deal with the diversity versus multiplexing gain trade off. It is desirable to have a trade off scheme that is best suited to particular channel statistics. An SFBC is chosen due to low mobility and the long coherence time of the channel. This scheme allows for receiver implementation simpler than a MMSE receiver. The combined solution enables higher throughput over a larger range. Embodiments of the present invention allow for per subcarrier power/bit loading and maintains a sustained robust link through closed loop operation with channel state feedback. Another potential benefit is that it is easily scalable to any number of antennas at both transmitter and receiver.

[0025] The CSI can be obtained at the transmitter either by feedback from the receiver or through exploiting channel reciprocity. Channel reciprocity is useful for mainly TDD based systems. In this case it is possible for the transmitter and receiver to independently estimate and decompose the channel. The channel update rate can be lowered when the SNR is high resulting in a reduced feedback bandwidth load. Latency requirements and feedback data rates are typically not significant to the inherent frequency non-selectivity of eigenvalues.

[0026] The closed loop mode requires calibrations of the transmitter to compensate amplitude and phase difference of the estimated channels in the uplink and downlink directions. This is done infrequently, for example during

STA association or under application control, and can use channel reciprocity for the estimation of the channel at both ends. In addition, a CQI (or SNR) per eigen-beam is fed back to the transmitter to support adaptive rate control.

[0027] Figure 1 is a block diagram of an OFDM-MIMO system 100 implementing a closed loop mode. The system 100 comprises a transmitter 110 and a receiver 130. The transmitter 110 comprises a channel encoder 112, a multiplexer 114, a power loading unit 116, a plurality of SFBC encoding units 118, a plurality of serial-to-parallel (S/P) converters 120, a plurality of eigen-beamformers 122, a plurality of IFFT units 124 and a plurality of transmit antennas (not shown). The channel encoder 112 encodes data preferably in accordance with a channel quality indicator (CQI) which is sent from the receiver 130. The CQI is used to determine a coding rate and modulation scheme per sub-carrier or group of sub-carriers. The coded data stream is multiplexed by the multiplexer 114 into two or more data streams.

[0028] The transmit power level of each data stream is adjusted by the power loading unit 116 based on feedback. The power loading unit 116 adjusts power levels with respect to the data rate of each eigenbeam to balance the total transmit power over all eigenbeams (or sub-carriers), which will be explained in detail below.

[0029] The SFBC encoding units 118 perform SFBC encoding on the data streams. SFBC encoding is done over eigen-beams and sub-carriers for each data rate that is transmitted. Eigen-beam and sub-carrier pairs are selected to ensure independent channels. OFDM symbols are carried on K sub-carriers. To accommodate SFBC, the sub-carriers are divided into L pairs of sub-carriers (or group of sub-carriers). The bandwidth of each group of sub-carriers should be less than the coherence bandwidth of the channel. However, when combined with eigen-beamforming this restriction is relaxed due to the frequency insensitivity of the eigen-beams.

[0030] The pairs of sub-carrier groups used by the block code are considered independent. The following is an example of the Alamouti type SFBC applied to an OFDM symbol:

$$S = \begin{bmatrix} s_1 & -s_2^* \\ s_2 & s_1^* \end{bmatrix}$$

[0031] Once the SFBC encoding units 118 construct OFDM symbols for all sub-carriers, the coded blocks are multiplexed by the S/P converters 120 and input to the eigen-beamformers 122. The eigen-beamformers 122 distribute the eigenbeams to the transmit antennas. The IFFT units 124 convert the data in frequency domain to the data in time domain.

[0032] The receiver 130 comprises a plurality of receive antennas (not shown), a plurality of FFT units 132, eigen-beamformers 134, SFBC decoding units 136, a combiner 138, a channel decoder 144, a channel estimator 140, a CSI generator 142 and a CQI generator 146.

[0033] The FFT units 132 convert the received samples to frequency domain and the eigen-beamformer 134, the SFBC decoding unit 136 and a channel decoder 144 perform the opposite operation which is performed at the transmitter 110. The combiner 138 combines the SFBC decoding results using maximal ratio combining (MRC).

[0034] The channel estimator 140 generates channel matrix using a training sequence transmitted from the transmitter and decomposes the channel matrix into two beam-forming unitary matrices U and V , (U for transmit and V for receive), and a diagonal matrix D per sub-carrier (or per sub-carrier group) by singular value decomposition (SVD) or eigenvalue decomposition. The CSI generator 142 generates CSI from the channel estimation results and the CQI generator generates a CQI based on the decoding results. The CSI and the CQI are sent back to the transmitter 110.

[0035] The channel matrix H between n_T transmit antennas and n_R receive antennas can be written as follows:

$$H = \begin{bmatrix} h_{1,1} & h_{1,2} & \cdots & h_{1,n_T} \\ h_{2,1} & h_{2,2} & \cdots & h_{2,n_T} \\ \vdots & \vdots & \ddots & \vdots \\ h_{n_R,1} & h_{n_R,2} & \cdots & h_{n_R,n_T} \end{bmatrix}$$

[0036] The channel matrix H is decomposed by SVD as follows:

$$H = UDV^H,$$

where U and V are unitary matrices and D is a diagonal matrix. $U \in \mathbb{C}^{n_R \times n_R}$ and $V \in \mathbb{C}^{n_T \times n_T}$. Then, for transmit symbol vector s , transmit precoding is simply performed as follows:

$$x = Vs \text{ (transmitted signal).}$$

[0037] The received signal becomes as follows:

$$y = HVs + n,$$

where n is the noise introduced in the channel. The receiver completes the decomposition by using a matched filter:

$$V^H H^H = V^H V D^H U^H = D^H U^H.$$

[0038] After normalizing channel gain for eigenbeams, the estimate of the transmit symbols s becomes

$$\begin{aligned} \hat{s} &= \alpha D^H U^H HVs + \eta \\ &= s + \eta \end{aligned}$$

[0039] s is detected without having to perform successive interference cancellation or MMSE type detector. $D^H D$ is a diagonal matrix that is formed by eigenvalues of H across the diagonal. Therefore, the normalization factor $\alpha = D^{-2}$. U are eigenvectors of HH^H , V are eigenvectors of $H^H H$ and D is a diagonal matrix of singular values of H (square roots of eigenvalues of HH^H).

[0040] Figure 2 is a block diagram of a system 200 implementing open loop mode in accordance with the present invention. The system 200 comprises a transmitter 210 and a receiver 230. In the open loop mode, a combination of space-frequency coding and spatial spreading in the

transmitter 210 provides diversity without requiring CSI. A variant of this scheme can be used when operating with legacy 802.11a/g STAs.

[0041] The transmitter 210 comprises a channel encoder 212, a multiplexer 214, a power loading unit 216, a plurality of SFBC encoding units 218, a plurality of serial-to-parallel (S/P) converters 220, a beamformer network (BFN) 222, a plurality of IFFT units 224 and a plurality of transmit antennas 226. As in the closed loop mode, the channel encoder 212 uses CQI to determine coding rate and modulation per sub-carrier or group of sub-carriers. The coded data stream is multiplexed by the multiplexer 214 into two or more data streams.

[0042] In the open loop, the eigen-beamformer is replaced with the Beam Forming Network (BFN) 222. The BFN 22 forms N beams in space, where N is the number of antennas 226. The beams are pseudo-randomly constructed by the BFN matrix operation. The independent sub-carrier groups used for the SFBC coding are transmitted on individual beams.

[0043] For legacy support, SFBC coding may not be performed. Instead diversity through beam permutation is performed which improves diversity and therefore the performance of legacy 802.11a/g equipment.

[0044] The receiver 230 comprises receive antennas 231, FFT units 232, a BFN 234, an SFBC decoding and combining unit 236 and a channel decoder 238. The FFT units 232 convert the received signal in time domain to the signal in frequency domain. The SFBC decoding and combining unit 236 decodes and combines symbols received from sub-carrier groups/eigen-beams and converts them from parallel to serial using a prior knowledge of the constellation size. Symbols are combined using MRC. The channel decoder 238 decodes the combined symbol and generates a CQI.

[0045] A first embodiment of power loading is explained hereinafter. The spatial processing is a combination of space-frequency coding and eigen-beamforming. This is performed to give the best compromise between the redundancy gains that SFBC affords and the spatial multiplexing that the eigen-beamformer provides. The power loading scheme operates across the

eigen-modes of the channel matrix. However, SFBC also introduces the constraint that the outputs of the coder have the same power loading no matter what the input power loading is due to the cross-operation inside the coder.

[0046] Figure 3 is a block diagram of a transmitter 110 for depicting power loading. Figure 3 illustrates 4x4 case as an example and the first embodiment of the power loading scheme will be explained with reference to 4x4 case. However, it should be noted that the 4x4 case can be extended to any other cases.

[0047] For a particular subcarrier k , four streams of data are mapped to 2 pairs of power loading/AMC modes. In other words the modulation order is selected the same for each pair of inputs. This is later mapped to pairs of eigenmodes. Output of the power loading unit 116 is applied to the dual 2x2 SFBC encoding units 118 and then passed on to the eigen-beamformer 122. The eigen-beamformer 122 maps the inputs to the eigen-modes of the channel through the preprocessing.

[0048] For all K subcarriers, the eigenvalues of the channel matrix are known at the transmitter. The channel energy for each eigenmode is defined as follows:

$$\alpha_i = \sum_{k=1}^K |\lambda_{i,k}|^2,$$

where $\lambda_{i,k}$ is the i -th eigenvalue for the k -th subcarrier's channel. Two SNIRs are defined for two coupled eigenmodes as follows:

$$\beta_{\text{mod1}} = \sum_{i=1}^{M/2} |\alpha_i|^2 \text{ and } \beta_{\text{mod2}} = \sum_{i=M/2+1}^M |\alpha_i|^2$$

where M is the number of eigenmodes. In other words, the eigenmodes are grouped such that half of the eigenmodes with the largest channel energy (or SNIR) are in one group and the other half with the weakest channel energies are in the other. Therefore, the harmonic SNIRs represent the total channel energy of the stronger and weaker eigenmodes. Channel energy is an indication of how robust the eigenmodes and hence the signal that is carried

over these eigenmodes would be. This information is used to apply different adaptivemodulation and coding (AMC) and/or different power loading for each half as is explained in more detail subsequently. The separation of the coupled SNIRs are defined as follows:

$$\Delta_{\beta} = \beta_{\text{mod1}} - \beta_{\text{mod2}}$$

[0049] During the closed loop operation the transmitter 110 has the knowledge of current CSI from which it extracts the eigenvalues and preprocessing matrix. The transmitter 110 also infers the data rate that can be supported in the link, R_b , from the CSI. Then, power loading for a given, acceptable, CQI is an optimization between the number of bits that can be sent per OFDM symbol and the type of modulation that is to be used for each mode.

[0050] Using the channel energy calculated for eigenmode i as explained above, the maximum bit rate that can be supported for the channel condition is determined. Then, using the mode separation calculation above it is determined how the bit rate needs to be distributed between the two pairs of modes. Figure 4 is a diagram of an exemplary power loading and adaptive modulation and coding mapping between two pairs of modes. In this example, the bit rate that can be supported is 24 bits per OFDM symbol for the particular sub-carrier. The lowest modulation order satisfying the bit rate is found in Figure 4 as indicated by the dashed arrow. In this example, first and second modes (first pair of coupled modes) will be using 16 QAM and third and fourth modes (second pair of coupled modes) will be using 256 QAM.

[0051] Note that this mapping is described for one CQI that is acceptable and for one subcarrier. In the case of alternative MIMO configurations, such as 2x4, 2x2, etc, the same power loading scheme is applicable except that the total number of bits in the table entries are scaled down to represent the transmit capability and that power loading can be done on a single pair of modes.

[0052] A power loading scheme in accordance with a second embodiment is explained hereinafter. The eigenvalues per subcarrier ($\lambda_1(k) > \lambda_2(k) > \dots >$

$\lambda_{nT}(k)$) are ranked and eigenbeams ($E^1, E^2, \dots, E^{nT}$) are created by grouping the same ranked eigenvalues for all subcarriers as follows:

$$E^i = \{\lambda_i(1), \lambda_i(2), \dots, \lambda_i(K)\} \text{ for } i = 1, 2, \dots, nT,$$

where K is the number of subcarriers, nT is the number of transmit antennas and $\lambda_i(j)$ is the i -th eigenvalue of the j -th subcarrier. nT is an even number.

[0053] The average of the eigenvalues per eigenbeam are computed as follows:

$$\lambda_{av}^i = \frac{1}{K} \sum_{j=1}^K \lambda_i(j) \quad \text{for } i = 1, 2, \dots, nT.$$

[0054] The eigenbeams are paired to create Alamouti space-frequency blocks, such as $\{E^1, E^2\}_1, \{E^3, E^4\}_2, \dots, \{E^{2i-1}, E^{2i}\}_i \dots \{E^{nT-1}, E^{nT}\}_{nT/2}$. However, if the SNR of a pair is greater than SNR_{max} , then the second eigenbeam of the pair is replaced with the eigenbeam with the next lower eigenvalue average until its SNR is less than or equal to SNR_{min} .

$$SNR(i) = (\lambda_{av}^i + \lambda_{av}^{i+1}) / \sigma_n^2,$$

where σ_n^2 is the noise variance and SNR_{min} is the minimum required SNR for the highest data rate for a required quality of service. This step is repeated until all the eigenbeams are paired. Figure 5 shows an example of pairing of subcarrier groups for power/bit loading.

[0055] A data rate for each pair of eigenbeams are determined by mapping the SNR of a pair to the data rate for a given quality. The required SNRs may be adjusted for all pairs of eigenbeams to compensate for the measurement errors and make the total transmit power be constant.

[0056] A weight vector per pair of eigenbeams per subcarrier may be computed as follows:

$$w_k(i, j) = \sqrt{\frac{SNR(i)\sigma_n^2}{2\lambda_i(j)}},$$

where i is the i -th pair of eigenbeams, j is the j -th subcarrier.

[0057] In accordance with the third embodiment, in addition to the first or second embodiment, another power loading is applied across the sub-

carriers or group of sub-carriers for weak eigen-modes. In other word, instead of power loading being applied to all eigenmodes it can be applied only to those that are weaker and hence can benefit from the power loading the most. In such a case, those eigenmodes that are not power loaded can still have SFBC or other coding or can have different AMC settings individually, whereas those eigenmodes that power loaded share the same AMC setting for instance. Also, the eigenmodes of the channel are always ordered in power, from strongest to weakest. By pairing eigenmodes of similar power one may improve the power loading of the channel.

[0058] A spatial processing scheme is configurable to any number of receive and transmit antenna combinations. Depending on the number of antennas on each side, a combination of SFBC and eigen-beamforming options are used. The table below summarizes the various configurations supported and the state of the spatial processing and power loading that is applicable to each scenario.

Antenna Configuration (Tx X Rx)	Space Frequency Block Code	Eigen-Beamforming
M X N (M, N $\neq$ 1)	M/2 block codes	M beams at Tx N beams at Rcv
1 X N (N $\neq$ 1)	not used	To be determined by receiver vendor
M X 1 (M $\neq$ 1)	M/2 block codes	M beams at Tx

Table 1

[0059] Although the features and elements of the present invention are described in the preferred embodiments in particular combinations, each feature or element can be used alone without the other features and elements of the preferred embodiments or in various combinations with or without other features and elements of the present invention.

*

*

*

CLAIMS

What is claimed is:

1. A base station comprising:
a plurality of antennas; and
circuitry configured to receive information including at least one channel quality indicator and at least one indication of a precoding matrix from a wireless transmit/receive unit (WTRU); wherein the channel quality indicator indicates modulation and coding information;
wherein the circuitry is further configured based on the received information to process first data using a first modulation and coding and to process second data using a second modulation and coding; and
wherein the circuitry is further configured to substantially simultaneously transmit the first data and the second data using orthogonal frequency division multiplexing (OFDM) spatial multiplexing over the plurality of antennas to the WTRU.
2. The base station of claim 1 wherein the first modulation and coding and the second modulation and coding are different.
3. The base station of claim 1 wherein the received information includes a plurality of channel quality indicators; wherein each of the plurality of channel quality indicators corresponds to a group of subcarriers.
4. The base station of claim 1 wherein the first data and the second data are processed with different modulation orders.
5. The base station of claim 1 wherein the first data and the second data correspond to four streams transmitted using the plurality of antennas.
6. The base station of claim 5 wherein the plurality of antennas are four antennas.

7. A wireless transmit/receive unit (WTRU) comprising:
circuitry configured to wirelessly transmit information including at least one channel quality indicator and at least one indication of a precoding matrix to a base station; wherein the channel quality indicator indicates modulation and coding information;

wherein the circuitry is further configured to wirelessly substantially simultaneously receive orthogonal frequency division multiplexing (OFDM) spatially multiplexed first data processed using a first modulation and coding and second data processed using a second modulation and coding; wherein the circuitry is further configured to recover the first data and the second data.

8. The WTRU of claim 7 wherein the first modulation and coding and the second modulation and coding are different.

9. The WTRU of claim 7 wherein the transmitted information includes a plurality of channel quality indicators; wherein each of the plurality of channel quality indicators corresponds to a group of subcarriers.

10. The WTRU of claim 7 wherein the first data and the second data are received with different modulation orders.

11. A method comprising:
wirelessly transmitting, by a wireless transmit/receive unit (WTRU), information including at least one channel quality indicator and at least one indication of a precoding matrix to a base station; wherein the channel quality indicator indicates modulation and coding information; and
wirelessly substantially simultaneously receiving, by the WTRU, orthogonal frequency division multiplexing (OFDM) spatially multiplexed first data processed using a first modulation and coding and second data processed using a second modulation and coding; and
recovering, by the WTRU, the first data and the second data from the received OFDM spatially multiplexed first data and second data.

12. The method of claim 11 wherein the first modulation and coding and the second modulation and coding are different.

13. The method of claim 11 wherein the transmitted information includes a plurality of channel quality indicators; wherein each of the plurality of channel quality indicators corresponds to a group of subcarriers.

14. The method of claim 11 wherein the first data and the second data are received with different modulation orders.

15. A transmitter comprising:
a plurality of transmit antennas;
circuitry configured to generate a first channel coded data stream;
wherein the circuitry is further configured to perform space frequency block coding (SFBC) encoding on the first channel coded data stream producing SFBC encoded data;
wherein the circuitry is further configured to apply a precoding matrix to the SFBC encoded data to map the SFBC encoded data to the transmit antennas; wherein the precoding matrix applies weights to the SFBC encoded data; and
wherein the circuitry is further configured to transmit the mapped SFBC encoded data over a plurality of subcarriers as an orthogonal frequency division multiplexed (OFDM) signal.

16. The transmitter of claim 15 wherein the precoding matrix is derived using an open loop mode.

17. The transmitter of claim 15 wherein the sub-carriers are divided into groups of sub-carriers.

18. The transmitter of claim 16 wherein the circuitry is further configured to transmit a second channel coded data stream using a closed loop mode.

19. The transmitter of claim 15 wherein the transmitter is a base station.
20. A transmitter comprising:
a plurality of transmit antennas;
a channel coder configured to generate a channel coded data stream;
a multiplexer coupled to the channel coder, the multiplexer configured to multiplex the channel coded data stream into a plurality of data streams;
a plurality of space frequency block coding (SFBC) encoders, each SFBC encoder configured to encode a respective one of the data streams over sub-carriers for each data rate that is transmitted; and
circuitry configured to map each sub-carrier to a respective one of the transmit antennas using a preprocessing matrix.
21. The transmitter of claim 20 wherein orthogonal frequency division multiplexing (OFDM) symbols are carried on the sub-carriers.
22. The transmitter of claim 20 wherein the sub-carriers are divided into groups of sub-carriers.
23. The transmitter of claim 22 wherein each group of sub-carriers has a bandwidth that is less than a coherence bandwidth of the channel.
24. The transmitter of claim 20 wherein the transmitter is a base station.