

PROCESS FOR FABRICATING A RECEIVER SUBSTRATE FOR A SEMICONDUCTOR-ON-INSULATOR STRUCTURE FOR RADIOFREQUENCY APPLICATIONS AND PROCESS FOR FABRICATING SUCH A STRUCTURE

TECHNICAL FIELD OF THE INVENTION

The present invention relates to the fabrication of a substrate, called the “receiver substrate”, for producing a semiconductor-on-insulator structure for radiofrequency applications. The invention also relates to a process for fabricating such a structure via transfer of a layer of a second substrate, called the “donor substrate”, to the receiver substrate.

PRIOR ART

In the context of fabrication of a semiconductor-on-insulator structure (acronym SeOI), a particular example thereof being a silicon-on-insulator (SOI) structure when the semiconductor is silicon, a donor substrate is bonded to a receiver substrate.

Generally, the donor substrate comprises a single-crystal semiconductor substrate, for example a single-crystal silicon substrate, and the receiver substrate comprises at least one base substrate in particular intended to serve as carrier for a thin semiconductor layer that must be transferred from the donor substrate to the receiver substrate.

An oxide layer is formed on the donor substrate or on the receiver substrate, so that said oxide layer is located at the bonding interface after the donor substrate and the receiver substrate have been bonded. The oxide layer is then said to be “buried”, and called the “BOX” for Buried OXide.

For radiofrequency (RF) applications, a polysilicon (polycrystalline silicon) layer is integrated into the receiver substrate under the buried oxide layer, in order to trap electrical charge present at the interface between the base layer and the buried oxide layer. This polysilicon layer is arranged on the base layer of the receiver substrate before bonding.

The oxide layer is formed either on the substrate made of single-crystal semiconductor of the donor substrate, using a first process called “direct bonding”, or on the polysilicon layer of the receiver substrate, using a second process called “reverse bonding”.

With reference to Figure 1, in the direct-bonding process a receiver substrate 10 comprising a base substrate 1 covered with a charge-trapping layer 2 made of polysilicon (polycrystalline silicon), and a donor substrate 20 comprising a substrate 4 made of single-crystal semiconductor, are provided. The substrate made of single-crystal material of the donor substrate is oxidized to form an oxide layer 3.

Next, atomic species are implanted into the layer 4 made of single-crystal material through the oxide layer 3, in order to form a zone called the “weakened zone” in said layer

made of single-crystal material. The weakened zone is created at a defined depth that corresponds substantially to the thickness of the layer to be transferred. The layer to be transferred then comprises the oxide layer and a segment of the single-crystal substrate.

The donor substrate 20 is then bonded to the receiver substrate 10, the polysilicon layer 2 and the oxide layer 3 being at the bonding interface, then the donor substrate 20 is detached along the weakened zone, so as to transfer the oxide layer 3 and the segment of single-crystal substrate to the receiver substrate 10.

The direct-bonding process has the drawback that the oxide layer is located on the donor substrate. Thus, during the implantation, the atomic species must pass through the oxide layer before reaching the single-crystal layer, this requiring a high implantation energy. Now, the higher the implantation energy, the larger the amount of ions to be implanted must be, and the lower the implantation current (current density), this leading to an increase in production cost, limiting the feasibility of the process, and in particular limiting the maximum thickness of the oxide layer. In addition, this process decreases the reusability of the donor substrate, since some of the donor substrate is consumed to form the oxide layer.

With reference to Figure 2, in the reverse-bonding process a receiver substrate 10 comprising a base substrate 1 covered with a charge-trapping layer 2 made of polysilicon, and a donor substrate 20 comprising a substrate 4 made of single-crystal semiconductor, are provided. However, in contrast to the direct-bonding process, the oxide layer 3 is formed directly on the receiver substrate 10 via oxidation of the charge-trapping layer 2.

To form the weakened zone, the implantation of atomic species is then carried out directly into the layer 4 made of single-crystal material of the donor substrate, and does not pass through the oxide layer 3. The layer to be transferred then solely comprises a segment of the single-crystal substrate.

The donor substrate is then bonded to the receiver substrate, the single-crystal substrate and the oxide layer being at the bonding interface, then the donor substrate is detached along the weakened zone, so as to transfer the segment of single-crystal substrate to the receiver substrate.

The reverse-bonding process allows production cost to be decreased and the reusability of the donor substrate to be improved.

In contrast, the oxide layer formed on the polysilicon layer has a breakdown voltage (V_{bd}) that is too low, with respect to that obtained by growth on the single-crystal material of the donor substrate (in particular when it is a question of single-crystal silicon) in the direct-bonding process. The breakdown voltage is too low to be compatible with radiofrequency applications.

To illustrate this statement, Figure 3 shows a graph that plots the variation in the electrical current, amperes (A), as a function of electric field, in megavolts per centimetre

(MV/cm), for various receiver substrates in which the buried oxide layer was formed by direct bonding (substrate such as that in Figure 1) or by reverse bonding (substrate such as that in Figure 2) according to the prior art.

The two curves on the right in the graph, referenced D_1 and D_2 , correspond to two substrates obtained by direct bonding. In these two substrates, the oxide layer was formed by oxidation of the single-crystal semiconductor of the donor substrate and was then transferred to the charge-trapping layer.

The five curves on the left in the graph, referenced I_1 , I_2 , I_3 , I_4 , and I_5 , correspond to five substrates obtained by reverse bonding. In the substrates, the oxide layer was formed by oxidation of the charge-trapping layer made of polycrystalline silicon of the receiver substrate.

The electrical current was measured between ground and the free surface of the substrate by way of a piece of aluminium arranged on the oxide layer and a measurement probe.

Regarding the direct bonding, the two curves D_1 and D_2 exhibit a break in slope corresponding to a maximum electric field that the substrate may withstand before short-circuit of about 7 MV/cm. The value of the maximum electric field corresponding to the curve D_2 is slightly higher than that corresponding to the curve D_1 .

Regarding the reverse bonding, the five curves I_1 , I_2 , I_3 , I_4 , and I_5 exhibit a break in slope corresponding to a maximum electric field that the substrate may withstand before short-circuit of about 3 MV/cm. The value of the maximum electric field increases between I_1 and I_5 .

By comparison it may be seen that the value of the maximum electric field is clearly lower for substrates obtained by reverse bonding with respect to those obtained by direct bonding. The average distance between the two sets of curves is about 4 MV/cm.

Fabrication of a substrate by reverse bonding therefore induces a drop in the maximum electric field, this resulting in a corresponding drop in breakdown voltage.

BRIEF DESCRIPTION OF THE INVENTION

Embodiments of the invention seek to provide a process allowing the aforementioned drawbacks to be overcome. Embodiments of the invention aim to provide such a process allowing a receiver substrate to be fabricated for a semiconductor-on-insulator structure the buried oxide layer of which may possess a sufficient breakdown voltage for radiofrequency applications, while limiting production cost.

An aspect of the invention provides a process for fabricating a receiver substrate for a semiconductor-on-insulator structure for radiofrequency applications, comprising the following steps:

- providing a semiconductor substrate comprising a base substrate made of single-crystal material and a charge-trapping layer made of polysilicon arranged on the base substrate,
- oxidizing the charge-trapping layer in order to form an oxide layer arranged on said charge-trapping layer,

the process mainly being characterized in that the charge-trapping layer is oxidized at least partially at a temperature lower than or equal to 875°C, in the following way:

- starting the oxidation at a first temperature higher than 750°C and lower than or equal to 1000°C,
- decreasing the temperature to a second temperature below the first temperature and comprised between 750°C and 875°C,
- continuing the oxidation at the second temperature.

The temperatures lower than or equal to 875°C are lower than the temperatures at which the oxidation of a trapping layer is usually carried out in the prior art. Specifically, the applicant has discovered, surprisingly, that decreasing the temperature of oxidation of the charge-trapping layer allows the breakdown voltage of the formed oxide layer to be increased, contrary to what those skilled in the art in the field of radio frequencies would expect based on their current knowledge, such as in particular illustrated by publication [1].

The oxidation of the charge-trapping layer made of polysilicon consumes the polysilicon, and the rate of formation of the oxide depends on the crystal orientation of the polysilicon grains. Thus, the fact that the crystal grains of the polysilicon layer are oriented differently causes the silicon oxide formed from these grains to grow at different rates. For example, the oxide grows at a different rate in the <100> direction and in the <111> direction, from grains oriented in the same <100> and <111> directions. The indices <100> and <111> are Miller indices, which allow the orientation of the planes in a crystal to be determined, and therefore the orientation of the crystal grains in the crystal structure to be expressed.

These differences in the growth rate of the oxide depending on the orientation of the crystal grains of the polysilicon generate mechanical stresses within the crystal structure, and most particularly at the interface between the oxide layer in growth and the subjacent polysilicon layer. As the volume of the oxide layer in growth increases and as the oxidation progresses, these stresses are amplified at the polysilicon surface.

According to embodiments, the process has the following various features, which may be implemented alone or in technically feasible combinations thereof:

- the charge-trapping layer is oxidized at least partially at a temperature higher than or equal to 750°C. The oxidation rate is thus more compatible with industrial requirements and remains economically viable;
- the decrease in the temperature from the first temperature T_1 to the second temperature T_2 is gradual;

- at least 50%, and preferably at least 70%, of the thickness of the oxide layer is produced at the first temperature T_1 , and at least 20%, and preferably at least 30%, of the thickness of the oxide layer is produced at the second temperature T_2 ;
- the formed oxide layer has a thickness comprised between 200 nm and 400 nm;
- the charge-trapping layer has a thickness comprised between 20 nm and 500 nm;
- the charge-trapping layer is deposited beforehand on the base substrate made of single-crystal material by low-pressure chemical vapour deposition in a reactor.

Another aspect of the invention provides a process for fabricating a semiconductor-on-insulator structure for radiofrequency applications, characterized in that it comprises the following steps:

- fabricating a receiver substrate such as described above,
- providing a donor substrate comprising single-crystal substrate,
- bonding the donor substrate to the receiver substrate,
- transferring a layer of the donor substrate to the receiver substrate.

According to embodiments, the process has the following various features, which may be implemented alone or in technically feasible combinations thereof:

- the layer transferred from the donor substrate comprises a semiconductor;
- the layer transferred from the donor substrate comprises a ferroelectric material;
- the ferroelectric material is chosen from: LiTaO_3 , LiNbO_3 , LiAlO_3 , BaTiO_3 , PbZrTiO_3 , KNbO_3 , BaZrO_3 , CaTiO_3 , PbTiO_3 , KTaO_3 .
- said transfer comprises the following steps:
 - implanting atomic species in the donor substrate so as to form a weakened zone that delineates a layer of single-crystal semiconductor or ferroelectric material to be transferred,
 - bonding the donor substrate to the receiver substrate, the oxide layer and the layer of single-crystal semiconductor or ferroelectric material to be transferred being at the bonding interface,
 - detaching the donor substrate along the weakened zone in order to transfer the layer of single-crystal semiconductor or ferroelectric material to the receiver substrate, the oxide layer being arranged between the charge-trapping layer and the transferred layer of single-crystal semiconductor or ferroelectric material.

The single-crystal semiconductor or ferroelectric material preferably lies at the surface of the donor substrate, the implantation of atomic species being carried out directly through said surface.

DESCRIPTION OF THE FIGURES

Other advantages and features of the invention will become apparent on reading the following description given by way of illustrative and nonlimiting example, with reference to the following appended figures:

Figure 1 is a diagram illustrating the fabrication of a semiconductor-on-insulator substrate for radiofrequency applications by direct bonding;

Figure 2 is a diagram illustrating the fabrication of a semiconductor-on-insulator substrate for radiofrequency applications by reverse bonding;

Figure 3 is a graph that shows the variation in the magnitude of the current as a function of electric field, for various receiver substrates in which the buried oxide layer was formed by direct bonding or by reverse bonding according to the prior art;

Figure 4 is a graph that shows the growth time of an oxide layer of a thickness of 400 nm for oxide crystals of <100> and <111> Miller indices as a function of temperature;

Figure 5 is a graph that shows the variation in the difference between the two curves of Figure 4 as a function of temperature;

Figure 6 is a schematic of the substrate of Figure 2 obtained after oxidation of the charge-trapping layer, and having a convex curvature;

Figure 7 is a graph that shows the variation in the magnitude of the current as a function of electric field, for various receiver substrates in which the buried oxide layer was formed by reverse bonding according to the invention.

For the sake of legibility of the figures, the various layers forming the substrates are not necessarily shown to scale.

DETAILED DESCRIPTION OF EMBODIMENTS OF THE INVENTION

The present invention relates to a process for fabricating a receiver substrate (30) for a semiconductor-on-insulator structure for radiofrequency applications, comprising the following steps:

The process according to the invention is a reverse-bonding process. It comprises, with reference to Figure 2, a step of providing a semiconductor substrate 10 comprising a base substrate 1 made of single-crystal material and a charge-trapping layer 2 made of polysilicon arranged on the base substrate, followed by a step of oxidizing the charge-trapping layer 2 to form an oxide layer 3 arranged on said charge-trapping layer.

The charge-trapping layer 2 may be formed by epitaxy on the base substrate 1, or alternatively deposited on said base substrate in particular by chemical vapour deposition (CVD).

The charge-trapping layer 2 is oxidized at least partially at a temperature comprised between 750°C and 875°C.

Such a process makes it possible to form, by reverse bonding, a receiver substrate 30 the oxide layer of which has a higher breakdown voltage than when the oxidation is carried out at a temperature above 875°C.

The formed oxide layer 3 has a thickness of a few hundred nanometres (nm), and preferably a thickness comprised between 200 nm and 400 nm.

The charge-trapping layer remaining after the oxidation preferably has a thickness comprised between 20 nm and 500 nm.

The expression “at least partially” means that the entirety of the oxidation is carried out at a temperature comprised between 750°C and 875°C, or that only some of the oxidation is carried out at a temperature comprised between 750°C and 875°C.

According to one embodiment, to begin with the charge-trapping layer 2 is oxidized at a temperature T_1 comprised between 750°C and 1000°C, then the temperature is decreased, directly or gradually, until a temperature T_2 lower than T_1 and comprised between 750°C and 875°C is reached, the oxidation then being continued.

The temperature T_1 may therefore be lower than 875°C, or indeed higher than 875°C and for example equal to 900°C or to 950°C.

In this embodiment, the upper segment of the oxide layer 3 is produced at the temperature T_1 , whereas the lower segment of the oxide layer 3 is produced at the temperature T_2 , which is lower than T_1 . Specifically, the charge-trapping layer 2 is oxidized from its upper face to its lower face, and the oxidation interface moves from the upper face to the lower face as the reaction advances.

This embodiment allows the oxidation rate of the upper segment of the charge-trapping layer 2 to be increased since oxidation rate increases with temperature, and therefore the time required to oxidize the trapping layer to be decreased.

The increase in the breakdown voltage of the oxide layer 3 is observed both in the case where the entirety of the oxidation is carried out at a temperature comprised between 750°C and 875°C, and in the case where only some of the oxidation is carried out at a temperature comprised between 750°C and 875°C. Specifically, it is simply necessary for at least one segment of the charge-trapping layer 2, which extends from the interface between said charge-trapping layer and the base substrate towards the free surface of the charge-trapping layer, to be oxidized at a temperature comprised between 750°C and 875°C.

It is possible to adjust the oxidation parameters in order to minimize the segment of the charge-trapping layer produced at the temperature comprised between 750°C and 875°C, and therefore the total length of the oxidation step.

According to one embodiment, at least 50%, and preferably at least 70%, of the thickness of the oxide layer 3 is produced at the first temperature T_1 , and at least 20%, and

preferably at least 30%, of the thickness of the oxide layer is produced at the second temperature T_2 ;

A study of the variation in the time taken to grow an oxide layer as a function of temperature has been carried out, for crystals of different crystal orientations.

Figure 4 is a graph that shows the growth time (in hours) of an oxide layer of a thickness of 400 nm as a function of temperature (in degrees Celsius) for oxide crystals with the Miller indices $\langle 100 \rangle$ (curve E_1) and $\langle 111 \rangle$ (curve E_2).

Figure 5 is a graph that shows the relative difference in growth rate Δv (in relative percent) between oxide crystals with the Miller indices $\langle 100 \rangle$ (curve E_1) and $\langle 111 \rangle$ (curve E_2) of Figure 4 as a function of temperature (in degrees Celsius).

These results show that the lower the temperature, the larger the difference in growth rate between the crystals of different $\langle 100 \rangle$ and $\langle 111 \rangle$ crystal orientations. In particular, this relative difference is about 48% when the temperature is 875°C, then increases for temperatures lower than 875°C to above 50%.

In contrast, the higher the temperature, the smaller the difference in growth rate between the crystals of different $\langle 100 \rangle$ and $\langle 111 \rangle$ crystal orientations. In particular, this difference is about 9% when the temperature is 1200°C.

In addition, the oxidation time increases very greatly for temperatures lower than 1000°C, and even further for temperatures lower than 850°C. Thus, it is desirable not to drop below 750°C in order for the process to be able to be carried out in a time compatible with industrial requirements and to remain economically viable.

The oxidation of the charge-trapping layer 2 is accompanied by the oxidation of the opposite side of the base substrate 1. On account of the difference in materials between the two sides of the substrate, the semiconductor substrate 10 comprising the base substrate 1 and the charge-trapping layer 2 deforms. This deformation affects the entire substrate, i.e. the curvature of the substrate in its entirety is modified such that it becomes concave or convex. When the substrate is disc-shaped, it will have a generally parabolic shape after deformation.

More precisely, during the oxidation, the charge-trapping layer 2 sustains the mechanical stresses of the oxide layer 3 in growth. The substrate then deforms convexly.

The terms “convex” and “concave” are to be understood with respect to the curvature of the side of the substrate 30 that is intended to form the bonding interface with the donor substrate described below in the present text, which side is referred to as the “front side”. Thus, the substrate is said to be “convex” when the curvature of the front side is convex, and said to be “concave” when the curvature of the front side is concave.

The substrate 30 shown in Figure 6 has deformed convexly. The front side 31 is the upper side. The back side 32 is parallel to the front side.

The curvature of the substrate is typically quantified via an amplitude parameter called bow and denoted Bw.

Bw corresponds to the distance between the central point C of the median plane Pm (shown by the dashed line) of the substrate and a reference plane P corresponding to a reference holder on which the substrate rests. Bw is positive in the case of a convex curvature (as shown in Figure 6) and negative in the case of a concave curvature.

The applicant has furthermore noted that carrying out at least some of the oxidation of the charge-trapping layer 2 at a lower temperature than in the prior art, and in particular at a temperature comprised between 750°C and 875°C, allows bow Bw to be decreased. The differences in curvature between the lower surface of the charge-trapping layer 2 at the interface with the base substrate 1 and the upper surface of the charge-trapping layer at the interface with the oxide 3 are thus decreased, this thus decreasing mechanical stresses within the charge-trapping layer.

From the receiver substrate 30 obtained using the process described above, a semiconductor-non-insulator structure for radiofrequency applications is fabricated, using a fabricating process the steps of which are described below.

The receiver substrate 30, which comprises, in succession, the base substrate 1, the charge-trapping layer 2, and the oxide layer 3, is provided. A second substrate, called the donor substrate, which is made of a single-crystal material, is also provided.

Preferably, the donor substrate comprises a semiconductor substrate.

A weakened zone is formed in said donor substrate, so as to delineate a layer to be transferred.

The layer to be transferred is preferably a semiconductor layer.

The weakened zone is formed in the donor substrate at a predefined depth that corresponds substantially to the thickness of the layer to be transferred. Preferably, the weakened zone is created by implanting atomic species, for example hydrogen and/or helium atoms, into the donor substrate. In practice, the implantation of the atomic species is preferably carried out directly through the single-crystal material at the free surface of the donor substrate.

The donor substrate is then bonded to the receiver substrate. The oxide layer and the layer to be transferred are located at the bonding interface.

The donor substrate is then detached along the weaken zone, in order to transfer the layer to the receiver substrate (Smart Cut™ process). The final structure, in which the oxide layer is arranged between the charge-trapping layer and the transferred layer, is thus obtained.

Alternatively, the layer may be transferred by thinning the donor substrate from its side opposite the bonding interface, until the thickness desired for the layer is obtained.

According to one embodiment, the layer to be transferred of the donor substrate comprises a ferroelectric material.

The ferroelectric material is advantageously chosen from: LiTaO_3 , LiNbO_3 , LiAlO_3 , BaTiO_3 , PbZrTiO_3 , KNbO_3 , BaZrO_3 , CaTiO_3 , PbTiO_3 and KTaO_3 .

The donor substrate of said single-crystal layer to be transferred may take the form of a circular wafer of standardized size, for example of 150 mm or 200 mm diameter. The invention is not however in any way limited to these dimensions or to this form. The wafer may have been obtained from an ingot of ferroelectric material, in such a way as to form a donor substrate having a preset crystal orientation. Alternatively, the donor substrate may comprise a layer of ferroelectric material joined to a carrier substrate.

The crystal orientation of the single-crystal layer of ferroelectric material to be transferred is chosen depending on the intended application. Thus, as regards the material LiTaO_3 , it is conventional to choose an orientation comprised between 30° and 60°XY , or between 40° and 50°XY , in particular in the case where it is desired to exploit the properties of the thin layer to form a SAW filter (SAW being the acronym of Surface Acoustic Wave). As regards the material LiNbO_3 , it is conventional to choose an orientation of about 128°XY . However, the invention is not in any way limited to a particular crystalline orientation.

Whatever the crystal orientation of the ferroelectric material of the donor substrate, the process for example comprises introducing hydrogen and/or helium species (ions and/or atoms) into this donor substrate. This introduction may for example correspond to a hydrogen implantation, i.e. a hydrogen ion bombardment of the planar face of the donor substrate.

As is known *per se*, the aim of the implanted ions is to form a weakened plane delineating a first layer of ferroelectric material to be transferred, which layer is located on the side of the face, and another portion forming the rest of the substrate. The nature, the dose of the implanted species and the type of ions implanted, and the implantation energy, are chosen depending on the thickness of the layer that it is desired to transfer and on the physicochemical properties of the donor substrate. In the case of a donor substrate made of LiTaO_3 , it may thus be chosen to implant a dose of hydrogen of between $1\text{E}16$ and $5\text{E}17$ at/cm^2 with an energy of between 30 and 300 keV to delineate a first layer of about 20 to 2000 nm thickness.

EXPERIMENTAL RESULTS

Variation in the magnitude of the electrical current in the structure as a function of electric field.

To illustrate the advantages achieved using the process of the invention described above, a study of the variation in the electrical current in the structure as a function of electric field was carried out.

Figure 7 shows a graph that plots the variation in the magnitude of the current, in amperes (A) multiplied by a factor of 100 in order to make the graph more legible, as a function of electric field, in megavolts per centimetre (MV/cm), for various substrates obtained by reverse bonding according to the invention. Said substrates differ in the conditions of formation of the oxidation of the receiver substrate used to form the buried oxide layer.

The electrical current was measured between ground and the free surface of the substrate by way of a piece of aluminium arranged on the oxide layer and a measurement probe.

The curves referenced C_{ref} , C_1 , C_2 , C_3 , C_4 , and C_5 plot the following:

- the curve C_{ref} corresponds to a reference, i.e. a substrate obtained by direct bonding, with an oxide layer of 4000 angströms. It has a break in slope corresponding to a maximum electric field of about 7 MV/cm;
- the curve C_1 corresponds to an oxidation entirely carried out at 850°C without additional anneal. It has a maximum electric field of about 6 MV/cm;
- the curve C_2 corresponds to an oxidation carried out at 950°C then the temperature of which was increased to 1100°C in a conventional oven for 1 hour. It has a maximum electric field of about 3.7 MV/cm;
- the curve C_3 corresponds to an oxidation entirely carried out at 950°C without thermal anneal. It has a maximum electric field of about 3.5 MV/cm;
- the curve C_4 corresponds to an oxidation entirely carried out at 950°C followed by a rapid thermal anneal (RTA) of 45 seconds at 1100°C. It has a maximum electric field of about 2.8 MV/cm;
- the curve C_5 corresponds to an oxidation entirely carried out at 1000°C followed by a rapid thermal anneal (RTA) of 45 seconds at 1100°C. It has a maximum electric field of about 2.8 MV/cm.

These results show that a decrease in the oxidation temperature allows the maximum electric field to be increased, this resulting in a corresponding increase in breakdown voltage.

REFERENCES

[1]: *Effect of Physical Stress on the Degradation of Thin SiO₂ Films Under Electrical Stress*, Tien-Chun Yang, 2000 IEEE.

CLAIMS

1. Process for fabricating a receiver substrate for a semiconductor-on-insulator structure for radiofrequency applications, comprising the following steps:
 - providing a semiconductor substrate comprising a base substrate made of single-crystal material and a charge-trapping layer made of polysilicon arranged on the base substrate,
 - oxidizing the charge-trapping layer in order to form an oxide layer arranged on said charge-trapping layer,the process being characterized in that the charge-trapping layer is oxidized at least partially at a temperature lower than or equal to 875°C, in the following way:
 - starting the oxidation at a first temperature higher than 750°C and lower than or equal to 1000°C,
 - decreasing the temperature to a second temperature below the first temperature and comprised between 750°C and 875°C,
 - continuing the oxidation at the second temperature.
2. Process according to Claim 1, wherein the charge-trapping layer is oxidized at least partially at a temperature higher than or equal to 750°C.
3. Process according to Claim 1 or Claim 2, wherein the decrease in the temperature from the first temperature to the second temperature is gradual.
4. Process according to one of Claims 1 to 3, wherein at least 50%, and preferably at least 70%, of the thickness of the oxide layer is produced at the first temperature, and at least 20%, and preferably at least 30%, of the thickness of the oxide layer is produced at the second temperature.
5. Process according to any one of the preceding claims, wherein the formed oxide layer has a thickness comprised between 200 nm and 400 nm.
6. Process according to any one of the preceding claims, wherein the charge-trapping layer has a thickness comprised between 20 nm and 500 nm.
7. Process according to any one of the preceding claims, wherein the charge-trapping layer is deposited beforehand on the base substrate made of single-crystal material by low-pressure chemical vapour deposition in a reactor.

8. Process for fabricating a semiconductor-on-insulator structure for radiofrequency applications, characterized in that it comprises the following steps:
 - fabricating a receiver substrate according to any one of the preceding claims,
 - providing a donor substrate comprising single-crystal substrate,
 - bonding the donor substrate to the receiver substrate,
 - transferring a layer of the donor substrate to the receiver substrate.
9. Process according to Claim 8, wherein the layer transferred from the donor substrate comprises a semiconductor.
10. Process according to Claim 8, wherein the layer transferred from the donor substrate comprises a ferroelectric material.
11. Process according to Claim 10, wherein the ferroelectric material is chosen from: LiTaO_3 , LiNbO_3 , LiAlO_3 , BaTiO_3 , PbZrTiO_3 , KNbO_3 , BaZrO_3 , CaTiO_3 , PbTiO_3 , KTaO_3 .
12. Process according to one of Claims 8 to 11, wherein said transfer comprises the following steps:
 - implanting atomic species in the donor substrate so as to form a weakened zone that delineates a layer of single-crystal semiconductor or ferroelectric material to be transferred,
 - bonding the donor substrate to the receiver substrate, the oxide layer and the layer of single-crystal semiconductor or ferroelectric material to be transferred being at the bonding interface,
 - detaching the donor substrate along the weakened zone in order to transfer the layer of single-crystal semiconductor or ferroelectric material to the receiver substrate, the oxide layer being arranged between the charge-trapping layer and the transferred layer of single-crystal semiconductor or ferroelectric material.
13. Process according to Claim 12, wherein the single-crystal semiconductor or ferroelectric material lies at the surface of the donor substrate, the implantation of atomic species being carried out directly through said surface.