

[0001] METHOD AND APPARATUS FOR
TRANSMITTING AND RECEIVING A PACKET VIA
HIGH SPEED DOWNLINK PACKET ACCESS

[0002] FIELD OF INVENTION

[0003] The present invention is related to wireless communications systems.

[0004] BACKGROUND

[0005] HSDPA is a feature that was introduced in Release 5 of the third generation partnership project (3GPP) specifications in order to increase data rates in the downlink for packet data users. Downlink data is transmitted by a Node-B to a wireless transmit/receive unit (WTRU) via a high speed downlink shared channel (HS-DSCH). The WTRU sends feedback to the Node-B via a high speed dedicated control channel (HS-DPCCH).

[0006] Adaptive modulation and coding (AMC), hybrid automatic repeat request (H-ARQ) and fast Node-B scheduling are some of the new features in HSDPA. AMC adapts the transmission data rate on the HS-DSCH according to the channel conditions perceived by the WTRU. The Node-B determines the best rate and scheduling for individual transmissions using the following information:

 (1) a channel quality indicator (CQI) reported from a WTRU, which indicates the quality of the channel that is perceived by the WTRU;

 (2) a transmit power control (TPC) command of associated dedicated channels; and

 (3) positive acknowledgement (ACK)/negative acknowledgement (NACK) feedback in response to previous HS-DSCH transmissions.

[0007] Lower data rates are generally used for transmissions to WTRUs perceiving unfavorable channel conditions, (e.g., at cell-edge), resulting in smaller transport blocks per 2 ms transmission time interval (TTI). Higher data rates are used for transmissions to WTRUs perceiving favorable channel conditions, resulting in larger transport blocks per 2 ms TTI.

[0008] The WTRU reports the CQI over the HS-DPCCH, which provides to the Node-B an indication of the quality of the channel that is perceived by the WTRU in the downlink. The CQI indicates the highest MAC-hs transport block size that the WTRU may receive in the downlink within the 2 ms TTI, for which the transport block error probability is less than 0.1, (i.e., 10 %). The mapping between CQI and transport block size for Category 10 WTRU is shown in Table 1. Different CQI lookup tables are provided for each WTRU category. A higher CQI value corresponds to a larger transport block size.

CQI value	Transport Block Size	Number of HS-PDSCH	Modulation	CQI value	Transport Block Size	Number of HS-PDSCH	Modulation
1	137	1	QPSK	16	3565	5	16-QAM
2	173	1	QPSK	17	4189	5	16-QAM
3	233	1	QPSK	18	4664	5	16-QAM
4	317	1	QPSK	19	5287	5	16-QAM
5	377	1	QPSK	20	5887	5	16-QAM
6	461	1	QPSK	21	6554	5	16-QAM
7	650	2	QPSK	22	7168	5	16-QAM
8	792	2	QPSK	23	9719	7	16-QAM
9	931	2	QPSK	24	11418	8	16-QAM
10	1262	3	QPSK	25	14411	10	16-QAM
11	1483	3	QPSK	26	17237	12	16-QAM
12	1742	3	QPSK	27	21754	15	16-QAM
13	2279	4	QPSK	28	23370	15	16-QAM
14	2583	4	QPSK	29	24222	15	16-QAM
15	3319	5	QPSK	30	25558	15	16-QAM

Table 1

[0009] An important application for HSDPA is the transmission of Voice over IP (VoIP) traffic. VoIP is an emerging technology for the transport of speech over packet-switched networks. VoIP significantly differs from non real-time data-oriented applications in terms of quality of service (QoS), as end-to-end delay is the strictest requirement.

[0010] Figure 1 shows protocol architecture for transmission of VoIP in universal mobile telecommunication system (UMTS). The speech signal is

encoded by a voice codec in frames of 20 ms duration. The encoded voice signal is then carried over real-time transmit protocol (RTP), user datagram protocol (UDP) and Internet protocol (IP). These are commonly accepted protocols for the transportation of voice traffic over packet-switched networks.

[0011] Figure 2 shows a conventional VoIP packet. The VoIP packet that is transmitted over the radio network may be 72 or 92 bytes in size, depending on the IP version, (i.e., IPv4 or IPv6). Referring again to Figure 1, the VoIP packets are delivered to the packet data convergence protocol (PDCP) layer, which compresses the RTP, UDP and IP headers for transmission over the air interface. The PDCP layer uses robust header compression (ROHC). A number of states may be defined for ROHC throughout the life of a single VoIP call. In one state, a full frame without any compression may be delivered to lower layers for transmission. In another state, full compression of RTP/UDP/IP headers down to ~1 byte may take place. This results in variable packet sizes, ranging from 33 bytes to 92 bytes.

[0012] The compressed PDCP layer packets are then delivered to a radio link control (RLC) layer. The RLC layer typically operates in an unacknowledged mode (UM) for VoIP packets. The RLC layer appends an additional one (1) byte header to the PDCP layer packets. The RLC protocol data units (PDUs) that are delivered to a medium access control (MAC) layer have sizes ranging from 34 bytes (full header compression with IPv4) to 93 bytes (no header compression). The MAC layer includes one or more RLC PDUs (each RLC PDU corresponding to a VoIP packet) in a single transport block for transmission.

[0013] The WTRU reports perceived downlink channel quality by sending a CQI to the Node-B. The CQI indicates the maximum transport block size that the WTRU may receive with a 10 % probability of packet error. Low CQI values are reported to the Node-B in bad channel conditions, corresponding to smaller transport block sizes. In some cases, the next packet to be transmitted to the WTRU may be larger than the maximum transport block size specified via the CQI. Considering the VoIP service as an example, where RLC PDUs range from 272 bits (34 bytes) to 736 bits (92 bytes) in size, according to Table 1, CQI values

1, 2 and 3 suggest transport blocks that are too small for the 272-bit RLC PDU. Similarly, CQI values 1 through 7 suggest transport block sizes which are too small for the largest RLC PDU, (i.e., 736 bits).

[0014] The Node-B may react in two different ways when the CQI indicates a block size that is smaller than the next packet in queue. The Node-B may wait until the channel conditions improve and the WTRU indicates that the WTRU is able to receive the MAC-hs PDU with reasonable error probability. Alternatively, the Node-B may transmit a larger transport block size than is indicated by the CQI and rely on the H-ARQ process for successful delivery of the packet.

[0015] In the first approach, the Node-B does not schedule any transmission to the WTRU until the Node-B receives a CQI large enough to transmit the next packet in queue. This can take an extended amount of time as larger CQI reports will only be reported once channel conditions improve. This approach might be suitable for non real-time applications, which can tolerate variable delays, but unacceptable for delay sensitive applications such as VoIP.

[0016] In the second approach, the Node-B schedules the transmission of the VoIP packet regardless of the poor CQI. The transmission will likely fail because of the larger transport block than can be received with 10 % error probability. A successful transmission should eventually occur after a certain number of retransmissions via H-ARQ mechanism. However, the H-ARQ retransmissions introduce undesirable delays for real-time applications. Conventional HSDPA systems do not effectively transfer real-time traffic, especially for users perceiving poor channel conditions.

[0017] SUMMARY

[0018] A method and apparatus for transmitting and receiving a packet via HSDPA are disclosed. At least one HSDPA medium access control (MAC-hs) service data unit (SDU) is segmented into a plurality of segments. A plurality of MAC-hs PDUs are generated from the segments wherein each MAC-hs PDU includes at least one segment. Each MAC-hs PDU may include one segment from

a single MAC-hs SDU. The size of the segments may match to the size of the MAC-hs PDUs minus the size of the header of the MAC-hs PDU, except the last segment of the MAC-hs SDU. The sizes of the segments may be determined based on the number of segments to which the MAC-hs SDU is segmented. The segment included in the MAC-hs PDU may be selected arbitrarily. Alternatively, each MAC-hs PDU may include a combination of segments from a plurality of MAC-hs SDUs or a combination of at least one segment from one MAC-hs SDU and at least one entire MAC-hs SDU.

[0019] BRIEF DESCRIPTION OF THE DRAWINGS

[0020] A more detailed understanding may be had from the following description, given by way of example and to be understood in conjunction with the accompanying drawings wherein:

[0021] Figure 1 shows protocol architecture for transmission of VoIP in UMTS;

[0022] Figure 2 shows a conventional VoIP packet;

[0023] Figure 3 shows a MAC-hs layer in a Node-B;

[0024] Figure 4 shows a MAC-hs layer in a WTRU;

[0025] Figure 5 shows a MAC-hs SDU segmentation scheme in accordance with a first embodiment;

[0026] Figure 6 shows a MAC-hs SDU segmentation scheme in accordance with a second embodiment;

[0027] Figure 7 shows a MAC-hs SDU segmentation scheme in accordance with a third embodiment;

[0028] Figure 8 shows a MAC-hs SDU segmentation scheme in accordance with a fourth embodiment;

[0029] Figure 9 shows generation of the MAC-hs PDU including the last segment of a MAC-hs SDU and entire one or more subsequent MAC-hs SDU(s);

[0030] Figure 10 shows segmentation of the MAC-hs SDU and loss of one of the segments;

[0031] Figure 11 shows generation of a packet almost filled with padding; and

[0032] Figure 12 shows generation of two MAC-hs PDUs almost filled with MAC-hs SDU bits.

[0033] DETAILED DESCRIPTION

[0034] When referred to hereafter, the terminology "WTRU" includes but is not limited to a user equipment (UE), a mobile station, a fixed or mobile subscriber unit, a pager, a cellular telephone, a personal digital assistant (PDA), a computer, or any other type of user device capable of operating in a wireless environment. When referred to hereafter, the terminology "Node-B" includes but is not limited to a base station, a site controller, an access point (AP), or any other type of interfacing device capable of operating in a wireless environment.

[0035] The embodiments described herein may be implemented in any wireless communication system including, but not limited to, 3GPP UMTS wireless communication systems.

[0036] In order to improve transfer of delay-sensitive data, (e.g., VoIP traffic), in the downlink for HSDPA systems, packets may be segmented at a MAC-hs layer. Larger packets are segmented into smaller packets to allow successive transfer of the smaller segments with higher reliability. This allows the Node-B to transmit segments over multiple TTIs, reducing the transport block size per TTI. The smaller transport blocks may be transmitted using lower modulations and/or higher coding rates, ensuring more reliable transfer and minimizing H-ARQ retransmissions.

[0037] Figure 3 shows functional architecture of an MAC-hs layer 300 in a Node-B. The MAC-hs layer 300 includes a scheduling and priority handling entity 302, a segmentation entity 306, an H-ARQ entity 308, and a transport format and resource combination (TFRC) selection entity 310. MAC-hs SDUs are received from a higher layer, (e.g., MAC-d layer), and stored in one of a plurality of priority queues 305 in accordance with priority queue distribution function

304. The scheduling and priority handling entity 302 manages and determines the queue ID and TSN for each new MAC-hs PDU.

[0038] The segmentation entity 306 is included in the MAC-hs layer 300 of the Node-B so that at least one MAC-hs SDU is segmented into a plurality of segments. At least one MAC-hs SDU may be segmented to a plurality of segments by the segmentation entity 306. At least one segment is then included in an MAC-hs PDU, which is transmitted via an H-ARQ entity 308. An H-ARQ process is performed individually for each MAC-hs PDU over the air interface. The TFRC selection entity 310 selects a transport format and resource for each MAC-hs PDU. The MAC-hs PDUs are transmitted over the air via a physical layer 320.

[0039] Figure 4 shows functional architecture of an MAC-hs layer 400 in a WTRU. The MAC-hs layer 400 includes an H-ARQ entity 402, reordering queue distribution 404, a reordering entity 406, a reassembly entity 408, and a disassembly entity 410. MAC-hs PDUs are received by an H-ARQ entity 402 via a physical layer 420. The received MAC-hs PDUs are sent to the reordering entity 406 via reordering queue distribution 404 for reordering in accordance with a transmission sequence number (TSN). The reordered MAC-hs PDUs are reassembled by the reassembly entity 408. The reassembled MAC-hs PDUs are sent to the disassembly entity 410 for extracting the MAC-hs SDU to be sent to a higher layer, (e.g., MAC-d layer).

[0040] Coordination of the segmentation and reassembly of PDUs between the Node-B and the WTRU may be signaled by using a new MAC-hs header which will be explained in detail below or via high speed shared control channel (HS-SCCH).

[0041] Figure 5 shows a MAC-hs SDU segmentation scheme in accordance with a first embodiment. A MAC-hs SDU 502, (e.g., MAC-d PDU), may be segmented into a plurality of segments. Each MAC-hs PDU 504a-504n includes a single segment 508a-508n from at most one MAC-hs SDU 502. The size of each segment matches exactly the size of the MAC-hs PDU minus the MAC-hs header

size, except the last segment. The MAC-hs PDU 504n containing the last segment may contain padding bits 510.

[0042] Figure 5 also shows a MAC-hs header format in accordance with the first embodiment. The MAC-hs header 506a-506n indicates the MAC-hs segmentation scheme. The MAC-hs header 506a-506n includes a version flag (VF), a queue ID, a TSN, a size identifier (SID), and a fragment sequence number (FSN). It should be noted that the exact order of the information elements in the MAC-hs header 506a-506n is not important and may be changed.

[0043] A conventional one-bit VF field may be extended from one bit to two (2) bits. The first bit may be set to '1' (previously a reserved value) to indicate the new MAC-hs PDU format supporting segmentation of MAC-hs SDUs. The new MAC-hs PDU format should only be used when one MAC-hs SDU is segmented in two or more segments. Otherwise, conventional MAC-hs PDU format should be used to transport the MAC-hs SDUs. The second bit of the VF field may be set to '0' while the value '1' is reserved for future purposes.

[0044] The queue ID identifies the reordering queue in the WTRU in order to support independent buffer handling of data belonging to different reordering queues. The TSN is an identifier for the transmission sequence number on the HS-DSCH. The TSN is used for reordering purposes to support in-sequence delivery to higher layers. The SID is an identifier for the size of the MAC-hs SDU. Optionally, the SID may be omitted in any MAC-hs PDU not containing the first segment. The FSN is optional and provides an identifier for the fragment sequence number.

[0045] Optionally, an additional 1-bit flag (not shown in Figure 5) may be added to the MAC-hs header to indicate whether or not there is padding in the MAC-hs PDU. This 1-bit flag is optional as the WTRU is capable of determining the amount of padding bits based on the FSN and the sizes of previous segments. The size of the segment need not be indicated in the header either because only the MAC-hs PDU containing the last segment contains padding bits or because the size of the MAC-hs SDU is indicated by the SID.

[0046] Figure 6 shows a MAC-hs SDU segmentation scheme in accordance with a second embodiment. Each MAC-hs PDU 604a-604n contains data from at most a single MAC-hs SDU 602. All segments 608a-608m of the MAC-hs SDU 602 have pre-determined sizes based on the number of segments, (S total segments). A rule is defined to calculate the sizes. Preferably, the sizes for the first S-1 segments is the size of the MAC-hs SDU rounded up to the nearest multiple of S then divided by S. The size of the last segment 608m is the size of the MAC-hs SDU 602 minus the sum of the sizes of previous S-1 segments. Any MAC-hs PDU 604a-604n may contain padding bits. The WTRU knows which bits are padding bits based on the known sizes of segments of MAC-hs SDUs. Each MAC-hs PDU 604a-604n contains one or more segments of the MAC-hs SDU (not necessarily contiguous). A Node-B scheduler has flexibility of transmitting any subset of segments of the MAC-hs SDU based on current channel conditions and success or failure of past transmissions of MAC-hs PDU containing segments of the same MAC-hs SDU.

[0047] Compared to the first embodiment, the second embodiment has an advantage of allowing more selectivity in retransmitting the segments. The drawback is possibly more overhead in each MAC-hs PDU due to header and padding.

[0048] Figure 6 also shows a MAC-hs header format in accordance with the second embodiment. The MAC-hs header 606a-606n includes a VF, a queue ID, a TSN, a number of fragments of MAC-hs SDU (NFM) field, an FSDI, and an SID. It should be noted that the exact order of the information elements in the MAC-hs header is not important and may be changed. The VF, queue ID, TSN and SID are same as the first embodiment, and therefore will not be explained again for simplicity.

[0049] The NFM field indicates the number of segments of the MAC-hs SDU. The NFM field may be omitted if the number of segments of the MAC-hs SDU is fixed to a certain value, (e.g., eight (8)). The number of bits for the NFM field depends on the number of possible segments. For instance, the NFM field may be one (1) bit if the number of segments may be either 2 or 4.

[0050] The FSID is a bitmap indicating the segments that are transmitted in the MAC-hs PDU. The size of the FSID is the number of segments indicated by the NFM field. Therefore, the NFM field should precede the FSID field unless the NFM field does not exist. The SID may be omitted in any MAC-hs PDU not containing the first segment.

[0051] Figure 7 shows a MAC-hs SDU segmentation scheme in accordance with a third embodiment. Each MAC-hs PDU 704a-704n may include a signal segment from at most a single MAC-hs SDU 702. The position of the segment within the MAC-hs SDU 702 is arbitrary and indicated in the MAC-hs PDU header 706a-706n containing the segment. The Node-B scheduler has flexibility of transmitting any segment of any size at any position of the MAC-hs SDU 702 based on current channel conditions and success or failure of past transmissions of MAC-hs PDU 704a-704n containing segments of the same MAC-hs SDU 702.

[0052] Figure 7 also shows a MAC-hs header format in accordance with the third embodiment. The MAC-hs header 706a-706n includes a VF, a queue ID, a TSN, a starting position identifier (SPID), and an SID. It should be noted that the exact order of the information elements in the MAC-hs header is not important and may be changed. The VF, queue ID, TSN and SID are same as the first embodiment, and therefore will not be explained again for simplicity. The SID may be omitted in any MAC-hs PDU not containing the first segment.

[0053] The SPID indicates the starting position of the segment within the MAC-hs SDU. Several schemes for defining the granularity of the position indication are possible. The SPID may indicate the starting position of the segment in bits or bytes. For example, if MAC-hs SDU sizes up to 1024 bits are allowed, the size of SPID is 10 bits if expressed in bits or 7 bits if expressed in bytes.

[0054] Alternatively, the SPID may indicate a segment number which indicates the starting positions. For example, if there are four (4) pre-established starting positions for any MAC-hs SDU, the starting positions are calculated by rounding up the MAC-hs SDU size up to the closest multiple of four, dividing by 4, and taking multiples of this number. Optionally, the number of pre-established

starting positions may be indicated by a separate field similar to the NFM of the second embodiment.

[0055] To reduce the overhead, the first bit of the SPID may be reserved to indicate whether the starting position is the start of the MAC-hs SDU. If the starting position is the start of the MAC-hs SDU, the SPID field may be a single bit. Thus, the size of the SPID may be one (1) bit if the segment starts at the start of the MAC-hs SDU and $N+1$ bits otherwise where N is the number of bits required to indicate the starting positions. This scheme reduces the overhead if the number of bits required to indicate the starting positions is larger than the number of transmitted segments.

[0056] Optionally, an end position indicator (EPID) or length indicator (LID) may be included in the MAC-hs PDU header to indicate the end position of the segment in the MAC-hs SDU or the length of the segment, respectively. Similar scheme may be used for encoding the EPID and LID as SPID.

[0057] Figure 8 shows a MAC-hs SDU segmentation scheme in accordance with a fourth embodiment. Each MAC-hs PDU 804a-804n may contain a combination of one or more segments 808a-808m from one or more MAC-hs SDU 802a, 802b or a combination of one or more segments from one MAC-hs SDU and one or multiple entire MAC-hs SDUs 802a, 802b. Any MAC-hs PDU 804a-804n may contain padding bits. The WTRU knows which bits are padding bits based on the known sizes of segments of MAC-hs SDUs 802a, 802b. The segments associated to a given MAC-hs SDU all have the same size and this size is based on the number of segments. The sizes for the first $S-1$ segments may be the size of the MAC-hs SDU rounded up to the nearest multiple of S then divided by S . The size of the last segment is the size of the MAC-hs SDU minus the sum of the sizes of previous segments.

[0058] The fourth embodiment allows the Node-B to transmit, in the same MAC-hs PDU, the last segment of a MAC-hs SDU and either the first segment of a subsequent MAC-hs SDU (as shown in Figure 8) or entire one or more subsequent MAC-hs SDU(s) (as shown in Figure 9). This allows for a more efficient use of the radio resources as it allows the Node-B to transmit traffic data

rather than padding bits when there is still room in an MAC-hs PDU containing the last segment of a MAC-hs SDU. This may be especially useful in situations where poor channel conditions had lead to segmentation but channel conditions improve after the first segment has been sent.

[0059] Figure 8 also shows a MAC-hs header format in accordance with the fourth embodiment. The MAC-hs header 806a-806n includes a VF, a queue ID, an SID, a TSN, an NFM, an FSID, an N field and an F field. It should be noted that the exact order of the information elements in the MAC-hs header is not important and may be changed. The VF, queue ID, TSN and SID are same as the first embodiment, and therefore will not be explained again for simplicity.

[0060] A set of SID, NFM, FSID, N and F is associated with one or more MAC-hs SDUs. Multiple sets of SID, NFM, FSID, N and F may be included in the MAC-hs PDU header.

[0061] The NFM indicates the number of segments of MAC-hs SDU associated to the given set of SID, NFM, FSID, N, and F. For example, a value of '0' may indicate that the set of SID, NFM, FSID, N, and F is not associated with any MAC-hs SDU segment.

[0062] The FSID is a bitmap indicating the segments that are transmitted in the MAC-hs PDU. The FSID may be removed if NFM (in a particular set of SID, NFM, FSID, N, F) is set to '0'.

[0063] The N field indicates the number of consecutive entire MAC-hs SDUs with equal size associated to a particular set of SID, NFM, FSID, N, and F. A value of '0' may indicate that the current set of SID, NFM, FSID, N, and F is not associated with any entire MAC-hs SDU, but only to a segment(s).

[0064] The F field is a flag indicating whether or not more fields are present in the MAC-hs PDU header. For example, if the F field is set to '0' the F field is followed by an additional set of SID, NFM, FSID, N and F, or vice versa.

[0065] Optionally, a DTSN field (not shown in Figure 8) may be added to allow the Node-B to transmit a MAC-hs PDU containing a MAC-hs SDU for which segments have already been sent and received successfully by the WTRU. The DTSN field identifies the TSN(s) that the WTRU needs to delete in order to

prevent duplicate MAC-hs PDU(s) to reach the upper layer, (e.g., MAC-d layer). Where poor channel conditions had lead to segmentation but channel conditions have improved after the first segment(s) have been sent, it may be desirable for the Node-B to send the entire MAC-hs SDU although parts of it have already been successfully received by the WTRU.

[0066] The following examples illustrate the MAC-hs PDU header setting in accordance with the fourth embodiment.

[0067] Example 1: If the Node-B wants to transmit the last two segments of MAC-hs SDU X and the first segment of MAC-hs SDU Y, the MAC-hs PDU includes the two sets of SID, NFM, FSID, N, and F, wherein the first set is set to: $SID > 0$, $NFM > 0$, $FSID \neq 0$, $N=0$, $F=0$, and the second set is set to: $SID > 0$, $NFM > 0$, $FSID \neq 0$, $N=0$, $F=1$.

[0068] Example 2: If the Node-B wants to transmit the last two segments of MAC-hs SDU X and the next subsequent whole MAC-hs SDUs Y and Z, one set of SID, NFM, FSID, N, and F is set to: $SID > 0$, $NFM > 0$, $FSID \neq 0$, $N=2$, $F=1$.

[0069] With segmentation, one MAC-hs SDU may be split into two or more segments and the segments are transmitted separately. One or more segments of the MAC-hs SDU may be lost. Figure 10 shows segmentation of an MAC-hs SDU 1002 which has lost one of the segments. The MAC-hs SDU 1002 is segmented into four (4) segments. Each segment is included in a separate MAC-hs PDU 1004a-1004d and transmitted separately. The first, second and fourth segments 1004a, 1004b, 1004d are successfully received by the WTRU and buffered. However, the third segment 1004c is lost. Due to the missing third segment, the segments 1004a-1004d cannot be reassembled into the MAC-hs SDU 1002.

[0070] The WTRU autonomously determines that the transmission has failed for a particular segment. Once it is determined that the H-ARQ process for one segment has failed, the WTRU deletes all segments of the same MAC-hs SDU in a buffer that is waiting for reassembly.

[0071] The following mechanisms may be used individually or in any combination to determine that a segment is lost. The WTRU may use a timer-based mechanism. The WTRU sets a timer, and if the timer expires before all

segments of the same MAC-hs SDU have been received, the WTRU flushes all segments of the MAC-hs SDU waiting for reassembly. The timer may be reset every time the WTRU receives a segment that is part of the MAC-hs SDU. Alternatively, the timer may be reset only once upon reception of the first segment of the MAC-hs SDU. The duration of the timer may be configurable by higher layers, (e.g., radio resource control (RRC) signaling).

[0072] Alternatively, the WTRU may flush all segments of the MAC-hs SDU that are waiting for reassembly when the WTRU detects an H-ARQ process failure. The WTRU may detect the H-ARQ process failure when the maximum number of H-ARQ retransmissions has been reached and the WTRU is unable to successfully decode the MAC-hs PDU. Alternatively, the WTRU may detect the H-ARQ process failure when the WTRU receives a transmission indicating new data on the same H-ARQ process, (i.e., via H-ARQ process information field on an HS-SCCH), for which the WTRU was expecting a retransmission.

[0073] Alternatively, a new signaling mechanism may be used by the Node-B to indicate to the WTRU that all segments corresponding to a MAC-hs SDU should be deleted. The signaling may be achieved by introducing new L1 or L2 signaling or by modifying conventional L1 or L2 signaling.

[0074] The segmentation of a larger packet has an advantage as explained above. However, if the segmentation of a larger packet into smaller packets results in a significantly smaller packet that is almost filled with padding. The transmission of such a (mostly padding) MAC-hs packet would reduce the efficiency of MAC-hs transmission and waste valuable air interface resources.

[0075] Figure 11 shows generation of a packet almost filled with padding. The MAC-hs PDU size is 180 bits, and the MAC-hs SDU size is 200 bits. The MAC-hs SDU need to be segmented into two MAC-hs PDUs. The first MAC-hs PDU would be totally filled with the first 180 bits of the MAC-hs SDU. However, the second MAC-hs PDU would be filled with only 20 bits of the MAC-hs SDU and the remainder of the second MAC-hs PDU (160 bits) would be padding. A more efficient solution for this situation would be to avoid segmentation, and instead, transmit a larger transport block size (big enough for the original MAC-

hs SDU size of 200 bits) and rely on the H-ARQ process for successful delivery of the packet.

[0076] Figure 12 shows generation of two MAC-hs PDUs almost filled with MAC-hs SDU bits. The MAC-hs PDU size is 180 bits, and the MAC-hs SDU size is 350 bits. The MAC-hs SDU is segmented into two MAC-hs PDUs. The first MAC-hs PDU is totally filled with the first 180 bits of the MAC-hs SDU. The second MAC-hs PDU would be almost completely filled with the remaining 170 bits of the MAC-hs SDU. In this situation, the most efficient solution would be to allow for segmentation of the MAC-hs SDU. The two MAC-hs PDUs, transferred over successive TTIs would reduce the need for excessive H-ARQ retransmissions, reducing the burden on the MAC-hs downlink transmission system.

[0077] In accordance with one embodiment, before segmenting the MAC-hs SDU, the Node-B calculates the ratio of MAC-hs PDU bits taken up by the MAC-hs SDU segment to the remaining MAC-hs PDU bits. The Node-B then compares the ratio to the threshold. The Node-B may segment the MAC-hs SDU only if the ratio is greater than the threshold.

[0078] Embodiments.

1. A method for transmitting a packet via HSDPA.
2. The method of embodiment 1 comprising generating at least one MAC-hs SDU.
3. The method of embodiment 2 comprising segmenting the MAC-hs SDU into a plurality of segments.
4. The method of embodiment 3 comprising generating a plurality of MAC-hs PDUs, each MAC-hs PDU including at least one segment.
5. The method of embodiment 4 comprising transmitting the MAC-hs PDUs.
6. The method as in any one of embodiments 4-5, wherein each MAC-hs PDU includes one segment from a single MAC-hs SDU.

7. The method as in any one of embodiments 4-5, wherein the size of the segments matches to the size of the MAC-hs PDUs minus the size of the header of the MAC-hs PDU, except the last segment of the MAC-hs SDU.

8. The method as in any one of embodiments 4-7, wherein the header of the MAC-hs PDU includes an FSN.

9. The method as in any one of embodiments 4-5, wherein the sizes of the segments is determined based on the number of segments to which the MAC-hs SDU is segmented.

10. The method of embodiment 9 wherein the sizes for the first S-1 segments of the MAC-hs SDU is the size of the MAC-hs SDU rounded up to the nearest multiple of S then divided by S, and the size of the last segment of the MAC-hs SDU is the size of the MAC-hs SDU minus the sum of the sizes of previous S-1 segments.

11. The method as in any one of embodiments 9-10, wherein a header of the MAC-hs PDU includes a field indicating the number of segments of the MAC-hs SDU.

12. The method as in any one of embodiments 9-11, wherein a header of the MAC-hs PDU includes a field indicating the segment of the MAC-hs SDU that is included in the MAC-hs PDU.

13. The method as in any one of embodiments 9-12, wherein the number of segments of the MAC-hs SDU is fixed to a predefined value.

14. The method as in any one of embodiments 4-13, wherein the segment included in the MAC-hs PDU is selected arbitrarily.

15. The method of embodiment 14 wherein a header of the MAC-hs PCU includes an SPID indicating a starting position of the segment within the MAC-hs SDU.

16. The method of embodiment 15 wherein the SPID indicates the starting position of the segment in one of bits and bytes.

17. The method of embodiment 15 wherein the SPID indicates a segment number which indicates the starting position.

18. The method of embodiment 15 wherein the first bit of the SPID indicates whether the starting position of the segment is the start of the MAC-hs SDU.

19. The method of embodiment 14 wherein the header includes at least one of an EPID indicating an end position of the segment within the MAC-hs SDU and an LID indicating the length of the segment.

20. The method as in any one of embodiments 4-5, wherein each MAC-hs PDU includes one of a combination of segments from a plurality of MAC-hs SDUs and a combination of at least one segment from one MAC-hs SDU and at least one entire MAC-hs SDU.

21. The method of embodiment 20 wherein a header of the MAC-hs PDU includes a field indicating the number of segments of the MAC-hs SDU.

22. The method as in any one of embodiments 20-21, wherein a header of the MAC-hs PDU includes at least one set of SID, NFM, FSID, N field and F field that is associated with one or more MAC-hs SDUs, the N field indicating the number of consecutive entire MAC-hs SDUs with equal size, the F field indicating whether or not more fields are present in the MAC-hs PDU header.

23. The method as in any one of embodiments 20-22, wherein a header of the MAC-hs PDU includes a field identifying a TSN that needs to be deleted from a buffer.

24. The method as in any one of embodiments 4-23, further comprising calculating a ratio of MAC-hs PDU bits taken up by the segment to the remaining MAC-hs PDU bits.

25. The method of embodiment 24 comprising comparing the ratio to a predefined threshold, wherein the MAC-hs SDU is segmented only if the ratio is greater than the threshold.

26. A method for receiving a packet via HSDPA.

27. The method of embodiment 26 comprising receiving a plurality of MAC-hs PDUs, the MAC-hs PDUs carrying segments of an MAC-hs SDU.

28. The method of embodiment 27 comprising storing the MAC-hs PDUs in a buffer.

29. The method as in any one of embodiments 27-28, comprising reassembling the segments to the MAC-hs SDU.

30. The method of embodiment 21 wherein each MAC-hs PDU includes one segment from a single MAC-hs SDU.

31. The method as in any one of embodiments 27-30, wherein the sizes of the segments is determined based on the number of segments to which the MAC-hs SDU is segmented.

32. The method as in any one of embodiments 27-31, wherein the segment included in the MAC-hs PDU is selected arbitrarily.

33. The method as in any one of embodiments 27-32, wherein each MAC-hs PDU includes one of a combination of segments from a plurality of MAC-hs SDUs and a combination of at least one segment from one MAC-hs SDU and at least one entire MAC-hs SDU.

34. The method as in any one of embodiments 27-33, further comprising determining whether a transmission has failed for at least one of the plurality of segments.

35. The method of embodiment 34 further comprising deleting segments of the MAC-hs SDU in the buffer waiting for reassembly when at least one segment of the MAC-hs SDU is lost.

36. The method as in any one of embodiments 27-33, further comprising setting a timer.

37. The method of embodiment 36 comprising flushing all segments of the same MAC-hs SDU in the buffer that are waiting for reassembly if the timer expires before all segments of the same MAC-hs SDU have been received.

38. The method as in any one of embodiments 36-37, wherein the timer is reset every time a segment that is part of the MAC-hs SDU is received in correct order.

39. The method as in any one of embodiments 36-38, wherein the timer is configurable by RRC signaling.

40. The method as in any one of embodiments 36-39, wherein the timer is reset only once upon reception of the first segment of the MAC-hs SDU.

41. The method as in any one of embodiments 27-33, further comprising detecting H-ARQ process failure for a particular segment.

42. The method of embodiment 41 comprising flushing all segments of the same MAC-hs SDU in the buffer that are waiting for reassembly.

43. The method as in any one of embodiments 41-42, wherein the H-ARQ process failure is detected when the maximum number of H-ARQ retransmissions has been reached.

44. The method as in any one of embodiments 41-42, wherein the H-ARQ process failure is detected when a transmission indicating new data is received on the same H-ARQ process while expecting a retransmission.

45. The method as in any one of embodiments 27-33, further comprising receiving a signal indicating that all segments corresponding to a particular MAC-hs SDU be flushed from the buffer.

46. The method of embodiment 45 comprising flushing the indicated segments from the buffer.

47. A Node-B for transmitting a packet via HSDPA.

48. The Node-B of embodiment 47 comprising an MAC-hs layer for segmenting a MAC-hs SDU to a plurality of segments and generating a plurality of MAC-hs PDUs, each MAC-hs PDU including at least one segment.

49. The Node-B of embodiment 48 comprising a physical layer for transmitting the MAC-hs PDUs.

50. The Node-B as in any one of embodiments 48-49, wherein each MAC-hs PDU includes one segment from a single MAC-hs SDU.

51. The Node-B as in any one of embodiments 48-50, wherein the size of the segments matches to the size of the MAC-hs PDUs minus the size of the header of the MAC-hs PDU, except the last segment of the MAC-hs SDU.

52. The Node-B of embodiment 51 wherein the header of the MAC-hs PDU includes an FSN.

53. The Node-B as in any one of embodiments 48-50, wherein the sizes of the segments is determined based on the number of segments to which the MAC-hs SDU is segmented.

54. The Node-B of embodiment 53 wherein the sizes for the first S-1 segments of the MAC-hs SDU is the size of the MAC-hs SDU rounded up to the nearest multiple of S then divided by S, and the size of the last segment of the MAC-hs SDU is the size of the MAC-hs SDU minus the sum of the sizes of previous S-1 segments.

55. The Node-B as in any one of embodiments 48-50, wherein a header of the MAC-hs PDU includes a field indicating the number of segments of the MAC-hs SDU.

56. The Node-B as in any one of embodiments 48-50, wherein a header of the MAC-hs PDU includes a field indicating the segment of the MAC-hs SDU that is included in the MAC-hs PDU.

57. The Node-B as in any one of embodiments 48-50, wherein the number of segments of the MAC-hs SDU is fixed to a predefined value.

58. The Node-B as in any one of embodiments 48-50, wherein the segment included in the MAC-hs PDU is selected arbitrarily.

59. The Node-B of embodiment 58 wherein a header of the MAC-hs PCU includes an SPID indicating a starting position of the segment within the MAC-hs SDU.

60. The Node-B as in any one of embodiments 58-59, wherein the SPID indicates the starting position of the segment in one of bits and bytes.

61. The Node-B as in any one of embodiments 58-60, wherein the SPID indicates a segment number which indicates the starting position.

62. The Node-B as in any one of embodiments 58-6,1 wherein the first bit of the SPID indicates whether the starting position of the segment is the start of the MAC-hs SDU.

63. The Node-B of embodiment 58 wherein the header includes at least one of an EPID indicating an end position of the segment within the MAC-hs SDU and an LID indicating the length of the segment.

64. The Node-B as in any one of embodiments 48-50, wherein each MAC-hs PDU includes one of a combination of segments from a plurality of MAC-

hs SDUs and a combination of at least one segment from one MAC-hs SDU and at least one entire MAC-hs SDU.

65. The Node-B of embodiment 64 wherein a header of the MAC-hs PDU includes a field indicating the number of segments of the MAC-hs SDU.

66. The Node-B as in any one of embodiments 64-65, wherein a header of the MAC-hs PDU includes at least one set of SID, NFM, FSID, N field and F field that is associated with one or more MAC-hs SDUs, the N field indicating the number of consecutive entire MAC-hs SDUs with equal size, the F field indicating whether or not more fields are present in the MAC-hs PDU header.

67. The Node-B as in any one of embodiments 48-66, wherein a header of the MAC-hs PDU includes a field identifying a TSN that needs to be deleted from a buffer.

68. The Node-B as in any one of embodiments 48-67, wherein the MAC-hs layer is configured to calculate a ratio of MAC-hs PDU bits taken up by the segment to the remaining MAC-hs PDU bits and compare the ratio to a predefined threshold, so that the MAC-hs SDU is segmented only if the ratio is greater than the threshold.

69. A WTRU for receiving a packet via HSDPA.

70. The WTRU comprising a physical layer for receiving a plurality of MAC-hs PDUs, the MAC-hs PDUs carrying segments of an MAC-hs SDU.

71. The WTRU of embodiment 70 comprising an MAC-hs layer for storing the received MAC-hs PDUs and reassembling the segments to the MAC-hs SDU.

72. The WTRU as in any one of embodiments 70-71, wherein each MAC-hs PDU includes one segment from a single MAC-hs SDU.

73. The WTRU of embodiment 72 wherein the sizes of the segments is determined based on the number of segments to which the MAC-hs SDU is segmented.

74. The WTRU as in any one of embodiments 70-73, wherein the segment included in the MAC-hs PDU is selected arbitrarily.

75. The WTRU of embodiment 74 wherein each MAC-hs PDU includes one of a combination of segments from a plurality of MAC-hs SDUs and a combination of at least one segment from one MAC-hs SDU and at least one entire MAC-hs SDU.

76. The WTRU as in any one of embodiments 70-75, wherein the MAC-hs layer is configured to determine whether a transmission has failed for at least one of the plurality of segments.

77. The WTRU of embodiment 76 wherein the MAC-hs layer is configured to delete stored segments waiting for reassembly when at least one segment of the MAC-hs SDU is lost.

78. The WTRU as in any one of embodiments 70-77, wherein the MAC-hs layer is configured to flush all segments of the same MAC-hs SDU that are waiting for reassembly from a buffer if a timer expires before all segments of the same MAC-hs SDU have been received.

79. The WTRU of embodiment 78 wherein the timer is reset every time a segment that is part of the MAC-hs SDU is received in correct order.

80. The WTRU as in any one of embodiments 78-79, wherein the timer is configurable by RRC signaling.

81. The WTRU as in any one of embodiments 78-80, wherein the timer is reset only once upon reception of the first segment of the MAC-hs SDU.

82. The WTRU as in any one of embodiments 78-81, wherein the MAC-hs layer flushes all segments of the same MAC-hs SDU that are waiting for reassembly from a buffer when H-ARQ process failure is detected for a particular segment.

83. The WTRU of embodiment 82 wherein the H-ARQ process failure is detected when the maximum number of H-ARQ retransmissions has been reached.

84. The WTRU of embodiment 82 wherein the H-ARQ process failure is detected when a transmission indicating new data is received on the same H-ARQ process while expecting a retransmission.

[0079] Although the features and elements are described in the embodiments in particular combinations, each feature or element can be used alone without the other features and elements of the embodiments or in various combinations with or without other features and elements. The methods provided may be implemented in a computer program, software, or firmware tangibly embodied in a computer-readable storage medium for execution by a general purpose computer or a processor. Examples of computer-readable storage mediums include a read only memory (ROM), a random access memory (RAM), a register, cache memory, semiconductor memory devices, magnetic media such as internal hard disks and removable disks, magneto-optical media, and optical media such as CD-ROM disks, and digital versatile disks (DVDs).

[0080] Suitable processors include, by way of example, a general purpose processor, a special purpose processor, a conventional processor, a digital signal processor (DSP), a plurality of microprocessors, one or more microprocessors in association with a DSP core, a controller, a microcontroller, Application Specific Integrated Circuits (ASICs), Field Programmable Gate Arrays (FPGAs) circuits, any other type of integrated circuit (IC), and/or a state machine.

[0081] A processor in association with software may be used to implement a radio frequency transceiver for use in a wireless transmit receive unit (WTRU), user equipment (UE), terminal, base station, radio network controller (RNC), or any host computer. The WTRU may be used in conjunction with modules, implemented in hardware and/or software, such as a camera, a video camera module, a videophone, a speakerphone, a vibration device, a speaker, a microphone, a television transceiver, a hands free headset, a keyboard, a Bluetooth® module, a frequency modulated (FM) radio unit, a liquid crystal display (LCD) display unit, an organic light-emitting diode (OLED) display unit, a digital music player, a media player, a video game player module, an Internet browser, and/or any wireless local area network (WLAN) module.

CLAIMS

What is claimed is:

1. A method for transmitting a packet via high speed downlink packet access (HSDPA), the method comprising:

generating at least one HSDPA medium access control (MAC-hs) service data unit (SDU);

segmenting the MAC-hs SDU into a plurality of segments;

generating a plurality of MAC-hs protocol data units (PDUs), each MAC-hs PDU including at least one segment; and

transmitting the MAC-hs PDUs.

2. The method of claim 1 wherein each MAC-hs PDU includes one segment from a single MAC-hs SDU.

3. The method of claim 2 wherein the size of the segments matches to the size of the MAC-hs PDUs minus the size of the header of the MAC-hs PDU, except the last segment of the MAC-hs SDU.

4. The method of claim 3 wherein the header of the MAC-hs PDU includes a fragment sequence number (FSN).

5. The method of claim 2 wherein the sizes of the segments is determined based on the number of segments to which the MAC-hs SDU is segmented.

6. The method of claim 5 wherein the sizes for the first S-1 segments of the MAC-hs SDU is the size of the MAC-hs SDU rounded up to the nearest multiple of S then divided by S, and the size of the last segment of the MAC-hs SDU is the size of the MAC-hs SDU minus the sum of the sizes of previous S-1 segments.

7. The method of claim 5 wherein a header of the MAC-hs PDU includes a field indicating the number of segments of the MAC-hs SDU.

8. The method of claim 5 wherein a header of the MAC-hs PDU includes a field indicating the segment of the MAC-hs SDU that is included in the MAC-hs PDU.

9. The method of claim 5 wherein the number of segments of the MAC-hs SDU is fixed to a predefined value.

10. The method of claim 2 wherein the segment included in the MAC-hs PDU is selected arbitrarily.

11. The method of claim 10 wherein a header of the MAC-hs PCU includes a segment position identifier (SPID) indicating a starting position of the segment within the MAC-hs SDU.

12. The method of claim 11 wherein the SPID indicates the starting position of the segment in one of bits and bytes.

13. The method of claim 11 wherein the SPID indicates a segment number which indicates the starting position.

14. The method of claim 11 wherein the first bit of the SPID indicates whether the starting position of the segment is the start of the MAC-hs SDU.

15. The method of claim 11 wherein the header includes at least one of an end position indicator (EPID) indicating an end position of the segment within the MAC-hs SDU and a length indicator (LID) indicating the length of the segment.

16. The method of claim 1 wherein each MAC-hs PDU includes one of a combination of segments from a plurality of MAC-hs SDUs and a combination of at least one segment from one MAC-hs SDU and at least one entire MAC-hs SDU.

17. The method of claim 16 wherein a header of the MAC-hs PDU includes a field indicating the number of segments of the MAC-hs SDU.

18. The method of claim 16 wherein a header of the MAC-hs PDU includes at least one set of size identifier (SID), number of fragmented MAC-hs SDU (NFM), fragmentation size identifier (FSID), N field and F field that is associated with one or more MAC-hs SDUs, the N field indicating the number of consecutive entire MAC-hs SDUs with equal size, the F field indicating whether or not more fields are present in the MAC-hs PDU header.

19. The method of claim 16 wherein a header of the MAC-hs PDU includes a field identifying a transmission sequence number (TSN) that needs to be deleted from a buffer.

20. The method of claim 1 further comprising:
calculating a ratio of MAC-hs PDU bits taken up by the segment to the remaining MAC-hs PDU bits; and
comparing the ratio to a predefined threshold, wherein the MAC-hs SDU is segmented only if the ratio is greater than the threshold.

21. A method for receiving a packet via high speed downlink packet access (HSDPA), the method comprising:

receiving a plurality of HSDPA medium access control (MAC-hs) protocol data units (PDUs), the MAC-hs PDUs carrying segments of an MAC-hs service data unit (SDU);

storing the MAC-hs PDUs in a buffer; and

reassembling the segments to the MAC-hs SDU.

22. The method of claim 21 wherein each MAC-hs PDU includes one segment from a single MAC-hs SDU.

23. The method of claim 22 wherein the sizes of the segments is determined based on the number of segments to which the MAC-hs SDU is segmented.

24. The method of claim 22 wherein the segment included in the MAC-hs PDU is selected arbitrarily.

25. The method of claim 21 wherein each MAC-hs PDU includes one of a combination of segments from a plurality of MAC-hs SDUs and a combination of at least one segment from one MAC-hs SDU and at least one entire MAC-hs SDU.

26. The method of claim 21, further comprising:
determining whether a transmission has failed for at least one of the plurality of segments.

27. The method of claim 26 further comprising:
deleting segments of the MAC-hs SDU in the buffer waiting for reassembly when at least one segment of the MAC-hs SDU is lost.

28. The method of claim 21 further comprising:
setting a timer; and
flushing all segments of the same MAC-hs SDU in the buffer that are waiting for reassembly if the timer expires before all segments of the same MAC-hs SDU have been received.

29. The method of claim 28 wherein the timer is reset every time a segment that is part of the MAC-hs SDU is received in correct order.

30. The method of claim 28 wherein the timer is configurable by radio resource control (RRC) signaling.

31. The method of claim 28 wherein the timer is reset only once upon reception of the first segment of the MAC-hs SDU.

32. The method of claim 21 further comprising:
detecting hybrid automatic repeat request (H-ARQ) process failure for a particular segment; and
flushing all segments of the same MAC-hs SDU in the buffer that are waiting for reassembly.

33. The method of claim 32 wherein the H-ARQ process failure is detected when the maximum number of H-ARQ retransmissions has been reached.

34. The method of claim 32 wherein the H-ARQ process failure is detected when a transmission indicating new data is received on the same H-ARQ process while expecting a retransmission.

35. The method of claim 21 further comprising:
receiving a signal indicating that all segments corresponding to a particular MAC-hs SDU be flushed from the buffer; and
flushing the indicated segments from the buffer.

36. A Node-B for transmitting a packet via high speed downlink packet access (HSDPA), the Node-B comprising:

an HSDPA medium access control (MAC-hs) layer for segmenting a MAC-hs service data unit (SDU) to a plurality of segments and generating a plurality of MAC-hs protocol data units (PDUs), each MAC-hs PDU including at least one segment; and

a physical layer for transmitting the MAC-hs PDUs.

37. The Node-B of claim 36 wherein each MAC-hs PDU includes one segment from a single MAC-hs SDU.

38. The Node-B of claim 37 wherein the size of the segments matches to the size of the MAC-hs PDUs minus the size of the header of the MAC-hs PDU, except the last segment of the MAC-hs SDU.

39. The Node-B of claim 38 wherein the header of the MAC-hs PDU includes a fragment sequence number (FSN).

40. The Node-B of claim 37 wherein the sizes of the segments is determined based on the number of segments to which the MAC-hs SDU is segmented.

41. The Node-B of claim 40 wherein the sizes for the first S-1 segments of the MAC-hs SDU is the size of the MAC-hs SDU rounded up to the nearest multiple of S then divided by S, and the size of the last segment of the MAC-hs SDU is the size of the MAC-hs SDU minus the sum of the sizes of previous S-1 segments.

42. The Node-B of claim 40 wherein a header of the MAC-hs PDU includes a field indicating the number of segments of the MAC-hs SDU.

43. The Node-B of claim 40 wherein a header of the MAC-hs PDU includes a field indicating the segment of the MAC-hs SDU that is included in the MAC-hs PDU.

44. The Node-B of claim 40 wherein the number of segments of the MAC-hs SDU is fixed to a predefined value.

45. The Node-B of claim 37 wherein the segment included in the MAC-hs PDU is selected arbitrarily.

46. The Node-B of claim 45 wherein a header of the MAC-hs PCU includes a segment position identifier (SPID) indicating a starting position of the segment within the MAC-hs SDU.

47. The Node-B of claim 46 wherein the SPID indicates the starting position of the segment in one of bits and bytes.

48. The Node-B of claim 46 wherein the SPID indicates a segment number which indicates the starting position.

49. The Node-B of claim 46 wherein the first bit of the SPID indicates whether the starting position of the segment is the start of the MAC-hs SDU.

50. The Node-B of claim 46 wherein the header includes at least one of an end position indicator (EPID) indicating an end position of the segment within the MAC-hs SDU and a length indicator (LID) indicating the length of the segment.

51. The Node-B of claim 36 wherein each MAC-hs PDU includes one of a combination of segments from a plurality of MAC-hs SDUs and a combination of

at least one segment from one MAC-hs SDU and at least one entire MAC-hs SDU.

52. The Node-B of claim 51 wherein a header of the MAC-hs PDU includes a field indicating the number of segments of the MAC-hs SDU.

53. The Node-B of claim 51 wherein a header of the MAC-hs PDU includes at least one set of size identifier (SID), number of fragmented MAC-hs SDU (NFM), fragmentation size identifier (FSID), N field and F field that is associated with one or more MAC-hs SDUs, the N field indicating the number of consecutive entire MAC-hs SDUs with equal size, the F field indicating whether or not more fields are present in the MAC-hs PDU header.

54. The Node-B of claim 51 wherein a header of the MAC-hs PDU includes a field identifying a transmission sequence number (TSN) that needs to be deleted from a buffer.

55. The Node-B of claim 37 wherein the MAC-hs layer is configured to calculate a ratio of MAC-hs PDU bits taken up by the segment to the remaining MAC-hs PDU bits and compare the ratio to a predefined threshold, so that the MAC-hs SDU is segmented only if the ratio is greater than the threshold.

56. A wireless transmit/receive unit (WTRU) for receiving a packet via high speed downlink packet access (HSDPA), the WTRU comprising:

a physical layer for receiving a plurality of HSDPA medium access control (MAC-hs) protocol data units (PDUs), the MAC-hs PDUs carrying segments of an MAC-hs service data unit (SDU); and

an MAC-hs layer for storing the received MAC-hs PDUs and reassembling the segments to the MAC-hs SDU.

57. The WTRU of claim 56 wherein each MAC-hs PDU includes one segment from a single MAC-hs SDU.

58. The WTRU of claim 57 wherein the sizes of the segments is determined based on the number of segments to which the MAC-hs SDU is segmented.

59. The WTRU of claim 57 wherein the segment included in the MAC-hs PDU is selected arbitrarily.

60. The WTRU of claim 56 wherein each MAC-hs PDU includes one of a combination of segments from a plurality of MAC-hs SDUs and a combination of at least one segment from one MAC-hs SDU and at least one entire MAC-hs SDU.

61. The WTRU of claim 56 wherein the MAC-hs layer is configured to determine whether a transmission has failed for at least one of the plurality of segments.

62. The WTRU of claim 61 wherein the MAC-hs layer is configured to delete stored segments waiting for reassembly when at least one segment of the MAC-hs SDU is lost.

63. The WTRU of claim 56 wherein the MAC-hs layer is configured to flush all segments of the same MAC-hs SDU that are waiting for reassembly from a buffer if a timer expires before all segments of the same MAC-hs SDU have been received.

64. The WTRU of claim 63 wherein the timer is reset every time a segment that is part of the MAC-hs SDU is received in correct order.

65. The WTRU of claim 63 wherein the timer is configurable by radio resource control (RRC) signaling.

66. The WTRU of claim 63 wherein the timer is reset only once upon reception of the first segment of the MAC-hs SDU.

67. The WTRU of claim 56 wherein the MAC-hs layer flushes all segments of the same MAC-hs SDU that are waiting for reassembly from a buffer when hybrid automatic repeat request (H-ARQ) process failure is detected for a particular segment.

68. The WTRU of claim 67 wherein the H-ARQ process failure is detected when the maximum number of H-ARQ retransmissions has been reached.

69. The WTRU of claim 67 wherein the H-ARQ process failure is detected when a transmission indicating new data is received on the same H-ARQ process while expecting a retransmission.