Description

A requirement has arisen in recent years for high-quality reproduction of both printed images and continuous tone images by utilizing certain types of display device, such as a gas plasma display, which are inherently capable of generating only two levels of display density. This is achieved by generating a spatial gray scale display image. However problems are presented by the prior art methods proposed for implementing such reproduction.

With such a bi-level display device, each picture element generated by the display can be set (e.g. as an element of a dot matrix) in either a bright or a dark state. There have been various proposals for implementing pseudo-continuous tone reproduction by such display devices by employing a spatial gray scale. These methods are based on setting a relatively high proportion of picture elements of the display in the light state to represent a light-density region of the original image, and a high proportion in the dark state in the case of a region of the image which should appear dark.

The most well-known method of providing such pseudo-continuous tone reproduction is the dither technique. With this method, a continuous tone image is reproduced on the basis of numbers of dots within each of predetermined areas of the continuous tone image, and utilizes a dither matrix. Threshold values of the dither matrix are compared with the level of an input signal, one picture element at a time, to thereby execute bi-level image conversion processing. However this method has the disadvantage that the continuous tone characteristic and the resolution of the image that is obtained will depend directly upon the size of the dither matrix, and have a mutually incompatible relationship. Moreover with the dither technique, it is difficult to avoid the generation of moire patterns, particularly when printed images are reproduced.

A method has been proposed in the prior art which is highly effective in overcoming the problems of the dither method, i.e. reducing the incompatibility between a good continuous tone characteristic and high resolution, and suppressing the generation of moire patterns. The method is called the error diffusion method, which has been proposed by R. Floyd and L. Steinberg under the title "An Adaptive Algorithm for Spatial Gray Scale", published in the SID 75 Digest, pp 36-37. The basic principles of the proposed method are as follows. To determine whether a picture element of the input signal is to be displayed at the dark or at the light level, the corresponding level of the input image signal is compared with a threshold value, and a light/dark decision thereby made. The density of a picture element of the display will in general be in error with relation to the desired density of that element, i.e. the density of the corresponding picture element in the original continuous tone image. This error is referred to in the following as the bi-level conversion error. However the effects of this error are substantially reduced by subsequently modifying the respective values of desired density of a set of picture elements which are positioned peripherally adjacent to the object picture element.

With the method proposed by Floyd and Steinberg, the effects of the bi-level conversion error of each picture element are substantially reduced by modifying the respective desired densities of a set of picture elements which are positioned peripherally adjacent to that picture element, the modification being performed by apportioning the the value of error obtained for that object picture element among these peripheral picture elements, with the error being apportioned in accordance with predetermined fixed factors. Such factors are referred to in the following as apportionment factors.

The error diffusion methd is superior to the dither method, with regard to image resolution and continuous tone characteristic, and enables the degree of generation of moire patterns to be made very small, even when a printed image is being reproduced. However in the case of reproduction of an image which has only small amounts of changes in density, and computer-generated images which have areas of extremely uniform density, the error diffusion method produces regions of texture in the reproduced image, with this texture being specific to the error diffusion method. For this reason, the error diffusion method has not been widely adopted. The reason for generation of this texture is that a fixed relationship is continuously maintained between an object picture element and the aforementioned set of picture elements which are disposed peripherally adjacent to the object picture element, and fixed values are also maintained for the respective proportions by which the bi-level conversion error of the object picture element is apportioned among these peripheral picture elements.

The term "object picture element" as used herein has the significance of a picture element which is currently being processed, to determine a corresponding bi-level display image value, with data being utilized in that processing which have been obtained beforehand during processing of preceding picture elements.

US-A-4,449,150 (Kato) discloses an image signal processing apparatus in accordance with the precharacterising portion of claim 1 but in which the apportionment factor values are fixed.

The present invention can provide an image signal processing apparatus which prevents generation of a texture such as that produced by the error diffusion method described above, and which also provides an excellent continuous tone characteristic and high resolution, with only a very small degree of moire pattern being produced even when a printed image or an image containing regions of highly uniform density is being reproduced.

According to the present invention, there is provided an image signal processing apparatus for sampling an input signal representing a continuous tone image, in units of picture elements contained in successive scanning lines of said input signal, to produce a bi-level image signal; the apparatus comprising:

error memory means for storing accumulated errors at positions respectively corresponding to an object picture element and a plurality of picture elements which are positioned peripherally adjacent to said object picture element;

input correction means for adding a level of said input signal, representing the density of said object picture element in said image, to an accumulated error which has been stored during a preceding processing step at said position within said error memory means corresponding to said object picture element, to derive a corrected level as a result of said addition;

bi-level conversion means for comparing said corrected level with a predetermined threshold value to thereby determine a bi-level value for said object picture element, and for producing said bi-level value as said bi-level image signal;

difference computation means for deriving a bi-level conversion error which is the difference between said corrected level and said bi-level value determined for said object picture element;

apportionment factor generating means for generating a plurality of apportionment factors for apportioning said bi-level conversion error among a plurality of picture elements which have not yet been processed and are positioned at the periphery of said object picture element; and

error apportionment and updating means for computing respective error apportionment values corresponding to said peripherally adjacent picture elements, based on said bi-level conversion error for said object picture element and said plurality of apportionment factors, for adding said error apportionment values to corresponding accumulated errors which have been previously stored in said error memory means at predetermined storage positions corresponding to said peripherally adjacent picture elements, to obtain updated accumulated errors, and for storing the updated accumulated errors in said error memory means;

the apparatus being characterised in that said apportionment factor generating means is adapted to periodically alter said apportionment factors.

The following five configurations can be utilized to implement the aforementioned apportionment factor generating means.

Firstly, the apportionment factor generating means can comprise means which function to alter a correspondence between respective picture element positions and a set of apportionment factors for the plurality of picture elements which have not yet been processed and are positioned at the periphery of the object picture element, with the alteration being executed periodically with a predetermined alteration period.

Secondly, the apportionment factor generating means can comprise means which function to generate apportionment factors for the plurality of picture elements which have not yet been processed and are positioned at the periphery of the object picture element, by executing selection of apportionment factors from a plurality of sets of apportionment factors, said selection being executed at intervals having a predetermined alteration period.

Thirdly, the apportionment factor generating means can comprise means which function to generate apportionment factors for the plurality of picture elements which have not yet been processed and are positioned at the periphery of the object picture element, by randomly selecting the apportionment factors from a plurality of sets of apportionment factors, the selection being performed periodically with a predetermined alteration period.

Fourthly, the apportionment factor generating means can comprise means which function to generate apportionment factors for the plurality of picture elements which have not yet been processed and are positioned at the periphery of the object picture element, by randomly establishing correspondences between these peripheral picture elements and apportionment factors of a single set of apportionment factors.

Fifthly, the apportionment factor generating means can comprise means which function to generate apportionment factors for the plurality of picture elements which have not yet been processed and are positioned at the periphery of the object picture element, by randomly selecting these apportionment factors from among a plurality of sets of apportionment factors, with the random selecting being executed in accordance with random number generation which is initialized once in each occurrence of an arbitrary number of successive scanning lines.

In the accompanying exemplary drawings:

Fig. 1 is a conceptual block diagram of an embodiment of an image signal processing apparatus according to the present invention and;

Figs. 2 through 5 are general circuit diagrams showing essential components of second through fifth embodiments of the invention respectively, illustrating specific configurations for an apportionment factor generating updating section and an error apportioning and updating section.

Fig. 1 is a conceptual block diagram showing the essential components of a first embodiment of an image signal processing apparatus according to the present invention. In Fig. 1, the display coordinates of an object picture element (i.e. a picture element for which image processing is currently being executed, as defined hereinabove) are designated as (x,y). Reference numeral 1 denotes an error memory, and numeral 2 denotes a storage region of error memory 1 which corresponds to a region of the image to be processed containing a plurality of picture elements that have not yet been processed and are positioned adjacent to the periphery of the object picture element. Positions within this region 2 can be expressed in terms of an error apportionment factor matrix. Numeral 3 denotes a position within the error memory 1 in which has been stored an accumulated error S_{xy} for the object picture element having coordinates (x,y), as indicated by the "*" symbol. Numeral 4 denotes an input terminal coupled to receive an input image signal. A level I_{xy} of this input signal represents a desired value of display density for the object picture element having coordinates (x,y). Numeral 5 denotes an adder which amends the input signal level I_{xy} by adding thereto the accumulated error S_{xy} (previously derived and stored as described hereinafter) to produce a corrected input level I'_{xy},i.e. $I'_{xy} = I_{xy} + S_{xy}$. Numeral 6 denotes an output terminal from which a bi-level output value P_{xy} corresponding to the input level I_{xy} is produced as an output signal, i.e. a bi-level image signal, either at a level designated as the R level or at O level. Numeral 7 denotes a terminal to which is applied a threshold level, for example a fixed threshold value of R/2, and 8 denotes a device such as a comparator, for executing bi-level conversion of the input level I'_{xy},by comparing the level I'_{xy} with the fixed threshold value R/2, to produce as output a bi-level value P_{xy} at the R level if $I'_{xy} > R/2$, and otherwise producing P_{xy} at the O level. Numeral 9 denotes a subtractor, for computing a difference between the input level I'_{xy} and the output bi-level value P_{xy} to thereby derive a bi-level conversion error E_{xy} (i.e. $E_{xy} = I'_{xy} - P_{xy}$) for the object picture element. Numeral 10 denotes an apportionment factor generating section for generating apportionment factors for apportioning the bi-level error E_{xy} among the peripherally adjacent picture elements in region 2. Numeral 11 denotes an error apportionment and updating section for computing error apportionment values corresponding to the picture elements which have not yet been processed and are positioned at the periphery of the object picture element, (these error apportionment values being computed based on a plurality of apportionment factors produced from the apportionment factor generating section 10 and the bi-level error E_{xy} for the object picture element) and for adding these error apportionment values to respective values of accumulated error for the set of peripheral picture elements A to D of the region 2, these accumulated error values having been derived during preceding similarly executed processing steps for other picture elements and stored at corresponding positions within the error memory 1. The results of these additions, which constitute a set of updated accumulated errors, are then stored by the error apportioning and updating section 11 in the error memory 1, to be utilized in succeeding picture element processing steps. Numeral 12 denotes a sync signal input terminal from which a sync signal 13 is applied to control the timing of operations by the apportioning factor generating section 10 and the error apportioning and updating section 11, e.g. to determine the period between successive picture element processing steps.

The apparatus of Fig. 1, in effect, functions to periodically sample the input image signal applied to terminal 4, to obtain a level value I_{xy} of that signal which represents the density of a picture element of the original image, and to convert that level I_{xy} to a corresponding bi-level output value P_{xy}. The picture elements which are sampled in this way extend along successive (horizontal) lines of the display image, i.e. the x-direction, and a sync signal whose period determines the period of these conversions along the x-direction will be referred to in the following as the x-sync signal. The successive lines of picture elements which are displayed will be referred to as scanning lines. These are periodically selected along the y-direction (i.e. vertical direction) of the display, for processing, and a sync signal whose period corresponds to the period between successive scanning lines will be referred to in the following as the y-sync signal.

With the embodiment of Fig. 1, the x-sync signal is applied as sync signal 13 to control the operation of both the apportionment factor generating section 10 and the error apportionment and updating section 11. However it would be equally possible to operate the apportionment factor generating section 10 based on the y-sync signal rather than the x-sync signal.

It should be noted that the present invention is not limited to the application of a fixed threshold value to the signal terminal 7, and that it would be equally possible to apply to that terminal an ar-

bitrary signal such as a signal representing a different image from that being processed, and to thereby execute control of the output image signal produced by the apparatus, on the basis of the signal thus applied to terminal 7.

With the apparatus having the configuration set out above, the accumulated error S_{xy} for the object picture element is obtained on the basis of the following equation:

$$S_{xy} = K_{ij} * E_{x-j+2,\, y-i+1} \quad (1)$$

In the above, i and j are coordinates expressed within the error apportionment factor matrix, while the error apportionment factor K_{ij} expresses weighting values for apportionment of the error E_{xy} among a predetermined plurality of peripheral picture elements positioned adjacent to the object picture element, as described hereinabove.

The above computation is executed by the error apportioning and updating section 11, which then apportions the bi-level conversion error E_{xy} among the respective unprocessed picture elements A to D of the region 2 in accordance with the respective apportionment factors for these picture elements which are produced by the apportionment factor generating section 10, and performs updating, by addition processing, of respective amounts of accumulated error for each of these picture elements.

The apportionment factor generating section 10 functions on the basis of one or more predetermined sets of apportionment factors, and operates in synchronism with the x-sync signal 13 applied from input terminal 12. The apportionment factor generating section 10 functions to generate a set of apportionment factors KA to KD for apportioning the bi-level conversion error E_{xy} among the plurality of picture element positions A to D within the peripheral picture element region 2, and supplies these apportionment factors to the error apportioning and updating section 11. The error apportioning and updating section 11 operates in synchronism with the sync signal 13 to execute processing utilizing these apportionment factors KA to KD, the bi-level conversion error E_{xy} of the object picture element (produced from the subtractor 9), and a set of accumulated errors S'_A, S'_C and S'_D (which have been generated and stored in previously executed image processing operations), by reading out these accumulated errors from respective predetermined storage locations within the error memory 1 which respectively correspond to the picture element positions A, C and D of the peripheral region 2. This processing includes multiplication and addition processing, and serves to derive a set of updated accumulated errors S_A to S_D which respectively correspond to the picture element positions A, C and D of the peripheral region 2. The computation processing executed for this purpose is in accordance with the following equations:

$$\begin{aligned} S_A &= S'_A + K_A \times E_{xy} \\ S_B &= K_B \times E_{xy} \\ S_C &= S'_C + K_C \times E_{xy} \\ S_D &= S'_D + K_D \times E_{xy} \end{aligned} \quad (3)$$

Updating processing is then executed by the error apportioning and updating section 11, by storing the new values of the accumulated errors S_A to S_D at locations in the error memory 1 which respectively correspond to the picture element positions A to D. These updated values of accumulated errors are subsequently utilized in processing succeeding picture elements, in the same way as described above.

This completes a step of image processing whereby the bi-level value P_{xy} for the picture element 3 shown in Fig. 1 is generated and accumulated error updating performed for peripherally adjacent picture elements A, B, C and D of picture element 3. In the succeeding stage of image processing, the processing described above is again executed, to obtain a bi-level output value P_{xy} for the next picture element (i.e. that indicated as A, in Fig. 1), utilizing the accumulated error S_A which was derived and stored as described above, as the new value of accumulated error S_{xy}, and with new values of accumulated error being derived and stored for a set of picture elements in a new region 2 disposed peripherally adjacent to that picture element A (i.e. including picture elements C and B).

In the following, descriptions will be given of four other embodiments of the present invention. The principles of operation of each of these other embodiments are basically similar to those of the embodiment of Fig. 1, and the operation and components relating to application of the accumulated error S_{xy} and the bi-level conversion error E_{xy} are identical to those of the embodiment of Fig. 1. For that reason, only the operation of the apportionment factor generating section 10 and the error apportioning and updating section 11, in conjunction with the error memory 1, will be described in detail for each of these embodiments.

It should be noted that each of the configurations for the apportionment factor generating section 10 respectively described for the following embodiments is equally applicable to the first embodiment of Fig. 1 described above.

Fig. 2 shows the configuration of the apportionment factor generating section 10 and the error apportioning and updating section 11 for a second embodiment of the present invention. As shown in Fig. 2, the apportionment factor generating section

10 contains a recirculating shift register consisting of four shift register stages, respectively designated as 200 (SR1) to 203 (SR4). Prior to the commencement of image processing, a set of apportionment factors KA0, KB0, KC0 and KD0 are loaded into the registers 200 to 203 as respective initial values. The x-direction sync signal 13 is applied from an input terminal 12 to each of the registers 200 to 203, to produce recirculation of the stored apportionment factors through these registers in the direction of registers 203, 200, 201, 202. The output data from the registers 200 to 204 are supplied to the error apportioning and updating section 11 as apportionment factors K_A to K_D respectively. In this way, the value of the apportionment factor K_A will change in the sequence KA0, KB0, KC0, KD0, in synchronism with the sync signal from input terminal 13. Similarly the apportionment factor K_B will change in the sequence KB0, KC0, KD0, KA0, the apportionment factor K_C will change in the sequence KC0, KD0, KA0, KB0, and tha apportionment factor K_D will change in the sequence KD0 KA0, KB0, KC0. The error apportioning and updating section 11 multiplies the apportionment factor K_A by the bi-level conversion error E_{xy} that is inputted from the subtractor 9, and the result is then added to the accumulated error S'_A which corresponds to the picture element position A, (the accumulated error S'_A being read out from the error memory 1) and the result of this is temporarily stored in an internal register 204 (RA) to be utilized as the accumulated error S_{xy} for the next picture element to be processed, in the suceeding picture element processing step. Since the accumulated error for the picture element B is first produced during processing of the object picture element 3, the bi-level conversion error E_{xy} and the apportionment factor K_B are multiplied together and the result is temporarily stored as the accumulated error for the picture element position B, in an internal register 205 (RB). The apportionment factor KC and the bi-level conversion error E_{xy} are multiplied together, and the result is added to an accumulated error which was derived during the immediately preceding picture element processing operation and had been temporarily stored in the internal register 205 (RB), and the result of this addition is then temporarily stored in the internal register 206 (RC), as the accumulated error value for the picture element position C. The apportionment factor KD and the bi-level conversion error E_{xy} are multiplied together, and the result is added to an accumulated error which was derived during the immediately preceding picture element processing operation and had been temporarily stored in the internal register 206 (RC), and the result of this addition is then stored in a position in the error memory 1 which corresponds to the picture element position D, as the updated accumulated error value for the picture element position D.

As a result of this operation of the error apportioning and updating section 11, the only memory accessing which is required for the error memory 1 consists of read-out access corresponding to the picture element A, and write-in access corresponding to the picture element D. Thus, a practical configuration for this embodiment can be easily implemented.

It should be noted that it would be possible to attain results which are close to those obtainable with the above embodiment, if apportionment factor alteration by the apportionment factor generating section 10 were to be executed once in each occurrence of a plurality of successive picture element processing steps, rather than upon each successive processing step (in synchronism with the x-direction sync signal) as in the above embodiment. For example, it would be equally possible to execute shift operation of register stages 200 to 203 in response to the y-direction sync signal, rather than the x-direction sync signal.

With the second embodiment of the invention described above, a plurality of apportionment factors in a set of apportionment factors produced by the apportionment factor generating section 10 are sequentially altered as image processing proceeds, to thereby avoid a condition in which the respective proportions by which a bi-level conversion error of an object picture element is apportioned among a set of peripherally adjacent picture elements are held constant. As a result, the texture which is produced with the prior art error diffusion method is substantially eliminated.

Fig. 3 shows a specific configuration for the error apportioning and updating section 11 and the apportionment factor generating section 10 of a third embodiment of an image signal processing apparatus according to the present invention. As shown in Fig. 3, the apportionment factor generating section 10 contains memories 300 and 301, for respectively storing two sets of apportionment factors $K1_A$ to $K1_D$ and $K2_A$ to $K2_D$. These apportionment factors are stored beforehand in the memories 300 and 301, prior to the commencement of image processing. A selection signal generating circuit 302 receives from a sync signal input terminal 12 an x-direction sync signal 13, and produces as output a selection signal 307 at predetermined image processing intervals. This signal 307 is applied to a set of selectors 303 to 306. The selectors 303 to 306 function to select apportionment factors K_A to K_D (which respectively correspond to the picture element positions A to D of the error memory 1) from the two sets of apportionment factors stored in memories 300 nd 301, i.e. apportionment

factors $K1_A$, $K1_B$, $K1_C$ and $K1_D$) and ($K2_A$, $K2_B$, $K2_C$ and $K2_D$). The selection signal generator 302 within the apportionment factor generating section 10 of this embodiment produces a selection signal whereby the two sets of apportionment factors stored in memories 300 and 301 are sequentially selected by the selectors 303 to 306 to be produced as the apportionment factors K_A to K_D. However it would be equally possible utilize as the selection signal generator 302 a maximum length counter circuit, for example, coupled to receive the x-sync signal 13 from input terminal 12, and to thereby execute random, rather than periodic selection of the two sets of apportionment factors in memories 300 and 301, i.e. to generate and apply to the selectors 303 to 306 a selection signal which executes such random selection.

The error apportioning and updating section 11 operates in synchronism with the sync signal 13 to multiply the apportionment factors KA to KD thus produced by the bi-level conversion error E_{xy} that is inputted from the subtractor 9, to thereby obtain a set of error apportionment values 312 to 315.. The error apportionment value 312 is then added to the accumulated error S'_A that corresponds to the picture element position A, (the accumulated error S'_A being read out from the error memory 1) and the result of this is temporarily stored in an internal register 317 (RA) to be utilized as the accumulated error S_{xy} for the next picture element to be processed in the succeeding processing step. The error apportionment value 313 is temporarily stored (without being altered) as the accumulated error SB for the picture element position B, in an internal register 318 (RB). The error apportionment value 314 and data which were derived during the immediately preceding image processing operation and had been temporarily stored in the internal register 318 (RB) are added together, and the result of the addition is then temporarily stored in the internal register 320, as the accumulated error value (RC) for the picture element position C. The error apportionment value 315 is added to data which were derived during the immediately preceding picture element processing operation and temporarily stored in the internal register 320 (RC), and the result of this addition is stored in a memory position in the error memory 1 which corresponds to the picture element position D. In this way, the ony memory accessing which is required in the error memory 1 consists of read-out access corresponding to the picture element A, and write-in access corresponding to the picture element D, so that a practical configuration can be easily implemented.

With the third embodiment described above, the image signal processing apparatus includes apportionment factor generating means which function by selecting a single set of apportionment factors from a plurality of predetermined sets of apportionment factors, with the selection being performed in a predetermined sequence or in a random sequence. As a result, the amounts of bi-level conversion error which are apportioned among picture elements disposed peripherally adjacent to an object picture element are prevented from being biased towards particular picture elements which have a fixed mutual positional relationship with the object picture element, whereby an output image produced by processing by the apparatus of the present invention can be kept substantially free from a texture pattern.

A specific configuration for the error apportioning and updating section 11 and the apportionment factor generating section 10 of a foruth embodiment of an image signal processing apparaus according to the present invention 1 will now be described, referring to Fig. 4. In Fig. 4, a memory 400 is provided within the apportionment factor generating section 10, for storing a single set of apportionment factors K1 to K4. This set of apportionment factors is stored prior to the commencement of image processing. A random signal generator 401 produces a selection signal 402 at periodic timings which are synchronized with the x-direction sync signal 13 supplied from sync signal input terminal 12. The random signal generator 401 can be configured as a maximum length counter circuit, for example. A selector 403 has four output terminals 403a to 403d, and selects respective ones of the stored apportionment factors K1 to K4 to be transferred to the output terminals 403a to 403d, in response to the selection signal 402. The selector 403 thereby performs random selection from the set of apportionment factors K1 to K4 stored in the memory 400, to produce apportionment factors KA to KD respectively corresponding to the picture elements A to D in the peripherally picture element region 2 adjacent to the object picture element 1. There are 401 possible ways in which the apportionment factors KA to KD can be selected from K1 to K4, i.e. in which KA to KD can be connected as K1 to K4, so that the selection signal 402 is a 4-bit parallel signal.

The error apportioning and updating section 11 operates in synchronism with the sync signal 13 to multiply the apportionment factors KA to KD (supplied from the apportionment factor generating section 10) by the bi-level conversion error E_{xy} that is supplied from the subtractor 9, to thereby obtain a set of error apportionment values 408 to 411. This multiplication is executed by a set of multipliers 404 to 407. The error apportionment value 408 is then added (by an adder 412) to the accumulated error S'_A thatcorresponds to the picture element position A, (the accumulated error S'_A being read out from the error memory 1) and the

result of this is temporarily stored in an internal register 413 (RA) to be utilized as the accumulated error S_{xy} for the next picture element to be processed in the succeeding processing step. The error apportionment value 409 is temporarily stored (without alternation) as the acccumulated error SB for the picture element position B, in an internal register 413 (RB). The error apportionment value 409 and data which were derived during the immediately preceding picture element processing operation and temporarily stored in the internal register 413 (RB) are added together (by an added 414), and the result of the addition is then temporarily stored in the internal register 415, as the accumulated error value (SC) for the picture element position C. The error apportionment value 409 is then added to data which were derived during the immediately preceding picture element processing operation and temporarily stored in the internal register 415 (RC), and the result of this addition is stored in a memory position in the error memory 1 which corresponds to the picture element position D. As for the previously described configurations, a practical configuration for this embodiment can be easily implemented, due to the limited number of memory access operations required.

With the configuration shown in Fig. 4 and described above, as for the two previously described embodiments, a condition is avoided wherein fixed proportions of apportionment of a bi-level conversion error of an object picture element are estabilished among peripherally adjacent picture elements to that object picture element, this condition being avoided due to the use of an apportionment factor generating section which executes random selection from a single predetermined set of apportionment factors of a plurality of apportionment factors respectively corresponding to peripheral picture element positions, with this selection being repetitively executed as image processing proceeds. As a result, a texture pattern which is produced with the prior art error diffusion method is substantially eliminated.

It should also be noted that it would be equally possible to apply a sync signal to the random signal generating circuit 401 such that alteration of the apportionment factors K_A to K_D occurs once in each of an arbitrary plurality of successive picture element processing steps, rather than upon each successive processing step (in response to the x-direction sync signal 13) as in the above embodiment.

A specific configuration for the error apportioning and updating section 11 and the apportionment factor generating section 10 of a fifth embodiment of an image signal processing apparatus according to the present invention will now be described, referring to Fig. 5. With this configuration the apportionment factor generating section 10 is provided with two memories 500 and 501, which respectively have apportionment factor sets $K1_A$ to $K1_D$ and $K2_A$ to $K2_D$ stored therein prior to the commencement of processing, i.e. a plurality of sets of apportionment factors are stored beforehand.

An initial value table 502 has initial values stored therein prior to the commencement of image processing, which are used to determine the starting point of random signal generation, which is performed periodically once in a plurality of scanning lines. An initial value 505 is thereby outputted in response to a line sync (i.e. y-direction sync) signal 504 which is applied from a sync signal input terminal 503. The line sync signal 504 is synchronized with the period of processing successive lines of picture elements, as described hereinabove. The initial value table can be configured from a RAM or ROM memory, having stored therein a set of values of successively increasing magnitude, which are read out on successive scanning lines, in response to the line sync signal applied thereto. However it would be equally possible to configure the initial value table as a counter, which counts successive pulses of the line sync signal, so that successive initial values produced thereby are incremented by a predetermined integer once in each occurrence of an arbitrary number of scanning line periods.

The random signal generator 506 periodically generates a random selection based on random number generation, in synchronism with the sync signal 13 which is generated in synchronism with an image processing period along the x-direction. The starting point of this random signal generation is periodically set to a new initial value 505 which is produced from the initial value table 502 in response to the line sync signal 504.

The selection signal 507 can be generated for example by utilizing a maximum length counter circuit as the random signal generator 506. The selectors 508 to 511 are responsive to this selection signal 507 for randomly selecting and transferring respective ones of the two sets of apportionment factors stored in the memories 500 and 501, to be outputted from the selectors as the apportionment factors K_A to K_D.

The error apportioning and updating section 11 operates in synchronization with the sync signal 13 to multiply the apportionment factors K_A to K_D from the apportionment factor generating section 10 by the bi-level conversion error E_{xy} which is supplied from the subtractor 9, to thereby obtain a set of error apportionment values 516 to 519. This multiplication is executed by a set of multipliers 512 to 515. The error apportionment value 516 is then

added by an adder 520 to the accumulated error S'_A that corresponds to the picture element position A, (the accumulated error S'_A being read out from the error memory 1) and the result of this is temporarily stored in an internal register 521 (RA) to be utilized as the accumulated error S_{xy} for the next picture element to be processed in the suceeding processing step. The error apportionment value 517 is temporarily stored as the accumulated error SB for the picture element position B, in an internal register 522 (RB). The error apportionment value 518 and data which had been temporarily stored in the internal register 24 (RB) are added together by an adder 523, and the result is then temporarily stored in the internal register 524, as the accumulated error value (SC) for the picture element position C. The error apportionment value 519 is added by an adder 525 to data which had been temporarily stored in the internal register 524 (RC), and the result is stored in a memory position in the error memory 1 which corresponds to the picture element position D.

With the configuration of Fig. 5 described above, as for the previously described embodiments, a condition is avoided whereby the respective proportions of apportionment of a bi-level conversion error of an object picture element among a set of peripherally adjacent picture elements are held constant. This is achieved by random selection of apportionment factors from a plurality of sets of apportionment factors, as image processing proceeds. Elimination of a texture pattern is thereby achieved, as for these previous embodiments.

Furthermore, due to the fact that the starting point of random signal generation (i.e. based on generation of successive random numbers) is newly established periodically, once in each occurrence of an arbitrary number of successive scanning lines, texture is effectively suppressed irrespective of the number of picture elements which exist along the x-direction.

It will be apparent from the above that each of the second through fifth embodiments differs from the first embodiment of Fig. 1 with respect to the manner in which accumulated errors are stored. With the embodiment of Fig. 1, all of the accumulated errors are stored in the error memory 1, so that a substantial number of memory read and write access operations with respect to the error memory 1 must be executed during each picture element processing step. However with the embodiments of Figs. 2 to 5, three internal registers of the error apportioning and updating section 11 are utilized for temporary storage of accumulated errors, with the accumulated error S_{xy} for an object picture element being produced from one of these registers (i.e. RA) at the start of a picture element processing step. Thus, the operation and configuration of the error memory 1 can be made more simple, with the embodiments of Figs. 2 to 5, due to the reduced number of memory accesses which are necessary during each processing step. In spite of these differences, the basic operation of accumulated error generation is substantially identical for all of the embodiments, and the embodiments of Figs. 2 to 5 can be considered (with respect to the configuration and operation of the error apportioning and updating section 11 and error memory 1) as modifications of the embodiment of Fig. 1, with error memory means in these embodiments being constituted by the set of registers RA to RC in conjunction with the error memory 1, whereas the error memory means of the first embodiment is entirely constituted by the error memory 1.

Although the present invention has been described in the above with reference to specific embodiments, it should be noted that various changes and modifications to these may be envisaged. For example, any of the apportionment factor generating sections of the embodiments of Figs. 2 through 5 can be utilized as the apportionment factor generating section of the embodiment of Fig. 1.

Claims

1. An image signal processing apparatus for sampling an input signal representing a continuous tone image, in units of picture elements contained in successive scanning lines of said input signal, to produce a bi-level image signal; the apparatus comprising:

error memory means (1) for storing accumulated errors at positions respectively corresponding to an object picture element and a plurality of picture elements which are positioned peripherally adjacent to said object picture element;

input correction means (5) for adding a level of said input signal, representing the density of said object picture element in said image, to an accumulated error which has been stored during a preceding processing step at said position within said error memory means corresponding to said object picture element, to derive a corrected level as a result of said addition;

bi-level conversion means (8) for comparing said corrected level with a predetermined threshold value to thereby determine a bi-level value for said object picture element, and for producing said bi-level value as said bi-level image signal;

difference computation means (9) for deriving a bi-level conversion error which is the

added by an adder 520 to the accumulated error S'_A that corresponds to the picture element position A, (the accumulated error S'_A being read out from the error memory 1) and the result of this is temporarily stored in an internal register 521 (RA) to be utilized as the accumulated error S_{xy} for the next picture element to be processed in the suceeding processing step. The error apportionment value 517 is temporarily stored as the accumulated error SB for the picture element position B, in an internal register 522 (RB). The error apportionment value 518 and data which had been temporarily stored in the internal register 24 (RB) are added together by an adder 523, and the result is then temporarily stored in the internal register 524, as the accumulated error value (SC) for the picture element position C. The error apportionment value 519 is added by an adder 525 to data which had been temporarily stored in the internal register 524 (RC), and the result is stored in a memory position in the error memory 1 which corresponds to the picture element position D.

With the configuration of Fig. 5 described above, as for the previously described embodiments, a condition is avoided whereby the respective proportions of apportionment of a bi-level conversion error of an object picture element among a set of peripherally adjacent picture elements are held constant. This is achieved by random selection of apportionment factors from a plurality of sets of apportionment factors, as image processing proceeds. Elimination of a texture pattern is thereby achieved, as for these previous embodiments.

Furthermore, due to the fact that the starting point of random signal generation (i.e. based on generation of successive random numbers) is newly established periodically, once in each occurrence of an arbitrary number of successive scanning lines, texture is effectively suppressed irrespective of the number of picture elements which exist along the x-direction.

It will be apparent from the above that each of the second through fifth embodiments differs from the first embodiment of Fig. 1 with respect to the manner in which accumulated errors are stored. With the embodiment of Fig. 1, all of the accumulated errors are stored in the error memory 1, so that a substantial number of memory read and write access operations with respect to the error memory 1 must be executed during each picture element processing step. However with the embodiments of Figs. 2 to 5, three internal registers of the error apportioning and updating section 11 are utilized for temporary storage of accumulated errors, with the accumulated error S_{xy} for an object picture element being produced from one of these registers (i.e. RA) at the start of a picture element processing step. Thus, the operation and configuration of the error memory 1 can be made more simple, with the embodiments of Figs. 2 to 5, due to the reduced number of memory accesses which are necessary during each processing step. In spite of these differences, the basic operation of accumulated error generation is substantially identical for all of the embodiments, and the embodiments of Figs. 2 to 5 can be considered (with respect to the configuration and operation of the error apportioning and updating section 11 and error memory 1) as modifications of the embodiment of Fig. 1, with error memory means in these embodiments being constituted by the set of registers RA to RC in conjunction with the error memory 1, whereas the error memory means of the first embodiment is entirely constituted by the error memory 1.

Although the present invention has been described in the above with reference to specific embodiments, it should be noted that various changes and modifications to these may be envisaged. For example, any of the apportionment factor generating sections of the embodiments of Figs. 2 through 5 can be utilized as the apportionment factor generating section of the embodiment of Fig. 1.

Claims

1. An image signal processing apparatus for sampling an input signal representing a continuous tone image, in units of picture elements contained in successive scanning lines of said input signal, to produce a bi-level image signal; the apparatus comprising:

error memory means (1) for storing accumulated errors at positions respectively corresponding to an object picture element and a plurality of picture elements which are positioned peripherally adjacent to said object picture element;

input correction means (5) for adding a level of said input signal, representing the density of said object picture element in said image, to an accumulated error which has been stored during a preceding processing step at said position within said error memory means corresponding to said object picture element, to derive a corrected level as a result of said addition;

bi-level conversion means (8) for comparing said corrected level with a predetermined threshold value to thereby determine a bi-level value for said object picture element, and for producing said bi-level value as said bi-level image signal;

difference computation means (9) for deriving a bi-level conversion error which is the

* C L M S *

difference between said corrected level and said bi-level value determined for said object picture element;

apportionment factor generating means (10) for generating a plurality of apportionment factors for apportioning said bi-level conversion error among a plurality of picture elements which have not yet been processed and are positioned at the periphery of said object picture element; and

error apportionment and updating means (11) for computing respective error apportionment values corresponding to said peripherally adjacent picture elements, based on said bi-level conversion error for said object picture element and said plurality of apportionment factors, adding said error apportionment values to corresponding accumulated errors which have been previously stored in said error memory means at predetermined storage positions corresponding to said peripherally adjacent picture elements, to obtain updated accumulated errors, and storing the updated accumulated errors in said error memory means;

the apparatus being characterised in that said apportionment factor generating means (10) is adapted to periodically alter said apportionment factors.

2. An image signal processing apparatus according to claim 1, wherein said apportionment factor generating means (10) comprises a recirculating shift register having a plurality of shift register stages (200, 201, 202, 203) for holding respective ones of a predetermined set of apportionment factors and responsive to a periodically generated shift signal for executing shift operations, said apportionment factors being periodically shifted through said shift register stages and being generated as outputs from said shift register stages, to be supplied to said error apportioning and updating means.

3. An image signal processing apparatus according to claim 1, wherein said apportionment factor generating means (10) comprises means for generating said apportionment factors by sequentially selecting said apportionment factors from a plurality of predetermined sets of apportionment factor values.

4. An image signal processing apparatus according to claim 3, wherein said apportionment factor generating means (10) comprises:

a plurality of memory means (300, 301) having stored therein respective sets of apportionment factor values;

selection signal generating means (302) for periodically generating a selection signal (307) ; and

selector means (303, 304, 305, 306), responsive to said selection signal for sequentially selecting values from said sets of apportionment factor values stored in said memory means, to to be produced from said selector elements as said apportionment factors (K_A-K_O) for apportioning said bi-level conversion error among said peripherally adjacent picture elements.

5. An image signal processing apparatus according to claim 1, wherein said apportionment factor generating means (10) comprises means for generating said apportionment factors by periodically executing random selection of respective values for said apportionment factors from a plurality of predetermined sets of apportionment factor values.

6. An image signal processing apparatus according to claim 5, wherein said apportionment factor generating means (10) comprises:

a plurality of memory means (501, 502,) having stored therein respective sets of apportionment factor values (K_{1a}-K_{1d}, K_{2a}-K_{2d});

selection signal generating means (506) for periodically generating a randomly varying selection signal (507) ; and

a plurality of selector elements (508, 509, 510, 511), each of said selector elements being responsive to said selection signal for randomly selecting one of a plurality of values which are respectively stored in said plurality of memory means, the randomly selected values being outputted from said selector elements as said apportionment factors for apportioning said bi-level conversion error among said peripherally adjacent picture elements.

7. An image signal processing apparatus according to claim 6, wherein said random signal generating means (506) comprises a maximum length counter circuit.

8. An image signal processing apparatus according to claim 7, wherein said random signal generating means (506) generates said selection signal (507) based upon random number generation, wherein said random number generation is initiated from an arbitrary initial value, and wherein said initial value is periodically altered.

9. An image signal processing apparatus according to claim 8, comprising initial value generating means (502) for generating said arbitrary

initial value as a value which is periodically incremented by a predetermined integer.

10. An image signal processing apparatus according to claim 9, wherein said initial value generating means (502) executes said periodic incrementing once in each of an arbitrary number of successive ones of said scanning lines.

11. An image signal processing apparatus according to claim 1, wherein said apportionment factor generating means (10) comprises means for generating said apportionment factors by periodically executing random selection of respective values for said apportionment factors from a single predetermined set of apportionment factor values.

12. An image signal processing apparatus according to claim 12, wherein said apportionment factor generating means (10) comprises:

memory means (400) having stored therein a set of apportionment factor values;

selection signal generating means (401) for periodically generating a randomly varying selection signal (402) ; and

selector means (403) responsive to said selection signal for randomly selecting combinations of said values stored in said memory means (400) and for outputting the selected combination of values as said apportionment factors for apportioning said bi-level conversion error among said peripherally adjacent picture elements.

Patentansprüche

1. Bildsignal-Bearbeitungsvorrichtung zum Abtasten eines anliegenden Signals, das ein kontinuierlich getöntes Bild darstellt, in Einheiten von Bildelementen, die in aufeinander folgenden Abtastzeilen des Eingangssignals enthalten sind, zur Erzeugung eines Zweipegel-Bildsignals; wobei die Vorrichtung umfaßt:
Fehlerspeichermittel (1) zum Speichern akkumulierter Fehler an Positionen, die jeweils einem Objekt-Bildelement und einer Vielzahl von Bildelementen entsprechen, welche peripher benachbart zum Objekt-Bildelement angeordnet sind;
Eingangskorrekturmittel (5), um einen die Dichte des Objekt-Bildelements in dem Abbild repräsentierenden Eingangssignalpegel zu einem akkumulierten Fehler zu addieren, der während eines vorangehenden Bearbeitungsschritts an der dem Objekt-Bildelement entsprechenden Position innerhalb des Fehlerspeichermittels gespeichert worden ist, um einen korrigierten Pegel als ein Ergebnis der Addition abzuleiten;
Zweipegel-Wandlermittel (8) zum Vergleichen des korrigierten Pegels mit einem vorbestimmten Schwellwert, um dadurch einen Zweipegel-Wert für das Objekt-Bildelement zu bestimmen und um den Zweipegel-Wert als das Zweipegel-Bildsignal zu erzeugen;
Differenzrechenmittel (9) zum Ableiten eines Zweipegel-Wandlerfehlers, der die Differenz zwischen dem korrigierten Pegel und dem für das Objekt-Bildelement bestimmten Zweipegel-Wert ist;
Zuteilungsfaktor-Erzeugermittel (10) zum Erzeugen einer Vielzahl von Zuteilungsfaktoren zum Aufteilen des Zweipegel-Wandlerfehlers unter einer Vielzahl von Bildelementen, die noch nicht bearbeitet wurden und an der Peripherie des Objekt-Bildelements angeordnet sind; und
Fehlerzuteilungs- und Aktualisierungsmittel (11) zum Errechnen jeweiliger Fehlerzuteilungs-Werte entsprechend den peripher benachbarten Bildelementen aufgrund des Zweipegel-Wandlerfehlers für das Objekt-Bildelement und dervielzahl von Zuteilungsfaktoren, zum Addieren der Fehlerzuteilungs-Werte zu entsprechenden akkumulierten Fehlern, die vorher in dem Fehlerspeichermittel an vorbestimmten Speicherplätzen gespeichert worden sind, entsprechend den peripher benachbarten Bildelementen, um aktualisierte akkumulierte Fehler zu erhalten und um die aktualisierten akkumulierten Fehler in dem Fehlerspeichermittel zu speichern;
wobei die Vorrichtung dadurch gekennzeichnet ist, daß das Zuteilungsfaktor-Erzeugungsmittel (10) ausgelegt ist, die Zuteilungsfaktoren periodisch zu ändern.

2. Bildsignal-Bearbeitungsvorrichtung nach Anspruch 1, bei der das Zuteilungsfaktor-Erzeugermittel (10) umfaßt ein umlaufendes Schieberegister mit einer Vielzahl von Schieberegisterstufen (200, 201, 202, 203) zum Halten jeweiliger Zuteilungsfaktoren aus einer vorbestimmten Reihe von Zuteilungsfaktoren und zum Ausführen von Schiebevorgängen in Reaktion auf ein periodisch erzeugtes Schiebesignal, wobei die Zuteilungsfaktoren periodisch durch die Schieberegisterstufen geschoben werden, um zu dem Fehlerzuteilungs- und Aktualisierungsmittel zugeführt zu werden.

3. Bildsignal-Bearbeitungsvorrichtung nach Anspruch 1, bei der das Zuteilungsfaktor-Erzeugungsmittel (10) Mittel umfaßt zum Erzeugen der Zuteilungsfaktoren aus einer Vielzahl von vorbestimmten Reihen von Zuteilungsfaktor-

* C L M S *

werten.

4. Bildsignal-Bearbeitungsvorrichtung nach Anspruch 3, bei der das Zuteilungsfaktor-Erzeugungsmittel (10) umfaßt: eine Vielzahl von Speichermitteln (300, 301), in denen jeweilige Reihen von Zuteilungsfaktorwerten gespeichert sind;
Auswahlsignal-Erzeugermittel (302) zum periodischen Erzeugen eines Auswahlsignals (307); und
Auswahlmittel (303, 304, 305, 306), um nacheinander Werte aus den Reihen von in dem Speichermittel gespeicherten Zuteilungsfaktorwerten in Reaktion auf das Auswahlsignal auszuwählen, um von den Auswahlelementen als die Zuteilungsfaktoren (K_A-K_O) zum Zuteilen des Zweipegel-Wandlerfehlers an die peripher benachbarten Bildelemente erzeugt zu werden.

5. Bildsignal-Bearbeitungsvorrichtung nach Anspruch 1, bei der das Zuteilungsfaktor-Erzeugermittel (10) Mittel zum Erzeugen der Zuteilungsfaktoren durch periodisches Ausführen von Zufallsauswahl von jeweiligen Werten für die Zuteilungsfaktoren aus einer Vielzahl von vorbestimmten Reihen von Zuteilungsfaktorwerten umfaßt.

6. Bildsignal-Bearbeitungsvorrichtung nach Anspruch 5, bei der das Zuteilungsfaktor-Erzeugermittel (10) umfaßt:
eine Vielzahl von Speichermitteln (501, 502) mit darin gespeicherten jeweiligen Sätzen von Zuteilungsfaktorwerten (K_{1a}-K_{1d}' K_{2a}-K_{2d});
Auswahlsignal-Erzeugermittel (506) zum periodischen Erzeugen eines sich zufällig ändernden Auswahlsignals (507); und
eine Vielzahl von Auswahlelementen (508, 509, 510, 511), wobei jedes Auswahlelement auf das Auswahlsignal reagiert zum zufälligen Auswählen eines Wertes aus einer Vielzahl von Werten, die jeweils in der Vielzahl von Speichermitteln gespeichert sind, wobei die zufällig ausgewählten Werte von den Auswahlelementen als die Zuteilungsfaktoren ausgegeben werden zum Zuteilen des Zweipegel-Wandlerfehlers an die peripher benachbarten Bildelemente.

7. Bildsignal-Bearbeitungsvorrichtung nach Anspruch 6, bei der das Zufallssignal-Erzeugermittel (506) eine Maximallängen-Zählerschaltung umfaßt.

8. Bildsignal-Bearbeitungsvorrichtung nach Anspruch 7, bei der das Zufallssignal-Erzeugermitel (506) das Auswahlsignal (507) aufgrund von Zufallszahl-Erzeugung erzeugt, wobei die Zufallszahl-Erzeugung von einem willkürlichen Initialwert eingeleitet wird und der Initialwert periodisch geändert wird.

9. Bildsignal-Bearbeitungsvorrichtung nach Anspruch 8, der umfaßt Initialwert-Erzeugermittel (502) zum Erzeugen des willkürlichen Initialwerts als einen Wert, der periodisch um eine vorbestimmte ganze Zahl erhöht wird.

10. Bildsignal-Bearbeitungsvorrichtung nach Anspruch 9, bei der das Initialwert-Erzeugermittel (502) die periodische Erhöhung einmal bei einer willkürlichen Anzahl von aufeinanderfolgenden Abtastzeilen ausführt.

11. Bildsignal-Bearbeitungsvorrichtung nach Anspruch 1, bei der das Zuteilungsfaktor-Erzeugermittel (10) Mittel umfaßt, welche die Zuteilungsfaktoren erzeugen durch periodisches Ausführen von Zufallsauswahl von jeweiligen Werten für die Zuteilungsfaktoren aus einer einzigen vorbestimmten Reihe von Zuteilungsfaktorwerten.

12. Bildsignal-Bearbeitungsvorrichtung nach Anspruch 12, bei der das Zuteilungsfaktor-Erzeugermittel (10) umfaßt: Speichermittel (400), das darin eingespeichert eine Reihe von Zuteilungsfaktorwerten besitzt;
Auswahlsignal-Erzeugermittel (401) zum periodischen Erzeugen eines sich zufällig ändernden Auswahlsignals (402); und
Auswahlmittel (403) in Abhängigkeit von dem Auswahlsignal zum zufälligen Auswählen von Kombinationen der in dem Speichermittel (400) eingespeicherten Werte und zum Ausgeben der ausgewählten Kombinationen von Werten als Zuteilungsfaktoren zum Zuteilen des Zweipegel-Wandlerfehlers an die peripher benachbarten Bildelemente.

Revendications

1. Appareil de traitement de signaux d'image pour échantillonner un signal d'entrée représentant une image de tonalité continue, en unités d'éléments d'image contenus dans des lignes de balayage successives du signal d'entrée de manière à produire un signal d'image bi-niveau, l'appareil comprenant :
un moyen (1) de mémorisation d'erreurs pour stocker dans des positions correspondant respectivement à un élément d'image d'objet et à une pluralité d'éléments d'images qui sont périphériquement adjacents audit élément d'image d'objet des erreurs accumulées ;

un moyen (5) de correction d'entrée pour ajouter le niveau du signal d'entrée, représentant la densité de l'élément d'image d'objet de ladite image, à une erreur accumulée qui a été stockée pendant une étape de traitement précédente à ladite position à l'intérieur du moyen de mémorisation d'erreurs correspondant à l'élément d'image d'objet, de manière à déduire du résultat de ladite addition un niveau corrigé ;

un moyen (8) de conversion bi-niveau pour comparer le niveau corrigé avec une valeur de seuil prédéterminée de manière à déterminer ainsi une valeur bi-niveau pour l'élément d'image d'objet et pour produire ladite valeur bi-niveau en tant que signal d'image bi-niveau ;

un moyen (9) de calcul de différence pour trouver une erreur de conversion bi-niveau qui est la différence entre le niveau corrigé et la valeur bi-niveau déterminée par l'élément d'image d'objet ;

un moyen (10) de génération de facteurs de répartition pour engendrer une pluralité de facteurs de répartition en vue de répartir l'erreur de conversion bi-niveau parmi une pluralité d'éléments d'image qui n'ont pas encore été traités et qui se trouvent à la périphérie de l'élément d'image d'objet ; et

un moyen (11) de répartition et de remise à jour d'erreurs pour calculer les valeurs respectives de répartition d'erreurs correspondant aux éléments d'image périphériquement adjacents sur la base de l'erreur de conversion bi-niveau pour l'élément d'image d'objet et de la pluralité de facteurs de répartition, afin d'ajouter les valeurs de répartition d'erreurs aux erreurs correspondantes accumulées qui ont été stockées précédemment dans le moyen de mémorisation d'erreurs à des positions de stockage prédéterminées correspondant aux éléments d'image périphériquement adjacents de manière à obtenir des erreurs accumulées remises à jour, et pour stocker les erreurs accumulées remises à jour dans le moyen de mémorisation d'erreurs ;

l'appareil étant caractérisé en ce que le moyen (10) de génération de facteurs de répartition est adapté pour modifier périodiquement les facteurs de répartition.

2. Appareil de traitement de signaux d'image selon la revendication 1, dans lequel le moyen (10) de génération de facteurs de répartition comprend un registre à décalage à recirculation comportant une pluralité d'étages (200, 201, 202, 203) de registre à décalage destiné à contenir les facteurs de répartition respectifs d'un ensemble prédéterminé de facteurs de répartition et sensible à un signal de décalage engendré périodiquement pour effectuer des opérations de décalage, les facteurs de répartition étant décalés périodiquement à travers les étages de registre à décalage et étant engendrés en tant que sorties des étages de registre à décalage pour être délivrés au moyen de répartition et de mise à jour d'erreurs.

3. Appareil de traitement de signaux d'image selon la revendication 1, dans lequel le moyen (10) de génération de facteurs de répartition comprend un moyen pour engendrer les facteurs de répartition par sélection de façon séquentielle des facteurs de répartition d'une pluralité d'ensembles prédéterminés de valeurs de facteurs de répartition.

4. Appareil de traitement signaux d'image selon la revendication 3, dans lequel le moyen (10) de génération de facteurs de répartition comprend :

une pluralité de moyens de mémorisation (300, 301) dans lesquels sont stockés des ensembles respectifs de valeurs de facteurs de répartition ;

un moyen (302) de génération de signal de sélection pour engendrer périodiquement un signal de sélection (307) ; et

des moyens de sélection (303, 304, 305, 306) sensibles au signal de sélection pour sélectionner de façon séquentielle, parmi les ensembles de valeurs de facteurs de répartition stockées dans le moyen de mémorisation, des valeurs devant être produites par les éléments de sélection en tant que facteurs de répartition (K_A-K_O) pour répartir l'erreur de conversion bi-niveau parmi les éléments d'image périphériquement adjacents.

5. Appareil de traitement de signaux d'image selon la revendication 1, dans lequel le moyen (10) de génération de facteurs de répartition comprend un moyen pour engendrer les facteurs de répartition par exécution de façon périodique d'une sélection aléatoire de valeurs respectives relatives aux facteurs de répartition parmi une pluralité d'ensembles prédéterminés de valeurs de facteurs de répartition.

6. Appareil de traitement de signaux d'image selon la revendication 5, dans lequel le moyen (10) de génération de facteurs de répartition comprend :

une pluralité de moyens de mémorisation (501, 502) dans lesquels sont stockés les ensembles respectifs de valeurs (K_{1a}-K_{1d}, K_{2a}-

* C L M S *

K_{2d}) de facteurs de répartition ;

un moyen (506) de génération de signal de sélection pour engendrer périodiquement un signal de sélection (507) qui varie de façon aléatoire ; et

une pluralité d'éléments de sélection (508, 509, 510, 511), chacun desdits éléments de sélection étant sensible au signal de sélection pour sélectionner de façon aléatoire une valeur parmi une pluralité de valeurs qui sont stockées respectivement dans la pluralité de moyens de mémorisation, les valeurs sélectionnées de façon aléatoire étant délivrées à la sortie des éléments de sélection comme facteurs de répartition pour répartir l'erreur de conversion bi-niveau parmi les éléments d'image périphériquement adjacents.

7. Appareil de traitement de signaux d'image selon la revendication 6, dans lequel le moyen (506) de génération de signal aléatoire comprend un circuit de comptage de longueur maximale.

8. Appareil de traitement de signaux d'image selon la revendication 7, dans lequel le moyen (506) de génération de signal aléatoire engendre le signal de sélection (507) sur la base de la génération de nombre aléatoire, dans lequel la génération de nombre aléatoire est déclenchée par une valeur initiale arbitraire, et dans lequel ladite valeur initiale est modifiée périodiquement.

9. Appareil de traitement de signaux d'image selon la revendication 8, comprenant un moyen (502) de génération de valeur initiale pour engendrer une valeur initiale arbitraire en tant que valeur incrémentée périodiquement d'un nombre entier prédéterminé.

10. Appareil de traitement de signaux d'image selon la revendication 9, dans lequel le moyen (502) de génération de valeur initiale exécute l'incrémentation périodique, une fois au cours de chaque ligne de balayage, d'un nombre arbitraire de lignes de balayage successives.

11. Appareil de traitement de signaux d'image selon la revendication 1, dans lequel le moyen (10) de génération de facteurs de répartition comprend un moyen pour engendrer les facteurs de répartition par exécution de façon périodique d'une sélection aléatoire de valeurs respectives relatives aux facteurs de répartition à partir d'un seul ensemble prédéterminé de valeurs de facteurs de répartition.

12. Appareil de traitement de signaux d'image selon la revendication 11, dans lequel le moyen (10) de génération de facteurs de répartition comprend :

un moyen de mémorisation (400) dans lequel est stocké un ensemble de valeurs de facteurs de répartition ;

un moyen (401) de génération de signal de sélection pour engendrer périodiquement un signal de sélection (402) variant de façon aléatoire ; et

un moyen de sélection (403) sensible au signal de sélection pour sélectionner de façon aléatoire des combinaisons des valeurs stockées dans le moyen de mémorisation (400) et pour délivrer à sa sortie les combinaisons sélectionnées de valeurs en tant que facteurs de répartition pour répartir l'erreur de conversion bi-niveau parmi les éléments d'image périphériquement adjacents.