

A GLITCH-FREE CLOCK SIGNAL MULTIPLEXER CIRCUIT AND METHOD OF OPERATION

FIELD

[0001] The disclosed subject matter relates to digital circuitry, such as digital circuitry for digital signal processing, wireless communications and other applications. More particularly, this disclosure relates to a novel and improved glitch-free clock signal multiplexer circuit such as may be useful for many types of digital circuits.

DESCRIPTION OF THE RELATED ART

[0002] The use of code division multiple access (CDMA) techniques in a multiple access communication system is disclosed in U.S. Pat. No. 4,901,307, entitled "SPREAD SPECTRUM MULTIPLE ACCESS COMMUNICATION SYSTEM USING SATELLITE OR TERRESTRIAL REPEATERS," and U.S. Pat. No. 5,103,459, entitled "SYSTEM AND METHOD FOR GENERATING WAVEFORMS IN A CDMA CELLULAR TELEHANDSET SYSTEM," both assigned to the assignee of the claimed subject matter. A CDMA system is typically designed to conform to one or more standards. One such standard is offered by a consortium named the "3rd Generation Partnership Project" (3GPP) and embodied in a set of documents including Document Nos. 3G TS 25.211, 3G TS 25.212, 3G TS 25.213, and 3G TS 25.214, which are readily available to the public. The 3GPP standard is hereinafter referred to as the W-CDMA Standard.

[0003] In a further enhancement, W-CDMA broadband technology, one particular type of chipset for WCDMA handsets is known as the Mobile Station Modem™ (MSM chipset™) line of chipsets. The MSM chipset line of chipsets is offered by the present assignee of the disclosed subject matter and, at least some of such chipsets use 65 nm CMOS technology and interface to RF CMOS single-chip transceiver and multi-band receiver devices, to provide great cost-efficiency. The MSM chipset line of chipsets, for example support EDGE, GPRS and GSM networks, and provide multimedia capabilities integrated into camera and image processing, video streaming, playback, recording and video telephony; streaming and playback of popular audio codecs such as MP3, AAC/aacPlus™ and Enhanced aacPlus; Bluetooth® connectivity; 2D/3D graphics; as well as OMA 2.0-compliant digital rights management

(DRM). Moreover, some MSM chipset provide interoperability between single-chip Radio-on-Chip for Mobile™ (ROCm) solutions, giving them the ability to support 802.11g and 802.11a/g wireless LAN (WLAN) technology.

[0004] MSM chipset and similar chipsets oftentimes use multiple clocks that feed multiple subsystems. These clocks are generally asynchronous to each other, because to operate properly the various subsystems require different clocks at different times. With more and more multi-frequency clocks being used in these and similar chipsets, especially in the communications field, it is often necessary to switch the source of a clock line while the chip is running. This is usually implemented by multiplexing two or more different frequency clock sources in hardware and controlling the multiplexer select line by internal logic. The two clock frequencies could be totally unrelated to each other or they may be multiples of each other. In either case, there is a chance of generating an undesirable glitch on the clock line at the time of the switch. A glitch on the clock line is hazardous to the whole system, as it could be interpreted as a capture clock edge by some registers while missed by others or provide too little time for the computations in programs to finish.

[0005] One approach to address this problem is to provide a circuit for selecting and switching from one to another of a plurality of clock sources having different frequencies without generating runt pulses, electrical glitches, metastable conditions, or other anomalies is described in U.S. Patent No. 4,853,653. In such a solution, a multiple input clock selector is provided for switching asynchronously from one to another of a plurality of oscillators that generate clock signals having different frequencies. The clock selector has a plurality of sections corresponding to the plurality of oscillators. Each section of the clock selector comprises an initial AND gate, a pair of flip-flops, and a final AND gate all connected in series. The oscillator signal for each section is applied to the final AND gate and to the flip-flops as a clock input. An inverted signal from the second flip-flop of each section is fed back as an input to the initial AND gates of all the other sections. An oscillator select signal is also provided as an input to the initial AND gate of each section. The outputs of all final AND gates pass through an OR gate that provides the selected clock output. The clock selector switches between oscillators as determined by the select signals without producing runt pulses, metastable conditions, or other anomalous signals. However, this solution requires that the select

lines remain stable until the switching operation is complete, otherwise the circuit may produce glitches.

[0006] Another approach uses a “phase switch multiplexer.” The phase switch multiplexer, unfortunately, demonstrates the undesirable behavior of compressing some clock phases. It is also subject to metastability. Metastability exists when the storage node of a sequential element goes to a state between an ideal “one” and an ideal “zero.” A metastable state can be interpreted differently by the clock multiplexer and the enable feedback of the other flip flop. Therefore, it is required that capturing edges of both flip flops and the launch edge of the SELECT signal should be set apart from each other to avoid any asynchronous interfacing.

[0007] Accordingly, there is the need for a solution to the problem of switching between clocks in a glitch-free and phase-compression-free manner.

[0008] There is a need for fast switching time and simplicity in clock switching circuits that may be used for mobile system chipsets and similar applications.

[0009] There is a further need for a clock signal switching circuit that provides a low probability of metastability or other anomalies during the switching process.

SUMMARY

[0010] Techniques for providing a novel and improved glitch-free clock signal multiplexer circuit are disclosed, which techniques improve both the operation of a digital signal processing chipsets for increasingly powerful software applications including applications operating in personal computers, personal digital assistants, wireless handsets, and similar electronic devices, as well as increasing the associated digital processing speed, energy use and service quality.

[0011] According to one aspect of the disclosed subject matter, there is provided a method and system that prevent glitches in clock signal switching from a first clock input driving a clock multiplexer circuit to a second clock input driving the clock multiplexer. The method and system provide for receiving a first clock input signal in a clock multiplexer circuit and providing a clock signal output from the clock multiplexer circuit in response to the clock multiplexer circuit receiving the first clock input signal. The disclosed subject matter determines a low phase output level in the clock signal output in response to a low phase input level in the first clock signal output and forces,

for a limited period of time, the clock multiplexer circuit to maintain the low phase output level irrespective of the phase level of the first clock input signal. The clock multiplexer circuit also receives a second clock input signal and determines the presence of a low phase input level in the second clock input signal. Switching from providing the clock signal output in response to the first clock input signal to providing the clock signal output in response to the second clock input signal occurs while maintaining the low phase output level and during the low phase input level in the second clock input signal. Then, method and system allow the output of the clock multiplexer circuit to follow the phase level of the second clock signal input after the switching step.

[0012] These and other advantages of the disclosed subject matter, as well as additional novel features, will be apparent from the description provided herein. The intent of this summary is not to be a comprehensive description of the claimed subject matter, but rather to provide a short overview of some of the subject matter's functionality. Other systems, methods, features and advantages here provided will become apparent to one with skill in the art upon examination of the following **FIGURES** and detailed description. It is intended that all such additional systems, methods, features and advantages be included within this description, be within the scope of the accompanying claims.

BRIEF DESCRIPTIONS OF THE DRAWINGS

[0013] The features, nature, and advantages of the disclosed subject matter will become more apparent from the detailed description set forth below when taken in conjunction with the drawings in which like reference characters identify correspondingly throughout and wherein:

[0014] **FIGURE 1** is a simplified block diagram of a mobile station modem system that may implement the disclosed subject matter;

[0015] **FIGURE 2** demonstrates the concept of clock circuit glitch as addressed by the disclosed subject matter;

[0016] **FIGURE 3** illustrates aspects of a clock control pipeline relevant to the present disclosure; and

[0017] **FIGURE 4** illustrates aspects of a phase path as appropriate for the present disclosure;

[0018] **FIGURES 5 and 6** shows a clock switching circuit embodying aspects of the disclosed subject matter;

[0019] **FIGURE 7** provides a functional flow chart depicting specific steps of the present disclosure; and

[0020] **FIGURE 8** is a flow chart for the metastability correction aspects of the disclosed subject matter.

DETAILED DESCRIPTION OF THE SPECIFIC EMBODIMENTS

[0021] The disclosed subject matter for a novel and improved glitch-free clock signal multiplexer circuit may find use for signal processing applications of any type for which the benefits here presented may be advantageous. One such application appears in telecommunications and, in particular, in wireless handsets that employ one or more digital signal processing circuits.

[0022] **FIGURE 1** is a simplified block diagram of a mobile station modem (MSM) chipset **10** that may implement the disclosed subject matter. Understand, however, that the presently disclosed subject matter may be applied to many different types of chipsets operating in many different environments. The presentation here made, therefore, provides a demonstration of one such use. In particular, **FIGURE 1** shows MSM chipset **10** in which the presently disclosed subject matter may find advantageous application. MSM chipset **10** includes connectivity applications **12**, such as keypad interface **14**, SD/SDIO application **16**, USB OTG connection **18**, and universal asynchronous receive and transmit (UART) devices such as UART1 **20**, UART2/receive unit interface modem (RU IM1) **22**, and UART3/RU IM2) **24**. Video input to MSM chipset **10** may come through CMOS CCD camera input **26** to camera processing circuitry **28** and MODI client **30**, while audio interfaces include handset speaker **32**, stereo headset **34**, microphone **36**, and stereo input **38** for interfacing audio circuitry **40**. Audio circuitry **40** may be capable of supporting applications such as MP3, AAC/aacPlus functions, EVRC, QCELP, EVRC, QCELP, AMR, CMX, and MIDI applications.

[0023] In the MSM chipset **10** example of **FIGURE 1**, dual memory busses **42** interface various memory and related functional circuits. These may include EB1 **44** for interfacing memory devices such as SDRAM **46**, Burst P SRAM **48**, and Burst NOR **50**,

and EB2 52 for interfacing LCD 54, NAND 56, and other devices 58. Also, MDDI (mobile display digital interface) Host 60 may provide an interface with LCD 54. MSM chipset 10 may also include graphics circuitry 62 for supporting OpenGL[®] ES, 3D, and 2D functions and video circuitry 64 for supporting MPEG-4, H.263 and H.264 functions. In addition, processing functions, such as those of CDMA processor 66, GSM/GPRS processor 68, gpsOne processor 70, and BT 1.2 processor 72 may be included in MSM chipset 10. Providing signal conversion processes and the like, MSM chipset 10 may include serial bus interface (SBI) 74, receive A/D converter (Rx ADC) 76, and transmit D/A converter (Tx DAC) 78.

[0024] MSM chipset 10 may further include various chipset processors, such as Qualcomm Inc.'s QDSP 4000 processor 80, Arm, Inc.'s ARM 926EJS processor 82, and Qualcomm, Inc.'s Modem QDSP 4000 86, as well as one or more phase lock loop (PLL) circuits 86. PLLs 86 assist with the generation of a clock signal. Essentially any portion of MSM chipset 10 that needs a clock signal for digital circuit operation may draw upon PLLs 86 for such clock signals. In addition, there may be many PLLs 86, e.g., six or more, operating in different embodiments of MSM chipset 10.

[0025] At times it is possible to have one PLL 86 provide a clock to two or more portions of MSM chipset 10. This is advantageous from a power use standpoint in that the same PLL 86 may provide a clock signal to two or more portions of MSM chipset 10, e.g., to CDMA processor 66, GSM/GPRS processor 68, and gpsOne processor 70. With PLLs 86 providing multi-frequency clocks to the various components of MSM chipset 10, it is often necessary to switch the source of a clock line while the respective component is running. Control of which PLL 86 may provide the desired clock signal is the focus of the present disclosure, with one embodiment appearing below in **FIGURES 5 through 8.**

[0026] The disclosed subject matter provides for multiplexing two different frequency clock sources in hardware and controlling the multiplexer select line by internal logic. The two clock frequencies could be totally unrelated to each other, may have some arbitrary relationship to one another, or they may be multiples of each other. In either case, the present disclosure avoids generating a glitch on the clock line at the time of the switch. A glitch on the clock line is hazardous to all of MSM chipset 10, as

it could be interpreted as a capture clock edge by some registers while missed by others or provide too little time for the computations in programs to finish.

[0027] **FIGURE 2** illustrates more specifically what is here to be understood as “glitch” within a clock circuit. The **clk** signal **90** depicts the presence of glitch **106** in switching from **clka** signal **92** to **clkb** signal **94**. A clock signal multiplexer may respond to a select signal (at the time indicated by line **96**) for switching from **clka** to **clkb** signal **94** less than a complete **clka** phase duration **98** after **clka** rising edge **100** and before for a **clkb** falling edge **102** of **clkb** phase duration **104**. In such instance, **clk** signal **90** demonstrates a glitch **106** where the high phase of the output clock is compressed. Such a condition may, for example, adversely affect the entire operation of MSM chipset **10**.

[0028] In contrast, a multiplexer designed specifically for multiplexing clock signals. The select lines are allowed to switch asynchronously. The clock circuit ensures that output clock **90** never glitches (i.e., its high or low phase does not get compressed). The disclosed subject matter provides such a clock switching circuit.

[0029] Setup and hold time violations can lead to metastability, which may exist for an undetermined amount of time. Theoretically, therefore, the time required to resolve the state of the latch may then be infinite. There will always be points in the continuous domain which are equidistant (or nearly so) from the points of the discrete domain, making a decision as to which discrete point to select a difficult and potentially lengthy process. If the inputs to an arbiter or flip-flop arrive almost simultaneously, the circuit most likely will traverse a point of metastability. The disclosed subject matter, as will be shown below, addresses this problem in providing the desired glitch-free clock signal switching.

[0030] In **FIGURE 3**, **clka** line **112** provides **clka** signal **92** into clock control pipeline (CCP) **114**. CCP **114** may be one of a number of CCPs that control inputs into multiplexer circuit **116**. That is, **clka** signal **112** is one of, for example five (5) possible clock signal inputs from which multiplexer circuit **116** may generate output clock signal **118**.

[0031] **FIGURE 4** shows aspects of clock signal timing applicable to CCP **114** for demonstrating graphically the problem of glitch in a digital circuit. The CCP **114** critical timing path appears as switching examples **120** and **122**. In phase path **120**,

falling edge **124** of multiplexer select (active low) signal **126** must be stable before rising edge **128** of **clka** clock signal **92** to allow its undistorted propagation through multiplexer **116**. A late falling edge **124** will chop the high-phase of the **clka** clock signal **92**. Likewise, rising edge **130** of multiplexer select **132** must also be stable before rising edge **134** of **clka** clock signal **92** to prevent a glitch at **clk** output **118** of multiplexer **116**.

[0032] **FIGURE 5** illustrates clock switching circuit **150** in which the present disclosure may be advantageously employed. Clock switching circuit **150** includes decoder circuitry **152** for receiving init, **req1**, **req0**, and halt inputs. Select control signals are fed to clock control pipeline **154** for the **clka** signal, clock control pipeline **156** for the **clkb** signal, clock control pipeline **158** for the **clkc** signal, and clock control pipeline **160** for the **clkd** signal. The 5-to-1 multiplexer circuit **162** receives clock signals, **clka**, **clkb**, **clkc**, **clkd**, and **clkt** (test clock). In addition and of particular importance to the disclosed subject matter, clock switching circuit **150** provides locking circuitry **164** for locking the internal request lines **reqa**, **reqb**, **reqc**, **reqd** and, thereby, preventing glitch.

[0033] Locking circuitry **164** further includes early select lines **166** and late select lines **168**. **FIGURE 6**, shows with more specificity one embodiment of the inputs for the clock control pipelines **154** through **160** that may be employed to achieve the objects of the present disclosure.

[0034] Clock switching circuit **150** provides control logic for switching from one clock to another that includes waiting for a low phase level of the current clock. When no selects into multiplexer circuitry **162** are active, the output is low. Clock switching circuit **150** forces the output of multiplexer circuitry **162** low and waits for the low phase of the new clock signal. Then, clock circuitry **150** allows multiplexer circuitry **162** to follow the high and low phase levels of the new clock.

[0035] In clock switching circuit **150**, select lines (**sela**, **selb**, **selc**, and **seld**) may switch asynchronously to **clka**, **clkb**, **clkc**, and **clkd**, while fully avoiding output clock glitches. The disclosed embodiment of clock switching circuit **150** supports four (4) CCPs including pipelines **154** through **160**. Clock switching circuit **150** merges logic of CCP **114** with that of a multiplexer **162** to reduce the number of stages in the PLL clock path. A technical advantage of the disclosed embodiment is significant

improvement in both jitter and duty cycle distortion. In addition, clock switching circuit **150** allows the CCP logic to be disabled when not needed. Additional technical advantages of the disclosed subject matter include clock switching support for a 1.0-GHz clock in one embodiment. The present disclosure demonstrates a low probability of metastability, low jitter, low duty cycle distortion, low power and energy requirements, low area requirements and low skew.

[0036] **FIGURE 7** provides a functional flow chart **170** depicting specific steps of the present disclosure, as may be performed by clock switching circuit **150**. In further explaining a switching process between clocks, consider clocking switching circuit **150** to be in steady state when the clock currently selected is consistent with the external request lines **req1** and **req0** (step **172**). That is, assume that clock switching circuit **150** is in steady state with **clka** selected (step **174**). The external request lines are not blocked from propagating through the decoder. Then, **req0** may rise and **clkb** is then requested (step **176**). The event propagates through decoder circuitry **152**, forcing **reqa** low and **reqb** high (step **178**). Then, **reqa** injects a zero in the pipeline controlling **sela** **154** (step **180**). However, **reqb** has no immediate effect. In operation, **reqb** is not yet allowed to enter the pipeline controlling **clkb**, since **sela** is still high (step **182**).

[0037] Some time later, **req1** may switch (step **184**). Then, **reqd** now goes high and replaces **reqb**, still with no immediate effect on the multiplexer **162** output clock signal (step **186**). At some point, the early select for **clka** will fall. This will lock the internal request lines feeding pipelines **152** through **160** (step **188**). Then, decoder circuitry **152** may become metastable. Within one clock cycle, the disclosed circuit substantially reduces the probability that metastability occurs (step **190**). After one cycle, **sela** will fall as well, allowing **reqd** to inject a one into the pipeline controlling **clkd** **160** (step **192**). Eventually, **seld** will go high, which will unlock the internal request lines and place clock switching circuit **150** back in steady state (step **194**).

[0038] As flowchart **200** of **FIGURE 8** details, clock switching circuit **150** also effectively addresses decoder circuitry **152** metastability. Beginning at step **202**, assume that clock switching circuit **150** is in steady state with **clka** selected (step **202**). The external request lines are not blocked from propagating through the decoder. Assume that **req0** rises and that **clkb** is now being requested (step **204**). The event propagates through decoder circuitry **152**, forcing **reqa** low and **reqb** high (step **206**). Then, **reqa**

injects a zero in the pipeline controlling **sela 154** (step **208**). At some point, the early select circuitry **166** for **clka** will fall. This will lock the internal request lines feeding pipelines **152** through **160** (step **210**). Decoder circuitry **152** may become metastable, if **req0** falls at the same time (step **212**). Metastability on **reqa** can be tolerated because the next sampling event for it will occur only one clock cycle later (step **214**).

Metastability on **reqb**, **reqc**, and **reqd** can also be tolerated since **sela**, the late select for **clka**, will remain high for another cycle (step **216**).

[0039] In the disclosed embodiment, a test mode of operation may also be provided for selecting the test clock. Selecting the test clock, **clkt**, bypasses the functional clock normally produced by 5-to-1 multiplexer circuitry **162**. Selecting the **clkt** does not impact the state of clock switching circuit **150** in controlling the operation of multiplexer circuitry **162**. Selecting the **clkt** does not impact clock switching circuit **150**. The test clock select line overrides clock switching circuit **150**.

[0040] In summary, the present disclosure provides a method and system that prevent glitches in clock signal switching from a first clock input driving a clock multiplexer circuit to a second clock input driving the clock multiplexer. The method and system provide for receiving a first clock input signal in a clock multiplexer circuit and providing a clock signal output from the clock multiplexer circuit in response to the clock multiplexer circuit receiving the first clock input signal. The disclosed subject matter determines a low phase output level in the clock signal output in response to a low phase input level in the first clock signal output and forces, for a limited period of time, the clock multiplexer circuit to maintain the low phase output level irrespective of the phase level of the first clock input signal. The clock multiplexer circuit also receives a second clock input signal and determines the presence of a low phase input level in the second clock input signal. Switching from providing the clock signal output in response to the first clock input signal to providing the clock signal output in response to the second clock input signal occurs while maintaining the low phase output level and during the low phase input level in the second clock input signal. Then, method and system allow the output of the clock multiplexer circuit to follow the phase level of the second clock signal input after the switching step.

[0041] The processing features and functions described herein for reducing glitch in switching from a first clock signal input driving a clock multiplexer circuit to a

second clock input driving said clock multiplexer circuit may be implemented in various manners. Moreover, the process and features here described may be stored in magnetic, optical, or other recording media for reading and execution by such various signal and instruction processing systems. The foregoing description of the preferred embodiments, therefore, is provided to enable any person skilled in the art to make or use the claimed subject matter. Various modifications to these embodiments will be readily apparent to those skilled in the art, for example, one further embodiment may include an N-to-1 version of the circuit, and the generic principles defined herein may be applied to other embodiments without the use of the innovative faculty. Thus, the claimed subject matter is not intended to be limited to the embodiments shown herein but is to be accorded the widest scope consistent with the principles and novel features disclosed herein.

CLAIMS**WHAT IS CLAIMED IS:**

1. A method for reducing glitch in switching from a first clock signal input driving a clock multiplexer circuit to a second clock input driving said clock multiplexer circuit, comprising the steps of:

receiving a first clock input signal in a clock multiplexer circuit;

providing a clock signal output from said clock multiplexer circuit in response to said clock multiplexer circuit receiving said first clock input signal;

determining a low phase output level in said clock signal output in response to a low phase input level in said first clock signal output;

locking said clock multiplexer circuit to maintain said low phase output level irrespective of the phase level of said first clock input signal;

receiving a second clock input signal in said clock multiplexer circuit;

determining the presence of a low phase input level in said second clock input signal;

switching from providing said clock signal output in response to said first clock input signal to providing said clock signal output in response to said second clock input signal while maintaining said low phase output level and during said low phase input level in said second clock input signal; and

allowing said output of said clock multiplexer circuit to follow the phase level of said second clock signal input after said switching step.

2. The method of Claim 1, further comprising the step of eliminating a metastable condition arising associated said switching step within approximately one clock cycle.

3. The method of Claim 1, further comprising the step of performing said locking step as an early stage locking step for a first part of said locking step and a later stage locking step for a later part of said locking step.

4. The method of Claim 1, further comprising the step of testing the operation of said clock multiplexer circuit using circuitry at least of portion of which operates independently of said first clock signal input and said second clock signal input.

5. The method of Claim 1, further comprising the step of associating said first clock signal input with said clock multiplexer circuit using a first clock control pipeline and said second clock signal input with said clock multiplexer circuit using a second clock control pipeline.

6. The method of Claim 5, further comprising the step of associating a decoder circuit with said first clock control pipeline and said second clock control pipeline.

7. The method of Claim 1, further comprising the steps of deriving said first clock signal input from a first phase locked loop circuit and said second clock signal input from a second phase locked loop circuit.

8. The method of Claim 1, further comprising the step of associating output of said clock multiplexer circuit with a plurality of digital signal processing circuits.

9. The method of Claim 1, further comprising the steps of associating said output of said clock multiplexer circuit with a mobile station modem chipset.

10. A glitch reducing clock switching circuit for reducing glitch in switching from a first clock signal input driving a clock multiplexer circuit to a second clock input driving said clock multiplexer circuit, comprising:

a clock multiplexer circuit for receiving a first clock input signal in;

a clock multiplexer circuit output for providing a clock signal output from said clock multiplexer circuit in response to said clock multiplexer circuit receiving said first clock input signal;

clock output level determining circuitry for determining a low phase output level in said clock signal output in response to a low phase input level in said first clock signal output;

locking circuitry for locking said clock multiplexer circuit to maintain said low phase output level irrespective of the phase level of said first clock input signal;

clock multiplexer input circuitry for receiving a second clock input signal in said clock multiplexer circuit;

low phase input level determining circuitry for determining the presence of a low phase input level in said second clock input signal;

switching circuitry for switching from providing said clock signal output in response to said first clock input signal to providing said clock signal output in response to said second clock input signal while maintaining said low phase output level and during said low phase input level in said second clock input signal; and

clock multiplexer circuit output circuitry for allowing said output of said clock multiplexer circuit to follow the phase level of said second clock signal input after said switching step.

11. The system of Claim **10**, wherein said glitch reducing clock switching circuitry further comprises circuitry and instructions for eliminating a metastable condition arising associated said switching step within approximately one clock cycle.

12. The system of Claim **10**, wherein said glitch reducing clock switching circuitry further comprises circuitry and instructions for performing said locking step as an early stage locking step for a first part of said locking step and a later stage locking step for a later part of said locking step.

13. The system of Claim **10**, wherein said glitch reducing clock switching circuitry further comprises circuitry and instructions for testing the operation of said clock multiplexer circuit using circuitry at least of portion of which operates independently of said first clock signal input and said second clock signal input.

14. The system of Claim **10**, wherein said glitch reducing clock switching circuitry further comprises circuitry and instructions for associating said first clock signal input with said clock multiplexer circuit using a first clock control pipeline and said second clock signal input with said clock multiplexer circuit using a second clock control pipeline.

15. The system of Claim **10**, wherein said glitch reducing clock switching circuitry further comprises a decoder circuit for associating with said first clock control pipeline and said second clock control pipeline.

16. The system of Claim **10**, wherein said glitch reducing clock switching circuitry further comprises circuitry and instructions for deriving said first clock signal input from a first phase locked loop circuit and said second clock signal input from a second phase locked loop circuit.

17. The system of Claim **10**, wherein said glitch reducing clock switching circuitry further comprises circuitry and instructions for associating output of said clock multiplexer circuit with a plurality of digital signal processing circuits.

18. The system of Claim **10**, wherein said glitch reducing clock switching circuitry further comprises circuitry and instructions for associating said output of said clock multiplexer circuit with a mobile station modem chipset.

19. A mobile station modem for operation in support of a personal electronics device, said digital signal process comprising means for reducing glitch in switching from a first clock signal input driving a clock multiplexer circuit to a second clock input driving said clock multiplexer circuit, comprising the steps of:

receiving means for receiving a first clock input signal in a clock multiplexer circuit;

means for providing a clock signal output from said clock multiplexer circuit in response to said clock multiplexer circuit receiving said first clock input signal;

means for determining a low phase output level in said clock signal output in response to a low phase input level in said first clock signal output;

means for forcing said clock multiplexer circuit to maintain said low phase output level irrespective of the phase level of said first clock input signal;

means for receiving a second clock input signal in said clock multiplexer circuit;

means for determining the presence of a low phase input level in said second clock input signal;

switching means for switching from providing said clock signal output in response to said first clock input signal to providing said clock signal output in response to said second clock input signal while maintaining said low phase output level and during said low phase input level in said second clock input signal; and

means for allowing said output of said clock multiplexer circuit to follow the phase level of said second clock signal input after operation of said switching means.

20. The mobile station modem of Claim **19**, further comprising means for eliminating a metastable condition arising associated said switching step within approximately one clock cycle.

21. The mobile station modem of Claim **19**, further comprising means for performing said locking step as an early stage locking step for a first part of said locking step and a later stage locking step for a later part of said locking step.

22. The mobile station modem of Claim **19**, further comprising means for testing the operation of said clock multiplexer circuit using circuitry at least of portion of which operates independently of said first clock signal input and said second clock signal input.

23. The mobile station modem of Claim **19**, further comprising means for associating said first clock signal input with said clock multiplexer circuit using a first clock control pipeline and said second clock signal input with said clock multiplexer circuit using a second clock control pipeline.

24. The mobile station modem of Claim 19, further comprising means for associating a decoder circuit with said first clock control pipeline and said second clock control pipeline.

25. The mobile station modem of Claim 19, further comprising means for deriving said first clock signal input from a first phase locked loop circuit and said second clock signal input from a second phase locked loop circuit.

26. The mobile station modem of Claim 19, further comprising means for associating output of said clock multiplexer circuit with a plurality of digital signal processing circuits.

27. The mobile station modem of Claim 19, further comprising means for associating said output of said clock multiplexer circuit with a personal electronics device.

28. A computer usable medium having computer readable program code means embodied therein for processing instructions on the digital signal processor for reducing glitch in switching from a first clock signal input driving a clock multiplexer circuit to a second clock input driving said clock multiplexer circuit, comprising:

computer readable program code means for receiving a first clock input signal in a clock multiplexer circuit;

computer readable program code means for providing a clock signal output from said clock multiplexer circuit in response to said clock multiplexer circuit receiving said first clock input signal;

computer readable program code means for determining a low phase output level in said clock signal output in response to a low phase input level in said first clock signal output;

computer readable program code means for forcing said clock multiplexer circuit to maintain said low phase output level irrespective of the phase level of said first clock input signal;

computer readable program code means for receiving a second clock input signal in said clock multiplexer circuit;

computer readable program code means for determining the presence of a low phase input level in said second clock input signal;

computer readable program code means for switching from providing said clock signal output in response to said first clock input signal to providing said clock signal output in response to said second clock input signal while maintaining said low phase output level and during said low phase input level in said second clock input signal; and

computer readable program code means for allowing said output of said clock multiplexer circuit to follow the phase level of said second clock signal input after said switching step.

29. The computer usable medium of Claim **28**, further comprising computer readable program code means for associating output of said clock multiplexer circuit with a plurality of digital signal processing circuits.

30. The computer usable medium of Claim **28**, further comprising computer readable program code means for associating said output of said clock multiplexer circuit with a mobile station modem chipset.