

DOUBLE TUNED CIRCUIT WITH BALANCED OUTPUT  
AND IMAGE TRAP

BACKGROUND

5           The present invention concerns RF tuning circuits for a television receiver, and more particularly a double tuned circuit with a balanced output having an image trap.

          It is sometimes desirable to process RF signals in a balanced circuit configuration. In particular, a tuner integrated circuit (IC), the  
10   CXA1594L of the Sony Corporation, is designed for a balanced input signal to the UHF mixer. The data sheet for this IC shows the deriving of a balanced signal from a balun transformer. Balun transformers have the disadvantage of being larger and more expensive than RF transformers.

15           Additionally, it is often desirable that certain traps or filters be included in RF tuning circuits in order to prevent unwanted harmonics, beat frequencies, and images which are produced by extraneous signals and can have a detrimental effect on the processing of the desired signal. Some such traps are for a strong channel 7 signal  
20   which can interfere with a channel 6 signal, a 27 MHz trap against strong citizens band transmitters in the United States, and a trap for 890 MHz image signals produced by the transmissions of cellular telephones in the United States. It is herein recognized that when a trap or other filter is used to prevent detrimental effects of such  
25   extraneous signals in a balanced circuit, that it is necessary that such traps be used on both sides of the balanced configuration.

SUMMARY OF THE INVENTION

          Briefly, the present invention concerns circuitry for the  
30   conversion of an RF signal amplifier from an unbalanced signal configuration to a balanced signal configuration and including an image trap for both sides of the balanced circuit. The grounded side of the secondary of a double tuned circuit is lifted from ground to provide a balanced circuit configuration. A trap filter is provided in the  
35   balanced circuit configuration by a pair of small capacitors coupled between the balanced secondary leads to appropriate signal nodes.





### BRIEF DESCRIPTION OF THE DRAWINGS

Reference may be had to the drawings wherein like members are designated with like numerals, and wherein:

Figure 1 shows a schematic of a prior art RF amplifier of an RF section including an image trap.

Figure 2 is an graph of the amplitude vs frequency characteristic of the image trap of Figure 1.

Figure 3 shows a schematic of an RF amplifier according to aspects of the present invention.

### DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

Referring now to FIGURE 1, there is shown a portion of an exemplary tuner for a television set, FM radio receiver, or the like. For an exemplary range of frequencies, e.g., including the VHF and UHF bands, the RF input signal is derived from an antenna (not shown) or other source. The signal from the source is coupled to an RF amplifier 12, which in the exemplary embodiment is a dual gate FET amplifier. The output of amplifier 12 is fed through a coupling capacitor 13 to a double tuned transformer 14 having a primary coil 16 tuned with a primary capacitor, e.g., a varactor diode 18 in series with a trimmer capacitor 19, and a secondary coil 20 tuned by a secondary capacitor, e.g., a varactor diode 22 in series with a trimmer capacitor 23. Tuning is accomplished by application of a tuning voltage TV to varactor diodes 18 and 20 through respective resistors 21 and 25, thus changing the capacitance of varactor diodes 18, 22 in a manner well known in the art. The changing of the capacitance of varactor diodes 18, 22, responsive to tuning voltage TV, provides for the tuning selection of a desired channel from the plurality of channels of the RF input signal. Mutual magnetic coupling is provided between primary coil 16 and secondary coil 20. Coils 16 and 20 provide the DC return for respective varactor diodes 18, 22.

The configuration of transformer 14 is commonly called a doubly tuned circuit with one lead 16a, 20a, of respective coils 16 and 20 being coupled to a voltage reference (ground). The unbalanced output from transformer 14, is fed through impedance matching circuit 24 and provides an unbalanced signal for further signal processing (not shown), e.g., a SAW filter, video luminance, chrominance, and synchronization processing, as well as sound processing. In the exemplary embodiment, the a portion of further RF processing circuitry

is provided by the CXA13551 integrated circuit, i.e., mixing and IF amplification.


5 Still referring to Figure 1, a capacitor Cs is coupled from output signal node 27 at secondary coil 20 to input node 28 at primary coil 16. Cs is a fraction of a picofarad, e.g., in the exemplary embodiment 0.15 pf, and is can be provided as a capacitor formed by copper conductors on a printed circuit board. Capacitor Cs operates in combination with the mutual inductance of transformer 14 to provide attenuation at an image notch frequency at output terminal 26, which  
10 in the exemplary embodiment is an image frequency of 890 MHz for cellular telephones in the United States. This frequency characteristic is shown in Figure 2.

Figure 2 shows the amplitude-frequency characteristic of double tuned circuit 14 having a center tuned pass band of frequencies  
15 with the upper skirt being modified to give an attenuation notch the a frequency to be rejected which is distal from the center of the pass band of frequencies.

The CXA1594L IC requires a balanced signal and balanced impedance at the signal input terminals of the UHF mixer. To  
20 accommodate these requirements, changes to the circuit of Figure 1 are shown in Figure 3, according to aspects of the present invention. Like members of Figure 3 corresponding to members of Figure 1 have been designated with like numerals.

For providing a balanced output, lead 20a of Figure 1 has  
25 been decoupled from the reference potential (ground) and is coupled to a terminal 26b through coupling capacitor 30b. Output lead 26 remains coupled to terminal 26a through coupling capacitor 30a. Thus, the output voltage at terminals 26a and 26b is balanced with respect to ground and terminals 26a and 26b have balanced impedances with respect to ground. Since the DC return for varactor diode 22 has been  
30 lifted from ground, a relatively high DC return resistor 32 is provided.

For the balanced circuit, capacitor Cs is divided into Cs1 and Cs2. In operation, capacitors Cs1 and Cs2 are in series. Thus, the values of each of the capacitors Cs1 and Cs2 must be doubled in value to equal  
35 the original value of capacitor Cs to keep the same notch frequency. In practice, the values of Cs, Cs1, and Cs2 are much smaller in value than varactor diodes 18, 20.





## Claims:

1. In a television receiver, tuning apparatus, comprising:  
means (12) for amplifying an RF signal and having an  
output coupled to a signal node with respect to a reference potential,  
5 a first tuned circuit (14,16,18) including a first varactor  
diode (18) responsive to a tuning voltage and a first inductance  
element (14,16) coupled from the signal node to a point of reference  
potential for selecting one of said amplified RF signals in response to  
a tuning voltage,  
10 a second tuned circuit (14,20,22) including a second  
varactor diode (22) responsive to a tuning voltage and a second  
inductance element (14,20) for further selecting said one of said  
amplified RF signals in response to the tuning voltage,  
said first and second tuned circuits (14,16,18,20,22)  
15 forming a double tuned circuit, said first and second inductance  
elements (16,18) being inductively coupled,  
the second inductance element (20) having a pair of  
output terminals balanced with respect to the reference potential,  
a first trap capacitor (CS1) coupled between one output  
20 terminal of the second inductance element (20) and the signal node,  
and characterized by  
a second trap capacitor (CS2) coupled between the other  
output terminal of the second inductance element (20) and the  
reference potential,  
25 the first and second trap capacitors (CS1,CS2) providing a  
notch frequency for the tuned RF signal at each of a pair of output  
terminals (26a,26b).
2. The tuning apparatus of claim 1 characterized in that  
30 each of the first and second trap capacitors (CS1,CS2) are smaller  
than the capacitance of the first and second varactor diodes (18,22).
3. The tuning apparatus of claim 2 characterized in that  
each of the first and second trap capacitors (CS1,CS2) are formed by  
35 conductors etched into a printed circuit board.

