

DESCRIPTION

TITLE OF THE INVENTION:

PERIODIC EXTERNAL DISTURBANCE SUPPRESSION CONTROL DEVICE

5

TECHNICAL FIELD

[0001] The present invention relates to suppression of periodic disturbance with a periodic disturbance observer with learning function, and more specifically to periodic disturbance suppression control realizing a stable control system even in case of large condition change in an actual system or real system.

10

BACKGROUND ART

[0002] Recently, the utilization of dispersed power system with smart grid, microgrid and new energy such as solar power and wind power is gathering attention, and further spread and expansion are expected. With this trend, the number of loads generating harmonics and the number of interconnected units of semiconductor power conversion systems are increasing, and hence there is concern over harmonics problem in the power distribution system. Since harmonics exert adverse influence on other interconnected devices, the harmonics are controlled and stipulated by harmonic guidelines etc. and various measures are taken to harmonics interference problem by using power active filters or other means.

15

20

[0003] However, conventional measures and methods might become insufficient from the viewpoint of harmonics compensation effect and control stability because the interconnection of many unspecified dispersed power sources everywhere could cause various problems such as increase of accumulated harmonics, complication of sources of harmonics, fluctuation of system impedance and load impedance with change in the construction of the distribution system,

25

30

changeover of a phase advancing capacitor, and operating condition, and variation of system resonance characteristics.

[0004] As to the application and operation of active filters, adjusting operations are required to adjust control parameters on the spot and, moreover, operations are required for readjustment in case of change in the operating situation.

[0005] Based on the above-mentioned background, Patent Document 1 discloses a technique expanding a generalized periodic disturbance compensating method using the complex vector notation, proposed by the inventor of the present application et al., and correcting, by learning, the reciprocal of the transfer characteristic of the observer real system from information on complex vector loci of the periodic disturbance. The technique of Patent Document 1 is configured to extract a harmonic frequency component of each order in a power system active filter control system for controlling a system current as the object of control, automatically learning a frequency transfer function (taking account of dead times of sensors and control calculations and impedance characteristics collectively) from the harmonic suppressing command of each order to the sensed harmonic, and estimating and suppressing the current including the periodic disturbance in the form of harmonic. With this technique, it is possible to construct a robust power active filter control system eliminating the need for preparatory system identification.

Prior Art Documents

25 Patent Document

[0006] Patent Document 1: JP2012-55148A

SUMMARY OF THE INVENTION

[0007] The technique of correcting the reciprocal Q_n of the transfer characteristic in Patent Document 1 enables a correction (learning correction) to correct the model (parameter) error of the periodic

disturbance observer, in a manner following condition change of the real system. However, this technique does not take divergence condition of harmonic and stagnation of harmonic change into consideration. Therefore, when the condition change of the real system is great, the stability and convergence become problematical outside the range of the robust stability condition from the relationship (FIG. 16) of the amplitude error A_n and phase error ϕ_n of the inverse model Q^n . Moreover, as expressed by the expression (10), in the range of amplitude error $A_n < 1$, the response of the learning correction becomes problematical in dependence on the characteristic of amplitude error A_n .

[0008] Therefore, a task is to correct an inverse model of a transfer characteristic of a real system successively during estimation even in case of large condition change in the real system in a periodic disturbance suppressing control apparatus and thereby to realize a stable control system.

[0009] The present invention has been devised in view of the above-mentioned problem. According to one aspect of the present invention, a periodic disturbance suppressing control apparatus comprises: a periodic disturbance sensing section to sense a periodic disturbance of a controlled object as a sensed periodic disturbance in a form of a direct current component; a periodic disturbance estimating section to estimate the periodic disturbance by determining a difference between a signal obtained by multiplication of the sensed periodic disturbance with a multiplier using a reciprocal of a transfer characteristic from a periodic disturbance suppressing command to the sensed periodic disturbance, determined according to a transfer characteristic of a control system, and a signal obtained by adding only a detection delay to the periodic disturbance suppressing command; an adder to calculate the periodic disturbance suppressing

command by calculating a deviation between an estimated periodic disturbance estimated by the periodic disturbance estimating section and a periodic disturbance command to suppress a disturbance; and a learning control section to correct the reciprocal of the transfer

5 characteristic in accordance with a quantity obtained by dividing a difference of the periodic disturbance suppressing command during one sample interval by a difference of the sensed periodic disturbance during the one sample interval.

[0010] According to another aspect, the periodic disturbance
10 suppressing apparatus is arranged to suppress the periodic disturbance by superposing the periodic disturbance suppressing command on a command of a power conversion device connected with a system bus of a power source.

[0011] According to still another aspect, the learning control section
15 is configured to use average or mean values during an interval of a control period of a periodic disturbance observer, as the sensed periodic disturbance and the period disturbance suppressing command.

[0012] According to still another aspect, the learning control section is configured to stop a learning control and output the reciprocal of the
20 transfer characteristic just before stoppage when the difference during a one sample interval in an average value of the sensed periodic disturbance is lower than or equal to a threshold value.

[0013] Furthermore, the learning control section may be arranged to deliver an output through a filter.

25 [0014] Furthermore, the control apparatus may further comprise a limiter to limit an amplitude of the periodic disturbance suppressing command.

[0015] Furthermore, a plurality of the periodic disturbance control
30 apparatus may be arranged in parallel to suppress periodic disturbance of a plurality of orders.

[0016] According to the present invention, in the periodic disturbance suppressing control apparatus, it is possible to correct the inverse model of the transfer characteristic of the real system successively during estimation even in case of large condition change in the real system in the periodic disturbance suppressing control apparatus and thereby to realize a stable control system.

BRIEF EXPLANATION OF THE DRAWINGS

[0017] FIG. 1 is a control block diagram showing a periodic disturbance observer to harmonic of an n-th order frequency component according to a first embodiment.

FIG. 2 is a block diagram showing a learning control section according to the first embodiment.

FIG. 3 is a control block diagram showing a periodic disturbance observer to harmonic of an n-th order frequency component according to a second embodiment.

FIG. 4 is a block diagram showing a learning control section according to the second embodiment.

FIG. 5 is a block diagram showing a learning control section according to a third embodiment.

FIG. 6 is a block diagram showing a learning control section according to a fourth embodiment.

FIG. 7 is a view showing a periodic disturbance suppression control apparatus according to a fifth embodiment.

FIG. 8 is a control block diagram showing a periodic disturbance observer to harmonic of an n-th order frequency component according to a sixth embodiment.

FIG. 9 is a block diagram showing a limiter in the sixth embodiment.

FIG. 10 is a view showing a periodic disturbance suppressing control apparatus according to a seventh embodiment.

FIG. 11 is a concept view showing one example of a power distribution system.

FIG. 12 is a circuit diagram showing a control model of a source current detecting type shunt active filter.

5 FIG. 13 is a basic block diagram of an active filter control system.

FIG. 14 is a control block diagram showing a periodic disturbance observer to a harmonic of n-th order frequency component.

10 FIG. 15 is a diagram showing a control system of the periodic disturbance observer, focusing only on the n-th order frequency component of the $d_n q_n$ coordinates.

FIG. 16 is a graphic view showing stability boundary condition of model error.

[0018] FIG. 11 is a conceptual view showing an existing typical power distribution system. A power distribution network is arranged to supply power from a system power supply 1 to demanders or users Feeder1, Feeder2, ... and FeederX. In this power distribution network, there is provided a shunt active filter AF of a source current detection type, at a power receiving point of the demander Feeder2 who is a large demander in the figure.

20 [0019] In the demander Feeder2, there are harmonics sources (harmonic loads) 2a and 2b. A switch SW1 is a switch for supposing the fluctuation of a harmonic load current and a switch SW2 is a switch for supposing the fluctuation of load impedance due to changeover of a phase advanced capacitor 3a. Moreover, in order to take account of system impedance fluctuation of demander Feeder2 as viewed from active filter AF and influence of other demanders, the changeover of phase advanced capacitor 3b is supposed with a switch SW3 of the demander Feeder1.

25 [0020] FIG. 12 shows the circuit configuration of a control model of the source current detection type shunt active filter AF and an example

of a control device. Impedances of an actual or real system 4 and loads $2a, 2b, \dots, 2n$ (n is a natural number) are unknown and the quantity of harmonics generation is varied with load variation.

[0021] As shown in FIG. 12, following symbols are used: a voltage
5 V_s of a system interconnection point; a current i_s of the system interconnection point; an active filter current i_{AF} ; an active filter input current i_{AFi} ; an active filter dc voltage V_{dc} ; and a load current (total) i_L . The inside of the active filter control system is explained later.

[0022] Instead of detection of current i_s at the system
10 interconnection point, it is possible to employ a configuration to detect the active filter input current i_{AFi} and the load current (total) i_L , and to determine a current corresponding to the interconnection point current i_s by addition in a controller.

[0023] In the distribution system, the orders of harmonics
15 exceeding the guideline level and causing problems are limited to certain orders such as fifth and seventh. Therefore, a frequency component of each of the specified orders is extracted and compensation is made for each order.

[0024] FIG. 13 shows a basic configuration of an active filter control
20 system as one example of an embodiment 1.

[0025] First, an AC voltage phase θ is detected from the
interconnection point voltage V_s by a PLL (Phase Locked Loop) 11. A dq axes orthogonal rotating coordinate system is constructed in synchronization with the AC voltage phase θ as a reference phase, and
25 a current vector control is performed on the d and q axes.

[0026] A later-mentioned periodic disturbance observer (periodic disturbance suppression control apparatus) 12 produces d axis command current value I^*_d and q axis command current value I^*_q of a periodic disturbance suppressing current command. A current I^*_{dc} for

controlling the active filter DC voltage V_{dc} constant is added to the d axis command current I^*d . The constant control of active filter DC voltage V_{dc} is performed with a PI controller 13, to follow an active filter DC command voltage V^*dc .

5 [0027] A sensed value of the active filter input current i_{AFi} is converted into a d axis sensed current I_d and a q axis sensed current I_q , with a dq rotating coordinate transforming section 14 synchronous with the frequency component of the AC voltage phase θ . The control system determines a deviation of the d axis sensed current I_d from the
10 d axis command current I^*d and a deviation of the q axis sensed current I_q from the q axis command current I^*q , and produces a d axis command voltage V^*d and a q axis command voltage V^*q , with PI controllers 15d and 15q, respectively. These command voltages are converted into a 3-phase voltage command V^*AFi based on the AC
15 voltage phase θ , with a dq rotating axis inverse transforming section 16. A comparator 17 compares the amplitude of the 3-phase voltage command V^*AFi serving as the fundamental or fundamental wave, and the amplitude of the carrier signal, and thereby produces gate control signals of a PWM controller.

20 [0028] FIG. 14 is a control block diagram showing a control configuration of the periodic disturbance observer 12 for a harmonic of n-th frequency component. To extract the n-th harmonic in the d_nq_n coordinate axes synchronous with the n-th frequency component, a dq rotating coordinate transforming section 21 converts the sensed 3-
25 phase interconnection point current (the sensed value of the input signal) $i_s(=[i_{su} \ i_{sv} \ i_{sw}]^T)$, to a d_n axis sensed current i_{sdn} and a q_n axis sensed current i_{sqn} in the nth d_nq_n rotating coordinates, by a d_nq_n coordinate transforming equation given by an expression (1).

[0029] [Math. 1]

$$\begin{bmatrix} i_{sdn} \\ i_{sqn} \end{bmatrix} = \sqrt{\frac{2}{3}} \begin{bmatrix} \cos n\theta & \cos\left(n\theta - \frac{2}{3}\pi\right) & \cos\left(n\theta + \frac{2}{3}\pi\right) \\ -\sin n\theta & -\sin\left(n\theta - \frac{2}{3}\pi\right) & -\sin\left(n\theta + \frac{2}{3}\pi\right) \end{bmatrix} \begin{bmatrix} i_{su} \\ i_{sv} \\ i_{sw} \end{bmatrix} \quad \dots(1)$$

[0030] In the d_n axis sensed current i_{sdn} and q_n axis sensed current i_{sqn} , the n -th order component extracted as a specified order appears as DC component, and frequency components other than the n -th order appear as fluctuation component. Therefore, respectively, through LPFs (Low-Pass Filters) 22d and 22q represented by an expression (2), the control system extracts the d_n axis current I_{sdn} and q_n axis current I_{sqn} which are sensed periodic disturbance currents of the DC components synchronous with the $d_n q_n$ rotating coordinates. Since the expression (2) is a simplest example of LPF advantageous for simplicity in calculation, it is possible to change the order and form in dependence on conditions such as noise at the time of extraction of pulsating component. Alternatively, it is possible to use Fourier transform. The dq rotating coordinate transforming section 21 and LPFs 22d and 22q constitute a periodic disturbance sensing section 30.

[0031] [Math. 2]

$$G_F(s) = \frac{w_f}{s + w_f} \quad \dots (2)$$

wf: cutoff frequency, s: Laplace operator.

[0032] The periodic disturbance observer 12 forms the control system contributing only to the specific frequency component. Therefore, a transfer characteristic P_n of the real system or actual system of the $d_n q_n$ coordinate axes for the n -th component can be expressed, as an expression (3), in the form of a one dimensional

complex vector having a d_n axis component P_{dn} in a real part and a q_n axis component P_{qn} in an imaginary part.

[0033] [Math. 3]

$$P_n = P_{dn} + jP_{qn} \quad (3)$$

5 [0034] The transfer characteristic P_n of the real system stands for a frequency transfer characteristic from a periodic disturbance suppressing command current $I^*_n (=I^*_{dn}+jI^*_{qn})$ at the n th order of the periodic disturbance observer 12, to the periodic disturbance sensed current (sensed value of the input signal) $\dot{I}_{Sn} (=i_{Sdn}+ji_{Sq_n})$,

10 and takes the generalized form including not only the impedance characteristic of the controlled object, but also the inverter control characteristic, computation delay, dead time, delay of the current detection, other disturbances of circuit characteristic, and transfer characteristics of the control device and peripheral devices (such as
15 sensors) relating to the control.

[0035] To explain the operation of periodic disturbance observer 12 briefly, a control system focusing only on the n th frequency component of the d_nq_n coordinate axes is expressed as shown in FIG. 15. In FIG. 15, the vector notation means the complex vector. $G_F(s)$ given by the
20 expression (2) is LPF acting on each of the real part and imaginary part components.

[0036] The basic operation is an operation to estimate an real system input current $\hat{I}_n (= \hat{I}_{dn}+j\hat{I}_{qn})$ as expressed by an expression (5) with a multiplier 23, from the period disturbance sensed current $\dot{I}_{Sn}$
25 $(=i_{Sdn}+ji_{Sq_n})$ from LPF 22, by the use of a model $\hat{Q}_n (=P_n^{-1})$ of a reciprocal Q_n of the transfer characteristic of the real system expressed by an expression (4).

[0037] [Math. 4]

$$\hat{Q}_n = \hat{Q}_{dn} + j\hat{Q}_{qn} = \frac{1}{\hat{P}_{dn} + j\hat{P}_{qn}} \quad \dots (4)$$

$$\therefore \hat{Q}_{dn} = \frac{\hat{P}_{dn}}{\hat{P}_{dn}^2 + \hat{P}_{qn}^2}, \quad \hat{Q}_{qn} = -\frac{\hat{P}_{qn}}{\hat{P}_{dn}^2 + \hat{P}_{qn}^2}$$

$$\hat{I}_n = \hat{Q}_n I_{Sn} \quad \dots (5)$$

[0038] Since the periodic disturbance current dI_n is included in the real system input current $\hat{I}_n$, an estimated periodic disturbance current $d\hat{I}_n (=d\hat{I}_{dn} + jd\hat{I}_{qn})$ is determined by subtracting the periodic disturbance suppressing command current $I_n^* (=I_{dn}^* + jI_{qn}^*)$ obtained through $G_F(s)$ 25, from the estimated real system input current $\hat{I}_n$ of the equation (5), with an adder 26 as expressed by an expression (6).

[0039] [Math. 5]

$$d\hat{I}_n = \hat{Q}_n I_{Sn} - G_F(s) I_n^* \quad \dots (6)$$

[0040] An adder 27 can cancel out the periodic disturbance current dI_n by subtracting the estimated periodic disturbance current $d\hat{I}_n$ expressed by the expression (6), from the periodic disturbance command current $dI_n^* (=dI_{dn}^* + jdI_{qn}^*)$ (normally equal to zero).

[0041] The system of FIG. 14 is obtained by expanding the basic configuration of FIG. 15, for the active filter control of the $d_n q_n$ coordinate axes, and the system of FIG. 14 can provide the d_n axis

command current I_{dn}^* and q_n axis command current I_{qn}^* of the periodic disturbance suppressing command current to suppress the periodic disturbance, with the learning function using the reciprocal Q_n of the transfer characteristic. Specifically, multipliers 23da, 23db, 23qa and 23qb determine products of the periodic disturbance sensed currents I_{sdn} and I_{sqn} and the reciprocal $Q_{dn} + jQ_{qn}$ of the transfer characteristic of the real system, and adders 24d and 24q calculate the

estimate values $\hat{I}_{dn}$ and $\hat{I}_{dq}$ of the input current of the real system by addition.

[0042] The reciprocals Q_{dn} and Q_{qn} of the transfer characteristics of the real system are the reciprocals of the transfer characteristics from the d axis command current I^*_d and q axis command current I^*_q of the periodic disturbance suppressing command current, to the sensed value (sensed input signal) i_s of the interconnection point current. With these reciprocals, the control system can cancel out the transfer characteristic of a phase delay etc. The reciprocals Q_{dn} and Q_{qn} are corrected in accordance with the sensed harmonic currents i_{sdn} and i_{sqn} , by a learning control section 29. A periodic disturbance estimating section is constituted by the multipliers 23, adders 24, LPFs 25 and adders 26. The learning control section 29 will be explained later.

[0043] Next, the disturbance is estimated. The disturbance is determined by determining a deviation between two signals.

(1) A quantity $(\hat{I}_{dn}, \hat{I}_{qn})$ obtained by passage of the periodic disturbance suppression command currents I^*_{dn} and I^*_{qn} through the real system and multiplication of the reciprocals Q_{dn} and Q_{qn} of the transfer characteristics of the real system to cancel out the transfer characteristic of the real system.

(2) A quantity obtained by application of the periodic disturbance suppression command currents I^*_{dn} and I^*_{qn} to LPFs 25d and 25q, without passage through the real system.

[0044] The above-mentioned quantity (1) is the signal on which the disturbance of the real system is superimposed. The quantity (2) is the signal which results from only the application of LPFs 25d and 25q to the periodic disturbance suppression command currents I^*_{dn} and I^*_{qn} and which does not include the disturbance. By determining the

difference between these two signals with adders 26d and 26q, the control system can determine the periodic disturbance estimated currents $\hat{dI}_{dn}$ and $\hat{dI}_{qn}$.

[0045] Adders 27d and 27q determine deviations of the thus-
5 obtained periodic disturbance estimated currents $\hat{dI}_{dn}$ and $\hat{dI}_{qn}$ and the periodic disturbance command currents dI^*_{dn} and dI^*_{qn} .

Normally, the periodic disturbance command currents dI^*_{dn} and dI^*_{qn} are set to zero to control the disturbance to "0".

[0046] With this calculation, the control system determines the
10 periodic disturbance suppressing command currents I^*_{dn} and I^*_{qn} . The periodic disturbance suppressing command currents I^*_{dn} and I^*_{qn} are LPF-processed with LPFs 25d and 25q and used for the estimation of periodic disturbance estimated currents $\hat{dI}_{dn}$ and $\hat{dI}_{qn}$ by comparison with the real system estimated input currents $\hat{I}_{dn}$ and $\hat{I}_{qn}$.

[0047] The periodic disturbance suppressing command currents
15 I^*_{dn} and I^*_{qn} of the d_nq_n coordinate axes are converted by a dq coordinate inverse transforming section 28, into the d axis command current I^*_d and q axis command current I^*_q of the dq coordinate periodic disturbance suppressing command, as expressed by an
20 equation (7), and used as the current command of the dq axes current vector control system of FIG. 13.

[0048] A signal $(n-1)\theta$ is inputted into the dq rotation coordinate
inverse transforming section 28 because, by the inverse transformation at the $(n-1)$ th order, it is possible to obtain orthogonal two axes
25 components with the signal of n multiple of the fundamental being DC value.

[0049] [Math. 6]

$$\begin{bmatrix} I^*_d \\ I^*_q \end{bmatrix} = \begin{bmatrix} \cos\{(n-1)\theta\} & -\sin\{(n-1)\theta\} \\ \sin\{(n-1)\theta\} & \cos\{(n-1)\theta\} \end{bmatrix} \cdot \begin{bmatrix} I^*_{dn} \\ I^*_{qn} \end{bmatrix} \quad \dots (7)$$

[0050] [Influence of Model Error]

Next, influence of model error is examined.

[0051] Actual power systems involve fluctuation such as impedance fluctuation, and hence, the transfer characteristic P_n of the real system becomes a time-varying parameter. Therefore, consideration is given to influence of a model error $\hat{Q}_n \neq Q_n$ of the reciprocal of the transfer characteristic P_n of the real system, on the stability of periodic disturbance observer 12.

[0052] In the control system of the $d_n q_n$ rotation coordinates shown in FIG. 15, a disturbance response transfer function from the periodic disturbance to the sensed value is given by an equation (8). However, an ideal condition is set by removing the other frequency components with LPF of the equation (2).

[0053] [Math. 7]

$$15 \quad \frac{I_{Sn}}{dI_n} = \frac{w_f P_n s}{s^2 + w_f (1 + P_n \hat{Q}_n) s + w_f^2 P_n \hat{Q}_n} \quad \dots (8)$$

I_{Sn} : sensed current

dI_n : periodic disturbance current

w_f : cutoff frequency

[0054] An inverse model $\hat{Q}_n$ of the reciprocal $Q_n (=P_n^{-1})$ of the transfer characteristic of the real system is defined as an expression (9) by using an amplitude error A_n ($A_n > 0$) in the inverse model, and a phase error ϕ_n ($-\pi < \phi_n \leq \pi$). When the amplitude error $A_n = 1$ and the phase error $\phi_n = 0$, the inverse model $\hat{Q}_n$ is equal to a true value.

[0055] [Math. 8]

$$25 \quad \hat{Q}_n = A_n e^{j\phi_n} Q_n \quad \dots (9)$$

[0056] An expression (10) is obtained by substituting expression (9) in expression (8) and rearranging. In this equation, $C_n(s)$ is a periodic disturbance response transfer characteristic.

[0057] [Math. 9]

$$\frac{I_{Sn}}{dI_n} = \frac{w_f s}{(s+w_f)(s+w_f A_n e^{j\phi_n})} P_n = C_n(s) P_n \quad \dots (10)$$

[0058] From a condition of $-w_f < 0$, $-w_f A_n \cos \phi_n < 0$ where the real part of the pole of $C_n(s)$ is negative, a robust stability condition to the phase error ϕ_n is given by an expression (11).

5 [0059] [Math. 10]

$$-\frac{\pi}{2} < \phi_n < \frac{\pi}{2} \quad \dots (11)$$

[0060] Since $A_n > 0$, the amplitude error does not affect the stability condition in a continuous system. However, the pole is shifted to the stable direction as the amplitude error A_n become larger instead of the

10 true value $A_n = 1$. Although a dominant pole in $A_n > 1$ is determined by the cutoff frequency w_f of LPF, the control with $A_n > 1$ is possible as a kind of observer gain to improve the quickness of the response.

However, the robust stability condition is considered with a transfer function of an equation (12) in a discrete system because there is a

15 need for avoiding a calculation dead time and algebraic loop accompanied by the digital control.

[0061] [Math 11]

$$C_n(z^{-1}) = \frac{z^{-1} G_F(z^{-1}) (1 - z^{-1} G_F(z^{-1}))}{1 + (A_n e^{j\phi_n} - 1) z^{-1} G_F(z^{-1})} \quad \dots (12)$$

[0062] An expression (14) is obtained by bilinear transformation of

20 GF(s) of expression (2) with the calculation period T_s as expressed by an expression (13), and substitution in equation (12) to solve a characteristic equation.

[0063] [Math. 12]

$$G_F(z^{-1}) = \frac{w_f T_s (1 + z^{-1})}{2 + w_f T_s + (w_f T_s - 2) z^{-1}} \quad \dots (13)$$

$$\begin{cases} Z = 0 \\ Z = \frac{2-w_f T_s}{2+w_f T_s} \\ Z = \frac{2-w_f T_s A_n e^{j\phi_n} \pm \sqrt{(w_f T_s A_n e^{j\phi_n} - 2)^2 - 4w_f T_s (2+w_f T_s)(A_n e^{j\phi_n} - 1)}}{2(2+w_f T_s)} \end{cases} \quad \dots (14)$$

[0064] Although stability is achieved if all the poles of the discrete system of expression (14) are disposed within a unit circle, it is difficult to find an algebraic solution. Accordingly, a stable boundary condition shown in FIG. 16 is obtained by determining a robust stability numerically to the amplitude error A_n and phase error ϕ_n with the setting of cutoff frequency $w_f=2\pi$ [rad/s], and calculation period $T_s=100$ [μ s], for example.

[0065] When the phase error ϕ_n is null, the stability margin to amplitude error A_n is greatest. The stability decreases with increase of the phase error ϕ_n , and the system becomes unstable outside the range of expression (11). Within a stable region, it is possible to improve the quickness of the response of the periodic disturbance suppression by increasing amplitude error A_n . However, in the actual use, it is required to consider model error fluctuation due to system impedance fluctuation, and to determine the setting with a sufficient stability margin.

MODE(S) FOR CARRYING OUT THE INVENTION

[0066] The following explanation is directed to embodiments arranged to correct and control the error between the control form of the real system and the periodic disturbance observer sequentially with an observer inverse model, in an example using an active filter AF.

[0067] In this description, the explanation takes, as a typical example, a source current detection type shunt active filter AF for a power distribution system. However, the control technique can be applied to other apparatus and configurations in similar manners. For example, the technique can be used for load current detection type

active filter AF or voltage detection type active filter AF, or a periodic disturbance suppressing control apparatus for correcting distortion of source voltage instead of distortion of current distortion.

[0068] [Embodiment 1]

5 The learning control explained in a first embodiment (correction control of inverse model Q^n following condition change of the real system) is auxiliary function intended to prevent degradation of control performance and destabilization of the periodic disturbance observer 12. Therefore, this learning control does not require high speed
10 calculation as compared to the control period or cycle of the harmonic suppression control. For example, the learning control period T_L is set at $T_L=20[\text{ms}]$ (50Hz system fundamental period), as compared to the calculation period T_s of the periodic disturbance observer 12 set at $T_s=100 [\mu\text{s}]$, in consideration of the calculation load of harmonic vector
15 loci.

[0069] Next, the explanation is directed to a method of estimating a transfer characteristic P_n of the real system at the learning control period T_L . The transfer characteristic P_n of the real system in the first
20 embodiment is a n -th order component (n is an arbitrary order) of the frequency transfer characteristic from a harmonic suppressing command $I^n (=I^n_d + jI^n_q)$ of the periodic disturbance observer to a harmonic sensed current (the sensed value of input signal)
 $i^n (=i^n_s + ji^n_q)$.

[0070] In the following explanation, consideration is given to
25 various values of an N -th sample sampled with the learning control period T_L and various values of a previous sample ($N-1$) taken one sample before. A suffix $[N]$ represents values of the N th sample, and a suffix $[N-1]$ represents values of the previous sample taken one sample ago.

[0071] FIG. 1 is a block diagram showing the periodic disturbance observer provided with a learning function. First, the input-output relationship of the real system shown in FIG. 15 is given by an expression (15) for each sample.

5 [0072] [Math. 13]

$$\begin{cases} I_{Sn[N]} = G_F(z_{[N]}^{-1}) \cdot P_{n[N]} (I_{n[N]}^* + dI_{n[N]}) \\ I_{Sn[N-1]} = G_F(z_{[N-1]}^{-1}) \cdot P_{n[N-1]} (I_{n[N-1]}^* + dI_{n[N-1]}) \end{cases} \dots (15)$$

[0073] A following expression defines a difference $\Delta P_{n[N]}$ of the transfer characteristic of the real system during one sample interval of the learning control period T_L , a difference $\Delta dI_{n[N]}$ of the periodic disturbance current during one sample interval, a difference $\Delta I_{n[N]}^*$ of the harmonic suppressing command current during one sample interval, and a difference $\Delta I_{Sn[N]}$ of the harmonic sensed current during one sample interval.

10

[0074] [Math. 14]

$$\begin{cases} \Delta I_{Sn[N]} = I_{Sn[N]} - I_{Sn[N-1]} \\ \Delta I_{n[N]}^* = G_F(z_{[N]}^{-1}) \cdot I_{n[N]}^* - G_F(z_{[N-1]}^{-1}) \cdot I_{n[N-1]}^* \\ \Delta P_{n[N]} = P_{n[N]} - P_{n[N-1]} \\ \Delta dI_{n[N]} = dI_{n[N]} - dI_{n[N-1]} \end{cases} \dots (16)$$

15

[0075] From the expressions (15) and (16), a following relationship is obtained as to the differences between consecutive samples.

[0076] [Math. 15]

$$\begin{aligned} \Delta I_{Sn[N]} = & P_{n[N]} \left(\Delta I_{n[N]}^* + \left(G_F(z_{[N]}^{-1}) - G_F(z_{[N-1]}^{-1}) \right) \cdot \Delta dI_{n[N]} \right) \\ & + \Delta P_{n[N]} \left(G_F(z_{[N]}^{-1}) \cdot I_{n[N]}^* - \Delta I_{n[N]}^* + G_F(z_{[N-1]}^{-1}) \cdot \Delta dI_{n[N]} \right) \\ & + \Delta dI_{n[N]} \cdot G_F(z_{[N-1]}^{-1}) \cdot (P_{n[N]} - \Delta P_{n[N]}) \end{aligned}$$

20

$$\dots (17)$$

[0077] The first embodiment is intended to suppress the harmonics of the power system. In general, the variation of the harmonic

characteristic and the variation of the system impedance are gradual in the power system, and the variations are very small during a very short time interval of the learning control period $T_L=20\text{ms}$.

[0078] Therefore, an expression (18) is obtained by regarding the difference (variation) $\Delta P_n[N]$ of the transfer characteristic of the real system and the difference (variation) $\Delta d_{In}[N]$ of the periodic disturbance current during one sample interval of the learning control period T_L (the N -th sample – the $(N-1)$ th sample) in the expression (17) as being equal to zero and neglecting these differences.

10 Moreover, the LPF of the N -th sample and the LPF of the $(N-1)$ th sample are regarded as $GF(z^{-1}[N]) = GF(z^{-1}[N-1])$.

[0079] [Math. 16]

$$\Delta I_{Sn}[N] \cong P_{n[N]} \Delta I_{n[N]}^* \quad \dots (18)$$

[0080] From the expression (18), the estimated value $\hat{P}_n[N]$ of the transfer characteristic of the rear system to the n -th order harmonic of the N -th sample is estimated as an expression (19).

[0081] [Math. 17]

$$\hat{P}_n[N] \cong \frac{\Delta I_{Sn}[N]}{\Delta I_{n[N]}^*} \quad \dots (19)$$

[0082] Therefore, the inverse model $\hat{Q}_n (= \hat{P}_n^{-1})$ of the periodic disturbance 12 for the n -th order harmonic of the N -th sample is given by an expression (20).

[0083] [Math. 18]

$$\hat{Q}_n[N] \cong \frac{\Delta I_{n[N]}^*}{\Delta I_{Sn}[N]} \quad \dots (20)$$

[0084] An expression or equation (21) is obtained by expanding Expression (20) with the $d_n q_n$ rotating coordinate system.

[0085] [Math. 19]

$$\begin{cases} \hat{Q}_{dn}[N] = \frac{(I_{sdn}[N] - I_{sdn}[N-1])(I_{dn}^*[N] - I_{dn}^*[N-1]) + (I_{sqn}[N] - I_{sqn}[N-1])(I_{qn}^*[N] - I_{qn}^*[N-1])}{(I_{sdn}[N] - I_{sdn}[N-1])^2 + (I_{sqn}[N] - I_{sqn}[N-1])^2} \\ \hat{Q}_{qn}[N] = \frac{(I_{sdn}[N] - I_{sdn}[N-1])(I_{qn}^*[N] - I_{qn}^*[N-1]) - (I_{sqn}[N] - I_{sqn}[N-1])(I_{dn}^*[N] - I_{dn}^*[N-1])}{(I_{sdn}[N] - I_{sdn}[N-1])^2 + (I_{sqn}[N] - I_{sqn}[N-1])^2} \end{cases} \quad \dots (21)$$

[0086] FIG. 2 is a block diagram of the learning control section 29 shown in FIG. 1. The current sample values $I_{sdn}[N]$ and $I_{sqn}[N]$ of the d axis and q axis n-th order sensed periodic disturbances and the current sample values $I_{dn}^*[N]$ and $I_{qn}^*[N]$ of the d axis and q axis n-th order harmonic suppressing command currents, and the previous sample values $I_{sdn}[N-1]$, $I_{sqn}[N-1]$, $I_{dn}^*[N-1]$ and $I_{qn}^*[N-1]$ obtained through delay circuits Z^{-1} are substituted in the inverse model estimating expression of the N-th sample d axis and q axis n-th order harmonic, expressed by the expression or equation (21). The estimated inverse models $\hat{Q}_{dn}[N]$ and $\hat{Q}_{qn}[N]$ are applied to the multipliers 23da, 23db, 23qa and 23qb of periodic disturbance observer 12 successively.

[0087] According to the first embodiment, even in case of a large condition change in the real system and an error between the transfer characteristic P_n of the real system and the model of periodic disturbance observer 12, the control system can follow the condition change and correct the inverse models $\hat{Q}_{dn}[N]$ and $\hat{Q}_{qn}[N]$ of the transfer characteristic of the real system during estimation, so that the first embodiment can realize the very stable control system. Moreover, even if the power system impedance that is the controlled object to be controlled has been changed during the harmonic suppressing control, the control system according to the first embodiment can immediately correct the inverse models $\hat{Q}_{dn}[N]$ and $\hat{Q}_{qn}[N]$

$\hat{q}_n[N]$ of the transfer characteristic of the real system properly and continue the harmonic suppressing operation automatically.

[0088] As explained above, in addition to the robust stability of the base control configuration in the form of the periodic disturbance observer 12, the first embodiment makes it possible to achieve the stability in all the operating regions by correcting the model of the periodic disturbance observer 12 automatically even if the transfer characteristic P_n of the real system is varied and the operation is brought into the region outside the robust stability region.

[0089] Accordingly, it is possible to eliminate the need for identification of the power system in advance even if the power system impedance is unknown, to facilitate the maintenance and to automatize the control adjustment.

[0090] [Embodiment 2]

In the first embodiment, the pulsation frequency component I_{Sn} extracted through LPF $GF(s)$ of the expression (2) is substituted, as the harmonic sensed current, into the inverse model estimating equation (21) in the N -th sample, d axis and q axis n -th order harmonic. A response delay is involved in LPF $GF(s)$, and therefore, the estimation of the expression (21) is delayed with respect to the variation of transfer characteristic P_n of the real system. Therefore, the second embodiment uses an average harmonic current $\bar{i}_{Sn}$ in the learning control period T_L as expressed by an expression (22), as the harmonic current detection technique for the learning control.

[0091] [Math. 20]

$$\bar{i}_{Sn[N]} = \bar{i}_{sdn[N]} \mp j \bar{i}_{sqn[N]} = \frac{1}{T_L} \int_{t-T_L}^t i_{sdn}(t) dt + j \frac{1}{T_L} \int_{t-T_L}^t i_{sqn}(t) dt \quad \dots (22)$$

[0092] Since the learning control period T_L is set as $T_L=20$ [ms] while the control period T_s of the periodic observer is $T_s=100$ [μ s]

under the condition of this description, for example, it is possible to determine the average value $\bar{i}_{Sn}$ in the learning control period T_L by averaging 200 data items obtained by sampling the harmonic sensed current i_{Sn} at the control period T_s . Thus the average harmonic

5 current $\bar{i}_{Sn}$ can be calculated as in an expression (23) on the premise that the learning control period T_L is an integral multiple of the control period T_s of the periodic disturbance observer.

[0093] [Math. 21]

$$\bar{i}_{Sn[N]} = \bar{i}_{sdn[N]} + j\bar{i}_{sqn[N]} = \frac{1}{T_L/T_s} \cdot \sum_{k=K-T_L/T_s}^K (i_{sdn[k]} + j \cdot i_{sqn[k]})$$

10 ... (23)

[0094] In this expression, a suffix K indicate a k-th sampling of the periodic disturbance observer.

[0095] Similarly, an average $\bar{I}^*n$ of the harmonic suppressing command current I^*n .

15 [0096] [Math. 22]

$$\bar{I}^*_{n[N]} = \bar{I}^*_{dn[N]} + j \cdot \bar{I}^*_{qn[N]} = \frac{1}{T_L/T_s} \cdot \sum_{k=K-T_L/T_s}^K (I^*_{dn[k]} + j \cdot I^*_{qn[k]})$$

... (24)

[0097] FIG. 3 is a block diagram of the second embodiment. The input-output relationship of the real system is given by an expression

20 (25).

[0098] [Math. 23]

$$\begin{cases} \bar{i}_{Sn[N]} = P_{n[N]}(\bar{I}^*_{n[N]} + dI_{n[N]}) \\ \bar{i}_{Sn[N-1]} = P_{n[N-1]}(\bar{I}^*_{n[N-1]} + dI_{n[N-1]}) \end{cases} \quad \dots (25)$$

[0099] As in the first embodiment, the difference of each signal during one sample interval (the N-th sample – the (N-1)th sample) of the learning control period TL is defined as follows.

[0100] [Math. 24]

$$5 \quad \begin{cases} \Delta \bar{i}_{Sn[N]} = \bar{i}_{Sn[N]} - \bar{i}_{Sn[N-1]} \\ \Delta \bar{I}_{n[N]}^* = \bar{I}_{n[N]}^* - \bar{I}_{n[N-1]}^* \\ \Delta P_{n[N]} = P_{n[N]} - P_{n[N-1]} \\ \Delta dI_{n[N]} = dI_{n[N]} - dI_{n[N-1]} \end{cases} \quad \dots (26)$$

[0101] From the expressions (25) and (26), a following relationship holds about the differences during one sample interval.

[0102] [Math. 25]

$$10 \quad \begin{aligned} \Delta \bar{i}_{Sn[N]} &= P_{n[N]} \Delta \bar{I}_{n[N]}^* + \Delta P_{n[N]} (\bar{I}_{n[N]}^* - \Delta \bar{I}_{n[N]}^* + \Delta dI_{n[N]}) \\ &\quad + \Delta dI_{n[N]} (P_{n[N]} - \Delta P_{n[N]}) \end{aligned} \quad \dots (27)$$

[0103] In general, the variation of the harmonic characteristics of the power system and the variation of the system impedance are gradual and the amounts of the variations are very small within the very short time of the learning control period TL=20ms. Therefore, an expression (28) is obtained by neglecting, as being approximately equal to zero, the difference $\Delta P_{n[N]}$ of the real system transfer characteristic and the difference $\Delta dI_{n[N]}$ of the periodic disturbance current during one sample interval in the expression (27).

[0104] [Math. 26]

$$20 \quad \Delta \bar{i}_{Sn[N]} \cong P_{n[N]} \Delta \bar{I}_{n[N]}^* \quad \dots (28)$$

[0105] From the expression (28), the estimated value $\hat{P}_{n[N]}$ of the transfer characteristic of the real system to the n-th order harmonic of the N-th sample is estimated as an expression (29).

[0106] [Math. 27]

$$\Delta \hat{P}_{n[N]} \cong \frac{\Delta \bar{i}_{sn[N]}}{\Delta \bar{I}_{n[N]}^*} \quad \dots (29)$$

[0107] Therefore, the inverse model $\hat{Q}^*n (=P^{-1}n)$ of the periodic disturbance for the n-th order harmonic of the N-th sample is given by an expression (30).

5 [0108] [Math. 28]

$$\Delta \hat{Q}_{n[N]} \cong \frac{\Delta \bar{I}_{n[N]}^*}{\Delta \bar{i}_{sn[N]}} \quad \dots (30)$$

[0109] By expanding the expression (30) with the $d_n q_n$ rotating coordinate system, the d axis and q axis estimated inverse models $\hat{Q}^*$

10 $d_n[N]$ and $\hat{Q}^*q_n[N]$ of the n-th order harmonic in the N-th sample are given by an expression or equation (31).

[0110] [Math. 29]

$$\begin{cases} \hat{Q}_{dn[N]} = \frac{(\bar{i}_{sdn[N]} - \bar{i}_{sdn[N-1]})(\bar{I}_{dn[N]}^* - \bar{I}_{dn[N-1]}^*) + (\bar{i}_{sqn[N]} - \bar{i}_{sqn[N-1]})(\bar{I}_{qn[N]}^* - \bar{I}_{qn[N-1]}^*)}{(\bar{i}_{sdn[N]} - \bar{i}_{sdn[N-1]})^2 + (\bar{i}_{sqn[N]} - \bar{i}_{sqn[N-1]})^2} \\ \hat{Q}_{qn[N]} = \frac{(\bar{i}_{sdn[N]} - \bar{i}_{sdn[N-1]})(\bar{I}_{qn[N]}^* - \bar{I}_{qn[N-1]}^*) - (\bar{i}_{sqn[N]} - \bar{i}_{sqn[N-1]})(\bar{I}_{dn[N]}^* - \bar{I}_{dn[N-1]}^*)}{(\bar{i}_{sdn[N]} - \bar{i}_{sdn[N-1]})^2 + (\bar{i}_{sqn[N]} - \bar{i}_{sqn[N-1]})^2} \end{cases} \quad \dots (31)$$

15 [0111] FIG. 4 is a block diagram of the learning control section 29 shown in FIG. 3. The current average sampling values $\bar{i}_{sdn[N]}$ and $\bar{i}_{sqn[N]}$ of the sensed harmonic current and the current average sampling values $\bar{I}_{dn[N]}^*$ and $\bar{I}_{qn[N]}^*$ of the harmonic suppressing commands, and the previous average sampling values $\bar{i}_{sdn[N-1]}$, $\bar{i}_{sqn[N-1]}$, $\bar{I}_{dn[N-1]}^*$ and $\bar{I}_{qn[N-1]}^*$ obtained through delay circuits Z-1 are substituted into the inverse model estimating expression of the

20

expression or equation (31). The estimated inverse models $\hat{Q}_{dn}[N]$ and $\hat{Q}_{qn}[N]$ are applied to the multipliers 23da, 23db, 23qa and 23qb of periodic disturbance observer 12 successively.

[0112] According to the second embodiment, the model is
5 estimated by using the average or mean values obtained by averaging the harmonic sensed current i_{sn} and the harmonic suppressing command current I^*n obtained during the time interval of the control period T_s of the periodic disturbance observer 12. Therefore, in addition to the effects of the first embodiment, the second embodiment
10 makes it possible to estimate the reciprocals Q_{dn} and Q_{qn} of the periodic disturbance observer 12 with the learning control period T_L speedily without being affected by the detection response delay of LPF $GF(s)$ as in the first embodiment.

[0113] [Embodiment 3]

15 When the denominator becomes equal to zero in the inverse model estimating expression (31) of the second embodiment, for example, the calculation becomes unfeasible in the form of division by zero. Therefore, the third embodiment employs means for preventing division by zero in the control system of the first embodiment or the second
20 embodiment.

[0114] In the following explanation, the expression (31) of the second embodiment is taken as an example. The denominator in the expression (31) is expressed by a following equation (den: denominator).

25 [0115] [Math. 30]

$$\text{den} = (\bar{i}_{sdn}[N] - \bar{i}_{sdn}[N-1])^2 + (\bar{i}_{sqn}[N] - \bar{i}_{sqn}[N-1])^2 \quad \cdots (32)$$

[0116] The denominator den is expressed by the differences during one sample interval of the d axis component and the q axis component in the average value of the harmonic sensed current i_n . Therefore,

when the variation of the harmonic sensed current isn during one sample interval of the learning control period TL becomes zero, then the denominator den becomes equal to zero.

[0117] Therefore, as shown in an expression or equation (33) and
5 FIG. 5, when the denominator den is smaller than or equal to an arbitrary threshold Th, the control system performs a sequential operation to turn off the learning control and holds the estimated inverse models $\hat{Q}_{dn}[N]$ and $\hat{Q}_{qn}[N]$ just before the turn-off, unchanged during the period of the turn-off. In FIG. 5, flg-latch is a
10 latch flag, and $\hat{Q}'_{dn}$ and $\hat{Q}'_{qn}$ are estimated model values obtained by an inverse latch operation.

[0118] [Math. 31]

$$\begin{cases} \text{den} = (\bar{i}_{sdn}[N] - \bar{i}_{sdn}[N-1])^2 + (\bar{i}_{sqn}[N] - \bar{i}_{sqn}[N-1])^2, & \text{flg-latch} = 0 \text{ (if: den} > Th) \\ \text{den} = Th, & \text{flg-latch} = 1 \text{ (if: den} \leq Th) \end{cases} \dots (33)$$

15 [0119] The control system of the third embodiment can prevent the division by zero, of the equation to find the estimated values $\hat{Q}_{dn}[N]$ and $\hat{Q}_{qn}[N]$ of the inverse model, stop the learning function of the model at the operating condition generating the division by zero, hold the estimated inverse model values $\hat{Q}_{dn}[N]$ and $\hat{Q}_{qn}[N]$ just
20 before the stoppage of the learning function and output the estimated inverse model values immediately before the stoppage.

[0120] [Embodiment 4]

The actual system involves measurement errors and might result in unexpected control operation in case of the application of the
25 estimation result of the observer model directly to the inverse models $\hat{Q}_{dn}[N]$ and $\hat{Q}_{qn}[N]$ of the periodic disturbance observer. Therefore, as shown in FIG. 6, a fourth embodiment employs an arbitrary filter 48 at an output portion outputting the estimation result of the observer model, in addition to the third embodiment.

[0121] Though the type of filter 48 is not limited specifically, the use of a low pass filter of a kind exerting no influence on the response speed of the estimation result of the observer model or a moving average filter, or the operation of limiting the rate of change is effective for providing performance following the correct observer model gently and avoiding abrupt change of the observer model.

[0122] [Embodiment 5]

As shown in FIG. 7, a control system according to a fifth embodiment is designed to deal with a plurality of harmonic components of orders (-5th order, 7th order ... n-th order, for example) with a parallel arrangement of the control configurations of the periodic disturbance observers 12 according to one of the first to fourth embodiment.

[0123] The inside of the periodic disturbance observer 12 of each other is identical to that shown in one of the first to fourth embodiments. The d axis harmonic suppressing command current I^*d is determined by adding up the d axis components I^*d_5 , I^*d_7 ... I^*d_n of the harmonic suppression command of the orders, and the q axis harmonic suppressing command current I^*q is determined by adding up the q axis components I^*q_5 , I^*q_7 ... I^*q_n of the harmonic suppression command of the orders.

[0124] The fifth embodiment can suppress the harmonic components of the plurality of orders simultaneously, in addition to the effects and operations of the first to fourth embodiments.

[0125] [Embodiment 6]

As one of the important points in the actual system using the power conversion device functioning as the active filter, the system cannot compensate for the harmonic current exceeding the capacity of the power conversion device. The active filter connected with the power system can supply the harmonic suppression current as long as

possible. In this case, however, the active filter operates in the state in which the harmonic suppressing command currents I^*_{dn} and I^*_{qn} are saturated. Therefore, a sixth embodiment proposes the model learning function and harmonic suppressing technique in the saturated state of the harmonic suppressing command current.

[0126] The harmonic suppressing effect becomes lower when the device capacity of the inverter becomes insufficient to the harmonic compensation quantity for compensation. The required compensation capacities are different in dependence on the orders of the harmonics, and the harmonic suppressing control taking no account of this difference might be unable to provide the effect of suppressing the harmonic of a specified order. Therefore, as shown in FIG. 8, the sixth embodiment employs a limiter 32 for limiting the command amplitude for the harmonic suppressing command currents (before limiter) I'_{dn} and I'_{qn} of the periodic disturbance observer 12 designed for control of each order of the harmonics.

[0127] The learning control section 29 employs the configuration of FIG. 2. However, the values after the limiter are used as the harmonic suppressing command currents I^*_{dn} and I^*_{qn} . Limiter 32 limits only the amplitudes of the harmonic suppressing command currents (before limiter) I'_{dn} and I'_{qn} , to a desired limit value Lim_n . The phases of the harmonic suppressing command currents I^*_{dn} and I^*_{qn} are not limited and allowed to vary freely even if the amplitudes are limited by limiter 32. The above-mentioned learning function can be performed properly to estimate the model Q^n of the periodic disturbance observer 12 as long as changes in the $dnqn$ coordinates are read for the harmonic suppressing command currents I^*_{dn} and I^*_{qn} and the periodic disturbance sensed currents I_{sdn} and I_{sqn} or the sensed harmonic currents i_{sdn} and i_{sqn} . Therefore, it is possible to continue the estimation of the inverse model Q^n of the periodic disturbance

observer 12 with the learning control function even during the limiter operation if there is a change in the phase while the amplitude is limited.

[0128] Thus, the suppression can be performed effectively by automatically searching the harmonic suppressing current phase capable of suppressing the harmonic most within the range of the amplitude limitation. The control apparatus can cause the inverse model Q^{-n} of the periodic disturbance observer 12 to follow correctly even if the amplitude and phase characteristics of the system and the harmonic component have been changed during the operation.

[0129] FIG. 9 shows an implementation example of limiter 32. FIG. 9 is a merely one example. It is possible to employ any of various other implementation forms as long as only the amplitude is limited.

[0130] An amplitude calculating section 51 determines an amplitude $\sqrt{I'^2_{dn} + I'^2_{qn}}$, from the harmonic suppressing command currents (before limiter) I'_{dn} and I'_{qn} . A comparator 52 compares the amplitude $\sqrt{I'^2_{dn} + I'^2_{qn}}$ with a desired limit value Lim_n . By using a greater one chosen by the comparison, a dividing section 53 divides the limit value Lim_n . Thus, the ratio of the limitation is outputted.

Multipliers 54 and 55 multiply the n-th order harmonic suppressing command currents I'_{dn} and I'_{qn} , by the ratio obtained by the dividing section and thereby outputs the final n-th order harmonic suppressing command currents I^*_{dn} and I^*_{qn} .

[0131] [Embodiment 7]

As shown in FIG. 10, a control system according to a seventh embodiment is designed to deal with a plurality of harmonic components of orders (-5th order, 7th order ... n-th order, for example) with a parallel arrangement of the control configurations of the periodic disturbance observers 12.

[0132] The inside of the periodic disturbance observer 12 of each order is identical to that shown in FIG. 8. The d axis harmonic suppressing command current I^*d is determined by adding up the d axis components $I^*d_5, I^*d_7 \dots I^*d_n$ of the harmonic suppression

5 command of the orders, and the q axis harmonic suppressing command current I^*q is determined by adding up the q axis components $I^*q_5, I^*q_7 \dots I^*q_n$ of the harmonic suppression command of the orders.

[0133] The seventh embodiment can suppress the harmonic components of the plurality of orders simultaneously, in addition to the effects and operations of the sixth embodiment.

[0134] Moreover, the limit values of the limiters of the different orders can be set individually and arbitrarily. For example, the impedance of the harmonic component of a higher order tends to become higher, and hence the inverter voltage required for generating the harmonic disturbance suppressing current tends to become higher, so that the tendency of voltage saturation is increased. Therefore, by setting the limit value lower for the higher order, the control system can perform the operation restraining the proportion of the suppression for the higher order harmonic, and laying emphasis on the suppression of lower order harmonic components.

[0135] Furthermore, it is possible to monitor the proportions of the component of each order of the sensed harmonic, and to determine the limit values by laying emphasis on the suppression of the order having a larger proportion.

25 [0136] Although the above detailed explanation is directed to practical examples in which the present invention is applied to the harmonic suppression of the power system with the periodic disturbance observer, various variation and modifications are possible within the purview of the technical concept of the present invention.

30 The present invention is applicable widely to the suppression of periodic

disturbance of a controlled object in general. These variations and modifications are naturally within the scope of the patent claims.

CLAIMS

1. A periodic disturbance suppressing control apparatus comprising:
 - a periodic disturbance sensing section to sense a periodic disturbance of a controlled object as a sensed periodic disturbance of a
 - 5 direct current component;
 - a periodic disturbance estimating section to estimate the periodic disturbance by determining a difference between a signal obtained by multiplication of the sensed periodic disturbance with a multiplier using a reciprocal of a transfer characteristic from a periodic
 - 10 disturbance suppressing command to the sensed periodic disturbance, determined according to a transfer characteristic of a control system, and a signal obtained by adding only a detection delay to the periodic disturbance suppressing command;
 - an adder to calculate the periodic disturbance suppressing
 - 15 command by calculating a deviation between an estimated periodic disturbance estimated by the periodic disturbance estimating section and a periodic disturbance command to suppress a disturbance; and
 - a learning control section to correct the reciprocal of the transfer characteristic in accordance with a quantity obtained by dividing a
 - 20 difference of the periodic disturbance suppressing command during one sample interval by a difference of the sensed periodic disturbance during the one sample interval, by regarding a difference of the transfer function of the control system and a difference of the periodic disturbance of the controlled object during the one sample interval as
 - 25 being approximately equal to zero.
2. The periodic disturbance suppressing control apparatus as recited in Claim 1, wherein the periodic disturbance suppressing apparatus is arranged to suppress the periodic disturbance by superposing the

periodic disturbance suppressing command on a command of a power conversion device connected with a system bus of a power source.

3. The periodic disturbance suppressing control apparatus as recited
5 in Claim 1 or 2, wherein the learning control section is configured to use average values during an interval of a control period of a periodic disturbance observer, as the sensed periodic disturbance and the period disturbance suppressing command.
- 10 4. The periodic disturbance suppressing control apparatus as recited in one of Claims 1~3, wherein the learning control section is configured to stop a learning control and output the reciprocal of the transfer characteristic just before stoppage when the difference during a one sample interval in an average value of the sensed periodic disturbance
15 is lower than or equal to a threshold value.
5. The periodic disturbance suppressing control apparatus as recited in one of Claims 1~4, wherein the learning control section includes a filter suppressing abrupt change in the reciprocal of the transfer
20 characteristic.
6. The periodic disturbance suppressing control apparatus as recited in one of Claims 1~5, wherein there is provided a limiter to limit an amplitude of the periodic disturbance suppressing command when the
25 amplitude of the periodic disturbance suppressing command is greater than a limit value.
7. The periodic disturbance suppressing control apparatus as recited in one of Claims 1~6, wherein a plurality of the periodic disturbance

control apparatus are arranged in parallel and configured to suppress periodic disturbances of a plurality of orders.

8. The periodic disturbance suppressing control apparatus as recited in one of Claims 1, wherein the learning control section is configured to stop a learning control and output the reciprocal of the transfer characteristic just before stoppage when the difference during the one sample interval of the sensed periodic disturbance is smaller than or equal to a threshold value.

9. A periodic disturbance suppressing control process comprising:
a periodic disturbance sensing operation of sensing a periodic disturbance of a controlled object as a sensed periodic disturbance in a form of a direct current component;

a periodic disturbance estimating operation of determining an estimated periodic disturbance by calculating a difference between a signal obtained by multiplication of the sensed periodic disturbance by a reciprocal of a transfer characteristic from a periodic disturbance suppressing command to the sensed periodic disturbance, and a signal obtained by adding only a detection delay to the periodic disturbance suppressing command;

a producing operation of producing the periodic disturbance suppressing command from the estimated periodic disturbance; and

a learning control operation of correcting the reciprocal of the transfer characteristic in accordance with a quantity determined by dividing a variation of the periodic disturbance suppressing command by a variation of the sensed periodic disturbance.

10. The periodic disturbance suppressing control process as claimed in Claim 9, wherein the variation of the sensed periodic disturbance is a

difference between a previous value of the sensed periodic disturbance determined in a previous cycle of the learning control operation performed periodically and a current value of the sensed periodic disturbance determined in a current cycle next to the previous cycle of the learning control operation, and

the variation of the periodic disturbance suppressing command is a difference between a previous value of the periodic disturbance suppressing command determined in a previous cycle and a current value of the periodic disturbance suppressing command determined in the current cycle.

11. The periodic disturbance suppressing control process as claimed in Claim 10, wherein the previous value of the sensed periodic disturbance is a previous average value of the sensed periodic disturbance determined by averaging values of the sensed periodic disturbance sampled during the previous cycle of the learning control operation performed periodically, the current value of the sensed periodic disturbance is a current average value of the sensed periodic disturbance determined by averaging values of the sensed periodic disturbance sampled during the current cycle next to the previous cycle, the previous value of the periodic disturbance suppressing command is a previous average value of the periodic disturbance suppressing command determined by averaging values of the periodic disturbance suppressing command sampled during the previous cycle of the learning control operation and the current value of the periodic disturbance suppressing command is a current average value of the periodic disturbance suppressing command determined by averaging values of the periodic disturbance suppressing command sampled during the current cycle of the learning control operation.

12. The periodic disturbance suppressing control process as claimed in one of Claims 9-11 wherein the learning control operation is stopped and a most recent value of the reciprocal of the transfer characteristic just before stoppage is outputted when the variation of the sensed
5 periodic disturbance is smaller than or equal to a predetermined threshold value.

13. A periodic disturbance suppressing control apparatus comprising:

10 a periodic disturbance sensing section to sense a periodic disturbance of a controlled object as a sensed periodic disturbance in a form of a direct current component;

a periodic disturbance estimating section to determine an estimated periodic disturbance by calculating a difference between a
15 signal obtained by multiplication of the sensed periodic disturbance by a reciprocal of a transfer characteristic from a periodic disturbance suppressing command to the sensed periodic disturbance, and a signal obtained by adding only a detection delay to the periodic disturbance suppressing command;

20 a producing section to produce the periodic disturbance suppressing command from the estimated periodic disturbance; and

a learning control section to correct the reciprocal of the transfer characteristic in accordance with a quantity determined by dividing a variation of the periodic disturbance suppressing command by a
25 variation of the sensed periodic disturbance.

14. The periodic disturbance suppressing control apparatus as claimed in Claim 13, wherein the learning control section is configured to set the variation of the sensed periodic disturbance equal to a
30 difference between a previous value of the sensed periodic disturbance

determined from a previous sample of data collected in a previous cycle of the learning control operation performed periodically and a current value of the sensed periodic disturbance determined from a current sample of data collected in a current cycle next to the previous cycle of the learning control operation, and to set the variation of the periodic disturbance suppressing command equal to a difference between a previous value of the periodic disturbance suppressing command determined from the previous sample in the previous cycle and a current value of the periodic disturbance suppressing command determined from the current sample in the current cycle.

15. The periodic disturbance suppressing control apparatus as claimed in Claim 14, wherein the learning control section is configured to use, as the previous value of the sensed periodic disturbance, a previous average value of the sensed periodic disturbance determined by averaging values of the sensed periodic disturbance sampled during the previous cycle of the learning control operation, to use, as the current value of the sensed periodic disturbance, a current average value of the sensed periodic disturbance determined by averaging values of the sensed periodic disturbance sampled during the current cycle next to the previous cycle, to use, as the previous value of the periodic disturbance suppressing command, a previous average value of the periodic disturbance suppressing command determined by averaging values of the periodic disturbance suppressing command sampled during the previous cycle of the learning control operation and to use as the current value of the periodic disturbance suppressing command, a current average value of the periodic disturbance suppressing command determined by averaging values of the periodic disturbance suppressing command sampled during the current cycle of the learning control operation.
