

Description

This invention relates to non-linear interferometers for use, for example, as optical switches or logic gates.

The advantages of all optical signal processing for high bit rate systems are being increasingly recognised, primarily for their potential for performing switching and logic operations, for example, at extremely rapid rates since optical frequencies are of the order of 10^{14} Hz. In order to exploit this potential it is necessary to construct devices whose response is determined by the optical input. This essentially means a device which responds differently to different intensities of input optical signal, that is, an optically non-linear device.

One approach to obtaining such a non-linear device is to employ an interferometer arrangement comprising an optical splitter which splits an input signal into two portions of different intensities which travel along an optically non-linear transmission medium, or media, to an optical combiner. An example of such device is described in the applicant's co-pending application EP 0265233 A1 which comprises an optical waveguide formed from an optical fibre having non-linear refractive index coupled to a first pair of ports of an optical coupler. In this configuration the coupler acts as both the splitter to split an input optical signal into two counter-propagating signal portions of different intensity round a common, non-linear medium and as the combiner.

The output from the combiner is dependant on the final relative phase shift of the two portions after they have propagated from the splitter to the combiner. In particular, as discussed in detail in the above referenced application, the output from the ports of the coupler is an oscillatory, periodic, function of the intensity of the input signal. The difference of the maximum and minimum intensities between which the output signal oscillates, the contrast ratio, is a function of the asymmetry of the splitter. The same oscillatory behaviour can also be realised in other interferometer arrangements, for example a Mach-Zehnder interferometer. Such interferometers, which include a non-linear transmission medium, will be referred to hereinafter as non-linear interferometers.

Such known non-linear interferometers can be used for switching and logic applications but they suffer from the disadvantage that the intensity of the input signal must be controlled within predetermined bounds to ensure that the intensity of the output signal remains close to some predetermined threshold level which determines that the output is of a given logic level. If the intensity of the input signal increases too much the output of the device reverts to the other logic level.

It is an object of the present invention to provide an optical device which does not require the previous-

ly required degree of control of the intensity of the input signal to the device. In accordance with one aspect of the present invention, a non-linear interferometer comprises an asymmetric optical splitter, an optically non-linear transmission medium and an optical combiner, the optical splitter in use splitting an input signal into two portions of different intensities which travel through the transmission medium to the optical combiner, the transmission medium exhibiting above a threshold an intensity dependent optical scattering and is characterised in that the degree of asymmetry of the splitter and the scattering threshold of the transmission medium are such that the intensity of a signal output from the interferometer is a non-oscillatory function of the intensity of the input signal, said function having at most a single period.

In accordance with a second aspect of the present invention, we provide a method of generating an optical output signal from a single optical input signal, the method comprising

- i) asymmetrically splitting the optical input signal into two portions of different intensities;
- ii) causing the two portions to travel through an optically non-linear transmission medium which exhibits an intensity dependent optical scattering above a threshold; and,
- iii) optically combining the two portions to generate the optical output signal;

wherein the degree of asymmetrical splitting in step (i) and the scattering threshold of the transmission medium are such that the intensity of the optical output signal is a non-oscillatory function of the intensity of the optical input signal, the function having at most a single period.

The intensity dependant optical scattering of the transmission medium causes the intensities of the two portions to be limited to substantially the same intensity after propagating some distance along the transmission medium. This has the effect of flattening the oscillatory output intensity at some point corresponding to a respective input signal intensity. Consequently the output intensity from interferometer will be a substantially constant function of input intensity for at least a significant range of input intensity. This desired output intensity level is therefore less sensitive to the input intensity at this point. In particular, the transmission medium can be chosen to exhibit scattering at an intensity which will produce an output intensity which is a sigmoid response i.e. step-like, to the input intensity.

An embodiment of the invention and its method of operation will now be described by way of example only with reference to the accompanying drawings in which -

Figure 1 is a schematic diagram of a known fibre loop interferometer;

Figure 2 illustrates graphically the variation between the input intensity and output intensity (af-

ter normalisation) for two different coupling ratios of a device as shown in Figure 1;

Figure 3 is a schematic diagram of an experimental arrangement used to measure the non-linear response of the device of Figure 1;

Figure 4 is a graph of the response of the device of Figure 1 as a function of peak input power;

Figure 5 (a) to (c) are graphs of input, reflected and transmitted pulses corresponding to a peak input power of 12.5W from a Q-switched laser; and

Figure 6 is a graph of the transmitted and reflected pulses generated by a mode locked laser input pulse of 15.8W peak power.

The prior art optical device shown in Figure 1 is an interferometer defined by a single silica optical fibre 1 formed into a loop 2 which fibre constitutes the transmission medium. Portions of the optical fibre 1 are positioned close to one another to define a cross-coupler 3 having a pair of first ports 4, 5 and a pair of second ports 6, 7. The coupler 3 is adapted to couple portions of an optical signal received at the ports 6 or 7 into each of the ports 4, 5 in accordance with a pre-determined coupling ratio α . Similarly, optical signals arriving at the coupler 3 received by either the port 4 or port 5 will be coupled by the same coupling ratio into the ports 6, 7.

Thus, under normal (linear) circumstances the device shown in Figure 1 will operate as a mirror. That is with the input E_1 at the port 6, the light all returns back to the port 6 if the coupling ratio is 50:50. Another value for the coupling ratio will give an appropriate split in the output power between the two ports 6, 7. By convention, light exiting at ports 6 and 7 is said to be reflected and transmitted respectively.

The coupler 3 causes a single input E_1 to be split into two counter propagating fields which return in coincidence to combine back at the coupler 3. The optical path length is precisely the same for both propagating fields since they follow the same path but in opposite directions. When operating at intensities in the linear regime the fields will emerge the same, i.e. independent of which way round they traverse the loop; non-linearly this may not be the case as will now be described because the non-linearity can break the identical propagation effect for the two paths.

Consider the situation where the loop 2 of the waveguide is formed at least partly from a non-linear material exhibiting a refractive index n given by the formula:-

$$n = n_0 + n_2 |E|^2$$

where n_0 is the linear refractive index, n_2 is the Kerr co-efficient, and $|E|^2$ is the intensity of the transmitted signal.

In this situation, signal with different intensities when fed in opposite directions around the waveguide will experience different refractive indices. As will be explained below, this results in the signals experienc-

ing different phase shifts so that when the signals return back to the coupling means, they have an intensity dependent relative phase shift. By varying the coupling ratio, α , and/or the length of the waveguide, for example, it is possible to vary the phase shift between the returning signals for any particular working intensity of input signal. The intensity dependence of the relative phase shift results in a device whose output is an oscillatory function of the intensity of the input signal.

For $\alpha \neq 0.5$ the signals propagating in the opposite directions in the loop fibre experience different intensity dependent phase change and the transmittivity, T , is given by

$$T = P_t/P_i = 1 - 2\alpha(1 - \alpha) [1 + \cos(1 - 2\alpha)\phi]$$

where ϕ is the nonlinear phase shift given by

$$\phi = (2\pi/\lambda)n_2 I (P_i/A_{eff})$$

and P_t and P_i are the transmitted and input powers respectively, l is the fibre loop length, λ is the wavelength, n_2 is the optical Kerr coefficient, and A_{eff} is the effective mode area.

The transmittivity shows nonlinear switching behaviour between the low power value, i.e. $1 - 4\alpha(1 - \alpha)$, and 1 whenever P_i increases by

$$\frac{\lambda \alpha A_{eff}}{2(1 - 2\alpha)n_2 L}$$

For silica based fibres $n_2 = 3.2 \times 10^{-16} \text{ cm}^2/\text{Wm}$, and taking $\lambda = 1.06 \mu\text{m}$ and fibre areas $100 \mu\text{m}^2$ then:

$$|E|^2_L = \frac{\pi}{(1 - 2\alpha)} \times 5 \times 10^2$$

For the example of $\alpha = 0.4$ then we need $|E|^2 = 8 \text{ kW}$ for $L = 1 \text{ m}$. If $\alpha = 0.1$ then the required peak power comes down to 1.9 kW but the switching contrast is correspondingly reduced as shown in Figure 2 which shows the variation between input intensity and output intensity (after normalisation) for two different coupling ratios.

It is also known to use other interferometric arrangements to obtain an optical output which is a sinusoidal function of the intensity of an input signal, for example the Mach-Zehnder configuration, although the loop arrangement of Figure 1 has the advantage of automatically ensuring the two propagating paths are identical. Transmission media other than optical fibres can also be employed, for example planar waveguides formed in substrates, or materials included in the optical paths of a bulk optical interferometer.

The applicants have realised that if the transmission exhibits an intensity dependent optical scattering it will act as limiter for the input power and to a first approximation will prevent any further variation in the differential phase shift of the two input signal portions with input signal intensity above a corresponding input intensity threshold. In particular, the material can be selected so that the threshold of the scattering produces a sigmoid response of output intensity as a function of input intensity which provides an optical device whose output is for more stable to small variations of input intensity at the high input intensity

switch state.

In the case of silica optical fibres, spontaneous Raman scattering can be used as the optical scattering mechanism as its threshold can be reduced by changing the fibre dopants. In particular, GeO_2 doping increases the Raman gain co-efficient. The Raman gain co-efficient, g , for GeO_2 doped fibres is related to that for the pure SiO_2 fibres by

$$g = g_0 (1 + 80 \Delta)$$

where

$$\Delta = 1 - (n_w/n_0)$$

and g_0 is the Raman gain co-efficient of pure silica fibre and has a value $7.4 \times 10^{-14} \text{ m/W}$.

Other means for determining the Raman gain threshold can be employed for the purpose of the present invention. For example, polarisation maintaining fibres has a lower threshold power than non-polarisation maintaining fibre of the same materials.

Referring now to Figure 3 a fibre loop mirror constituting an interferometer 31 according to the present invention is coupled to apparatus 33 for investigating the non-linear response of the interferometer 31.

The device 31 is essentially a fibre directional coupler 35 with power-coupling ratio α : $(1-\alpha)$ having its output ports spliced to a British Telecom, high-germanium silica fibre 37 with a Δn of 0.02 and a higher mode cut-off of $1.125 \mu\text{m}$. The fibre was weakly polarisation maintaining with the polarisation holding parameter, h , of $3.2 \times 10^{-3} \text{ m}^{-1}$ at $1.32 \mu\text{m}$. The loop mirror 31 (loop length 25 m) was fabricated by splicing the output arms of length 24 m and 1 m respectively of the directional coupler 35 which had a splitting ratio 38:62. The input port 39 of the mirror was spliced to a port 41 of a second directional coupler 43 which had a splitting ratio of 52:48. In this configuration the outputs from the three other ports 45, 47 and 49 of the coupler 43 can be used to monitor the input power provide a measure of the reflected and transmitted powers of the interferometer 31 respectively.

The nonlinear response of the device was investigated using both Q-switched pulses ($\sim 850 \text{ ns}$ FWHM and 500 Hz repetition rate) and CW mode-locked pulses ($\sim 180 \text{ ps}$ FWHM and 76 MHz repetition rate) of a Nd:YAG laser 61 operating at $1.32 \mu\text{m}$ wavelength. In this device configuration the splices and couplers act as depolarising elements and it is necessary to control the polarisation using mechanical fibre polarisation controllers 51 and 53, at the input of the interferometer 31 and in the loop respectively. However, for a given setting of the polarisation controllers the output of the loop mirror 31 was generally stable for the duration of the experimental measurements (several hours). For the investigation of the nonlinear behaviour of the device 31 the polarisation controllers 51 and 53 were set to give minimum transmission at a lower power. The linear transmittivity was measured to be 0.06 which is the value given by the measured

α . The total insertion loss of the device was measured to be $\sim 3 \text{ dB}$. The input, the reflected and the transmitted signals were monitored using narrow band pass filters (NBFs) 55, collimating lenses 59, and fast In-GaAs photodiodes 57 coupled to the output ports by lenses 59.

All three signals were simultaneously displayed on a three channel EG&G 4420 digital boxcar operating in temporal waveform recovery mode. This measurement approach overcomes any ambiguity due to pulse-to-pulse amplitude fluctuations and the use of NBFs allowed investigation of the behaviour of the loop mirror 31 at power levels above the Raman threshold. The peak input, reflected P_r and transmitted P_t powers of the pulse were measured. These were used to plot the peak reflectivity and transmittivity $P_r/(P_r+P_t)$ as a function of the peak input power and these are displayed in Figure 4. The curves clearly show a nonlinear increase in the transmittivity with a corresponding decrease in the reflectivity and the overall sigmoid response of the output of the interferometer 31. At high input peak powers Stokes radiation was observed due to spontaneous Raman scattering. This has the effect of limiting the available pump power at $1.32 \mu\text{m}$ and hence the device response shows saturation. Significantly, there is a large change in the transmittivity, from 0.06 to 0.6, with the change in input peak power from 0.1 W to 33 W . The crossover point occurs for a peak input power of 22 W . It is anticipated that reductions in power by working with longer loops ($>100 \text{ m}$) would be obtainable but the very good stability observed in the particular device of 31 of Figure 3 would gradually deteriorate.

Referring now to Figure 5 the input (FWHM=850ns), reflected (FWHM=930ns) and transmitted (FWHM=525ns) pulses are shown for a peak input power of 12.5 W are shown. It can be clearly seen that at high power levels the transmitted pulse shows narrowing whilst the reflected pulse shows broadening. This implies that we do not observe complete pulse switching ie. the high power parts of the pulse switch rather than its wings. For this reason the Figure 4 describes the device behaviour for square pulses (pulse duration $\gg$ rise and fall times). The above experiment with the Q-switched pulses is in the quasi-CW regime; where the pulse length ($\sim 175 \text{ ns}$) is long compared to the loop length. In this case the nonlinear phase shift is induced by cross-phase modulation. The experiments with CW mode-locked pulses (FWHM $\sim 180 \text{ ps}$) show a similar nonlinear behaviour. In figure 6 the reflected (FWHM $\sim 195 \text{ ps}$) and transmitted (FWHM $\sim 150 \text{ ps}$) pulses are shown for a peak power of 15.8 W . In this case the pulse length ($\sim 0.04 \text{ ns}$) is much shorter than the loop length and the nonlinear phase shift is induced by self-phase modulation. The above experiments demonstrate that the switching is incomplete for non-square pulses. This has implications for ultra-fast high bit rate systems in

that it is necessary to either produce square optical pulses (non-trivial) or to use "soliton" like pulses which can allow complete switching. For a loop of 25m, as used here, good soliton-switching can be expected for pulse durations of 0.5ps. Such pulses can be obtained for example from the "soliton" laser. Incomplete switching with square pulses due to pump depletion by Raman effect can be avoided by using silica fibres with a lower germania content. For example in our case the Raman gain coefficient is ~ 3x that for a pure silica fibre.

It will be appreciated that the present invention is applicable to configurations of non-linear interferometers other than these specifically described above, and that other intensity dependant optical scattering mechanism other than Raman scattering may be employable to provide the required optical limiting, for example Brillouin scattering.

Claims

1. A non-linear interferometer comprising an asymmetric optical splitter (35), an optically non-linear transmission medium (37) and an optical combiner (35), the optical splitter (35) in use splitting an input signal into two portions of different intensities which travel through the transmission medium to the optical combiner, the transmission medium exhibiting above a threshold an intensity dependent optical scattering, characterised in that the degree of asymmetry of the splitter and the scattering threshold of the transmission medium are such that the intensity of a signal output from the interferometer is a non-oscillatory function of the intensity of the input signal, said function having at most a single period.
2. A non-linear interferometer as claimed in claim 1, wherein the asymmetric optical splitter (35) has a splitting ratio (α) of between 0.38 and 0.5.
3. A non-linear interferometer as claimed in claim 1 or claim 2, wherein the asymmetric optical splitter (35) has a splitting ratio (α) of about 0.4.
4. A non-linear interferometer as claimed in any one of the preceding claims, wherein the transmission medium (37) is a germania doped silica fibre.
5. A non-linear interferometer as claimed in any of the preceding claims, wherein the optical splitter and the optical combiner are provided by a single 2 by 2 coupler (35).
6. A non-linear interferometer as claimed in any one of the preceding claims, wherein the intensity dependent optical scattering of the transmission

medium is Raman scattering.

7. A non-linear interferometer as claimed in claim 6, wherein the Raman gain coefficient of the transmission medium is about 3 times that of pure silica.
8. A non-linear interferometer as claimed in any one of the preceding claims, wherein a narrow band pass filter (55) is provided in the optical output path downstream of the optical combiner (35).
9. A non-linear interferometer as claimed in any one of the preceding claims, optically coupled to a source of optical solitons.
10. A non-linear interferometer as claimed in claim 9, wherein the source of optical solitons produces, in use, solitons having a pulse duration of 0.5 ps.
11. A method of generating an optical output signal from a single optical input signal, the method comprising
 - i) asymmetrically splitting the optical input signal into two portions of different intensities;
 - ii) causing the two portions to travel through an optically non-linear transmission medium (37) which exhibits an intensity dependent optical scattering above a threshold; and,
 - iii) optically combining the two portions to generate the optical output signal;
 wherein the degree of asymmetrical splitting in step (i) and the scattering threshold of the transmission medium are such that the intensity of the optical output signal is a non-oscillatory function of the intensity of the optical input signal, the function having at most a single period.

Patentansprüche

1. Nichtlineares Interferometer mit einer asymmetrischen optischen Weiche (35), einem optischen, nichtlinearen Übertragungsmedium (37) und einem optischen Verknüpfungsglied (35), wobei die verwendete optische Weiche (35) ein Eingangssignal in zwei Teile mit verschiedenen Intensitäten aufteilt, welche sich durch das Übertragungsmedium zu dem optischen Verknüpfungsglied bewegen, wobei das Übertragungsmedium überhalb eines Schwellwerts eine Intensität entwickelt, welche abhängig von der optischen Streuung ist, gekennzeichnet dadurch, daß der Asymmetriebetrag der Weiche und der Streuungsschwellwert des Übertragungsmediums derart gewählt sind, daß die Intensität eines

that it is necessary to either produce square optical pulses (non-trivial) or to use "soliton" like pulses which can allow complete switching. For a loop of 25m, as used here, good soliton-switching can be expected for pulse durations of 0.5ps. Such pulses can be obtained for example from the "soliton" laser. Incomplete switching with square pulses due to pump depletion by Raman effect can be avoided by using silica fibres with a lower germania content. For example in our case the Raman gain coefficient is ~ 3x that for a pure silica fibre.

It will be appreciated that the present invention is applicable to configurations of non-linear interferometers other than these specifically described above, and that other intensity dependant optical scattering mechanism other than Raman scattering may be employable to provide the required optical limiting, for example Brillouin scattering.

Claims

1. A non-linear interferometer comprising an asymmetric optical splitter (35), an optically non-linear transmission medium (37) and an optical combiner (35), the optical splitter (35) in use splitting an input signal into two portions of different intensities which travel through the transmission medium to the optical combiner, the transmission medium exhibiting above a threshold an intensity dependent optical scattering, characterised in that the degree of asymmetry of the splitter and the scattering threshold of the transmission medium are such that the intensity of a signal output from the interferometer is a non-oscillatory function of the intensity of the input signal, said function having at most a single period.
2. A non-linear interferometer as claimed in claim 1, wherein the asymmetric optical splitter (35) has a splitting ratio (α) of between 0.38 and 0.5.
3. A non-linear interferometer as claimed in claim 1 or claim 2, wherein the asymmetric optical splitter (35) has a splitting ratio (α) of about 0.4.
4. A non-linear interferometer as claimed in any one of the preceding claims, wherein the transmission medium (37) is a germania doped silica fibre.
5. A non-linear interferometer as claimed in any one of the preceding claims, wherein the optical splitter and the optical combiner are provided by a single 2 by 2 coupler (35).
6. A non-linear interferometer as claimed in any one of the preceding claims, wherein the intensity dependent optical scattering of the transmission

medium is Raman scattering.

7. A non-linear interferometer as claimed in claim 6, wherein the Raman gain coefficient of the transmission medium is about 3 times that of pure silica.
8. A non-linear interferometer as claimed in any one of the preceding claims, wherein a narrow band pass filter (55) is provided in the optical output path downstream of the optical combiner (35).
9. A non-linear interferometer as claimed in any one of the preceding claims, optically coupled to a source of optical solitons.
10. A non-linear interferometer as claimed in claim 9, wherein the source of optical solitons produces, in use, solitons having a pulse duration of 0.5 ps.
11. A method of generating an optical output signal from a single optical input signal, the method comprising
 - i) asymmetrically splitting the optical input signal into two portions of different intensities;
 - ii) causing the two portions to travel through an optically non-linear transmission medium (37) which exhibits an intensity dependent optical scattering above a threshold; and,
 - iii) optically combining the two portions to generate the optical output signal;
 wherein the degree of asymmetrical splitting in step (i) and the scattering threshold of the transmission medium are such that the intensity of the optical output signal is a non-oscillatory function of the intensity of the optical input signal, the function having at most a single period.

Patentansprüche

1. Nichtlineares Interferometer mit einer asymmetrischen optischen Weiche (35), einem optischen, nichtlinearen Übertragungsmedium (37) und einem optischen Verknüpfungsglied (35), wobei die verwendete optische Weiche (35) ein Eingangssignal in zwei Teile mit verschiedenen Intensitäten aufteilt, welche sich durch das Übertragungsmedium zu dem optischen Verknüpfungsglied bewegen, wobei das Übertragungsmedium überhalb eines Schwellwerts eine Intensität entwickelt, welche abhängig von der optischen Streuung ist, gekennzeichnet dadurch, daß der Asymmetriebetrag der Weiche und der Streuungsschwellwert des Übertragungsmediums derart gewählt sind, daß die Intensität eines



Signalausgangs des Interferometers eine nicht-oszillierende Funktion der Intensität des Eingangssignals ist, wobei die Funktion höchstens eine einzelne Periode aufweist.

2. Nichtlineares Interferometer nach Anspruch 1, in dem die asymmetrische, optische Weiche (35) ein Aufteilungsverhältnis (α) zwischen 0,38 und 0,5 aufweist.
3. Nichtlineares Interferometer nach Anspruch 1 oder 2, in dem die asymmetrische, optische Weiche (35) ein Aufteilungsverhältnis (α) von ungefähr 0,4 aufweist.
4. Nichtlineares Interferometer nach irgendeinem der vorangehenden Ansprüche, in dem das Übertragungsmedium (37) eine mit Germanium dotierte Silicafaser ist.
5. Nichtlineares Interferometer nach irgendeinem der vorangehenden Ansprüche, in dem die optische Weiche und das optische Verknüpfungsglied durch ein einzelnes 2-In-2-Verknüpfungsglied (35) gebildet werden.
6. Nichtlineares Interferometer nach irgendeinem der vorangehenden Ansprüche, in dem die von der Intensität abhängige optische Streuung des Übertragungsmediums eine Raman-Streuung ist.
7. Nichtlineares Interferometer nach Anspruch 6, in dem der Raman-Verstärkungskoeffizient des Übertragungsmediums ungefähr dreimal so groß ist, wie der von reinem Silica.
8. Nichtlineares Interferometer nach irgendeinem der vorangehenden Ansprüche, in dem ein schmaler Bandpaßfilter (55) für den optischen Ausgangspfad stromab des optischen Verknüpfungsglieds (35) vorgesehen ist.
9. Nichtlineares Interferometer nach irgendeinem der vorangehenden Ansprüche, das optisch mit einer Quelle von optischen Solitons gekoppelt ist.
10. Nichtlineares Interferometer nach Anspruch 9, in dem die Quelle der optischen Solitons im Betrieb Solitons mit einer Pulsdauer von 0,5 ps erzeugen.
11. Verfahren zum Erzeugen eines optischen Ausgangssignals aus einem einzelnen optischen Eingangssignal, wobei das Verfahren folgende Schritte aufweist:
 - i) asymmetrisches Aufteilen des optischen Eingangssignals in zwei Teile mit verschiede-

nen Intensitäten,

ii) Verursachen, daß sich die beiden Teile durch ein optisches, nichtlineares Übertragungsmedium (37) bewegen, welches eine Intensitätsabhängige optische Streuung überhalb einem Schwellwert aufweist, und
 iii) optisches Verbinden der beiden Teile zum Erzeugen eines optischen Ausgangssignals, wobei die Stärke der asymmetrischen Aufteilung in Schritt (i) und der Streuungsschwellwert des Übertragungsmediums derart gewählt sind, daß die Intensität des optischen Ausgangssignals eine nichtoszillierende Funktion der Intensität des optischen Eingangssignals ist, wobei die Funktion höchstens eine einzelne Periode aufweist.

Revendications

1. Interféromètre non linéaire comprenant un séparateur optique asymétrique (35), un support de transmission non linéaire optique (37) et un mélangeur optique (35), le séparateur optique (35) séparant, lorsqu'il est utilisé, un signal en entrée en deux parties d'intensités différentes qui parcourent le support de transmission vers le mélangeur optique, le support de transmission présentant au-dessus d'un seuil une dispersion optique dépendant de l'intensité, caractérisé en ce que le degré d'asymétrie du séparateur et le seuil de dispersion du support de transmission sont tels que l'intensité d'une sortie de signal provenant de l'interféromètre est une fonction non oscillatoire de l'intensité du signal d'entrée, ladite fonction présentant au plus une seule période.
2. Interféromètre non linéaire selon la revendication 1, dans lequel le séparateur optique asymétrique (35) présente un rapport de séparation (α) entre 0,38 et 0,5.
3. Interféromètre non linéaire selon la revendication 1 ou la revendication 2, dans lequel le séparateur optique asymétrique (35) présente un rapport de séparation (α) d'environ 0,4.
4. Interféromètre non linéaire selon l'une quelconque des revendications précédentes, dans lequel le support de transmission (37) est une fibre de silice dopée au germanium.
5. Interféromètre non linéaire selon l'une quelconque des revendications précédentes, dans lequel le séparateur optique et le mélangeur optique sont procurés par un seul coupleur 2 par 2 (35).
6. Interféromètre non linéaire selon l'une quelcon-



que des revendications précédentes, dans lequel la dispersion optique dépendant de l'intensité du support de transmission est une dispersion de Raman.

7. Interféromètre non linéaire selon la revendication 6, dans lequel le coefficient de gain de Raman du support de transmission est environ trois fois celui de la silice pure.

5

8. Interféromètre non linéaire selon l'une quelconque des revendications précédentes, dans lequel un filtre passe-bande étroit (55) est procuré dans le trajet de sortie optique en aval du mélangeur optique (35).

10

9. Interféromètre non linéaire selon l'une quelconque des revendications précédentes, couplé optiquement à une source de solitons optiques.

15

10. Interféromètre non linéaire selon la revendication 9, dans lequel la source de solitons optiques produit en utilisation, des solitons présentant une durée d'impulsions de 0,5 ps.

20

11. Procédé de génération d'un signal de sortie optique à partir d'un signal en entrée optique unique, le procédé comprenant

25

i) la séparation asymétrique du signal en entrée optique en deux parties d'intensités différentes,

30

ii) le fait d'amener les deux parties à parcourir un support de transmission non linéaire optique (37) qui présente une dispersion optique dépendant de l'intensité au-dessus d'un seuil, et

35

iii) la combinaison optique des deux parties afin de générer le signal de sortie optique,

dans lequel le degré de séparation asymétrique dans l'étape (i) et le seuil de dispersion du support de transmission sont tels que l'intensité du signal de sortie optique est une fonction non-oscillatoire de l'intensité du signal en entrée optique, la fonction présentant au plus une seule période.

40

45

50

55

7

