

ELECTROMAGNETIC SIGNAL TRANSCIVING APPARATUS

BACKGROUND

1. Technical Field

[0001] The present application relates to an electromagnetic signal transceiving apparatus.

2. Description of the Related Art

[0002] Existing RF electromagnetic wave transceiving apparatuses mainly use conductive materials to form a specific shape and size to transmit or receive an electromagnetic wave of a specific spectrum. The examples are patents or patent applications such as EP0378905A1, US10224630, US7136,021, US6825819, US6580402, US8178457, US7122891, CN101118985, US3866234, US6154176, US6320547, US6650303, US8154464, US6750820, US6195049, US8497804, and US8952858. The signal transceiving performance of such apparatuses may be affected by approximating other dielectric objects or contacting with other dielectric materials and conductive materials in an environment. Thus, in practical applications, problems of spectrum shift and performance attenuation during signal transmission due to different environments. FIG. 3 illustrates the effect of the spectrum shift due to the proximity of a dielectric object in an environment.

SUMMARY

[0003] To address the technical problem of the aforementioned defects of the existing electromagnetic wave transceiving apparatuses, the present application provides an electromagnetic wave transceiving apparatus whose performance of electromagnetic wave transmission is not affected by the contact of dielectric materials.

[0004] According to one objective of the present application, an electromagnetic wave

transceiving apparatus is provided, including a detection and control unit, an electromagnetic exciter, a dielectric adjustment unit, and a positioning unit. Wherein, the detection and control unit is configured for detecting the voltage standing wave ratio or the reflection coefficient. The electromagnetic exciter is connected to the detection and control unit. The detection and control unit is configured to adjust the electromagnetic wave spectrum emitted by the electromagnetic exciter. The electromagnetic exciter is configured to generate and receive electromagnetic waves. The dielectric adjustment unit is connected to the electromagnetic exciter, and the positioning unit is configured to fix the electromagnetic wave transceiving apparatus to a surface of an external dielectric body. When the electromagnetic wave transceiving apparatus is fixedly attached to the surface of the external dielectric body, the electromagnetic exciter, the dielectric adjustment unit and the external dielectric body constitute a resonator with a specific electromagnetic wave spectrum.

[0005] When the electromagnetic wave transceiving apparatus emits an electromagnetic wave, the electromagnetic exciter generates an electromagnetic wave of a first spectrum, and the electromagnetic wave of the first spectrum is transmitted to the dielectric adjustment unit and adjusted as an electromagnetic wave of a second spectrum. The electromagnetic wave of the second spectrum then enters the coupled external dielectric body and propagates to the surface thereof to form an electromagnetic wave of the third spectrum, which is subsequently emitted to the outside. When the electromagnetic wave transceiving apparatus receives an electromagnetic wave, an electromagnetic wave of the third spectrum enters the dielectric adjustment unit from the outside through the coupled external dielectric body, and then gets adjusted as an electromagnetic wave of a second spectrum. The electromagnetic wave of the second spectrum is then transmitted to the electromagnetic exciter and adjusted as an electromagnetic wave of a first spectrum.

[0006] Preferably, the electromagnetic exciter may be a monopole-type, dipole-type, slot-type, spiral-type, or patch-type electromagnetic exciter.

[0007] Preferably, the electromagnetic exciter may be configured for transceiving an electromagnetic wave of at least one spectrum.

[0008] Preferably, the electromagnetic exciter may be configured for adjusting and transceiving an electromagnetic wave of at least one spectrum.

[0009] Preferably, the dielectric adjustment unit may be a dielectric structure with a fixed dielectric constant, the dielectric constant of dielectric adjustment unit may range from 1 to 10000.

[0010] Preferably, the dielectric adjustment unit may be a dielectric structure with of an adjustable dielectric constant, the detection and control unit may be configured to control the dielectric constant of the dielectric adjustment unit, and the value of the dielectric constant thereof may range from 1 to 10000.

[0011] Preferably, the dielectric adjustment unit may be constituted by a plurality of dielectric bodies with different dielectric constants to form a composite dielectric adjustment unit, and the value of an equivalent dielectric constant thereof may range from 1 to 10000.

[0012] Preferable, the dielectric adjustment unit may have a thickness of 0.1 mm to 20 mm.

[0013] Preferable, the value of the dielectric constant of the external dielectric body may range from 1 to 100.

[0014] Preferable, the first spectrum may be the same as the second spectrum or the third spectrum.

[0015] Preferable, the second spectrum may be the same as the third spectrum.

[0016] Preferably, the dielectric adjustment unit may be partially interposed between the electromagnetic exciter and the surface of the coupled external dielectric body.

[0017] Preferably, the dielectric adjustment unit may further include at least one dielectric material layer, a dielectric constant of each layer may be between 1 and 10000.

[0018] Preferably, the dielectric adjustment unit may further include a gap area.

[0019] Preferably, the gap area may be interposed between the dielectric adjustment unit and the surface of the coupled external dielectric body.

[0020] Preferably, the gap area may be disposed inside the dielectric adjustment unit without contacting the surface of the coupled external dielectric body.

[0021] Preferably, the positioning unit may be partially interposed between the dielectric adjustment unit and the surface of the coupled external dielectric body.

[0022] Preferably, the positioning unit may further include at least one dielectric material layer, and the dielectric constant of each layer may be between 1 and 10000.

[0023] Preferably, the positioning unit may further include a gap area.

[0024] According to the electromagnetic signal transceiving apparatus proposed by the present invention, considering the influence of the external dielectric body to which the electromagnetic wave transceiving apparatus is coupled, when the electromagnetic wave transceiving apparatus is coupled to the surface of the external dielectric body, the electromagnetic exciter and the dielectric adjustment unit may be adjusted by the detection and control unit such that the electromagnetic exciter, the dielectric adjustment unit, and the coupled external dielectric body may form a resonator with the required frequency. Therefore, the transmission and reception performance of electromagnetic signals would not be affected by the contacted dielectric material.

BRIEF DESCRIPTION OF THE DRAWINGS

[0025] The present application is further described below together with the accompanying drawings and embodiments, in the accompanying drawings:

[0026] FIG. 1A is a schematic diagram of the electromagnetic wave transceiving apparatus according to an embodiment of the present application.

[0027] FIG. 1B is a schematic diagram of the electromagnetic wave transceiving apparatus of FIG. 1A being coupled to the surface of the external dielectric body.

[0028] FIG. 2 is a structural schematic diagram of a slot-type electromagnetic exciter.

[0029] FIG. 3 is a schematic diagram of an existing electromagnetic wave transceiving apparatus at a working frequency of 2.5 GHz affected by the occurrence of the spectrum shift due to the proximity of the dielectric material in the environment.

[0030] FIG. 4 is an S11 chart of the first spectrum generated by the electromagnetic exciter in the electromagnetic wave transceiving apparatus according to an embodiment of the present application.

[0031] FIG. 5 is an S11 chart of the second spectrum emitted after an adjustment by the dielectric unit in the electromagnetic wave transceiving apparatus according to an embodiment of the present application.

[0032] FIG. 6 is an S11 chart of the third spectrum emitted after the apparatus is coupled with the external dielectric body in the electromagnetic wave transceiving apparatus according to an embodiment of the present application.

[0033] FIG. 7 is an S11 chart of the first to third spectrums in another embodiment with 2.5 GHz as the target frequency.

[0034] Description of the numeral references: 1: detection and control unit; 2: electromagnetic exciter; 3: dielectric adjustment unit; 4: positioning unit; 5: external dielectric body; 20: slot; 21: metal layer; and 22: feed point.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0035] To illustrate of the technical features, contents, advantages, and achievable effects of the present disclosure, the embodiments together with the accompanying drawings are described in detail as follows. However, the drawings are used only for the purpose of indicating and supporting the specification, which is not necessarily in the real proportion

and precise configuration after the implementation of the present disclosure. Therefore, the relations of the proportion and configuration of the accompanying drawings should not be interpreted to limit the actual scope of implementation of the present disclosure.

[0036] Referring FIG. 1A, which is the schematic diagram of the electromagnetic wave transceiving apparatus according to an embodiment of the present application. As illustrated, the electromagnetic wave transceiving apparatus may be used for communication, or for transmitting and receiving electromagnetic waves as a radar. The electromagnetic wave transceiving apparatus of the embodiment includes a detection and control unit 1, an electromagnetic exciter 2, a dielectric adjustment unit 3, and a positioning unit 4. Specifically, the electromagnetic exciter 2 is connected to the detection and control unit 1, the dielectric adjustment unit 3 is connected to the electromagnetic exciter 2, and the positioning unit 4 couples the apparatus with the surface of the external dielectric body. The VSWR (voltage standing wave ratio) bridge equivalent circuit may be utilized by the detection and control unit 1 to detect the voltage standing wave ratio or reflection coefficient to determine whether the apparatus matches the emission spectrum of the electromagnetic wave. The detection and control unit 1 may also be configured to adjust the electromagnetic wave spectrum emitted by the electromagnetic exciter 2. The electromagnetic exciter 2 is configured to generate and receive electromagnetic waves with the required spectrum, and the positioning unit 4 is configured to couple and fix the transceiving apparatus to the surface of the external dielectric body.

[0037] Referring to FIG. 1B, which is a schematic diagram of the electromagnetic wave transceiving apparatus of FIG. 1A being coupled to the surface of the external dielectric body. As illustrated, when the electromagnetic wave transceiving apparatus is attached to the surface of the external dielectric body 5, the electromagnetic exciter 2, the dielectric adjustment unit 3, the positioning unit 4, and the external dielectric body 5 constitute a resonator with a specific electromagnetic wave spectrum. When the electromagnetic wave transceiving apparatus emits an electromagnetic wave, the electromagnetic exciter 2 generates an electromagnetic wave of a first spectrum, and the electromagnetic wave of the

first spectrum is guided to the dielectric adjustment unit 3 and adjusted as an electromagnetic wave of a second spectrum; the electromagnetic wave of the second spectrum is transmitted to the coupled external dielectric body 5 to form an electromagnetic wave of the third spectrum and emitted to the outside.

[0038] Please refer to FIG. 4 to FIG. 6, which are charts illustrating the spectrums of the embodiments with 2.5 GHz as the target working frequency. Specifically, FIG. 4 is a chart of the electromagnetic wave spectrum of the first spectrum emitted by the electromagnetic exciter 2 in an embodiment; FIG. 5 is a chart of the electromagnetic wave spectrum of the second spectrum generated after the electromagnetic wave of the first spectrum is guided to the dielectric adjustment unit 3; FIG. 6 is a chart of the electromagnetic wave spectrum of the third spectrum emitted from the surface of the external dielectric body after the second spectrum electromagnetic wave is guided to the coupled external dielectric body 5, and the electromagnetic wave of the third spectrum is the required working spectrum.

[0039] FIG. 7 is a chart of the spectrums of the first to third spectrum electromagnetic waves with 2.5 GHz as the target frequency in another embodiment. The electromagnetic wave of the third spectrum is transmitted to the dielectric adjustment unit 3 in the apparatus via the external dielectric body 5 coupled by the apparatus and then adjusted as the electromagnetic wave of the second spectrum. The electromagnetic waves of the second spectrum are transmitted to the electromagnetic exciter 2 and adjusted to the electromagnetic waves of the first spectrum for being received.

[0040] In an embodiment of the electromagnetic wave transceiving apparatus of the present disclosure, the detection and control unit 1 may be a VSWR (voltage standing wave ratio) bridge without being limited to the aforementioned circuit that may be configured to detect voltage standing wave ratio or reflection coefficient. The electromagnetic exciter 2 may be a monopole-type, dipole-type, slot-type, spiral-type, or patch-type electromagnetic exciter without being limited to the aforementioned electromagnetic exciter. The electromagnetic exciter may also be other conventional electromagnetic exciters suitable for transceiving

electromagnetic waves. Referring to FIG. 2, which is a structural schematic diagram of a slot-type electromagnetic exciter, wherein numeral reference 20 refers to a slot, numeral reference 21 refers to a metal layer, and numeral reference 22 refers to a feed point. Using the metal layer 21 to shield the slot 20 may adjust the working frequency of the transceiving electromagnetic waves of the electromagnetic exciter 2. The greater the duty cycle of the slot 20 is, the lower the working frequency would be; the smaller the duty cycle is, the higher the working frequency would be. By this method, the frequency of the electromagnetic waves transmitted or received by the electromagnetic exciter 2 may be adjusted.

[0041] In an embodiment of the electromagnetic wave transceiving apparatus of the present disclosure, the dielectric adjustment unit 3 may be a dielectric structure with a fixed dielectric constant, and the value of the dielectric constant thereof may range from 1 to 10000. The dielectric adjustment unit 3 may also be a dielectric structure of an adjustable dielectric constant, the detection and control unit 1 may then be configured to control the dielectric constant of the dielectric adjustment unit 3, and the value of the dielectric constant thereof may range from 1 to 10000. The dielectric adjustment unit 3 may be constituted by a plurality of dielectric bodies with different dielectric constants to form a composite dielectric adjustment unit, and the value of an equivalent dielectric constant thereof may range from 1 to 10000. The following are representative materials that may be used but not limited thereto. The materials may include low dielectric constant materials: PTFE, PE, PC, PVC, acrylic, PU, epoxy, silicone, and the like; medium dielectric constant materials: quartz, glass, aluminum oxide crystals and ceramics, aluminum nitride crystals and ceramics, magnesium oxide crystals and ceramics, silicon carbide crystals and ceramics, zirconia crystals and ceramics, and the like; high dielectric constant materials: titanium oxide crystals and ceramics, barium titanate polymer composites, and the like. The mixture of the dielectric materials with high and low values may be configured to manufacture the materials with the required dielectric constants required by the dielectric adjustment unit 3. The dielectric adjustment unit 3 may have a thickness of 0.1 mm to 20

mm.

[0042] According to the embodiment of the present disclosure, the positioning unit 4 may be, but is not limited to, constituted by at least one dielectric body. It may be configured to connect the apparatus and the surface of the external dielectric body by adopting resin, polymer adhesive, a sucking disk, and a vacuum suction device.

[0043] According to an embodiment of the present disclosure, the value of the dielectric constant of the surface of the external dielectric body 5 is 1 to 100.

[0044] In an embodiment of the present disclosure, the first spectrum may be the same as the second spectrum or the third spectrum. In other embodiments of the present disclosure, the second spectrum may be the same as the third spectrum.

[0045] In the electromagnetic wave transceiving apparatus of the present disclosure, the influence of the external dielectric body to which the electromagnetic wave transceiving apparatus is coupled has been considered, and after the electromagnetic wave transceiving apparatus is coupled to the external dielectric body, the electromagnetic exciter 2 and the dielectric adjustment unit 3 may be adjusted by the detection and control unit 1 such that the composite structure constituted by the electromagnetic exciter 2, the dielectric adjustment unit 3, and the external dielectric body 5 may form a resonator with the required frequency. Therefore, the transmission and reception performance of electromagnetic signals would not be affected by the contacted dielectric material.

[0046] The embodiments of the present application are described above with reference to the accompanying drawings, but the present application is not limited to the aforementioned specific embodiments. The specific implementation as mentioned above is merely indicative rather than restrictive. Under the implication of the present application, a person of ordinary skill in the art can make many forms without departing from the objectives of the present application and the scope of the claims, which all fall within the protection of the present application.

WHAT IS CLAIMED IS:

1. An electromagnetic wave transceiving apparatus, comprising:

a detection and control unit configured to detect a voltage standing wave ratio or a reflection coefficient;

an electromagnetic exciter connected to the detection and control unit, the electromagnetic exciter configured to generate and receive electromagnetic waves, and the detection and control unit being configured to adjust spectrums of the electromagnetic waves generated by the electromagnetic exciter;

a dielectric adjustment unit coupled to the electromagnetic exciter; and

a positioning unit configured to couple and fix the electromagnetic wave transceiving apparatus on a surface of an external dielectric body, and the electromagnetic exciter, the dielectric adjustment unit, and the surface of the external dielectric body constituting a resonator with a specific electromagnetic wave spectrum when the electromagnetic wave transceiving apparatus is coupled to the surface of the external dielectric body;

wherein,

when the electromagnetic wave transceiving apparatus emits the electromagnetic waves, an electromagnetic wave of a first spectrum is generated by the electromagnetic exciter, and the electromagnetic wave of the first spectrum is transmitted to the dielectric adjustment unit and adjusted as an electromagnetic wave of a second spectrum, the electromagnetic wave of the second spectrum then enters the coupled external dielectric body and propagates to the surface of the external dielectric body to form an electromagnetic wave of a third spectrum, and the electromagnetic wave of the third spectrum is then emitted to the outside; and

when the electromagnetic wave transceiving apparatus receives the electromagnetic waves, the electromagnetic wave of the third spectrum enters the dielectric adjustment unit

from the outside through the coupled external dielectric body and gets adjusted as the electromagnetic wave of the second spectrum, and the electromagnetic wave of the second spectrum is then transmitted to the electromagnetic exciter and adjusted as the electromagnetic wave of the first spectrum.

2. The electromagnetic wave transceiving apparatus according to claim 1, wherein the electromagnetic exciter is a monopole-type, dipole-type, slot-type, spiral-type, or patch-type electromagnetic exciter.
3. The electromagnetic wave transceiving apparatus according to claim 1, wherein the electromagnetic exciter is configured to transmit or receive an electromagnetic wave of at least one spectrum.
4. The electromagnetic wave transceiving apparatus according to claim 1, wherein the electromagnetic exciter is configured to adjust and transmit or receive an electromagnetic wave of at least one spectrum.
5. The electromagnetic wave transceiving apparatus according to claim 1, wherein the dielectric adjustment unit is a dielectric structure with a fixed dielectric constant, and a value of the fixed dielectric constant of the dielectric adjustment unit ranges from 1 to 10000.
6. The electromagnetic wave transceiving apparatus according to claim 1, wherein the dielectric adjustment unit is a dielectric structure of an adjustable dielectric constant, the detection and control unit is configured to control the dielectric constant of the dielectric adjustment unit, and a value of the dielectric constant of the dielectric adjustment unit ranges from 1 to 10000.
7. The electromagnetic wave transceiving apparatus according to claim 1, wherein the dielectric adjustment unit is constituted by a plurality of dielectric bodies with different dielectric constants to form a composite dielectric adjustment unit, and a value of an equivalent dielectric constant of the dielectric adjustment unit ranges from 1 to 10000.

8. The electromagnetic wave transceiving apparatus according to claim 1, wherein the dielectric adjustment unit has a thickness of 0.1 mm to 20 mm.
9. The electromagnetic wave transceiving apparatus according to claim 1, wherein a value of a dielectric constant of the external dielectric body ranges from 1 to 100.
10. The electromagnetic wave transceiving apparatus according to claim 1, wherein the first spectrum is the same as the second spectrum or the third spectrum.
11. The electromagnetic wave transceiving apparatus according to claim 1, wherein the second spectrum is the same as the third spectrum.