

"A Semiconductor Memory"

The present invention relates to a semiconductor memory and more particularly to a read only memory (hereinafter referred to as "ROM").

With the recent development in semiconductor techniques and semiconductor device application techniques, there has been an increasing demand for a semiconductor memory which has a large capacity.

10 To obtain a ROM with a large capacity, various problems must be solved.

In a ROM with a large capacity, for example, a large number of memory cells are connected to each of data lines. In consequence, the data line may be
15 undesirably coupled with stray or parasitic capacitance of relatively large value. In the ROM, for example, the content of data stored in a selected memory cell is judged according to whether, after the stray and parasitic capacitances coupled to the data
20 line are precharged, the selected memory cell discharges the electric charge in its capacitance. More specifically, the data in the selected memory cell is judged according to whether, after the potential of the data line is raised to a
25 predetermined value, the selected memory cell causes

the data line potential to be lower than the predetermined value. Since a ROM with a large capacity has data lines undesirably coupled with stray or parasitic capacitance of relatively large value, the selected memory cell requires a comparatively long time to make the data line potential become lower than a predetermined value. As a result, a ROM which has a large capacity requires a relatively long time to read out data from a desired memory cell and this is disadvantageous.

Moreover, in a ROM having a large capacity, the stray or parasitic capacitance coupled to the data lines may have large values. Therefore, it takes a considerably long time from the time when precharging of the capacitances is started until the data line potential reaches a predetermined value. In consequence, a ROM having a large capacity requires a relatively long time from one data output operation to the subsequent data output operation.

It is desirable that the power consumption of the ROM be small from various points of view.

In addition, any defect in memory cells becomes a serious problem particularly in a ROM having a large capacity.

Previously, a circuit has been known from

22

information theory, in which data error is corrected by employing an error correcting code. This circuit will hereinafter be referred to as an "ECC circuit".

5 We have tried to improve the production yield of a semiconductor memory by incorporating an ECC circuit in a one-chip semiconductor memory thereby to redress a defective memory cell.

10 It is an object of the invention to provide a semiconductor memory capable of a high-speed operation, and with relatively low power consumption.

According to the present invention there is provided a semiconductor memory including:

(a) a first memory array including: a plurality of read-only memory cells each having a selection terminal, an
15 output terminal and a reference terminal and arranged in a matrix form; plurality word lines provided to respectively correspond to the rows of said memory cells and respectively coupled to the selection terminals of said plural memory cells; a plurality of data lines provided to respectively
20 correspond to the columns of said memory cells and respectively coupled to the output terminals of said plural memory cells; and a plurality of earth lines provided to respectively correspond to the columns of said memory cells and respectively coupled to the reference terminals of said
25 plural memory cells;

(b) a second memory array having a similar construction to that of the said first memory array;

(c) first and second common data lines;

63

- 4 -

(d) a first column switch controlled by switch control signals in order to couple that one of the plural data lines of said first memory array, which is to be selected to said first common data line;

5 (e) a second column switch controlled by switch control signals corresponding to the first mentioned switch control signals in order to couple that one of the plural data lines of said second memory array, which is to be selected, to said second common data line;

10 (f) a differential amplifier having a pair of input terminals, a first terminal being coupled to said first common data line and a second terminal being coupled to said second common data line;

(g) a plurality of dummy cells provided to respectively correspond to the data lines of said first and second memory arrays and each including: an output terminal to be coupled to the corresponding one of said data lines; a selection terminal to be fed with an operation control signal; and a reference terminal to be fed with earth
15 potential of the circuit, said dummy cells applying the reference potential, which is to be referred to by said differential amplifier, to the corresponding ones of said data lines when they are respectively brought to their operative states; and

25 (h) a selecting circuit including: a plurality of output terminals, which are to be coupled to the word lines of said first and second memory arrays; a plurality of output terminals which are to be coupled to the selection terminals

of said dummy cells,

wherein the reference potential, which is to be referred to by said differential amplifier when one of the memory cells of said first memory array is selected, is generated by that one of said dummy cells, which is coupled to said second memory array, whereas the reference potential, which is to be referred to by said differential amplifier when one of the memory cells of said second memory array, is generated by that one of said dummy cells, which is coupled to said first memory array, and wherein each of said first and second column switches comprises tree-like circuits constituted by a plurality of MOSFETs which are controlled by said switch control signals.

The present invention will now be described in greater detail by way of example with reference to the accompanying drawings, wherein:-

Figure 1 is a block circuit diagram of a preferred form of ROM;

Figures 2A and 2B are detailed circuit diagrams of the blocks M-ARY₁ to M-ARY₄, the blocks D-ARY₁ to D-ARY₄, the blocks CW₁ to CW₄ and the sense amplifier SA shown in Figure 1;

Figure 3 illustrates circuit symbols employed in a MOSFET;

Figure 4 is a logical symbol diagram of an example of an inverter circuit;

Figure 5 is a circuit diagram of an example of an X decoder;

Figure 6 is a graph showing the operations of the circuit shown in Figures 2A and 2B;

Figure 7 is a circuit diagram of an example of a Y decoder Y-DCR₁;

Figure 8 is a circuit diagram of an example of an exclusive OR circuit;

Fig. 9 schematically shows an example of an ECC circuit;

Fig. 10 is a circuit diagram of an example of a multiplexor MPX and an output buffer DOB;

Fig. 11 is a block diagram of an example of an address transition detector ATD and a control signal generator CSG;

Fig. 12 is a circuit diagram of an example of an address buffer ADB;

Fig. 13 is a waveform diagram for explaining the operation of the address transition detector ATD;

Fig. 14 is a circuit diagram of an example of an OR circuit;

Fig. 15 is a circuit diagram of an example of an inverter circuit;

Fig. 16 is a circuit diagram of a Y decoder Y-DCR₂ and an address buffer ADB;

Fig. 17 is a diagram for explaining how data are taken out in a time division manner; and

Fig. 18 is a waveform diagram for explaining the operation of each of the address transition detector ATD, the control signal generator CSG and the ROM shown in Fig. 1.

Referring to Fig. 1, the mask ROM has four memory arrays M-ARY₁ to M-ARY₄ and has a memory capacity of about one megabits as a whole. Each of the memory arrays M-ARY₁ to M-ARY₄ has memory cells

arranged in 512 rows by 608 columns. Accordingly, each of the memory arrays M-ARY₁ to M-ARY₄ has a memory capacity of 311,296 bits.

The circuit blocks shown in Fig. 1 are formed on a single semiconductor substrate by known semiconductor integrated circuit techniques. In addition, the arrangement of essential circuit blocks is drawn in Fig. 1 so as to practically correspond to the actual arrangement thereof on a semiconductor substrate.

Each of the memory arrays M-ARY₁ to M-ARY₄ is constituted by a dynamic circuit and includes a dummy cell array for forming a reference voltage in the readout operation.

An address buffer ADB, for receiving external address signals A₀ to A₁₆ delivered from the outside, is constituted by a static circuit and forms internal address signals a₀, $\overline{a_0}$ to a₁₆, $\overline{a_{16}}$, each pair of the internal address signals being constituted by true and false levels. The address buffer ADB has its operation controlled by a chip selecting signal $\overline{CE}$ delivered from the outside.

The internal address signals a₀, $\overline{a_0}$ to a₉, $\overline{a_9}$ are transmitted to X decoders X-DCR₁ and X-DCR₂, whilst the internal address signals a₁₀, $\overline{a_{10}}$ to a₁₃,

$\overline{a}_{13}$ and a_{15} , $\overline{a}_{15}$ to a_{16} , $\overline{a}_{16}$ are transmitted to Y decoders $Y\text{-DCR}_1$ and $Y\text{-DCR}_2$.

Each of the address decoders $X\text{-DCR}_1$, $X\text{-DCR}_2$, $Y\text{-DCR}_1$ and $Y\text{-DCR}_2$ is formed by a static circuit.

5 To row address selecting lines (word lines) in the memory arrays $M\text{-ARY}_1$ to $M\text{-ARY}_4$, 1,024 (2^{10}) kinds of word line selecting signals are applied which are formed in the X decoders (also serving as word line drivers) $X\text{-DCR}_1$ and $X\text{-DCR}_2$ that receive the internal
10 address signals a_0 , $\overline{a}_0$ to a_9 , $\overline{a}_9$. In these signals, 512 kinds of word line selecting signals formed in the X decoder $X\text{-DCR}_1$ are applied to 512 word lines W_0 to W_{511} , respectively, in the memory arrays $M\text{-ARY}_1$ and $M\text{-ARY}_2$ on the left-hand side. The other 512 kinds of
15 word line selecting signals formed in the X decoder $X\text{-DCR}_2$ are applied to 512 word lines W_{512} to W_{1023} , respectively, in the memory arrays $M\text{-ARY}_3$ and $M\text{-ARY}_4$ on the right-hand side.

Moreover, in accordance with the internal
20 address signals a_9 , $\overline{a}_9$, which are the highest order bits, the X decoders $X\text{-DCR}_1$ and $X\text{-DCR}_2$ form dummy word line selecting signals for selecting dummy cells from dummy arrays $D\text{-ARY}_3$ and $D\text{-ARY}_4$ on the right-hand side when selecting memory cells from the memory arrays
25 $M\text{-ARY}_1$ and $M\text{-ARY}_2$ on the left-hand side, and form

dummy word line selecting signals for selecting dummy cells from dummy arrays D-ARY₁ and D-ARY₂ on the left-hand side when selecting memory cells from the memory arrays M-ARY₃ and M-ARY₄ on the right-hand side.

5 The Y decoder Y-DCR₁ receives the four-bit internal address signals a_{10} , $\overline{a_{10}}$ to a_{13} , $\overline{a_{13}}$ and forms 16 kinds of decoded signals. Each of the memory arrays M-ARY₁ to M-ARY₄ has 608 columns as mentioned above. Consequently, column switches CW₁ and CW₄ are controlled by the decoded signals formed in the address decoder Y-DCR₁ so that 38 columns are simultaneously selected from each memory array in response to one decoded signal. Thereby, the column switches CW₁ and CW₂ output signals delivered from a total of 76 memory cells (or dummy cells) in the memory arrays M-ARY₁ and M-ARY₂ on the left-hand side, whilst the column switches CW₃ and CW₄ output signals delivered from a total of 76 dummy cells (or memory cells) in the memory arrays M-ARY₃ and M-ARY₄ on the right-hand side.

15 A sense amplifier SA which receives the signals from the column switches CW₁ to CW₄ comprises a total of 76 dynamic differential amplifier circuits. The 76 dynamic differential amplifier circuits are divided into 38 sets each formed by two dynamic

25

30

- 11 -

differential amplifier circuits. The respective output signals of the two dynamic differential amplifier circuits of each set are made common to each other through respective transfer insulated-gate field-effect transistors (hereinafter referred to as "MOSFET") and supplied to a circuit (not shown) which is effectively a latching circuit having a data holding function. One of the differential amplifier circuits constituting one set and the transfer MOSFET corresponding thereto have their operations controlled by the internal address signal a_{14} , whilst the operations of the other differential amplifier circuit and the corresponding transfer MOSFET are controlled by the internal address signal $\overline{a_{14}}$. Accordingly, in the readout operation of the ROM, either of the two differential amplifier circuits determine by the internal address signals a_{14} , $\overline{a_{14}}$ operates to supply its output to the circuit (not shown) which is effectively a latching circuit. Consequently, in the readout operation of the ROM, 38 output signals are delivered from the sense amplifier SA.

In the case where 76 memory cells are selected from the memory arrays $M-ARY_1$ and $M-ARY_2$ on the left-hand side in response to the word line selecting signal delivered from the X decoder $X-DCR_1$ and 76

dummy cells are selected from the dummy cell arrays D-ARY₃ and D-ARY₄ on the right-hand side in response to the dummy word line selecting signal delivered from the X decoder X-DCR₂, the respective dynamic

5 differential amplifier circuits receive signals delivered from the memory cells selected and signals delivered from the dummy cells selected which correspond to these memory cells through the column switches CW₁ to CW₄. In these 76 dynamic

10 differential amplifier circuits, 38 dynamic differential amplifier circuits are selected by the internal address signals a_{14} , $\overline{a_{14}}$. Each of the 38 differential amplifier circuits amplifies the potential difference between the signal supplied from

15 the corresponding memory cell and the signal supplied from the dummy cell corresponding thereto. In other words, each of the 38 differential amplifier circuits compares the potential of the signal supplied from the corresponding selected memory cell and the reference

20 voltage of the signal supplied from the dummy cell corresponding to the memory cell in order to detect whether the data stored in the memory cell is a binary signal "1" or "0".

The 38-bit data detected in the sense

25 amplifier SA is transferred to the ECC circuit through

a circuit (not shown) which is effectively a latching circuit. As will be described later with reference to Figs. 2A and 2B, this latching circuit is formed by 38 unit latching circuits. In addition, each unit

5 latching circuit comprises a main amplifier and an inverter and has effectively a latching function. A 32-bit data in the 38-bit data read out is defined as data signals, and the other six-bit data is defined as parity check bits. The ECC circuit corrects error

10 data and outputs the corrected one in the case where the supplied 38-bit data has any error, i.e., data different from what has been written is supplied to the ECC circuit.

The ECC circuit is formed by a static circuit.

15 Moreover, in order to allow a static output signal to be delivered from the ECC circuit, the latching circuit is provided, as described above, which receives the output signal from each dynamic differential amplifier circuit and forms a static

20 output signal and also serves as a main amplifier.

The 32-bit data signals corrected for a possible error by the ECC circuit are transmitted to an output buffer DOB by a multiplexor MPX, eight bits by eight bits, in four stages. For such a time

25 division operation, the external address signals A_{15} ,

A_{16} are employed. Internal address signals $a_{15}, \overline{a_{15}}$ and $a_{16}, \overline{a_{16}}$ formed based on the respective external address signals A_{15} and A_{16} are supplied to the Y decoder $Y-DCR_2$. The Y decoder $Y-DCR_2$ decodes the
5 supplied internal address signals to form four kinds of control signals. The multiplexor MPX is controlled by the four kinds of control signals. Therefore, by simply determining the level of each of the external address signals A_{15} and A_{16} , it is
10 possible to select a desired eight bits from the 32-bit data signals delivered from the ECC circuit and output the same in parallel. Moreover, by properly changing the external address signals A_{15} and A_{16} , it is also possible to output all the 32-bit data
15 signals, eight bits by eight bits, in four stages.

The output buffer DOB is formed by a static circuit and has a tristate output function including a high-output impedance state.

An address transition detector ATD for
20 receiving address signals delivered from the address buffer ADB and a control signal generator CSG are provided in order to form control signals necessary for the operation of each of the dynamic memory arrays $M-ARY_1$ to $M-ARY_4$, the sense amplifier SA, e.g. a
25 timing signal for precharging and a timing signal for

34

- 15 -

discharging. The address transition detector ATD detects the change in level of either one of the internal address signals a_0 to a_{14} and the chip selecting signal $\overline{CE}$ and then forms one trigger pulse.

5 The control signal generator CSG receives the trigger pulse and form various signals necessary for the readout operation of each of the memory arrays and the sense amplifier. In Fig. 1, the following signals are shown as representatives thereof: a timing signal
10 $\overline{\phi_{PC}}$ for controlling the precharging and discharging of the memory arrays and the sense amplifier; a timing signal ϕ_X for regulating the word line selecting timing; and a timing signal ϕ_{PA1} for regulating the activating timing for the sense amplifier SA.

15 The ROM shown in Fig. 1 is employed as a circuit for generating Chinese character patterns in which one character pattern is constituted by 32x32 bits. Accordingly, the ROM is able to store up to 1,024 character patterns.

20 Essential circuit blocks of the ROM will now be described in greater detail.

In the following description, circuit symbols shown in the drawings will be used as illustrated in Fig. 3 in order to simplify the drawings. Referring
25 to Fig. 3, a circuit symbol accompanied by a letter P

denotes an enhancement-mode P-channel MOSFET; a circuit symbol accompanied by a letter N designates an enhancement-mode N-channel MOSFET; and a circuit symbol accompanied by a letter X represents an enhancement-mode N-channel MOSFET which has a threshold voltage made high so as to be in the OFF state at all times.

The memory arrays M-ARY₁ to M-ARY₄ and the sense amplifier SA are shown in greater detail in Figs. 2A and 2B. Each circuit is constituted by a CMOS (complementary MOS) circuit composed of a P-channel MOSFET and an N-channel MOSFET.

Figs. 2A and 2B show detailed circuits of the memory arrays arranged on the right-hand side of the sense amplifier SA in Fig. 1, for example, the memory arrays M-ARY₃ and M-ARY₄. Accordingly, 512 word lines, i.e. the word lines W₅₁₂ to W₁₀₂₃, are formed from the top to the bottom. These word lines are employed for the memory arrays M-ARY₃ and M-ARY₄ in common.

The memory arrays M-ARY₁ and M-ARY₂ shown by blocks have practically the same constructions as those of the memory arrays M-ARY₃ and M-ARY₄. Accordingly, similar to the memory arrays M-ARY₃ and M-ARY₄, 512 word lines, i.e. the word lines W₀ to

W_{511} , are formed in the left-hand side memory arrays $M-ARY_1$ and $M-ARY_2$ shown by blocks.

The memory arrays and the dummy arrays have earth lines G and data lines DL alternately arranged from right to left. An earth line G_0 is formed as the first line, and a data line DL_0 is formed as the second line. Then, in the similar manner, the earth lines and the data lines are alternately arranged: an earth line G_1 is placed next to the data line DL_0 , and a data line DL_1 is placed next to the earth line G_1 .

Storage MOSFETs (memory cells) M_0 to M_6 are formed at the respective intersections between the word lines and the data lines.

Each storage MOSFET is an N-channel device and has its gate connected to the corresponding word line and its drain connected to the corresponding data line and moreover its source connected to the corresponding earth line. Accordingly, except for the earth line G_0 at an end, one data line DL_0 has the drains of different storage MOSFETs M_0 and M_1 , on the same word line W_{512} , connected thereto in common, whilst the earth line G_1 has the sources of different storage MOSFETs M_1 and M_2 , on the same word line W_{512} , connected thereto in common. These earth and data lines are constructed of the semiconductor regions

which are integrally formed with the semiconductor regions constituting the sources and drains of the memory MOSFETs, respectively. Thus, it becomes unnecessary to specially form contact regions for electrically connecting, for example, the data lines and the drains of the memory MOSFETs. Accordingly, it is possible to increase the integration degree of the memory arrays. Each of these memory MOSFETs has its threshold voltage predetermined in response to the information "1" or "0".

As shown, eight data lines are connected to one input/output terminal of a single dynamic differential amplifier circuit through a plurality of switching MOSFETs. Therefore, it can be considered that a single memory array is constituted by a plurality of memory cells connected to the eight data lines, a plurality of precharging MOSFETs, described later, provided in relation to the eight data lines, and a plurality of discharging MOSFETs. It can also be considered that in correspondence to the unit memory array, a single unit dummy cell array is constituted by a plurality of dummy cells connected to the eight data lines. Moreover, it can be considered that a unit column switch is constituted by a plurality of switching MOSFETs provided between the

eight data lines and the dynamic differential amplifier circuit.

Each data line is mutually used by the memory cells formed on the upper side (as viewed in the Figure) thereof and the memory cells formed on the lower side thereof. Accordingly, a single memory array has 304 data lines. In consequence, a single memory array is formed by 38 memory arrays and 38 dummy cell arrays. In correspondence thereto, a single column switch is formed by 38 column switches. Therefore, the memory arrays $M-ARY_1$ to $M-ARY_4$ are constituted by 152 memory arrays and 152 dummy cell arrays. The column switches CW_1 and CW_4 are formed by 152 column switches.

The memory arrays have substantially the same construction, also the dummy cell arrays have substantially the same construction, and moreover, the column switches have substantially the same construction.

Each dynamic differential amplifier circuit is provided between a column switch CWC_0 , a dummy cell array DS_0 and a memory array MS_0 on one hand and a column switch $\overline{CWC_0}$, a dummy cell array $\overline{DS_0}$ and a memory array $\overline{MS_0}$ which correspond to the former switch and arrays respectively on the other. Since there

are 76 dynamic differential amplifier circuits, there are 76 sets each formed as described above.

For the sake of clarity, the drawing shows only 38 sets in the 76 sets: namely, 38 dynamic differential amplifier circuits, the operation of which are controlled by the internal address signal a_{14} ; 76 column switches CWC_0 to CWC_{37} and $\overline{CWC_0}$ to $\overline{CWC_{37}}$ connected to the input/output terminals of the dynamic differential amplifier circuits; 76 memory arrays MS_0 to MS_{37} and $\overline{MS_0}$ to $\overline{MS_{37}}$; and 76 dummy cell arrays DS_0 to DS_{37} and $\overline{DS_0}$ to $\overline{DS_{37}}$.

Reference symbols PD_0 to PD_{37} and $\overline{PD_0}$ to $\overline{PD_{37}}$ denote precharging and discharging circuits respectively. Each precharging and discharging circuit is formed by a plurality of precharging MOSFETs and a plurality of discharging MOSFETs provided in relation to the eight data lines.

The eight data lines DL_0 to DL_7 are made common to each other through P-channel MOSFETs S_0 to S_{11} constituting a column switch and are connected to one input terminal of the sense amplifier SA_0 . The column switch is formed by a series-circuit consisting of the MOSFETs S_8 to S_{11} which select four data lines and the MOSFETs S_0 to S_7 which select two data lines for each. In other words, the column switch is formed

by a plurality of tree-like circuits. For example, if the MOSFETs S_8 and S_0 are turned ON, then the data line DL_0 is selected. Thus, the column switches have the function of decoding column addresses. It is thus possible to reduce the number of wires required for connecting the address buffer ADB and the address decoder Y-DCR₁, so that the IC chip can be reduced in size.

Each of the earth lines and the data lines is provided with a precharging MOSFET for receiving the precharging signal $\overline{\phi_{PC}}$ delivered from the control signal generator CSG in order to precharge the stray and parasitic capacitances connected thereto. As shown, precharging P-channel MOSFETs P_0 to P_8 are provided between the respective earth and data lines and the power source voltage V_{CC} for receiving the precharging signal $\overline{\phi_{PC}}$.

Moreover, a discharging MOSFET is provided between each earth line and earth potential of the circuit. Discharging N-channel MOSFETs D_0 to D_4 are provided between the earth lines G_0 to G_4 , shown as representatives, and earth potential, respectively. To the gates of the respective discharging MOSFETs D_0 to D_4 , eight selecting signals ϕ_{S0} to ϕ_{S7} formed by decoding the column address signals are applied in

synchronism with the timing signal ϕ_S , respectively, the timing signal ϕ_S being formed in the control signal generator CGS shown in Fig. 1.

The plurality of precharging MOSFETs and the plurality of discharging MOSFETs constitute the above-described precharging and discharging circuit PDS₀.

When the timing signal ϕ_S is brought into the high level state from the low level state, the eight selecting signals ϕ_{S0} to ϕ_{S7} are applied to the corresponding discharging N-channel MOSFETs. At this time, in the eight selecting signals ϕ_{S0} to ϕ_{S7} only one selecting signal corresponding to the column address signals is made high, and the other seven selecting signals are made low.

Consequently, one discharging MOSFET is selected from the discharging MOSFETs D₀ to D₈ in each of the precharging and discharging circuits PD₀ to PD₃₇ and $\overline{PD_0}$ to $\overline{PD_{37}}$ and is turned ON. At this time, the other discharging MOSFETs are held OFF.

The selection of the memory cell M₁ will now be described in greater detail.

After each of the data and earth lines is precharged, the output signal delivered from the Y decoder Y-DCR₁ causes the MOSFETs S₀ and S₈ to turn ON and other MOSFETs S₁, S₃, S₅, S₇ and S₉ to S₁₁ to turn

OFF. On the other hand, the selecting signal ϕ_{S1} causes the discharging MOSFET D_1 to turn ON and the other discharging MOSFETs to turn OFF. Consequently, one input node of the unit sense amplifier SA_0 and the data line DL_0 are electrically connected together. Moreover, the electric charge stored in the stray and parasitic capacitances connected to the earth line G_1 is discharged through the discharging MOSFET D_1 . Thus, the earth line G_1 is selected, and the potential thereof is brought to the earth potential of the circuit.

In the ROM, one data line, e.g. the data line DL_1 , is mutually used by the memory cells formed on the upper side thereof and the memory cells formed on the lower side thereof.

In the case where one of the memory cells formed on the lower side of data line DL_0 , i.e. one of the memory cells provided between the data line DL_0 and the earth line G_1 is selected, the discharging MOSFET D_1 is turned ON by the selecting signal ϕ_{S1} , and the earth line G_1 is selected. Thereby, the plurality of memory cells provided between the data line DL_0 and the earth line G_1 are made selectable. When the desired word line W_{512} is brought to a selection level, e.g. the high level, by the output

signal from the X decoder $X\text{-DCR}_2$, the memory cell M_1 is selected from the plurality of memory cells on the lower side of the data line DL_0 . The potential of the data line DL_0 changes in accordance with the data stored in the selected memory cell M_1 . Thus, a signal in accordance with the data stored in the selected memory cell M_1 is transmitted to one input/output terminal of the sense amplifier SA_0 .

In the case where one of the memory cells formed on the upper side of the data line DL_0 , i.e. one of the memory cells formed between the data line DL_0 and the earth line G_0 , e.g. the memory cell M_0 , is selected, the discharging MOSFET D_0 is turned ON by the selecting signal ϕ_{S0} and the earth line G_0 is selected, thereby allowing the memory cell M_0 to be selected in the same manner as in the case described above.

In the ROM, two MOSFETs constituting a dummy cell are provided in series between each data line and the corresponding earth line.

More specifically, with respect to the data line DL_0 , MOSFETs DC_{01} and DC_{02} constituting a dummy cell are provided between the data line DL_0 and one earth line G_0 corresponding thereto, and MOSFETs DC_{03} and DC_{04} constituting a dummy cell are provided

between the data line DL_0 and the other earth line G_1 corresponding thereto.

Series MOSFETs constituting a dummy cell, e.g. the MOSFETs DC_{01} and DC_{02} , are MOSFETs having the same size as the memory MOSFETs and are formed simultaneously with the memory MOSFETs having a low threshold voltage. Moreover, these MOSFETs have the same construction.

The following is a description of a dummy cell selecting operation. In the selection of a dummy cell, the following signals are employed: the highest order address signal A_9 in the external row address signals, and the lowest order signal A_{10} in the column address signals used in forming the selecting signals ϕ_{S0} to ϕ_{S7} , as described above. More specifically, the highest order external address signal A_9 is used to determine whether a dummy cell should be selected from the dummy arrays on the right-hand side or left-hand side. The lowest order external address signal A_{10} is used to determine whether a dummy cell should be selected from the dummy arrays formed on the upper side or lower side of a data line. The lowest order external address signal A_{10} , in the selecting signals ϕ_{S0} to ϕ_{S7} , is an address signal to determine whether the discharging MOSFETs connected to the earth line on

the upper side of a data line should be turned ON or the discharging MOSFETs connected to the earth line on the lower side of the data line should be turned ON.

In practice, the two address signals and the word line selecting timing signal ϕ_X are decoded to form four kinds of dummy word line driving signals ϕ_{a0} , ϕ_{a1} , $\overline{\phi_{a0}}$, $\overline{\phi_{a1}}$.

The selecting operation of a dummy cell constituted by the MOSFETs DC_{03} and DC_{04} , will now be described in greater detail.

Each of the data and earth lines is precharged in the same manner as in the case of the above-described memory cell selecting operation. The MOSFETs S_0 and S_8 are turned ON by the output signal from the Y decoder $Y-DCR_1$, and the discharging MOSFET D_1 is turned ON by the selecting signal ϕ_{S1} to select the earth line G_1 . Thereby, the data line DL_0 is electrically connected to the input terminal of the unit sense amplifier SA_0 , and the potential of the earth line G_1 is brought to earth potential. When the selecting signal ϕ_{a1} is brought to a selection level, e.g. the high level, in order to select the above-mentioned dummy cell, the MOSFETs DC_{03} and DC_{04} are turned ON.

As described above, each of the MOSFETs

46

constituting a dummy cell is a MOSFET having the same size as the memory MOSFETs and formed simultaneously with the memory MOSFETs having a low threshold voltage and moreover has the same construction as those MOSFETs. Thus, the conductance of a dummy cell measured when it is selected, i.e. the combined conductance of the MOSFETs DC_{03} and DC_{04} in the ON state, is a value substantially half the conductance of a memory MOSFET arranged to have a low threshold voltage measured when it is selected. A memory MOSFET arranged to have a high threshold voltage remains substantially OFF whether it is being selected or not. Accordingly, the conductance of the dummy cell is larger than the conductance of the memory MOSFET arranged to have a high threshold voltage measured when it is selected. In other words, the conductance of the dummy cell is an intermediate value between the conductance of the memory MOSFET having a low threshold voltage and that of the memory MOSFET having a high threshold voltage.

The electric charge stored in the stray and parasitic capacitances of the data line by precharging is discharged in accordance with the conductance of the selected dummy cell. in other words, the potential of the data line DL_1 gradually lowers in

accordance with the conductance of the dummy cell.

Accordingly, the potential of a data line measured when a dummy cell connected thereto is selected is an intermediate value between the potential of a data line measured when a memory MOSFET having a low threshold voltage and connected thereto is selected and the potential of the data line measured when a memory MOSFET having a high threshold voltage and connected thereto is selected.

10 In the readout operation, when a memory cell is selected from the unit memory array MS_0 on the right-hand side of the unit sense amplifier SA_0 , the dummy cell corresponding to the above memory cell is selected from the unit dummy cell array $\overline{DS}_0$ on the

15 left-hand side of the unit sense amplifier SA_0 . For instance, when the memory cell M_1 is selected from the unit memory array MS_0 , a dummy cell connected to the data line $\overline{DL}_0$ corresponding to the data line DL_0 is selected in the unit dummy cell array $\overline{DS}_0$ on the left-

20 hand side of the unit sense amplifier SA_0 . More specifically, in the unit dummy cell array $\overline{DS}_0$ on the left-hand side of the unit sense amplifier SA_0 , a dummy cell is selected which is provided between the earth line connected with the discharging MOSFETs

25 adapted to turn ON in response to the selecting signal

ϕ_{S0} and the data line $\overline{DL_0}$.

The potential of the data line DL_0 becomes a value in accordance with the data stored in the selected memory cell and is transmitted to one input terminal of the unit sense amplifier SA_0 . On the other hand, the potential of the data line $\overline{DL_0}$ becomes a value in accordance with the conductance of the selected dummy cell, i.e. the reference potential, and is transmitted to the other input terminal of the unit sense amplifier SA_0 .

In the ROM, a compensating circuit is provided to each dummy word line in order to prevent malfunction. The compensating circuit is constituted by two MOSFETs arranged to have a high threshold voltage. More specifically, two MOSFETs are series-connected between a data line and the corresponding earth line, and the gate of each MOSFET is connected to the corresponding dummy word line. With respect to the data line DL_0 , MOSFETs DD_{01} and DD_{02} having a high threshold voltage and constituting a compensating circuit are series-connected between the data line DL_0 and one earth line G_0 corresponding thereto, and MOSFETs DD_{03} and DD_{04} having a high threshold voltage and constituting a compensating circuit are series-connected between the data line DL_0 and the other

earth line G_1 corresponding thereto.

The other data lines and the data lines on the left-hand side of the sense amplifier SA_0 are similarly provided with respective compensating circuits. Each of the MOSFETs constituting a compensating circuit is arranged to have a high threshold voltage as mentioned above so that the MOSFET will not be turned ON even if a selecting signal is applied to the dummy word line connected to the gate thereof. The MOSFETs constituting each compensating circuit are formed simultaneously with the memory MOSFETs.

The dummy cells provided on the upper side of a data line are connected to the dummy word line to which the compensating circuits provided on the lower side of the data line are connected, whilst the dummy cells provided on the lower side of a data line are connected to the dummy word line to which the compensating circuits provided on the upper side of the data line are connected.

With respect to the data line DL_0 , the gate electrodes of the respective MOSFETs DC_{01} and DC_{02} constituting a dummy cell are connected to their corresponding dummy word lines DW_{11} and DW_{12} respectively, and the gate electrodes of the

50

respective MOSFETs DD_{03} and DD_{04} constituting a compensating circuit are also connected to their corresponding dummy word lines DW_{11} and DW_{12} . In the same manner, the gate electrodes of the respective MOSFETs DC_{03} and DC_{04} constituting a dummy cell and those of the MOSFETs DD_{01} and DD_{02} constituting a compensating circuit are connected to their corresponding dummy word lines DW_{21} and DW_{22} .

Thus, between a data line and the earth line corresponding thereto, one MOSFET is connected to one dummy word line in the same manner as one word line. Accordingly, the total number of the MOSFETs connected to one word line equals that of the MOSFETs connected to one dummy word line. These MOSFETs are formed simultaneously. Thereby, these MOSFETs have gate insulating films equal to each other in film thickness and dielectric constant. Moreover, these MOSFETs have substantially the same overlapping amount between each gate electrode and the corresponding source region and that between each gate electrode and the corresponding drain region. Consequently, these MOSFETs have substantially the same value in the MOSFET capacitance comprising the capacitance formed between each gate electrode and the corresponding source region, the capacitance formed between each

gate electrode and the corresponding drain region, and other capacitances. Therefore, equalizing the total number of MOSFETs connected permits the value of capacitances connected to a dummy word line and that of capacitances connected to a word line to be substantially equal to each other.

It is possible to make the value of the capacitance of a dummy word line constituted by the capacitances of the respective MOSFETs connected thereto and that of the capacitance of a word line constituted by the capacitances of the respective MOSFETs similarly connected thereto substantially equal to each other. In other words, it is possible to make the value of the capacitance of a dummy word line which is to be a load capacitance with respect to the X decoder (driver) and that of the capacitance of a word line which is to be a load capacitance with respect to the X decoder (driver) substantially equal to each other. When applying an output signal to a word line, the X decoder applies an output signal to the corresponding dummy word line substantially simultaneously.

Accordingly, it is possible to make the change in potential of a word line when it is rising to the selection level in response to the output signal from

the X decoder and the change in potential of the corresponding dummy word line when it is rising to the selection level in response to the output signal from the X decoder substantially equal to each other.

5 It is also possible to make the voltage applied to the gate of the memory MOSFET to be selected and the voltage applied to the gate of the MOSFET of the dummy cell to be selected substantially equal to each other at all times. Consequently, the
10 conductance of the selected dummy cell becomes an intermediate value between the conductance of the selected memory MOSFET having a load threshold voltage and the conductance of the selected memory MOSFET having a high threshold voltage. In other words, in
15 the readout operation of the ROM, the potential of a data line measured when a dummy cell connected thereto is selected will never be lower than the potential of a data line measured when a memory MOSFET having a low threshold voltage and connected thereto is selected or
20 higher than the potential of a data line measured when a memory MOSFET having a high threshold voltage and connected thereto is selected. Accordingly, it is possible to prevent malfunction.

 The above-described discharging MOSFETs D_0 to
25 D_4 prevent wasteful consumption of current by

prohibiting discharging of the capacitances of the respective data and earth lines not selected. The size of each of these MOSFETs D_0 to D_4 is such that the conductance of the MOSFET measured when it is ON is sufficiently larger than that of a memory MOSFET measured when it is ON.

10 Thereby, the time constant in discharging the electric charge stored in the stray or parasitic capacitance connected to a data line is substantially determined by the capacitances and the conductance of a storage MOSFET measured when it is in the selected state, or substantially by the capacitances and the conductance of a dummy cell measured when it is in the selected state, i.e. the combined conductance of the two MOSFETs connected in series.

The MOSFETs constituting each dummy cell are formed simultaneously with the memory MOSFETs. Therefore, the ROM manufacturing process will not be more complicated. Moreover, by the simultaneous formation, if there should be any change in characteristics, e.g. conductance of memory MOSFETs owing to manufacturing condition variations, the MOSFETs constituting the dummy cells have the same change in their characteristics. Therefore, it is possible to make the conductance of each dummy cell substantially half the conductance of a memory MOSFET having a low threshold voltage which turns ON when selected, independently of variations in manufacturing conditions. Accordingly, it is possible to manufacture a memory with a high production yield.

The writing of data into each memory MOSFET is effected by implanting impurity ions into a region for forming the channel of the memory MOSFET. More specifically, the threshold voltage of a memory MOSFET is determined by the impurity ion implantation. For example, into a region for forming the channel of a memory MOSFET required to have a high threshold voltage, impurity ions having a conductivity type opposite to that of the channel are implanted. The region for forming the channel of a memory MOSFET

required to have a low threshold voltage is not subjected to the ion implantation for shifting the threshold voltage. As a result, it is possible to write a binary signal "1" or "0" into a memory MOSFET.

5 In this case, the threshold voltage of a memory MOSFET determined by the ion implantation is made to correspond to the binary signal "1", whilst the low threshold voltage of a storage MOSFET not subjected to the ion implantation is made to correspond to the
10 binary signal "0".

The readout operation is effected by detecting whether a memory MOSFET selected is substantially turned ON or OFF by the voltage applied between the gate and source thereof. In other words, the readout
15 operation corresponds to the detection of whether the conductance of the selected memory MOSFET is large or small. The reference used for the detection of the size of the conductance is given by the dummy cell.

An example of a method of manufacturing MOSFETs
20 used in the ROM will now be described in greater detail.

A gate insulating film is formed on a semiconductor substrate (or well region), and a polycrystalline silicon layer is formed thereon.
25 Then, the polycrystalline silicon layer is etched so as

to form a gate electrode. With the polycrystalline silicon layer constituting the gate electrode used as a mask, a source region and a drain region are formed on the semiconductor substrate (or well region). The
5 source and drain regions are formed in a self-aligning manner using as a mask the polycrystalline silicon layer constituting the gate electrode.

A heat treatment is carried out in order to form an interlayer insulating film. The heat
10 treatment undesirably causes diffusion of the source and drain regions formed on the semiconductor substrate (or well region). Thereby, the gate electrode and the source region, and the gate electrode and the drain region are undesirably overlapped with each other,
-15 respectively. Consequently, the MOSFET has capacitances such as the capacitance formed between the gate electrode and the source region and that formed between the gate electrode and the drain region,

The memory MOSFETs, the MOSFETs constituting
20 the dummy cells and the MOSFETs constituting the compensating circuits are simultaneously formed by the manufacturing technique described above. Moreover, if necessary, the channel forming region of the MOSFET is subjected to the ion implantation for shifting the
25 threshold voltage as described above.

The sense amplifier SA_0 is constituted by a single dynamic differential amplifier circuit for receiving a signal delivered from the unit memory array MS_0 or $\overline{MS_0}$ and a reference signal delivered from the unit dummy cell array $\overline{DS_0}$ or DS_0 .

The dynamic differential amplifier circuit is constituted by P-channel MOSFETs Q_1 , Q_2 and N-channel MOSFETs Q_3 , Q_4 , Q_6 . A latching circuit is constituted by two CMOS inverters each composed of the P-channel MOSFET Q_1 (Q_2) and the N-channel MOSFET Q_3 (Q_4), and the N-channel MOSFET Q_6 as a power switch is provided between the sources of the MOSFET Q_3 and Q_4 and earth to form a dynamic circuit. As will be described later in detail, in order to precharge, in a short period of time, the stray or parasitic capacitance connected to a data line, precharging of a data line is also effected from the sense amplifier side. For this purpose, the sense amplifier is provided with the P-channel MOSFET Q_5 , which is provided between the electrode of the respective MOSFETs Q_3 and Q_4 serving as sources in the ordinary operating state and the supply voltage V_{CC} . A timing signal formed on the basis of the timing signal ϕ_{PA1} for controlling the operation of the sense amplifier and the internal address signal a_{14} is applied to the gates of the respective MOSFETs Q_5 and

Q₆. The signal applied is a timing signal formed by combining the timing signal ϕ_{PA1} and the internal address signal a_{14} .

The output signal from the sense amplifier SA₀ is transmitted to the input/output terminal of the main amplifier in the latching circuit MA₀ via the transfer N-channel MOSFETs Q₈ and Q₉. A timing signal based on a timing signal ϕ_{PA2} and the internal address signal a_{14} is applied to the gates of the respective transfer MOSFETs Q₈ and Q₉. A timing signal formed by combining the timing signal ϕ_{PA2} and the internal address signal a_{14} is applied to the gates of the respective transfer MOSFETs Q₈ and Q₉.

One sense amplifier (not shown) is supplied with a timing signal based on the timing signal ϕ_{PA1} and the internal address signal $\overline{a_{14}}$, and the output signal therefrom is transmitted to the input/output terminal of the main amplifier in the latching circuit MA₀ via a pair of transfer MOSFETs (not shown). The timing signal based on the timing signal ϕ_{PA2} and the internal address signal $\overline{a_{14}}$ is applied to the gates of the pair of transfer MOSFETs.

Thus, in the two sense amplifiers, only the sense amplifier selected by the external address signal a_{14} is supplied with the timing signal ϕ_{PA1} for

activating the sense amplifier. In addition, only the output signal of this selected sense amplifier is transmitted to the main amplifier via the transfer MOSFETs controlled by the timing signal ϕ_{PA2} . In the two sense amplifiers, only the sense amplifier selected by the external address signal A_{14} operates, and the output signal therefrom is supplied to the main amplifier. Therefore, in the 76 sense amplifiers, only 38 sense amplifiers operate in the readout operation. Accordingly, there are provided only 38 latching circuits each including a main amplifier.

For the sake of clarity, it is assumed that each sense amplifier is supplied with the timing signal ϕ_{PA1} , and the transfer MOSFETs provided between the sense amplifier and the main amplifier are supplied with the timing signal ϕ_{PA2} . In other words, what is illustrated is an imaginary state where the unit sense amplifier and the transfer MOSFETs have been selected by the external address signal A_{14} . In addition, the following description will be given on the assumption that this imaginary state is maintained.

Fig. 6 shows the changes with time of the potentials V_D and $\overline{V_D}$ of the pair of data lines DL_0 and $\overline{DL_0}$ selected from the unit memory array MS_0 and the unit dummy cell array $\overline{DS_0}$ shown in Figs. 2A and 2B.

In Fig. 6, a broken line represents the change in potential of the data line $\overline{DL}_0$ connected with the dummy cells. On the other hand, a one-dot-and-dash line represents the change in potential of the data line DL_0 when data "0" is being written into a memory MOSFET, whilst a two-dot-and-dash line represents the change in potential of the data line DL_0 when data "1" is being written into a memory MOSFET.

Each memory MOSFET has a conductance which is determined in accordance with the data stored therein as described above. Therefore, the electric charge in the data line DL_0 precharged beforehand is started to be discharged in accordance with the data stored in a memory MOSFET when the same is selected.

A dummy cell selected simultaneously with the selection of the corresponding memory MOSFET has, as described above, an intermediate conductance between the conductance of a memory MOSFET storing data "1" and that of a memory MOSFET storing data "0". Therefore, the electric charge in the data line $\overline{DL}_0$ precharged beforehand starts to become discharged in accordance with the conductance of a dummy cell when the same is selected.

Accordingly, the potentials of the respective data lines DL_0 and $\overline{DL}_0$ change as shown.

The sense amplifier SA_0 amplifies the voltage difference between the pair of data lines and transmits the amplified voltage difference to the main amplifier in the unit latching circuit MA_0 .

5 As shown in Figs. 2A and 2B, a P-channel MOSFET Q_7 for short-circuiting is provided between a pair of input/output terminals of the sense amplifier. The short-circuiting MOSFET Q_7 is held ON while the data line is being precharged, by the timing signal $\overline{\phi}_{PC}$.

10 As will be described later in detail with reference to Fig. 7, the MOSFETs constituting each unit column switch are all held ON during the precharging period by output signals $y_0, y_1, \text{ and } y_{00} \text{ to } y_{11}$ delivered from the Y decoder $Y-DCR_2$. Accordingly, the following data lines are electrically connected to each other: a data line connecting one input/output terminal of the sense amplifier and the column switch CWC_0 , i.e. a common data line; a common data line connecting the other input/output terminal of the sense amplifier and the column switch $\overline{CWC_0}$; each of the data lines formed in the memory array MS_0 and the dummy cell array DS_0 ; and each of the data lines formed in the memory array $\overline{MS_0}$ and the dummy cell array $\overline{DS_0}$. Therefore, the potentials of the respective data and common data lines
25 precharged can be made substantially equal to each

other. As a result, it is possible to improve the operating speed of the ROM.

In the case where the data line DL_0 formed on the right-hand side of the sense amplifier SA_0 and the data line $\overline{DL}_0$ formed on the left-hand side thereof are made different in potential from each other by the precharging operation, for example, when the potential of the data line DL_0 is made higher than that of the data line $\overline{DL}_0$ by the precharging operation, the readout operation of the ROM is retarded as follows.

For instance, in the case where a memory MOSFET is selected which stores data "1" and has its drain connected to the data line DL_0 , the potential of the data line DL_0 starts to lower from a value higher than the potential of the data line $\overline{DL}_0$. In consequence, a relatively long time is required until the potential of the data line DL_0 becomes lower than the potential of the data line $\overline{DL}_0$ having the selected dummy cell connected thereto. Accordingly, in order to accurately read out data from a memory MOSFET, it is necessary to set a relatively long time from the time when the memory MOSFET and the corresponding dummy cell are selected until the corresponding unit sense amplifier is actuated. As a result, the speed of operation of the ROM is reduced.

The provision of the short-circuiting MOSFETs permits the potentials of the precharged pair of data lines DL_0 and $\overline{DL}_0$ to be substantially equal to each other. Consequently, when a memory MOSFET and the corresponding dummy cell are selected, the potential of the data line DL_0 and that of the data line $\overline{DL}_0$ change from substantially the same value. More specifically, from the time when the selection is made, the potential of the data line DL_0 is a value higher or lower than the potential of the data line $\overline{DL}_0$ in accordance with the data stored in the memory MOSFET. Accordingly, it is possible to accurately read out data even if the sense amplifier is actuated in a short period of time after the selection of the memory MOSFET and the corresponding dummy cell. As a result, it is possible to increase the speed of operation of the ROM.

The sense amplifier SA_0 has a relatively high sensitivity, since it is constituted by a differential amplifier circuit. Accordingly, if the sense amplifier is actuated when the potential difference between the data lines DL_0 and $\overline{DL}_0$ is relatively small, the sense amplifier is able to amplify the potential difference without any malfunction. In other words, it is possible to actuate the sense amplifier in a relatively short period of time after the selection of

the memory cell and the corresponding dummy cell, so that the readout operation of the ROM can be made higher in speed.

The following advantage is offered by forming
5 each sense amplifier as a differential amplifier circuit and arranging it such that when, for example, word lines in the memory arrays M-ARY₃ and M-ARY₄ on the right-hand side as viewed in Fig. 1 are selected, the corresponding dummy word lines in the dummy arrays
10 D-ARY₁ and D-ARY₂ on the left-hand side are simultaneously selected.

Namely, when the potential of a word line changes from the non-selection level to the selection level, the potential change is undesirably transmitted
15 to one data line via the unfavourable capacitance coupling between the word line and the one data line. Thereby, the potential of the one data line is undesirably changed. However, substantially simultaneously with the selection of the word line, the
20 corresponding dummy word line is selected. Consequently, the potential change of the dummy word line, i.e. the potential change from the non-selection level to the selection level, is also transmitted to the other data line via the unfavourable capacitance
25 coupling between the dummy word line and the other data

line. Accordingly, the potential of the other data line is also undesirably changed. The potential change of the one data line and that of the other data line are the same in phase. Since the sense amplifier for amplifying the potential difference between the pair of data lines is constituted by substantially a differential amplifier circuit, the undesirable potential change in each of the pair of data lines is hardly amplified. Accordingly, it is possible to obtain a ROM which is substantially free from malfunction.

By providing the compensating circuits as shown in Figs. 2A and 2B, it is possible to obtain a semiconductor memory with greater reliability.

More specifically, the capacitance formed between the data line and the word line is substantially constituted by the capacitance formed between the drain region and the gate electrode of the memory MOSFET formed on the upper side of the data line and that formed between the drain region of the gate electrode of the memory MOSFET formed on the lower side of the data line. On the other hand, the capacitance formed between the other data line and the dummy word line is substantially constituted by the capacitance formed between the gate electrode and the drain region

of each of two MOSFETs connected to this data line,
i.e. one MOSFET in the dummy cell and one MOSFET in the
compensating circuit. Since these MOSFETs are formed
so as to be substantially equal in dimensions to each
5 other, the capacitances formed between the gate
electrodes and the drain regions of these MOSFETs
respectively have values substantially equal to each
other. Moreover, since these MOSFETs are
simultaneously formed, they have gate-drain
10 capacitances (capacitances formed between the gate
electrodes and the drain regions, respectively)
substantially equal to each other independently of
manufacturing condition variations. Consequently, the
value of the capacitance formed between the one data
15 line and the word line and that of the capacitance
formed between the other data line and the dummy word
line can be made substantially equal to each other
independently of manufacturing condition variations.
As a result, the change in potential of the one data
20 line caused by the change in potential of the word line
and the change in potential of the other data line
caused by the change in potential of the dummy word
line can be made substantially equal to each other.
Since these changes in potential of the pair of data
25 lines are the same in phase, these changes are not

substantially amplified by the differential amplifier circuit constituting the sense amplifier unit. Accordingly, it is possible to obtain a semiconductor memory which is more reliable.

5 In the sense amplifier SA_0 , the differential amplifier circuit is formed so as to constitute a latching circuit. Therefore, it is possible to amplify the potential difference between the data lines to a predetermined potential in a relatively short
10 period of time, so that the speed of the readout operation of the ROM can be increased. In addition, since the latching circuit is preferably constituted by a CMOS circuit, the potentials of a pair of data lines can be amplified to the supply voltage and earth
15 potential, respectively.

Between a pair of input/output terminals of the main amplifier in the latching circuit MA_0 are provided precharging MOSFETs constituted by P-channel MOSFETs Q_{10} and Q_{11} , together with a short-circuiting P-channel
20 MOSFET Q_{12} for making the precharging levels of these MOSFETs uniform. This short-circuiting MOSFET Q_{12} has substantially the same function as the short-circuiting MOSFET Q_7 described above. A timing signal $\overline{\phi_S}$ is applied to the gates of the respective MOSFETs Q_{10} to
25 Q_{12} .

The main amplifier is constituted by a dynamic differential amplifier circuit in the same manner as the sense amplifier SA_0 . As shown, the main amplifier is constituted by a latching circuit comprising two CMOS inverters each composed of a P-channel MOSFET Q_{13} (Q_{14}) and an N-channel MOSFET Q_{115} (Q_{116}), and an N-channel MOSFET Q_{118} as a power switch.

The output signal from the main amplifier, i.e. the output signal taken out from a node NB_0 , is applied to an inverter which is constituted by a P-channel MOSFET Q_{19} and N-channel MOSFETs Q_{20} and Q_{21} and functions as a tristate circuit. The inverter outputs a signal BL_0 . A timing signal ϕ_{1a} is applied to the gate of the N-channel MOSFET Q_{21} and the gate of the MOSFET Q_{18} for controlling the operation of the differential circuit. During the period when the timing signal ϕ_{1a} is high, the differential circuit amplifies the signal transmitted from the sense amplifier SA_0 and latches the same. Accordingly, a static output signal BL_0 is delivered from the latching circuit MA_0 constituted by the inverters and the main amplifier.

The main amplifier is provided with a P-channel MOSFET Q_{17} having the same function as the MOSFET Q_5 in the sense amplifier SA_0 . It should be noted that when

the input/output terminal of the main amplifier is under precharging, the timing signal $\overline{\phi}_s$ is held low. Consequently, the MOSFET Q_{17} is turned ON, and the precharging of the main amplifier is also effected from the MOSFET Q_{17} , in order to increase the speed of precharging.

Moreover, while the main amplifier is being precharged, the timing signal ϕ_{1a} is held low. In addition, since the node NB_0 is held at the high level by the precharging, the MOSFET Q_{19} is also turned OFF. Consequently, the level of the output signal BL_0 having been delivered from the inverter before the precharging of the main amplifier is held by the stray or parasitic capacitance coupled to the line for transmitting the output signal BL_0 and the stray or parasitic capacitance of the MOSFETs Q_{19} and Q_{20} . Accordingly, even when the main amplifier is being precharged, the same output signal as that delivered before the precharging is delivered from the inverter.

The output signals BL_0 to BL_{37} delivered from the latching circuit MA_0 to MA_{37} are supplied to inverters IV such as shown in Fig. 4, respectively, to form signals $\overline{D}_0'$ to $\overline{D}_{31}'$ and $\overline{P}_0$ to $\overline{P}_5$ formed by inverting the phase of the output signals BL_0 to BL_{37} , respectively, and signals D_0' to D_{31}' and P_0 to P_5

corresponding to the output signals BL_0 to BL_{37} .

These signals are supplied to the circuit ECC in the subsequent stage, described later. It is to be noted that each of the inverters IV is a static CMOS inverter constituted by a P-channel MOSFET and an N-channel MOSFET such as shown in Fig. 15.

Fig. 5 shows a preferred form of circuit of the X decoder $X-DCR_1$ shown in Fig. 1.

The X decoder $X-DCR_1$ is constituted by a plurality of decoders. The Figure shows the circuit of one of these decoders. A selecting signal for selecting a word line is formed in three stages. More specifically, address signals are decoded in three stages.

The internal address signals a_4 to a_9 and $\overline{a_4}$ to $\overline{a_9}$ are decoded by a decoder circuit constituted by a plurality of NAND circuits. The Figure shows the circuit of one of the plurality of NAND circuits. A CMOS NAND circuit is constituted by P-channel MOSFETs Q_{30} to Q_{35} and N-channel MOSFETs Q_{36} to Q_{41} . The NAND circuit is supplied with the internal address signals $\overline{a_4}$ to $\overline{a_9}$ as shown.

The internal address signals a_2 , $\overline{a_2}$ and a_3 , $\overline{a_3}$ are supplied to the decoder circuit constituted by four two-input AND circuits. In this decoder circuit, the

internal address signals are decoded to form decoded signals a_{00} to a_{11} . For instance, when each of the internal address signals $\overline{a_2}$ and $\overline{a_3}$ is "1", the decoder circuit delivers the decoded signal a_{00} of high level ("1") and the decoded signals a_{01} to a_{11} of low level ("0").

A two-input NAND circuit is constituted by P-channel MOSFETs Q_{42} , Q_{43} and N-channel MOSFETs Q_{44} , Q_{45} . One input terminal of this NAND circuit is supplied with the output signal of the CMOS NAND circuit phase-inverted by the inverter IV_1 , while the other input terminal is supplied with the decoded signal a_{00} . This NAND circuit forms selecting signals for four word lines. These selecting signals are applied to the gates of four word line driving circuits DV_0 to DV_3 , respectively, each comprising a P-channel MOSFET Q_{46} and N-channel MOSFET Q_{47} which are connected to form an inverter.

The internal address signals a_0 , $\overline{a_0}$ and a_1 , $\overline{a_1}$ are supplied to a decoder circuit constituted by a plurality of AND circuits. The decoder circuit is further supplied with the word line selecting timing signal ϕ_X . In the decoder circuit, the internal address signals a_0 , $\overline{a_0}$ and a_1 , $\overline{a_1}$ are decoded, and the decoded signals formed by the decoding are delivered as word line selecting signals ϕ_{W00} to ϕ_{W11} in synchronism with the word line selecting timing signal ϕ_X . For instance, when both the internal address signals $\overline{a_0}$ and $\overline{a_1}$ are made high ("1"), the decoder circuit delivers the high-level word line selecting timing signal ϕ_{W00} in synchronism with the word line selecting timing signal ϕ_X . At this time, the word line selecting timing signals ϕ_{W01} , ϕ_{W10} and ϕ_{W11} are held low.

The four kinds of word line selecting timing signals, ϕ_{W00} to ϕ_{W11} formed in synchronism with the word line selecting timing signal ϕ_X are transmitted to the drains of the P-channel MOSFETs Q_{46} of the respective driving circuits DV_0 to DV_3 , respectively.

Thereby, when all the internal address signals a_0 to a_9 are made low ("0"), in other words, when all the internal address signals $\overline{a_0}$ to $\overline{a_9}$ are made high ("1"), the MOSFET Q_{46} in the driving circuit DV_0 is turned ON, and in synchronism with the selecting timing signal ϕ_X ,

the high-level word selecting timing signal ϕ_{W00} is transmitted to the word line W_0 via the MOSFET Q_{46} . As a result, the potential of the word line W_0 rises to the high level which is the memory cell selecting level.

5 Each word line is connected with an N-channel MOSFET for holding the potential of the non-selected word lines at earth potential on the opposite side to the corresponding word line driving circuit. The gates of the MOSFETs are supplied with signals formed by phase-inverting the word line selecting timing signals ϕ_{W00} to ϕ_{W11} supplied to the word line driving circuits corresponding thereto, respectively. For example, the word line W_0 connected to the driving circuit DV_0 is connected with a MOSFET Q_{170} having its gate supplied with a signal $\overline{\phi_{W00}}$ formed by phase-inverting the timing signal ϕ_{W00} . Thus, the potential across a word line not selected, e.g. the word line W_3 , is held at earth potential by the MOSFETs Q_{48} and Q_{173} . Accordingly, it is possible to prevent selection of any undesired word line, such as multiselection of word lines, so that possible malfunctions can be reduced. It is possible to readily form the timing signals $\overline{\phi_{W00}}$ to $\overline{\phi_{W11}}$ by, for example, phase-inverting the timing signals ϕ_{W00} to ϕ_{W11} by means of the respective inverters.

25 The following advantages are offered by the

arrangement where the internal address signals are decoded in a plurality of stages as in the case of the X decoder illustrated.

Firstly, it is possible to prevent production of any wasteful blank portion in the IC chip, so that the IC chip can be made more compact. The decoder circuit can be constituted by, for example, a plurality of AND circuits. If a multiplicity of internal address signals are attempted to be decoded by a single AND circuit, the AND circuit is inevitably constituted by a multiplicity of MOSFETs, which disadvantageously requires a relatively large area. Consequently, it is difficult to make the lateral arrangement pitch of the AND circuits coincide with the word line arrangement pitch in the memory arrays.

In order to transmit the selecting signals delivered from the AND circuits to the corresponding word lines, it is necessary to enlarge the word line arrangement pitch, for example. In such a case, the distance between the adjacent word lines enlarges, causing wasteful blank portions to be produced in the IC chip. On the other hand, in the X decoder, the internal address signals are decoded by combinations of a plurality of small decoder circuits. Since a small decoder circuit can be constituted by fewer MOSFETs, the

decoder circuit can be readily formed so as to match with the distance between the adjacent word lines.

Accordingly, it is possible to reduce wasteful blank portions in the IC chip.

5 Secondly, it is possible to reduce the load on one internal address signal line, so that the potential change of the internal address signal can be made faster. This is because since the decoder circuit requires fewer MOSFETs for receiving one internal address signal, the
10 load connected to the wire for transmitting the internal address signal is reduced.

Fig. 7 shows a part of the circuit of the Y decoder $Y\text{-DCR}_1$ shown in Fig. 1. The Figure shows one decoder unit in the decoder circuit which forms the
15 decoded signals Y_{00} to Y_{11} to be supplied to the MOSFETs S_8 to S_{11} constituting the column switch shown in Figs. 2A and 2B. The decoder circuit for forming the decoded signals Y_{00} to Y_{11} is constituted by four decoders. Although the Figure shows only the decoder for forming
20 the decoded signal Y_{00} , the other three decoders are constituted in substantially the same manner as that one illustrated.

The decoder is constituted by MOSFETs Q_{50} to Q_{54} and inverters IV_2 , IV_3 . A two-input NAND gate is
25 constituted by the parallel-connected P-channel MOSFETs

Q_{51} and Q_{52} and the series-connected N-channel MOSFETs Q_{53} and Q_{54} . When the decoded signal Y_{00} is formed, the internal address signals $\overline{a_{12}}$ and $\overline{a_{13}}$ are applied to the NAND gate. The P-channel MOSFETs Q_{50} is provided in series to the parallel-connected MOSFETs Q_{51} and Q_{52} , while the N-channel MOSFET Q_{52} is provided in parallel to the series-connected MOSFETs Q_{53} and Q_{54} . The timing signal ϕ_{PC} is applied to the gates of the respective MOSFETs Q_{50} and Q_{52} .

10 The output signal from this logical gate circuit is passed through the inverters IV_2 and IV_3 to form the decoded signal Y_{00} .

The decoded signals Y_0 and Y_1 to be supplied to the MOSFETs S_0 to S_7 constituting the column switch shown 15 in Figs. 2A and 2B are also formed by two decoders similar to the decoder shown in Fig. 7. Each decoder receives a one-bit internal address signal and the timing signal ϕ_{PC} and forms the decoder signals Y_0 and Y_1 .

The timing signal ϕ_{PC} is held high during the 20 precharging period when the precharging signal $\overline{\phi_{PC}}$ is held low in order to precharge the data lines.

Consequently, the decoded signals Y_0 , Y_1 and Y_{00} to Y_{11} are all made low. Accordingly, the P-channel MOSFETs S_0 to S_{11} constituting the column switch are all 25 turned ON. In consequence, during the precharging

period, the stray or parasitic capacitance of the data lines and the stray or parasitic capacitance coupled to the common data lines are precharged by the precharging MOSFETs P_1, P_3, P_5 and P_7 which are turned ON by the precharging signal $\overline{\phi_{PC}}$ when it is low, and moreover, the above-mentioned capacitances are precharged from the sense amplifier side via the MOSFETs constituting the column switch.

As shown in Figure 18, the timing signal ϕ_{PA1} is held low during the precharging period. As a result, the MOSFET Q_5 in the sense amplifier SA_0 is turned ON, so that the supply voltage V_{CC} is applied to one electrode of the respective N-channel MOSFETs Q_3 and Q_4 . The potentials of the data lines are applied to the gates of the respective N-channel MOSFETs Q_3 and Q_4 via the P-channel MOSFETs constituting the column switch which are turned on by the decoded signals y_0, y_1 and y_{00} and y_{11} . As the potentials of the common data lines are raised through the precharging of the data lines and the common data lines effected by the precharging MOSFETs, the N-channel MOSFETs Q_3 and Q_4 are turned ON. As a result, the stray and parasitic capacitances of the data lines are precharged via the MOSFET Q_5 , the N-channel MOSFET Q_3 (Q_4) and the MOSFETs constituting the column switch.

The capacitances coupled to the common data lines and the

data lines are precharged by the precharging elements from both ends of the data line. By thus precharging the data lines through the precharging MOSFETs and the sense amplifier, it is possible to raise the data line potentials to a desired value in a short period of time, so that the speed of operation of the ROM can be increased.

Fig. 9 is a schematic illustration of an example of the ECC circuit shown in Fig. 1.

A logical operation circuit ELG receives the 38-bit signals $D_0, \overline{D_0}$ to $D_{31}, \overline{D_{31}}$ and $P_0, \overline{P_0}$ to $P_5, \overline{P_5}$ delivered from the memory arrays and forms syndromes S_0 to S_5 for indicating error bits by exclusive ORs of predetermined combinations.

In the 38-bit data written in the memory arrays, the six-bit parity check bits P_0 to P_5 have their respective values previously set in accordance with the 32-bit data signals and a proper check matrix.

Table 1 below shows an example of the check matrix.

Table 1 Check matrix

Bit No. Syndrome	Information bits													
	D ₀	D ₁	D ₂	D ₃	D ₄	D ₅	D ₆	D ₇	D ₈	D ₉	D ₁₀	D ₁₁	D ₁₂	D ₁₃
S ₀	1	1	1	1	1									
S ₁	1					1	1	1	1					
S ₂		1				1				1	1	1		
S ₃			1				1			1			1	1
S ₄				1				1			1		1	
S ₅					1				1			1		1

CONTINUED

D ₁₄	D ₁₅	D ₁₆	D ₁₇	D ₁₈	D ₁₉	D ₂₀	D ₂₁	D ₂₂	D ₂₃	D ₂₄	D ₂₅	D ₂₆	D ₂₇
1	1	1	1	1	1	1	1						
1	1	1	1					1	1	1	1		
				1	1			1	1			1	1
	1			1		1	1	1		1		1	1
		1			1	1			1		1	1	
			1				1			1	1		1

CONTINUED

				Parity bits					
D ₂₈	D ₂₉	D ₃₀	D ₃₁	P ₀	P ₁	P ₂	P ₃	P ₄	P ₅
1	1			1					
		1			1				
1		1	1			1			
							1		
	1		1					1	
1	1	1	1						1

In Table 1, a flag 1 is added to each of bits to be checked.

Table 2 below shows an example of data W to be written into the memory arrays. It is to be noted that, in Table 2, data signals are denoted by symbols B_0 to B_{31} , while parity signals are designated by symbols BP_0 to BP_5 .

Table 2

(W)	B_0	B_1	B_2	B_3	B_4	B_5	B_6	B_7	B_8	B_9	B_{10}	B_{11}	B_{12}	B_{13}	B_{14}
	1	1	1	1	1	0	0	0	0	0	0	0	0	0	1

CONTINUED

B_{15}	B_{16}	B_{17}	B_{18}	B_{19}	B_{20}	B_{21}	B_{22}	B_{23}	B_{24}	B_{25}	B_{26}	B_{27}
1	1	1	1	1	1	1	0	0	0	0	0	0

CONTINUED

B_{28}	B_{29}	B_{30}	B_{31}	BP_0	BP_1	BP_2	BP_3	BP_4	BP_5
1	1	0	0	1	1	1	1	1	1

The value of each parity bit is determined by checking the bits indicated in Table 1 in the 32-bit data signals to be written. The parity bit to be obtained has a value such that the combined exclusive OR value of the bit signals checked and the parity bit to be obtained will be "0". In other words, each parity bit is set so that the combined exclusive OR value of the bits respectively checked according to Table 1 will be "0".

For example, the parity bit BP_0 in Table 2 is set as follows. Namely, for setting the parity bit BP_0 , the data bits B_0 to B_4 , B_{14} to B_{21} and B_{28} to B_{29} are checked in the 32-bit data bits B_0 to B_{31} in accordance with the first line (syndrome S_0) of Table 1. The exclusive OR of these data bits checked is "1". Therefore, the parity bit BP_0 is determined as "1". More specifically, the parity bit BP_0 is set so that the exclusive OR of the data bits checked and the parity bit BP_0 will be "0".

Then, in the similar manner, data are checked on the basis of the second to fifth lines (syndromes S_1 through S_5) of Table 1, and the parity bits BP_1 to BP_5 are determined so that the exclusive OR with respect to each parity bit will be "0".

In the case where each of the 32-bit data bits is set to be such a value as shown in Table 2, the parity bits BP_0 to BP_5 are all "1" as shown in the Table.

As will be clear from Table 1 and the previous description relating thereto, logical formulae for calculating the syndromes S_0 to S_5 are given by the following formulae (3) to (8):

$$S_0 = B_0 \oplus B_1 \oplus B_2 \oplus B_3 \oplus B_4 \oplus B_{14} \oplus B_{15} \oplus B_{16} \oplus B_{17} \oplus B_{18} \oplus B_{19} \oplus B_{20} \oplus B_{21} \oplus B_{28} \oplus B_{29} \oplus BP_0 \dots \dots (3)$$

$$S_1 = B_0 \oplus B_5 \oplus B_6 \oplus B_7 \oplus B_8 \oplus B_{14} \oplus B_{15} \oplus B_{16} \oplus B_{17} \oplus B_{22} \oplus B_{23} \oplus B_{24} \oplus B_{25} \oplus B_{30} \dots \dots (4)$$

$$S_2 = B_1 \oplus B_5 \oplus B_9 \oplus B_{10} \oplus B_{11} \oplus B_{14} \oplus B_{18} \oplus B_{19} \oplus B_{22} \oplus B_{23} \oplus B_{26} \oplus B_{27} \oplus B_{28} \oplus B_{30} \oplus B_{31} \oplus BP_2 \dots \dots (5)$$

$$S_3 = B_2 \oplus B_6 \oplus B_9 \oplus B_{12} \oplus B_{13} \oplus B_{15} \oplus B_{18} \oplus B_{20} \oplus B_{21} \oplus B_{22} \oplus B_{24} \oplus B_{26} \oplus B_{27} \oplus BP_3 \dots \dots (6)$$

$$S_4 = B_3 \oplus B_7 \oplus B_{10} \oplus B_{12} \oplus B_{16} \oplus B_{19} \oplus B_{20} \oplus B_{23} \oplus B_{25} \oplus B_{26} \oplus B_{29} \oplus B_{31} \oplus BP_4 \dots \dots (7)$$

$$S_5 = B_4 \oplus B_8 \oplus B_{11} \oplus B_{13} \oplus B_{17} \oplus B_{21} \oplus B_{24} \oplus B_{25} \oplus B_{27} \oplus B_{28} \oplus B_{29} \oplus B_{30} \oplus B_{31} \oplus BP_5 \dots \dots (8)$$

It will be noted that in these logical formulae, the mark $\oplus$ denotes an exclusive OR operation

The logical operation circuit ELG shown in Fig. 9 is constituted by logical circuits (not shown) for forming the syndromes S_0 to S_5 satisfying the above formulae (3) to (8). It will be noted that it is possible to select at will the order of combining the exclusive ORs of a plurality of bits with each other. Accordingly, the exclusive ORs of e.g. the four bits B_0 to B_3 may be obtained in such a way that an output $B_0 \oplus B_1$ is formed by means of a first exclusive OR circuit and an output $B_2 \oplus B_3$ is formed by means of a second exclusive OR circuit and then the formed two outputs are supplied to a third exclusive OR circuit. As will be apparent from comparison between the formulae (3) to (8), the exclusive OR of the bits B_{14} to B_{17} appears in the formulae (3) and (4) in common. The exclusive OR of the bits B_{18} and B_{19} appears in the formulae (3) and (5) in common. Accordingly, in order to reduce the number of the logical circuits constituting the logical operation circuit ELG, the exclusive ORs common to the formulae may be previously formed by means of mutual circuits, respectively.

The defects previously produced in the memory MOSFETs, switching MOSFETs and signal wiring to be

84

65

selected and the practical defects caused in the circuit operation by an undesirable change in the circuit operation conditions will give errors to the readout data to be supplied to the ECC circuit.

5 Assuming now that memory cells in which the write data W as shown in Table 2 should have been written are selected, and the readout data R at that time is erroneous as shown in Table 3 below, for example. Further, it will be assumed that the seventh bit B₇ of the readout data R has changed from "0" to "1".

Table 3

5	B ₀	B ₁	B ₂	B ₃	B ₄	B ₅	B ₆	B ₇	B ₈	B ₉	B ₁₀	B ₁₁	B ₁₂	B ₁₃	B ₁₄	B ₁₅
(R)	1	1	1	1	1	0	0	1	0	0	0	0	0	0	1	1

B ₁₆	B ₁₇	B ₁₈	B ₁₉	B ₂₀	B ₂₁	B ₂₂	B ₂₃	B ₂₄	B ₂₅	B ₂₆	B ₂₇	B ₂₈	B ₂₉
1	1	1	1	1	1	0	0	0	0	0	0	1	1

B ₃₀	B ₃₁	BP ₀	BP ₁	BP ₂	BP ₃	BP ₄	BP ₅
0	0	1	1	1	1	1	1

When the data R is supplied, the logical operation circuit ELG in the ECC circuit carries out logical operations on the syndromes S_0 to S_5 in accordance with the formulae (3) to (8). In the operation process for calculating the syndromes S_0 to S_5 , the seventh bit B_7 is employed in the logical operations for calculating the syndromes S_1 and S_4 as will be clear from Table 1. Due to the fact that the seventh bit B_7 has changed from "0" to "1", each of the syndromes S_1 and S_4 becomes "1". The bits are not erroneous which are taken in the operation processes for calculating the other syndromes S_0 , S_2 , S_3 and S_5 . Therefore, each of the syndromes S_0 , S_2 , S_3 and S_5 becomes "0".

When the readout data R such as shown in Table 3 is delivered, the bit pattern of the syndromes S_5 to S_0 delivered from the logical operation circuit ELG becomes "010010". This bit pattern coincides with the bit pattern of the syndromes S_5 through S_0 indicating the seventh bit D_7 in check matrix shown in Table 1. In the check matrix, the pattern of the syndromes S_5 to S_0 in the row of the bit D_7 is "010010", which coincides with the bit pattern of the syndromes S_5 to S_0 delivered from the logical operation circuit. It will be noted that each of blank columns in the check matrix is regarded as "0".

As will be apparent from Table 1, a plurality of check bits are set to each of the 38-bit signals. The check bits set to one signal have a pattern corresponding to only this signal.

5 Owing to the fact that the check matrix is arranged as shown in Table 1, the bit patterns constituted by the syndromes S_5 to S_0 delivered from the logical operation circuit ELG shown in Fig. 9 correspond to the positions of the error data bits in the readout
10 data R respectively.

The syndromes S_0 to S_5 delivered from the logical operation circuit ELG are fed to the decoder DCR directly and via inverters.

The decoder DCR delivers a decoded signal
15 representative of the error digit by decoding the syndromes S_0 to S_5 . The decoder DCR is constituted by AND gates G_0 to G_{31} made to correspond to the 32-bit data signals respectively. The AND gates G_0 to G_{31} have their respective inputs determined so as to detect bit
20 patterns different from each other. Each AND gate delivers a "0" level signal when the data bit made to correspond thereto is not erroneous but delivers a "1" level signal when the data bit is erroneous. For example, the AND gate G_0 , as will be obvious from the
25 illustrated connection and the check matrix shown in

Table 1, delivers a "1" level signal when the first digit (first bit) signal in the 32-bit data signals is erroneous but delivers a "0" level signal when the signal is not erroneous.

5 The outputs of the decoder DCR, i.e. the outputs of the respective AND gates G_0 to G_{31} , and the data bits B_0 to B_{31} of the readout data R are fed to exclusive OR circuits EOR_0 to EOR_{31} respectively. The exclusive OR circuits EOR_0 to EOR_{31} form corrected output data D_0 to D_{31} to be supplied to the multiplexor MPX shown in Fig.

10 1. For instance, if the seventh data signal has an error as shown in Table 3, the output of the AND gate G_6 becomes "1" correspondingly, so that the seventh signal erroneously read out as "1" is inverted from "1" to "0" by the exclusive circuit EOR_7 . The value of the data signal D_6 is revised to the correct value.

 It will be noted that the ECC circuit is able to correct the error for one bit but unable to correct the error over two or more bits. In order to obtain an ECC circuit capable of correcting the error over two bits, it is necessary to provide a complicated construction, so that the number of elements required is increased. Moreover, in such a case, it is necessary to greatly increase the number of parity bits (redundant bits).

25 Fig. 8 shows a practical example of the exclusive

OR circuit provided in the logical operation circuit ELG and employed for the error correction.

The exclusive OR circuit comprises P-channel MOSFETs Q_{p1} to Q_{p4} and N-channel MOSFETs Q_{n1} to Q_{n4} .

5 The MOSFETs Q_{p1} , Q_{p2} and the MOSFETs Q_{n1} , Q_{n2} are connected in series. In the same manner, the MOSFETs Q_{p3} , Q_{p4} and the MOSFETs Q_{n3} , Q_{n4} are connected in series. The junction between the MOSFETs Q_{p2} and Q_{n1} and the junction between the MOSFETs Q_{p4} and Q_{n3} are
10 mutually connected to form an output OUT. Input signals a and b are applied to the gates of the respective MOSFETs Q_{n1} and Q_{n2} , whilst input signals $\bar{a}$ and $\bar{b}$ are applied to the gates of the respective MOSFETs Q_{n3} and Q_{n4} .

15 Moreover, input signals $\bar{a}$, $\bar{b}$ are applied to the gates of the respective MOSFETs Q_{p1} and Q_{p4} , whilst input signals b and a are applied to the gates of the respective MOSFETs Q_{p2} and Q_{p3} .

When both the input signals a and b are high ("1"), the MOSFETs Q_{n1} and Q_{n2} are turned ON, causing the
20 output OUT to be low ("0"). On the contrary, when both the input signals $\bar{a}$ and $\bar{b}$ are high, the MOSFETs Q_{n3} and Q_{n4} are turned ON, similarly causing the output OUT to be low.

25 When the input signal a (or $\bar{a}$) is low and the

input signal $\bar{b}$ (or b) is low, the MOSFETs Q_{p3} (or Q_{p1}) and the MOSFET Q_{p4} (or Q_{p2}) are turned ON, causing the output OUT to be high. Thus, when the levels of the input signal a and b coincide with each other, the output OUT is made low. On the other hand, when these signals do not coincide with each other, the output OUT is made high.

The above described exclusive OR circuit has the advantage of an extremely small power consumption, since the circuit has only eight elements, and no D.C. current flows between the supply voltage V_{CC} and earth.

In the logical operation circuit ELG in the ECC circuit, logical operations such as shown by the above logical formulae (3) to (8) are carried out in order to form the syndromes S_0 to S_5 as described above. More specifically, a multiplicity of exclusive OR operations are performed in the logical operation circuit.

By employing the exclusive OR circuit shown in Fig. 8 as a logical circuit constituting the logical operation circuit ELG, it becomes possible to constitute the circuit with a relatively small number of elements, and moreover, it is possible to reduce the power consumption.

Binary signals are written into the memory MOSFETs constituting the memory arrays $M-ARY_3$ and $M-ARY_4$,

these binary signals being formed by inverting the binary signals to be stored therein, in order to reduce the number of elements required to constitute the ECC circuit as well as to reduce the power consumption in the ECC circuit. More specifically, to store, for example, a binary signal "1" in the memory MOSFET M_0 in the memory array $M\text{-ARY}_3$, the binary signal "0" formed by inverting the binary signal "1" is written into the MOSFET M_0 .

Thus, no matter which memory MOSFETs in the memory arrays $M\text{-ARY}_1$ to $M\text{-ARY}_4$ are selected, signals having levels which correspond to those of the binary signals stored in the memory MOSFETs are always delivered from the corresponding latching circuits. More specifically, the signals delivered from the respective latching circuits are positive-phase outputs D_n' at all times, whilst the signals inverted by inverters are negative-phase outputs $\overline{D_n'}$ at all times. Accordingly, by simply providing the inverters, it becomes possible to supply the signals from the respective latching circuits to the exclusive OR circuits in the logical operation circuit ELG, so that the logical operation circuit can be further simplified.

Fig. 10 shows a practical circuit of each of the multiplexor MPX and the output buffer DOB.

The output data D_0 to D_{31} from the ECC circuit are transmitted to the output buffer DOB, eight bits by

eight bits, by the multiplexor MPX such as described hereinunder.

The multiplexor MPX is constituted by 32 tristate circuits, eight tristate circuits being combined to form one set. Accordingly, the 32 tristate circuits are divided into four sets.

For the sake of clarity only the tristate circuit for receiving the signal D_0 in the output data D_0 through D_{31} is shown in detail in Fig. 10. The other 31 tristate circuits have substantially the same construction as the one illustrated.

The data signal D_0 is passed through an inverter IV_4 and transmitted to the gate of each of a P-channel MOSFET Q_{55} and an N-channel MOSFET Q_{58} . The drains of the respective MOSFETs Q_{55} and Q_{58} are connected to an output node $O1_0$ via a P-channel MOSFET Q_{56} and an N-channel MOSFET Q_{57} , respectively.

Timing signals ϕ_{00} to ϕ_{11} are formed by an address buffer and the Y decoder $Y-DCR_2$ as shown in Fig.

16. The address buffer is constituted by two buffers AD_1 and AD_2 . Since the buffers have the same construction, the circuit of only the buffer AD_1 is shown in detail in Fig. 16. The buffer AD_1 comprises a static circuit consisting of MOSFETs Q_{136} to Q_{163} . The Y-decoder $Y-DCR_2$ comprises four decoders YU_1 to YU_4 all having the

same construction. Therefore, only the decoder YU_1 is shown in Fig. 16. The decoder YU_1 comprises MOSFETs Q_{164} to Q_{169} and has a circuit configuration requiring no special selecting timing signal, unlike the X decoder shown in Fig. 5. Consequently, the Y decoder $Y-DCR_2$ is able to form the timing signals ϕ_{00} to ϕ_{11} by employing only the internal address signals supplied from the address buffer.

The Y decoder $Y-DCR_2$ receives the internal address signals a_{15} , $\overline{a_{15}}$ and a_{16} , $\overline{a_{16}}$ and forms four kinds of selecting signals by decoding these signals.

For instance, when both the internal address signals a_{15} and a_{16} are low ("0"), the timing signal ϕ_{00} is made high. The timing signal ϕ_{00} is supplied to the gate of the N-channel MOSFET Q_{57} in Fig. 10. Moreover, the timing signal ϕ_{00} is inverted by an inverter IV_5 and supplied to the gate of the P-channel MOSFET Q_{56} .

Accordingly, when the timing signal ϕ_{00} is high, both the MOSFETs Q_{56} and Q_{57} are turned ON. Therefore, the data signal D_0 is transmitted to the output buffer DOB. When the timing signal ϕ_{00} is low, both the MOSFETs Q_{56} and Q_{57} are turned OFF, so that the output node O_{10} has a high impedance independently of the data signal D_0 .

Eight tristate circuits, similar to the above

tristate circuits, for receiving the eight-bit data signals D_0 to D_7 are combined to form one set and controlled by the timing signal ϕ_{00} . The other data signals are also divided so that eight bits form each

5 set: namely, the data signals D_8 to D_{15} ; D_{16} to D_{23} ; and D_{24} to D_{31} . Then, the eight-bit data signals constituting one set are supplied to the corresponding tristate circuits. These tristate circuits are controlled by the other timing signals ϕ_{01} to ϕ_{11} . In
10 addition, output nodes of the four tristate circuits are made common to data eight bits apart from each other, such as the bits D_0 , D_8 , D_{16} , D_{24} which correspond to each other. Accordingly, the total number of output lines from the multiplexor MPX is eight.

15 The output buffer DOB is constituted by eight output circuits provided so as to correspond to the output lines. Only one of the output circuits is shown in Fig. 10.

The output buffer DOB comprises two two-input
20 NAND gates constituted by MOSFETs Q_{59} to Q_{66} , four inverters IV_6 to IV_9 and a push-pull output circuit constituted by N-channel MOSFETs Q_{67} , Q_{68} . The output signal of the inverter IV_6 for receiving the output signals from the multiplexor MPX through the output lines
25 is applied to one input of the NAND gate constituted by

the MOSFETs Q_{59} to Q_{62} . On the other hand, the output signal of the inverter IV_7 for receiving the output signal from the inverter IV_6 is applied to one input of the NAND gate constituted by the MOSFETs Q_{63} to Q_{66} . In addition, a timing signal ϕ_{HZ} is applied to the other input of each of these two NAND gates. The output signals from the two NAND gates are transmitted to the gates of the output MOSFETs Q_{67} and Q_{68} through the inverters IV_8 and IV_9 , respectively.

10 The timing signal ϕ_{HZ} is formed on the basis of reference signals ϕ_{PCS} and ϕ_{XS} described later with reference to Fig. 11, and the chip selecting signal $\overline{CE}$. The timing signal ϕ_{HZ} is held low during the period when the chip is in the non-selected state and the period when

15 the output signals from the ECC circuit are indefinite owing to the fact that new data signals are delivered from the latching circuits to the ECC circuit. When the timing signal ϕ_{HZ} is made low, both the output MOSFETs Q_{67} and Q_{68} are turned OFF independently of the output

20 data from the ECC circuit. Consequently, the external output terminal D_n ($n=0$ to 7) becomes high in impedance. Thereby, it is possible to connect the semiconductor memory to any system of common data bus type as well as prevent indefinite data from being delivered.

25 Fig. 11 illustrates detailed block diagrams of

the address transition detector and the control signal generator which are shown in Fig. 1.

The internal address signals a_0 to a_{14} formed in the address buffer ADB are fed to delay circuits DLC_0 to DLC_{14} , respectively. The delay circuits DLC_0 to DLC_{14} form delay signals a_0' to a_{14}' delayed with respect to the internal address signals a_0 to a_{14} . The internal address signals a_0 to a_{14} and the delay signals a_0' to a_{14}' are fed to exclusive OR circuits EX_0 through EX_{14} , respectively. Each of the outputs of the exclusive OR circuits EX_0 through EX_{14} is supplied to an OR gate circuit OR. This OR gate circuit OR forms a trigger pulse ϕ_{apd} .

As the internal address signal a_0 changes as shown in Fig. 13, the levels of the respective input signals a_0 and a_0' supplied to the exclusive OR circuit EX_0 do not coincide with each other during the delay of the delay circuit DLC_0 . As a result, the exclusive OR circuit EX_0 forms a pulse having a pulse width corresponding to the delay. This pulse is delivered as the trigger pulse ϕ_{apd} via the OR gate circuit OR. Accordingly, the address transition detector ATD forms the trigger pulse ϕ_{apd} when either one of the internal address signals a_0 to a_{14} changes.

The address buffer ADB comprises a static circuit

in order to permit the address transition detector ATD to form the trigger pulse ϕ_{apd} even if the external address signals A_0 to A_{14} change asynchronously, which is constituted by a CMOS circuit composed of P-channel MOSFETs and N-channel MOSFETs. Fig. 12 shows an example of the static address buffer constituted by a CMOS circuit. Although the Figure shows only the address buffer which received the external address signal A_0 and forms the address signals a_0 and $\overline{a_0}$ complementary to each other, identical address buffers are provided with respect to the other address signals.

The address buffer with respect to the external address signal A_0 is constituted by P-channel MOSFETs Q_{100} to Q_{107} and N-channel MOSFETs Q_{108} to Q_{115} , and two-input NOR gate circuit and six inverters. The two-input NOR gate circuit is supplied with the external address signal A_0 and the chip selecting signal $\overline{CE}$. The internal address signal a_0 delivered from the inverter constituted by the P-channel MOSFET Q_{104} and the N-channel MOSFET Q_{112} and the internal address signal $\overline{a_0}$ delivered from the inverter constituted by the P-channel MOSFET Q_{107} and the N-channel MOSFET Q_{115} are transmitted to the X decoders $X-DCR_1$ and $X-DCR_2$, respectively. On the other hand, the internal address signal a_0 delivered from the inverter constituted by the P-channel MOSFET

Q₁₀₂ and the N-channel MOSFET Q₁₁₀ is transmitted to the address transition detector ATD.

Similarly to the address buffer, the exclusive OR circuits in the address transition circuit are constituted by static circuits, respectively. For example, such an exclusive OR circuit as shown in Fig. 8 is employed as each of the exclusive OR circuits.

The OR gate circuit OR is constituted by such a CMOS circuit as shown in Fig. 14. More specifically, the OR gate circuit OR comprises MOSFETs Q₁₁₆ to Q₁₂₉.

The OR gate OR comprises two NOR gate circuits and one NAND gate circuit. One NOR gate circuit is constituted by the P-channel MOSFETs Q₁₁₆ to Q₁₁₈ and the N-channel MOSFETs Q₁₁₉ to Q₁₂₁, the other NOR gate circuit comprises the P-channel MOSFETs Q₁₂₇, Q₁₂₈ and the N-channel MOSFETs Q₁₂₆, Q₁₂₉, and the NAND gate circuit comprises the P-channel MOSFETs Q₁₂₂, Q₁₂₅ and the N-channel MOSFETs Q₁₂₃, Q₁₂₄.

Each of the output signals of the respective exclusive OR circuits EX₀ to EX₁₄ is supplied to the NOR gate circuits, and the output signals from the two NOR gate circuits are supplied to the NAND gate circuit, from which the trigger pulse ϕ_{apd} is taken out.

The control signal generator CSG shown in Fig. 11 comprises two pulse width stretching circuits each

constituted by a static circuit, and an internal control signal generator. The control signal generator CSG receives the trigger pulse ϕ_{apd} and forms various timing signals required to operate the ROM. In the Figure, only
 5 essential timing signals, i.e. various timing signals such as mentioned above, are shown in order to simplify the description. Fig. 18 shows waveforms of the timing signals ϕ_{XS} , ϕ_{PCS} , ϕ_X , ϕ_{PC} , ϕ_{PA1} , ϕ_{PA2} , ϕ_{1a} , ϕ_S and ϕ_{HZ} . The precharging signal $\overline{\phi_{PC}}$ and the timing
 10 signal $\overline{\phi_S}$ are omitted in Fig. 18 but these signals $\overline{\phi_{PC}}$ and $\overline{\phi_S}$ are signals formed by phase-inverting the timing signals ϕ_{PC} and ϕ_S , respectively.

In the two pulse width stretching circuits PWS_1 and PWS_2 shown in Fig. 11, one pulse width stretching
 15 circuit PWS_1 forms the precharging signal $\overline{\phi_{PC}}$, the timing signal ϕ_{PC} formed by phase-inverting the same, and the reference signal ϕ_{PCS} required to generate the above-mentioned various signals from the internal control signal generator. The reference signal ϕ_{PCS} is a signal
 20 formed by stretching the pulse width of the trigger pulse ϕ_{apd} by the pulse width stretching circuit PWS_1 and is adjusted so as to have a predetermined pulse width. Moreover, the timing signal ϕ_{PC} is a signal decaying in synchronism with the rising of the reference signal ϕ_{PCS} .
 25 Consequently, the precharging signal $\overline{\phi_{PC}}$ rises in

99

synchronism with the decaying of the reference signal ϕ_{PCS} . The precharging of the capacitances in the data lines formed in the memory arrays and the precharging of the sense amplifier are carried out when the precharging signal $\overline{\phi_{PC}}$ is low. Accordingly, the precharging time is restricted in accordance with the reference signal ϕ_{PCS} formed by stretching the pulse width of the trigger pulse ϕ_{apd} . The pulse width stretching operation in the pulse width stretching circuit can be realized by the combination of the delay circuits and the logical gate circuits.

The other pulse width stretching circuit PWS_2 forms the word line selecting timing signal ϕ_X , and the reference signal ϕ_{XS} required to generate the above-mentioned various timing signals from the internal control signal generator similarly to the reference signal ϕ_{PCS} . The reference signal ϕ_{XS} is, similarly to the reference signal ϕ_{PCS} , a signal formed by stretching the pulse width of the trigger pulse ϕ_{apd} and has a pulse width adjusted to the time required to raise the level of the word lines to the selection level of the memory cells.

The internal control signal generator receives the above-described two reference signals ϕ_{PCS} and ϕ_{XS} and forms the timing signals ϕ_S , ϕ_{PA1} , ϕ_{PA2} , ϕ_{1a} and ϕ_{HZ} shown in Fig. 18.

5 By thus forming the timing signals essential for operating the ROM in the respective pulse width stretching circuits, it is possible to set the essential timing signals separately from each other, so that designing is facilitated and moreover, the following
10 advantages are offered.

Namely, since the reference signal ϕ_{PCS} for regulating the precharging period for the data lines and the reference signal ϕ_{XS} for regulating the time required to raise the level of the word lines to the selection
15 level of the memory cells are supplied to the internal control signal generator from the respective pulse width stretching circuits, if the readout timing is determined on the basis of these two kinds of reference signals, then it is possible to obtain a ROM capable of conducting
20 an accurate data readout operation. More specifically, the two pulse width stretching circuits PWS_1 and PWS_2 are simultaneously formed. Therefore, if the characteristics of the pulse width stretching circuit PWS_1 should change owing to manufacturing condition
25 variations, the characteristics of the pulse width

stretching circuit PWS_2 also change in the same manner. For example, if the pulse width of the reference signal ϕ_{PCS} should enlarge owing to manufacturing condition variations, the pulse width of the reference signal ϕ_{XS} also enlarges in the same manner. However, the relationship between the two kinds of reference signals, for example, the relationship that the reference signal ϕ_{XS} rises after a predetermined time has passes after the decaying of the reference signal ϕ_{PCS} , is maintained independently of the manufacturing condition variations. Consequently, there is no possibility that, for example, the timing signal ϕ_S which rises in response to the decaying of the reference signal ϕ_{PCS} and decays in response to the decaying of the reference signal ϕ_{XS} is not generated owing to the manufacturing condition variations. In other words, it is possible to obtain a ROM which is substantially unaffected by manufacturing condition variations.

The decaying of the precharging signal $\overline{\phi_{PC}}$ is controlled by the timing signal ϕ_n synchronized with the timing signal ϕ_{PA1} for activating the sense amplifier in order to reduce the power consumption. Thus, the arrangement is such that the precharging of the data lines, the sense amplifiers are started at the time when the signals from the memory cells are amplified by the

sense amplifiers respectively. For instance, if the precharging is not carried out after the signals from the memory cells are amplified by the respective sense amplifiers, the electric charge in the stray and parasitic capacitances of the data lines connected with the memory cells not selected will leak with time. A comparatively large power is required to again precharge the capacitances of the data lines once discharged. Therefore, the stray and parasitic capacitances of the data lines are precharged immediately after the signals from the memory cells are amplified by the respective sense amplifiers as described above.

Before the starting of this precharging operation, the signal amplified in each sense amplifier is transmitted via the MOSFETs Q_8 and Q_9 to the main amplifier in the respective latching circuit. Since the transfer MOSFETs Q_8 and Q_9 are held ON during the period when the timing signal ϕ_{PA2} is held high, the signal amplified in the sense amplifier is transmitted to the main amplifier via the transfer MOSFETs Q_8 and Q_9 . When the precharging of the data lines is started, the timing signal ϕ_{PA2} is made low. Consequently, the MOSFETs Q_8 and Q_9 are turned OFF, so that the pair of input/output terminals of the sense amplifier and the input/output terminal of the main amplifier are electrically separated

from each other. Accordingly, there is no possibility that the input/output terminal of the main amplifier is precharged by the above-described precharging of the data lines.

5 As described later in detail, the level of the word lines is brought to the non-selection level of the memory cells after the data in memory cells are transmitted to the data lines in order to reduce the power consumption of the ROM. The arrangement is such
10 that, as shown in Fig. 11, the word line selecting timing signal ϕ_X is delivered via a gate circuit AND controlled by the signal ϕ_{PA1} for activating the sense amplifier. Thus, as the sense amplifier starts to operate, the level
15 of all the word lines is brought to the non-selection level of the memory cells.

The operation of the circuit will now be described with reference to the waveforms shown in Fig.
18.

20 First of all, the external address signals A_0 to A_{14} are changed in order to read out data from desired memory cells. Thereupon, the trigger pulse ϕ_{apd} is generated from the address transition detector ATD.

One pulse width stretching circuit PWS_1 receives the trigger pulse ϕ_{apd} and forms the reference signal
25 ϕ_{PCS} for regulating the precharging time of the data

lines. On the other hand, the other pulse width stretching circuit PWS_2 forms, in response to the decaying of the trigger pulse ϕ_{apd} , the word line selecting timing signal ϕ_X and the reference signal ϕ_{XS} having a pulse width corresponding to the time required to raise the level of the word lines to the selection level of the memory cells. The rising of the word line selection timing signal ϕ_X causes the potentials of the word lines connected with the desired memory cells and those of the corresponding dummy word lines to start to rise.

When a predetermined time has passed after the change of the address signals, i.e. when the time has passed which is required to precharge the stray and parasitic capacitances of the data lines and the sense amplifier, the reference signal ϕ_{PCS} decays. In response thereto, the internal control signal generator raises a timing signal ϕ_S as well as decays a timing signal ϕ_{PC} . The decaying of the timing signal ϕ_{PC} terminates the precharging of the data lines and the sense amplifier. On the other hand, the main amplifier starts to precharge in response to the rising of the timing signal ϕ_S .

Moreover, the internal control signal generator decays the timing signal ϕ_{1a} to the low level,

subsequently to the rising of the timing signal ϕ_s to the high level. Thereby, the main amplifier and the inverter in the stage subsequent thereto which have been previously energized are de-energized.

5 Consequently, the potential at the node NB_n of the main amplifier changes from the value delivered previously to the precharging level (the supply voltage V_{CC}).

Moreover, in response to the rising of the timing
10 signal ϕ_s , the discharging MOSFETs of the earth lines connected with the desired memory cells and the discharging MOSFETs of the earth lines connected with the dummy cells corresponding to the desired memory cells are turned ON. Further, the timing signal ϕ_{PC} decays at
15 this time. Consequently, the MOSFETs constituting the column switches which have connected all the data lines to the sense amplifier in order to precharge the data lines operate so as to connect to the sense amplifier only the data lines connected with the desired memory
20 cells and the data lines connected with the dummy cells corresponding to the desired memory cells. Accordingly, the data stored in one desired memory cell is transmitted to one input/output terminal of the corresponding sense amplifier, as a change in potential of the data line, and
25 the reference voltage from the corresponding dummy cell

87

is transmitted to the other input/output terminal of the sense amplifier. More specifically, the potential of the data line DL_n connected with one desired memory cell changes as shown by a broken line or solid line in accordance with the data stored in the memory cell, as shown in Fig. 18.

Next, the reference signal ϕ_{XS} decays. By this time, the potentials of the word lines connected with the desired memory cells have risen to a certain extent.

In response to the decaying of the reference signal ϕ_{XS} , the internal control signal generator decays the timing signal ϕ_S . This terminates the precharging operation for the main amplifier.

In synchronism with the decaying of the timing signal ϕ_S , the internal control signal generator raises the timing signal ϕ_{PA1} for activating the sense amplifier. Thereby, the sense amplifier starts to amplify the potential difference between each of the data lines connected with the above-mentioned memory cells and the corresponding one of the data lines connected with the above-mentioned dummy cells.

In addition, the internal control signal generator decays the word line selecting timing signal ϕ_X in synchronism with the rising of the timing signal ϕ_{PA1} . In other words, the word lines are brought to the non-

107
88
selection level. Thereby, the power consumption of the ROM is reduced.

As described above, as the sense amplifier starts to operate, the potential of the data line DL_n connected with a desired memory cell largely changes in accordance with the data stored therein as shown in the Figure.

When the potential difference between the above-mentioned pair of data lines is amplified to a certain extent by the sense amplifier, the internal control signal generator raises the timing signal ϕ_{PA2} . Thereby, the output signal from the sense amplifier is transmitted to the main amplifier.

Subsequently to the rising of the timing signal ϕ_{PA2} , the internal timing signal generator raises the timing signal ϕ_{1a} to the high level again. In response to the rising of the timing signal ϕ_{1a} , the main amplifier and the inverter are activated, and the output signal transmitted from the sense amplifier is amplified as well as latched and then transmitted to the ECC circuit. More specifically, the level at the node NB_n of the main amplifier changes from the precharging level to the level corresponding to the data read out from a desired memory cell. Consequently, the inverter stops delivering the old data held in the stray and parasitic capacitances coupled to its output node and starts to

deliver a new data.

Moreover, the ECC circuit starts to deliver a new data after delivering an indefinite data during a certain time determined by the time required for the inverter to
5 change its output content from the old data to the new data and the delay of the ECC circuit itself.

The timing signal ϕ_{HZ} is held low during the time when the ECC circuit is delivering an indefinite data. Consequently, during this period, the external output
10 terminal DO_0 to DO_7 are in the floating state. Thereafter, new data are delivered from the external output terminals.

Moreover, the internal control signal generator raises the timing signal ϕ_{PC} to the high level again
15 after decaying the timing signal ϕ_{PA1} to the low level. Thereby, the precharging operation for the data lines and the sense amplifier is resumed.

109

It will be noted that since previous data is held by the inverter in the stage subsequent to the main amplifier during the time from when the main amplifier is de-energized until the same is again energized by the timing signal ϕ_{1a} , the output signals D_n from the ECC circuit and the output signals DO_n from the respective external output terminals are the previous data.

The following is a description of the relationship between the external address signals and the output data DO_n ($n=0$ to 7) from the external output terminals. Fig. 17 shows the relationship between the external address signals A_0 to A_{16} and the output data DO_n .

When either one of the external address signals A_0 to A_{14} changes, the 32-bit data are delivered from the ECC circuit as described above. The 32-bit data can be taken out from the external output terminals in four sets in a time division manner. More specifically, it is possible to determine which one of the four sets should be taken out, according to the combination of the external address signals A_{15} and A_{16} .

As shown in Fig. 17, if the external address signals A_{15} and A_{16} are combined as at (1), then eight-bit data shown by $DO((1))$ are delivered from the external output terminals. If the external address signals A_{15}

and A_{16} are combined as at (2) subsequently thereto, then eight-bit data shown by $DO(2)$ are delivered in a short period of time. Thereafter, in the same manner, eight-bit data shown by $DO(3)$ and eight-bit data shown by $DO(4)$ are delivered successively in a short period of time.

The reason why the data $DO(2)$, the data $DO(3)$ and the data $DO(4)$ are delivered in a short period of time is that the data $DO(2)$ to $DO(4)$ have already reached the output nodes of the ECC circuit by the time the data $DO(1)$ is delivered.

The memory cell arrays, the dummy cell arrays, the sense amplifier and the latching circuit are all constituted by dynamic circuits, whilst the other circuits are constituted by static circuits. The internal timing signals required for the operations of the dynamic circuits are all formed inside the ROM by detecting the changes of the address signals, i.e. in accordance with the timing of the starting of the readout access operation of the ROM. Accordingly, signals supplied from the outside in the readout operation can be made substantially the same as signals in a static ROM, so that the handling of the ROM becomes extremely easy.

On the other hand, the internal essential circuits, i.e. the memory cell arrays, the dummy cell

arrays and the sense amplifier are constituted by dynamic circuits. Therefore, it is possible to make the power consumption smaller and the integration degree higher.

In the readout operation, the dynamic circuits are

5 precharged by utilizing the time required for the memory cell selecting operation. In addition, as the sense amplifier, a highly sensitive differential amplifier circuit is employed. Therefore, it is possible to read out the contents of the memory cells at an extremely high
10 speed.

Moreover, the word lines are brought to the non-selection level again after being brought to the selection level of the memory cells for a readout operation. Thereby, the power consumption of the ROM is
15 reduced. More specifically, if the word lines are not brought to the non-selection level again after being brought to the selection level of the memory cells for a readout operation, a large ineffectively-consumed current undesirably flows for the following reasons.

20 For instance, in the case where the memory MOSFETs M_0 to M_6 have data "0" written therein in Figs. 2A and 2B, when, in order to select, for example, the memory MOSFET M_0 , the word line W_{512} is brought to the selection level (high level) and the earth line G_0 is
25 brought to the low level, the electric charge stored in

the stray and parasitic capacitances of the data line DL_0 is discharged via the memory MOSFET M_0 . In accordance therewith, the potential of the data line DL_0 gradually falls. By the way, the capacitances of the data lines and those of the earth lines are all precharged beforehand. Therefore, all the data and earth lines except for the data line DL_0 connected with the selected memory cell and the earth line G_0 are held at the precharging level (high level) at this time.

10 Consequently, with respect to the memory MOSFET M_1 , the electrode thereof connected to the data line DL_0 is made to function as a source, and the electrode thereof connected to the earth line G_1 is made to function as a drain. Accordingly, when the potential of the data line

15 DL_0 gradually falls until it becomes lower than the threshold voltage of the memory MOSFET M_1 with respect to the potential of the word line W_{512} , the memory MOSFET M_1 also turns ON. As a result, the electric charge stored in the stray and parasitic capacitances of the earth line

20 G_1 is also discharged via the memory MOSFETs M_0 and M_1 . Thus, the level of the earth line G_1 also gradually falls. Also, with respect to the memory MOSFET M_2 , in the same manner, the electrode thereof on the side of the earth line G_1 is made to function as a source, and the

25 electrode thereof on the side of the data line DL_1 is

made to function as a drain. Accordingly, when the level of the earth line G_1 becomes lower than the threshold voltage of the memory MOSFET M_2 with respect to the level of the word line W_{512} , the memory MOSFET M_2 also turns ON. In consequence, the electric charge stored in the capacitances of the data line DL_1 is discharged via the MOSFETs M_0 , M_1 and M_2 and as a result, the potential of the data line DL_1 also gradually falls. Then, the memory MOSFETs M_3 to M_6 undergo the same phenomena as the memory MOSFETs M_1 and M_2 , so that the electric charge stored in the stray and parasitic capacitances of each of the earth lines G_2 , G_3 and the data lines DL_2 , DL_3 is undesirably discharged. More specifically, also the electric charge previously precharged in the stray and parasitic capacitances of each of the data lines DL_1 to DL_3 and the earth lines G_1 to G_3 is undesirably discharged. Consequently, a relatively large ineffectively-consumed current disadvantageously flows. Moreover, in the subsequent readout operation, these stray and parasitic capacitances having been discharged must be precharged again. Accordingly, the power consumption is undesirably increased.

Therefore, the level of the word lines is brought to the non-selection level again after the level of the word lines is brought to the selection level and the data

stored in the selected memory cell is taken out to the data line. Thus, it is possible to reduce the number of the above-mentioned memory MOSFETs to turn ON, so that the flowing of a large ineffective current can be prevented. For example, with respect to the memory MOSFET M_1 , when the word line W_{512} is brought to the selection level and the memory MOSFET M_0 is turned ON, the potential of the data line DL_0 gradually falls. If the word line W_{512} is held at the selection level as it is, the potential of the data line DL_0 will become lower than the threshold voltage of the storage MOSFET M_1 with respect to the level of the word lines, resulting in a large power consumption of the ROM as described above. Therefore, the level of the word lines is brought to the non-selection level before the potential of the data line DL_0 becomes lower than the threshold voltage of the memory MOSFET M_1 with respect to the level of the word lines. Thus, the memory MOSFET M_1 will not turn ON, and it is possible to prevent the flowing of a large ineffective current.

The above description is that the word lines are brought to the non-selection level in order to prevent the memory MOSFETs other than the selected memory MOSFET from undesirably turning ON. In order to allow the potential of a data line to largely change in accordance

with the data stored in a selected memory MOSFET, however, it is desirable to bring the word line to the non-selection level before either one of the memory MOSFETs M_2 to M_6 turns ON. For example, if the arrangement is such that the word line W_{512} is brought to the non-selection level after it is brought to the selection level and before the memory MOSFET M_2 turns ON, the memory MOSFET M_1 turns ON, and the potential of the earth line G_1 gradually falls. However, a considerably large amount of electric charge stored in the capacitances of the earth line G_1 needs to be discharged until the potential of the earth line G_1 becomes lower than the threshold voltage of the memory MOSFET M_2 with respect to the level of the word line W_{512} ; therefore, it takes a comparatively long period of time. During this period, the potential of the data line DL_0 is substantially reduced. Accordingly, it is possible to take out to the data line DL_0 a large level in accordance with the data stored in the selected memory MOSFET M_0 .

In practice, as shown in Fig. 11, the word line selecting timing signal ϕ_x delivered from the control signal generator CSG is controlled by means of the timing signal ϕ_{PA1} for activating the sense amplifier. Thereby, the word lines are brought to the selection level, and then, after a predetermined time has passed, the word

lines are brought to the non-selection level. More specifically, when the sense amplifier is actuated, all the word lines are brought to the non-selection level.

In the dummy cell arrays, the compensating
5 circuits are OFF at all times. In other words, the compensating circuits are constituted by the MOSFETs, accompanied by a mark x, formed simultaneously with the memory MOSFETs in which binary signals "1" are written. These MOSFETs equalize the total numbers of the MOSFETs
10 connected to each dummy word line and those connected to each word line. Thus, it is possible to equalize the stray and parasitic capacitances coupled to the dummy word line and those connected to the word line, so that the dummy word line and the word line can be made equal
15 in the rising timing to each other. Thus, in the readout operation of the ROM, even if the timing of selecting the word lines and the dummy word lines is behind the discharging of the memory arrays, the gate voltages of the memory cell and the dummy cell will be equal to each
20 other. Consequently, a voltage in accordance with the conductance ratio between the memory cell and the dummy cell is applied between both the input terminals of the sense amplifier, so that no malfunction will occur. Such an arrangement of memory cells and dummy cells can be
25 used for ordinary static ROMs or dynamic ROMs.

The compensating circuit may be constituted by a capacitor, since the compensating circuit is required only to make the value of the capacitances connected to the dummy word line and that of the capacitances

5 connected to the word line substantially equal to each other. More specifically, the arrangement may be such that a capacitor is connected to the dummy word line so that the value of the capacitances coupled to the word line and that of the capacitances coupled to the dummy
10 word line are substantially equal to each other.

It is, however, desirable to constitute the compensating circuit by MOSFETs. This is because if the value of capacitances of a memory MOSFET should change owing to variations in manufacturing conditions, the
15 value of capacitances of a MOSFET constituting the compensating circuit also similarly changes; therefore, it is possible to make the value of the capacitances connected to the dummy word line and that of the capacitances connected to the word line substantially
20 equal to each other independently of variations in manufacturing conditions. More specifically, if, for example, the overlapping amount between the source region and the gate electrode of a memory MOSFET and the overlapping amount between the drain region thereof and
25 the gate electrode thereof should change owing to

manufacturing condition variations, since a MOSFET constituting the compensating circuit is formed simultaneously with the memory MOSFET, also in the MOSFET constituting the compensating circuit, the degree of overlapping between the source region and the gate electrode and the degree of overlapping between the drain region and the gate electrode change in the same manner as those in the memory MOSFET owing to the manufacturing condition variations. Accordingly, it is possible to make the value of capacitances of the memory MOSFET and that of capacitances of the MOSFET constituting the compensating circuit substantially equal to each other independently of variations in manufacturing conditions. Thus, it is possible to make the value of the capacitances coupled to the dummy word line and that of the capacitances coupled to the word line substantially equal to each other independently of variations in manufacturing conditions.

In the case where the compensating circuit is constituted by a MOSFET, since it is only necessary to equalize the numbers of MOSFETs connected to the dummy word line and those connected to the word line, any MOSFET can be employed, provided that the MOSFET has such an arrangement that the gate thereof is connected to the dummy word line, and the data line and the earth line are

made non-conductive. For instance, the arrangement may be such that the compensating circuit is not connected to the data line and the earth line.

In the case where the ECC circuit is incorporated in the ROM, it is possible to substantially improve the production yield of the semiconductor memory owing to the error correcting function of the ECC circuit.

In the case where an ECC circuit is incorporated in a one-chip semiconductor memory to redress any defective memory cell thereby to improve the production yield, an ECC circuit having the one-bit error correcting function requires, for example, four-bit parity signals for eight-bit data; six-bit parity signals for 32-bit data; and eight-bit parity signals for 100-bit data. Thus, when the number of data bits is smaller, the percentage of the number of parity bits with respect to the whole is larger, so that the memory capacity of the memory cell arrays decreases. On the other hand, if the number of data bits is increased, it is necessary to provide a large number of external terminals for the data output; therefore, it is difficult to incorporate the ECC circuit in the semiconductor memory.

The ROM is arranged such that data of a plurality of bits delivered from the ECC circuit are taken out in several stages by means of the multiplexor MPX as

- described above. Thereby, it is possible to increase the number of data bits and reduce the percentage of the number of necessary parity bits with respect to the whole without increasing the number of output terminals of the
- 5 IC chip. Accordingly, the memory capacity of the memory arrays can be increased.

In general, in a monolithic IC type large-capacity memory, defects apt to be produced simultaneously in a plurality of memory cells adjacent to each other are attributable to, for example, the inevitable imperfectness of the IC manufacturing technique. For example, such a mask film as comprising a photoresist provided for selectively etching an insulation film and conductor film is not necessarily well processed owing to the ununiformity of the material and the adverse effects of dust. If the pattern of the processed mask film should have defects such as undesirable unevenness and pinholes, the defectives are unfavourably transferred to the insulation film and conductor film to be processed by the mask film. If there should be any defect in the mask film employed for the impurity ion implantation, impurity ions are introduced into an undesired portion on the semiconductor substrate surface or the impurity ions are not introduced into a desired portion. The semiconductor substrate to be employed, on the other hand, has defects such as the crystal defect which brings defects to the characteristics of the semiconductor elements to be formed thereon.

In the large-capacity memory, semiconductor elements and wiring layers are miniaturized in order to

obtain a higher density. In consequence, a plurality of circuit elements are apt to be included in one defect area. Accordingly, a plurality of defective cells are liable to be produced in concentration. In the readout operation of the ROM, each of a plurality of memory MOSFETs from which data are simultaneously taken out is selected from one of the memory cell arrays corresponding to the sense amplifiers as described above. More specifically, a plurality of bits fed to the ECC circuit are taken out from the memory MOSFETs formed at positions on the semiconductor substrate distributed away from each other. The data read out from a plurality of defective cells produced in concentration are dispersed in a plurality of sets of data. As a result, the error bit included in one set of data can be reduced to on the order of one bit at maximum. Therefore, even an ECC circuit having a low error correcting capability (correcting capability of one bit) is able to correct the error bit. Accordingly, it is possible to substantially improve the production yield of the semiconductor memory.

If the memory cell arrays, the dummy cell arrays and the sense amplifier are constituted by dynamic circuits, static readout data and parity signals can be supplied to the ECC circuit by providing

123

a latching circuit. In consequence, the ECC circuit can be constituted by a simple static circuit. In other words, it becomes possible to simplify the construction and operation of the ECC circuit.

5 Moreover, the current consumption can be reduced by thus providing the latching circuit. More specifically, if no latching circuit is provided, the changes of the sense amplifier output signals caused by the precharging operation are undesirably supplied to
10 the ECC circuit. Consequently, the ECC circuit is actuated when the operation thereof is not desired. The undesirable operation of the ECC circuit increases the current consumption. The provision of the latching circuit prevents the changes of the output signals of
15 the sense amplifier caused by the precharging operation from being transmitted to the ECC circuit. More specifically, during the time when the memory arrays, the sense amplifier, and the main amplifier are being precharged, the output terminals of the ECC circuit and
20 the main amplifier are substantially separated from each other by the tristate circuits. Therefore, the potential change at the output terminal of the main amplifier caused by the precharging operation is not transmitted to the ECC circuit. Accordingly, it is
25 possible to prevent the ECC circuit from being

undesirably actuated; hence, it is possible to prevent an increase in the current consumption.

Since the static circuits are constituted by CMOS circuits, the power consumption of the ROM can be reduced.

In an alternative construction an arrangement may be employed in which the address buffer for receiving the external address signals delivered from the outside and the output buffer for forming the output signals delivered to the outside are constituted by static circuits and the other circuits are all constituted by dynamic circuits. It will also be noted that in the case where the address decoders are constituted by static circuits, the address selecting operation is initiated immediately after application of the external address signals. This arrangement has the advantage that the memory arrays, the dummy cell arrays and the sense amplifier can be precharged by utilizing the period from the application of the external address signals until the selection of addresses.

The invention can be widely used for vertical mask ROMs, programmable ROMs (electrically programmable ROMs), or electrically alterable ROMs in addition to the above-described horizontal mask ROMs. It is possible to modify the arrangements of the memory cell

arrays, the dummy cell arrays, the sense amplifiers, the address decoders and the control signal generators.

Attention is drawn to our Application No. 83.15593 (Serial No. 2,123,640) from which this
5 Application has been divided.

Attention is further drawn to our Application Nos. 85.19907; 85.19908 and 85.19909, respectively published under Serial Nos. 2,163,313; 2,162,397; and 2,162,398, which have also been divided out of the
10 parent Application No. 83.15593.

CLAIMS.

1. A semiconductor memory including:

(a) a first memory array including: a plurality of read-only memory cells each having a selection terminal, an output terminal and a reference terminal and arranged in a matrix form; plurality word lines provided to respectively correspond to the rows of said memory cells and respectively coupled to the selection terminals of said plural memory cells; a plurality of data lines provided to respectively correspond to the columns of said memory cells and respectively coupled to the output terminals of said plural memory cells; and a plurality of earth lines provided to respectively correspond to the columns of said memory cells and respectively coupled to the reference terminals of said plural memory cells;

(b) a second memory array having a similar construction to that of the said first memory array;

(c) first and second common data lines;

(d) a first column switch controlled by switch control signals in order to couple that one of the plural data lines of said first memory array, which is to be selected to said first common data line;

(e) a second column switch controlled by switch control signals corresponding to the first mentioned switch control signals in order to couple that one of the plural data lines of said second memory array, which is to be selected, to said second common data line;



(f) a differential amplifier having a pair of input terminals, a first terminal being coupled to said first common data line and a second terminal being coupled to said second common data line;

5 (g) a plurality of dummy cells provided to respectively correspond to the data lines of said first and second memory arrays and each including: an output terminal to be coupled to the corresponding one of said data lines; a selection terminal to be fed with an
10 operation control signal; and a reference terminal to be fed with earth potential of the circuit, said dummy cells applying the reference potential, which is to be referred to by said differential amplifier, to the corresponding ones of said data lines when they are respectively brought
15 to their operative states; and

(h) a selecting circuit including: a plurality of output terminals, which are to be coupled to the word lines of said first and second memory arrays; a plurality of output terminals which are to be coupled to the
20 selection terminals of said dummy cells,

wherein the reference potential, which is to be referred to by said differential amplifier when one of the memory cells of said first memory array is selected, is generated by that one of said dummy cells, which is
25 coupled to said second memory array, whereas the reference potential, which is to be referred to by said differential amplifier when one of the memory cells of said second



memory array, is generated by that one of said dummy cells, which is coupled to said first memory array, and wherein each of said first and second column switches comprises tree-like circuits constituted by a plurality of MOSFETs which are controlled by said switch control signals.

2. A semiconductor memory according to claim 1, additionally including:

(i) a plurality of switching elements having respective selecting terminals and provided between the earth lines in said first and second memory cell arrays and the earth potential point of the circuit respectively;

(j) a control circuit for forming a control signal for controlling said selecting circuit.

3. A semiconductor memory according to claim 2, wherein in order to select one of the memory cells in said first or second memory cell arrays, one of said switching elements connected with the reference terminal of the memory cell to be selected is made conductive by said selecting circuit, and when a predetermined time has passed after the potential of the word line connected with the selecting terminal of the memory cell to be selected starts to change to the selection potential of the memory cells, said control circuit forms a control signal for controlling said selecting circuit so as to bring the potential of the word line to the non-selection potential of the memory cells.



4. A semiconductor memory according to claim 3,
wherein said differential amplifier comprises a dynamic
differential amplifier which is dynamically operated by
a control signal formed by said control circuit, and
5 wherein said control circuit forms a control signal for
controlling said selecting circuit so as to bring the
potential of the word lines to the non-selection potential
of the memory cells in synchronism with the formation of
the control signal for dynamically operating said dynamic
10 differential amplifier.

5. A semiconductor memory according to claim 3,
wherein said differential amplifier comprises a dynamic
differential circuit which is dynamically operated by a
control signal formed by said control circuit.

15 6. A semiconductor memory according to any one of
the preceding claims 3 to 5, wherein each of said memory
cells comprises a storage semiconductor element arranged
to have a first or second conductance corresponding to
the data stored therein when the memory cell is selected.

20 7. A semiconductor memory according to claim 6,
further including a plurality of precharging elements
for precharging the respective data lines in said first
and second memory cell arrays.

8. A semiconductor memory according to claim 7,
25 further including a plurality of precharging elements
for precharging the respective earth lines in said first
and second memory cell arrays.



9. A semiconductor memory according to claim 3, wherein each of said switching elements comprises a MOSFET.

10. A semiconductor memory according to claim 4 or 5, wherein said dynamic differential amplifier comprises:

5 a first MOSFET of first conductivity type to the gate of which said first common data line is connected;

a second MOSFET of first conductivity type to the gate of which said second common data line is connected;

a switching MOSFET provided between first
10 electrodes of said first and second MOSFETs on one hand and a first potential point on the other and ON/OFF controlled by a control signal delivered from said control circuit; and

a load circuit provided between second
15 electrodes of said first and second MOSFETs on one hand and a second potential point on the other.

11. A semiconductor memory according to claim 2, wherein each of said first and second column switches comprises tree-like circuits each constituted by a
20 plurality of MOSFETs.

12. A semiconductor memory according to claim 11, wherein each of said tree-like circuits comprises a first MOSFET having one input/output electrode thereof connected to one of the data lines, a second MOSFET
25 having one input/output electrode thereof connected to another one of the data lines in the same memory array as said data line and the other input/output electrode



(31)

- 112 -

thereof connected to the other input/output electrode of the first MOSFET, and a third MOSFET series-connected between the other input/output electrode of said second MOSFET and the common data line corresponding to said memory cell array; said first and second MOSFETs being arranged to be complementarily ON/OFF operated by said selecting signals.

