

TERMINAL CHARGING SYSTEM, CHARGING METHOD, AND TERMINAL

TECHNICAL FIELD

[0001] The present disclosure generally relates to a terminal technical field, and more particularly, to a charging system for a terminal, a charging method for a terminal, and a terminal.

BACKGROUND

[0002] Nowadays, mobile terminals such as smart phones are increasingly favored by consumers. However, the mobile terminal consumes large power energy, and needs to be charged frequently.

[0003] Typically, the mobile terminal is charged by a power adapter. The power adapter generally includes a primary rectifier circuit, a primary filter circuit, a transformer, a secondary rectifier circuit, a secondary filter circuit and a control circuit, such that the power adapter converts an input alternating current of 220V into a stable and low voltage direct current (for example, 5V) suitable for requirements of the mobile terminal, and provides the direct current to a power management device and a battery of the mobile terminal, thereby realizing charging the mobile terminal.

[0004] However, as the power of the power adapter becomes larger, for example, upgrade from 5W to 10W, 15W, 25W and other larger power, more electronic elements capable of bearing large power and realizing better control are required for adaptation, which not only increases a size of the power adapter, but also increases a production cost and manufacture difficulties of the power adapter.

SUMMARY

[0005] The present disclosure is made based on the inventor's knowledge and research on the following issues.

[0006] The inventors find that, during a charging to a battery of a mobile terminal by a power adapter, as the power of the power adapter becomes larger, it is easy to increase polarization resistance of the battery and increase temperature of the battery, thus reducing a service life of the battery, and affecting a reliability and a safety of the battery.

[0007] Moreover, when powered with an alternating current, most devices cannot work directly with the alternating current, this is because the alternating current such as mains supply of 220V and 50Hz outputs electric energy discontinuously. In order to avoid the discontinuity, it needs to use an electrolytic capacitor to store the electric energy, such that when the power supply

is in the trough period, continuity of power supply relies on the electric energy stored in the electrolytic capacitor to maintain a stable power supply. Thus, when an alternating current power source charges the mobile terminal via the power adapter, the alternating current such as the alternating current of 220V provided by the alternating current power source is converted into a stable direct current, and the stable direct current is provided to the mobile terminal. However, the power adapter charges the battery in the mobile terminal so as to supply power to the mobile terminal indirectly, and the continuity of power supply can be guaranteed by the battery, such that it is unnecessary for the power adapter to output a stable direct current continuously when charging the battery.

[0008] Further, in the related art, when the mobile terminal is charged in the VOOC charging mode with a low voltage and high current, since the power adapter is directly coupled to the battery and the power adapter is configured to adjust the output voltage and current, the power adapter needs to know information on voltage of the battery, to determine whether a target voltage is met according to the information on the voltage of the battery, and to decrease the output current when the target voltage is met. However, the information on the voltage of the battery is typically obtained by ADC sampling, and the sampled voltage is transient voltage which is available during a direct current charging process but incurs an error during a charging process with the pulsating voltage. Since the input current is of pulsating and internal resistance of cell exists in the battery, the battery cross the battery varies with fluctuation of the pulsating current, such that the voltage of the battery would have a peak and a valley. In this case, in order to avoid overvoltage of the battery, it is required to ensure that the peak voltage of the battery does not exceed nominal voltage. However, since the voltage sampled by ADC sampling is transient voltage, when the sampled voltage is valley voltage, an influence on adjustment of system may be caused.

[0009] Accordingly, a first objective of the present disclosure is to provide a charging system for a terminal, which enables a voltage with a pulsating waveform outputted by a power adapter to be applied to a battery of the terminal directly, thus realizing miniaturization and low cost of the power adapter, prolonging a service life of the battery and ensuring that the sampled voltage is peak voltage of the battery. In this way, the power adapter can adjust a charging state in time, so as to ensure safety and reliability of the system.

[0010] A second objective of the present disclosure is to provide a terminal. A third objective of the present disclosure is to provide a charging method for a terminal.

[0011] To achieve above objectives, embodiments of a first aspect of the present disclosure provide a charging system for a terminal. The charging system includes a power adapter and a terminal. The power adapter is configured to convert an input alternating current to output a

voltage with a pulsating waveform, to provide the voltage with the pulsating waveform to the terminal and to output a peak synchronizing signal according to a peak voltage of the voltage with the pulsating waveform. The terminal includes a battery and a quick charging component. The quick charging component is configured to apply the voltage with the pulsating waveform to the battery, to acquire the peak synchronizing signal, to acquire a peak voltage of the battery according to the peak synchronizing signal, and to communicate with the power adapter such that the power adapter adjusts a charging state according to the peak voltage of the battery.

[0012] With the charging system according to embodiments of the present disclosure, the power adapter is configured to output the voltage with the pulsating waveform, and the quick charging component directly applies the voltage with the pulsating waveform outputted by the power adapter to the battery, thus realizing fast charging to the battery directly by the pulsating output voltage/current. In contrast to the conventional constant voltage and constant current, a magnitude of the pulsating output voltage/current changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interfaces may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve charging speed, and decrease heat emitted by the battery, thus ensuring a reliability and safety of the terminal during the charging. Moreover, since the power adapter outputs the voltage with the pulsating waveform, it is unnecessary to provide an electrolytic capacitor in the power adapter, which not only realizes simplification and miniaturization of the power adapter, but also decreases cost greatly. Furthermore, in the process that the power adapter charges the battery of the terminal in a pulsating charging mode, the power adapter outputs the peak synchronizing signal according to the peak voltage of the voltage with the pulsating waveform, the quick charging component acquires the peak synchronizing signal and samples the voltage of the battery according to the peak synchronizing signal to acquire the peak voltage of the battery, such that the sampled voltage is peak voltage of the battery, and the power adapter can adjust the charging state according to the peak voltage of the battery in time, thus ensuring safety and reliability of the system.

[0013] To achieve above objectives, embodiments of a second aspect of the present disclosure provide a terminal. The terminal includes a battery and a quick charging component. The quick charging component is configured to apply the voltage with the pulsating waveform outputted by a power adapter to the battery. The power adapter is configured to convert an input alternating current to output the voltage with a pulsating waveform, to provide the voltage with the pulsating waveform to the terminal and to output a peak synchronizing signal according to a peak

voltage of the voltage with the pulsating waveform. The quick charging component is further configured to acquire the peak synchronizing signal, to acquire a peak voltage of the battery according to the peak synchronizing signal, and to communicate with the power adapter such that the power adapter adjusts a charging state according to the peak voltage of the battery.

5 **[0014]** With the terminal according to embodiments of the present disclosure, the quick charging component directly applies the voltage with the pulsating waveform outputted by the power adapter to the battery, thus realizing fast charging to the battery directly by the pulsating output voltage/current. In contrast to the conventional constant voltage and constant current, a magnitude of the pulsating output voltage/current changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interfaces may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve charging speed, and decrease heat emitted by the battery, thus ensuring a reliability and safety of the battery during the charging. Moreover, since the power adapter outputs the voltage with the pulsating waveform, it is unnecessary to provide an electrolytic capacitor, which not only realizes simplification and miniaturization of the power adapter, but also decreases cost greatly. Furthermore, in the process that the battery is charged in a pulsating charging mode, the power adapter outputs the peak synchronizing signal according to the peak voltage of the voltage with the pulsating waveform, the quick charging component acquires the peak synchronizing signal and samples the voltage of the battery according to the peak synchronizing signal to acquire the peak voltage of the battery, such that the sampled voltage is peak voltage of the battery, and the power adapter can adjust the charging state according to the peak voltage of the battery in time, thus ensuring safety and reliability of the system.

25 **[0015]** To achieve above objectives, embodiments of a third aspect of the present disclosure provide a charging method for a terminal. The terminal includes a battery and a quick charging component. The method includes: converting by a power adapter an input alternating current to output a voltage with a pulsating waveform, providing the voltage with the pulsating waveform to the terminal and outputting a peak synchronizing signal according to a peak voltage of the voltage with the pulsating waveform; applying by the quick charging component the voltage with the pulsating waveform to the battery, acquiring the peak synchronizing signal, acquiring a peak voltage of the battery according to the peak synchronizing signal; and communicating by the quick charging component with the power adapter such that the power adapter adjusts a charging state according to the peak voltage of the battery.

30 **[0016]** With the charging method for a terminal according to embodiments of the present

disclosure, the power adapter is configured to output the voltage with the pulsating waveform and meeting the charging requirement, and the quick charging component directly applies the voltage with the pulsating waveform outputted by the power adapter to the battery, thus realizing fast charging to the battery directly by the pulsating output voltage/current. In contrast to the
5 conventional constant voltage and constant current, a magnitude of the pulsating output voltage/current changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interface may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve
10 charging speed, and decrease heat emitted by the battery, thus ensuring a reliability and safety of the terminal during the charging. Moreover, since the voltage with the pulsating waveform is output from the power adapter, it is unnecessary to provide an electrolytic capacitor in the power adapter, which not only realizes simplification and miniaturization of the power adapter, but also decreases cost greatly. Furthermore, in the process that the battery is charged in a pulsating
15 charging mode, the power adapter outputs the peak synchronizing signal according to the peak voltage of the voltage with the pulsating waveform, the quick charging component acquires the peak synchronizing signal and samples the voltage of the battery according to the peak synchronizing signal to acquire the peak voltage of the battery, such that the sampled voltage is peak voltage of the battery, and the power adapter can adjust the charging state according to the
20 peak voltage of the battery in time, thus ensuring safety and reliability of the system.

BRIEF DESCRIPTION OF THE DRAWINGS

- [0017]** Fig. 1A is a schematic diagram illustrating a charging system for a terminal using a flyback switching power supply according to an embodiment of the present disclosure.
- 25 **[0018]** Fig. 1B is a schematic diagram illustrating a charging system for a terminal using a forward switching power supply according to an embodiment of the present disclosure.
- [0019]** Fig. 1C is a schematic diagram illustrating a charging system for a terminal using a push-pull switching power supply according to an embodiment of the present disclosure.
- [0020]** Fig. 1D is a schematic diagram illustrating a charging system for a terminal using a
30 half-bridge switching power supply according to an embodiment of the present disclosure.
- [0021]** Fig. 1E is a schematic diagram illustrating a charging system for a terminal using a full-bridge switching power supply according to an embodiment of the present disclosure.
- [0022]** Fig. 2A is a block diagram of a charging system for a terminal according to an embodiment of the present disclosure.

[0023] Fig. 2B is a block diagram of a charging system for a terminal having a function of battery voltage detection according to an embodiment of the present disclosure.

[0024] Fig. 3 is a schematic diagram illustrating a waveform of a charging voltage outputted to a battery from a power adapter according to an embodiment of the present disclosure.

5 **[0025]** Fig. 4 is a schematic diagram illustrating a waveform of a charging current outputted to a battery from a power adapter according to an embodiment of the present disclosure.

[0026] Fig. 5 is a schematic diagram illustrating a control signal outputted to a switch unit according to an embodiment of the present disclosure.

10 **[0027]** Fig. 6 is a schematic diagram illustrating a fast charging process according to an embodiment of the present disclosure.

[0028] Fig. 7A is a schematic diagram of a charging system for a terminal according to an embodiment of the present disclosure.

[0029] Fig. 7B is a schematic diagram of a power adapter with a LC filter circuit according to an embodiment of the present disclosure.

15 **[0030]** Fig. 8 is a schematic diagram of a charging system for a terminal according to another embodiment of the present disclosure.

[0031] Fig. 9 is a schematic diagram of a charging system for a terminal according to yet another embodiment of the present disclosure.

20 **[0032]** Fig. 10 is a schematic diagram of a charging system for a terminal according to still another embodiment of the present disclosure.

[0033] Fig. 11 is a block diagram of a sampling unit according to an embodiment of the present disclosure.

[0034] Fig. 12 is a schematic diagram of a charging system for a terminal according to still yet another embodiment of the present disclosure.

25 **[0035]** Fig. 13 is a schematic diagram of a terminal according to an embodiment of the present disclosure.

[0036] Fig. 14 is a schematic diagram of a terminal according to another embodiment of the present disclosure.

30 **[0037]** Fig. 15 is a flow chart of a charging method for a terminal according to an embodiment of the present disclosure.

[0038] Fig. 16 is a flow chart of a charging method for a terminal according to an embodiment of the present disclosure.

DETAILED DESCRIPTION

[0039] Descriptions will be made in detail to embodiments of the present disclosure, examples of which are illustrated in drawings, in which the same or similar elements and the elements having same or similar functions are denoted by like reference numerals throughout the descriptions. The embodiments described herein with reference to drawings are explanatory, are intended to understand the present disclosure, and are not construed to limit the present disclosure.

[0040] Before describing charging system for a terminal, a terminal, a power adapter and a charging method for a terminal according to embodiments of the present disclosure, a power adapter (hereinafter, “related adapter”) for charging the device to be charged such as a terminal in the related art will be described.

[0041] Voltage outputted by the related adapter is basically constant, such as 5V, 9V, 12V or 20V or the like, when the related adapter works in a constant voltage mode.

[0042] The voltage outputted by the related adapter is unsuitable for being directly applied to both ends of a battery. It is required to convert the voltage by a conversion circuit in the device to be charged (such as the terminal) to obtain a charging voltage and/or charging current expected by the battery in the device to be charged (such as the terminal).

[0043] The conversion circuit is configured to convert the voltage outputted by the related adapter, to meet a requirement of the charging voltage and/or charging current expected by the battery.

[0044] As an example, the conversion circuit may be a charging management module, such as a charging integrated circuit (IC) in the terminal. During a charging process of the battery, the conversion circuit may be configured to manage the charging voltage and/or charging current of the battery. The conversion circuit may have functionality of a voltage feedback module and/or functionality of a current feedback module, so as to manage the charging voltage and/or charging current of the battery.

[0045] For example, the charging process of the battery may include one or more of a trickle charging stage, a constant current charging stage and a constant voltage charging stage. In the trickle charging stage, the conversion circuit may utilize a current feedback loop to ensure that a current flowing into the battery in the trickle charging stage meets the charging current (such as a first charging current) expected by the battery. In the constant current charging stage, the conversion circuit may utilize a current feedback loop to ensure that the current flowing into the battery in the constant current charging stage meets the charging current (such as a second charging current, which may be greater than the first charging current) expected by the battery. In the constant voltage charging stage, the conversion circuit may utilize a voltage feedback loop to ensure that a voltage applied to both ends of the battery in the constant voltage charging stage

meets the charging voltage expected by the battery.

[0046] As an example, when the voltage outputted by the related adapter is greater than the charging voltage expected by the battery, the conversion circuit may be configured to perform a buck conversion on the voltage outputted by the related adapter to enable a buck-converted charging voltage to meet the requirement of the charging voltage expected by the battery. As another example, when the voltage outputted by the related adapter is less than the charging voltage expected by the battery, the conversion circuit may be configured to perform a boost conversion on the voltage outputted by the related adapter to enable a boost-converted charging voltage to meet the requirement of the charging voltage expected by the battery.

[0047] As another example, assume that the related adapter outputs a constant voltage of 5V. When the battery includes a single battery cell (such as a lithium battery cell, a charging cut-off voltage of a single battery cell is typically 4.2V), the conversion circuit (for example, a buck circuit) may perform a buck conversion on the voltage outputted by the related adapter, such that the charging voltage obtained after the buck conversion meets a requirement of the charging voltage expected by the battery.

[0048] As yet another example, assume that the related adapter outputs a constant voltage of 5V. When the related adapter charges a battery including two or more battery cells (such as lithium battery cell, a charging cut-off voltage of a single battery cell is typically 4.2V) coupled in series, the conversion circuit (for example, a boost circuit) may perform a boost conversion on the voltage outputted by the related adapter, such that the charging voltage obtained after the boost conversion meets a requirement of the charging voltage expected by the battery.

[0049] Limited by a poor conversion efficiency of the conversion circuit, unconverted electric energy is lost in a form of heat, and the heat may gather inside the device to be charged (such as the terminal). A design space and a space for heat dissipation of the device to be charged (such as the terminal) are small (for example, the physical size of a mobile terminal used by a user becomes thinner and thinner, while plenty of electronic elements are densely arranged in the mobile terminal to improve performance of the mobile terminal), which not only increases difficulty in designing the conversion circuit, but also results in that it is hard to dissipate the heat gathered in the device to be charged (such as the terminal) in time, thus further causing an abnormality of the device to be charged (such as the terminal).

[0050] For example, the heat gathered on the conversion circuit may cause a thermal interference on electronic elements neighboring the conversion circuit, thus causing abnormal operations of the electronic elements. For another example, the heat gathered on the conversion circuit may shorten the service life of the conversion circuit and neighboring electronic elements.

For yet another example, the heat gathered on the conversion circuit may cause a thermal interference on the battery, thus causing abnormal charging and/or abnormal discharging of the battery. For still another example, the heat gathered on the conversion circuit may increase the temperature of the device to be charged (such as the terminal), thus affecting user experience during the charging. For still yet another example, the heat gathered on the conversion circuit may short-circuit the conversion circuit, such that the voltage outputted by the related adapter is directly applied to both ends of the battery, thus causing an abnormality in charging of the battery, which brings safety hazard if the over-voltage charging lasts for a long time, for example, the battery may explode.

[0051] The power adapter according to embodiments of the present disclosure may obtain status information of the battery. The status information of the battery at least includes electric quantity information and/or voltage information of the battery. The power adapter adjusts the voltage outputted by itself according to the obtained status information of the battery, to meet the requirement of the charging voltage and/or charging current expected by the battery. The output voltage after the adjustment may be directly applied to both ends of the battery for charging the battery. The voltage outputted by the power adapter may be a voltage with a pulsating waveform.

[0052] The power adapter may have functionality of the voltage feedback module and functionality of the current feedback module, so as to realize a government of the charging voltage and/or charging current of the battery.

[0053] In some embodiments, the power adapter may adjust the voltage outputted by itself according to the obtained status information of the battery as follows. The power adapter may obtain the status information of the battery in real time, and adjust the voltage outputted by itself according to the status information of the battery obtained in real time, to meet the charging voltage and/or charging current expected by the battery.

[0054] In some embodiments, the power adapter may adjust the voltage outputted by itself according to the status information of the battery obtained in real time as follows. During the charging process, with the increasing of the charging voltage of the battery, the power adapter may obtain status information of the battery at different time points in the charging process, and adjust the voltage outputted by itself in real time according to the status information of the battery at different time points in the charging process, to meet the requirement of the charging voltage and/or charging current expected by the battery. The output voltage after the adjustment of the power adapter may be directly applied to both ends of the battery to charge the battery.

[0055] For example, the charging process of the battery may include at least one of a trickle charging stage, a constant current charging stage and a constant voltage charging stage. In

the trickle charging stage, the power adapter may output the first charging current (the first charging current may be a current with a pulsating waveform) to charge the battery, so as to meet the requirement of the charging current expected by the battery. In the constant current charging stage, the power adapter may utilize a current feedback loop to ensure that the current outputted by the power adapter and flowing into the battery in the constant current charging stage meets the requirement of the charging current expected by the battery (such as a second charging current, which may be a current with a pulsating waveform, and may be greater than the first charging current. For example, the second charging current being greater than the first charging current means that, a peak value of the current with the pulsating waveform in the constant current charging stage is greater than that of the current with the pulsating waveform in the trickle charging stage, while “constant current” of the constant current charging stage means that, in the constant current charging stage, a peak value or a mean value of the current with the pulsating waveform is basically constant). In the constant voltage charging stage, the power adapter may utilize a voltage feedback loop to ensure that a voltage (i.e., a voltage with a pulsating waveform) outputted by the power adapter to the device to be charged (such as the terminal) within the constant voltage charging stage is constant.

[0056] For example, the power adapter according to embodiments of the present disclosure is mainly configured to control the constant current charging stage of the battery in the device to be charged (such as the terminal). In other embodiments, the control on the trickle charging stage and the constant voltage charging stage of the battery in the device to be charged (such as the terminal) can be realized by the power adapter according to embodiments of the present disclosure in coordination with an additional charging chip in the device to be charged (such as the terminal). Compared to the constant current charging stage, the charging power received by the battery in the trickle charging stage and the constant voltage charging stage is smaller, such that the conversion loss and heat accumulation of the charging chip in the device to be charged (such as the terminal) is acceptable. In some embodiments, the constant current charging stage or the constant current stage involved in embodiments of the present disclosure may refer to a charging mode in which the current outputted by the power adapter is controlled. It is unnecessary to keep the current outputted by the power adapter completely constant. For example, the constant current may refer to that, a peak value or a mean value of the current with the pulsating waveform outputted by the power adapter is basically constant, or keeps constant during a certain time period. For example, in practice, the power adapter typically adopts a multi-stage constant current mode for charging in the constant current charging stage.

[0057] The multi-stage constant current charging may include N constant current stages,

where N is an integer no less than 2. The first charging stage of the multi-stage constant current charging starts with a predetermined charging current. M constant current stages in the multi-stage constant current charging are performed in sequence from the first charging stage to the (N-1)th charging stage. After the constant current charging is switched from one constant current stage to the next constant current stage, the peak value or mean value of the current with the pulsating waveform may be decreased. When the battery voltage reaches a charging stop voltage threshold, the constant current charging is switched from the present constant current stage to the next constant current stage. The current change between two adjacent constant current stages may be gradual, or may be in a stepped skip manner.

[0058] Further, it should be noted that, the terminal according to embodiments of the present disclosure includes, but is not limited to a device configured to receive/transmit communication signals via a wired connection (for example, public switched telephone network (PSTN), digital subscriber line (DSL) connection, digital cable connection, direct cable connection and/or another data connection/network) and/or via a wireless interface (for example, cellular network, wireless local area network (WLAN), digital TV network such as digital video broadcasting handheld (DVB-H) network, satellite network, an amplitude modulation-frequency modulation (AM-FM) broadcasting transmitter, and/or a wireless interface of another communication terminal). The communication terminal configured to communicate via the wireless interface may be referred to as “wireless communication terminal”, “wireless terminal” and/or “mobile terminal”. Examples of a mobile terminal include, but are not limited to a satellite phone or a cell phone, a terminal combining a cell radio phone and a personal communication system (PCS) having capability of data process, fax, and data communication, a personal digital assistant (PDA) including a radio phone, a pager, Internet/Intranet access, a web browser, a note pad & address book, a calendar and/or a global positioning system (GPS) receiver, and a common laptop and/or handheld receiver, or other electronic devices including a radio phone transceiver.

[0059] In addition, in embodiments of the present disclosure, when the voltage with the pulsating waveform outputted by the adapter is directly applied to both ends of the battery in the terminal to charge the battery, the charging current may be characterized by a pulsating waveform such as a steamed bun waveform. In some embodiments, the charging current may be used to charge the battery intermittently. A period of the charging current may vary with a frequency of an input alternating current (such as a frequency of an alternating current power grid). For example, the frequency corresponding to the period of the charging current may be an integral multiple or a fraction of the frequency of the power grid. Moreover, when the charging current is used to charge the battery intermittently, a current waveform corresponding to the charging current may be

formed of one pulse or a set of pulses synchronous to the power grid.

[0060] In the following, a charging system, a terminal, a power adapter, and a charging method for a terminal provided in embodiments of the present disclosure will be described with reference to drawings.

5 **[0061]** Referring to Figs. 1A-14, the charging system for a terminal provided in embodiments of the present disclosure includes a power adapter 1 and a terminal 2.

[0062] In an embodiment of the present disclosure, as illustrated in Fig. 2A and Fig. 2B, the power adapter 1 is configured to convert an input alternating current (mains supply, for example AC of 220V) to output a voltage with a pulsating waveform (hereinafter, “the third voltage with the third pulsating waveform”), to provide the voltage with the pulsating waveform to the terminal 2, and to output a peak synchronizing signal according to a peak voltage of the voltage with the pulsating waveform. As illustrated in Fig. 2B, the terminal 2 includes a battery 202 and a quick charging component 206 and an electricity meter 207. The electricity meter 207 is coupled to the power adapter 1 and the battery 202 respectively. The electricity meter 207 is configured to sample a voltage of the battery 202 in response to receiving the peak synchronizing signal, so as to acquire the peak voltage of the battery 202. The quick charging component 206 is configured to apply the voltage with the pulsating waveform to the battery 202, to communicate with the electricity meter 207 to acquire the peak voltage of the battery 202, and to communicate with the power adapter 1 to send the peak voltage of the battery 202 to the power adapter 1, such that the power adapter 1 determines whether to adjust a charging state according to the peak voltage of the battery 202.

[0063] The electricity meter 207 is configured to receive the peak synchronizing signal, to sample the voltage of the battery 202 in response to receiving the peak synchronizing signal, so as to acquire the peak voltage of the battery 202. The electricity meter 207 is further configured to communicate with the quick charging component 206 to send the peak voltage of the battery 202 to the quick charging component 206.

[0064] In another embodiment of the present disclosure, the charging system for a terminal may include a power adapter and a terminal. The power adapter is configured to convert an input alternating current to output a voltage with a pulsating waveform, to provide the voltage with the pulsating waveform to the terminal and to output a peak synchronizing signal according to a peak voltage of the voltage with the pulsating waveform. The terminal includes a battery and a quick charging component. The quick charging component is configured to apply the voltage with the pulsating waveform to the battery, to acquire the peak synchronizing signal, to acquire a peak voltage of the battery according to the peak synchronizing signal, and to communicate with the

power adapter such that the power adapter adjusts a charging state according to the peak voltage of the battery.

[0065] In an embodiment, the quick charging component is further configured to send the peak voltage of the battery to the power adapter, such that the power adapter determines whether to adjust the charging state according to the peak voltage of the battery.

[0066] In an embodiment, the quick charging component is further configured to determine whether to adjust the charging state of the power adapter according to the peak voltage of the battery, and to send an adjusting signal to the power adapter in response to determining to adjust the charging state of the power adapter, such that the power adapter adjusts the charging state according to the adjusting signal.

[0067] In embodiments of the present disclosure, the quick charging component can send the acquired peak voltage of the battery to the power adapter, such that the power adapter can determine according to the peak voltage of the battery whether to adjust the charging state. The quick charging component can determine according to the peak voltage of the battery whether to adjust the charging state of the power adapter, and send the adjusting signal to the power adapter in response to determining to adjust the charging state of the power adapter, such that the power adapter can adjust the charging state according to the adjusting signal.

[0068] Regardless of whether the quick charging component or the power adapter performs the determination, the power adapter can adjust the charging state according to the peak voltage of the battery.

[0069] The quick charging component can directly acquire the peak synchronizing signal by, for example, communicating with the power adapter, and directly acquire the peak voltage of the battery according to the peak synchronizing signal by, for example, directly sampling the voltage of the battery, so as to acquire the peak voltage of the battery.

[0070] In another embodiment of the present disclosure, the terminal 2 includes a battery 202, a quick charging component 206 and an electricity meter 207. The electricity meter 207 is configured to sample the voltage of the battery. The quick charging component 206 is configured to sample the voltage of the battery through the electricity meter 207 in response to acquiring the peak synchronizing signal so as to acquire the peak voltage of the battery.

[0071] The quick charging component can directly acquire the peak synchronizing signal by, for example, communicating with the power adapter, and sample the voltage of the battery through the electricity meter in response to receiving the peak synchronizing signal, so as to acquire the peak voltage of the battery.

[0072] Adjusting the charging state refers to adjusting an operation state of the power

adapter, for example adjusting the output voltage and/or output current of the power adapter.

[0073] In an embodiment of the power adapter, as illustrated in Fig. 2B, the electricity meter 207 can communicate with the quick charging component 206 in a manner of I2C, so as to send the peak voltage of the battery to the quick charging component 206. The peak voltage of the battery can be sent to the power adapter 1 via the communication between the quick charging component 206 and the power adapter 1, such that the power adapter 1 can determine whether to adjust the charging state in time according to the peak voltage of the battery.

[0074] With the charging system for a terminal according to embodiments of the present disclosure, when the power adapter charges the terminal in a pulsating charging mode, the power adapter can know the time when the voltage with the pulsating waveform reaches the peak voltage, such that the power adapter can send the peak synchronizing signal to the electricity meter at the arrival of the peak voltage of the voltage with the pulsating waveform, so as to instruct the electricity meter to sample the voltage of the battery right now. In this way, the voltage sampled by the electricity meter is the peak voltage of the battery. The quick charging component sends the peak voltage of the battery to the power adapter, such that the power adapter can adjust the charging state in time, thus ensuring the safety and reliability of the system.

[0075] In an embodiment of the present disclosure, as illustrated in Fig. 2A and Fig. 2B, the power adapter 1 includes a first charging interface 105 and the terminal 2 includes a second charging interface 201. When the first charging interface 105 is coupled to the second charging interface 201, a charging path and a communication path can be established between the quick charging component 206 and the power adapter 1.

[0076] The quick charging component 206 communicates with the power adapter 1 via the communication path to determine a charging mode. The charging mode includes a first charging mode and a second charging mode.

[0077] In an embodiment of the present disclosure, when the power adapter 1 charges the terminal 2 in the first charging mode, the quick charging component 206 applies the voltage with the pulsating waveform to the battery 202.

[0078] In embodiments of the present disclosure, the quick charging component 206 may include a charging control switch 203, a controller 204 and a communication unit 205 as described below.

[0079] In the following, the process during which the power adapter 1 charges the terminal 2 will be described in detail with reference to accompany drawings.

[0080] As illustrated in Fig. 2A, the power adapter 1 includes a first rectifier 101, a switch unit 102, a transformer 103, a second rectifier 104, a first charging interface 105, a sampling unit

106, and a control unit 107. The first rectifier 101 is configured to rectify an input alternating current (mains supply, for example AC of 220V) to output a first voltage with a first pulsating waveform, for example a voltage with a steamed bun waveform. As illustrated in Fig. 1A, the first rectifier 101 may be a full-bridge rectifier circuit formed of four diodes. The switch unit 102 is configured to modulate the first voltage with the first pulsating waveform according to a control signal. The switch unit 102 may be formed of MOS transistors. A pulse width modulation (PWM) control is performed on the MOS transistors to perform a chopping modulation on the voltage with the steamed bun waveform. The transformer 103 is configured to output a second voltage with a second pulsating waveform according to the modulated first voltage. The second rectifier 104 is configured to rectify the second voltage with the second pulsating waveform and output a third voltage with a third pulsating waveform. The second rectifier 104 may be formed of diodes or MOS transistors, and can realize a secondary synchronous rectification, such that the third pulsating waveform keeps synchronous with a waveform of the modulated first voltage. It should be noted that, the third pulsating waveform keeping synchronous with the waveform of the modulated first voltage means that, a phase of the third pulsating waveform is consistent with that of the waveform of the modulated first voltage, and a variation trend of magnitude of the third pulsating waveform is consistent with that of the waveform of the modulated first voltage. The first charging interface 105 is coupled to the second rectifier 104. The first current sampling circuit 1061 is configured to sample current and/or voltage outputted by the second rectifier 104 to obtain a current sampling value and/or a voltage sampling value. The control unit 107 is coupled to the sampling unit 106 and the switch unit 102 respectively. The control unit 107 is configured to output the control signal to the switch unit 102, to adjust a duty ratio of the control signal according to the current sampling value and/or the voltage sampling value, such that the third voltage outputted by the second rectifier 104 meets a charging requirement of the terminal 2.

[0081] As illustrated in Fig. 2A, the terminal 2 includes a second charging interface 201 and a battery 202. The second charging interface 201 is coupled to the battery 202. When the second charging interface 201 is coupled to the first charging interface 105, the second charging interface 201 is configured to apply the third voltage with the third pulsating waveform to the battery 202, so as to charge the battery 202.

[0082] In an embodiment of the present disclosure, as illustrated in Fig. 1A, the power adapter 1 may adopt a flyback switching power supply. In detail, the transformer 103 may include a primary winding and a secondary winding. One end of the primary winding is coupled to a first output end of the first rectifier 101. A second output end of the first rectifier 101 is grounded. Another end of the primary winding is coupled to the switch unit 102 (for example, when the

switch unit 102 is a MOS transistor, the other end of the primary winding is coupled to a drain of the MOS transistor). The transformer 103 is configured to output a second voltage with a second pulsating waveform according to the modulated first voltage.

[0083] The transformer 103 is a high-frequency transformer of which a working frequency ranges from 50KHz to 2MHz. The high-frequency transformer is configured to couple the modulated first voltage to the secondary side so as to output via the secondary winding. In embodiments of the present disclosure, with the high-frequency transformer, a characteristic of a small size compared to the low-frequency transformer (also known as an industrial frequency transformer, mainly used in the frequency of mains supply such as an alternating current of 50Hz or 60Hz) may be exploited to realize miniaturization of the power adapter 1.

[0084] In an embodiment of the present disclosure, as illustrated in Fig. 1B, the power adapter 1 may also adopt a forward switching power supply. In detail, the transformer 103 includes a first winding, a second winding and a third winding. A dotted terminal of the first winding is coupled to a second output end of the first rectifier 101 via a backward diode. A non-dotted terminal of the first winding is coupled to a dotted terminal of the second winding and then coupled to a first output end of the first rectifier 101. A non-dotted terminal of the second winding is coupled to the switch unit 102. The third winding is coupled to the second rectifier 104. The backward diode is configured to realize reverse peak clipping. An induced potential generated by the first winding may perform amplitude limiting on a reverse potential via the backward diode and return limited energy to an output of the first rectifier 101, so as to charge the output of the first rectifier 101. Moreover, a magnetic field generated by current flowing through the first winding may demagnetize a core of the transformer, so that the magnetic field intensity in the core of the transformer returns to an initial state. The transformer 103 is configured to output the second voltage with the second pulsating waveform according to the modulated first voltage.

[0085] According to an embodiment of the present disclosure, as illustrated in Fig. 1C, the above-mentioned power adapter 1 may adopt a push-pull switching power supply. In detail, the transformer includes a first winding, a second winding, a third winding and a fourth winding. A dotted terminal of the first winding is coupled to the switch unit 102. A non-dotted terminal of the first winding is coupled to a dotted terminal of the second winding and then coupled to the first output end of the first rectifier 101. A non-dotted terminal of the second winding is coupled to the switch unit 102. A non-dotted terminal of the third winding is coupled to a dotted terminal of the fourth winding. The transformer is configured to output the second voltage with the second pulsating waveform according to the modulated first voltage.

[0086] As illustrated in Fig. 1C, the switch unit 102 includes a first MOS transistor Q1 and

a second MOS transistor Q2. The transformer 103 includes a first winding, a second winding, a third winding and a fourth winding. A dotted terminal of the first winding is coupled to a drain of the first MOS transistor Q1 in the switch unit 102. A non-dotted terminal of the first winding is coupled to a dotted terminal of the second winding. A node between the non-dotted terminal of the first winding and the dotted terminal of the second winding is coupled to the first output end of the first rectifier 101. A non-dotted terminal of the second winding is coupled to a drain of the second MOS transistor Q2 in the switch unit 102. A source of the first MOS transistor Q1 is coupled to a source of the second MOS transistor Q2 and then coupled to the second output end of the first rectifier 101. A dotted terminal of the third winding is coupled to a first input end of the second rectifier 104. A non-dotted terminal of the third winding is coupled to a dotted terminal of the fourth winding. A node between the non-dotted terminal of the third winding and the dotted terminal of the fourth winding is grounded. A non-dotted terminal of the fourth winding is coupled to a second input end of the second rectifier 104.

[0087] As illustrated in Fig. 1C, the first input end of the second rectifier 104 is coupled to the dotted terminal of the third winding, and the second input end of the second rectifier 104 is coupled to the non-dotted terminal of the fourth winding. The second rectifier 104 is configured to rectify the second voltage with the second pulsating waveform to output the third voltage with the third pulsating waveform. The second rectifier 104 may include two diodes. An anode of one diode is coupled to the dotted terminal of the third winding. An anode of another diode is coupled to a non-dotted terminal of the fourth winding. A cathode of one diode is coupled to that of the other diode.

[0088] According to an embodiment of the present disclosure, as illustrated in Fig. 1D, the above-mentioned power adapter 1 may also adopt a half-bridge switching power supply. In detail, the switch unit 102 includes a first MOS transistor Q1, a second MOS transistor Q2, a first capacitor C1 and a second capacitor C2. The first capacitor C1 and the second capacitor C2 are coupled in series, and then coupled in parallel to the output ends of the first rectifier 101. The first MOS transistor Q1 and the second MOS transistor Q2 are coupled in series, and then coupled in parallel to the output ends of the first rectifier 101. The transformer 103 includes a first winding, a second winding and a third winding. A dotted terminal of the first winding is coupled to a node between the first capacitor C1 and the second capacitor C2 coupled in series. A non-dotted terminal of the first winding is coupled to a node between the first MOS transistor Q1 and the second MOS transistor Q2 coupled in series. A dotted terminal of the second winding is coupled to the first input end of the second rectifier 104. A non-dotted terminal of the second winding is coupled to a dotted terminal of the third winding, and then grounded. A non-dotted terminal of the

third winding is coupled to the second input end of the second rectifier 104. The transformer 103 is configured to output the second voltage with the second pulsating waveform according to the modulated first voltage.

[0089] According to an embodiment of the present disclosure, as illustrated in Fig. 1E, the above-mentioned power adapter 1 may also adopt a full-bridge switching power supply. In detail, the switch unit 102 includes a first MOS transistor Q1, a second MOS transistor Q2, a third MOS transistor Q3 and a fourth MOS transistor Q4. The third MOS transistor Q3 and the fourth MOS transistor Q4 are coupled in series and then coupled in parallel to the output ends of the first rectifier 101. The first MOS transistor Q1 and the second MOS transistor Q2 are coupled in series and then coupled in parallel to the output ends of the first rectifier 101. The transformer 103 includes a first winding, a second winding and a third winding. A dotted terminal of the first winding is coupled to a node between the third MOS transistor Q3 and the fourth MOS transistor Q4 coupled in series. A non-dotted terminal of the first winding is coupled to a node between the first MOS transistor Q1 and the second MOS transistor Q2 coupled in series. A dotted terminal of the second winding is coupled to the first input end of the second rectifier 104. A non-dotted terminal of the second winding is coupled to a dotted terminal of the third winding, and then grounded. A non-dotted terminal of the third winding is coupled to the second input end of the second rectifier 104. The transformer 103 is configured to output the second voltage with the second pulsating waveform according to the modulated first voltage.

[0090] Therefore, in embodiments of the present disclosure, the above-mentioned power adapter 1 may adopt any one of the flyback switching power supply, the forward switching power supply, the push-pull switching power supply, the half-bridge switching power supply and the full-bridge switching power supply to output the voltage with the pulsating waveform.

[0091] Further, as illustrated in Fig. 1A, the second rectifier 104 is coupled to a secondary winding of the transformer 103. The second rectifying unit 104 is configured to rectify the second voltage with the second pulsating waveform to output a third voltage with a third pulsating waveform. The second rectifier 104 may consist of diodes, and can realize a secondary synchronous rectification, such that the third pulsating waveform keeps synchronous with a waveform of the modulated first voltage. It should be noted that, the third pulsating waveform keeping synchronous with the waveform of the modulated first voltage means that, a phase of the third pulsating waveform is consistent with that of the waveform of the modulated first voltage, and a variation trend of magnitude of the third pulsating waveform is consistent with that of the waveform of the modulated first voltage. The first charging interface 105 is coupled to the second rectifier 104. The sampling unit 106 is configured to sample the voltage and/or current outputted

by the second rectifier 104 to obtain a voltage sampling value and/or a current sampling value. The control unit 107 is coupled to the sampling unit 106 and the switch unit 102 respectively. The control unit 107 is configured to output the control signal to the switch unit 102, and to adjust a duty ratio of the control signal according to the current sampling value and/or the voltage sampling value, such that the third voltage outputted by the second rectifier 104 meets a charging requirement of the terminal 2.

[0092] As illustrated in Fig. 1A, the terminal 2 includes a second charging interface 201 and a battery 202. The second charging interface 201 is coupled to the battery 202. When the second charging interface 201 is coupled to the first charging interface 105, the second charging interface 201 applies the third voltage with the third pulsating waveform to the battery 202 to charge the battery 202.

[0093] It should be noted that, the third voltage with the third pulsating waveform meeting the charging requirement means that, the third voltage and current with the third pulsating waveform need to meet the charging voltage and charging current when the battery is charged. In other words, the control unit 107 is configured to adjust the duty ratio of the control signal (such as a PWM signal) according to the sampled voltage and/or current outputted by the power adapter, so as to adjust the output of the second rectifier 104 in real time and realize a closed-loop adjusting control, such that the third voltage with the third pulsating waveform meets the charging requirement of the terminal 2, thus ensuring the stable and safe charging of the battery 202. In detail, a waveform of a charging voltage outputted to a battery 202 is illustrated in Fig. 3, in which the waveform of the charging voltage is adjusted according to the duty ratio of the PWM signal. A waveform of a charging current outputted to a battery 202 is illustrated in Fig. 4, in which the waveform of the charging current is adjusted according to the duty ratio of the PWM signal.

[0094] It can be understood that, when adjusting the duty ratio of the PWM signal, an adjusting instruction may be generated according to the voltage sampling value, or according to the current sampling value, or according to the voltage sampling value and the current sampling value.

[0095] Therefore, in embodiments of the present disclosure, by controlling the switch unit 102, a PWM chopping modulation is directly performed on the first voltage with the first pulsating waveform i.e. the steamed bun waveform after a rectification, and then a modulated voltage is sent to the high-frequency transformer and is coupled from the primary side to the secondary side via the high-frequency transformer, and then restore to the voltage/current with the steamed bun waveform after a synchronous rectification. The voltage/current with the steamed bun waveform is directly transmitted to the battery so as to realize fast charging to the battery. The magnitude of the

voltage with the steamed bun waveform may be adjusted according to the duty ratio of the PWM signal, such that the output of the power adapter may meet the charging requirement of the battery. It can be seen, the power adapter according to embodiments of the present disclosure, without providing electrolytic capacitors at the primary side and the secondary side, may directly charge the battery via the voltage with the steamed bun waveform, such that a size of the power adapter may be reduced, thus realizing miniaturization of the power adapter, and decreasing cost greatly.

[0096] In an embodiment of the present disclosure, the control unit 107 may be a micro controller unit (MCU), which means that the control unit 107 may be a micro processor integrated with a switch driving control function, a synchronous rectification function, a voltage/current adjusting control function.

[0097] According to an embodiment of the present disclosure, the control unit 107 is further configured to adjust a frequency of the control signal according to the voltage sampling value and/or the current sampling value. That is, the PWM signal outputted to the switch unit 102 can be controlled by the control unit 107 to continuously output for a time period, and then the output of the PWM signal is stopped for a predetermined time period and then restarted. In this way, the voltage applied to the battery is intermittent, thus realizing the intermittent charging of the battery, which avoids a safety hazard caused by heating phenomenon occurring when the battery is charged continuously and improves the reliability and safety of the charging of the battery.

[0098] For lithium batteries, under a low temperature condition, since the conductivity of ions and electrons of the lithium battery decreases, it is prone to intensify degree of polarization during a charging process for the lithium battery. A continuous charging not only makes this polarization serious but also increases a possibility of lithium precipitation, thus affecting safety performance of the battery. Furthermore, the continuous charging may accumulate heat generated due to the charging, thus leading to a rising of internal temperature of the battery. When the temperature exceeds a certain value, performance of the battery may be limited, and possibility of safety hazard is increased.

[0099] In embodiments of the present disclosure, by adjusting the frequency of the control signal, the power adapter outputs intermittently, which means that a battery resting process is introduced into the charging process, such that the lithium precipitation due to the polarization during the continuous charging is reduced and continuous accumulation of generated heat may be avoided to realize drop in the temperature, thus ensuring the safety and reliability of charging of the battery.

[00100] The control signal outputted to the switch unit 102 is illustrated in Fig. 5, for example. The PWM signal is continuously outputted for a time period, then output of the PWM

signal is stopped for a certain time period, and then the PWM signal is continuously outputted for a time period again. In this way, the control signal output to the switch unit 102 is intermittent, and the frequency is adjustable.

[00101] As illustrated in Fig. 1A, the control unit 107 is coupled to the first charging interface 105. The control unit 107 is further configured to obtain status information of the terminal 2 by performing a communication with the terminal 2 via the first charging interface 105. In this way, the control unit 107 is further configured to adjust the duty ratio of the control signal (such as the PWM signal) according to the status information of the terminal, the voltage sampling value and/or the current sampling value.

[00102] The status information of the terminal may include an electric quantity of the battery, a temperature of the battery, a voltage of the battery, interface information of the terminal and information on path impedance of the terminal.

[00103] In detail, the first charging interface 105 includes a power wire and a data wire. The power wire is configured to charge the battery. The data wire is configured to communicate with the terminal. When the second charging interface 201 is coupled to the first charging interface 105, communication query instructions may be transmitted by the power adapter 1 and the terminal 2 to each other. A communication connection can be established between the power adapter 1 and the terminal 2 after receiving a corresponding reply instruction. The control unit 107 may obtain the status information of the terminal 2, so as to negotiate with the terminal 2 about a charging mode and charging parameters (such as the charging current, the charging voltage) and to control the charging process.

[00104] The charging mode supported by the power adapter and/or the terminal may include a first charging mode and a second charging mode. A charging speed of the first charging mode is faster than that of the second charging mode. For example, a charging current of the first charging mode is greater than that of the second charging mode. In general, the second charging mode may be understood as a charging mode in which a rated output voltage is 5V and a rated output current is less than or equal to 2.5A. In addition, in the second charging mode, D+ and D- in the data wire of an output port of the power adapter may be short-circuited. On the contrary, in the first charging mode according to embodiments of the present disclosure, the power adapter may communicate with the terminal via D+ and D- wire in the data wire to realize data exchange, i.e., fast charging instructions may be sent by the power adapter and the terminal to each other. The power adapter sends a fast charging query instruction to the terminal. After receiving a fast charging reply instruction from the terminal, the power adapter obtains the status information of the terminal and starts the first charging mode according to the fast charging reply instruction. The charging current

in the first charging mode may be greater than 2.5A, for example, may be 4.5A or more. The second charging mode is not limited in embodiments of the present disclosure. As long as the power adapter supports two charging modes one of which has a charging speed (or current) greater than the other charging mode, the charging mode with a slower charging speed may be regarded as the second charging mode. As to the charging power, the charging power in the first charging mode may be greater than or equal to 15W.

[00105] The control unit 107 communicates with the terminal 2 via the first charging interface 105 to determine the charging mode. The charging mode includes the first charging mode and the second charging mode.

[00106] In detail, the power adapter is coupled to the terminal via a universal serial bus (USB) interface. The USB interface may be a general USB interface, a micro USB interface, or a USB interface in other types. A data wire in the USB interface is configured as the data wire in the first charging interface, and configured for a bidirectional communication between the power adapter and the terminal. The data wire may be the D+ and/or D- wire in the USB interface. The bidirectional communication may refer to an information interaction performed between the power adapter and the terminal.

[00107] The power adapter performs the bidirectional communication with the terminal via the data wire in the USB interface, so as to determine to charge the terminal in the first charging mode.

[00108] It should be noted that, during a process that the power adapter negotiates with the terminal whether to charge the terminal in the first charging mode, the power adapter may only keep a coupling with the terminal but does not charge the terminal, or charges the terminal in the second charging mode or charges the terminal with a small current, which is not limited herein.

[00109] The power adapter adjusts a charging current to a charging current in the first charging mode, and charges the terminal. After determining to charge the terminal in the first charging mode, the power adapter may directly adjust the charging current to the charging current in the first charging mode or may negotiate with the terminal about the charging current of the first charging mode. For example, the charging current in the first charging mode may be determined according to a current electric quantity of the battery of the terminal.

[00110] In embodiments of the present disclosure, the power adapter does not increase the output current blindly for fast charging, but needs to perform the bidirectional communication with the terminal so as to negotiate whether to adopt the first charging mode. Compared with the related art, the safety of fast charging is improved.

[00111] As an embodiment, the control unit 107 is configured to send a first instruction to

the terminal when performing the bidirectional communication with the terminal via the first charging interface so as to determine to charge the terminal in the first charging mode. The first instruction is configured to query the terminal whether to operate in the first charging mode. The control unit 107 is configured to receive a reply instruction of the first instruction from the terminal. The reply instruction of the first instruction is configured to indicate that the terminal agrees to operate in the first charging mode.

[00112] As an embodiment, before the control unit sends the first instruction to the terminal, the power adapter is configured to charge the terminal in the second charging mode. The control unit is configured to send the first instruction to the terminal when determining that a charging duration of the second charging mode is greater than a predetermined threshold.

[00113] It should be understood that, when the power adapter determines that the charging duration of the second charging mode is greater than the predetermined threshold, the power adapter may determine that the terminal has identified it as a power adapter, and the fast charging query communication may start.

[00114] As an embodiment, after determining to charge the terminal for a predetermined time period with a charging current greater than or equal to a predetermined current threshold, the power adapter is configured to send the first instruction to the terminal.

[00115] As an embodiment, the control unit is further configured to control the power adapter to adjust a charging current to a charging current in the first charging mode by controlling the switch unit. Before the power adapter charges the terminal with the charging current in the first charging mode, the control unit is configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine a charging voltage in the first charging mode, and to control the power adapter to adjust a charging voltage to the charging voltage in the first charging mode.

[00116] As an embodiment, when the control unit performs the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging voltage in the first charging mode, the control unit is configured to send a second instruction to the terminal, to receive a reply instruction of the second instruction sent from the terminal, and to determine the charging voltage in the first charging mode according to the reply instruction of the second instruction. The second instruction is configured to query whether a current output voltage of the power adapter is suitable as the charging voltage in the first charging mode. The reply instruction of the second instruction is configured to indicate that the current output voltage of the power adapter is suitable as the charging voltage in the first charging mode, relatively high the or low for being used as the charging voltage in the first charging mode.

[00117] As an embodiment, before controlling the power adapter to adjust the charging current to the charging current in the first charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current in the first charging mode.

5 **[00118]** As an embodiment, when performing the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current in the first charging mode, the control unit is configured to send a third instruction to the terminal, to receive a reply instruction of the third instruction sent from the terminal and to determine the charging current in the first charging mode according to the reply instruction of the third instruction. The third instruction is configured to query a maximum charging current currently supported by the terminal. The reply instruction of the third instruction is configured to indicate the maximum charging current currently supported by the terminal.

[00119] The power adapter may determine the above maximum charging current as the charging current in the first charging mode, or may set the charging current as a charging current less than the maximum charging current.

15 **[00120]** As an embodiment, during a process that the power adapter charges the terminal in the first charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface, so as to continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit.

[00121] The power adapter may query the status information of the terminal continuously, for example, query the voltage of the battery of the terminal, the electric quantity of the battery, etc., so as to continuously adjust the charging current outputted from the power adapter to the battery.

25 **[00122]** As an embodiment, when the control unit performs the bidirectional communication with the terminal via the data wire of the first charging interface to continuously adjust the charging current outputted to the battery from the power adapter by controlling the switch unit, the control unit is configured to send a fourth instruction to the terminal, to receive a reply instruction of the fourth instruction sent by the terminal in which the fourth instruction is configured to query a current voltage of the battery in the terminal, and to adjust the charging current outputted from the power adapter to the battery by controlling the switch unit according to the current voltage of the battery. The reply instruction of the fourth instruction is configured to indicate the current voltage of the battery in the terminal.

[00123] As an embodiment, the control unit is configured to adjust the charging current

outputted to the battery from the power adapter to a charging current value corresponding to the current voltage of the battery by controlling the switch unit according to the current voltage of the battery and a predetermined correspondence between battery voltage values and charging current values.

5 **[00124]** In detail, the power adapter may store the correspondence between battery voltage values and charging current values in advance. The power adapter may also perform the bidirectional communication with the terminal via the data wire of the first charging interface to obtain from the terminal the correspondence between battery voltage values and charging current values stored in the terminal.

10 **[00125]** As an embodiment, during the process that the power adapter charges the terminal in the first charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine whether the first charging interface and the second charging interface are in poor contact. When determining that the first charging interface and the second charging interface are in poor contact,
15 the control unit is configured to control the power adapter to quit the first charging mode.

[00126] As an embodiment, before determining whether the first charging interface and the second charging interface are in poor contact, the control unit is further configured to receive from the terminal information indicating path impedance of the terminal. The control unit is configured to send a fourth instruction to the terminal. The fourth instruction is configured to query a current
20 voltage of the battery in the terminal. The control unit is configured to receive a reply instruction of the fourth instruction sent by the terminal. The reply instruction of the fourth instruction is configured to indicate the voltage of the battery in the terminal. The control unit is configured to determine path impedance from the power adapter to the battery according to an output voltage of the power adapter and the voltage of the battery. The control unit is configured to determine
25 whether the first charging interface and the second charging interface are in poor contact according to the path impedance from the power adapter to the battery, the path impedance of the terminal, and path impedance of a charging circuit between the power adapter and the terminal.

[00127] The terminal may record the path impedance thereof in advance. For example, since the terminals in the same type have the same structure, the path impedance of terminals in the same type is set to the same value when configuring factory settings. Similarly, the power adapter
30 may record the path impedance of the charging circuit in advance. When the power adapter obtains the voltage cross both ends of the battery of the terminal, the path impedance of the whole path can be determined according to the voltage drop cross two ends of the battery and the current of the path. When the path impedance of the whole path > the path impedance of the terminal + the path

impedance of the charging circuit, or the path impedance of the whole path – (the path impedance of the terminal + the path impedance of the charging circuit) > an impedance threshold, it can be considered that the first charging interface and the second charging interface are in poor contact.

[00128] As an embodiment, before the power adapter quits the first charging mode, the control unit is further configured to send a fifth instruction to the terminal. The fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[00129] After sending the fifth instruction, the power adapter may quit the first charging mode or reset.

[00130] The fast charging process according to embodiments of the present disclosure has been described from the perspective of the power adapter; hereinafter, the fast charging process according to embodiments of the present disclosure will be described from the perspective of the terminal in the following.

[00131] It should be understood that, the interaction between the power adapter and the terminal, relative characteristics, and functions described at the terminal side correspond to descriptions at the power adapter side, thus repetitive description will be omitted for simplification.

[00132] According to an embodiment of the present disclosure, as illustrated in Fig. 13, the terminal 2 further includes a charging control switch 203 and a controller 204. The charging control switch 203, such as a switch circuit formed of an electronic switch element, is coupled between the second charging interface 201 and the battery 202. The charging control switch 203 is configured to switch on or switch off a charging process of the battery 202 under control of the controller 204. In this way, the charging process of the battery 202 can be controlled at the terminal side, thus ensuring the safety and reliability of the charging of battery 202.

[00133] As illustrated in Fig. 14, the terminal 2 further includes a communication unit 205. The communication unit 205 is configured to establish a bidirectional communication between the controller 204 and the control unit 107 via the second charging interface 201 and the first charging interface 105. In other words, the terminal 2 and the power adapter 1 can perform the bidirectional communication via the data wire in the USB interface. The terminal 2 supports the first charging mode and the second charging mode. The charging current of the first charging mode is greater than that of the second charging mode. The communication unit 205 performs the bidirectional communication with the control unit 107 such that the power adapter 1 determines to charge the terminal 2 in the first charging mode, and the control unit 107 controls the power adapter 1 to output according to the charging current in the first charging mode, to charge the battery 202 in the

terminal 2.

[00134] In embodiments of the present disclosure, the power adapter 1 does not increase the output current blindly for the fast charging, but needs to perform the bidirectional communication with the terminal to negotiate whether to adopt the first charging mode. Compared with the related art, the safety of the fast charging process is improved.

[00135] As an embodiment, the controller is configured to receive the first instruction sent by the control unit via the communication unit. The first instruction is configured to query the terminal whether to start the first charging mode. The controller is configured to send a reply instruction of the first instruction to the control unit via the communication unit. The reply instruction of the first instruction is configured to indicate that the terminal agrees to start the first charging mode.

[00136] As an embodiment, before the controller receives the first instruction sent by the control unit via the communication unit, the battery in the terminal is charged by the power adapter in the second charging mode. When the control unit determines that a charging duration of the second charging mode is greater than a predetermined threshold, the control unit sends the first instruction to the communication unit in the terminal, and the controller receives the first instruction sent by the control unit via the communication unit.

[00137] As an embodiment, before the power adapter outputs according to the charging current in the first charging mode to charge the battery in the terminal, the controller is configured to perform the bidirectional communication with the control unit via the communication unit, such that the power adapter determines the charging voltage in the first charging mode.

[00138] As an embodiment, the controller is configured to receive a second instruction sent by the control unit, and to send a reply instruction of the second instruction to the control unit. The second instruction is configured to query whether a current output voltage of the power adapter is suitable as the charging voltage in the first charging mode. The reply instruction of the second instruction is configured to indicate that the current output voltage of the power adapter is suitable, high or low.

[00139] As an embodiment, the controller is configured to perform the bidirectional communication with the control unit, such that the power adapter determines the charging current in the first charging mode.

[00140] The controller is configured to receive a third instruction sent by the control unit, in which the third instruction is configured to query a maximum charging current currently supported by the terminal. The controller is configured to send a reply instruction of the third instruction to the control unit, in which the reply instruction of the third instruction is configured to indicate the

maximum charging current currently supported by the terminal, such that the power adapter determines the charging current in the first charging mode according to the maximum charging current.

[00141] As an embodiment, during a process that the power adapter charges the terminal in the first charging mode, the controller is configured to perform the bidirectional communication with the control unit, such that the power adapter continuously adjusts a charging current outputted to the battery from the power adapter.

[00142] The controller is configured to receive a fourth instruction sent by the control unit, in which the fourth instruction is configured to query a current voltage of the battery in the terminal. The controller is configured to send a reply instruction of the fourth instruction to the control unit, in which the reply instruction of the fourth instruction is configured to indicate the current voltage of the battery in the terminal, such that the power adapter continuously adjusts the charging current outputted to the battery from the power adapter according to the current voltage of the battery.

[00143] As an embodiment, during the process that the power adapter charges the terminal in the first charging mode, the controller is configured to perform the bidirectional communication with the control unit via the communication unit, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact.

[00144] The controller receives a fourth instruction sent by the control unit. The fourth instruction is configured to query a current voltage of the battery in the terminal. The controller sends a reply instruction of the fourth instruction to the control unit, in which the reply instruction of the fourth instruction is configured to indicate the current voltage of the battery in the terminal, such that the control unit determines whether the first charging interface and the second charging interface are in poor contact according to an output voltage of the power adapter and the current voltage of the battery.

[00145] As an embodiment, the controller is configured to receive a fifth instruction sent by the control unit. The fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[00146] In order to initiate and adopt the first charging mode, the power adapter may perform a fast charging communication procedure with the terminal, and fast charging of a battery can be realized after one or more handshakes. Referring to Fig. 6, the fast charging communication procedure according to embodiments of the present disclosure and respective stages in the fast charging process will be described in detail. It should be understood that, communication actions or operations illustrated in Fig. 6 are merely exemplary. Other operations or various modifications

of respective operations in Fig. 6 can be implemented in embodiments of the present disclosure. In addition, respective stages in Fig. 6 may be executed in an order different from that illustrated in Fig. 6, and it is unnecessary to execute all the operations illustrated in Fig. 6. It should be noted that, a curve in Fig. 6 represents a variation trend of a peak value or a mean value of the charging current, rather than a curve of an actual charging current.

[00147] As illustrated in Fig. 6, the fast charging process may include the following five stages.

[00148] Stage 1:

[00149] After being coupled to a power supply providing device, the terminal may detect the type of the power supply providing device via the data wire D+ and D-. When detecting that the power supply providing device is a power adapter, the terminal may absorb current greater than a predetermined current threshold I2, such as 1A. When the power adapter detects that the current outputted by the power adapter is greater than or equal to I2 within a predetermined time period (such as a continuous time period T1), the power adapter determines that the terminal has completed the recognition of the type of the power supply providing device. The power adapter initiates a handshake communication between the power adapter and the terminal, and sends an instruction 1 (corresponding to the above-mentioned first instruction) to query the terminal whether to operate in the first charging mode (or flash charging).

[00150] When receiving a reply instruction indicating that the terminal disagrees to operate in the first charging mode from the terminal, the power adapter detects the output current of the power adapter again. When the output current of the power adapter is still greater than or equal to I2 within a predetermined continuous time period (such as a continuous time period T1), the power adapter initiates a request again to query the terminal whether to operate in the first charging model. The above actions in stage 1 are repeated, until the terminal replies that it agrees to operate in the first charging mode or the output current of the power adapter is no longer greater than or equal to I2.

[00151] After the terminal agrees to operate in the first charging mode, the fast charging process is initiated, and the fast charging communication procedure goes into stage 2.

[00152] Stage 2:

[00153] For the voltage with the steamed bun waveform outputted by the power adapter, there may be several levels. The power adapter sends an instruction 2 (corresponding to the above-mentioned second instruction) to the terminal to query the terminal whether the output voltage of the power adapter matches to the current voltage of the battery (or whether the output voltage of the power adapter is suitable, i.e., suitable as the charging voltage in the first charging

mode), i.e., whether the output voltage of the power adapter meets the charging requirement.

[00154] The terminal replies that the output voltage of the power adapter is higher, lower or suitable. When the power adapter receives a feedback indicating that the output voltage of the power adapter is lower or higher from the terminal, the control unit adjusts the output voltage of the power adapter by one level by adjusting the duty ratio of the PWM signal, and sends the instruction 2 to the terminal again to query the terminal whether the output voltage of the power adapter matches.

[00155] The above actions in stage 2 are repeated, until the terminal replies to the power adapter that the output voltage of the power adapter is at a matching level. And then the fast charging communication procedure goes into stage 3.

[00156] Stage 3:

[00157] After the power adapter receives from the terminal the feedback indicating that the output voltage of the power adapter matches, the power adapter sends an instruction 3 (corresponding to the above-mentioned third instruction) to the terminal to query the maximum charging current currently supported by the terminal. The terminal returns to the power adapter the maximum charging current currently supported by itself, and then the fast charging communication procedure goes into stage 4.

[00158] Stage 4:

[00159] After receiving from the terminal a feedback indicating the maximum charging current supported by the terminal, the power adapter may set an output current reference value. The control unit 107 adjusts the duty ratio of the PWM signal according to the output current reference value, such that the output current of the power adapter meets the charging current requirement of the terminal, and the fast charging communication procedure goes into constant current stage. The constant current stage means that the peak value or mean value of the output current of the power adapter basically remains unchanged (which means that the variation amplitude of the peak value or mean value of the output current is very small, for example within a range of 5% of the peak value or mean value of the output current), namely, the peak value of the current with the third pulsating waveform keeps constant in each period.

[00160] Stage 5:

[00161] When the fast charging communication procedure goes into the constant current stage, the power adapter sends an instruction 4 (corresponding to the above-mentioned fourth instruction) at intervals to query the current voltage of battery in the terminal. The terminal may feedback to the power adapter the current voltage of the battery, and the power adapter may determine according to the feedback of the current voltage of the battery whether the USB contact

(i.e., the contact between the first charging interface and the second charging interface) is good and whether it is necessary to decrease the present charging current value of the terminal. When the power adapter determines that the USB contact is poor, the power adapter sends an instruction 5 (corresponding to the above-mentioned fifth instruction), and then the power adapter is reset, such that the fast charging communication procedure goes into stage 1 again.

[00162] In some embodiments of the present disclosure, in stage 1, when the terminal replies to the instruction 1, data corresponding to the instruction 1 may carry data (or information) on the path impedance of the terminal. The data on the path impedance of the terminal may be used in stage 5 to determine whether the USB contact is good.

[00163] In some embodiments of the present disclosure, in stage 2, the time period from when the terminal agrees to operate in the first charging mode to when the power adapter adjusts the voltage to a suitable value may be controlled to be within a certain range. If the time period exceeds a predetermined range, the terminal may determine that the request is abnormal, thus a quick reset is performed.

[00164] In some embodiments of the present disclosure, in stage 2, the terminal may give a feedback indicating that the output voltage of the power adapter is suitable/matching to the power adapter when the output voltage of the power adapter is adjusted to a value higher than the current voltage of the battery by ΔV (ΔV is about 200-500mV). When the terminal gives a feedback indicating that the output voltage of the power adapter is not suitable (higher or lower) to the power adapter, the control unit 107 adjusts the duty ratio of the PWM signal according to the voltage sampling value, so as to adjust the output voltage of the power adapter.

[00165] In some embodiments of the present disclosure, in stage 4, the adjusting speed of the output current value of the power adapter may be controlled to be within a certain range, thus avoiding an abnormal interruption of the fast charging due to a too fast adjusting speed.

[00166] In some embodiments of the present disclosure, in stage 5, the variation amplitude of the output current value of the power adapter may be controlled to be within 5%, i.e., stage 5 may be regarded as the constant current stage.

[00167] In some embodiments of the present disclosure, in stage 5, the power adapter monitors the impedance of a charging loop in real time, i.e., the power adapter monitors the impedance of the whole charging loop by measuring the output voltage of the power adapter, the present charging current and the read-out voltage of the battery in the terminal. When the impedance of the charging loop > the path impedance of the terminal + the impedance of the fast charging data wire, it may be considered that the USB contact is poor, and thus a fast charging reset is performed.

[00168] In some embodiments of the present disclosure, after the first charging mode is initiated, a time interval of communications between the power adapter and the terminal may be controlled to be in a certain range, such that the fast charging reset can be avoided.

[00169] In some embodiments of the present disclosure, the stop of the first charging mode (or the fast charging process) may be a recoverable stop or an unrecoverable stop.

[00170] For example, when the terminal detects that the battery is fully charged or the USB contact is poor, the fast charging is stopped and reset, and the fast charging communication procedure goes into stage 1. When the terminal disagrees to operate in the first charging mode, the fast charging communication procedure would not go into stage 2. This stop of the fast charging process may be considered as an unrecoverable stop.

[00171] For another example, when an abnormal occurs in the communication between the terminal and the power adapter, the fast charging is stopped and reset, and the fast charging communication procedure goes into stage 1. After requirements for stage 1 are met, the terminal agrees to operate in the first charging mode to recover the fast charging process. This stop of the fast charging process may be considered as a recoverable stop.

[00172] For another example, when the terminal detects an abnormal occurring in the battery, the fast charging is stopped and reset, and the fast charging communication procedure goes into stage 1. After the fast charging communication procedure goes into stage 1, the terminal disagrees to operate in the first charging mode. Till the battery returns to normal and the requirements for stage 1 are met, the terminal agrees to start the fast charging to recover the fast charging process. This stop of fast charging process may be considered as a recoverable stop.

[00173] It should be noted that, communication actions or operations illustrated in Fig. 6 are merely exemplary. For example, in stage 1, after the terminal is coupled to the power adapter, the handshake communication between the terminal and the power adapter may be initiated by the terminal. In other words, the terminal sends an instruction 1 to query the power adapter whether to operate in the first charging mode (or flash charging). When receiving a reply instruction indicating that the power adapter agrees to start the first charging mode from the power adapter, the terminal operates in the fast charging process.

[00174] It should be noted that, communication actions or operations illustrated in Fig. 6 are merely exemplary. For example, after stage 5, there may be a constant voltage charging stage. In other words, in stage 5, the terminal may feedback the current voltage of the battery in the terminal to the power adapter. As the voltage of the battery increases continuously, the charging process goes into the constant voltage charging stage when the current voltage of the battery reaches a constant voltage charging voltage threshold. The control unit 107 adjusts the duty ratio of the

PWM signal according to the voltage reference value (i.e., the constant voltage charging voltage threshold), such that the output voltage of the power adapter meets the charging voltage requirement of the terminal, i.e., the output voltage of the power adapter basically changes at a constant rate. During the constant voltage charging stage, the charging current decreases gradually.

5 When the current reduces to a certain threshold, the charging is stopped, and at this point, it is indicated that the battery is fully charged. The constant voltage charging refers to that the peak voltage with the third pulsating waveform basically keeps constant.

[00175] It should be noted that, in embodiments of the present disclosure, acquiring output voltage of the power adapter means that the peak value or mean value of voltage with the third pulsating waveform is acquired. Acquiring output current of the power adapter means that the peak value or mean value of current with the third pulsating waveform is acquired.

[00176] In an embodiment of the present disclosure, as illustrated in Fig. 7A, the power adapter 1 further includes a controllable switch 108 and a filtering unit 109 coupled in series. The controllable switch 108 and the filtering unit 109 connected in series are coupled to the first output end of the second rectifier 104. The control unit 107 is further configured to control the controllable switch 108 to switch on when determining that the charging mode is the second charging mode, and to control the controllable switch 108 to switch off when determining that the charging mode is the first charging mode. One or more groups of small capacitors are further coupled in parallel to the output end of the second rectifier 104, which can not only achieve noise reduction, but also reduce the occurrence of surge phenomenon. A LC filtering circuit or π type filtering circuit may be further coupled to the output end of the second rectifier 104, so as to filter out pulsating interference. As illustrated in Fig. 7B, an LC filtering circuit is coupled to the output end of the second rectifier 104. It should be noted that, capacitors in the LC filtering circuit or the π type filtering circuit are small capacitors, which occupy small space.

25 **[00177]** The filtering unit 109 includes a filtering capacitor, which supports a standard charging of 5V in the second charging mode. The controllable switch 108 may be formed of a semiconductor switch element such as a MOS transistor. When the power adapter charges the battery in the terminal in the second charging mode (or standard charging), the control unit 107 controls the controllable switch 108 to switch on so as to incorporate the filtering unit 109 into the circuit, such that the output of the second rectifier 104 can be filtered. In this way, this allows for better compatibility with current charging technology, i.e., the direct current can be applied to the battery in the terminal so as to achieve the direct current charging of the battery. For example, in general, the filtering unit includes an electrolytic capacitor and a common capacitor such as a small capacitor supporting standard charging of 5V (for example, a solid-state capacitor) coupled

in parallel. Since the electrolytic capacitor occupies a relatively large volume, in order to reduce the size of the power adapter, the electrolytic capacitor may be removed from the power adapter and only one capacitor with low capacitance is left. When the second charging mode is adopted, a branch where the small capacitor is located can be controlled to switch on to filter the current, so as to realize a stable output with low power to perform a direct current charging on the battery. When the first charging mode is adopted, a branch where the small capacitor is located can be controlled to switch off, and the output of the second rectifier 104, that is, the voltage/current of pulsating waveforms, can be directly applied to the battery without filtering, so as to realize a fast charging of the battery.

[00178] According to an embodiment of the present disclosure, the control unit 107 is further configured to obtain the charging current and/or the charging voltage in the first charging mode according to the status information of the terminal and to adjust the duty ratio of the control signal such as the PWM signal according to the charging current and/or the charging voltage in the first charging mode, when determining the charging mode as the first charging mode. In other words, when determining the current charging mode as the fast charging mode, the control unit 107 obtains the charging current and/or the charging voltage in the first charging mode according to the obtained status information of the terminal such as the voltage, the electric quantity and the temperature of the battery, running parameters of the terminal, and power consumption information of applications running on the terminal, and adjusts the duty ratio of the control signal according to the obtained charging current and/or the charging voltage, such that the output of the power adapter meets the charging requirement, thus realizing the fast charging of the battery.

[00179] The status information of the terminal includes the temperature of the terminal. When the temperature of the battery is greater than a first predetermined temperature threshold, or the temperature of the battery is less than a second predetermined temperature threshold, if the current charging mode is the first charging mode, the first charging mode will be switched to the second charging mode. The first predetermined temperature threshold is greater than the second predetermined temperature threshold. In other words, when the temperature of the battery is too low (for example, corresponding to less than the second predetermined temperature threshold) or too high (for example, corresponding to greater than the first predetermined temperature threshold), it is unsuitable to perform the fast charging, such that it needs to switch from the first charging mode to the second charging mode. In embodiments of the present disclosure, the first predetermined temperature threshold and the second predetermined temperature threshold can be set or can be written into a storage of the control unit (such as the MCU of the power adapter) according to actual situations.

[00180] In an embodiment of the present disclosure, the control unit 107 is further configured to control the switch unit 102 to switch off when the temperature of the battery is greater than a predetermined high temperature protection threshold. Namely, when the temperature of the battery exceeds the high temperature protection threshold, the control unit 107 needs to
5 apply a high temperature protection strategy to control the switch unit 102 to switch off, such that the power adapter stops charging the battery, thus realizing high temperature protection of the battery and improving the safety of charging. The high temperature protection threshold may be different from or the same as the first temperature threshold. In an embodiment, the high temperature protection threshold is greater than the first temperature threshold.

[00181] In another embodiment of the present disclosure, the controller is further configured to obtain the temperature of the battery, and to control the charging control switch to switch off when the temperature of the battery is greater than the predetermined high temperature protection threshold, that is, the charging control switch can be switched off at the terminal side, so as to stop the charging process of the battery and to ensure the safety of charging.

[00182] Moreover, in an embodiment of the present disclosure, the control unit is further configured to obtain a temperature of the first charging interface, and to control the switch unit to switch off when the temperature of the first charging interface is greater than a predetermined protection temperature. In other words, when the temperature of the charging interface exceeds a certain temperature, the control unit 107 needs to apply the high temperature protection strategy to
20 control the switch unit 102 to switch off, such that the power adapter stops charging the battery, thus realizing high temperature protection of the battery and improving the safety of charging.

[00183] Certainly, in another embodiment of the present disclosure, the controller performs the bidirectional communication with the control unit to obtain the temperature of the first charging interface. When the temperature of the first charging interface is greater than the
25 predetermined protection temperature, the controller controls the charging control switch to switch off (referring to Fig. 13 and Fig. 14), i.e., switch off the charging control switch at the terminal side, so as to stop the charging process of the battery, thus ensuring the safety of charging.

[00184] In detail, in an embodiment of the present disclosure, as illustrated in Fig. 8, the power adapter 1 further includes a driving unit 110 such as a MOSFET driver. The driving unit 110
30 is coupled between the switch unit 102 and the control unit 107. The driving unit 110 is configured to drive the switch unit 102 to switch on or switch off according to the control signal. Certainly, it should be noted, in other embodiments of the present disclosure, the driving unit 110 may also be integrated in the control unit 107.

[00185] Further, as illustrated in Fig. 8, the power adapter 1 further includes an isolation

unit 111. The isolation unit 111 is coupled between the driving unit 110 and the control unit 107, to realize signal isolation between the primary side and the secondary side of the power adapter 1 (or signal isolation between the primary winding and the secondary winding of the transformer 103). The isolation unit 111 may be implemented in an optocoupler isolation manner or in other isolation
5 manners. By providing the isolation unit 111, the control unit 107 may be disposed at the secondary side of the power adapter 1 (or the secondary winding side of the transformer 103), thereby facilitating communication with the terminal 2, and the space design of the power adapter 1 can be easier and simpler.

[00186] Certainly, it should be understood that, in other embodiments of the present
10 disclosure, both the control unit 107 and the driving unit 110 can be disposed at the primary side, in this way, the isolation unit 111 can be disposed between the control unit 107 and the sampling unit 106, so as to realize the signal isolation between the primary side and the secondary side of the power adapter 1.

[00187] Further, it should be noted that, in embodiments of the present disclosure, when the
15 control unit 107 is disposed at the secondary side, an isolation unit 111 is required, and the isolation unit 111 may be integrated in the control unit 107. In other words, when the signal is transmitted from the primary side to the secondary side or from the secondary side to the primary side, an isolation unit is required to realize the signal isolation.

[00188] In an embodiment of the present disclosure, as illustrated in Fig. 9, the power
20 adapter 1 further includes an auxiliary winding and a power supply unit 112. The auxiliary winding generates a fourth voltage with a fourth pulsating waveform according to the modulated first voltage. The power supply unit 112 is coupled to the auxiliary winding. The power supply unit 112 (for example, including a filtering voltage regulator module, a voltage converting module and the like) is configured to convert the fourth voltage with the fourth pulsating waveform to
25 output a direct current, and to supply power to the driving unit 110 and/or the control unit 107 respectively. The power supply unit 112 may be formed of a small filtering capacitor, a voltage regulator chip or other elements, processing and conversation on the fourth voltage with the fourth pulsating waveform can be achieved to output a low voltage direct current of 3.3V, 5V or the like.

[00189] In other words, the power supply of the driving unit 110 can be obtained through a
30 voltage conversation performed on the fourth voltage with the fourth pulsating waveform by the power supply unit 112. When the control unit 107 is disposed at the primary side, the power supply of the control unit 107 can also be obtained through a voltage conversation performed on the fourth voltage with the fourth pulsating waveform by the power supply unit 112. As illustrated in Fig. 9, when the control unit 107 is disposed at the primary side, the power supply unit 112

provides two direct current outputs, so as to supply power to the driving unit 110 and the control unit 107 respectively. An optocoupler isolation unit 111 is arranged between the control unit 107 and the sampling unit 106 to realize the signal isolation between the primary side and the secondary side of the power adapter 1.

5 **[00190]** When the control unit 107 is disposed at the primary side and integrated with the driving unit 110, the power supply unit 112 supplies power to the control unit 107 separately. When the control unit 107 is disposed at the secondary side and the driving unit 110 is disposed at the primary side, the power supply unit 112 supplies power to the driving unit 110 separately. The power supply to the control unit 107 is realized by the secondary side, for example, the third
10 voltage with the third pulsating waveform outputted by the second rectifier 104 is converted to a direct current through a power supply unit to supply power to the control unit 107.

[00191] Moreover, in embodiments of the present disclosure, multiple small capacitors are coupled in parallel to the output end of first rectifier 101 for filtering. Or a LC filtering circuit is coupled to the output end of the first rectifier 110.

15 **[00192]** In another embodiment of the present disclosure, as illustrated in Fig. 10, the power adapter 1 further includes a first voltage detecting unit 113. The first voltage detecting unit 113 is coupled to the auxiliary winding and the control unit 107 respectively. The first voltage detecting unit 113 is configured to detect the fourth voltage to generate a voltage detecting value. The control unit 107 is further configured to adjust the duty ratio of the control signal according to the
20 voltage detecting value.

[00193] In other words, the control unit 107 may reflect the voltage outputted by the second rectifier 104, according to the voltage outputted by the secondary winding and detected by the first voltage detecting unit 113, and then adjusts the duty ratio of the control signal according to the voltage detecting value, such that the output of the second rectifier 104 meets the charging
25 requirement of the battery.

[00194] In detail, in an embodiment of the present disclosure, as illustrated in Fig. 11, the sampling unit 106 includes a first current sampling circuit 1061 and a first voltage sampling circuit 1062. The first current sampling circuit 1061 is configured to sample the current outputted by the second rectifier 104 so as to obtain the current sampling value. The first voltage sampling circuit
30 1062 is configured to sample the voltage outputted by the second rectifier 104 so as to obtain the voltage sampling value.

[00195] In an embodiment of the present disclosure, the first current sampling circuit 1061 can sample the voltage on a resistor (current detection resistor) coupled to a first output end of the second rectifier 104 so as to sample the current outputted by the second rectifier 104. The first

voltage sampling circuit 1062 can sample the voltage across the first output end and a second output end of the second rectifier 104 so as to sample the voltage outputted by the second rectifier 104.

[00196] Moreover, in an embodiment of the present disclosure, as illustrated in Fig. 11, the first voltage sampling circuit 1062 includes a peak voltage sampling and holding unit, a cross-zero sampling unit, a discharging unit and an AD sampling unit. The peak voltage sampling and holding unit is configured to sample and hold a peak voltage of the third voltage. The cross-zero sampling unit is configured to sample a zero crossing point of the third voltage. The discharging unit is configured to perform a discharging on the peak voltage sampling and holding unit at the zero crossing point. The AD sampling unit is configured to sample the peak voltage in the peak voltage sampling and holding unit so as to obtain the voltage sampling value.

[00197] By providing the peak voltage sampling and holding unit, the cross-zero sampling unit, the discharging unit and the AD sampling unit in the first voltage sampling circuit 1062, the voltage outputted by the second rectifier 104 may be sampled accurately, and it can be guaranteed that the voltage sampling value is synchronized with the first voltage, i.e., the phase is synchronized and the variation trend of magnitude of the voltage sampling value is consistent with that of the first voltage.

[00198] According to an embodiment of the present disclosure, as illustrated in Fig. 12, the power adapter 1 further includes a second voltage sampling circuit 114. The second voltage sampling circuit 114 is configured to sample the first voltage with the first pulsating waveform. The second voltage sampling circuit 114 is coupled to the control unit 107. When the voltage value sampled by the second voltage sampling circuit 114 is greater than a first predetermined voltage value, the control unit 107 controls the switch unit 102 to switch on for a first predetermined time period, to discharge the surge voltage, spike voltage and the like in the first pulsating waveform.

[00199] As illustrated in Fig. 12, the second voltage sampling circuit 114 can be coupled to the first output end and the second output end of the first rectifier 101, so as to sample the first voltage with the first pulsating waveform. The control unit 107 judges the voltage value sampled by the second voltage sampling circuit 114. When the voltage value sampled by the second voltage sampling circuit 114 is greater than the first predetermined voltage value, it indicates that the power adapter 1 is suffering a lightning interference and a surge voltage occurs, and at this time, it needs to drain off the surge voltage to ensure the safety and reliability of charging. The control unit 107 controls the switch unit 102 to switch on for a certain time period to form a discharging path, such that the discharging is performed on the surge voltage caused by the lightning is drained off, thus avoiding the lightning interference on the power adapter when charging the terminal, and effectively improving the safety and reliability of the charging of the terminal. The first

predetermined voltage value may be determined according to actual situations.

[00200] In an embodiment of the present disclosure, during a process that the power adapter 1 charges the battery 202 in the terminal 2, the control unit 107 is further configured to control the switch unit 102 to switch off when the value of the voltage sampled by the sampling unit 106 is greater than a second predetermined voltage value. Namely, the control unit 107 further judges the magnitude of the value of the voltage sampled by the sampling unit 106. When the value of the voltage sampled by the sampling unit 106 is greater than the second predetermined voltage value, it indicates that the voltage outputted by the power adapter 1 is too high. At this time, the control unit 107 controls the switch unit 102 to switch off, such that the power adapter 1 stops charging the battery 202 in the terminal 2. In other words, the control unit 107 realizes the over-voltage protection of the power adapter 1 by controlling the switch unit 102 to switch off, thus ensuring the safety of charging.

[00201] Certainly, in an embodiment of the present disclosure, the controller 204 performs a bidirectional communication with the control unit 107 to obtain the value of the voltage sampled by the sampling unit 106 (referring to Fig. 13 and Fig. 14), and controls the charging control switch 203 to switch off when the value of the voltage sampled by the sampling unit 106 is greater than the second predetermined voltage value. Namely, the charging control switch 203 is controlled to switch off at the terminal 2 side, so as to stop the charging process of the battery 202, such that the safety of charging can be ensured.

[00202] Further, the control unit 107 is further configured to control the switch unit 102 to switch off when the value of the current sampled by the sampling unit 106 is greater than a predetermined current value. In other words, the control unit 107 is further configured to judge the magnitude of the value of the current sampled by the sampling unit 106. When the value of the current sampled by the sampling unit 106 is greater than the predetermined current value, it indicates that the current outputted by the power adapter 1 is too high. At this time, the control unit 107 controls the switch unit 102 to switch off, such that the power adapter 1 stops charging the terminal. In other words, the control unit 107 realizes the over-current protection of the power adapter 1 by controlling the switch unit 102 to switch off, thus ensuring the safety of charging.

[00203] Similarly, the controller 204 performs the bidirectional communication with the control unit 107 to obtain the value of the current sampled by the sampling unit 106 (referring to Fig. 13 and Fig. 14), and controls the charging control switch 203 to switch off when the value of the current sampled by the sampling unit 106 is greater than the predetermined current value. In other words, the charging control switch 203 is controlled to switch off at the terminal 2 side, so as to stop the charging process of the battery 202, thus ensuring the safety of charging.

[00204] The second predetermined voltage value and the predetermined current value may be set or written into a storage of the control unit (for example, the control unit 107 of the power adapter 1, such as an MCU) according to actual situations.

[00205] In embodiments of the present disclosure, the terminal may be a mobile terminal, such as a mobile phone, a mobile power supply such as a power bank, a multimedia player, a notebook PC, a wearable device or the like.

[00206] With the charging system for a terminal according to embodiments of the present disclosure, the power adapter is configured to output the voltage with the pulsating waveform, and the quick charging component directly applies the voltage with the pulsating waveform outputted by the power adapter to the battery, thus realizing fast charging to the battery directly by the pulsating output voltage/current. A magnitude of the pulsating output voltage/current changes periodically, compared with the conventional constant voltage and constant current, lithium precipitation of the lithium battery may be reduced and the service life of the battery may be improved, moreover, the probability and intensity of arc discharge of a contact of a charging interface may be reduced and the service life of the charging interface may be prolonged. Besides, it is beneficial to reduce polarization effect of the battery, improve charging speed, and decrease heat emitted by the battery, thus ensuring the reliability and safety of the terminal during charging. Moreover, since the voltage outputted by the power adapter is a voltage with a pulsating waveform, it is unnecessary to provide an electrolytic capacitor in the power adapter, which not only realizes simplification and miniaturization of the power adapter, but also decreases cost greatly. Furthermore, in the process that the power adapter charges the battery of the terminal in a pulsating charging mode, the power adapter outputs the peak synchronizing signal to the electricity meter according to the peak voltage of the voltage with the pulsating waveform, the electricity meter samples the voltage of the battery in response to receiving the peak synchronizing signal to acquire the peak voltage of the battery, such that the voltage sampled by the electricity meter through ADC sample is peak voltage of the battery, and the power adapter can adjust the charging state according to the peak voltage of the battery in time, thus ensuring safety and reliability of the system.

[00207] Embodiments of the present disclosure further provide a power adapter. The power adapter includes a first rectifier, a switch unit, a transformer, a second rectifier, a first charging interface, a sampling unit, a control unit and a first isolation unit. The first rectifier is configured to rectify an input alternating current to output a first voltage with a first pulsating waveform. The switch unit is configured to modulate the first voltage according to a control signal. The transformer is configured to output a second voltage with a second pulsating waveform according

to the modulated first voltage. The second rectifier is configured to rectify the second voltage to output a third voltage with a third pulsating waveform. The first charging interface is coupled to the second rectifier, configured to apply the third voltage to a battery in a terminal via a second charging interface of the terminal when the first charging interface is coupled to the second charging interface, in which the second charging interface is coupled to the battery. The sampling unit is configured to sample a current and/or a voltage outputted by the second rectifier to obtain a current sampling value and/or a voltage sampling value. The control unit is coupled to the sampling unit and the switch unit respectively, and configured to output the control signal to the switch unit, and adjust a duty ratio of the control signal according to the current sampling value and/or the voltage sampling value, such that the third voltage meets a charging requirement of the terminal.

[00208] With the power adapter according to embodiments of the present disclosure, the third voltage with the third pulsating waveform is outputted via the first charging interface, and the third voltage is directly applied to the battery of the terminal via the second charging interface of the terminal, thus realizing fast charging of the battery with the pulsating output voltage/current directly. Compared with the conventional constant voltage and constant current, a magnitude of the pulsating output voltage/current changes periodically, and lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, moreover, the probability and intensity of arc discharge of a contact of a charging interface may be reduced and the service life of the charging interface may be prolonged. Besides, it is beneficial to reduce polarization effect of the battery, improve charging speed, and decrease heat emitted by the battery, thus ensuring a reliability and safety of the terminal during the charging. Moreover, since the voltage with the pulsating waveform is output, it is unnecessary to provide an electrolytic capacitor, which not only realizes simplification and miniaturization of the power adapter, but also decreases cost greatly.

[00209] The embodiments of the present disclosure further provide a terminal. The terminal includes a battery, a quick charging component and an electricity meter. The quick charging component is configured to apply the voltage with the pulsating waveform outputted by a power adapter to the battery. The power adapter is configured to convert an input alternating current to output the voltage with a pulsating waveform, to provide the voltage with the pulsating waveform to the terminal and to output a peak synchronizing signal according to a peak voltage of the voltage with the pulsating waveform. The electricity meter is coupled to the power adapter and the battery respectively. The electricity meter is configured to sample a voltage of the battery in response to receiving the peak synchronizing signal so as to acquire a peak voltage of the battery

and to communicate with the quick charging component to send the peak voltage of the battery to the quick charging component. The quick charging component is further configured to communicate with the power adapter to send the peak voltage of the battery to the power adapter such that the power adapter adjusts a charging state according to the peak voltage of the battery.

5 **[00210]** The electricity meter is configured to receive the peak synchronizing signal, to sample the voltage of the battery in response to receiving the peak synchronizing signal, so as to acquire the peak voltage of the battery. The electricity meter is further configured to communicate with the quick charging component to send the peak voltage of the battery to the quick charging component.

10 **[00211]** With the terminal according to embodiments of the present disclosure, the quick charging component directly applies the voltage with the pulsating waveform outputted by the power adapter to the battery, thus realizing fast charging to the battery directly by the pulsating output voltage/current. In contrast to the conventional constant voltage and constant current, a magnitude of the pulsating output voltage/current changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved,
15 and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interfaces may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve charging speed, and decrease heat emitted by the battery, thus ensuring a reliability and safety of the battery during the charging. Moreover, since the power
20 adapter outputs the voltage with the pulsating waveform, it is unnecessary to provide an electrolytic capacitor, which not only realizes simplification and miniaturization of the power adapter, but also decreases cost greatly. Furthermore, in the process that the battery is charged in a pulsating charging mode, the power adapter outputs the peak synchronizing signal to the electricity meter according to the peak voltage of the voltage with the pulsating waveform, the electricity
25 meter samples the voltage of the battery in response to receiving the peak synchronizing signal to acquire the peak voltage of the battery, such that the voltage sampled by the electricity meter through ADC sample is peak voltage of the battery, and the power adapter can adjust the charging state according to the peak voltage of the battery in time, thus ensuring safety and reliability of the system.

30 **[00212]** In an embodiment of the present disclosure, the terminal includes a battery and a quick charging component. The quick charging component is configured to apply the voltage with the pulsating waveform outputted by the power adapter to the battery. The power adapter is configured to convert an input alternating current to output the voltage with the pulsating waveform, to provide the voltage with the pulsating waveform to the terminal and to output a peak

synchronizing signal according to a peak voltage of the voltage with the pulsating waveform. The quick charging component is further configured to acquire the peak synchronizing signal, to acquire a peak voltage of the battery according to the peak synchronizing signal, and to communicate with the power adapter such that the power adapter adjusts a charging state according to the peak voltage of the battery.

[00213] In an embodiment, the quick charging component is further configured to send the peak voltage of the battery to the power adapter, such that the power adapter determines whether to adjust the charging state according to the peak voltage of the battery.

[00214] In an embodiment, the quick charging component is further configured to determine whether to adjust the charging state of the power adapter according to the peak voltage of the battery, and to send an adjusting signal to the power adapter in response to determining to adjust the charging state of the power adapter, such that the power adapter adjusts the charging state according to the adjusting signal.

[00215] In an embodiment, the terminal further includes an electricity meter. The electricity meter is configured to sample the voltage of the battery. The quick charging component is configured to sample the voltage of the battery through the electricity meter in response to acquiring the peak synchronizing signal so as to acquire the peak voltage of the battery.

[00216] In an embodiment of the present disclosure, the power adapter includes a first charging interface and the terminal includes a second charging interface. When the first charging interface is coupled to the second charging interface, a charging path and a communication path can be established between the quick charging component 206 and the power adapter 1.

[00217] The quick charging component communicates with the power adapter 1 via the communication path to determine a charging mode. The charging mode includes a first charging mode and a second charging mode.

[00218] In an embodiment of the present disclosure, when the power adapter charges the terminal in the first charging mode, the quick charging component applies the voltage with the pulsating waveform to the battery.

[00219] Fig. 15 is a flow chart of a charging method for a terminal according to embodiments of the present disclosure. As illustrated in Fig. 15, the charging method for a terminal includes the followings.

[00220] At block S1, when a first charging interface of a power adapter is coupled to a second charging interface of a terminal, a first rectification is performed on an alternating current inputted into the power adapter to output a first voltage with a first pulsating waveform.

[00221] In other words, a first rectifier in the power adapter rectifies the inputted alternating

current (i.e., the mains supply, such as an alternating current of 220V, 50Hz or 60Hz) and outputs the first voltage (for example, 100Hz or 120Hz) with the first pulsating waveform, such as a voltage with a steamed bun waveform.

[00222] At block S2, the first voltage with the first pulsating waveform is modulated by a switch unit, and then is converted by a transformer to obtain a second voltage with a second pulsating waveform.

[00223] The switch unit may be formed of a MOS transistor. A PWM control is performed on the MOS transistor to perform a chopping modulation on the voltage with the steamed bun waveform. And then, the modulated first voltage is coupled to a secondary side by the transformer, such that the secondary winding outputs the second voltage with the second pulsating waveform.

[00224] In an embodiment of the present disclosure, a high-frequency transformer can be used for conversion, in this way, the size of the transformer can be small, thus realizing high-power and miniaturization of the power adapter.

[00225] At block S3, a second rectification is performed on the second voltage with the second pulsating waveform to output a third voltage with a third pulsating waveform. The third voltage with the third pulsating waveform may be applied to a battery of the terminal via the second charging interface, so as to charge the battery of the terminal.

[00226] In an embodiment of the present disclosure, the second rectification is performed on the second voltage with the second pulsating waveform by a second rectifier. The second rectifier may be formed of diodes or MOS transistors, and can realize a secondary synchronous rectification, such that the third pulsating waveform keeps synchronous with the waveform of the modulated first voltage.

[00227] At block S4, the current and/or the voltage after the second rectification is sampled to obtain a current sampling value and/or a voltage sampling value.

[00228] At block S5, a duty ratio of a control signal outputted to the switch unit is adjusted according to the current sampling value and/or the voltage sampling value, such that the third voltage with the third pulsating waveform meets a charging requirement.

[00229] According to an embodiment of the present disclosure, a frequency of the control signal is adjusted according to the current sample value.

[00230] Further, a voltage after the second rectification can be sampled to obtain a voltage sample value, and the duty ratio of the control signal for controlling the switch unit according to the current sampling value, such that the third voltage meets the charging requirement.

[00231] It should be noted that, the third voltage with the third pulsating waveform meeting the charging requirement means that, the third voltage and current with the third pulsating

waveform need to meet the charging voltage and charging current for charging the batter. In other words, the duty ratio of the control signal (such as a PWM signal) can be adjusted according to the sampled voltage and/or current outputted by the power adapter, so as to adjust the output of the power adapter in real time and realize a closed-loop adjustment control, such that the third voltage with the third pulsating waveform meets the charging requirement of the terminal, thus ensuring the stable and safe charging of the battery. In detail, a waveform of a charging voltage outputted to a battery is illustrated in Fig. 3, in which the waveform of the charging voltage is adjusted according to the duty ratio of the PWM signal. A waveform of a charging current outputted to a battery is illustrated in Fig. 4, in which the waveform of the charging current is adjusted according to the duty ratio of the PWM signal.

[00232] In an embodiment of the present disclosure, by controlling the switch unit, a chopping modulation can be directly performed on the first voltage with the first pulsating waveform after a full-bridge rectification, i.e., the steamed bun waveform, and then the modulated voltage is sent to the high-frequency transformer and coupled from the primary side to the secondary side via the high-frequency transformer, and then is restored to the voltage/current with the steamed bun waveform after a synchronous rectification. The voltage/current with the steamed bun waveform is directly transmitted to the battery to realize fast charging of the battery. The magnitude of the voltage with the steamed bun waveform may be adjusted according to the duty ratio of the PWM signal, such that the output of the power adapter meets the charging requirement of the battery. It can be seen, electrolytic capacitors at the primary side and the secondary side in the power adapter can be removed, and the battery can be directly charged via the voltage with the steamed bun waveform, such that the size of the power adapter may be reduced, thus realizing miniaturization of the power adapter, and decreasing the cost greatly.

[00233] In an embodiment of the present disclosure, the terminal includes a battery, a quick charging component and an electricity meter. The charging method for a terminal may include: converting by a power adapter an input alternating current to output a voltage with a pulsating waveform, providing the voltage with the pulsating waveform to the terminal and outputting a peak synchronizing signal to the electricity meter according to a peak voltage of the voltage with the pulsating waveform; sampling by the electricity meter a voltage of the battery in response to receiving the peak synchronizing signal to acquire a peak voltage of the battery, communicating with the quick charging component to send the peak voltage of the battery to the quick charging component; applying by the quick charging component the voltage with the pulsating waveform to the battery, receiving the peak voltage of the battery; and communicating by the quick charging component with the power adapter to send the peak voltage of the battery to the power adapter

such that the power adapter determines whether to adjust a charging state according to the peak voltage of the battery.

[00234] The peak synchronizing signal is received through the electricity meter. The voltage of the battery is sampled by the electricity meter in response to receiving the peak synchronizing signal to acquire the peak voltage of the battery. And the peak voltage of the battery is sent to the quick charging component via a communication with the quick charging component.

[00235] In an embodiment of the present disclosure, the terminal may include a battery and a quick charging component. The charging method for a terminal may include: converting by a power adapter an input alternating current to output a voltage with a pulsating waveform, providing the voltage with the pulsating waveform to the terminal and outputting a peak synchronizing signal according to a peak voltage of the voltage with the pulsating waveform; applying by the quick charging component the voltage with the pulsating waveform to the battery, acquiring the peak synchronizing signal, acquiring a peak voltage of the battery according to the peak synchronizing signal; and communicating by the quick charging component with the power adapter such that the power adapter adjusts a charging state according to the peak voltage of the battery.

[00236] In an embodiment, the quick charging component sends the peak voltage of the battery to the power adapter, such that the power adapter determines whether to adjust the charging state according to the peak voltage of the battery.

[00237] In an embodiment of the present disclosure, the quick charging component is configured to determine whether to adjust the charging state of the power adapter according to the peak voltage of the battery, and to send an adjusting signal to the power adapter in response to determining to adjust the charging state, such that the power adapter adjusts the charging state according to the adjusting signal.

[00238] In an embodiment of the present disclosure, the terminal further includes an electricity meter. The quick charging component is configured to sample the voltage of the battery through the electricity meter in response to acquiring the peak synchronizing signal to acquire the peak voltage of the battery.

[00239] In an embodiment of the present disclosure, the power adapter includes a first charging interface and the terminal includes a second charging interface. When the first charging interface is coupled to the second charging interface, a charging path and a communication path are established between the quick charging component and the power adapter.

[00240] The quick charging component communicates with the power adapter via the communication path to determine a charging mode. The charging mode includes a first charging

mode and a second charging mode.

[00241] Further, when the power adapter charges the terminal in the first charging mode, the quick charging component applies the voltage with the pulsating waveform to the battery.

5 **[00242]** In an embodiment of the present disclosure, as illustrated in Fig. 16, the charging method for a terminal may include the followings.

[00243] At block S10, the power adapter directly informs the electricity meter of arrival of the peak voltage of the voltage with the pulsating waveform.

[00244] At block S20, the electricity meter starts the ADC sampling to sample a voltage of the battery so as to acquire a peak voltage of the battery.

10 **[00245]** At block S30, the electricity meter reports the peak voltage of the battery to the quick charging component.

[00246] At block S40, the quick charging component reports the received peak voltage of the battery to the power adapter.

15 **[00247]** At block S50, the power adapter determines whether to adjust a charging state according to the peak voltage of the battery, and act at block S10 is executed to start a next determination.

[00248] Adjusting the charging state refers to adjusting an operation state of the power adapter, for example adjusting the output voltage and/or output current of the power adapter.

20 **[00249]** In embodiments of the present disclosure, when the power adapter charges the terminal in a pulsating charging mode, the power adapter can know the time when the voltage with the pulsating waveform reaches the peak voltage, such that the power adapter can send the peak synchronizing signal to the electricity meter at the arrival of the peak voltage of the voltage with the pulsating waveform, so as to instruct the electricity meter to sample the voltage of the battery right now. In this way, the voltage sampled by the electricity meter is the peak voltage of the
25 battery. The quick charging component sends the peak voltage of the battery to the power adapter, such that the power adapter can adjust the charging state in time, thus ensuring the safety and reliability of the system.

30 **[00250]** According to an embodiment of the present disclosure, a frequency of the control signal is adjusted according to the voltage sampling value and/or the current sampling value. That is, the PWM signal outputted to the switch unit is controlled to continuously output for a time period, and then the output of the PWM signal is stopped for a predetermined time period and then restarted. In this way, the voltage applied to the battery is intermittent, thus realizing the intermittent charging of the battery, which avoids a safety hazard caused by heating phenomenon occurring when the battery is charged continuously and improves the reliability and safety of the

charging to the battery. The control signal outputted to the switch unit is illustrated in Fig.5.

[00251] Further, the above charging method for a terminal includes: performing a communication with the terminal via the first charging interface to obtain status information of the terminal, and adjusting the duty ratio of the control signal according to the status information of the terminal, the voltage sampling value and/or current sampling value.

[00252] In other words, when the second charging interface is coupled to the first charging interface, the power adapter and the terminal may send communication query instructions to each other, and a communication connection can be established between the power adapter and the terminal after a corresponding reply instruction is received, such that the power adapter can obtain the status information of the terminal, negotiate with the terminal about the charging mode and charging parameters (such as the charging current, the charging voltage) and control the charging process.

[00253] According to an embodiment of the present disclosure, a fourth voltage with a fourth pulsating waveform can be generated through a conversion of the transformer, and the fourth voltage with the fourth pulsating waveform can be detected to generate a voltage detecting value, so as to adjust the duty ratio of the control signal according to the voltage detecting value.

[00254] In detail, the transformer can be provided with an auxiliary winding. The auxiliary winding can generate the fourth voltage with the fourth pulsating waveform according to the modulated first voltage. The output voltage of the power adapter can be reflected by detecting the fourth voltage with the fourth pulsating waveform, and the duty ratio of the control signal can be adjusted according to the voltage detecting value, such that the output of the power adapter meets the charging requirement of the battery.

[00255] In an embodiment of the present disclosure, sampling the voltage after the second rectification to obtain the voltage sampling value includes: sampling and holding a peak value of the voltage after the second rectification, and sampling a zero crossing point of the voltage after the second rectification; performing a discharging on a peak voltage sampling and holding unit configured for sampling and holding the peak voltage at the zero crossing point; sampling the peak voltage in the peak voltage sampling and holding unit so as to obtain the voltage sampling value. In this way, accurate sampling on the voltage outputted by the power adapter can be achieved, and it can be guaranteed that the voltage sampling value keeps synchronous with the first voltage with the first pulsating waveform, i.e., the phase and the variation trend of magnitude of the voltage sampling value are consistent with those of the first voltage respectively.

[00256] Further, in an embodiment of the present disclosure, the above charging method for a terminal includes: sampling the first voltage with the first pulsating waveform, and controlling

the switch unit to switch on for a predetermined time period to discharge the surge voltage in the first pulsating waveform when a sampled voltage value is greater than a first predetermined voltage value.

5 **[00257]** The first voltage with the first pulsating waveform is sampled, and then the sampled voltage value is judged. When the sampled voltage value is greater than the first predetermined voltage value, it indicates that the power adapter is suffering a lightning interference and a surge voltage occurs, and at this point, it needs to drain off the surge voltage for ensuring the safety and reliability of charging. It is required to control the switch unit to switch on for a certain time period, to form a discharging path, such that the surge voltage caused by the lightning is drained off, thus
10 avoiding lightning interference on the power adapter when charging the terminal, and effectively improving the safety and reliability of the charging of the terminal. The first predetermined voltage value may be determined according to actual situations.

15 **[00258]** According an embodiment of the present disclosure, a communication with the terminal is performed via the first charging interface to determine a charging mode. When it is determined that the charging mode is the first charging mode, the charging current and/or charging voltage in the first charging mode can be obtained according to the status information of the terminal, so as to adjust the duty ratio of the control signal according to the charging current and/or charging voltage in the first charging mode. The charging mode includes the first charging mode and the second charging mode.

20 **[00259]** In other words, when it is determined that the current charging mode is the first charging mode, the charging current and/or charging voltage in the first charging mode can be obtained according to the obtained status information of the terminal, such as the voltage, electric quantity, temperature of the battery, running parameters of the terminal and power consumption information of applications running on the terminal or the like. The duty ratio of the control signal
25 is adjusted according to the obtained charging current and/or charging voltage, such that the output of the power adapter meets the charging requirement, thus realizing the fast charging of the terminal.

30 **[00260]** The status information of the terminal includes the temperature of the battery. When the temperature of the battery is greater than a first predetermined temperature threshold, or the temperature of the battery is less than a second predetermined temperature threshold, if the current charging mode is the first charging mode, the first charging mode is switched to the second charging mode. The first predetermined temperature threshold is greater than the second predetermined temperature threshold. In other words, when the temperature of the battery is too low (for example, corresponding to less than the second predetermined temperature threshold) or

too high (for example, corresponding to greater than the first predetermined temperature threshold), it is unsuitable for fast charging; therefore, it needs to switch from the first charging mode to the second charging mode. In embodiments of the present disclosure, the first predetermined temperature threshold and the second predetermined temperature threshold can be set according to actual situations.

[00261] In an embodiment of the present disclosure, the switch unit is controlled to switch off when the temperature of the battery is greater than a predetermined high temperature protection threshold. Namely, when the temperature of the battery exceeds the high temperature protection threshold, a high temperature protection strategy will be required to control the switch unit to switch off, such that the power adapter stops charging the battery, thus realizing high temperature protection of the battery and improving the safety of charging. The high temperature protection threshold may be different from or the same as the first temperature threshold. In an embodiment, the high temperature protection threshold is greater than the first temperature threshold.

[00262] In another embodiment of the present disclosure, the terminal further obtains the temperature of the battery, and controls to stop charging the battery (for example, by controlling a charging control switch to switch off at the terminal side) when the temperature of the battery is greater than the predetermined high temperature protection threshold, so as to stop the charging process of the battery and to ensure the safety of charging.

[00263] Moreover, in an embodiment of the present disclosure, the charging method for a terminal further includes: obtaining a temperature of the first charging interface, and controlling the switch unit to switch off when the temperature of the first charging interface is greater than a predetermined protection temperature. In other words, when the temperature of the charging interface exceeds a certain temperature, the control unit needs to apply the high temperature protection strategy to control the switch unit to switch off, such that the power adapter stops charging the battery, thus realizing the high temperature protection of the battery and improving the safety of charging.

[00264] Certainly, in another embodiment of the present disclosure, the terminal performs the bidirectional communication with the power adapter via the second charging interface to obtain the temperature of the first charging interface. When the temperature of the first charging interface is greater than the predetermined protection temperature, the terminal controls to stop charging the battery. That is, the charging control switch can be switched off at the terminal side, so as to stop the charging process of the battery, thus ensuring the safety of charging.

[00265] During a process that the power adapter charges the terminal, the switch unit is controlled to switch off when the voltage sampling value is greater than a second predetermined

voltage value. Namely, in the process of charging the terminal, the power adapter judges the magnitude of the voltage sampling value. When the voltage sampling value is greater than the second predetermined voltage value, it indicates that the voltage outputted by the power adapter is too high. At this time, the power adapter is controlled to stop charging the terminal by controlling the switch unit to switch off. In other words, the over-voltage protection of the power adapter is realized by controlling the switch unit to switch off, thus ensuring the safety of charging.

[00266] Certainly, in an embodiment of the present disclosure, the terminal performs a bidirectional communication with the power adapter via the second charging interface to obtain the voltage sampling value, and controls to stop charging the battery when the voltage sampling value is greater than the second predetermined voltage value. Namely, the charging control switch is controlled to switch off at the terminal side, so as to stop the charging process, such that the safety of charging can be ensured.

[00267] In an embodiment of the present disclosure, during the process that the power adapter charges the terminal, the switch unit is controlled to switch off when the current sampling value is greater than a predetermined current value. In other words, during the process that the power adapter charges the terminal, the power adapter judges the magnitude of the current sampling value. When the current sampling value is greater than the predetermined current value, it indicates that the current outputted by the power adapter is too high. At this time, the power adapter is controlled to stop charging the terminal by controlling the switch unit to switch off. In other words, the over-current protection of the power adapter is realized by controlling the switch unit to switch off, thus ensuring the safety of charging.

[00268] Similarly, the terminal performs the bidirectional communication with the power adapter via the second charging interface to obtain the current sampling value, and controls to stop charging the battery when the current sampling value is greater than the predetermined current value. In other words, the charging control switch is controlled to be switched off at the terminal side, such that the charging process of the battery is stopped, thus ensuring the safety of charging.

[00269] The second predetermined voltage value and the predetermined current value may be set according to actual situations.

[00270] In embodiments of the present disclosure, the status information of the terminal may include the electric quantity of the battery, the temperature of the battery, the voltage/current of the battery of the terminal, interface information of the terminal and information on path impedance of the terminal.

[00271] In detail, the power adapter can be coupled to the terminal via a USB interface. The USB interface may be a general USB interface, or a micro USB interface. A data wire in the USB

interface, that is, the data wire in the first charging interface, is configured for the bidirectional communication between the power adapter and the terminal. The data wire may be D+ and/or D- wire in the USB interface. The bidirectional communication may refer to an information interaction performed between the power adapter and the terminal.

5 **[00272]** The power adapter performs the bidirectional communication with the terminal via the data wire in the USB interface, so as to determine to charge the terminal in the first charging mode.

10 **[00273]** As an embodiment, when the power adapter performs the bidirectional communication with the terminal via the first charging interface so as to determine to charge the terminal in the first charging mode, the power adapter sends a first instruction to the terminal. The first instruction is configured to query the terminal whether to operate in the first charging mode. The power adapter receives a reply instruction of the first instruction from the terminal. The reply instruction of the first instruction is configured to indicate that the terminal agrees to operate in the first charging mode.

15 **[00274]** As an embodiment, before the power adapter sends the first instruction to the terminal, the power adapter charges the terminal in the second charging mode. When the power adapter determines that a charging duration of the second charging mode is greater than a predetermined threshold, the power adapter sends the first instruction to the terminal.

20 **[00275]** It should be understood that, when the power adapter determines that the charging duration of the second charging mode is greater than the predetermined threshold, the power adapter may determine that the terminal has identified it (that is, the power adapter) as a power adapter, such that the fast charging query communication may start.

25 **[00276]** As an embodiment, the power adapter is controlled to adjust a charging current to a charging current in the first charging mode by controlling the switch unit. Before the power adapter charges the terminal with the charging current in the first charging mode, a bidirectional communication is performed with the terminal via the first charging interface to determine a charging voltage in the first charging mode, and the power adapter is controlled to adjust a charging voltage to the charging voltage in the first charging mode.

30 **[00277]** As an embodiment, performing the bidirectional communication with the terminal via the first charging interface to determine the charging voltage in the first charging mode includes: sending by the power adapter a second instruction to the terminal, receiving by the power adapter a reply instruction of the second instruction sent from the terminal, and determining by the power adapter the charging voltage in the first charging mode according to the reply instruction of the second instruction. The second instruction is configured to query whether a current output

voltage of the power adapter is suitable as the charging voltage in the first charging mode. The reply instruction of the second instruction is configured to indicate that the current output voltage of the power adapter is suitable, high or low.

[00278] As an embodiment, before controlling the power adapter to adjust the charging current to the charging current in the first charging mode, the bidirectional communication with the terminal is performed via the first charging interface to determine the charging current in the first charging mode.

[00279] As an embodiment, performing the bidirectional communication with the terminal via the first charging interface to determine the charging current in the first charging mode includes: sending by the power adapter a third instruction to the terminal, receiving by the power adapter a reply instruction of the third instruction sent from the terminal and determining by the power adapter the charging current in the first charging mode according to the reply instruction of the third instruction. The third instruction is configured to query a maximum charging current currently supported by the terminal. The reply instruction of the third instruction is configured to indicate the maximum charging current currently supported by the terminal.

[00280] The power adapter may determine the above maximum charging current as the charging current in the first charging mode, or may set the charging current as a charging current less than the maximum charging current.

[00281] As an embodiment, during the process that the power adapter charges the terminal in the first charging mode, the bidirectional communication is performed with the terminal via the first charging interface, so as to continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit.

[00282] The power adapter may query the status information of the terminal continuously, so as to adjust the charging current continuously, for example, query the voltage of the battery of the terminal, the electric quantity of the battery, etc.

[00283] As an embodiment, performing the bidirectional communication with the terminal via the first charging interface to continuously adjust the charging current outputted to the battery from the power adapter by controlling the switch unit includes: sending by the power adapter a fourth instruction to the terminal, receiving by the power adapter a reply instruction of the fourth instruction sent by the terminal, in which the fourth instruction is configured to query a current voltage of the battery in the terminal, and adjusting the charging current by controlling the switch unit according to the current voltage of the battery. The reply instruction of the fourth instruction is configured to indicate the current voltage of the battery in the terminal.

[00284] As an embodiment, adjusting the charging current by controlling the switch unit

according to the current voltage of the battery includes: adjusting the charging current outputted to the battery from the power adapter to a charging current value corresponding to the current voltage of the battery by controlling the switch unit according to the current voltage of the battery and a predetermined correspondence between battery voltage values and charging current values.

5 **[00285]** In detail, the power adapter may store the correspondence between battery voltage values and charging current values in advance.

10 **[00286]** As an embodiment, during the process that the power adapter charges the terminal in the first charging mode, the power adapter further performs the bidirectional communication with the terminal via the first charging interface so as to whether the first charging interface and the second charging interface are in poor contact. When it is determined that the first charging interface and the second charging interface are in poor contact, the power adapter is controlled to quit the first charging mode.

15 **[00287]** As an embodiment, before determining whether the first charging interface and the second charging interface are in poor contact, the power adapter receives information indicating path impedance of the terminal from the terminal. The power adapter sends a fourth instruction to the terminal. The fourth instruction is configured to query a current voltage of the battery in the terminal. The power adapter receives a reply instruction of the fourth instruction sent by the terminal. The reply instruction of the fourth instruction is configured to indicate the current voltage of the battery in the terminal. The power adapter determines path impedance from the power adapter to the battery according to an output voltage of the power adapter and the current voltage of the battery and determines whether the first charging interface and the second charging interface are in poor contact according to the path impedance from the power adapter to the battery, the path impedance of the terminal, and path impedance of a charging circuit between the power adapter and the terminal.

25 **[00288]** As an embodiment, before the power adapter is controlled to quit the first charging mode, a fifth instruction is sent to the terminal. The fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

30 **[00289]** After sending the fifth instruction, the power adapter may quit the first charging mode or reset.

30 **[00290]** The fast charging process according to embodiments of the present disclosure has been described from the perspective of the power adapter; hereinafter, the fast charging process according to embodiments of the present disclosure will be described from the perspective of the terminal in the following.

30 **[00291]** In embodiments of the present disclosure, the terminal supports the first charging

mode and the second charging mode. The charging current of the first charging mode is greater than that of the second charging mode. The terminal performs the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines to charge the terminal in the first charging mode. The power adapter outputs according to a charging
5 current in the first charging mode to charge the battery in the terminal.

[00292] As an embodiment, performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines to charge the terminal in the first charging mode includes: receiving by the terminal the first instruction sent by the power adapter, in which the first instruction is configured to query the
10 terminal whether to operate in the first charging mode; sending by the terminal a reply instruction of the first instruction to the power adapter. The reply instruction of the first instruction is configured to indicate that the terminal agrees to operate in the first charging mode.

[00293] As an embodiment, before the terminal receives the first instruction sent by the power adapter, the battery in the terminal is charged by the power adapter in the second charging
15 mode. When the power adapter determines that a charging duration of the second charging mode is greater than a predetermined threshold, the terminal receives the first instruction sent by the power adapter.

[00294] As an embodiment, before the power adapter outputs according to the charging current in the first charging mode to charge the battery in the terminal, the terminal performs the
20 bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines the charging voltage in the first charging mode.

[00295] As an embodiment, performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines the charging voltage in the first charging mode includes: receiving by the terminal a second
25 instruction sent by the power adapter, and sending by the terminal a reply instruction of the second instruction to the power adapter. The second instruction is configured to query whether a current output voltage of the power adapter is suitable as the charging voltage in the first charging mode. The reply instruction of the second instruction is configured to indicate that the current output voltage of the power adapter is suitable, high or low.

[00296] As an embodiment, before the terminal receives the charging current in the first charging mode from the power adapter to charge the battery in the terminal, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such
30 that the power adapter determines the charging current in the first charging mode.

[00297] Performing by the terminal the bidirectional communication with the power adapter

via the second charging interface such that the power adapter determines the charging current in the first charging mode includes: receiving by the terminal a third instruction sent by the power adapter, in which the third instruction is configured to query a maximum charging current currently supported by the terminal; sending by the terminal a reply instruction of the third instruction to the power adapter, in which the reply instruction of the third instruction is configured to indicate the maximum charging current currently supported by the terminal, such that the power adapter determines the charging current in the first charging mode according to the maximum charging current.

[00298] As an embodiment, during a process that the power adapter charges the terminal in the first charging mode, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter continuously adjusts a charging current outputted to the battery.

[00299] Performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter continuously adjusts the charging current outputted to the battery includes: receiving by the terminal a fourth instruction sent by the power adapter, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; sending by the terminal a reply instruction of the fourth instruction to the power adapter, in which the reply instruction of the fourth instruction is configured to indicate the current voltage of the battery in the terminal, such that the power adapter continuously adjusts the charging current outputted to the battery according to the current voltage of the battery.

[00300] As an embodiment, during the process that the power adapter charges the terminal in the first charging mode, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact.

[00301] Performing by the terminal the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact includes: receiving by the terminal a fourth instruction sent by the power adapter, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; sending by the terminal a reply instruction of the fourth instruction to the power adapter, in which the reply instruction of the fourth instruction is configured to indicate the current voltage of the battery in the terminal, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact according to an output voltage of the power adapter and the current voltage of the battery.

[00302] As an embodiment, the terminal receives a fifth instruction sent by the power adapter. The fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[00303] In order to initiate and adopt the first charging mode, the power adapter may perform a fast charging communication procedure with the terminal, for example, by one or more handshakes, so as to realize the fast charging of battery can be achieved through one or more handshakes. Referring to Fig. 6, the fast charging communication procedure according to embodiments of the present disclosure and respective stages in the fast charging process will be described in detail. It should be understood that, communication actions or operations illustrated in Fig. 6 are merely exemplary. Other operations or various modifications of respective operations in Fig. 6 can be implemented in embodiments of the present disclosure. In addition, respective stages in Fig. 6 may be executed in an order different from that illustrated in Fig. 6, and it is unnecessary to execute all the operations illustrated in Fig. 6.

[00304] In conclusion, with the charging method for a terminal according to embodiments of the present disclosure, the power adapter is configured to output the voltage with the pulsating waveform and meeting the charging requirement, and the quick charging component directly applies the voltage with the pulsating waveform outputted by the power adapter to the battery, thus realizing fast charging to the battery directly by the pulsating output voltage/current. In contrast to the conventional constant voltage and constant current, a magnitude of the pulsating output voltage/current changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interface may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve charging speed, and decrease heat emitted by the battery, thus ensuring a reliability and safety of the terminal during the charging. Moreover, since the voltage with the pulsating waveform is output from the power adapter, it is unnecessary to provide an electrolytic capacitor in the power adapter, which not only realizes simplification and miniaturization of the power adapter, but also decreases cost greatly. Furthermore, in the process that the battery is charged in a pulsating charging mode, the power adapter outputs the peak synchronizing signal to the electricity meter according to the peak voltage of the voltage with the pulsating waveform, the electricity meter samples the voltage of the battery in response to receiving the peak synchronizing signal to acquire the peak voltage of the battery, such that the voltage sampled by the electricity meter through ADC sample is peak voltage of the battery, and the power adapter can adjust the charging state according to the peak voltage of the battery in time, thus ensuring safety and reliability of the

system.

[00305] In the specification of the present disclosure, it is to be understood that terms such as “central,” “longitudinal,” “lateral,” “length,” “width,” “thickness,” “upper,” “lower,” “front,” “rear,” “left,” “right,” “vertical,” “horizontal,” “top,” “bottom,” “inner,” “outer,” “clockwise,” “counterclockwise,” “axial,” “radial,” and “circumference” refer to the orientations and location relations which are the orientations and location relations illustrated in the drawings, and for describing the present disclosure and for describing in simple, and which are not intended to indicate or imply that the device or the elements are disposed to locate at the specific directions or are structured and performed in the specific directions, which could not be understood to the limitation of the present disclosure.

[00306] In addition, terms such as “first” and “second” are used herein for purposes of description and are not intended to indicate or imply relative importance or significance or to imply the number of indicated technical features. Thus, the feature defined with “first” and “second” may comprise one or more of this feature. In the description of the present disclosure, “a plurality of” means two or more than two, unless specified otherwise.

[00307] In the present disclosure, unless specified or limited otherwise, the terms “mounted,” “connected,” “coupled,” “fixed” and the like are used broadly, and may be, for example, fixed connections, detachable connections, or integral connections; may also be mechanical or electrical connections; may also be direct connections or indirect connections via intervening structures; may also be inner communications of two elements, which can be understood by those skilled in the art according to specific situations.

[00308] In the present disclosure, unless specified or limited otherwise, a structure in which a first feature is “on” or “below” a second feature may include an embodiment in which the first feature is in direct contact with the second feature, and may also include an embodiment in which the first feature and the second feature are not in direct contact with each other, but are contacted via an additional feature formed therebetween. Furthermore, a first feature “on,” “above,” or “on top of” a second feature may include an embodiment in which the first feature is right or obliquely “on,” “above,” or “on top of” the second feature, or just means that the first feature is at a height higher than that of the second feature; while a first feature “below,” “under,” or “on bottom of” a second feature may include an embodiment in which the first feature is right or obliquely “below,” “under,” or “on bottom of” the second feature, or just means that the first feature is at a height lower than that of the second feature.

[00309] Reference throughout this specification to “an embodiment,” “some embodiments,” “one embodiment,” “another example,” “an example,” “a specific example,” or “some examples,”

means that a particular feature, structure, material, or characteristic described in connection with the embodiment or example is included in at least one embodiment or example of the present disclosure. Thus, the appearances of the phrases such as “in some embodiments,” “in one embodiment”, “in an embodiment”, “in another example,” “in an example,” “in a specific
5 example,” or “in some examples,” in various places throughout this specification are not necessarily referring to the same embodiment or example of the present disclosure. Furthermore, the particular features, structures, materials, or characteristics may be combined in any suitable manner in one or more embodiments or examples.

[00310] Those skilled in the art may be aware that, in combination with the examples
10 described in the embodiments disclosed in this specification, units and algorithm steps can be implemented by electronic hardware, or a combination of computer software and electronic hardware. In order to clearly illustrate interchangeability of the hardware and software, components and steps of each example are already described in the description according to the function commonalities. Whether the functions are executed by hardware or software depends on
15 particular applications and design constraint conditions of the technical solutions. Persons skilled in the art may use different methods to implement the described functions for each particular application, but it should not be considered that the implementation goes beyond the scope of the present disclosure.

[00311] Those skilled in the art may be aware that, with respect to the working process of
20 the system, the device and the unit, reference is made to the part of description of the method embodiment for simple and convenience, which are described herein.

[00312] In embodiments of the present disclosure, it should be understood that, the disclosed system, device and method may be implemented in other way. For example, embodiments of the described device are merely exemplary. The partition of units is merely a
25 logical function partitioning. There may be other partitioning ways in practice. For example, several units or components may be integrated into another system, or some features may be ignored or not implemented. Further, the coupling between each other or directly coupling or communication connection may be implemented via some interfaces. The indirect coupling or communication connection may be implemented in an electrical, mechanical or other manner.

[00313] In embodiments of the present disclosure, it should be understood that, the units
30 illustrated as separate components can be or not be separated physically, and components described as units can be or not be physical units, i.e., can be located at one place, or can be distributed onto multiple network units. It is possible to select some or all of the units according to actual needs, for realizing the objective of embodiments of the present disclosure.

[00314] In addition, each functional unit in the present disclosure may be integrated in one progressing module, or each functional unit exists as an independent unit, or two or more functional units may be integrated in one module.

[00315] If the integrated module is embodied in software and sold or used as an independent product, it can be stored in the computer readable storage medium. Based on this, the technical solution of the present disclosure or a part making a contribution to the related art or a part of the technical solution may be embodied in a manner of software product. The computer software produce is stored in a storage medium, including some instructions for causing one computer device (such as a personal PC, a server, or a network device etc.) to execute all or some of steps of the method according to embodiments of the present disclosure. The above-mentioned storage medium may be a medium able to store program codes, such as, USB flash disk, mobile hard disk drive (mobile HDD), read-only memory (ROM), random-access memory (RAM), a magnetic tape, a floppy disc, an optical data storage device, and the like.

[00316] Although explanatory embodiments have been illustrated and described, it would be appreciated by those skilled in the art that the above embodiments cannot be construed to limit the present disclosure, and changes, alternatives, and modifications can be made in the embodiments without departing from spirit, principles and scope of the present disclosure.

WHAT IS CLAIMED IS:

1. A charging system for a terminal, comprising a power adapter and the terminal; wherein,
the power adapter is configured to convert an input alternating current to output a voltage
5 with a pulsating waveform, to provide the voltage with the pulsating waveform to the terminal and
to output a peak synchronizing signal according to a peak voltage of the voltage with the pulsating
waveform; and

the terminal comprises:

a battery;

10 a quick charging component, configured to apply the voltage with the pulsating
waveform to the battery, to acquire the peak synchronizing signal, to acquire a peak voltage
of the battery according to the peak synchronizing signal, and to communicate with the power
adapter such that the power adapter adjusts a charging state according to the peak voltage of
the battery.

15 2. The charging system according to claim 1, wherein the quick charging component is
further configured to send the peak voltage of the battery to the power adapter, such that the power
adapter determines whether to adjust the charging state according to the peak voltage of the
battery.

20 3. The charging system according to claim 1, wherein, the quick charging component is
further configured to determine whether to adjust the charging state of the power adapter
according to the peak voltage of the battery, and to send an adjusting signal to the power adapter in
response to determining to adjust the charging state of the power adapter, such that the power
adjusts the charging state according to the adjusting signal.

25 4. The charging system according to any of claims 1-3, wherein the terminal further
comprises an electricity meter configured to sample a voltage of the battery, the quick charging
component is configured to sample the voltage of the battery through the electricity meter in
response to acquiring the peak synchronizing signal, so as to acquire the peak voltage of the
battery.

30 5. The charging system according to claim 4, wherein, the electricity meter is further
configured to:

receive the peak synchronizing signal;

sample the voltage of the battery in response to receiving the peak synchronizing signal, so as
to acquire the peak voltage of the battery; and

communicate with the quick charging component to send the peak voltage of the battery to

the quick charging component.

6. The charging system according to claim 1, wherein the power adapter comprises a first charging interface, and the terminal further comprises a second charging interface, wherein when the first charging interface is coupled to the second charging interface, a charging path and a communication path are established between the quick charging component and the power adapter.

7. The charging system according to claim 6, wherein, the quick charging component is configured to communicate with the power adapter via the communication path to determine a charging mode; wherein the charging mode comprises a first charging mode and a second charging mode.

8. The charging system according to claim 7, wherein the quick charging component is configured to apply the voltage with the pulsating waveform to the battery when the power adapter charges the terminal in the first charging mode. 9. The charging system according to claim 5, wherein the quick charging component communicates with the electricity meter in a manner of I2C.

10. A terminal, comprising:
a battery;

a quick charging component, configured to apply a voltage with a pulsating waveform to the battery, wherein the voltage with the pulsating waveform is outputted by a power adapter, the power adapter is configured to convert an input alternating current to output the voltage with the pulsating waveform, to provide the voltage with the pulsating waveform to the terminal and to output a peak synchronizing signal according to a peak voltage of the voltage with the pulsating waveform; the quick charging component is further configured to acquire the peak synchronizing signal, to acquire a peak voltage of the battery according to the peak synchronizing signal, and to communicate with the power adapter such that the power adapter adjusts a charging state according to the peak voltage of the battery.

11. The terminal according to claim 10, wherein the quick charging component is further configured to send the peak voltage of the battery to the power adapter, such that the power adapter determines whether to adjust the charging state according to the peak voltage of the battery.

12. The terminal according to claim 10, wherein, the quick charging component is further configured to determine whether to adjust the charging state of the power adapter according to the peak voltage of the battery, and to send an adjusting signal to the power adapter in response to determining to adjust the charging state of the power adapter, such that the power adapter adjusts the charging state according to the adjusting signal.

13. The terminal according to any of claims 10-12, wherein, the terminal further comprises an electricity meter configured to sample a voltage of the battery, the quick charging component is configured to sample the voltage of the battery through the electricity meter in response to acquiring the peak synchronizing signal, so as to acquire the peak voltage of the battery.

14. The terminal according to claim 13, wherein the electricity meter is further configured to: receive the peak synchronizing signal; sample the voltage of the battery in response to receiving the peak synchronizing signal, so as to acquire the peak voltage of the battery; and

communicate with the quick charging component to send the peak voltage of the battery to the quick charging component.

15. The terminal according to claim 10, wherein the power adapter comprises a first charging interface, and the terminal further comprises a second charging interface, wherein when the first charging interface is coupled to the second charging interface, a charging path and a communication path are established between the quick charging component and the power adapter.

16. The terminal according to claim 15, wherein, the quick charging component is configured to communicate with the power adapter via the communication path to determine a charging mode; wherein the charging mode comprises a first charging mode and a second charging mode.

17. The terminal according to claim 16, wherein the quick charging component is configured to apply the voltage with the pulsating waveform to the battery when the power adapter charges the terminal in the first charging mode. 18. A charging method for a terminal, wherein the terminal comprises a battery and a quick charging component, and the method comprises:

by a power adapter, converting an input alternating current to output a voltage with a pulsating waveform, providing the voltage with the pulsating waveform to the terminal and outputting a peak synchronizing signal according to a peak voltage of the voltage with the pulsating waveform;

by the quick charging component, applying the voltage with the pulsating waveform to the battery, acquiring the peak synchronizing signal, acquiring a peak voltage of the battery according to the peak synchronizing signal; and

communicating by the quick charging component with the power adapter such that the power adapter adjusts a charging state according to the peak voltage of the battery.

19. The charging method according to claim 18, further comprising:

sending by the quick charging component the peak voltage of the battery to the power adapter, such that the power adapter determines whether to adjust the charging state according to the peak voltage of the battery.

20. The charging method according to claim 18, further comprising:

determining by the quick charging component whether to adjust the charging state of the power adapter according to the peak voltage of the battery; and

5 sending by the quick charging component an adjusting signal to the power adapter in response to determining to adjust the charging state of the power adapter, such that the power adapter adjusts the charging state according to the adjusting signal.

21. The charging method according to any of claims 18-20, wherein the terminal further comprises an electricity meter, and the quick charging component is configured to sample the voltage of the battery through the electricity meter in response to acquiring the peak synchronizing
10 signal, so as to acquire the peak voltage of the battery.

22. The charging method according to claim 21, wherein, the electricity meter is further configured to:

receive the peak synchronizing signal;

15 sample the voltage of the battery in response to receiving the peak synchronizing signal, so as to acquire the peak voltage of the battery; and

communicate with the quick charging component to send the peak voltage of the battery to the quick charging component.

23. The charging method according to claim 18, wherein the power adapter comprises a first charging interface, and the terminal further comprises a second charging interface, wherein the
20 method further comprises:

when the first charging interface is coupled to the second charging interface, establishing a charging path and a communication path between the quick charging component and the power adapter.

24. The charging method according to claim 23, further comprising:

25 communicating by the quick charging component with the power adapter via the communication path to determine a charging mode; wherein the charging mode comprises a first charging mode and a second charging mode.

25. The charging method according to claim 24, wherein the quick charging component is configured to apply the voltage with the pulsating waveform to the battery when the power adapter
30 charges the terminal in the first charging mode.