

DESCRIPTION

ENCODER, DECODER, ENCODING METHOD, AND DECODING METHOD

5 TECHNICAL FIELD

[0001]

This disclosure relates to video coding, and particularly to video encoding and decoding systems, components, and methods.

BACKGROUND ART

10 [0002]

With advancement in video coding technology, from H.261 and MPEG-1 to H.264/AVC (Advanced Video Coding), MPEG-LA, H.265/HEVC (High Efficiency Video Coding) and H.266/VVC (Versatile Video Codec), there remains a constant need to provide improvements and optimizations to the video coding technology to process an ever-increasing amount of digital video data in various applications.

[0003]

It is to be noted that Non Patent Literature (NPL) 1 relates to one example of the conventional standard on the above-mentioned video coding technology.

Citation List

Non Patent Literature

[0004]

NPL 1: H.265(ISO/IEC 23008-2 HEVC)/HEVC(High Efficiency Video Coding)

SUMMARY OF THE INVENTION

TECHNICAL PROBLEMS

[0005]

For such an encoding method, a new scheme is desired to be proposed in order to improve an encoding efficiency, improve an image quality, reduce the processing amount, reduce the scale of the circuitry, or appropriately select a constituent element/operation for a filter, a block, a size, a motion vector, a reference picture, a reference block, etc.

[0006]

The present disclosure provides the configurations or methods contributable to, for example, at least one of: an improvement in an encoding efficiency; an improvement in an image quality; a reduction of the processing amount; a reduction of the scale of the circuitry; an improvement in the processing speed; appropriate selection of a constituent element/operation. It should be noted that the present disclosure may include configurations or methods contributable to benefits other than the above-mentioned benefits.

SOLUTIONS TO PROBLEMS

[0007]

An encoder according to one aspect of the present disclosure is an encoder that encodes an image. The encoder includes: circuitry; and memory coupled to the circuitry, in which in operation, the circuitry: derives a prediction error of the image by subtracting a prediction image of the image from the image, the prediction image being generated using intra prediction or inter prediction; performs primary transform on the prediction error, and performs secondary transform on a result of the primary transform; performs quantization on a result of the secondary transform; and encodes a result of the quantization as data of the image, and in the performing of the secondary transform, when a matrix weighted intra prediction included in the intra prediction and having a plurality of prediction modes is used, the circuitry uses,

as a transform set for the secondary transform, a common transform set shared among the plurality of prediction modes, the matrix weighted intra prediction generating the prediction image by performing matrix calculation on a pixel sequence obtained from pixel values of surrounding pixels of a current block,
5 the transform set for the secondary transform being applied to primary transform coefficients obtained from the result of the primary transform.

[0008]

Some implementations of embodiments of the present disclosure may improve an encoding efficiency, may simply be an encoding/decoding process,
10 may accelerate an encoding/decoding process speed, may efficiently select appropriate components/operations used in encoding and decoding such as appropriate filter, block size, motion vector, reference picture, reference block, etc.

[0009]

15 Additional benefits and advantages of the disclosed embodiments will become apparent from the specification and drawings. The benefits and/or advantages may be individually obtained by the various embodiments and features of the specification and drawings, not all of which need to be provided in order to obtain one or more of such benefits and/or advantages.

20 [0010]

It should be noted that general or specific embodiments may be implemented as a system, a method, an integrated circuit, a computer program, a storage medium, or any selective combination thereof.

ADVANTAGEOUS EFFECT OF INVENTION

25 [0011]

The configuration or method according to an aspect of the present disclosure is contributable to, for example, at least one of: an improvement in

an encoding efficiency; an improvement in an image quality; a reduction of the processing amount; a reduction of the scale of the circuitry; an improvement in the processing speed; appropriate selection of a constituent element/operation.

It should be noted that the configuration or method according to an aspect of the present disclosure may be contributable to benefits other than the above-mentioned benefits.

BRIEF DESCRIPTION OF DRAWINGS

[0012]

FIG. 1 is a block diagram illustrating a functional configuration of an encoder according to an embodiment.

FIG. 2 is a flow chart indicating one example of an overall encoding process performed by the encoder.

FIG. 3 is a conceptual diagram illustrating one example of block splitting.

FIG. 4A is a conceptual diagram illustrating one example of a slice configuration.

FIG. 4B is a conceptual diagram illustrating one example of a tile configuration.

FIG. 5A is a chart indicating transform basis functions for various transform types.

FIG. 5B is a conceptual diagram illustrating example spatially varying transforms (SVT).

FIG. 6A is a conceptual diagram illustrating one example of a filter shape used in an adaptive loop filter (ALF).

FIG. 6B is a conceptual diagram illustrating another example of a filter shape used in an ALF.

FIG. 6C is a conceptual diagram illustrating another example of a filter

shape used in an ALF.

FIG. 7 is a block diagram indicating one example of a specific configuration of a loop filter which functions as a deblocking filter (DBF).

FIG. 8 is a conceptual diagram indicating an example of a deblocking
5 filter having a symmetrical filtering characteristic with respect to a block boundary.

FIG. 9 is a conceptual diagram for illustrating a block boundary on which a deblocking filter process is performed.

FIG. 10 is a conceptual diagram indicating examples of Bs values.

10 FIG. 11 is a flow chart illustrating one example of a process performed by a prediction processor of the encoder.

FIG. 12 is a flow chart illustrating another example of a process performed by the prediction processor of the encoder.

15 FIG. 13 is a flow chart illustrating another example of a process performed by the prediction processor of the encoder.

FIG. 14 is a conceptual diagram illustrating sixty-seven intra prediction modes used in intra prediction in an embodiment.

FIG. 15 is a flow chart illustrating an example basic processing flow of inter prediction.

20 FIG. 16 is a flow chart illustrating one example of derivation of motion vectors.

FIG. 17 is a flow chart illustrating another example of derivation of motion vectors.

25 FIG. 18 is a flow chart illustrating another example of derivation of motion vectors.

FIG. 19 is a flow chart illustrating an example of inter prediction in normal inter mode.

FIG. 20 is a flow chart illustrating an example of inter prediction in merge mode.

FIG. 21 is a conceptual diagram for illustrating one example of a motion vector derivation process in merge mode.

5 FIG. 22 is a flow chart illustrating one example of frame rate up conversion (FRUC) process.

FIG. 23 is a conceptual diagram for illustrating one example of pattern matching (bilateral matching) between two blocks along a motion trajectory.

10 FIG. 24 is a conceptual diagram for illustrating one example of pattern matching (template matching) between a template in a current picture and a block in a reference picture.

FIG. 25A is a conceptual diagram for illustrating one example of deriving a motion vector of each sub-block based on motion vectors of a plurality of neighboring blocks.

15 FIG. 25B is a conceptual diagram for illustrating one example of deriving a motion vector of each sub-block in affine mode in which three control points are used.

FIG. 26A is a conceptual diagram for illustrating an affine merge mode.

20 FIG. 26B is a conceptual diagram for illustrating an affine merge mode in which two control points are used.

FIG. 26C is a conceptual diagram for illustrating an affine merge mode in which three control points are used.

FIG. 27 is a flow chart illustrating one example of a process in affine merge mode.

25 FIG. 28A is a conceptual diagram for illustrating an affine inter mode in which two control points are used.

FIG. 28B is a conceptual diagram for illustrating an affine inter mode

in which three control points are used.

FIG. 29 is a flow chart illustrating one example of a process in affine inter mode.

FIG. 30A is a conceptual diagram for illustrating an affine inter mode
5 in which a current block has three control points and a neighboring block has two control points.

FIG. 30B is a conceptual diagram for illustrating an affine inter mode in which a current block has two control points and a neighboring block has three control points.

10 FIG. 31A is a flow chart illustrating a merge mode process including decoder motion vector refinement (DMVR).

FIG. 31B is a conceptual diagram for illustrating one example of a DMVR process.

FIG. 32 is a flow chart illustrating one example of generation of a
15 prediction image.

FIG. 33 is a flow chart illustrating another example of generation of a prediction image.

FIG. 34 is a flow chart illustrating another example of generation of a prediction image.

20 FIG. 35 is a flow chart illustrating one example of a prediction image correction process performed by an overlapped block motion compensation (OBMC) process.

FIG. 36 is a conceptual diagram for illustrating one example of a prediction image correction process performed by an OBMC process.

25 FIG. 37 is a conceptual diagram for illustrating generation of two triangular prediction images.

FIG. 38 is a conceptual diagram for illustrating a model assuming

uniform linear motion.

FIG. 39 is a conceptual diagram for illustrating one example of a prediction image generation method using a luminance correction process performed by a local illumination compensation (LIC) process.

5 FIG. 40 is a block diagram illustrating a mounting example of the encoder.

FIG. 41 is a block diagram illustrating a functional configuration of a decoder according to an embodiment.

10 FIG. 42 is a flow chart illustrating one example of an overall decoding process performed by the decoder.

FIG. 43 is a flow chart illustrating one example of a process performed by a prediction processor of the decoder.

FIG. 44 is a flow chart illustrating another example of a process performed by the prediction processor of the decoder.

15 FIG. 45 is a flow chart illustrating an example of inter prediction in normal inter mode in the decoder.

FIG. 46 is a block diagram illustrating a mounting example of the decoder.

20 FIG. 47 is a diagram for illustrating a method of predicting a pixel value using Matrix weighted Intra Prediction (MIP).

FIG. 48 is a flow chart illustrating one example of a NSST transform set selection process performed by a transformer of an encoder according to Aspect 1 of an embodiment.

25 FIG. 49 is a flow chart illustrating one example of a NSST transform set selection process performed by a transformer of an encoder according to Aspect 2 of an embodiment.

FIG. 50 is a block diagram illustrating an implementation example of

an encoder according to an embodiment.

FIG. 51 is a flow chart illustrating an operation example of the encoder shown in FIG. 50.

FIG. 52 is a block diagram illustrating an implementation example of a
5 decoder according to an embodiment.

FIG. 53 is a flow chart illustrating an operation example of the decoder shown in FIG. 52.

FIG. 54 is a block diagram illustrating an overall configuration of a content providing system for implementing a content distribution service.

10 FIG. 55 is a conceptual diagram illustrating one example of an encoding structure in scalable encoding.

FIG. 56 is a conceptual diagram illustrating one example of an encoding structure in scalable encoding.

15 FIG. 57 is a conceptual diagram illustrating an example of a display screen of a web page.

FIG. 58 is a conceptual diagram illustrating an example of a display screen of a web page.

FIG. 59 is a block diagram illustrating one example of a smartphone.

20 FIG. 60 is a block diagram illustrating an example of a configuration of a smartphone.

DESCRIPTION OF EXEMPLARY EMBODIMENTS

[0013]

For example, an encoder according to one aspect of the present disclosure is an encoder that encodes an image. The encoder includes:
25 circuitry; and memory coupled to the circuitry, in which in operation, the circuitry: derives a prediction error of the image by subtracting a prediction image of the image from the image, the prediction image being generated using

intra prediction or inter prediction; performs primary transform on the prediction error, and performs secondary transform on a result of the primary transform; performs quantization on a result of the secondary transform; and encodes a result of the quantization as data of the image, and in the performing
5 of the secondary transform, when a matrix weighted intra prediction included in the intra prediction and having a plurality of prediction modes is used, the circuitry uses, as a transform set for the secondary transform, a common transform set shared among the plurality of prediction modes, the matrix weighted intra prediction generating the prediction image by performing
10 matrix calculation on a pixel sequence obtained from pixel values of surrounding pixels of a current block, the transform set for the secondary transform being applied to primary transform coefficients obtained from the result of the primary transform.

[0014]

15 In this manner, when the matrix weighted intra prediction is used in the performing of the secondary transform, the encoder can use the common transform set to reduce the ROM size needed to store coefficients for the secondary transform. With this, in the encoder, it is possible to reduce the circuit size and improve the encoding efficiency.

20 [0015]

Here, for example, the common transform set may be identical to a transform set for use in a planar mode in the intra prediction other than the matrix weighted intra prediction.

[0016]

25 Moreover, for example, in the performing of the secondary transform, when the prediction image is generated using the matrix weighted intra prediction only for a luma signal, the circuitry may use, as the transform set for

the secondary transform, the common transform set only for the luma signal.

[0017]

Moreover, for example, in the performing of the secondary transform, for both a luma signal and a chroma signal, the circuitry may use, as the common transform set, a transform set for use in a planar mode.

[0018]

Moreover, for example, in the performing of the secondary transform: for a luma signal, the circuitry may use, as the common transform set, a transform set for use in a planar mode in the intra prediction other than the matrix weighted intra prediction; and for a chroma signal, the circuitry may use, as the common transform set, a transform set for use in a CCLM mode in the intra prediction other than the matrix weighted intra prediction.

[0019]

Moreover, a decoder according to one aspect of the present disclosure is a decoder that decodes an image. The decoder includes: circuitry; and memory coupled to the circuitry, in which in operation, the circuitry: decodes data of the image; performs inverse quantization on the data; performs secondary inverse transform on a result of the inverse quantization, and performs primary inverse transform on a result of the secondary inverse transform; and derives the image by adding, to a prediction image of the image, a result of the primary inverse transform as a prediction error of the image, and in the performing of the secondary inverse transform, when a matrix weighted intra prediction included in intra prediction and having a plurality of prediction modes is used, the circuitry uses, as an inverse transform set for the secondary inverse transform, a common inverse transform set shared among the plurality of prediction modes, the matrix weighted intra prediction generating the prediction image by performing matrix calculation on a pixel sequence obtained

from pixel values of surrounding pixels of a current block, the inverse transform set for the secondary inverse transform being applied to quantized coefficients obtained from the result of the inverse quantization.

[0020]

5 In this manner, when the matrix weighted intra prediction is used in the performing of the secondary inverse transform, the decoder can use the common inverse transform set to reduce the ROM size needed to store coefficients for the secondary inverse transform. With this, in the decoder, it is possible to reduce the circuit size and improve the encoding efficiency.

10 [0021]

 Here, for example, the common inverse transform set may be identical to an inverse transform set for use in a planar mode in the intra prediction other than the matrix weighted intra prediction.

[0022]

15 Moreover, for example, in the performing of the secondary inverse transform, when the prediction image is generated using the matrix weighted intra prediction only for a luma signal, the circuitry may use, as the inverse transform set for the secondary inverse transform, the common inverse transform set only for the luma signal.

20 [0023]

 Moreover, for example, in the performing of the secondary inverse transform, for both a luma signal and a chroma signal, the circuitry may use, as the common inverse transform set, an inverse transform set for use in a planar mode.

25 [0024]

 Moreover, for example, in the performing of the secondary inverse transform: for a luma signal, the circuitry may use, as the common inverse

transform set, an inverse transform set for use in a planar mode in the intra prediction other than the matrix weighted intra prediction; and for a chroma signal, the circuitry may use, as the common inverse transform set, an inverse transform set for use in a CCLM mode in the intra prediction other than the
5 matrix weighted intra prediction.
[0025]

Moreover, for example, an encoding method according to one aspect of the present disclosure is an encoding method of encoding an image. The encoding method includes: deriving a prediction error of the image by
10 subtracting a prediction image of the image from the image, the prediction image being generated using intra prediction or inter prediction; performing primary transform on the prediction error, and performing secondary transform on a result of the primary transform; performing quantization on a result of the secondary transform; and encoding a result of the quantization as data of the
15 image, in which in the performing of the secondary transform, when a matrix weighted intra prediction included in the intra prediction and having a plurality of prediction modes is used, a common transform set shared among the plurality of prediction modes is used as a transform set for the secondary transform, the matrix weighted intra prediction generating the prediction
20 image by performing matrix calculation on a pixel sequence obtained from pixel values of surrounding pixels of a current block, the transform set for the secondary transform being applied to primary transform coefficients obtained from the result of the primary transform.

[0026]
25 In this manner, when the matrix weighted intra prediction is used in the performing of the secondary transform, it is possible to use the common transform set to reduce the ROM size needed to store coefficients for the

secondary transform. With this, in the encoding method, it is possible to reduce the circuit size and improve the encoding efficiency.

[0027]

Moreover, for example, a decoding method according to one aspect of the
5 present disclosure is a decoding method of decoding an image. The decoding
method includes: decoding data of the image; performing inverse quantization
on the data; performing secondary inverse transform on a result of the inverse
quantization, and performing primary inverse transform on a result of the
secondary inverse transform; and deriving the image by adding, to a prediction
10 image of the image, a result of the primary inverse transform as a prediction
error of the image, in which in the performing of the secondary inverse
transform, when a matrix weighted intra prediction included in intra
prediction and having a plurality of prediction modes is used, a common inverse
transform set shared among the plurality of prediction modes is used as an
15 inverse transform set for the secondary inverse transform, the matrix weighted
intra prediction generating the prediction image by performing matrix
calculation on a pixel sequence obtained from pixel values of surrounding pixels
of a current block, the inverse transform set for the secondary inverse
transform being applied to quantized coefficients obtained from the result of
20 the inverse quantization. .

[0028]

In this manner, when the matrix weighted intra prediction is used in
the performing of the secondary inverse transform, it is possible to use the
common inverse transform set to reduce the ROM size needed to store
25 coefficients for the secondary inverse transform. With this, in the decoding
method, it is possible to reduce the circuit size and improve the encoding
efficiency.

[0029]

Furthermore, these general and specific aspects may be implemented using a system, a device, a method, an integrated circuit, a computer program, a computer-readable recording medium such as a CD-ROM, or any combination
5 of systems, devices, methods, integrated circuits, computer programs or recording media.

[0030]

Hereinafter, embodiments will be described with reference to the drawings. Note that the embodiments described below each show a general or
10 specific example. The numerical values, shapes, materials, components, the arrangement and connection of the components, steps, the relation and order of the steps, etc., indicated in the following embodiments are mere examples, and are not intended to limit the scope of the claims.

[0031]

15 Embodiments of an encoder and a decoder will be described below. The embodiments are examples of an encoder and a decoder to which the processes and/or configurations presented in the description of aspects of the present disclosure are applicable. The processes and/or configurations can also be implemented in an encoder and a decoder different from those according
20 to the embodiments. For example, regarding the processes and/or configurations as applied to the embodiments, any of the following may be implemented:

[0032]

(1) Any of the components of the encoder or the decoder according to the
25 embodiments presented in the description of aspects of the present disclosure may be substituted or combined with another component presented anywhere in the description of aspects of the present disclosure.

[0033]

(2) In the encoder or the decoder according to the embodiments, discretionary changes may be made to functions or processes performed by one or more components of the encoder or the decoder, such as addition, substitution, removal, etc., of the functions or processes. For example, any function or process may be substituted or combined with another function or process presented anywhere in the description of aspects of the present disclosure.

[0034]

(3) In methods implemented by the encoder or the decoder according to the embodiments, discretionary changes may be made such as addition, substitution, and removal of one or more of the processes included in the method. For example, any process in the method may be substituted or combined with another process presented anywhere in the description of aspects of the present disclosure.

[0035]

(4) One or more components included in the encoder or the decoder according to embodiments may be combined with a component presented anywhere in the description of aspects of the present disclosure, may be combined with a component including one or more functions presented anywhere in the description of aspects of the present disclosure, and may be combined with a component that implements one or more processes implemented by a component presented in the description of aspects of the present disclosure.

[0036]

(5) A component including one or more functions of the encoder or the decoder according to the embodiments, or a component that implements one or

more processes of the encoder or the decoder according to the embodiments,
may be combined or substituted with a component presented anywhere in the
description of aspects of the present disclosure, with a component including one
or more functions presented anywhere in the description of aspects of the
5 present disclosure, or with a component that implements one or more processes
presented anywhere in the description of aspects of the present disclosure.

[0037]

(6) In methods implemented by the encoder or the decoder according to
the embodiments, any of the processes included in the method may be
10 substituted or combined with a process presented anywhere in the description
of aspects of the present disclosure or with any corresponding or equivalent
process.

[0038]

(7) One or more processes included in methods implemented by the
15 encoder or the decoder according to the embodiments may be combined with a
process presented anywhere in the description of aspects of the present
disclosure.

[0039]

(8) The implementation of the processes and/or configurations
20 presented in the description of aspects of the present disclosure is not limited to
the encoder or the decoder according to the embodiments. For example, the
processes and/or configurations may be implemented in a device used for a
purpose different from the moving picture encoder or the moving picture
decoder disclosed in the embodiments.

25 [Encoder]

[0040]

First, an encoder according to an embodiment will be described. FIG.

1 is a block diagram illustrating a functional configuration of encoder 100 according to the embodiment. Encoder 100 is a video encoder which encodes a video in units of a block.

[0041]

As illustrated in FIG. 1, encoder 100 is an apparatus which encodes an image in units of a block, and includes splitter 102, subtractor 104, transformer 106, quantizer 108, entropy encoder 110, inverse quantizer 112, inverse transformer 114, adder 116, block memory 118, loop filter 120, frame memory 122, intra predictor 124, inter predictor 126, and prediction controller 128.

[0042]

Encoder 100 is implemented as, for example, a generic processor and memory. In this case, when a software program stored in the memory is executed by the processor, the processor functions as splitter 102, subtractor 104, transformer 106, quantizer 108, entropy encoder 110, inverse quantizer 112, inverse transformer 114, adder 116, loop filter 120, intra predictor 124, inter predictor 126, and prediction controller 128. Alternatively, encoder 100 may be implemented as one or more dedicated electronic circuits corresponding to splitter 102, subtractor 104, transformer 106, quantizer 108, entropy encoder 110, inverse quantizer 112, inverse transformer 114, adder 116, loop filter 120, intra predictor 124, inter predictor 126, and prediction controller 128.

[0043]

Hereinafter, an overall flow of processes performed by encoder 100 is described, and then each of constituent elements included in encoder 100 will be described.

[Overall Flow of Encoding Process]

[0044]

FIG. 2 is a flow chart indicating one example of an overall encoding

process performed by encoder 100.

[0045]

First, splitter 102 of encoder 100 splits each of pictures included in an input image which is a video into a plurality of blocks having a fixed size (e.g.,
5 128×128 pixels) (Step Sa_1). Splitter 102 then selects a splitting pattern for the fixed-size block (also referred to as a block shape) (Step Sa_2). In other words, splitter 102 further splits the fixed-size block into a plurality of blocks which form the selected splitting pattern. Encoder 100 performs, for each of the plurality of blocks, Steps Sa_3 to Sa_9 for the block (that is a current block
10 to be encoded).

[0046]

In other words, a prediction processor which includes all or part of intra predictor 124, inter predictor 126, and prediction controller 128 generates a prediction signal (also referred to as a prediction block) of the current block to
15 be encoded (also referred to as a current block) (Step Sa_3).

[0047]

Next, subtractor 104 generates a difference between the current block and a prediction block as a prediction residual (also referred to as a difference block) (Step Sa_4).

20 [0048]

Next, transformer 106 transforms the difference block and quantizer 108 quantizes the result, to generate a plurality of quantized coefficients (Step Sa_5). It is to be noted that the block having the plurality of quantized coefficients is also referred to as a coefficient block.

25 [0049]

Next, entropy encoder 110 encodes (specifically, entropy encodes) the coefficient block and a prediction parameter related to generation of a

prediction signal to generate an encoded signal (Step Sa_6). It is to be noted that the encoded signal is also referred to as an encoded bitstream, a compressed bitstream, or a stream.

[0050]

5 Next, inverse quantizer 112 performs inverse quantization of the coefficient block and inverse transformer 114 performs inverse transform of the result, to restore a plurality of prediction residuals (that is, a difference block) (Step Sa_7).

[0051]

10 Next, adder 116 adds the prediction block to the restored difference block to reconstruct the current block as a reconstructed image (also referred to as a reconstructed block or a decoded image block) (Step Sa_8). In this way, the reconstructed image is generated.

[0052]

15 When the reconstructed image is generated, loop filter 120 performs filtering of the reconstructed image as necessary (Step Sa_9).

[0053]

Encoder 100 then determines whether encoding of the entire picture has been finished (Step Sa_10). When determining that the encoding has not yet been finished (No in Step Sa_10), processes from Step Sa_2 are executed repeatedly.

[0054]

Although encoder 100 selects one splitting pattern for a fixed-size block, and encodes each block according to the splitting pattern in the above-described example, it is to be noted that each block may be encoded according to a corresponding one of a plurality of splitting patterns. In this case, encoder 100 may evaluate a cost for each of the plurality of splitting patterns, and, for

example, may select the encoded signal obtainable by encoding according to the splitting pattern which yields the smallest cost as an encoded signal which is output.

[0055]

5 As illustrated, the processes in Steps Sa_1 to Sa_10 are performed sequentially by encoder 100. Alternatively, two or more of the processes may be performed in parallel, the processes may be reordered, etc.

[Splitter]

[0056]

10 Splitter 102 splits each of pictures included in an input video into a plurality of blocks, and outputs each block to subtractor 104. For example, splitter 102 first splits a picture into blocks of a fixed size (for example, 128×128). Other fixed block sizes may be employed. The fixed-size block is also referred to as a coding tree unit (CTU). Splitter 102 then splits each
15 fixed-size block into blocks of variable sizes (for example, 64×64 or smaller), based on recursive quadtree and/or binary tree block splitting. In other words, splitter 102 selects a splitting pattern. The variable-size block is also referred to as a coding unit (CU), a prediction unit (PU), or a transform unit (TU). It is to be noted that, in various kinds of processing examples, there is no need to
20 differentiate between CU, PU, and TU; all or some of the blocks in a picture may be processed in units of a CU, a PU, or a TU.

[0057]

FIG. 3 is a conceptual diagram illustrating one example of block splitting according to an embodiment. In FIG. 3, the solid lines represent
25 block boundaries of blocks split by quadtree block splitting, and the dashed lines represent block boundaries of blocks split by binary tree block splitting.

[0058]

Here, block 10 is a square block having 128×128 pixels (128×128 block). This 128×128 block 10 is first split into four square 64×64 blocks (quadtree block splitting).

[0059]

5 The upper-left 64×64 block is further vertically split into two rectangular 32×64 blocks, and the left 32×64 block is further vertically split into two rectangular 16×64 blocks (binary tree block splitting). As a result, the upper-left 64×64 block is split into two 16×64 blocks 11 and 12 and one 32×64 block 13.

10 [0060]

 The upper-right 64×64 block is horizontally split into two rectangular 64×32 blocks 14 and 15 (binary tree block splitting).

[0061]

 The lower-left 64×64 block is first split into four square 32×32 blocks
15 (quadtree block splitting). The upper-left block and the lower-right block among the four 32×32 blocks are further split. The upper-left 32×32 block is vertically split into two rectangle 16×32 blocks, and the right 16×32 block is further horizontally split into two 16×16 blocks (binary tree block splitting). The lower-right 32×32 block is horizontally split into two 32×16 blocks (binary
20 tree block splitting). As a result, the lower-left 64×64 block is split into 16×32 block 16, two 16×16 blocks 17 and 18, two 32×32 blocks 19 and 20, and two 32×16 blocks 21 and 22.

[0062]

 The lower-right 64×64 block 23 is not split.

25 [0063]

 As described above, in FIG. 3, block 10 is split into thirteen variable-size blocks 11 through 23 based on recursive quadtree and binary tree

block splitting. This type of splitting is also referred to as quadtree plus binary tree (QTBT) splitting.

[0064]

It is to be noted that, in FIG. 3, one block is split into four or two blocks
5 (quadtree or binary tree block splitting), but splitting is not limited to these examples. For example, one block may be split into three blocks (ternary block splitting). Splitting including such ternary block splitting is also referred to as multi-type tree (MBT) splitting.

[Picture Structure: Slice/Tile]

10 [0065]

A picture may be configured in units of one or more slices or tiles in order to decode the picture in parallel. The picture configured in units of one or more slices or tiles may be configured by splitter 102.

[0066]

15 Slices are basic encoding units included in a picture. A picture may include, for example, one or more slices. In addition, a slice includes one or more successive coding tree units (CTU).

[0067]

FIG. 4A is a conceptual diagram illustrating one example of a slice
20 configuration. For example, a picture includes 11×8 CTUs and is split into four slices (slices 1 to 4). Slice 1 includes sixteen CTUs, slice 2 includes twenty-one CTUs, slice 3 includes twenty-nine CTUs, and slice 4 includes twenty-two CTUs. Here, each CTU in the picture belongs to one of the slices. The shape of each slice is a shape obtainable by splitting the picture
25 horizontally. A boundary of each slice does not need to be coincide with an image end, and may be coincide with any of the boundaries between CTUs in the image. The processing order of the CTUs in a slice (an encoding order or a

decoding order) is, for example, a raster-scan order. A slice includes header information and encoded data. Features of the slice may be described in header information. The features include a CTU address of a top CTU in the slice, a slice type, etc.

5 [0068]

A tile is a unit of a rectangular region included in a picture. Each of tiles may be assigned with a number referred to as TileId in raster-scan order.

[0069]

FIG. 4B is a conceptual diagram indicating an example of a tile
10 configuration. For example, a picture includes 11×8 CTUs and is split into four tiles of rectangular regions (tiles 1 to 4). When tiles are used, the processing order of CTUs are changed from the processing order in the case where no tile is used. When no tile is used, CTUs in a picture are processed in raster-scan order. When tiles are used, at least one CTU in each of the tiles is
15 processed in raster-scan order. For example, as illustrated in FIG. 4B, the processing order of the CTUs included in tile 1 is the order which starts from the left-end of the first row of tile 1 toward the right-end of the first row of tile 1 and then starts from the left-end of the second row of tile 1 toward the right-end of the second row of tile 1.

20 [0070]

It is to be noted that the one tile may include one or more slices, and one slice may include one or more tiles.

[Subtractor]

[0071]

25 Subtractor 104 subtracts a prediction signal (prediction sample that is input from prediction controller 128 indicated below) from an original signal (original sample) in units of a block input from splitter 102 and split by splitter

102. In other words, subtractor 104 calculates prediction errors (also referred to as residuals) of a block to be encoded (hereinafter also referred to as a current block). Subtractor 104 then outputs the calculated prediction errors (residuals) to transformer 106.

5 [0072]

The original signal is a signal which has been input into encoder 100 and represents an image of each picture included in a video (for example, a luma signal and two chroma signals). Hereinafter, a signal representing an image is also referred to as a sample.

10 [Transformer]

[0073]

Transformer 106 transforms prediction errors in spatial domain into transform coefficients in frequency domain, and outputs the transform coefficients to quantizer 108. More specifically, transformer 106 applies, for
15 example, a defined discrete cosine transform (DCT) or discrete sine transform (DST) to prediction errors in spatial domain. The defined DCT or DST may be predefined.

[0074]

It is to be noted that transformer 106 may adaptively select a transform
20 type from among a plurality of transform types, and transform prediction errors into transform coefficients by using a transform basis function corresponding to the selected transform type. This sort of transform is also referred to as explicit multiple core transform (EMT) or adaptive multiple transform (AMT).

25 [0075]

The transform types include, for example, DCT-II, DCT-V, DCT-VIII, DST-I, and DST-VII. FIG. 5A is a chart indicating transform basis functions

for the example transform types. In FIG. 5A, N indicates the number of input pixels. For example, selection of a transform type from among the plurality of transform types may depend on a prediction type (one of intra prediction and inter prediction), and may depend on an intra prediction mode.

5 [0076]

Information indicating whether to apply such EMT or AMT (referred to as, for example, an EMT flag or an AMT flag) and information indicating the selected transform type is normally signaled at the CU level. It is to be noted that the signaling of such information does not necessarily need to be performed at the CU level, and may be performed at another level (for example, at the bit sequence level, picture level, slice level, tile level, or CTU level).

[0077]

In addition, transformer 106 may re-transform the transform coefficients (transform result). Such re-transform is also referred to as adaptive secondary transform (AST) or non-separable secondary transform (NSST). For example, transformer 106 performs re-transform in units of a sub-block (for example, 4×4 sub-block) included in a transform coefficient block corresponding to an intra prediction error. Information indicating whether to apply NSST and information related to a transform matrix for use in NSST are normally signaled at the CU level. It is to be noted that the signaling of such information does not necessarily need to be performed at the CU level, and may be performed at another level (for example, at the sequence level, picture level, slice level, tile level, or CTU level).

[0078]

25 Transformer 106 may employ a separable transform and a non-separable transform. A separable transform is a method in which a transform is performed a plurality of times by separately performing a

transform for each of a number of directions according to the number of dimensions of inputs. A non-separable transform is a method of performing a collective transform in which two or more dimensions in multidimensional inputs are collectively regarded as a single dimension.

5 [0079]

In one example of a non-separable transform, when an input is a 4×4 block, the 4×4 block is regarded as a single array including sixteen elements, and the transform applies a 16×16 transform matrix to the array.

[0080]

10 In another example of a non-separable transform, a 4×4 input block is regarded as a single array including sixteen elements, and then a transform (hypercube gives transform) in which gives revolution is performed on the array a plurality of times may be performed.

[0081]

15 In the transform in transformer 106, the types of bases to be transformed into the frequency domain according to regions in a CU can be switched. Examples include spatially varying transforms (SVT). In SVT, as illustrated in FIG. 5B, CUs are split into two equal regions horizontally or vertically, and only one of the regions is transformed into the frequency
20 domain. A transform basis type can be set for each region. For example, DST7 and DST8 are used. In this example, only one of these two regions in the CU is transformed, and the other is not transformed. However, both of these two regions may be transformed. In addition, the splitting method is not limited to the splitting into two equal regions, and can be more flexible. For
25 example, the CU may be split into four equal regions, or information indicating splitting may be encoded separately and be signaled in the same manner as the CU splitting. It is to be noted that SVT is also referred to as sub-block

transform (SBT).

[Quantizer]

[0082]

Quantizer 108 quantizes the transform coefficients output from
5 transformer 106. More specifically, quantizer 108 scans, in a determined
scanning order, the transform coefficients of the current block, and quantizes
the scanned transform coefficients based on quantization parameters (QP)
corresponding to the transform coefficients. Quantizer 108 then outputs the
quantized transform coefficients (hereinafter also referred to as quantized
10 coefficients) of the current block to entropy encoder 110 and inverse quantizer
112. The determined scanning order may be predetermined.

[0083]

A determined scanning order is an order for quantizing/inverse
quantizing transform coefficients. For example, a determined scanning order
15 may be defined as ascending order of frequency (from low to high frequency) or
descending order of frequency (from high to low frequency).

[0084]

A quantization parameter (QP) is a parameter defining a quantization
step (quantization width). For example, when the value of the quantization
20 parameter increases, the quantization step also increases. In other words,
when the value of the quantization parameter increases, the quantization error
increases.

[0085]

In addition, a quantization matrix may be used for quantization. For
25 example, several kinds of quantization matrices may be used correspondingly
to frequency transform sizes such as 4×4 and 8×8, prediction modes such as
intra prediction and inter prediction, and pixel components such as luma and

chroma pixel components. It is to be noted that quantization means digitalizing values sampled at determined intervals correspondingly to determined levels. In this technical field, quantization may be referred to using other expressions, such as rounding and scaling, and may employ
5 rounding and scaling. The determined intervals and levels may be predetermined.

[0086]

Methods using quantization matrices include a method using a quantization matrix which has been set directly at the encoder side and a
10 method using a quantization matrix which has been set as a default (default matrix). At the encoder side, a quantization matrix suitable for features of an image can be set by directly setting a quantization matrix. This case, however, has a disadvantage of increasing a coding amount for encoding the quantization matrix.

15 [0087]

There is a method for quantizing a high-frequency coefficient and a low-frequency coefficient without using a quantization matrix. It is to be noted that this method is equivalent to a method using a quantization matrix (flat matrix) whose coefficients have the same value.

20 [0088]

The quantization matrix may be specified using, for example, a sequence parameter set (SPS) or a picture parameter set (PPS). The SPS includes a parameter which is used for a sequence, and the PPS includes a parameter which is used for a picture. Each of the SPS and the PPS may be
25 simply referred to as a parameter set.

[Entropy Encoder]

[0089]

Entropy encoder 110 generates an encoded signal (encoded bitstream) based on quantized coefficients which have been input from quantizer 108. More specifically, entropy encoder 110, for example, binarizes quantized coefficients, and arithmetically encodes the binary signal, and outputs a
5 compressed bit stream or sequence.

[Inverse Quantizer]

[0090]

Inverse quantizer 112 inverse quantizes quantized coefficients which have been input from quantizer 108. More specifically, inverse quantizer 112
10 inverse quantizes, in a determined scanning order, quantized coefficients of the current block. Inverse quantizer 112 then outputs the inverse quantized transform coefficients of the current block to inverse transformer 114. The determined scanning order may be predetermined.

[Inverse Transformer]

15 [0091]

Inverse transformer 114 restores prediction errors (residuals) by inverse transforming transform coefficients which have been input from inverse quantizer 112. More specifically, inverse transformer 114 restores the prediction errors of the current block by applying an inverse transform
20 corresponding to the transform applied by transformer 106 on the transform coefficients. Inverse transformer 114 then outputs the restored prediction errors to adder 116.

[0092]

It is to be noted that since information is lost in quantization, the
25 restored prediction errors do not match the prediction errors calculated by subtractor 104. In other words, the restored prediction errors normally include quantization errors.

[Adder]

[0093]

Adder 116 reconstructs the current block by adding prediction errors which have been input from inverse transformer 114 and prediction samples
5 which have been input from prediction controller 128. Adder 116 then outputs the reconstructed block to block memory 118 and loop filter 120. A reconstructed block is also referred to as a local decoded block.

[Block Memory]

[0094]

10 Block memory 118 is, for example, storage for storing blocks in a picture to be encoded (hereinafter referred to as a current picture) which is referred to in intra prediction. More specifically, block memory 118 stores reconstructed blocks output from adder 116.

[Frame Memory]

15 [0095]

Frame memory 122 is, for example, storage for storing reference pictures for use in inter prediction, and is also referred to as a frame buffer. More specifically, frame memory 122 stores reconstructed blocks filtered by loop filter 120.

20 [Loop Filter]

[0096]

Loop filter 120 applies a loop filter to blocks reconstructed by adder 116, and outputs the filtered reconstructed blocks to frame memory 122. A loop filter is a filter used in an encoding loop (in-loop filter), and includes, for
25 example, a deblocking filter (DF or DBF), a sample adaptive offset (SAO), and an adaptive loop filter (ALF).

[0097]

In an ALF, a least square error filter for removing compression artifacts is applied. For example, one filter selected from among a plurality of filters based on the direction and activity of local gradients is applied for each of 2×2 sub-blocks in the current block.

5 [0098]

More specifically, first, each sub-block (for example, each 2×2 sub-block) is categorized into one out of a plurality of classes (for example, fifteen or twenty-five classes). The classification of the sub-block is based on gradient directionality and activity. For example, classification index C (for example, C = 5D + A) is derived based on gradient directionality D (for example, 0 to 2 or 0 to 4) and gradient activity A (for example, 0 to 4). Then, based on classification index C, each sub-block is categorized into one out of a plurality of classes.

[0099]

15 For example, gradient directionality D is calculated by comparing gradients of a plurality of directions (for example, the horizontal, vertical, and two diagonal directions). Moreover, for example, gradient activity A is calculated by adding gradients of a plurality of directions and quantizing the result of addition.

20 [0100]

The filter to be used for each sub-block is determined from among the plurality of filters based on the result of such categorization.

[0101]

The filter shape to be used in an ALF is, for example, a circular
25 symmetric filter shape. FIG. 6A through FIG. 6C illustrate examples of filter shapes used in ALFs. FIG. 6A illustrates a 5×5 diamond shape filter, FIG. 6B illustrates a 7×7 diamond shape filter, and FIG. 6C illustrates a 9×9 diamond

shape filter. Information indicating the filter shape is normally signaled at the picture level. It is to be noted that the signaling of such information indicating the filter shape does not necessarily need to be performed at the picture level, and may be performed at another level (for example, at the
5 sequence level, slice level, tile level, CTU level, or CU level).

[0102]

The ON or OFF of the ALF is determined, for example, at the picture level or CU level. For example, the decision of whether to apply the ALF to luma may be made at the CU level, and the decision of whether to apply ALF to
10 chroma may be made at the picture level. Information indicating ON or OFF of the ALF is normally signaled at the picture level or CU level. It is to be noted that the signaling of information indicating ON or OFF of the ALF does not necessarily need to be performed at the picture level or CU level, and may be performed at another level (for example, at the sequence level, slice level,
15 tile level, or CTU level).

[0103]

The coefficient set for the plurality of selectable filters (for example, fifteen or up to twenty-five filters) is normally signaled at the picture level. It is to be noted that the signaling of the coefficient set does not necessarily need
20 to be performed at the picture level, and may be performed at another level (for example, at the sequence level, slice level, tile level, CTU level, CU level, or sub-block level).

[Loop Filter > Deblocking Filter]

[0104]

25 In a deblocking filter, loop filter 120 performs a filter process on a block boundary in a reconstructed image so as to reduce distortion which occurs at the block boundary.

[0105]

FIG. 7 is a block diagram illustrating one example of a specific configuration of loop filter 120 which functions as a deblocking filter.

[0106]

5 Loop filter 120 includes: boundary determiner 1201; filter determiner 1203; filtering executor 1205; process determiner 1208; filter characteristic determiner 1207; and switches 1202, 1204, and 1206.

[0107]

10 Boundary determiner 1201 determines whether a pixel to be deblock-filtered (that is, a current pixel) is present around a block boundary. Boundary determiner 1201 then outputs the determination result to switch 1202 and processing determiner 1208.

[0108]

15 In the case where boundary determiner 1201 has determined that a current pixel is present around a block boundary, switch 1202 outputs an unfiltered image to switch 1204. In the opposite case where boundary determiner 1201 has determined that no current pixel is present around a block boundary, switch 1202 outputs an unfiltered image to switch 1206.

[0109]

20 Filter determiner 1203 determines whether to perform deblocking filtering of the current pixel, based on the pixel value of at least one surrounding pixel located around the current pixel. Filter determiner 1203 then outputs the determination result to switch 1204 and processing determiner 1208.

25 [0110]

 In the case where filter determiner 1203 has determined to perform deblocking filtering of the current pixel, switch 1204 outputs the unfiltered

image obtained through switch 1202 to filtering executor 1205. In the opposite case where filter determiner 1203 has determined not to perform deblocking filtering of the current pixel, switch 1204 outputs the unfiltered image obtained through switch 1202 to switch 1206.

5 [0111]

When obtaining the unfiltered image through switches 1202 and 1204, filtering executor 1205 executes, for the current pixel, deblocking filtering with the filter characteristic determined by filter characteristic determiner 1207. Filtering executor 1205 then outputs the filtered pixel to switch 1206.

10 [0112]

Under control by processing determiner 1208, switch 1206 selectively outputs a pixel which has not been deblock-filtered and a pixel which has been deblock-filtered by filtering executor 1205.

[0113]

15 Processing determiner 1208 controls switch 1206 based on the results of determinations made by boundary determiner 1201 and filter determiner 1203. In other words, processing determiner 1208 causes switch 1206 to output the pixel which has been deblock-filtered when boundary determiner 1201 has determined that the current pixel is present around the block boundary and
20 filter determiner 1203 has determined to perform deblocking filtering of the current pixel. In addition, other than the above case, processing determiner 1208 causes switch 1206 to output the pixel which has not been deblock-filtered. A filtered image is output from switch 1206 by repeating output of a pixel in this way.

25 [0114]

FIG. 8 is a conceptual diagram indicating an example of a deblocking filter having a symmetrical filtering characteristic with respect to a block

boundary.

[0115]

In a deblocking filter process, one of two deblocking filters having different characteristics, that is, a strong filter and a weak filter is selected using pixel values and quantization parameters. In the case of the strong filter, pixels p0 to p2 and pixels q0 to q2 are present across a block boundary as illustrated in FIG. 8, the pixel values of the respective pixel q0 to q2 are changed to pixel values q'0 to q'2 by performing, for example, computations according to the expressions below.

[0116]

$$q'0 = (p1 + 2 \times p0 + 2 \times q0 + 2 \times q1 + q2 + 4) / 8$$

$$q'1 = (p0 + q0 + q1 + q2 + 2) / 4$$

$$q'2 = (p0 + q0 + q1 + 3 \times q2 + 2 \times q3 + 4) / 8$$

[0117]

It is to be noted that, in the above expressions, p0 to p2 and q0 to q2 are the pixel values of respective pixels p0 to p2 and pixels q0 to q2. In addition, q3 is the pixel value of neighboring pixel q3 located at the opposite side of pixel q2 with respect to the block boundary. In addition, in the right side of each of the expressions, coefficients which are multiplied with the respective pixel values of the pixels to be used for deblocking filtering are filter coefficients.

[0118]

Furthermore, in the deblocking filtering, clipping may be performed so that the calculated pixel values are not set over a threshold value. In the clipping process, the pixel values calculated according to the above expressions are clipped to a value obtained according to “a computation pixel value $\pm 2 \times$ a threshold value” using the threshold value determined based on a quantization parameter. In this way, it is possible to prevent excessive smoothing.

[0119]

FIG. 9 is a conceptual diagram for illustrating a block boundary on which a deblocking filter process is performed. FIG. 10 is a conceptual diagram indicating examples of Bs values.

5 [0120]

The block boundary on which the deblocking filter process is performed is, for example, a boundary between prediction units (PU) having 8×8 pixel blocks as illustrated in FIG. 9 or a boundary between transform units (TU). The deblocking filter process may be performed in units of four rows or four
10 columns. First, boundary strength (Bs) values are determined as indicated in FIG. 10 for block P and block Q illustrated in FIG. 9.

[0121]

According to the Bs values in FIG. 10, whether to perform deblocking filter processes of block boundaries belonging to the same image using different
15 strengths is determined. The deblocking filter process for a chroma signal is performed when a Bs value is 2. The deblocking filter process for a luma signal is performed when a Bs value is 1 or more and a determined condition is satisfied. The determined condition may be predetermined. It is to be noted that conditions for determining Bs values are not limited to those indicated in
20 FIG. 10, and a Bs value may be determined based on another parameter.

[Prediction Processor (Intra Predictor, Inter Predictor, Prediction Controller)]

[0122]

FIG. 11 is a flow chart illustrating one example of a process performed
25 by the prediction processor of encoder 100. It is to be noted that the prediction processor includes all or part of the following constituent elements: intra predictor 124; inter predictor 126; and prediction controller 128.

[0123]

The prediction processor generates a prediction image of a current block (Step Sb_1). This prediction image is also referred to as a prediction signal or a prediction block. It is to be noted that the prediction signal is, for example,
5 an intra prediction signal or an inter prediction signal. Specifically, the prediction processor generates the prediction image of the current block using a reconstructed image which has been already obtained through generation of a prediction block, generation of a difference block, generation of a coefficient block, restoring of a difference block, and generation of a decoded image block.

10 [0124]

The reconstructed image may be, for example, an image in a reference picture, or an image of an encoded block in a current picture which is the picture including the current block. The encoded block in the current picture is, for example, a neighboring block of the current block.

15 [0125]

FIG. 12 is a flow chart illustrating another example of a process performed by the prediction processor of encoder 100.

[0126]

The prediction processor generates a prediction image using a first
20 method (Step Sc_1a), generates a prediction image using a second method (Step Sc_1b), and generates a prediction image using a third method (Step Sc_1c). The first method, the second method, and the third method may be mutually different methods for generating a prediction image. Each of the first to third methods may be an inter prediction method, an intra prediction method, or
25 another prediction method. The above-described reconstructed image may be used in these prediction methods.

[0127]

Next, the prediction processor selects any one of a plurality of prediction methods generated in Steps Sc_1a, Sc_1b, and Sc_1c (Step Sc_2). The selection of the prediction image, that is selection of a method or a mode for obtaining a final prediction image may be made by calculating a cost for each of the generated prediction images and based on the cost. Alternatively, the selection of the prediction image may be made based on a parameter which is used in an encoding process. Encoder 100 may transform information for identifying a selected prediction image, a method, or a mode into an encoded signal (also referred to as an encoded bitstream). The information may be, for example, a flag or the like. In this way, the decoder is capable of generating a prediction image according to the method or the mode selected based on the information in encoder 100. It is to be noted that, in the example illustrated in FIG. 12, the prediction processor selects any of the prediction images after the prediction images are generated using the respective methods. However, the prediction processor may select a method or a mode based on a parameter for use in the above-described encoding process before generating prediction images, and may generate a prediction image according to the method or mode selected.

[0128]

For example, the first method and the second method may be intra prediction and inter prediction, respectively, and the prediction processor may select a final prediction image for a current block from prediction images generated according to the prediction methods.

[0129]

FIG. 13 is a flow chart illustrating another example of a process performed by the prediction processor of encoder 100.

[0130]

First, the prediction processor generates a prediction image using intra prediction (Step Sd_1a), and generates a prediction image using inter prediction (Step Sd_1b). It is to be noted that the prediction image generated by intra prediction is also referred to as an intra prediction image, and the
5 prediction image generated by inter prediction is also referred to as an inter prediction image.

[0131]

Next, the prediction processor evaluates each of the intra prediction image and the inter prediction image (Step Sd_2). A cost may be used in the
10 evaluation. In other words, the prediction processor calculates cost C for each of the intra prediction image and the inter prediction image. Cost C may be calculated according to an expression of an R-D optimization model, for example, $C = D + \lambda \times R$. In this expression, D indicates a coding distortion of a prediction image, and is represented as, for example, a sum of absolute
15 differences between the pixel value of a current block and the pixel value of a prediction image. In addition, R indicates a predicted coding amount of a prediction image, specifically, the coding amount required to encode motion information for generating a prediction image, etc. In addition, λ indicates, for example, a multiplier according to the method of Lagrange multiplier.

20 [0132]

The prediction processor then selects the prediction image for which the smallest cost C has been calculated among the intra prediction image and the inter prediction image, as the final prediction image for the current block (Step Sd_3). In other words, the prediction method or the mode for generating the
25 prediction image for the current block is selected.

[Intra Predictor]

[0133]

Intra predictor 124 generates a prediction signal (intra prediction signal) by performing intra prediction (also referred to as intra frame prediction) of the current block by referring to a block or blocks in the current picture and stored in block memory 118. More specifically, intra predictor 124
5 generates an intra prediction signal by performing intra prediction by referring to samples (for example, luma and/or chroma values) of a block or blocks neighboring the current block, and then outputs the intra prediction signal to prediction controller 128.

[0134]

10 For example, intra predictor 124 performs intra prediction by using one mode from among a plurality of intra prediction modes which have been defined. The intra prediction modes include one or more non-directional prediction modes and a plurality of directional prediction modes. The defined modes may be predefined.

15 [0135]

The one or more non-directional prediction modes include, for example, the planar prediction mode and DC prediction mode defined in the H.265 / high-efficiency video coding (HEVC) standard.

[0136]

20 The plurality of directional prediction modes include, for example, the thirty-three directional prediction modes defined in the H.265/HEVC standard. It is to be noted that the plurality of directional prediction modes may further include thirty-two directional prediction modes in addition to the thirty-three directional prediction modes (for a total of sixty-five directional prediction
25 modes). FIG. 14 is a conceptual diagram illustrating sixty-seven intra prediction modes in total that may be used in intra prediction (two non-directional prediction modes and sixty-five directional prediction modes).

The solid arrows represent the thirty-three directions defined in the H.265/HEVC standard, and the dashed arrows represent the additional thirty-two directions (the two non-directional prediction modes are not illustrated in FIG. 14).

5 [0137]

In various kinds of processing examples, a luma block may be referred to in intra prediction of a chroma block. In other words, a chroma component of the current block may be predicted based on a luma component of the current block. Such intra prediction is also referred to as cross-component linear
10 model (CCLM) prediction. The intra prediction mode for a chroma block in which such a luma block is referred to (also referred to as, for example, a CCLM mode) may be added as one of the intra prediction modes for chroma blocks.

[0138]

Intra predictor 124 may correct intra-predicted pixel values based on
15 horizontal/vertical reference pixel gradients. Intra prediction accompanied by this sort of correcting is also referred to as position dependent intra prediction combination (PDPC). Information indicating whether to apply PDPC (referred to as, for example, a PDPC flag) is normally signaled at the CU level. It is to be noted that the signaling of such information does not necessarily need
20 to be performed at the CU level, and may be performed at another level (for example, at the sequence level, picture level, slice level, tile level, or CTU level).

[Inter Predictor]

[0139]

Inter predictor 126 generates a prediction signal (inter prediction
25 signal) by performing inter prediction (also referred to as inter frame prediction) of the current block by referring to a block or blocks in a reference picture, which is different from the current picture and is stored in frame

memory 122. Inter prediction is performed in units of a current block or a current sub-block (for example, a 4×4 block) in the current block. For example, inter predictor 126 performs motion estimation in a reference picture for the current block or the current sub-block, and finds out a reference block or a sub-block which best matches the current block or the current sub-block. Inter predictor 126 then obtains motion information (for example, a motion vector) which compensates a motion or a change from the reference block or the sub-block to the current block or the sub-block. Inter predictor 126 generates an inter prediction signal of the current block or the sub-block by performing motion compensation (or motion prediction) based on the motion information. Inter predictor 126 outputs the generated inter prediction signal to prediction controller 128.

[0140]

The motion information used in motion compensation may be signaled as inter prediction signals in various forms. For example, a motion vector may be signaled. As another example, the difference between a motion vector and a motion vector predictor may be signaled.

[Basic Flow of Inter Prediction]

[0141]

FIG. 15 is a flow chart illustrating an example basic processing flow of inter prediction.

[0142]

First, inter predictor 126 generates a prediction signal (Steps Se_1 to Se_3). Next, subtractor 104 generates the difference between a current block and a prediction image as a prediction residual (Step Se_4).

[0143]

Here, in the generation of the prediction image, inter predictor 126

generates the prediction image through determination of a motion vector (MV) of the current block (Steps Se_1 and Se_2) and motion compensation (Step Se_3). Furthermore, in determination of an MV, inter predictor 126 determines the MV through selection of a motion vector candidate (MV candidate) (Step Se_1) and derivation of an MV (Step Se_2). The selection of the MV candidate is made by, for example, selecting at least one MV candidate from an MV candidate list. Alternatively, in derivation of an MV, inter predictor 126 may further select at least one MV candidate from the at least one MV candidate, and determine the selected at least one MV candidate as the MV for the current block. Alternatively, inter predictor 126 may determine the MV for the current block by performing estimation in a reference picture region specified by each of the selected at least one MV candidate. It is to be noted that the estimation in a reference picture region may be referred to as motion estimation.

[0144]

In addition, although Steps Se_1 to Se_3 are performed by inter predictor 126 in the above-described example, a process that is for example Step Se_1, Step Se_2, or the like may be performed by another constituent element included in encoder 100.

[Motion Vector Derivation Flow]

[0145]

FIG. 16 is a flow chart illustrating one example of derivation of motion vectors.

[0146]

Inter predictor 126 derives an MV of a current block in a mode for encoding motion information (for example, an MV). In this case, for example, the motion information is encoded as a prediction parameter, and is signaled.

In other words, the encoded motion information is included in an encoded signal (also referred to as an encoded bitstream).

[0147]

Alternatively, inter predictor 126 derives an MV in a mode in which
5 motion information is not encoded. In this case, no motion information is included in an encoded signal.

[0148]

Here, MV derivation modes may include a normal inter mode, a merge mode, a FRUC mode, an affine mode, etc. which are described later. Modes in
10 which motion information is encoded among the modes include the normal inter mode, the merge mode, the affine mode (specifically, an affine inter mode and an affine merge mode), etc. It is to be noted that motion information may include not only an MV but also motion vector predictor selection information which is described later. Modes in which no motion information is encoded
15 include the FRUC mode, etc. Inter predictor 126 selects a mode for deriving an MV of the current block from the modes, and derives the MV of the current block using the selected mode.

[0149]

FIG. 17 is a flow chart illustrating another example of derivation of
20 motion vectors.

[0150]

Inter predictor 126 derives an MV of a current block in a mode in which an MV difference is encoded. In this case, for example, the MV difference is encoded as a prediction parameter, and is signaled. In other words, the
25 encoded MV difference is included in an encoded signal. The MV difference is the difference between the MV of the current block and the MV predictor.

[0151]

Alternatively, inter predictor 126 derives an MV in a mode in which no MV difference is encoded. In this case, no encoded MV difference is included in an encoded signal.

[0152]

5 Here, as described above, the MV derivation modes include the normal inter mode, the merge mode, the FRUC mode, the affine mode, etc. which are described later. Modes in which an MV difference is encoded among the modes include the normal inter mode, the affine mode (specifically, the affine inter mode), etc. Modes in which no MV difference is encoded include the
10 FRUC mode, the merge mode, the affine mode (specifically, the affine merge mode), etc. Inter predictor 126 selects a mode for deriving an MV of the current block from the plurality of modes, and derives the MV of the current block using the selected mode.

[Motion Vector Derivation Flow]

15 [0153]

FIG. 18 is a flow chart illustrating another example of derivation of motion vectors. The MV derivation modes which are inter prediction modes include a plurality of modes and are roughly divided into modes in which an MV difference is encoded and modes in which no motion vector difference is
20 encoded. The modes in which no MV difference is encoded include the merge mode, the FRUC mode, the affine mode (specifically, the affine merge mode), etc. These modes are described in detail later. Simply, the merge mode is a mode for deriving an MV of a current block by selecting a motion vector from an encoded surrounding block, and the FRUC mode is a mode for deriving an MV
25 of a current block by performing estimation between encoded regions. The affine mode is a mode for deriving, as an MV of a current block, a motion vector of each of a plurality of sub-blocks included in the current block, assuming

affine transform.

[0154]

More specifically, as illustrated when the inter prediction mode information indicates 0 (0 in Sf_1), inter predictor 126 derives a motion vector
5 using the merge mode (Sf_2). When the inter prediction mode information indicates 1 (1 in Sf_1), inter predictor 126 derives a motion vector using the FRUC mode (Sf_3). When the inter prediction mode information indicates 2 (2 in Sf_1), inter predictor 126 derives a motion vector using the affine mode (specifically, the affine merge mode) (Sf_4). When the inter prediction mode
10 information indicates 3 (3 in Sf_1), inter predictor 126 derives a motion vector using a mode in which an MV difference is encoded (for example, a normal inter mode (Sf_5).

[MV Derivation > Normal Inter Mode]

[0155]

15 The normal inter mode is an inter prediction mode for deriving an MV of a current block based on a block similar to the image of the current block from a reference picture region specified by an MV candidate. In this normal inter mode, an MV difference is encoded.

[0156]

20 FIG. 19 is a flow chart illustrating an example of inter prediction in normal inter mode.

[0157]

First, inter predictor 126 obtains a plurality of MV candidates for a current block based on information such as MVs of a plurality of encoded blocks
25 temporally or spatially surrounding the current block (Step Sg_1). In other words, inter predictor 126 generates an MV candidate list.

[0158]

Next, inter predictor 126 extracts N (an integer of 2 or larger) MV candidates from the plurality of MV candidates obtained in Step Sg_1, as motion vector predictor candidates (also referred to as MV predictor candidates) according to a determined priority order (Step Sg_2). It is to be noted that the priority order may be determined in advance for each of the N MV candidates.

[0159]

Next, inter predictor 126 selects one motion vector predictor candidate from the N motion vector predictor candidates, as the motion vector predictor (also referred to as an MV predictor) of the current block (Step Sg_3). At this time, inter predictor 126 encodes, in a stream, motion vector predictor selection information for identifying the selected motion vector predictor. It is to be noted that the stream is an encoded signal or an encoded bitstream as described above.

[0160]

Next, inter predictor 126 derives an MV of a current block by referring to an encoded reference picture (Step Sg_4). At this time, inter predictor 126 further encodes, in the stream, the difference value between the derived MV and the motion vector predictor as an MV difference. It is to be noted that the encoded reference picture is a picture including a plurality of blocks which have been reconstructed after being encoded.

[0161]

Lastly, inter predictor 126 generates a prediction image for the current block by performing motion compensation of the current block using the derived MV and the encoded reference picture (Step Sg_5). It is to be noted that the prediction image is an inter prediction signal as described above.

[0162]

In addition, information indicating the inter prediction mode (normal inter mode in the above example) used to generate the prediction image is, for example, encoded as a prediction parameter.

[0163]

5 It is to be noted that the MV candidate list may be also used as a list for use in another mode. In addition, the processes related to the MV candidate list may be applied to processes related to the list for use in another mode. The processes related to the MV candidate list include, for example, extraction or selection of an MV candidate from the MV candidate list, reordering of MV
10 candidates, or deletion of an MV candidate.

[MV Derivation > Merge Mode]

[0164]

The merge mode is an inter prediction mode for selecting an MV candidate from an MV candidate list as an MV of a current block, thereby
15 deriving the MV.

[0165]

FIG. 20 is a flow chart illustrating an example of inter prediction in merge mode.

[0166]

20 First, inter predictor 126 obtains a plurality of MV candidates for a current block based on information such as MVs of a plurality of encoded blocks temporally or spatially surrounding the current block (Step Sh_1). In other words, inter predictor 126 generates an MV candidate list.

[0167]

25 Next, inter predictor 126 selects one MV candidate from the plurality of MV candidates obtained in Step Sh_1, thereby deriving an MV of the current block (Step Sh_2). At this time, inter predictor 126 encodes, in a stream, MV

selection information for identifying the selected MV candidate.

[0168]

Lastly, inter predictor 126 generates a prediction image for the current block by performing motion compensation of the current block using the derived MV and the encoded reference picture (Step Sh_3).

[0169]

In addition, information indicating the inter prediction mode (merge mode in the above example) used to generate the prediction image and included in the encoded signal is, for example, encoded as a prediction parameter.

[0170]

FIG. 21 is a conceptual diagram for illustrating one example of a motion vector derivation process of a current picture in merge mode.

[0171]

First, an MV candidate list in which MV predictor candidates are registered is generated. Examples of MV predictor candidates include: spatially neighboring MV predictors which are MVs of a plurality of encoded blocks located spatially surrounding a current block; temporally neighboring MV predictors which are MVs of surrounding blocks on which the position of a current block in an encoded reference picture is projected; combined MV predictors which are MVs generated by combining the MV value of a spatially neighboring MV predictor and the MV of a temporally neighboring MV predictor; and a zero MV predictor which is an MV having a zero value.

[0172]

Next, one MV predictor is selected from a plurality of MV predictors registered in an MV predictor list, and the selected MV predictor is determined as the MV of a current block.

[0173]

Furthermore, the variable length encoder describes and encodes, in a stream, merge_idx which is a signal indicating which MV predictor has been selected.

[0174]

5 It is to be noted that the MV predictors registered in the MV predictor list described in FIG. 21 are examples. The number of MV predictors may be different from the number of MV predictors in the diagram, the MV predictor list may be configured in such a manner that some of the kinds of the MV predictors in the diagram may not be included, or that one or more MV
10 predictors other than the kinds of MV predictors in the diagram are included.

[0175]

A final MV may be determined by performing a decoder motion vector refinement process (DMVR) to be described later using the MV of the current block derived in merge mode.

15 [0176]

It is to be noted that the MV predictor candidates are MV candidates described above, and the MV predictor list is the MV candidate list described above. It is to be noted that the MV candidate list may be referred to as a candidate list. In addition, merge_idx is MV selection information.

20 [MV Derivation > FRUC Mode]

[0177]

Motion information may be derived at the decoder side without being signaled from the encoder side. It is to be noted that, as described above, the merge mode defined in the H.265/HEVC standard may be used. In addition,
25 for example, motion information may be derived by performing motion estimation at the decoder side. In an embodiment, at the decoder side, motion estimation is performed without using any pixel value in a current block.

[0178]

Here, a mode for performing motion estimation at the decoder side is described. The mode for performing motion estimation at the decoder side may be referred to as a pattern matched motion vector derivation (PMMVD) mode, or a frame rate up-conversion (FRUC) mode.

[0179]

One example of a FRUC process in the form of a flow chart is illustrated in FIG. 22. First, a list of a plurality of candidates each having a motion vector (MV) predictor (that is, an MV candidate list that may be also used as a merge list) is generated by referring to a motion vector in an encoded block which spatially or temporally neighbors a current block (Step Si_1). Next, a best MV candidate is selected from the plurality of MV candidates registered in the MV candidate list (Step Si_2). For example, the evaluation values of the respective MV candidates included in the MV candidate list are calculated, and one MV candidate is selected based on the evaluation values. Based on the selected motion vector candidates, a motion vector for the current block is then derived (Step Si_4). More specifically, for example, the selected motion vector candidate (best MV candidate) is derived directly as the motion vector for the current block. In addition, for example, the motion vector for the current block may be derived using pattern matching in a surrounding region of a position in a reference picture where the position in the reference picture corresponds to the selected motion vector candidate. In other words, estimation using the pattern matching and the evaluation values may be performed in the surrounding region of the best MV candidate, and when there is an MV that yields a better evaluation value, the best MV candidate may be updated to the MV that yields the better evaluation value, and the updated MV may be determined as the final MV for the current block. A configuration in which no

such a process for updating the best MV candidate to the MV having a better evaluation value is performed is also possible.

[0180]

5 Lastly, inter predictor 126 generates a prediction image for the current block by performing motion compensation of the current block using the derived MV and the encoded reference picture (Step Si_5).

[0181]

A similar process may be performed in units of a sub-block.

[0182]

10 Evaluation values may be calculated according to various kinds of methods. For example, a comparison is made between a reconstructed image in a region in a reference picture corresponding to a motion vector and a reconstructed image in a determined region (the region may be, for example, a region in another reference picture or a region in a neighboring block of a
15 current picture, as indicated below). The determined region may be predetermined.

[0183]

 The difference between the pixel values of the two reconstructed images may be used for an evaluation value of the motion vectors. It is to be noted
20 that an evaluation value may be calculated using information other than the value of the difference.

[0184]

 Next, an example of pattern matching is described in detail. First, one MV candidate included in an MV candidate list (for example, a merge list) is
25 selected as a start point of estimation by the pattern matching. For example, as the pattern matching, either a first pattern matching or a second pattern matching may be used. The first pattern matching and the second pattern

matching are also referred to as bilateral matching and template matching, respectively.

[MV Derivation > FRUC > Bilateral Matching]

[0185]

5 In the first pattern matching, pattern matching is performed between two blocks along a motion trajectory of a current block which are two blocks in different two reference pictures. Accordingly, in the first pattern matching, a region in another reference picture along the motion trajectory of the current block is used as a determined region for calculating the evaluation value of the
10 above-described candidate. The determined region may be predetermined.

[0186]

FIG. 23 is a conceptual diagram for illustrating one example of the first pattern matching (bilateral matching) between the two blocks in the two reference pictures along the motion trajectory. As illustrated in FIG. 23, in
15 the first pattern matching, two motion vectors (MV0, MV1) are derived by estimating a pair which best matches among pairs in the two blocks in the two different reference pictures (Ref0, Ref1) which are the two blocks along the motion trajectory of the current block (Cur block). More specifically, a difference between the reconstructed image at a specified location in the first
20 encoded reference picture (Ref0) specified by an MV candidate and the reconstructed image at a specified location in the second encoded reference picture (Ref1) specified by a symmetrical MV obtained by scaling the MV candidate at a display time interval is derived for the current block, and an evaluation value is calculated using the value of the obtained difference. It is
25 possible to select, as the final MV, the MV candidate which yields the best evaluation value among the plurality of MV candidates, and which is likely to produce good results.

[0187]

In the assumption of a continuous motion trajectory, the motion vectors (MV0, MV1) specifying the two reference blocks are proportional to temporal distances (TD0, TD1) between the current picture (Cur Pic) and the two reference pictures (Ref0, Ref1). For example, when the current picture is temporally located between the two reference pictures and the temporal distances from the current picture to the respective two reference pictures are equal to each other, mirror-symmetrical bi-directional motion vectors are derived in the first pattern matching.

10 [MV Derivation > FRUC > Template Matching]

[0188]

In the second pattern matching (template matching), pattern matching is performed between a block in a reference picture and a template in the current picture (the template is a block neighboring the current block in the current picture (the neighboring block is, for example, an upper and/or left neighboring block(s))). Accordingly, in the second pattern matching, the block neighboring the current block in the current picture is used as the determined region for calculating the evaluation value of the above-described candidate.

[0189]

20 FIG. 24 is a conceptual diagram for illustrating one example of pattern matching (template matching) between a template in a current picture and a block in a reference picture. As illustrated in FIG. 24, in the second pattern matching, the motion vector of the current block (Cur block) is derived by estimating, in the reference picture (Ref0), the block which best matches the block neighboring the current block in the current picture (Cur Pic). More specifically, it is possible that the difference between a reconstructed image in an encoded region which neighbors both left and above or either left or above

and a reconstructed image which is in a corresponding region in the encoded reference picture (Ref0) and is specified by an MV candidate is derived, an evaluation value is calculated using the value of the obtained difference, and the MV candidate which yields the best evaluation value among a plurality of
5 MV candidates is selected as the best MV candidate.
[0190]

Such information indicating whether to apply the FRUC mode (referred to as, for example, a FRUC flag) may be signaled at the CU level. In addition, when the FRUC mode is applied (for example, when a FRUC flag is true),
10 information indicating an applicable pattern matching method (either the first pattern matching or the second pattern matching) may be signaled at the CU level. It is to be noted that the signaling of such information does not necessarily need to be performed at the CU level, and may be performed at another level (for example, at the sequence level, picture level, slice level, tile
15 level, CTU level, or sub-block level).

[MV Derivation > Affine Mode]
[0191]

Next, the affine mode for deriving a motion vector in units of a sub-block based on motion vectors of a plurality of neighboring blocks is
20 described. This mode is also referred to as an affine motion compensation prediction mode.
[0192]

FIG. 25A is a conceptual diagram for illustrating one example of deriving a motion vector of each sub-block based on motion vectors of a
25 plurality of neighboring blocks. In FIG. 25A, the current block includes sixteen 4×4 sub-blocks. Here, motion vector V_0 at an upper-left corner control point in the current block is derived based on a motion vector of a neighboring

block, and likewise, motion vector V_1 at an upper-right corner control point in the current block is derived based on a motion vector of a neighboring sub-block. Two motion vectors v_0 and v_1 may be projected according to an expression (1A) indicated below, and motion vectors (v_x, v_y) for the respective
5 sub-blocks in the current block may be derived.

[0193]

[Math. 1]

$$\begin{cases} v_x = \frac{(v_{1x}-v_{0x})}{w}x - \frac{(v_{1y}-v_{0y})}{w}y + v_{0x} \\ v_y = \frac{(v_{1y}-v_{0y})}{w}x - \frac{(v_{1x}-v_{0x})}{w}y + v_{0y} \end{cases} \quad (1A)$$

[0194]

10 Here, x and y indicate the horizontal position and the vertical position of the sub-block, respectively, and w indicates a determined weighting coefficient. The determined weighting coefficient may be predetermined.

[0195]

Such information indicating the affine mode (for example, referred to as
15 an affine flag) may be signaled at the CU level. It is to be noted that the signaling of the information indicating the affine mode does not necessarily need to be performed at the CU level, and may be performed at another level (for example, at the sequence level, picture level, slice level, tile level, CTU level, or sub-block level).

20 [0196]

In addition, the affine mode may include several modes for different methods for deriving motion vectors at the upper-left and upper-right corner control points. For example, the affine mode include two modes which are the affine inter mode (also referred to as an affine normal inter mode) and the
25 affine merge mode.

[MV Derivation > Affine Mode]

[0197]

FIG. 25B is a conceptual diagram for illustrating one example of deriving a motion vector of each sub-block in affine mode in which three control points are used. In FIG. 25B, the current block includes sixteen 4×4 blocks.

5 Here, motion vector V_0 at the upper-left corner control point for the current block is derived based on a motion vector of a neighboring block, and likewise, motion vector V_1 at the upper-right corner control point for the current block is derived based on a motion vector of a neighboring block, and motion vector V_2 at the lower-left corner control point for the current block is derived based on a
10 motion vector of a neighboring block. Three motion vectors v_0 , v_1 , and v_2 may be projected according to an expression (1B) indicated below, and motion vectors (v_x, v_y) for the respective sub-blocks in the current block may be derived.

[0198]

[Math. 2]

$$15 \quad \begin{cases} v_x = \frac{(v_{1x}-v_{0x})}{w}x - \frac{(v_{2x}-v_{0x})}{h}y + v_{0x} \\ v_y = \frac{(v_{1y}-v_{0y})}{w}x - \frac{(v_{2y}-v_{0y})}{h}y + v_{0y} \end{cases} \quad (1B)$$

[0199]

Here, x and y indicate the horizontal position and the vertical position of the center of the sub-block, respectively, w indicates the width of the current block, and h indicates the height of the current block.

20 [0200]

Affine modes in which different numbers of control points (for example, two and three control points) are used may be switched and signaled at the CU level. It is to be noted that information indicating the number of control points in affine mode used at the CU level may be signaled at another level (for
25 example, the sequence level, picture level, slice level, tile level, CTU level, or sub-block level).

[0201]

In addition, such an affine mode in which three control points are used may include different methods for deriving motion vectors at the upper-left, upper-right, and lower-left corner control points. For example, the affine
5 modes include two modes which are the affine inter mode (also referred to as the affine normal inter mode) and the affine merge mode.

[MV Derivation > Affine Merge Mode]

[0202]

FIG. 26A, FIG. 26B, and FIG. 26C are conceptual diagrams for
10 illustrating the affine merge mode.

[0203]

As illustrated in FIG. 26A, in the affine merge mode, for example, motion vector predictors at respective control points of a current block are calculated based on a plurality of motion vectors corresponding to blocks
15 encoded according to the affine mode among encoded block A (left), block B (upper), block C (upper-right), block D (lower-left), and block E (upper-left) which neighbor the current block. More specifically, encoded block A (left), block B (upper), block C (upper-right), block D (lower-left), and block E (upper-left) are checked in the listed order, and the first effective block encoded
20 according to the affine mode is identified. Motion vector predictors at the control points of the current block are calculated based on a plurality of motion vectors corresponding to the identified block.

[0204]

For example, as illustrated in FIG. 26B, when block A which neighbors
25 to the left of the current block has been encoded according to an affine mode in which two control points are used, motion vectors v_3 and v_4 projected at the upper-left corner position and the upper-right corner position of the encoded

block including block A are derived. Motion vector predictor v_0 at the upper-left corner control point of the current block and motion vector predictor v_1 at the upper-right corner control point of the current block are then calculated from derived motion vectors v_3 and v_4 .

5 [0205]

For example, as illustrated in FIG. 26C, when block A which neighbors to the left of the current block has been encoded according to an affine mode in which three control points are used, motion vectors v_3 , v_4 , and v_5 projected at the upper-left corner position, the upper-right corner position, and the lower-left corner position of the encoded block including block A are derived. Motion vector predictor v_0 at the upper-left corner control point of the current block, motion vector predictor v_1 at the upper-right corner control point of the current block, and motion vector predictor v_2 at the lower-left corner control point of the current block are then calculated from derived motion vectors v_3 , v_4 , and v_5 .

15 and v_5 .

[0206]

It is to be noted that this method for deriving motion vector predictors may be used to derive motion vector predictors of the respective control points of the current block in Step Sj_1 in FIG. 29 described later.

20 [0207]

FIG. 27 is a flow chart illustrating one example of the affine merge mode.

[0208]

In affine merge mode as illustrated, first, inter predictor 126 derives MV predictors of respective control points of a current block (Step Sk_1). The control points are an upper-left corner point of the current block and an upper-right corner point of the current block as illustrated in FIG. 25A, or an

upper-left corner point of the current block, an upper-right corner point of the current block, and a lower-left corner point of the current block as illustrated in FIG. 25B.

[0209]

5 In other words, as illustrated in FIG. 26A, inter predictor 126 checks encoded block A (left), block B (upper), block C (upper-right), block D (lower-left), and block E (upper-left) in the listed order, and identifies the first effective block encoded according to the affine mode.

[0210]

10 When block A is identified and block A has two control points, as illustrated in FIG. 26B, inter predictor 126 calculates motion vector v_0 at the upper-left corner control point of the current block and motion vector v_1 at the upper-right corner control point of the current block from motion vectors v_3 and v_4 at the upper-left corner and the upper-right corner of the encoded block including block A. For example, inter predictor 126 calculates motion vector v_0 at the upper-left corner control point of the current block and motion vector v_1 at the upper-right corner control point of the current block by projecting motion vectors v_3 and v_4 at the upper-left corner and the upper-right corner of the encoded block onto the current block.

20 [0211]

 Alternatively, when block A is identified and block A has three control points, as illustrated in FIG. 26C, inter predictor 126 calculates motion vector v_0 at the upper-left corner control point of the current block, motion vector v_1 at the upper-right corner control point of the current block, and motion vector v_2 at the lower-left corner control point of the current block from motion vectors v_3 , v_4 , and v_5 at the upper-left corner, the upper-right corner, and the lower-left corner of the encoded block including block A. For example, inter predictor

126 calculates motion vector v_0 at the upper-left corner control point of the current block, motion vector v_1 at the upper-right corner control point of the current block, and motion vector v_2 at the lower-left corner control point of the current block by projecting motion vectors v_3 , v_4 , and v_5 at the upper-left corner, the upper-right corner, and the lower-left corner of the encoded block onto the current block.

[0212]

Next, inter predictor 126 performs motion compensation of each of a plurality of sub-blocks included in the current block. In other words, inter predictor 126 calculates, for each of the plurality of sub-blocks, a motion vector of the sub-block as an affine MV, by using either (i) two motion vector predictors v_0 and v_1 and the expression (1A) described above or (ii) three motion vector predictors v_0 , v_1 , and v_2 and the expression (1B) described above (Step Sk_2). Inter predictor 126 then performs motion compensation of the sub-blocks using these affine MVs and encoded reference pictures (Step Sk_3). As a result, motion compensation of the current block is performed to generate a prediction image of the current block.

[MV Derivation > Affine Inter Mode]

[0213]

FIG. 28A is a conceptual diagram for illustrating an affine inter mode in which two control points are used.

[0214]

In the affine inter mode, as illustrated in FIG. 28A, a motion vector selected from motion vectors of encoded block A, block B, and block C which neighbor the current block is used as motion vector predictor v_0 at the upper-left corner control point of the current block. Likewise, a motion vector selected from motion vectors of encoded block D and block E which neighbor the

current block is used as motion vector predictor v_1 at the upper-right corner control point of the current block.

[0215]

FIG. 28B is a conceptual diagram for illustrating an affine inter mode
5 in which three control points are used.

[0216]

In the affine inter mode, as illustrated in FIG. 28B, a motion vector selected from motion vectors of encoded block A, block B, and block C which neighbor the current block is used as motion vector predictor v_0 at the
10 upper-left corner control point of the current block. Likewise, a motion vector selected from motion vectors of encoded block D and block E which neighbor the current block is used as motion vector predictor v_1 at the upper-right corner control point of the current block. Furthermore, a motion vector selected from motion vectors of encoded block F and block G which neighbor the current block
15 is used as motion vector predictor v_2 at the lower-left corner control point of the current block.

[0217]

FIG. 29 is a flow chart illustrating one example of an affine inter mode.

[0218]

20 In the affine inter mode as illustrated, first, inter predictor 126 derives MV predictors (v_0, v_1) or (v_0, v_1, v_2) of respective two or three control points of a current block (Step S_{j_1}). The control points are an upper-left corner point of the current block and an upper-right corner point of the current block as illustrated in FIG. 25A, or an upper-left corner point of the current block, an
25 upper-right corner point of the current block, and a lower-left corner point of the current block as illustrated in FIG. 25B.

[0219]

In other words, inter predictor 126 derives the motion vector predictors (v_0, v_1) or (v_0, v_1, v_2) of respective two or three control points of the current block by selecting motion vectors of any of the blocks among encoded blocks in the vicinity of the respective control points of the current block illustrated in either
5 FIG. 28A or FIG. 28B. At this time, inter predictor 126 encodes, in a stream, motion vector predictor selection information for identifying the selected two motion vectors.

[0220]

For example, inter predictor 126 may determine, using a cost
10 evaluation or the like, the block from which a motion vector as a motion vector predictor at a control point is selected from among encoded blocks neighboring the current block, and may describe, in a bitstream, a flag indicating which motion vector predictor has been selected.

[0221]

15 Next, inter predictor 126 performs motion estimation (Step Sj_3 and Sj_4) while updating a motion vector predictor selected or derived in Step Sj_1 (Step Sj_2). In other words, inter predictor 126 calculates, as an affine MV, a motion vector of each of sub-blocks which corresponds to an updated motion vector predictor, using either the expression (1A) or expression (1B) described
20 above (Step Sj_3). Inter predictor 126 then performs motion compensation of the sub-blocks using these affine MVs and encoded reference pictures (Step Sj_4). As a result, for example, inter predictor 126 determines the motion vector predictor which yields the smallest cost as the motion vector at a control point in a motion estimation loop (Step Sj_5). At this time, inter predictor 126
25 further encodes, in the stream, the difference value between the determined MV and the motion vector predictor as an MV difference.

[0222]

Lastly, inter predictor 126 generates a prediction image for the current block by performing motion compensation of the current block using the determined MV and the encoded reference picture (Step Sj_6).

[MV Derivation > Affine Inter Mode]

5 [0223]

When affine modes in which different numbers of control points (for example, two and three control points) are used may be switched and signaled at the CU level, the number of control points in an encoded block and the number of control points in a current block may be different from each other.

10 FIG. 30A and FIG. 30B are conceptual diagrams for illustrating methods for deriving motion vector predictors at control points when the number of control points in an encoded block and the number of control points in a current block are different from each other.

[0224]

15 For example, as illustrated in FIG. 30A, when a current block has three control points at the upper-left corner, the upper-right corner, and the lower-left corner, and block A which neighbors to the left of the current block has been encoded according to an affine mode in which two control points are used, motion vectors v_3 and v_4 projected at the upper-left corner position and
20 the upper-right corner position in the encoded block including block A are derived. Motion vector predictor v_0 at the upper-left corner control point of the current block and motion vector predictor v_1 at the upper-right corner control point of the current block are then calculated from derived motion vectors v_3 and v_4 . Furthermore, motion vector predictor v_2 at the lower-left corner
25 control point is calculated from derived motion vectors v_0 and v_1 .

[0225]

For example, as illustrated in FIG. 30B, when a current block has two

control points at the upper-left corner and the upper-right corner, and block A which neighbors to the left of the current block has been encoded according to the affine mode in which three control points are used, motion vectors v_3 , v_4 , and v_5 projected at the upper-left corner position, the upper-right corner position, and the lower-left corner position in the encoded block including block A are derived. Motion vector predictor v_0 at the upper-left corner control point of the current block and motion vector predictor v_1 at the upper-right corner control point of the current block are then calculated from derived motion vectors v_3 , v_4 , and v_5 .

10 [0226]

It is to be noted that this method for deriving motion vector predictors may be used to derive motion vector predictors of the respective control points of the current block in Step Sj_1 in FIG. 29.

[MV Derivation > DMVR]

15 [0227]

FIG. 31A is a flow chart illustrating a relationship between the merge mode and DMVR.

[0228]

Inter predictor 126 derives a motion vector of a current block according to the merge mode (Step Sl_1). Next, inter predictor 126 determines whether to perform estimation of a motion vector, that is, motion estimation (Step Sl_2). Here, when determining not to perform motion estimation (No in Step Sl_2), inter predictor 126 determines the motion vector derived in Step Sl_1 as the final motion vector for the current block (Step Sl_4). In other words, in this case, the motion vector of the current block is determined according to the merge mode.

25 [0229]

When determining to perform motion estimation in Step SI_1 (Yes in Step SI_2), inter predictor 126 derives the final motion vector for the current block by estimating a surrounding region of the reference picture specified by the motion vector derived in Step SI_1 (Step SI_3). In other words, in this case, the motion vector of the current block is determined according to the DMVR.

[0230]

FIG. 31B is a conceptual diagram for illustrating one example of a DMVR process for determining an MV.

10 [0231]

First, (for example, in merge mode) the best MVP which has been set to the current block is determined to be an MV candidate. A reference pixel is identified from a first reference picture (L0) which is an encoded picture in the L0 direction according to an MV candidate (L0). Likewise, a reference pixel is identified from a second reference picture (L1) which is an encoded picture in the L1 direction according to an MV candidate (L1). A template is generated by calculating an average of these reference pixels.

[0232]

Next, each of the surrounding regions of MV candidates of the first reference picture (L0) and the second reference picture (L1) are estimated, and the MV which yields the smallest cost is determined to be the final MV. It is to be noted that the cost value may be calculated, for example, using a difference value between each of the pixel values in the template and a corresponding one of the pixel values in the estimation region, the values of MV candidates, etc.

[0233]

It is to be noted that the processes, configurations, and operations

described here typically are basically common between the encoder and a decoder to be described later.

[0234]

Exactly the same example processes described here do not always need
5 to be performed. Any process for enabling derivation of the final MV by estimation in surrounding regions of MV candidates may be used.

[Motion Compensation > BIO/OBMC]

[0235]

Motion compensation involves a mode for generating a prediction
10 image, and correcting the prediction image. The mode is, for example, BIO and OBMC to be described later.

[0236]

FIG. 32 is a flow chart illustrating one example of generation of a prediction image.

15 [0237]

Inter predictor 126 generates a prediction image (Step Sm_1), and corrects the prediction image, for example, according to any of the modes described above (Step Sm_2).

[0238]

20 FIG. 33 is a flow chart illustrating another example of generation of a prediction image.

[0239]

Inter predictor 126 determines a motion vector of a current block (Step Sn_1). Next, inter predictor 126 generates a prediction image (Step Sn_2),
25 and determines whether to perform a correction process (Step Sn_3). Here, when determining to perform a correction process (Yes in Step Sn_3), inter predictor 126 generates the final prediction image by correcting the prediction

image (Step Sn_4). When determining not to perform a correction process (No in Step Sn_3), inter predictor 126 outputs the prediction image as the final prediction image without correcting the prediction image (Step Sn_5).

[0240]

5 In addition, motion compensation involves a mode for correcting a luminance of a prediction image when generating the prediction image. The mode is, for example, LIC to be described later.

[0241]

FIG. 34 is a flow chart illustrating another example of generation of a
10 prediction image.

[0242]

Inter predictor 126 derives a motion vector of a current block (Step So_1). Next, inter predictor 126 determines whether to perform a luminance correction process (Step So_2). Here, when determining to perform a
15 luminance correction process (Yes in Step So_2), inter predictor 126 generates the prediction image while performing a luminance correction process (Step So_3). In other words, the prediction image is generated using LIC. When determining not to perform a luminance correction process (No in Step So_2), inter predictor 126 generates a prediction image by performing normal motion
20 compensation without performing a luminance correction process (Step So_4).

[Motion Compensation > OBMC]

[0243]

It is to be noted that an inter prediction signal may be generated using motion information for a neighboring block in addition to motion information
25 for the current block obtained from motion estimation. More specifically, the inter prediction signal may be generated in units of a sub-block in the current block by performing a weighted addition of a prediction signal based on motion

information obtained from motion estimation (in the reference picture) and a prediction signal based on motion information for a neighboring block (in the current picture). Such inter prediction (motion compensation) is also referred to as overlapped block motion compensation (OBMC).

5 [0244]

In OBMC mode, information indicating a sub-block size for OBMC (referred to as, for example, an OBMC block size) may be signaled at the sequence level. Moreover, information indicating whether to apply the OBMC mode (referred to as, for example, an OBMC flag) may be signaled at the CU
10 level. It is to be noted that the signaling of such information does not necessarily need to be performed at the sequence level and CU level, and may be performed at another level (for example, at the picture level, slice level, tile level, CTU level, or sub-block level).

[0245]

15 Examples of the OBMC mode will be described in further detail. FIGs. 35 and 36 are a flow chart and a conceptual diagram for illustrating an outline of a prediction image correction process performed by an OBMC process.

[0246]

First, as illustrated in FIG. 36, a prediction image (Pred) is obtained
20 through normal motion compensation using a motion vector (MV) assigned to the processing target (current) block. In FIG. 36, the arrow “MV” points a reference picture, and indicates what the current block of the current picture refers to in order to obtain a prediction image.

[0247]

25 Next, a prediction image (Pred_L) is obtained by applying a motion vector (MV_L) which has been already derived for the encoded block neighboring to the left of the current block to the current block (re-using the

motion vector for the current block). The motion vector (MV_L) is indicated by an arrow “MV_L” indicating a reference picture from a current block. A first correction of a prediction image is performed by overlapping two prediction images Pred and Pred_L. This provides an effect of blending the boundary
5 between neighboring blocks.

[0248]

Likewise, a prediction image (Pred_U) is obtained by applying a motion vector (MV_U) which has been already derived for the encoded block neighboring above the current block to the current block (re-using the motion
10 vector for the current block). The motion vector (MV_U) is indicated by an arrow “MV_U” indicating a reference picture from a current block. A second correction of a prediction image is performed by overlapping the prediction image Pred_U to the prediction images (for example, Pred and Pred_L) on which the first correction has been performed. This provides an effect of
15 blending the boundary between neighboring blocks. The prediction image obtained by the second correction is the one in which the boundary between the neighboring blocks has been blended (smoothed), and thus is the final prediction image of the current block.

[0249]

20 Although the above example is a two-path correction method using left and upper neighboring blocks, it is to be noted that the correction method may be three- or more-path correction method using also the right neighboring block and/or the lower neighboring block.

[0250]

25 It is to be noted that the region in which such overlapping is performed may be only part of a region near a block boundary instead of the pixel region of the entire block.

[0251]

It is to be noted that the prediction image correction process according to OBMC for obtaining one prediction image Pred from one reference picture by overlapping additional prediction image Pred_L and Pred_U have been
5 described above. However, when a prediction image is corrected based on a plurality of reference images, a similar process may be applied to each of the plurality of reference pictures. In such a case, after corrected prediction images are obtained from the respective reference pictures by performing OBMC image correction based on the plurality of reference pictures, the
10 obtained corrected prediction images are further overlapped to obtain the final prediction image.

[0252]

It is to be noted that, in OBMC, the unit of a current block may be the unit of a prediction block or the unit of a sub-block obtained by further splitting
15 the prediction block.

[0253]

One example of a method for determining whether to apply an OBMC process is a method for using an obmc_flag which is a signal indicating whether to apply an OBMC process. As one specific example, an encoder determines
20 whether the current block belongs to a region having complicated motion. The encoder sets the obmc_flag to a value of “1” when the block belongs to a region having complicated motion and applies an OBMC process when encoding, and sets the obmc_flag to a value of “0” when the block does not belong to a region having complicated motion and encodes the block without applying an OBMC
25 process. The decoder switches between application and non-application of an OBMC process by decoding the obmc_flag written in the stream (for example, a compressed sequence) and decoding the block by switching between the

application and non-application of the OBMC process in accordance with the flag value.

[0254]

Inter predictor 126 generates one rectangular prediction image for a
5 rectangular current block in the above example. However, inter predictor 126
may generate a plurality of prediction images each having a shape different
from a rectangle for the rectangular current block, and may combine the
plurality of prediction images to generate the final rectangular prediction
image. The shape different from a rectangle may be, for example, a triangle.

10 [0255]

FIG. 37 is a conceptual diagram for illustrating generation of two
triangular prediction images.

[0256]

Inter predictor 126 generates a triangular prediction image by
15 performing motion compensation of a first partition having a triangular shape
in a current block by using a first MV of the first partition, to generate a
triangular prediction image. Likewise, inter predictor 126 generates a
triangular prediction image by performing motion compensation of a second
partition having a triangular shape in a current block by using a second MV of
20 the second partition, to generate a triangular prediction image. Inter
predictor 126 then generates a prediction image having the same rectangular
shape as the rectangular shape of the current block by combining these
prediction images.

[0257]

25 It is to be noted that, although the first partition and the second
partition are triangles in the example illustrated in FIG. 37, the first partition
and the second partition may be trapezoids, or other shapes different from each

other. Furthermore, although the current block includes two partitions in the example illustrated in FIG. 37, the current block may include three or more partitions.

[0258]

5 In addition, the first partition and the second partition may overlap with each other. In other words, the first partition and the second partition may include the same pixel region. In this case, a prediction image for a current block may be generated using a prediction image in the first partition and a prediction image in the second partition.

10 [0259]

 In addition, although an example in which a prediction image is generated for each of two partitions using inter prediction, a prediction image may be generated for at least one partition using intra prediction.

 [Motion Compensation > BIO]

15 [0260]

 Next, a method for deriving a motion vector is described. First, a mode for deriving a motion vector based on a model assuming uniform linear motion will be described. This mode is also referred to as a bi-directional optical flow (BIO) mode.

20 [0261]

 FIG. 38 is a conceptual diagram for illustrating a model assuming uniform linear motion. In FIG. 38, (v_x, v_y) indicates a velocity vector, and τ_0 and τ_1 indicate temporal distances between a current picture (Cur Pic) and two reference pictures (Ref0, Ref1). (MV_{x0}, MV_{y0}) indicate motion vectors corresponding to reference picture Ref0, and (MV_{x1}, MV_{y1}) indicate motion vectors corresponding to reference picture Ref1.

[0262]

Here, under the assumption of uniform linear motion exhibited by velocity vectors (v_x, v_y) , (MV_{x0}, MV_{y0}) and (MV_{x1}, MV_{y1}) are represented as $(v_x\tau_0, v_y\tau_0)$ and $(-v_x\tau_1, -v_y\tau_1)$, respectively, and the following optical flow equation (2) may be employed.

5 [0263]

[Math. 3]

$$\partial I^{(k)} / \partial t + v_x \partial I^{(k)} / \partial x + v_y \partial I^{(k)} / \partial y = 0. (2)$$

[0264]

Here, $I(k)$ indicates a motion-compensated luma value of reference picture k ($k = 0, 1$). This optical flow equation shows that the sum of (i) the time derivative of the luma value, (ii) the product of the horizontal velocity and the horizontal component of the spatial gradient of a reference image, and (iii) the product of the vertical velocity and the vertical component of the spatial gradient of a reference image is equal to zero. A motion vector of each block obtained from, for example, a merge list may be corrected in units of a pixel, based on a combination of the optical flow equation and Hermite interpolation.

15

[0265]

It is to be noted that a motion vector may be derived on the decoder side using a method other than deriving a motion vector based on a model assuming uniform linear motion. For example, a motion vector may be derived in units of a sub-block based on motion vectors of neighboring blocks.

20

[Motion Compensation > LIC]

[0266]

Next, an example of a mode in which a prediction image (prediction) is generated by using a local illumination compensation (LIC) process will be described.

25

[0267]

FIG. 39 is a conceptual diagram for illustrating one example of a prediction image generation method using a luminance correction process performed by a LIC process.

[0268]

5 First, an MV is derived from an encoded reference picture, and a reference image corresponding to the current block is obtained.

[0269]

Next, information indicating how the luma value changed between the reference picture and the current picture is extracted for the current block.

10 This extraction is performed based on the luma pixel values for the encoded left neighboring reference region (surrounding reference region) and the encoded upper neighboring reference region (surrounding reference region), and the luma pixel value at the corresponding position in the reference picture specified by the derived MV. A luminance correction parameter is calculated by using
15 the information indicating how the luma value changed.

[0270]

The prediction image for the current block is generated by performing a luminance correction process in which the luminance correction parameter is applied to the reference image in the reference picture specified by the MV.

20 [0271]

It is to be noted that the shape of the surrounding reference region illustrated in FIG. 39 is just one example; the surrounding reference region may have a different shape.

[0272]

25 Moreover, although the process in which a prediction image is generated from a single reference picture has been described here, cases in which a prediction image is generated from a plurality of reference pictures can

be described in the same manner. The prediction image may be generated after performing a luminance correction process of the reference images obtained from the reference pictures in the same manner as described above.

[0273]

5 One example of a method for determining whether to apply a LIC process is a method for using a `lic_flag` which is a signal indicating whether to apply the LIC process. As one specific example, the encoder determines whether the current block belongs to a region having a luminance change. The encoder sets the `lic_flag` to a value of “1” when the block belongs to a region
10 having a luminance change and applies a LIC process when encoding, and sets the `lic_flag` to a value of “0” when the block does not belong to a region having a luminance change and encodes the current block without applying a LIC process. The decoder may decode the `lic_flag` written in the stream and decode the current block by switching between application and non-application of a
15 LIC process in accordance with the flag value.

[0274]

 One example of a different method of determining whether to apply a LIC process is a determining method in accordance with whether a LIC process was applied to a surrounding block. In one specific example, when the merge
20 mode is used on the current block, whether a LIC process was applied in the encoding of the surrounding encoded block selected upon deriving the MV in the merge mode process is determined. According to the result, encoding is performed by switching between application and non-application of a LIC process. It is to be noted that, also in this example, the same processes are
25 applied in processes at the decoder side.

[0275]

 An embodiment of the luminance correction (LIC) process described

with reference to FIG. 39 is described in detail below.

[0276]

First, inter predictor 126 derives a motion vector for obtaining a reference image corresponding to a current block to be encoded from a reference
5 picture which is an encoded picture.

[0277]

Next, inter predictor 126 extracts information indicating how the luma value of the reference picture has been changed to the luma value of the current picture, using the luma pixel value of an encoded surrounding reference region
10 which neighbors to the left of or above the current block and the luma value in the corresponding position in the reference picture specified by a motion vector, and calculates a luminance correction parameter. For example, it is assumed that the luma pixel value of a given pixel in the surrounding reference region in the current picture is p_0 , and that the luma pixel value of the pixel
15 corresponding to the given pixel in the surrounding reference region in the reference picture is p_1 . Inter predictor 126 calculates coefficients A and B for optimizing $A \times p_1 + B = p_0$ as the luminance correction parameter for a plurality of pixels in the surrounding reference region.

[0278]

Next, inter predictor 126 performs a luminance correction process using
20 the luminance correction parameter for the reference image in the reference picture specified by the motion vector, to generate a prediction image for the current block. For example, it is assumed that the luma pixel value in the reference image is p_2 , and that the luminance-corrected luma pixel value of the
25 prediction image is p_3 . Inter predictor 126 generates the prediction image after being subjected to the luminance correction process by calculating $A \times p_2 + B = p_3$ for each of the pixels in the reference image.

[0279]

It is to be noted that the shape of the surrounding reference region illustrated in FIG. 39 is one example; a different shape other than the shape of the surrounding reference region may be used. In addition, part of the surrounding reference region illustrated in FIG. 39 may be used. For example, a region having a determined number of pixels extracted from each of an upper neighboring pixel and a left neighboring pixel may be used as a surrounding reference region. The determined number of pixels may be predetermined.

10 [0280]

In addition, the surrounding reference region is not limited to a region which neighbors the current block, and may be a region which does not neighbor the current block. In the example illustrated in FIG. 39, the surrounding reference region in the reference picture is a region specified by a motion vector in a current picture, from a surrounding reference region in the current picture. However, a region specified by another motion vector is also possible. For example, the other motion vector may be a motion vector in a surrounding reference region in the current picture.

15

[0281]

Although operations performed by encoder 100 have been described here, it is to be noted that decoder 200 typically performs similar operations.

20

[0282]

It is to be noted that the LIC process may be applied not only to the luma but also to chroma. At this time, a correction parameter may be derived individually for each of Y, Cb, and Cr, or a common correction parameter may be used for any of Y, Cb, and Cr.

25

[0283]

In addition, the LIC process may be applied in units of a sub-block. For example, a correction parameter may be derived using a surrounding reference region in a current sub-block and a surrounding reference region in a reference sub-block in a reference picture specified by an MV of the current sub-block.

[Prediction Controller]

[0284]

Inter predictor 128 selects one of an intra prediction signal (a signal output from intra predictor 124) and an inter prediction signal (a signal output from inter predictor 126), and outputs the selected signal to subtractor 104 and adder 116 as a prediction signal.

[0285]

As illustrated in FIG. 1, in various kinds of encoder examples, prediction controller 128 may output a prediction parameter which is input to entropy encoder 110. Entropy encoder 110 may generate an encoded bitstream (or a sequence), based on the prediction parameter which is input from prediction controller 128 and quantized coefficients which are input from quantizer 108. The prediction parameter may be used in a decoder. The decoder may receive and decode the encoded bitstream, and perform the same processes as the prediction processes performed by intra predictor 124, inter predictor 126, and prediction controller 128. The prediction parameter may include (i) a selection prediction signal (for example, a motion vector, a prediction type, or a prediction mode used by intra predictor 124 or inter predictor 126), or (ii) an optional index, a flag, or a value which is based on a prediction process performed in each of intra predictor 124, inter predictor 126, and prediction controller 128, or which indicates the prediction process.

[Mounting Example of Encoder]

[0286]

FIG. 40 is a block diagram illustrating a mounting example of encoder 100. Encoder 100 includes processor a1 and memory a2. For example, the plurality of constituent elements of encoder 100 illustrated in FIG. 1 are
5 mounted on processor a1 and memory a2 illustrated in FIG. 40.

[0287]

Processor a1 is circuitry which performs information processing and is accessible to memory a2. For example, processor a1 is dedicated or general electronic circuitry which encodes a video. Processor a1 may be a processor
10 such as a CPU. In addition, processor a1 may be an aggregate of a plurality of electronic circuits. In addition, for example, processor a1 may take the roles of two or more constituent elements out of the plurality of constituent elements of encoder 100 illustrated in FIG. 1, etc.

[0288]

15 Memory a2 is dedicated or general memory for storing information that is used by processor a1 to encode a video. Memory a2 may be electronic circuitry, and may be connected to processor a1. In addition, memory a2 may be included in processor a1. In addition, memory a2 may be an aggregate of a plurality of electronic circuits. In addition, memory a2 may be a magnetic
20 disc, an optical disc, or the like, or may be represented as a storage, a recording medium, or the like. In addition, memory a2 may be non-volatile memory, or volatile memory.

[0289]

For example, memory a2 may store a video to be encoded or a bitstream
25 corresponding to an encoded video. In addition, memory a2 may store a program for causing processor a1 to encode a video.

[0290]

In addition, for example, memory a2 may take the roles of two or more constituent elements for storing information out of the plurality of constituent elements of encoder 100 illustrated in FIG. 1, etc. For example, memory a2 may take the roles of block memory 118 and frame memory 122 illustrated in
5 FIG. 1. More specifically, memory a2 may store a reconstructed block, a reconstructed picture, etc.

[0291]

It is to be noted that, in encoder 100, all of the plurality of constituent elements indicated in FIG. 1, etc. may not be implemented, and all the
10 processes described above may not be performed. Part of the constituent elements indicated in FIG. 1, etc. may be included in another device, or part of the processes described above may be performed by another device.

[Decoder]

[0292]

15 Next, a decoder capable of decoding an encoded signal (encoded bitstream) output, for example, from encoder 100 described above will be described. FIG. 41 is a block diagram illustrating a functional configuration of decoder 200 according to an embodiment. Decoder 200 is a video decoder which decodes a video in units of a block.

20 [0293]

As illustrated in FIG. 41, decoder 200 includes entropy decoder 202, inverse quantizer 204, inverse transformer 206, adder 208, block memory 210, loop filter 212, frame memory 214, intra predictor 216, inter predictor 218, and prediction controller 220.

25 [0294]

Decoder 200 is implemented as, for example, a generic processor and memory. In this case, when a software program stored in the memory is

executed by the processor, the processor functions as entropy decoder 202, inverse quantizer 204, inverse transformer 206, adder 208, loop filter 212, intra predictor 216, inter predictor 218, and prediction controller 220. Alternatively, decoder 200 may be implemented as one or more dedicated
5 electronic circuits corresponding to entropy decoder 202, inverse quantizer 204, inverse transformer 206, adder 208, loop filter 212, intra predictor 216, inter predictor 218, and prediction controller 220.

[0295]

Hereinafter, an overall flow of processes performed by decoder 200 is
10 described, and then each of constituent elements included in decoder 200 will be described.

[Overall Flow of Decoding Process]

[0296]

FIG. 42 is a flow chart illustrating one example of an overall decoding
15 process performed by decoder 200.

[0297]

First, entropy decoder 202 of decoder 200 identifies a splitting pattern of a block having a fixed size (for example, 128×128 pixels) (Step Sp_1). This splitting pattern is a splitting pattern selected by encoder 100. Decoder 200
20 then performs processes of Step Sp_2 to Sp_6 for each of a plurality of blocks of the splitting pattern.

[0298]

In other words, entropy decoder 202 decodes (specifically, entropy-decodes) encoded quantized coefficients and a prediction parameter of
25 a current block to be decoded (also referred to as a current block) (Step Sp_2).

[0299]

Next, inverse quantizer 204 performs inverse quantization of the

plurality of quantized coefficients and inverse transformer 206 performs inverse transform of the result, to restore a plurality of prediction residuals (that is, a difference block) (Step Sp_3).

[0300]

5 Next, the prediction processor including all or part of intra predictor 216, inter predictor 218, and prediction controller 220 generates a prediction signal (also referred to as a prediction block) of the current block (Step Sp_4).

[0301]

 Next, adder 208 adds the prediction block to the difference block to
10 generate a reconstructed image (also referred to as a decoded image block) of the current block (Step Sp_5).

[0302]

 When the reconstructed image is generated, loop filter 212 performs filtering of the reconstructed image (Step Sp_6).

15 [0303]

 Decoder 200 then determines whether decoding of the entire picture has been finished (Step Sp_7). When determining that the decoding has not yet been finished (No in Step Sp_7), decoder 200 repeatedly executes the processes starting with Step Sp_1.

20 [0304]

 As illustrated, the processes of Steps Sp_1 to Sp_7 are performed sequentially by decoder 200. Alternatively, two or more of the processes may be performed in parallel, the processing order of the two or more of the processes may be modified, etc.

25 [Entropy Decoder]

[0305]

 Entropy decoder 202 entropy decodes an encoded bitstream. More

specifically, for example, entropy decoder 202 arithmetic decodes an encoded bitstream into a binary signal. Entropy decoder 202 then debinarizes the binary signal. With this, entropy decoder 202 outputs quantized coefficients of each block to inverse quantizer 204. Entropy decoder 202 may output a prediction parameter included in an encoded bitstream (see FIG. 1) to intra predictor 216, inter predictor 218, and prediction controller 220. Intra predictor 216, inter predictor 218, and prediction controller 220 in an embodiment are capable of executing the same prediction processes as those performed by intra predictor 124, inter predictor 126, and prediction controller 128 at the encoder side.

[Inverse Quantizer]

[0306]

Inverse quantizer 204 inverse quantizes quantized coefficients of a block to be decoded (hereinafter referred to as a current block) which are inputs from entropy decoder 202. More specifically, inverse quantizer 204 inverse quantizes quantized coefficients of the current block, based on quantization parameters corresponding to the quantized coefficients. Inverse quantizer 204 then outputs the inverse quantized transform coefficients of the current block to inverse transformer 206.

[Inverse Transformer]

[0307]

Inverse transformer 206 restores prediction errors by inverse transforming the transform coefficients which are inputs from inverse quantizer 204.

[0308]

For example, when information parsed from an encoded bitstream indicates that EMT or AMT is to be applied (for example, when an AMT flag is

true), inverse transformer 206 inverse transforms the transform coefficients of the current block based on information indicating the parsed transform type.

[0309]

Moreover, for example, when information parsed from an encoded
5 bitstream indicates that NSST is to be applied, inverse transformer 206 applies a secondary inverse transform to the transform coefficients.

[Adder]

[0310]

Adder 208 reconstructs the current block by adding prediction errors
10 which are inputs from inverse transformer 206 and prediction samples which are inputs from prediction controller 220. Adder 208 then outputs the reconstructed block to block memory 210 and loop filter 212.

[Block Memory]

[0311]

15 Block memory 210 is storage for storing blocks in a picture to be decoded (hereinafter referred to as a current picture) and to be referred to in intra prediction. More specifically, block memory 210 stores reconstructed blocks output from adder 208.

[Loop Filter]

20 [0312]

Loop filter 212 applies a loop filter to blocks reconstructed by adder 208, and outputs the filtered reconstructed blocks to frame memory 214, display device, etc.

[0313]

25 When information indicating ON or OFF of an ALF parsed from an encoded bitstream indicates that an ALF is ON, one filter from among a plurality of filters is selected based on direction and activity of local gradients,

and the selected filter is applied to the reconstructed block.

[Frame Memory]

[0314]

Frame memory 214 is, for example, storage for storing reference
5 pictures for use in inter prediction, and is also referred to as a frame buffer.
More specifically, frame memory 214 stores a reconstructed block filtered by
loop filter 212.

[Prediction Processor (Intra Predictor, Inter Predictor, Prediction
Controller)]

10 [0315]

FIG. 43 is a flow chart illustrating one example of a process performed
by a prediction processor of decoder 200. It is to be noted that the prediction
processor includes all or part of the following constituent elements: intra
predictor 216; inter predictor 218; and prediction controller 220.

15 [0316]

The prediction processor generates a prediction image of a current block
(Step Sq_1). This prediction image is also referred to as a prediction signal or
a prediction block. It is to be noted that the prediction signal is, for example,
an intra prediction signal or an inter prediction signal. Specifically, the
20 prediction processor generates the prediction image of the current block using a
reconstructed image which has been already obtained through generation of a
prediction block, generation of a difference block, generation of a coefficient
block, restoring of a difference block, and generation of a decoded image block.

[0317]

25 The reconstructed image may be, for example, an image in a reference
picture, or an image of a decoded block in a current picture which is the picture
including the current block. The decoded block in the current picture is, for

example, a neighboring block of the current block.

[0318]

FIG. 44 is a flow chart illustrating another example of a process performed by the prediction processor of decoder 200.

5 [0319]

The prediction processor determines either a method or a mode for generating a prediction image (Step Sr_1). For example, the method or mode may be determined based on, for example, a prediction parameter, etc.

[0320]

10 When determining a first method as a mode for generating a prediction image, the prediction processor generates a prediction image according to the first method (Step Sr_2a). When determining a second method as a mode for generating a prediction image, the prediction processor generates a prediction image according to the second method (Step Sr_2b). When determining a
15 third method as a mode for generating a prediction image, the prediction processor generates a prediction image according to the third method (Step Sr_2c).

[0321]

20 The first method, the second method, and the third method may be mutually different methods for generating a prediction image. Each of the first to third methods may be an inter prediction method, an intra prediction method, or another prediction method. The above-described reconstructed image may be used in these prediction methods.

[Intra Predictor]

25 [0322]

Intra predictor 216 generates a prediction signal (intra prediction signal) by performing intra prediction by referring to a block or blocks in the

current picture stored in block memory 210, based on the intra prediction mode
parsed from the encoded bitstream. More specifically, intra predictor 216
generates an intra prediction signal by performing intra prediction by referring
to samples (for example, luma and/or chroma values) of a block or blocks
5 neighboring the current block, and then outputs the intra prediction signal to
prediction controller 220.

[0323]

It is to be noted that when an intra prediction mode in which a luma
block is referred to in intra prediction of a chroma block is selected, intra
10 predictor 216 may predict the chroma component of the current block based on
the luma component of the current block.

[0324]

Moreover, when information parsed from an encoded bitstream
indicates that PDPC is to be applied, intra predictor 216 corrects
15 intra-predicted pixel values based on horizontal/vertical reference pixel
gradients.

[Inter Predictor]

[0325]

Inter predictor 218 predicts the current block by referring to a reference
20 picture stored in frame memory 214. Inter prediction is performed in units of
a current block or a sub-block (for example, a 4×4 block) in the current block.
For example, inter predictor 218 generates an inter prediction signal of the
current block or the sub-block by performing motion compensation by using
motion information (for example, a motion vector) parsed from an encoded
25 bitstream (for example, a prediction parameter output from entropy decoder
202), and outputs the inter prediction signal to prediction controller 220.

[0326]

It is to be noted that when the information parsed from the encoded
bitstream indicates that the OBMC mode is to be applied, inter predictor 218
generates the inter prediction signal using motion information of a neighboring
block in addition to motion information of the current block obtained from
5 motion estimation.
[0327]

Moreover, when the information parsed from the encoded bitstream
indicates that the FRUC mode is to be applied, inter predictor 218 derives
motion information by performing motion estimation in accordance with the
10 pattern matching method (bilateral matching or template matching) parsed
from the encoded bitstream. Inter predictor 218 then performs motion
compensation (prediction) using the derived motion information.
[0328]

Moreover, when the BIO mode is to be applied, inter predictor 218
15 derives a motion vector based on a model assuming uniform linear motion.
Moreover, when the information parsed from the encoded bitstream indicates
that the affine motion compensation prediction mode is to be applied, inter
predictor 218 derives a motion vector of each sub-block based on motion vectors
of neighboring blocks.

20 [MV Derivation > Normal Inter Mode]
[0329]

When information parsed from an encoded bitstream indicates that the
normal inter mode is to be applied, inter predictor 218 derives an MV based on
the information parsed from the encoded bitstream and performs motion
25 compensation (prediction) using the MV.
[0330]

FIG. 45 is a flow chart illustrating an example of inter prediction in

normal inter mode in decoder 200.

[0331]

Inter predictor 218 of decoder 200 performs motion compensation for each block. Inter predictor 218 obtains a plurality of MV candidates for a
5 current block based on information such as MVs of a plurality of decoded blocks temporally or spatially surrounding the current block (Step Ss_1). In other words, inter predictor 218 generates an MV candidate list.

[0332]

Next, inter predictor 218 extracts N (an integer of 2 or larger) MV
10 candidates from the plurality of MV candidates obtained in Step Ss_1, as motion vector predictor candidates (also referred to as MV predictor candidates) according to a determined priority order (Step Ss_2). It is to be noted that the priority order may be determined in advance for each of the N MV predictor candidates.

15 [0333]

Next, inter predictor 218 decodes motion vector predictor selection information from an input stream (that is, an encoded bitstream), and selects, one MV predictor candidate from the N MV predictor candidates using the
20 decoded motion vector predictor selection information, as a motion vector (also referred to as an MV predictor) of the current block (Step Ss_3).

[0334]

Next, inter predictor 218 decodes an MV difference from the input stream, and derives an MV for a current block by adding a difference value which is the decoded MV difference and a selected motion vector predictor (Step
25 Ss_4).

[0335]

Lastly, inter predictor 218 generates a prediction image for the current

block by performing motion compensation of the current block using the derived MV and the decoded reference picture (Step Ss_5).

[Prediction Controller]

[0336]

5 Prediction controller 220 selects either the intra prediction signal or the inter prediction signal, and outputs the selected prediction signal to adder 208. As a whole, the configurations, functions, and processes of prediction controller 220, intra predictor 216, and inter predictor 218 at the decoder side may correspond to the configurations, functions, and processes of prediction
10 controller 128, intra predictor 124, and inter predictor 126 at the encoder side.

[Mounting Example of Decoder]

[0337]

FIG. 46 is a block diagram illustrating a mounting example of decoder 200. Decoder 200 includes processor b1 and memory b2. For example, the
15 plurality of constituent elements of decoder 200 illustrated in FIG. 41 are mounted on processor b1 and memory b2 illustrated in FIG. 46.

[0338]

Processor b1 is circuitry which performs information processing and is accessible to memory b2. For example, processor b1 is dedicated or general
20 electronic circuitry which decodes a video (that is, an encoded bitstream). Processor b1 may be a processor such as a CPU. In addition, processor b1 may be an aggregate of a plurality of electronic circuits. In addition, for example, processor b1 may take the roles of two or more constituent elements out of the plurality of constituent elements of decoder 200 illustrated in FIG. 41, etc.

25 [0339]

Memory b2 is dedicated or general memory for storing information that is used by processor b1 to decode an encoded bitstream. Memory b2 may be

electronic circuitry, and may be connected to processor b1. In addition, memory b2 may be included in processor b1. In addition, memory b2 may be an aggregate of a plurality of electronic circuits. In addition, memory b2 may be a magnetic disc, an optical disc, or the like, or may be represented as a storage, a recording medium, or the like. In addition, memory b2 may be a non-volatile memory, or a volatile memory.

[0340]

For example, memory b2 may store a video or a bitstream. In addition, memory b2 may store a program for causing processor b1 to decode an encoded bitstream.

[0341]

In addition, for example, memory b2 may take the roles of two or more constituent elements for storing information out of the plurality of constituent elements of decoder 200 illustrated in FIG. 41, etc. Specifically, memory b2 may take the roles of block memory 210 and frame memory 214 illustrated in FIG. 41. More specifically, memory b2 may store a reconstructed block, a reconstructed picture, etc.

[0342]

It is to be noted that, in decoder 200, all of the plurality of constituent elements illustrated in FIG. 41, etc. may not be implemented, and all the processes described above may not be performed. Part of the constituent elements indicated in FIG. 41, etc. may be included in another device, or part of the processes described above may be performed by another device.

[Definitions of Terms]

[0343]

The respective terms may be defined as indicated below as examples.

[0344]

A picture is an array of luma samples in monochrome format or an array of luma samples and two corresponding arrays of chroma samples in 4:2:0, 4:2:2, and 4:4:4 color format. A picture may be either a frame or a field.

[0345]

5 A frame is the composition of a top field and a bottom field, where sample rows 0, 2, 4, ... originate from the top field and sample rows 1, 3, 5, ... originate from the bottom field.

[0346]

10 A slice is an integer number of coding tree units contained in one independent slice segment and all subsequent dependent slice segments (if any) that precede the next independent slice segment (if any) within the same access unit.

[0347]

15 A tile is a rectangular region of coding tree blocks within a particular tile column and a particular tile row in a picture. A tile may be a rectangular region of the frame that is intended to be able to be decoded and encoded independently, although loop-filtering across tile edges may still be applied.

[0348]

20 A block is an $M \times N$ (M -column by N -row) array of samples, or an $M \times N$ array of transform coefficients. A block may be a square or rectangular region of pixels including one Luma and two Chroma matrices.

[0349]

25 A coding tree unit (CTU) may be a coding tree block of luma samples of a picture that has three sample arrays, or two corresponding coding tree blocks of chroma samples. Alternatively, a CTU may be a coding tree block of samples of one of a monochrome picture and a picture that is coded using three separate color planes and syntax structures used to code the samples.

[0350]

A super block may be a square block of 64×64 pixels that consists of either 1 or 2 mode info blocks or is recursively partitioned into four 32×32 blocks, which themselves can be further partitioned.

5 [0351]

[Intra prediction using Matrix weighted Intra Prediction]

As described above, the prediction modes for generating the prediction signal are classified into: the intra prediction mode in which an encoded region in a picture to which the current block belongs is referred to; and the inter
10 prediction mode in which a region in an encoded picture different from a picture to which the current block belongs is referred to.

[0352]

Furthermore, the intra prediction is divided into Matrix weighted Intra Prediction (MIP) and intra prediction other than the MIP (hereinafter, also
15 referred to as normal intra prediction).

[0353]

The intra prediction other than the MIP, i.e. the normal intra prediction, is intra prediction including planar prediction, DC prediction, directional prediction, or the like.

20 [0354]

The MIP is intra prediction different from the normal intra prediction. When the MIP is used, the prediction image is generated by performing matrix calculation on a pixel sequence obtained from the pixel values of surrounding pixels of the current block. It is to be noted that the MIP may have multiple
25 prediction modes. The MIP is also referred to as Affine Linear Weighted Intra Prediction (ALWIP).

[0355]

According to the reference such as JVET-N0217, in the MIP, the prediction image is generated as follow: calculation based on matrix calculation and offset addition is performed on an input pixel sequence obtained by averaging the surrounding pixels of the current block for every N pixels, to
5 generate the prediction values in pixel positions where pixels in the block are decimated into $S \times T$ pixels (where S and T are each an integer less than the number of pixels of the block side). The pixel values in the remaining pixel positions, i.e. the removed pixel positions, are then interpolated using the generated prediction values in the $S \times T$ pixel positions, the pixel values of the
10 surrounding pixels, and the like. Here, the MIP may have as many prediction modes as the number of pairs of a matrix calculation and an offset for use in the calculation. It is to be noted that the number of pixels to be averaged and the decimation in the generating of the prediction values may be switched according to the size or shape of the block. For example, in a small block such
15 as 4×4 , the prediction values of all pixels may be generated without performing the decimation.

[0356]

The method of predicting pixel values (a prediction image) when the MIP is used will be described below with reference to FIG. 47.

20 [0357]

FIG. 47 is a diagram for illustrating a method of predicting a pixel value using the MIP. FIG. 47 shows an example in which the pixel values in the $W \times H$ -sized current block are predicted using the MIP.

[0358]

25 More specifically, first, the surrounding pixels of the current block are obtained as an input. In the example of FIG. 47, H surrounding pixels constituting the left-neighboring pixel sequence of the $W \times H$ -sized current

block and W surrounding pixels constituting the upper-neighboring pixel sequence of the $W \times H$ -sized current block are used as the input.

[0359]

Next, an input pixel sequence is obtained by averaging the obtained
5 surrounding pixels of the current block. In the example shown in FIG. 47, the input pixel sequence is obtained by averaging the surrounding pixels constituting each of the left-neighboring and upper-neighboring pixel sequences of the current block, based on the size and the shape of the current block.

10 [0360]

Next, prediction values in decimated pixel positions are generated by performing, on the obtained input pixel sequence, the calculation based on matrix calculation and offset addition. In the example shown in FIG. 47, the gray-scale pixel positions are shown as the decimated pixel positions.

15 [0361]

The pixel values in removed pixel positions are then generated by performing interpolation using the generated prediction values in the decimated pixel positions, the generated pixel values of the surrounding pixels, and the like. FIG. 47 shows the example in which the prediction image is
20 generated including pixel values in the removed pixel positions generated by performing linear interpolation using the generated prediction values in the decimated pixel positions denoted by gray-scale colors, the generated pixel values of the surrounding pixels denoted by gray-scale colors, and the like.

[0362]

25 It is to be noted that the method of predicting the pixel values of the prediction image is one example. The pixel values may be predicted using a method different from the above-mentioned method. For example, the

prediction image may be generated using an input pixel sequence obtained from calculation other than the averaging of the surrounding pixels of the current block, or the prediction image may be generated by directly applying the calculation based on matrix calculation and offset addition to the pixel values of the surrounding pixels. Furthermore, when these variations are applied in the MIP, the number of prediction modes may be increased by an amount equal to the number of applied variations.

[0363]

Moreover, the intra prediction may be switched between the normal intra prediction and the MIP using flag information for each CU, or the like. For example, when the flag information indicating that the MIP is valid is set, the MIP may be selected, and otherwise, the normal intra prediction may be selected.

[0364]

Moreover, in the MIP, multiple pairs of a matrix calculation equation and an offset addition value may be prepared as prediction modes. In this case, it is possible to select which of the pairs (prediction modes) is used.

[0365]

Furthermore, the prediction mode of the MIP to be applied to the current block may be specified using an index number, for example. The index number may be encoded using a most probable mode (MPM) list for the MIP. It is to be noted that the normal intra prediction and the MIP may be integrated with each other. For example, a mode of the normal intra prediction may be expanded to represent a mode of the MIP. In this case, whether the MIP has selected may be determined based on the mode of the intra prediction.

[0366]

The normal intra prediction and the MIP may use a different MPM list. In this case, a value indicating any of candidates in each MPM list may be encoded. Moreover, a common MVP list including the normal intra prediction and the MIP as candidates may be used to determine whether the intra
5 prediction is the normal intra prediction or the MIP, based on which of the candidates is used.

[0367]

[Aspect 1]

When secondary transform is performed on primary transform
10 coefficients obtained by performing primary transform on prediction errors, transformer 106 firstly selects a transform set to be used, from among multiple transform sets, and next determines a transform matrix (a basis matrix) to be used, from the selected transform set. Subsequently, transformer 106 performs the secondary transform on the primary transform coefficients using
15 the determined transform matrix. Hereinafter, the transform set selected when NSST (Non-Separable Secondary Transform) is performed as the secondary transform is also referred to as a NSST transform set. It is to be noted that LFNST (Low Frequency Non-Separable Transform) in which the NSST is applied to only low frequency components of the primary transform
20 coefficients may be performed as the secondary transform.

[0368]

The following describes, as Aspect 1, the first example of a method for selecting a NSST transform set in the matrix weighted intra prediction (MIP).

[0369]

25 FIG. 48 is a flow chart illustrating one example of the NSST transform set selection process performed by transformer 106 of an encoder according to Aspect 1 of an embodiment.

[0370]

Firstly, transformer 106 determines whether the intra prediction is to be used as the prediction mode for a current block such as a CU (S10). It is to be noted that when it is determined that the current block is encoded using the inter prediction at step S10 (“No” at S10), transformer 106 selects, as the NSST transform set, a transform set predefined for each of the prediction modes of the inter prediction (S11).

[0371]

When it is determined that the intra prediction is used as the prediction mode for the current block at step S10 (“Yes” at S10), transformer 106 determines whether the current block is encoded using the matrix weighted intra prediction (MIP) included in the intra prediction (S12).

[0372]

When it is determined that the current block is encoded using the normal intra prediction at step S12 (“No” at S12), transformer 106 selects, as the NSST transform set, a transform set predefined for each of the prediction modes of the normal intra prediction, in the performing of the secondary transform (S13). With this, in the performing of the secondary transform, transformer 106 can use a different transform set between the case where the current block is encoded using the planar prediction and the case where the current block is encoded using the directional prediction. It is to be noted that when the current block is encoded using the directional prediction, transformer 106 may use, as the NSST transform set, a transform set varying depending on the prediction direction. In the normal intra prediction, a specific feature may appear in occurrence of the residual coefficients, in accordance with the prediction direction of the directional prediction. Accordingly, in the performing of the NSST secondary transform, transformer 106 can use a

transform set varying depending on the prediction direction of the directional prediction to enhance the possibility of reduction in the ROM size needed to store the NSST coefficients.

[0373]

5 On the other hand, when it is determined that the current block is encoded using the matrix weighted intra prediction (MIP) at step S12 (“Yes” at S12), transformer 106 selects a common transform set shared among prediction modes of the matrix weighted intra prediction (MIP) regardless of the prediction modes (S14), in the performing of the secondary transform. Unlike
10 the normal intra prediction, in the prediction modes of the matrix weighted intra prediction (MIP), a different feature may not appear in occurrence of the coefficient values, in accordance with the prediction mode. Accordingly, in the performing of the NSST secondary transform, performance deterioration may not occur even when transformer 106 performs the secondary transform using
15 the common transform set shared among the prediction modes, and thus it is possible to reduce the ROM size needed to store the NSST coefficients.

[0374]

 Here, in the performing of the secondary transform, transformer 106 may use, as the common transform set, a transform set identical to that of the
20 planar mode in the normal intra prediction. That is because transformer 106 may be able to select an appropriate transform set by using a transform set for use in the non-directional prediction mode in the normal intra prediction since the matrix weighted intra prediction (MIP) is non-directional prediction. Moreover, in the performing of the secondary transform, transformer 106 may
25 use, as the common transform set, a transform set identical to that of the DC mode in the normal intra prediction.

[0375]

Next, transformer 106 performs the NSST secondary transform using a transform matrix included in the transform set selected at step S11, step S13, or step S14 (S15). More specifically, transformer 106 determines a transform matrix to be used, from among transform matrices included in the transform set selected at step S11, step S13, or step S14, and performs the NSST
5 secondary transform using the determined transform matrix.

[0376]

It is to be noted that the above-mentioned selection process is merely one example. A part of the process described above may be omitted, or a
10 process or conditional branch not described above may be added. For example, at step S14, transformer 106 may select a common transform set varying depending on the block size.

[0377]

Moreover, during the matrix weighted intra prediction (MIP), the NSST
15 may be disabled. In this case, in the CU to which the matrix weighted intra prediction (MIP) is applied as the intra prediction, the syntax regarding the NSST need not be encoded. With this, it is possible to omit, for example, flag information indicating the enabled/disabled state of the NSST, index information indicating the transform matrix of the NSST, etc. Moreover,
20 when the NSST is disabled during the matrix weighted intra prediction (MIP), the flag information for each CU may be used to indicate that the NSST is disabled.

[0378]

The processing of encoder 100 has been described above as a
25 representative, but the processing of decoder 200 is also almost the same. That is because the encoder is basically in common with the decoder, and differs from the decoder only in that a necessary signal for processing is

encoded into a stream or decoded from the stream.

[0379]

[Advantages Effect of Aspect 1]

According to Aspect 1, in the performing of the secondary transform by
5 transformer 106 of encoder 100, a difference between primary transform
coefficient distributions of the prediction modes may be smaller when the
matrix weighted intra prediction (MIP) included in the intra prediction is used
than when the normal intra prediction is used.

[0380]

10 Accordingly, when the current block is encoded using the matrix
weighted intra prediction (MIP) in the performing of the NSST secondary
transform, transformer 106 of encoder 100 selects the common transform set
shared among the prediction modes. With this, it is possible to reduce the
ROM size needed to store the NSST coefficients.

15 [0381]

Likewise, in the performing of the secondary inverse transform by
inverse transformer 206 of decoder 200, a difference between quantized
coefficient distributions of the prediction modes may be smaller when the
matrix weighted intra prediction (MIP) included in the intra prediction is used
20 than when the normal intra prediction is used.

[0382]

Accordingly, when the current block is decoded using the matrix
weighted intra prediction (MIP) in the performing of the NSST secondary
inverse transform, inverse transformer 206 of decoder 200 selects the common
25 inverse transform set shared among the prediction modes. With this, it is
possible to reduce the ROM size needed to store the NSST coefficients.

[0383]

It is to be noted that when the matrix weighted intra prediction (MIP) is used in the performing of the secondary transform, transformer 106 may use the above-mentioned common transform set only for the luma signal as the transform set for the secondary transform. Likewise, when the matrix weighted intra prediction (MIP) is used in the performing of the secondary inverse transform, inverse transformer 206 may use the common inverse transform set only for the luma signal as the transform set for the secondary inverse transform.

[0384]

It is to be noted that when the matrix weighted intra prediction (MIP) is used in the performing of the secondary transform, transformer 106 may use the above-mentioned common transform set for both the luma signal and the chroma signal. Here, the transform set for use in the planar mode of the normal intra prediction may be used as the common transform set. Likewise, when the matrix weighted intra prediction (MIP) is used in the performing of the secondary inverse transform, inverse transformer 206 may use the common inverse transform set for both the luma signal and the chroma signal. Here, the inverse transform set for use in the planar mode of the normal intra prediction may be used as the common inverse transform set.

[0385]

[Aspect 2]

The following describes, as Aspect 2, the second example of the method for selecting the NSST transform set in the matrix weighted intra prediction (MIP). In the present aspect, an example in which a transform set in the matrix weighted intra prediction (MIP) is selected based on a different rule between the luma and the chroma is described. This is because options for the transform set become more flexible by using a different transform set for the

luma and the chroma, and thereby enhancing the possibility of selecting a more appropriate transform set.

[0386]

FIG. 49 is a flow chart illustrating one example of the NSST transform set selection process performed by transformer 106 of an encoder according to Aspect 2 of an embodiment.

[0387]

Firstly, it is assumed that the intra prediction is used as the prediction mode for the current block.

10 [0388]

In this case, transformer 106 determines whether the current block is encoded using the matrix weighted intra prediction (MIP) included in the intra prediction (S20).

[0389]

15 When it is determined that the current block is encoded using the normal intra prediction at step S20 (“No” at S20), transformer 106 selects, as the NSST transform set, a transform set predefined for each of prediction modes of the normal intra prediction, in the performing of the secondary transform (S21).

20 [0390]

On the other hand, when it is determined that the current block is encoded using the matrix weighted intra prediction (MIP) at step S20 (“Yes” at S20), transformer 106 further determines whether to be chroma prediction or luma prediction (S22).

25 [0391]

When it is determined to be the chroma prediction at step S22 (“Yes” at S22), transformer 106 selects, as the NSST transform set, a transform set

identical to that of the CCLM mode in the normal intra prediction, in the performing of the secondary transform (S23). Here, the CCLM is an abbreviation for Cross-Component Linear Model, and the CCLM mode is a mode in which, in the intra prediction for a chroma block, a chroma component
5 of the current block is predicted based on a luma component of the current block. In other words, in the performing of the secondary transform, transformer 106 selects, as the NSST transform set, a transform set associated with the CCLM mode for use in the chroma prediction in the normal intra prediction. This is because the encoding efficiency is more likely to be
10 improved when occurrence of the residual coefficients in the case of generating a chroma prediction image using the matrix weighted intra prediction (MIP) is similar to occurrence of the residual coefficients in the CCLM mode of the normal intra prediction.

[0392]

15 When it is determined to be the luma prediction at step S22 (“No” at S22), transformer 106 selects, as the NSST transform set, a transform set identical to that of the Planar mode in the normal intra prediction, in the performing of the secondary transform (S24).

[0393]

20 Next, transformer 106 performs the NSST secondary transform using a transform matrix included in the transform set selected at step S21, step S23, or step S24 (S25). More specifically, transformer 106 determines a transform matrix to be used, from among transform matrices included in the transform set selected at step S21, step S23, or step S24, and performs the NSST
25 secondary transform using the determined transform matrix.

[0394]

The processing of encoder 100 has been described above as a

representative, but the processing of decoder 200 is also almost the same.

[0395]

[Advantages Effect of Aspect 2]

According to Aspect 2, when the matrix weighted intra prediction (MIP)
5 is used in the performing of the secondary transform, for the luma signal,
transformer 106 may use a transform set for use in the planar mode in the
normal intra prediction, as the common transform set. On the other hand,
when the matrix weighted intra prediction (MIP) is used in the performing of
the secondary transform, for the chroma signal, transformer 106 may use a
10 transform set for use in the CCLM mode in the normal intra prediction, as the
common transform set.

[0396]

In other words, in the performing of the secondary transform, for the
chroma signal, transformer 106 may select, as the NSST transform set, a
15 transform set associated with the CCLM mode for use in the chroma prediction
in the normal intra prediction. With this, it is possible to improve the
encoding efficiency when occurrence of the residual coefficients in the case of
generating a chroma prediction image using the matrix weighted intra
prediction (MIP) is similar to occurrence of the residual coefficients in the
20 CCLM mode of the normal intra prediction.

[0397]

It is to be noted that the advantageous effect of the processing of inverse
transformer 206 of decoder 200 is also almost the same, and thus its description
is omitted here.

25 [0398]

(Variations)

The following describes a variation of the processing of transformer 106

of encoder 100 as a representative, but the processing of inverse transformer 206 of decoder 200 is also almost the same.

[0399]

In other words, when the matrix weighted intra prediction (MIP) is
5 used in the performing of the secondary transform, transformer 106 may use,
as the NSST transform set, a transform set different from the transform sets
for the normal intra prediction. With this, options for the transform set to be
selected when transformer 106 performs the secondary transform become more
flexible, and thus the possibility of selecting a transform set more appropriate
10 to the matrix weighted intra prediction (MIP) is enhanced.

[0400]

Moreover, transformer 106 may switch the NSST transform set in the
matrix weighted intra prediction (MIP) for use in the performing of the
secondary transform, according to the prediction mode of the matrix weighted
15 intra prediction (MIP). With this, options for the transform set to be selected
when transformer 106 performs the secondary transform become more flexible,
and thus the possibility of selecting a more appropriate transform set is
enhanced.

[0401]

20 Moreover, for example, for each of NSST transform sets, the optimized
prediction mode of the matrix weighted intra prediction (MIP) may be selected.
Accordingly, the NSST transform set for use in the normal intra prediction can
be used without any change, and thus it is possible to reduce the circuit size
and improve the encoding efficiency.

25 [0402]

[Implementation Example of Encoder]

FIG. 50 is a block diagram illustrating an implementation example of

encoder 100 according to the present embodiment. Encoder 100 includes circuitry 160 and memory 162. For example, the components of encoder 100 shown in FIG. 1 are implemented as circuitry 160 and memory 162 shown in FIG. 50.

5 [0403]

Circuitry 160 performs information processing, and is accessible to memory 162. For example, circuitry 160 is a dedicated or general-purpose electronic circuit for encoding a moving picture. Circuitry 160 may be a processor such as a CPU. Circuitry 160 also may be an assembly of electronic
10 circuits. Moreover, for example, circuitry 160 may serve as components other than components for storing information among the components in encoder 100 shown in FIG. 1, etc.

[0404]

Memory 162 is a dedicated or general-purpose memory that stores
15 information for encoding a moving picture in circuitry 160. Memory 162 may be an electronic circuit, and be connected to circuitry 160. Memory 162 also may be included in circuitry 160. Memory 162 also may be an assembly of electronic circuits. Memory 162 also may be a magnetic disk, an optical disk, etc., and be referred to as a storage, a recording medium, etc. Memory 162
20 also may be a non-volatile memory or a volatile memory.

[0405]

For example, memory 162 may store a moving picture to be encoded, or a bitstream corresponding to the encoded moving picture. Memory 162 also may store a program for encoding a moving picture in circuitry 160.

25 [0406]

Moreover, for example, memory 162 may serve as components for storing information among the components in encoder 100 shown in FIG. 1, etc.

In particular, memory 162 may serve as block memory 118 and frame memory 122 shown in FIG. 1. More specifically, memory 162 may store a reconstructed block, a reconstructed picture, etc.

[0407]

5 It is to be noted that in encoder 100, all the components shown in FIG. 1, etc., need not be implemented, or all the foregoing processes need not be performed. Some of the components shown in FIG. 1, etc., may be included in another device, or some of the foregoing processes may be performed by another device. Then, in encoder 100, some of the components shown in FIG. 1, etc.,
10 are implemented and some of the forging processes are performed, and thereby the motion compensation is effectively performed.

[0408]

Hereinafter, an operation example of encoder 100 shown in FIG. 50 will be described.

15 [0409]

FIG. 51 is a flow chart illustrating an operation example of encoder 100 shown in FIG. 50. For example, in encoding of a moving picture, encoder 100 shown in FIG. 50 performs the operation shown in FIG. 51.

[0410]

20 In particular, circuitry 160 of encoder 100 preforms, in operation, the following. In other words, circuitry 160 derives a prediction error of the image by subtracting, from the image, a prediction image of the image generated using intra prediction or inter prediction (S311). Next, circuitry 160 performs primary transform on the prediction error, and performs secondary transform
25 on a result of the primary transform (S312). At step S312, in the performing of the secondary transform, when a matrix weighted intra prediction included in the intra prediction and having a plurality of prediction modes is used, the

circuitry uses, as a transform set for the secondary transform, a common transform set shared among the plurality of prediction modes. The matrix weighted intra prediction generates the prediction image by performing matrix calculation on a pixel sequence obtained from pixel values of surrounding pixels of a current block. The transform set for the secondary transform is applied to primary transform coefficients obtained from the result of the primary transform. Next, circuitry 160 performs quantization on a result of the secondary transform (S313). Next, circuitry 160 encodes a result of the quantization as data of the image (S314).

10 [0411]

In this manner, when the matrix weighted intra prediction is used, encoder 100 can use the common transform set to reduce the ROM size needed to store the NSST coefficients. With this, in encoder 100, it is possible to reduce the circuit size and improve the encoding efficiency.

15 [0412]

[Implementation Example of Decoder]

FIG. 52 is a block diagram illustrating an implementation example of decoder 200 according to the present embodiment. Decoder 200 includes circuitry 260 and memory 262. For example, the components in decoder 200 shown in FIG. 41 are implemented as circuitry 260 and memory 262 shown in FIG. 52.

[0413]

Circuitry 260 performs information processing, and is accessible to memory 262. For example, circuitry 260 is a dedicated or general-purpose electronic circuit for decoding a moving picture. Circuitry 260 may be a processor such as a CPU. Circuitry 260 also may be an assembly of electronic circuits. Moreover, for example, circuitry 260 may serve as components other

than components for storing information among the components in decoder 200 shown in FIG. 41, etc.

[0414]

Memory 262 is a dedicated or general-purpose memory that stores
5 information for decoding a moving picture in circuitry 260. Memory 262 may be an electronic circuit, and be connected to circuitry 260. Memory 262 also may be included in circuitry 260. Memory 262 also may be an assembly of electronic circuits. Memory 262 also may be a magnetic disk, an optical disk, etc., and be referred to as a storage, a recording medium, etc. Memory 262
10 also may be a non-volatile memory or a volatile memory.

[0415]

For example, memory 262 may store a bitstream corresponding to an encoded moving picture, or a moving picture corresponding to a decoded bitstream. Memory 262 also may store a program for decoding a moving
15 picture in circuitry 260.

[0416]

Moreover, for example, memory 262 may serve as components for storing information among the components in decoder 200 shown in FIG. 41, etc. In particular, memory 262 may serve as block memory 210 and frame
20 memory 214 shown in FIG. 41. More specifically, memory 262 may store a reconstructed block, a reconstructed picture, etc.

[0417]

It is to be noted that in decoder 200, all the components shown in FIG. 41, etc., need not be implemented, or all the foregoing processes need not be
25 performed. Some of the components shown in FIG. 41, etc., may be included in another device, or some of the foregoing processes may be performed by another device. Then, in decoder 200, some of the components shown in FIG. 41, etc.,

are implemented and some of the forging processes are performed, and thereby the motion compensation is effectively performed.

[0418]

Hereinafter, an operation example of decoder 200 shown in FIG. 52 will
5 be described. FIG. 53 is a flow chart for illustrating an operation example of decoder 200 shown in FIG. 52. For example, in decoding of a moving picture, decoder 200 shown in FIG. 52 performs the operation shown in FIG. 53.

[0419]

In particular, circuitry 260 of decoder 200 preforms, in operation, the
10 following. In other words, firstly, circuitry 260 decodes data of the image (S411). Next, circuitry 260 performs inverse quantization on the data decoded at step S411 (S412). Next, circuitry 260 performs secondary inverse transform on a result of the inverse quantization, and performs primary inverse transform on a result of the secondary inverse transform (S413). At step S413,
15 in the performing of the secondary inverse transform, when a matrix weighted intra prediction included in intra prediction and having a plurality of prediction modes is used, the circuitry uses, as an inverse transform set for the secondary inverse transform, a common inverse transform set shared among the plurality of prediction modes. The matrix weighted intra prediction generates the
20 prediction image by performing matrix calculation on a pixel sequence obtained from pixel values of surrounding pixels of a current block. The inverse transform set for the secondary inverse transform is applied to quantized coefficients obtained from the result of the inverse quantization. Next, circuitry 260 derives the image by adding, to a prediction image of the image, a
25 result of the primary inverse transform as a prediction error of the image (S414).

[0420]

In this manner, when the matrix weighted intra prediction is used, decoder 200 can use the common inverse transform set to reduce the ROM size needed to store the NSST coefficients. With this, in decoder 200, it is possible to reduce the circuit size and improve the encoding efficiency.

5 [0421]

[Supplementary]

Moreover, encoder 100 and decoder 200 according to the present embodiment may be used as an image encoder and an image decoder, or may be used as a video encoder or a video decoder, respectively. Alternatively,
10 encoder 100 and decoder 200 can be each used as an inter predictor (inter frame predictor).

[0422]

In other words, encoder 100 and decoder 200 may correspond only inter predictor (inter frame predictor) 126 and inter predictor (inter frame predictor)
15 218, respectively. The other components such as transformer 106 and inverse transformer 206 may be included in another device.

[0423]

Moreover, in the present embodiment, each component may be configured by a dedicated hardware, or may be implemented by executing a
20 software program suitable for each component. Each component may be implemented by causing a program executer such as a CPU or a processor to read out and execute a software program stored on a recording medium such as a hard disk or a semiconductor memory.

[0424]

25 In particular, encoder 100 and decoder 200 may each include processing circuitry and a storage which is electrically connected to the processing circuitry and is accessible from the processing circuitry. For example, the

processing circuitry corresponds to circuitry 160 or 260, and the storage corresponds to memory 162 or 262.

[0425]

The processing circuitry includes at least one of a dedicated hardware
5 and a program executor, and performs processing using the storage.
Moreover, when the processing circuitry includes the program executor, the storage stores a software program to be executed by the program executor.

[0426]

Here, a software for implementing encoder 100, decoder 200, etc.,
10 according to the present embodiment is a program as follows.

[0427]

In other words, this program may cause a computer to execute an encoding method of encoding an image. The encoding method includes:
deriving a prediction error of the image by subtracting a prediction image of the
15 image from the image, the prediction image being generated using intra prediction or inter prediction; performing primary transform on the prediction error, and performing secondary transform on a result of the primary transform; performing quantization on a result of the secondary transform; and encoding a result of the quantization as data of the image, in which in the
20 performing of the secondary transform, when a matrix weighted intra prediction included in the intra prediction and having a plurality of prediction modes is used, a common transform set shared among the plurality of prediction modes is used as a transform set for the secondary transform, the matrix weighted intra prediction generating the prediction image by
25 performing matrix calculation on a pixel sequence obtained from pixel values of surrounding pixels of a current block, the transform set for the secondary

transform being applied to primary transform coefficients obtained from the result of the primary transform.

[0428]

Alternatively, this program may cause a computer to execute a
5 decoding method of decoding an image. The decoding method includes:
decoding data of the image; performing inverse quantization on the data;
performing secondary inverse transform on a result of the inverse quantization,
and performing primary inverse transform on a result of the secondary inverse
transform; and deriving the image by adding, to a prediction image of the image,
10 a result of the primary inverse transform as a prediction error of the image, in
which in the performing of the secondary inverse transform, when a matrix
weighted intra prediction included in intra prediction and having a plurality of
prediction modes is used, a common inverse transform set shared among the
plurality of prediction modes is used as an inverse transform set for the
15 secondary inverse transform, the matrix weighted intra prediction generating
the prediction image by performing matrix calculation on a pixel sequence
obtained from pixel values of surrounding pixels of a current block, the inverse
transform set for the secondary inverse transform being applied to quantized
coefficients obtained from the result of the inverse quantization.

20 [0429]

Moreover, as described above, each component may be a circuit. The
circuits may be integrated into a single circuit as a whole, or may be separated
from each other. Moreover, each component may be implemented as a
general-purpose processor, or as a dedicated processor.

25 [0430]

Moreover, a process performed by a specific component may be
performed by another component. Moreover, the order of processes may be

changed, or multiple processes may be performed in parallel. Furthermore, a coding device may include encoder 100 and decoder 200.

[0431]

The ordinal numbers used in the illustration such as first and second
5 may be renumbered as needed. Moreover, the ordinal number may be newly assigned to a component, etc., or may be deleted from a component, etc.

[0432]

As described above, the aspects of encoder 100 and decoder 200 have been described based on the embodiment, but the aspects of encoder 100 and
10 decoder 200 are not limited to this embodiment. Various modifications to the embodiment that can be conceived by those skilled in the art, and forms configured by combining components in different embodiments without departing from the spirit of the present disclosure may be included in the scope of the aspects of encoder 100 and decoder 200.

15 [0433]

One or more of the aspects disclosed herein may be performed by combining at least part of the other aspects in the present disclosure. In addition, one or more of the aspects disclosed herein may be performed by combining, with other aspects, part of the processes indicated in any of the flow
20 charts according to the aspects, part of the configuration of any of the devices, part of syntaxes, etc.

[Implementations and Applications]

[0434]

As described in each of the above embodiments, each functional or
25 operational block may typically be realized as an MPU (micro processing unit) and memory, for example. Moreover, processes performed by each of the functional blocks may be realized as a program execution unit, such as a

processor which reads and executes software (a program) recorded on a recording medium such as ROM. The software may be distributed. The software may be recorded on a variety of recording media such as semiconductor memory. Note that each functional block can also be realized
5 as hardware (dedicated circuit). Various combinations of hardware and software may be employed.

[0435]

The processing described in each of the embodiments may be realized via integrated processing using a single apparatus (system), and, alternatively,
10 may be realized via decentralized processing using a plurality of apparatuses. Moreover, the processor that executes the above-described program may be a single processor or a plurality of processors. In other words, integrated processing may be performed, and, alternatively, decentralized processing may be performed.

15 [0436]

Embodiments of the present disclosure are not limited to the above exemplary embodiments; various modifications may be made to the exemplary embodiments, the results of which are also included within the scope of the embodiments of the present disclosure.

20 [0437]

Next, application examples of the moving picture encoding method (image encoding method) and the moving picture decoding method (image decoding method) described in each of the above embodiments will be described, as well as various systems that implement the application examples. Such a
25 system may be characterized as including an image encoder that employs the image encoding method, an image decoder that employs the image decoding method, or an image encoder-decoder that includes both the image encoder and

the image decoder. Other configurations of such a system may be modified on a case-by-case basis.

[Usage Examples]

[0438]

5 FIG. 54 illustrates an overall configuration of content providing system ex100 suitable for implementing a content distribution service. The area in which the communication service is provided is divided into cells of desired sizes, and base stations ex106, ex107, ex108, ex109, and ex110, which are fixed wireless stations in the illustrated example, are located in respective cells.

10 [0439]

 In content providing system ex100, devices including computer ex111, gaming device ex112, camera ex113, home appliance ex114, and smartphone ex115 are connected to internet ex101 via internet service provider ex102 or communications network ex104 and base stations ex106 through ex110.

15 Content providing system ex100 may combine and connect any combination of the above devices. In various implementations, the devices may be directly or indirectly connected together via a telephone network or near field communication, rather than via base stations ex106 through ex110. Further, streaming server ex103 may be connected to devices including computer ex111, gaming device ex112, camera ex113, home appliance ex114, and smartphone ex115 via, for example, internet ex101. Streaming server ex103 may also be connected to, for example, a terminal in a hotspot in airplane ex117 via satellite ex116.

[0440]

25 Note that instead of base stations ex106 through ex110, wireless access points or hotspots may be used. Streaming server ex103 may be connected to communications network ex104 directly instead of via internet ex101 or

internet service provider ex102, and may be connected to airplane ex117 directly instead of via satellite ex116.

[0441]

Camera ex113 is a device capable of capturing still images and video, such as a digital camera. Smartphone ex115 is a smartphone device, cellular phone, or personal handy-phone system (PHS) phone that can operate under the mobile communications system standards of the 2G, 3G, 3.9G, and 4G systems, as well as the next-generation 5G system.

[0442]

Home appliance ex114 is, for example, a refrigerator or a device included in a home fuel cell cogeneration system.

[0443]

In content providing system ex100, a terminal including an image and/or video capturing function is capable of, for example, live streaming by connecting to streaming server ex103 via, for example, base station ex106. When live streaming, a terminal (e.g., computer ex111, gaming device ex112, camera ex113, home appliance ex114, smartphone ex115, or a terminal in airplane ex117) may perform the encoding processing described in the above embodiments on still-image or video content captured by a user via the terminal, may multiplex video data obtained via the encoding and audio data obtained by encoding audio corresponding to the video, and may transmit the obtained data to streaming server ex103. In other words, the terminal functions as the image encoder according to one aspect of the present disclosure.

[0444]

Streaming server ex103 streams transmitted content data to clients that request the stream. Client examples include computer ex111, gaming

device ex112, camera ex113, home appliance ex114, smartphone ex115, and terminals inside airplane ex117, which are capable of decoding the above-described encoded data. Devices that receive the streamed data may decode and reproduce the received data. In other words, the devices may each
5 function as the image decoder, according to one aspect of the present disclosure.

[Decentralized Processing]

[0445]

Streaming server ex103 may be realized as a plurality of servers or computers between which tasks such as the processing, recording, and
10 streaming of data are divided. For example, streaming server ex103 may be realized as a content delivery network (CDN) that streams content via a network connecting multiple edge servers located throughout the world. In a CDN, an edge server physically near the client may be dynamically assigned to the client. Content is cached and streamed to the edge server to reduce load
15 times. In the event of, for example, some type of error or change in connectivity due, for example, to a spike in traffic, it is possible to stream data stably at high speeds, since it is possible to avoid affected parts of the network by, for example, dividing the processing between a plurality of edge servers, or switching the streaming duties to a different edge server and continuing
20 streaming.

[0446]

Decentralization is not limited to just the division of processing for streaming; the encoding of the captured data may be divided between and performed by the terminals, on the server side, or both. In one example, in
25 typical encoding, the processing is performed in two loops. The first loop is for detecting how complicated the image is on a frame-by-frame or scene-by-scene basis, or detecting the encoding load. The second loop is for processing that

maintains image quality and improves encoding efficiency. For example, it is possible to reduce the processing load of the terminals and improve the quality and encoding efficiency of the content by having the terminals perform the first loop of the encoding and having the server side that received the content perform the second loop of the encoding. In such a case, upon receipt of a decoding request, it is possible for the encoded data resulting from the first loop performed by one terminal to be received and reproduced on another terminal in approximately real time. This makes it possible to realize smooth, real-time streaming.

10 [0447]

In another example, camera ex113 or the like extracts a feature amount (an amount of features or characteristics) from an image, compresses data related to the feature amount as metadata, and transmits the compressed metadata to a server. For example, the server determines the significance of an object based on the feature amount and changes the quantization accuracy accordingly to perform compression suitable for the meaning (or content significance) of the image. Feature amount data is particularly effective in improving the precision and efficiency of motion vector prediction during the second compression pass performed by the server. Moreover, encoding that has a relatively low processing load, such as variable length coding (VLC), may be handled by the terminal, and encoding that has a relatively high processing load, such as context-adaptive binary arithmetic coding (CABAC), may be handled by the server.

20 [0448]

In yet another example, there are instances in which a plurality of videos of approximately the same scene are captured by a plurality of terminals in, for example, a stadium, shopping mall, or factory. In such a case, for

example, the encoding may be decentralized by dividing processing tasks between the plurality of terminals that captured the videos and, if necessary, other terminals that did not capture the videos, and the server, on a per-unit basis. The units may be, for example, groups of pictures (GOP), pictures, or
5 tiles resulting from dividing a picture. This makes it possible to reduce load times and achieve streaming that is closer to real time.

[0449]

Since the videos are of approximately the same scene, management and/or instructions may be carried out by the server so that the videos captured
10 by the terminals can be cross-referenced. Moreover, the server may receive encoded data from the terminals, change the reference relationship between items of data, or correct or replace pictures themselves, and then perform the encoding. This makes it possible to generate a stream with increased quality and efficiency for the individual items of data.

15 [0450]

Furthermore, the server may stream video data after performing transcoding to convert the encoding format of the video data. For example, the server may convert the encoding format from MPEG to VP (e.g., VP9), may convert H.264 to H.265, etc.

20 [0451]

In this way, encoding can be performed by a terminal or one or more servers. Accordingly, although the device that performs the encoding is referred to as a "server" or "terminal" in the following description, some or all of the processes performed by the server may be performed by the terminal, and
25 likewise some or all of the processes performed by the terminal may be performed by the server. This also applies to decoding processes.

[3D, Multi-angle]

[0452]

There has been an increase in usage of images or videos combined from images or videos of different scenes concurrently captured, or of the same scene captured from different angles, by a plurality of terminals such as camera
5 ex113 and/or smartphone ex115. Videos captured by the terminals may be combined based on, for example, the separately obtained relative positional relationship between the terminals, or regions in a video having matching feature points.

[0453]

10 In addition to the encoding of two-dimensional moving pictures, the server may encode a still image based on scene analysis of a moving picture, either automatically or at a point in time specified by the user, and transmit the encoded still image to a reception terminal. Furthermore, when the server can obtain the relative positional relationship between the video capturing
15 terminals, in addition to two-dimensional moving pictures, the server can generate three-dimensional geometry of a scene based on video of the same scene captured from different angles. The server may separately encode three-dimensional data generated from, for example, a point cloud and, based on a result of recognizing or tracking a person or object using three-dimensional
20 data, may select or reconstruct and generate a video to be transmitted to a reception terminal, from videos captured by a plurality of terminals.

[0454]

This allows the user to enjoy a scene by freely selecting videos corresponding to the video capturing terminals, and allows the user to enjoy the
25 content obtained by extracting a video at a selected viewpoint from three-dimensional data reconstructed from a plurality of images or videos. Furthermore, as with video, sound may be recorded from relatively different

angles, and the server may multiplex audio from a specific angle or space with the corresponding video, and transmit the multiplexed video and audio.

[0455]

In recent years, content that is a composite of the real world and a virtual world, such as virtual reality (VR) and augmented reality (AR) content, has also become popular. In the case of VR images, the server may create images from the viewpoints of both the left and right eyes, and perform encoding that tolerates reference between the two viewpoint images, such as multi-view coding (MVC), and, alternatively, may encode the images as separate streams without referencing. When the images are decoded as separate streams, the streams may be synchronized when reproduced, so as to recreate a virtual three-dimensional space in accordance with the viewpoint of the user.

[0456]

In the case of AR images, the server may superimpose virtual object information existing in a virtual space onto camera information representing a real-world space, based on a three-dimensional position or movement from the perspective of the user. The decoder may obtain or store virtual object information and three-dimensional data, generate two-dimensional images based on movement from the perspective of the user, and then generate superimposed data by seamlessly connecting the images. Alternatively, the decoder may transmit, to the server, motion from the perspective of the user in addition to a request for virtual object information. The server may generate superimposed data based on three-dimensional data stored in the server in accordance with the received motion, and encode and stream the generated superimposed data to the decoder. Note that superimposed data typically includes, in addition to RGB values, an α value indicating transparency, and

the server sets the α value for sections other than the object generated from three-dimensional data to, for example, 0, and may perform the encoding while those sections are transparent. Alternatively, the server may set the background to a determined RGB value, such as a chroma key, and generate
5 data in which areas other than the object are set as the background. The determined RGB value may be predetermined.

[0457]

Decoding of similarly streamed data may be performed by the client (e.g., the terminals), on the server side, or divided therebetween. In one
10 example, one terminal may transmit a reception request to a server, the requested content may be received and decoded by another terminal, and a decoded signal may be transmitted to a device having a display. It is possible to reproduce high image quality data by decentralizing processing and appropriately selecting content regardless of the processing ability of the
15 communications terminal itself. In yet another example, while a TV, for example, is receiving image data that is large in size, a region of a picture, such as a tile obtained by dividing the picture, may be decoded and displayed on a personal terminal or terminals of a viewer or viewers of the TV. This makes it possible for the viewers to share a big-picture view as well as for each viewer to
20 check his or her assigned area, or inspect a region in further detail up close.

[0458]

In situations in which a plurality of wireless connections are possible over near, mid, and far distances, indoors or outdoors, it may be possible to seamlessly receive content using a streaming system standard such as
25 MPEG-DASH. The user may switch between data in real time while freely selecting a decoder or display apparatus including the user's terminal, displays arranged indoors or outdoors, etc. Moreover, using, for example, information

on the position of the user, decoding can be performed while switching which terminal handles decoding and which terminal handles the displaying of content. This makes it possible to map and display information, while the user is on the move in route to a destination, on the wall of a nearby building in
5 which a device capable of displaying content is embedded, or on part of the ground. Moreover, it is also possible to switch the bit rate of the received data based on the accessibility to the encoded data on a network, such as when encoded data is cached on a server quickly accessible from the reception terminal, or when encoded data is copied to an edge server in a content delivery
10 service.

[Scalable Encoding]

[0459]

The switching of content will be described with reference to a scalable stream, illustrated in FIG. 55, which is compression coded via implementation
15 of the moving picture encoding method described in the above embodiments. The server may have a configuration in which content is switched while making use of the temporal and/or spatial scalability of a stream, which is achieved by division into and encoding of layers, as illustrated in FIG. 55. Note that there may be a plurality of individual streams that are of the same content but
20 different quality. In other words, by determining which layer to decode based on internal factors, such as the processing ability on the decoder side, and external factors, such as communication bandwidth, the decoder side can freely switch between low resolution content and high resolution content while decoding. For example, in a case in which the user wants to continue
25 watching, for example at home on a device such as a TV connected to the internet, a video that the user had been previously watching on smartphone ex115 while on the move, the device can simply decode the same stream up to a

different layer, which reduces the server side load.

[0460]

Furthermore, in addition to the configuration described above, in which scalability is achieved as a result of the pictures being encoded per layer, with the enhancement layer being above the base layer, the enhancement layer may include metadata based on, for example, statistical information on the image. The decoder side may generate high image quality content by performing super-resolution imaging on a picture in the base layer based on the metadata. Super-resolution imaging may improve the SN ratio while maintaining resolution and/or increasing resolution. Metadata includes information for identifying a linear or a non-linear filter coefficient, as used in super-resolution processing, or information identifying a parameter value in filter processing, machine learning, or a least squares method used in super-resolution processing.

[0461]

Alternatively, a configuration may be provided in which a picture is divided into, for example, tiles in accordance with, for example, the meaning of an object in the image. On the decoder side, only a partial region is decoded by selecting a tile to decode. Further, by storing an attribute of the object (person, car, ball, etc.) and a position of the object in the video (coordinates in identical images) as metadata, the decoder side can identify the position of a desired object based on the metadata and determine which tile or tiles include that object. For example, as illustrated in FIG. 56, metadata may be stored using a data storage structure different from pixel data, such as an SEI (supplemental enhancement information) message in HEVC. This metadata indicates, for example, the position, size, or color of the main object.

[0462]

Metadata may be stored in units of a plurality of pictures, such as stream, sequence, or random access units. The decoder side can obtain, for example, the time at which a specific person appears in the video, and by fitting the time information with picture unit information, can identify a picture in
5 which the object is present, and can determine the position of the object in the picture.

[Web Page Optimization]

[0463]

FIG. 57 illustrates an example of a display screen of a web page on
10 computer ex111, for example. FIG. 58 illustrates an example of a display screen of a web page on smartphone ex115, for example. As illustrated in FIG. 57 and FIG. 58, a web page may include a plurality of image links that are links to image content, and the appearance of the web page may differ depending on the device used to view the web page. When a plurality of image links are
15 viewable on the screen, until the user explicitly selects an image link, or until the image link is in the approximate center of the screen or the entire image link fits in the screen, the display apparatus (decoder) may display, as the image links, still images included in the content or I pictures; may display video such as an animated gif using a plurality of still images or I pictures; or may
20 receive only the base layer, and decode and display the video.

[0464]

When an image link is selected by the user, the display apparatus performs decoding while, for example, giving the highest priority to the base layer. Note that if there is information in the HTML code of the web page
25 indicating that the content is scalable, the display apparatus may decode up to the enhancement layer. Further, in order to guarantee real-time reproduction, before a selection is made or when the bandwidth is severely

limited, the display apparatus can reduce delay between the point in time at which the leading picture is decoded and the point in time at which the decoded picture is displayed (that is, the delay between the start of the decoding of the content to the displaying of the content) by decoding and displaying only
5 forward reference pictures (I picture, P picture, forward reference B picture). Still further, the display apparatus may purposely ignore the reference relationship between pictures, and coarsely decode all B and P pictures as forward reference pictures, and then perform normal decoding as the number of pictures received over time increases.

10 [Autonomous Driving]
[0465]

When transmitting and receiving still image or video data such as two- or three-dimensional map information for autonomous driving or assisted driving of an automobile, the reception terminal may receive, in addition to
15 image data belonging to one or more layers, information on, for example, the weather or road construction as metadata, and associate the metadata with the image data upon decoding. Note that metadata may be assigned per layer and, alternatively, may simply be multiplexed with the image data.
[0466]

20 In such a case, since the automobile, drone, airplane, etc., containing the reception terminal is mobile, the reception terminal may seamlessly receive and perform decoding while switching between base stations among base stations ex106 through ex110 by transmitting information indicating the position of the reception terminal. Moreover, in accordance with the selection
25 made by the user, the situation of the user, and/or the bandwidth of the connection, the reception terminal may dynamically select to what extent the metadata is received, or to what extent the map information, for example, is

updated.

[0467]

In content providing system ex100, the client may receive, decode, and reproduce, in real time, encoded information transmitted by the user.

5 [Streaming of Individual Content]

[0468]

In content providing system ex100, in addition to high image quality, long content distributed by a video distribution entity, unicast or multicast streaming of low image quality, and short content from an individual are also possible. Such content from individuals is likely to further increase in popularity. The server may first perform editing processing on the content before the encoding processing, in order to refine the individual content. This may be achieved using the following configuration, for example.

[0469]

15 In real time while capturing video or image content, or after the content has been captured and accumulated, the server performs recognition processing based on the raw data or encoded data, such as capture error processing, scene search processing, meaning analysis, and/or object detection processing. Then, based on the result of the recognition processing, the server - either when
20 prompted or automatically - edits the content, examples of which include: correction such as focus and/or motion blur correction; removing low-priority scenes such as scenes that are low in brightness compared to other pictures, or out of focus; object edge adjustment; and color tone adjustment. The server encodes the edited data based on the result of the editing. It is known that
25 excessively long videos tend to receive fewer views. Accordingly, in order to keep the content within a specific length that scales with the length of the original video, the server may, in addition to the low-priority scenes described

above, automatically clip out scenes with low movement, based on an image processing result. Alternatively, the server may generate and encode a video digest based on a result of an analysis of the meaning of a scene.

[0470]

5 There may be instances in which individual content may include content that infringes a copyright, moral right, portrait rights, etc. Such instance may lead to an unfavorable situation for the creator, such as when content is shared beyond the scope intended by the creator. Accordingly, before encoding, the server may, for example, edit images so as to blur faces of
10 people in the periphery of the screen or blur the inside of a house, for example. Further, the server may be configured to recognize the faces of people other than a registered person in images to be encoded, and when such faces appear in an image, may apply a mosaic filter, for example, to the face of the person. Alternatively, as pre- or post-processing for encoding, the user may specify, for
15 copyright reasons, a region of an image including a person or a region of the background to be processed. The server may process the specified region by, for example, replacing the region with a different image, or blurring the region. If the region includes a person, the person may be tracked in the moving picture, and the person's head region may be replaced with another image as
20 the person moves.

[0471]

 Since there is a demand for real-time viewing of content produced by individuals, which tends to be small in data size, the decoder may first receive the base layer as the highest priority, and perform decoding and reproduction,
25 although this may differ depending on bandwidth. When the content is reproduced two or more times, such as when the decoder receives the enhancement layer during decoding and reproduction of the base layer, and

loops the reproduction, the decoder may reproduce a high image quality video including the enhancement layer. If the stream is encoded using such scalable encoding, the video may be low quality when in an unselected state or at the start of the video, but it can offer an experience in which the image quality of
5 the stream progressively increases in an intelligent manner. This is not limited to just scalable encoding; the same experience can be offered by configuring a single stream from a low quality stream reproduced for the first time and a second stream encoded using the first stream as a reference.

[Other Implementation and Application Examples]

10 [0472]

The encoding and decoding may be performed by LSI (large scale integration circuitry) ex500 (see FIG. 54), which is typically included in each terminal. LSI ex500 may be configured of a single chip or a plurality of chips. Software for encoding and decoding moving pictures may be integrated into
15 some type of a recording medium (such as a CD-ROM, a flexible disk, or a hard disk) that is readable by, for example, computer ex111, and the encoding and decoding may be performed using the software. Furthermore, when smartphone ex115 is equipped with a camera, the video data obtained by the camera may be transmitted. In this case, the video data may be coded by LSI
20 ex500 included in smartphone ex115.

[0473]

Note that LSI ex500 may be configured to download and activate an application. In such a case, the terminal first determines whether it is compatible with the scheme used to encode the content, or whether it is capable
25 of executing a specific service. When the terminal is not compatible with the encoding scheme of the content, or when the terminal is not capable of executing a specific service, the terminal may first download a codec or

application software and then obtain and reproduce the content.

[0474]

Aside from the example of content providing system ex100 that uses internet ex101, at least the moving picture encoder (image encoder) or the moving picture decoder (image decoder) described in the above embodiments may be implemented in a digital broadcasting system. The same encoding processing and decoding processing may be applied to transmit and receive broadcast radio waves superimposed with multiplexed audio and video data using, for example, a satellite, even though this is geared toward multicast, whereas unicast is easier with content providing system ex100.

[Hardware Configuration]

[0475]

FIG. 59 illustrates further details of smartphone ex115 shown in FIG. 54. FIG. 60 illustrates a configuration example of smartphone ex115. Smartphone ex115 includes antenna ex450 for transmitting and receiving radio waves to and from base station ex110, camera ex465 capable of capturing video and still images, and display ex458 that displays decoded data, such as video captured by camera ex465 and video received by antenna ex450. Smartphone ex115 further includes user interface ex466 such as a touch panel, audio output unit ex457 such as a speaker for outputting speech or other audio, audio input unit ex456 such as a microphone for audio input, memory ex467 capable of storing decoded data such as captured video or still images, recorded audio, received video or still images, and mail, as well as decoded data, and slot ex464 which is an interface for SIM ex468 for authorizing access to a network and various data. Note that external memory may be used instead of memory ex467.

[0476]

Main controller ex460, which may comprehensively control display ex458 and user interface ex466, power supply circuit ex461, user interface input controller ex462, video signal processor ex455, camera interface ex463, display controller ex459, modulator/demodulator ex452, multiplexer/demultiplexer ex453, audio signal processor ex454, slot ex464, and memory ex467 are connected via bus ex470.

[0477]

When the user turns on the power button of power supply circuit ex461, smartphone ex115 is powered on into an operable state, and each component is supplied with power from a battery pack.

[0478]

Smartphone ex115 performs processing for, for example, calling and data transmission, based on control performed by main controller ex460, which includes a CPU, ROM, and RAM. When making calls, an audio signal recorded by audio input unit ex456 is converted into a digital audio signal by audio signal processor ex454, to which spread spectrum processing is applied by modulator/demodulator ex452 and digital-analog conversion, and frequency conversion processing is applied by transmitter/receiver ex451, and the resulting signal is transmitted via antenna ex450. The received data is amplified, frequency converted, and analog-digital converted, inverse spread spectrum processed by modulator/demodulator ex452, converted into an analog audio signal by audio signal processor ex454, and then output from audio output unit ex457. In data transmission mode, text, still-image, or video data may be transmitted under control of main controller ex460 via user interface input controller ex462 based on operation of user interface ex466 of the main body, for example. Similar transmission and reception processing is performed. In data transmission mode, when sending a video, still image, or

video and audio, video signal processor ex455 compression encodes, via the moving picture encoding method described in the above embodiments, a video signal stored in memory ex467 or a video signal input from camera ex465, and transmits the encoded video data to multiplexer/demultiplexer ex453. Audio
5 signal processor ex454 encodes an audio signal recorded by audio input unit ex456 while camera ex465 is capturing a video or still image, and transmits the encoded audio data to multiplexer/demultiplexer ex453. Multiplexer/demultiplexer ex453 multiplexes the encoded video data and encoded audio data using a determined scheme, modulates and converts the
10 data using modulator/demodulator (modulator/demodulator circuit) ex452 and transmitter/receiver ex451, and transmits the result via antenna ex450. The determined scheme may be predetermined.

[0479]

When video appended in an email or a chat, or a video linked from a
15 web page, is received, for example, in order to decode the multiplexed data received via antenna ex450, multiplexer/demultiplexer ex453 demultiplexes the multiplexed data to divide the multiplexed data into a bitstream of video data and a bitstream of audio data, supplies the encoded video data to video signal processor ex455 via synchronous bus ex470, and supplies the encoded audio
20 data to audio signal processor ex454 via synchronous bus ex470. Video signal processor ex455 decodes the video signal using a moving picture decoding method corresponding to the moving picture encoding method described in the above embodiments, and video or a still image included in the linked moving picture file is displayed on display ex458 via display controller ex459. Audio
25 signal processor ex454 decodes the audio signal and outputs audio from audio output unit ex457. Since real-time streaming is becoming increasingly popular, there may be instances in which reproduction of the audio may be

socially inappropriate, depending on the user's environment. Accordingly, as an initial value, a configuration in which only video data is reproduced, i.e., the audio signal is not reproduced, may be preferable; audio may be synchronized and reproduced only when an input, such as when the user clicks video data, is received.

[0480]

Although smartphone ex115 was used in the above example, other implementations are conceivable: a transceiver terminal including both an encoder and a decoder; a transmitter terminal including only an encoder; and a receiver terminal including only a decoder. In the description of the digital broadcasting system, an example is given in which multiplexed data obtained as a result of video data being multiplexed with audio data is received or transmitted. The multiplexed data, however, may be video data multiplexed with data other than audio data, such as text data related to the video. Further, the video data itself rather than multiplexed data may be received or transmitted.

[0481]

Although main controller ex460 including a CPU is described as controlling the encoding or decoding processes, various terminals often include GPUs. Accordingly, a configuration is acceptable in which a large area is processed at once by making use of the performance ability of the GPU via memory shared by the CPU and GPU, or memory including an address that is managed so as to allow common usage by the CPU and GPU. This makes it possible to shorten encoding time, maintain the real-time nature of the stream, and reduce delay. In particular, processing relating to motion estimation, deblocking filtering, sample adaptive offset (SAO), and transformation/quantization can be effectively carried out by the GPU instead

of the CPU in units of pictures, for example, all at once.

INDUSTRIAL APPLICABILITY

[0482]

The present disclosure is applicable to a television receiver, a digital
5 video recorder, a car navigation, a mobile phone, a digital camera, a digital
video camera, a teleconference system, an electronic mirror, etc.

REFERENCE MARKS IN THE DRAWINGS

[0483]

	100	encoder
10	102	splitter
	104	subtractor
	106	transformer
	108	quantizer
	110	entropy encoder
15	112, 204	inverse quantizer
	114, 206	inverse transformer
	116, 208	adder
	118, 210	block memory
	120, 212	loop filter
20	122, 214	frame memory
	124, 216	intra predictor
	126, 218	inter predictor
	128, 220	prediction controller
	200	decoder
25	202	entropy decoder
	1201	boundary determiner
	1202, 1204, 1206	switch

	1203	filter determiner
	1205	filtering executor
	1207	filtering characteristic determiner
	1208	processing determiner
5	a1, b1	processor
	a2, b2	memory

CLAIMS

1. An encoder that encodes an image, the encoder comprising:
circuitry; and
5 memory coupled to the circuitry, wherein
in operation, the circuitry:
derives a prediction error of the image by subtracting a
prediction image of the image from the image, the prediction image being
generated using intra prediction or inter prediction;
10 performs primary transform on the prediction error, and
performs secondary transform on a result of the primary transform;
performs quantization on a result of the secondary transform;
and
encodes a result of the quantization as data of the image, and
15 in the performing of the secondary transform,
when a matrix weighted intra prediction included in the intra
prediction and having a plurality of prediction modes is used, the circuitry uses,
as a transform set for the secondary transform, a common transform set shared
among the plurality of prediction modes, the matrix weighted intra prediction
20 generating the prediction image by performing matrix calculation on a pixel
sequence obtained from pixel values of surrounding pixels of a current block,
the transform set for the secondary transform being applied to primary
transform coefficients obtained from the result of the primary transform.
- 25 2. The encoder according to claim 1, wherein
the common transform set is identical to a transform set for use in a
planar mode in the intra prediction other than the matrix weighted intra

prediction.

3. The encoder according to claim 1 or 2, wherein
in the performing of the secondary transform,
5 when the prediction image is generated using the matrix weighted intra
prediction only for a luma signal, the circuitry uses, as the transform set for the
secondary transform, the common transform set only for the luma signal.

4. The encoder according to claim 1 or 2, wherein
10 in the performing of the secondary transform,
for both a luma signal and a chroma signal, the circuitry uses, as the
common transform set, a transform set for use in a planar mode.

5. The encoder according to any one of claims 1 to 3, wherein
15 in the performing of the secondary transform:
for a luma signal, the circuitry uses, as the common transform
set, a transform set for use in a planar mode in the intra prediction other than
the matrix weighted intra prediction; and
for a chroma signal, the circuitry uses, as the common
20 transform set, a transform set for use in a CCLM mode in the intra prediction
other than the matrix weighted intra prediction.

6. A decoder that decodes an image, the decoder comprising:
circuitry; and
25 memory coupled to the circuitry, wherein
in operation, the circuitry:
decodes data of the image;

performs inverse quantization on the data;
performs secondary inverse transform on a result of the inverse
quantization, and performs primary inverse transform on a result of the
secondary inverse transform; and
5 derives the image by adding, to a prediction image of the image,
a result of the primary inverse transform as a prediction error of the image, and
in the performing of the secondary inverse transform,
when a matrix weighted intra prediction included in intra prediction
and having a plurality of prediction modes is used, the circuitry uses, as an
10 inverse transform set for the secondary inverse transform, a common inverse
transform set shared among the plurality of prediction modes, the matrix
weighted intra prediction generating the prediction image by performing
matrix calculation on a pixel sequence obtained from pixel values of
surrounding pixels of a current block, the inverse transform set for the
15 secondary inverse transform being applied to quantized coefficients obtained
from the result of the inverse quantization.

7. The decoder according to claim 6, wherein
the common inverse transform set is identical to an inverse transform
20 set for use in a planar mode in the intra prediction other than the matrix
weighted intra prediction.

8. The decoder according to claim 6 or 7, wherein
in the performing of the secondary inverse transform,
25 when the prediction image is generated using the matrix weighted intra
prediction only for a luma signal, the circuitry uses, as the inverse transform
set for the secondary inverse transform, the common inverse transform set only

for the luma signal.

9. The decoder according to claim 6 or 7, wherein
in the performing of the secondary inverse transform,
5 for both a luma signal and a chroma signal, the circuitry uses, as the
common inverse transform set, an inverse transform set for use in a planar
mode.

10. The decoder according to any one of claims 6 to 8, wherein
10 in the performing of the secondary inverse transform:
for a luma signal, the circuitry uses, as the common inverse
transform set, an inverse transform set for use in a planar mode in the intra
prediction other than the matrix weighted intra prediction; and
for a chroma signal, the circuitry uses, as the common inverse
15 transform set, an inverse transform set for use in a CCLM mode in the intra
prediction other than the matrix weighted intra prediction.

11. An encoding method of encoding an image, the encoding method
comprising:
20 deriving a prediction error of the image by subtracting a prediction
image of the image from the image, the prediction image being generated using
intra prediction or inter prediction;
performing primary transform on the prediction error, and performing
secondary transform on a result of the primary transform;
25 performing quantization on a result of the secondary transform; and
encoding a result of the quantization as data of the image, wherein
in the performing of the secondary transform,

when a matrix weighted intra prediction included in the intra prediction and having a plurality of prediction modes is used, a common transform set shared among the plurality of prediction modes is used as a transform set for the secondary transform, the matrix weighted intra prediction
5 generating the prediction image by performing matrix calculation on a pixel sequence obtained from pixel values of surrounding pixels of a current block, the transform set for the secondary transform being applied to primary transform coefficients obtained from the result of the primary transform.

10 12. A decoding method of decoding an image, the decoding method comprising:

decoding data of the image;

performing inverse quantization on the data;

performing secondary inverse transform on a result of the inverse
15 quantization, and performing primary inverse transform on a result of the secondary inverse transform; and

deriving the image by adding, to a prediction image of the image, a result of the primary inverse transform as a prediction error of the image, wherein

20 in the performing of the secondary inverse transform,

when a matrix weighted intra prediction included in intra prediction and having a plurality of prediction modes is used, a common inverse transform set shared among the plurality of prediction modes is used as an inverse transform set for the secondary inverse transform, the matrix weighted intra
25 prediction generating the prediction image by performing matrix calculation on a pixel sequence obtained from pixel values of surrounding pixels of a current block, the inverse transform set for the secondary inverse transform being

applied to quantized coefficients obtained from the result of the inverse quantization.