

**Communication node suitable for receiving and/or transmitting radio
communications according to at least one first and one second communications
protocol simultaneously**

5 The present invention relates to a communication node suitable for receiving and/or transmitting radio communications according to at least one first communication protocol and one second communication protocol different from the first protocol, including:

10 a first digital processing stage suitable for performing operations specific to the first protocol on a digital signal and a second digital processing stage suitable for performing operations specific to the second protocol on a digital signal, said digital processing stages being suitable for operating in parallel,

 a first receiving stage suitable for operating according to the first communication protocol,

15 a second receiving stage suitable for operating according to the second communication protocol,

 the first, second, respectively, receiving stage comprising a radio frequency receiver suitable for receiving a radiofrequency signal, a demodulator suitable for demodulating the radiofrequency signal received and an analog/digital converter for
20 converting the demodulated analog signal into a digital signal provided to the first, second digital processing stage, respectively,

 a transmission stage suitable for operating according to the first communication protocol and according to the second communication protocol, comprising a digital/analog converter for converting a digital signal provided by the first digital processing stage or the
25 second digital processing stage into an analog signal, a modulator suitable for modulating said analog signal, an amplifier and a radiofrequency transmitter suitable for transmitting a radio frequency signal corresponding to the modulated analog signal.

 Such radio nodes are for example mobile and used in military tactical telecommunications applications.

30 Such a radio node makes it possible to offer a parallel communication capability on several communications networks configured differently, for example operating in different radio ranges.

 In the radio nodes of the prior art, when the node must handle the communications relay of an additional network, the node is completed by a complete receiving, processing,
35 transmission chain, according to the communication protocol implemented in that

additional network. The multiplication of networks thus causes the multiplication of the volume occupied by the node, as well as increased electricity consumption of the node.

Techniques also exist whereby shared modules are used for the communication on different networks, by using software to reconfigure the modules each time the network for which they are used changes. However, the software reconfiguration is a slow process, which requires between 5 and 30 seconds to load/unload the software from the different components of the digital boards of the modem. Simultaneous communications on the different networks are therefore not guaranteed. Therefore, the volume of the node remains significant if the number of networks with which it is necessary to communicate at the same time is high.

To that end, according to a first aspect, the invention relates to a telecommunications node of the aforementioned type, characterized in that it further comprises:

a control module suitable for detecting the occurrence of an event, for selecting as a function of a rule and of said detected event, the first communication protocol or the second communication protocol, and for commanding the transmission stage to operate selectively according to the selected protocol and to no longer operate according to the non-selected protocol.

The invention thus makes it possible to provide parallel communication capabilities on several networks using the same node, while complying with the power supply constraints and/or minimizing the volume of the nodes.

In embodiments, the communication node according to the invention further includes one or more of the following features:

- the control module is further suitable, following the selection of said protocol, for commanding the digital stage, among the first digital processing stage and the second digital processing stage, suitable for operating according to the non-selected communication protocol, to stop providing the digital signal to the transmission stage;

- the node is suitable for ordering the transmission by the transmission stage according to the non-selected communication protocol, before said transmission stage operates selectively according to the selected protocol, of a notification to stop transmission according to said non-selected communication protocol;

- the event detected by the control module comprises indicating a datum to be transmitted by the node, a synchronization request by one of the first and second digital processing stages and/or the absence of digital signal provided by one of the first and second digital processing stages;

- the rule relates to at least one receiving node and/or one transmitting node, a priority order assigned to the communication data received by the node, and/or a synchronization constraint specific to the first and/or second digital processing stage;

- the first, second receiving stage, respectively, is suitable for operating alternately according to the first communication protocol and the second communication protocol, and wherein, when the control module commands the transmission stage to operate selectively according to the selected protocol and to no longer operate according to the non-selected protocol, said control module:

- further commands the first receiving stage to operate selectively according to the selected protocol and to no longer operate according to the non-selected protocol,
- further commands the second receiving stage to operate selectively according to the non-selected protocol and to no longer operate according to the selected protocol,
- switches the first and second receiving stages to provide data intended for the first and second digital stages;

- the first and second digital processing stages each include at least one processor specific to them.

According to a second aspect, the invention relates to a processing method in a communication node suitable for receiving and/or transmitting radio communications according to at least one first communication protocol and one second communication protocol different from the first protocol, selectively, the node comprising

a first digital processing stage suitable for performing operations specific to the first protocol on a digital signal and a second digital processing stage suitable for performing operations specific to the second protocol on a digital signal, said digital processing stages being suitable for working in parallel,

a first, second receiving stage, respectively, suitable for operating according to the first, second communication protocol, respectively, and each comprising a radio frequency receiver suitable for receiving a radiofrequency signal, a demodulator suitable for demodulating the received radiofrequency signal and an analog/digital converter for converting the demodulated analog signal into a digital signal provided to the first, second digital processing stage, respectively,

a transmission stage suitable for operating according to the first communication protocol and according to the second communication protocol, comprising a digital/analog converter to convert a digital signal provided by the first digital processing stage or the second digital processing stage into an analog signal, a modulator suitable for modulating

said analog signal, an amplifier and a radiofrequency transmitter suitable for transmitting a radio frequency signal corresponding to the modulated analog signal,

the method being characterized in that it comprises the following steps carried out by the node:

- 5 - the occurrence of an event is detected, and the first communication protocol or the second communication protocol is selected as a function of a rule and of said detected event; and
- the transmission stage is commanded to operate selectively according to the selected protocol and no longer operate according to the non-selected protocol.

The invention will be better understood upon reading the following description and examining the accompanying figures. These figures are provided as an illustration, but are not limiting on the invention. These figures are as follows:

- figure 1 is a view of a node in one embodiment of the invention;
- 15 figure 2 illustrates a first operating configuration of the node 1;
- figure 3 illustrates a second operating configuration of the node 1;
- figure 4 is a view of a communication system including three nodes in one embodiment of the invention;
- figure 5 is a flowchart of a method in one embodiment of the invention.

20 Figure 1 shows an example embodiment of a radio node 1 in one embodiment of the invention.

The radio node 1 is a radio set suitable for constituting a radio node of a UHF telecommunications network and a VHF telecommunications network.

25 The radio node 1 includes a VHF/UHF transceiver module 11, a VHF/UHF receiver module 12, a control module 13, a VHF digital processing module 14 and a UHF digital processing module 15.

The control module is suitable for controlling the operation of the VHF/UHF transceiver module 11, the VHF/UHF receiver module 12, the VHF digital processing module 14 and the UHF digital processing module 15.

30 The VHF/UHF transceiver module 11 and the VHF/UHF receiver module 12 are suitable for each operating in the VHF (Very High Frequency) radiofrequency range (30 MHz to 300 MHz), or in the UHF (Ultra High Frequency) radiofrequency range (300 MHz to 3000 MHz), based on a respective command provided by the control module 13 indicating the VHF or UHF operating mode.

35 The receiver module 12 comprises a radio frequency receiver 16, suitable for receiving a radiofrequency signal indicating telecommunications data sent to the node 1

on a predetermined UHF or VHF radio receiving channel determined based on a command from the control module 13, a demodulator 17 suitable for the modulating such a radiofrequency signal and optionally applying filtering, an analog/digital converter 18 for converting the demodulated signal into digital data representative of the telecommunications data sent to the node 1.

The node 1 is further suitable for this digital data to be routed, under the control of the control module 13, toward the suitable VHF 14, UHF 15 digital processing module, respectively, depending on whether the receiver module 12 was operating in VHF, UHF mode, respectively, to deliver that digital data.

The VHF/UHF transceiver module 11 also includes a radiofrequency receiver 19, suitable for receiving a radiofrequency signal indicating telecommunications data sent to the node 1 on a predetermined UHF or VHF radio receiving channel determined based on a command from the control module 13, a demodulator 20 suitable for demodulating such a radiofrequency signal and optionally applying filtering, an analog/digital converter 21 for converting the demodulated signal into digital data representative of the telecommunications data.

The node 1 is further suitable for this digital data to then be routed under the control of the control module 13 toward the suitable VHF 14, UHF 15 digital processing module, respectively, depending on whether the receiver module 12 was operating in VHF, UHF mode, respectively, to deliver that digital data.

The VHF/UHF transceiver module 11 further includes a digital/analog converter 22 suitable for receiving digital data delivered by the VHF 14, UHF 15 digital processing module, respectively, according to the control of the control module 13, depending on whether the transceiver module 11 is operating in VHF, UHF mode, respectively, a modulator 23, a power amplifier 24 and a radiofrequency transmitter 25. The digital/analog converter 22 converts the received digital data into analog data and provides it to the modulator 23, which modulates the analog data using a signal at a VHF or UHF modulation frequency, depending on the frequency range commanded by the control module 13, before delivering it to the power amplifier 24, which, after having performed the power amplification (of approximately 20-30 dB) thereon, transmits the amplified signal to the radiofrequency transmitter 25. The latter then transmits the amplified radiofrequency signal.

The VHF 14, UHF 15 digital processing module, respectively, for example includes a digital board equipped with a microprocessor and suitable for performing processing operations specific to the VHF, UHF communication, respectively, to analyze the digital data transmitted to it as input from the receiver module 12 to the transceiver module 11,

depending on the control by the control module 13, and/or applying error correction codes, and/or regenerating data, identifying the node transmitting some of that data, requesting retransmissions of data from transmitting nodes, generating signal channel requests intended for at least one other node, etc.

5 Thus, the radio node 1 does not have a simultaneous UHF/VHF transmission capability, since it only uses one transmission resource, operating alternately, and not simultaneously, in UHF and VHF.

 According to the invention, the control module 13 is suitable for making a real-time determination of which digital processing module from among the VHF 14 and UHF 15
10 digital processing modules is selected to provide digital data for radiofrequency transmission to the transceiver module 11.

 In the case ("VHF transmission" case) where the control module 13 determines that it is the VHF digital processing module 14 that has been selected to provide digital data for radiofrequency transmission to the transceiver module 11, then the control
15 module 13 simultaneously:

- commands the transceiver module 11 to operate in the VHF range,
- commands the receiver module 12 to operate in a complementary manner in the UHF range,
- commands the connections between the digital processing modules 14, 15 and
20 the transceiver modules 11, 12, for example by controlling the switches, such that:
 - o the VHF module 14 is notified that it can provide digital data to be transmitted (end of "radio silence" mode) to the transceiver module 11 for radiofrequency transmission via the successive processing operations done by the
25 digital/analog converter 22, the modulator 23, the amplifier 24 and radiofrequency transmitter 25;
 - o the VHF data received by the receiver 19 from the transceiver 11, after being demodulated by the demodulator 20 and digitized by the analog/digital converter 21, are provided to the VHF digital processing module 14;
 - 30 o the UHF data received by the receiver 16 after being demodulated by the demodulator 17 and digitized by the analog/digital converter 18 are provided to the UHF digital processing module 15;
- commands the UHF digital processing module 15 to stop the supply by that
35 module of data to be transmitted ("radio silence" mode, also called "transmission standby").

The configuration corresponding to this "VHF transmission" case is illustrated in figure 2.

In the case ("UHF transmission" case) where the control module 13 determines that it is the UHF digital processing module 15 that has been selected to provide digital data for radiofrequency transmission to the transceiver module 11, then the control module 13 simultaneously:

- commands the transceiver module 11 to operate in the UHF range,
- commands the receiver module 12 to operate in a complementary manner in the VHF range,
- commands the connections between the digital processing modules 14, 15 and the transceiver modules 11, 12, for example by controlling switches, such that:
 - o the UHF module 15 is notified that it can provide digital data to be transmitted (end of "radio silence" mode) and the digital data processed by the UHF module 15 are provided to the transceiver module 11 for radiofrequency transmission via the successive processing operations done by the digital/analog converter 22, the modulator 23, the amplifier 24 and the radiofrequency transmitter 25;
 - o the UHF data received by the receiver 19 from the transceiver 11, after being demodulated by the demodulator 20 and digitized by the analog/digital converter 21, are provided to the UHF digital processing module 15;
 - o the VHF data received by the receiver 16, after being demodulated by the demodulator 17 and digitized by the analog/digital converter 18, are provided to the VHF digital processing module 14;
- commands the VHF digital processing module 14 to stop the supply by that module of data to be transmitted ("radio silence" or "transmission standby" mode).

The configuration corresponding to this "UHF transmission" case is illustrated in figure 3.

The operation for determining the case among the "VHF transmission" and "UHF transmission" cases is done each time a predetermined event(s) is (are) detected by the control module 13.

Such an event may be of various natures: for example, the passing of a given time delay and/or the identification of data to be transmitted by the node 1 by either of the VHF 14, UHF 15 digital processing modules and/or a notification of the VHF 14, UHF 15 digital processing module, respectively, according to which a synchronization operation must be

done with at least one other node on the VHF, UHF network, respectively, and/or a notification indicating an absence of data to be transmitted provided by one and/or the other of the VHF 14, UHF 15 digital processing modules, etc.

In one embodiment, the passage of the node 1 into "radio silence" mode in UHF, VHF, respectively, is indicated to the neighboring nodes by the UHF, VHF transmission, respectively, of the corresponding notification by the transceiver module 11 before the passage into the "radio silence" mode of the UHF processing module 15 and before the passage into the VHF mode of the transceiver module ("VHF transmission" case), respectively before passage into the "radio silence" mode of the VHF processing module 14 and before the passage into the UHF mode of the transceiver module 11 ("UHF transmission" case).

The nodes of the UHF, VHF network, respectively, affected by this radio silence are thus notified that their transmissions to the node 1 will not be acknowledged immediately by the latter, and may adapt their transmission mode so as to reliabilize it.

In another embodiment, the control module 13 does not command the digital processing module to which the receiver module 12 provides digital data to go into "radio silence" mode, for example when that configuration is provided to be short-lasting.

The determination of the case from among the "VHF transmission" and "UHF transmission" cases is done by the control module 13 based on a rule or several combined rules. A rule for example depends on one or more receiver(s)/transmitter(s) of data to be transmitted and/or data received by the node, and/or priorities assigned to the data and/or constraints related to the UHF and/or VHF synchronization.

Figure 4 shows a system 100 including three nodes P1, P2, P3 each similar to the node 1 and within radio range of each other.

Each piece of equipment referenced N in figure 1, for N = 11 to 15 in reference to the node 1, corresponds to the equipment referenced Ni of the node Pi, for i=1 to 3, in figure 4.

This figure 4 illustrates the possibilities of "full-duplex" communication, with these three nodes P1 to P3 being single-channel in transmission, and dual-channel in reception.

In the considered configuration:

- in node P1, the transceiver module 111 is operating in VHF, and the receiver module 121 is operating in UHF;
- in node P2, the transceiver module 112 is operating in UHF, and the receiver module 122 is operating in VHF;
- in node P3, the transceiver module 113 is operating in VHF, and the receiver module 123 is operating in UHF.

The sets P1 and P2 can thus communicate together in "full-duplex" mode on the different radio channels for communication in one direction (in UHF) and communication in the other direction (in VHF); at the same time that the sets P1 and P3 are communicating with each other in transceiver mode in VHF. The set P2 can transmit in UHF at the same time to P3, which can receive those data transmitted by P2.

As illustrated in figure 4, the nodes remain in two-way communication in two ways:

- either via the same frequency range in both directions of communication: for example, in the nodes P1 and P3, which communicate in VHF,
- or via one frequency range in one direction, and another in the other direction: for example, the node P1 transmits toward the node P2 in VHF, and receives from the node P2 in UHF.

When the connectivity in a node is broken in UHF, which has a more limited range than VHF:

- the simple receiver module makes it possible to continue to listen to messages and conferences in VHF;
- if a communication must be established in VHF, then the node switches its UHF and VHF channels;
- it remains in simple UHF reception (i.e., "radio silence" mode) with the nearby nodes and can give them orders via the VHF, since the latter are in simple VHF listening.

When UHF connectivity returns,

- the information is known owing to the simple UHF reception of the node, which detects the presence of a node that was out of range until then;
- the node returns to UHF transceiver and simple VHF receiver mode.

Figure 5 shows a flowchart of the steps of a method implemented in a radio node in one embodiment of the invention.

In a step 300, the occurrence of an event is detected, in the manner described above.

Based on this event and at least one rule, the "VHF transmission" case or the "UHF transmission" case is selected, in a step 301, in the manner described above.

The commands corresponding to the selected case are then carried out by the control module 13 (step 302a or 302b).

The invention thus makes it possible to miniaturize the radio node by decreasing the number of transmission resources, owing to the pooling of those resources between different telecommunications networks.

The radio node remains listening on all of the radio channels, and can transmit on all of the radio channels quasi-instantaneously owing to the quasi-immediate switching capability between the transmission modules and the digital processing modules (there are no delays due to software loading/unloading).

5 According to the invention, digital switching between the two UHF, VHF wave forms is done, in the transmission processing, before data to be transmitted are provided to the digital/analog converter 22, and the analog/digital conversion 22, modulator 23, amplifier 24, radiofrequency transmitter 25 modules are used in common for UHF transmission or VHF transmission.

10 In the embodiment described in reference to the figures, a transceiver hardware module and a simple receiver hardware module have been considered. The invention may nevertheless be implemented when one transmission module and two receiver modules independent of the transmission module are considered. In that case, there is no need to invert the receiver modules when the communication protocol implemented by the
15 transmission module changes.

 In another embodiment, the invention is for example carried out based on two transceiver hardware modules (in place of one transceiver hardware module and one simple receiver hardware module), the transmission functionality of one of the two modules not being used in order to comply with power supply constraints. The use of the
20 transmission functionality may in one usage mode be done alternately on each of the transceiver hardware modules. There is then no need to invert the transceiver modules for them to provide/receive data with respect to the digital processing modules.

 In reference to the figures, a node has been considered relaying the communications of two networks. Of course, the invention can be implemented in the
25 case of a node relaying the communications of any number n of networks, n being able to be strictly greater than 2, and the invention making it possible to share the transmission capabilities between several networks, inasmuch as the transmission capability can be used alternately for both networks. The node then includes n radiofrequency stages, some of which have a transmission and reception capability and others a reception capability
30 only. Only the radiofrequency transmission stages require a synonymous consumption and volume power amplifier. A control module commands the connections between the radiofrequency (and if applicable, receiver) transmission stages and the digital processing module specific to each network.

 One network has been considered based on communications of the UHF type, and
35 another on communications of the VHF type. Of course, the invention may be implemented with varied types of communication protocols, as long as a shared

transmission device can be used. For example, the protocols of the pooled transmission networks could be the 2G and 3G technologies. It may also be implemented with digital processing modules working in the same frequency range but on different frequency channels (for example, two modules working in VHF can, under the proposed method, pool the transmission module).

CLAIMS

1. A communication node (1) suitable for receiving and/or transmitting radio communications according to at least one first communication protocol (VHF) and one second communication protocol (UHF) different from the first protocol, including:

a first digital processing stage (14) suitable for performing operations specific to the first protocol on a digital signal and a second digital processing stage (15) suitable for performing operations specific to the second protocol on a digital signal, said digital processing stages being suitable for operating in parallel,

a first receiving stage (11) suitable for operating according to the first communication protocol,

a second receiving stage (12) suitable for operating according to the second communication protocol,

the first, second, respectively, receiving stage comprising a radio frequency receiver (19, 16) suitable for receiving a radiofrequency signal, a demodulator (20, 17) suitable for demodulating the radiofrequency signal received and an analog/digital converter (21, 18) for converting the demodulated analog signal into a digital signal provided to the first, second digital processing stage, respectively,

a transmission stage (11) suitable for operating according to the first communication protocol and according to the second communication protocol, comprising a digital/analog converter (22) for converting a digital signal provided by the first digital processing stage or the second digital processing stage into an analog signal, a modulator (23) suitable for modulating an analog signal provided as input to the modulator, a power amplifier (24) suitable for amplifying an analog signal provided as input to the power amplifier, and a radiofrequency transmitter (25) suitable for transmitting a radio frequency signal corresponding to the analog signal modulated by said modulator and amplified by said power amplifier,

said node being characterized in that it further includes a control module (13) suitable for detecting the occurrence of an event, for selecting as a function of a rule and of said detected event, the first communication protocol or the second communication protocol, and for commanding at least said modulator, power amplifier and radiofrequency transmitter of the transmission stage to operate selectively according to the selected protocol and to no longer operate according to the non-selected protocol and wherein switching between one selected of the first and second communication protocols to another selected of the first and second communication protocols is a digital switching.

2. The communication node (1) according to claim 1, wherein the control module (13) is further suitable, following the selection of said protocol, for commanding the digital stage, among the first digital processing stage (14) and the second digital processing stage (15), suitable for operating according to the non-selected communication protocol, to stop providing the digital signal to the transmission stage (11).

3. The communication node (1) according to claim 1 or 2, suitable for ordering the transmission by the transmission stage (11) according to the non-selected communication protocol, before said transmission stage operates selectively according to the selected protocol, of a notification to stop transmission according to said non-selected communication protocol.

4. The communication node (1) according to one of the preceding claims, wherein the event detected by the control module (13) comprises indicating a datum to be transmitted by the node, a synchronization request by one of the first and second digital processing stages and/or the absence of digital signal provided by one of the first and second digital processing stages.

5. The communication node (1) according to one of the preceding claims, wherein the rule relates to at least one receiving node and/or one transmitting node, a priority order assigned to the communication data received by the node, and/or a synchronization constraint specific to the first and/or second digital processing stage.

6. The communication node (1) according to one of the preceding claims, wherein the first (11), second (12) receiving stage, respectively, is suitable for operating alternately according to the first communication protocol and the second communication protocol, and wherein, when the control module (13) commands the transmission stage (11) to operate selectively according to the selected protocol and to no longer operate according to the non-selected protocol, said control module:

- further commands the first receiving stage to operate selectively according to the selected protocol and to no longer operate according to the non-selected protocol,
- further commands the second receiving stage to operate selectively according to the non-selected protocol and to no longer operate according to the selected protocol,

- switches the first and second receiving stages to provide data intended for the first and second digital stages.

7. The communication node (1) according to any one of the preceding claims, wherein the first (14) and second (15) digital processing stages each include at least one processor specific to them.

8. The communication node (1) according to any one of the preceding claims, wherein the same power amplifier (24) is used for amplifying the analog signal provided as input to the power amplifier to the first communication protocol when selected and according to the second communication protocol when selected.

9. A processing method in a communication node (1) suitable for receiving and/or transmitting radio communications according to at least one first communication protocol (VHF) and one second communication protocol (UHF) different from the first protocol, selectively, the node comprising

a first digital processing stage (14) suitable for performing operations specific to the first protocol on a digital signal and a second digital processing stage (15) suitable for performing operations specific to the second protocol on a digital signal, said digital processing stages being suitable for working in parallel,

a first (11), second (12) receiving stage, respectively, suitable for operating according to the first, second communication protocol, respectively, and each comprising a radio frequency receiver (19, 16) suitable for receiving a radiofrequency signal, a demodulator (20, 17) suitable for demodulating the received radiofrequency signal and an analog/digital converter (21, 18) for converting the demodulated analog signal into a digital signal provided to the first, second digital processing stage, respectively,

a transmission stage (11) suitable for operating according to the first communication protocol and according to the second communication protocol, comprising a digital/analog converter (22) for converting a digital signal provided by the first digital processing stage or the second digital processing stage into an analog signal, a modulator (23) suitable for modulating an analog signal provided as input to the modulator, a power amplifier (24) suitable for amplifying an analog signal provided as input to the power amplifier, and a radiofrequency transmitter (25) suitable for transmitting a radio frequency signal corresponding to the analog signal modulated by said modulator and amplified by said power amplifier,

said node further including a control module (13) suitable for detecting the occurrence of an event, for selecting as a function of a rule and of said detected event, the first communication protocol or the second communication protocol, and for commanding at least said modulator, power amplifier and radiofrequency transmitter of the transmission stage to operate selectively according to the selected protocol and to no longer operate according to the non-selected protocol and wherein switching between one selected of the first and second communication protocols to another selected of the first and second communication protocols is a digital switching;

the method being characterized in that it comprises the following steps carried out by the node:

- the occurrence of an event is detected, and the first communication protocol or the second communication protocol is selected as a function of a rule and of said detected event; and
- the transmission stage is commanded to operate selectively according to the selected protocol and no longer operate according to the non-selected protocol.

10. The processing method according to claim 9, wherein the detected event comprises the indication of a datum to be transmitted by the node, a synchronization request by one of the first and second digital processing stages and/or the absence of digital signal provided by one of the first and second digital processing stages.

11. The processing method according to claim 9 or 10, wherein the rule relates to at least one receiving node and/or one transmitting node, a priority order assigned to the communication data received by the node, and/or a synchronization constraint specific to the first and/or second digital processing stage.

12. The processing method according to any one of claims 9-11, wherein the same power amplifier (24) is used for amplifying the analog signal provided as input to the power amplifier to the first communication protocol when selected and according to the second communication protocol when selected.