

REMOTE CONTROL SYSTEM WITH KEY FUNCTION DISPLAY PROVISIONS

The present invention concerns remote control systems such as are used to allow controlled devices to
5 be controlled from a remote location. For example, many consumer electronics products such as television receivers, video cassette recorders (VCRs), audio record and cassette players, have associated hand-held remote control transmitter units for controlling various functions from a viewing or
10 listening position.

A typical remote control transmitter unit has a keyboard with a plurality of keys or buttons corresponding to the functions to be controlled. Usually the more functions that have to be controlled, the greater the number
15 of keys that have to be provided. Since modern consumer electronic products have a very large number of control functions, the keyboard of remote control transmitter units of such products are often cluttered with keys. Some manufacturers provide a single, unified remote control unit
20 for several controlled devices, such as a television receiver and a VCR which are intended to be operated together. The keyboards of such unified remote control transmitter units, therefore, may contain even more keys than dedicated remote control units for individual
25 controlled devices.

Remote control transmitter units with a large number of keys tend to be cumbersome to use and expensive to manufacture. Accordingly, there is a desire in the art to reduce the number of keys of remote control transmitter
30 units.

There have been attempts to reduce the number of keys by assigning multiple functions to at least some keys. The particular function of a key at any time can be

determined by a mode switch or by the sequence of prior key operations. To guide users, labels on the keyboard identifying the various functions of the keys may be employed. It is also possible in a television system with a viewing screen, to use the viewing screen to display information indicating the functions of the keys of the remote control transmitter during various modes of operation. However, such prior approaches are indirect and, therefore, may be confusing.

10 To avoid the confusion that may result from the indirect key function identification technique described above, it has been proposed in European Patent Application Publication No. 0 120 345 to provide a display arrangement on the remote control transmitter unit itself to identify the particular functions of keys at various steps of a control operation. The display arrangement may take the form of individual display devices located near respective keys or of individual display elements underlying transparent keys. Each display device is capable of displaying characters designating the function of the associated key. The information for the key function display arrangement is stored in a display memory contained in the remote control transmitter unit. For expansion, display memories for additional devices that may be controlled by the remote control transmitter unit may be added to the remote control transmitter unit.

While the type of remote control system described in the European Patent Application is useful, the provisions for expanding its capability to control new devices by adding display memories may be troublesome to users and may limit the number of devices that can be controlled due to wiring and size constraints of the remote control transmitter unit.

Other examples of prior art are to be found in published European applications nos. 0129286 and 0057970.

35 A remote control system constructed in accordance with the present invention comprises a transmitter unit including a multi-function user entry device with key

elements and a display unit for identifying the functions of the key elements at various steps of a control algorithm or sequence. The receiver unit of the remote control system, in addition to generating control signals for an associated controlled device in response to remote control messages received from the transmitter unit, includes a key function and display memory for storing information indicative of the functions of key elements of the transmitter unit. During various steps of the control algorithm, character representative data is retrieved from the key function and display memory and transmitted from the receiver unit to the transmitter unit. In response to the received character representative signals, the display unit displays information identifying the functions of the key elements.

Since the key function and display memory is contained in the receiver unit of the remote control system, rather than in the transmitter unit, the same transmitter unit can be used without modification for additional controlled devices. Also, there is no limit on the number of new controlled devices that may be controlled by the transmitter unit.

In a preferred embodiment of the invention, the key elements comprise areas on a touch-sensitive transparent or translucent membrane which overlays a display panel such as a liquid crystal device (LCD).

These and other features of the present invention will be explained in the following description with respect to the accompanying Drawing.

FIGURES 1 and 2 show, in block diagram form, the transmitter and receiver units of a remote control system constructed in accordance with the present invention; and

FIGURE 3 indicates the contents of a key function and display memory included with the receiver unit of the remote control system shown in FIGURES 1 and 2.

Before describing the embodiment of the remote control system shown in FIGURES 1, 2 and 3 in detail, a brief summary of some of its features is provided.

5 In the present remote control system shown in FIGURES 1, 2 and 3, a single remote control transmitter controls several controlled devices, such as a television receiver (TV), video cassette recorder (VCR) and audio tape
10 player (ATP). Each controlled device has a relatively large number of functions to be controlled. In order to reduce the clutter and cost associated with fixed or dedicated function arrangements, the keys of the remote control transmitter have multiple functions. A display unit is
15 provided on the remote control transmitter itself to identify the various functions of the keys.

The control process or algorithm provided by the remote control system shown in FIGURES 1, 2 and 3, occurs sequentially in steps of increasing levels of specificity. By way of example, the device to be controlled (e.g., TV,
20 VCR or ATP) is selected at a first control level; the property of the device to be controlled (e.g., reception channel, picture response or audio response of a television receiver) is selected at a second control level; and the specific manner in which a characteristic of the selected
25 property is to be controlled (e.g., increasing or decreasing the brightness, contrast or peaking of the picture) is selected at a third control level. More levels of control may be provided. For example, instead of actually controlling the specific manner in which a characteristic of
30 a selected property is to be controlled (e.g., increasing or decreasing the contrast) at the third level, the third level may be used merely to select the characteristic of the selected property to be controlled (e.g., the brightness, contrast or peaking of the picture) and a fourth level may
35 be provided to select the specific manner in which the selected characteristic is to be controlled (e.g., increasing or decreasing the contrast).

Referring now to FIGURE 1, a remote control transmitter 100 includes a multi-function user input device 102 comprising a transparent or translucent, flexible touch-sensitive membrane 104 which overlays a key function display panel 106. Key function display panel 106 displays information for identifying the functions of the "keys" or key elements of membrane 104 at various steps of a control sequence. By way of example, display panel 106 may comprise a liquid crystal device (LCD).

The centers of the touch areas of the "keys" of user input device 102 are defined by the intersection or cross-over points of relatively thin row and column conductors 108 and 110, respectively, within respective layers of membrane 104. Row conductors 108 are normally not electrically in contact with column conductors 110. When a user depresses the surface of membrane 104 in touch areas surrounding the cross-over points, respective ones of row conductors 108 and column conductors 110 are brought into electrical contact. Row conductors 108 and column conductors 110 are coupled (through respective connectors indicated by blocks) to a control unit 112 comprising, e.g., a microprocessor or microcomputer. As is conventional, control unit 112 includes a central processing unit (CPU) 114, a random access memory (RAM) 116 for the temporary storage of data and a read only memory (ROM) 118 containing a control program. Control unit 112 senses which ones of row conductors 108 and column conductors 110 have been brought into electrical contact and generates a corresponding digitally coded remote control message. The digital coded remote control message is coupled in serial form to an amplifier 120 which drives a transducer 122 for transmitting the remote control message to the controlled devices. By way of example, transducer 122 may comprise an infra-red (IR) light-emitting diode (LED).

As earlier indicated, at each step of the control sequence, alphanumeric and symbol characters indicating function information are caused to be displayed on display panel 106 in the touch areas surrounding the cross-over

points of row conductors 108 and column conductors 110 under the control of a character generator 124 in response to character-representative signals. In accordance with an aspect of the present invention, the character-representative signals are transmitted from the controlled devices to transmitter unit 100 as will be explained below.

The multi-function key arrangement of remote control transmitter 100 reduces the clutter and cost associated with single-function or dedicated key arrangements especially when the number of functions and/or the number of devices to be controlled is large. The key function display provisions significantly reduce the likelihood of confusion normally associated with prior multi-function key arrangements. Key function display arrangements for identifying the functions of multi-function keys are known, as discussed above. However, unlike prior key function display arrangements, the present arrangement does not require modification as new controlled devices are added. This is because the information for determining the functions of the various key elements and for providing the associated key function display is stored in the various controlled devices controlled by transmitter unit 100 (rather than in transmitter unit 100). The key function display information is transmitted from the controlled devices to remote control transmitter 100. Remote control transmitter 100 includes an input transducer 126, e.g., comprising an IR LED, an amplifier 128 and an input storage buffer 130 for receiving and temporarily storing the key function display information transmitted by the controlled devices. The manner in which the key function display information is transmitted by the controlled devices and processed in remote control transmitter unit 100 to indicate the functions of the keys at various steps of control sequence will now be described in detail.

FIGURE 2 shows the arrangement of the remote control receivers of the controlled devices which may be controlled by remote control transmitter 100 shown in FIGURE

1. By way of example, three home entertainment devices are shown, namely, a television receiver (TV) 200, a video cassette recorder (VCR) 300 and an audio tape player (ATP) 400. Since the remote control receivers (RCVRs) 202, 302 and 402 of all of the controlled devices are similar, only the one (202) for television receiver 200 is shown in detail.

Remote control receiver 202 of television receiver 200 includes an input transducer 204, such as an IR LED, and an amplifier 206 for receiving remote control messages transmitted by transmitter 100 and converting them to corresponding electrical signals. The data of the remote control message, which arrives serially (as it is transmitted), is coupled in the same fashion to a control unit 208 comprising a microprocessor or microcomputer with a CPU 210, a RAM 212 for temporarily storing data and a ROM 214 in which a control program is stored. Under program control, control unit 208 interprets the received remote control data and generates control signals for television receiver 200. Since receiver 202 has to be capable of receiving remote control messages even when the main signal processing portions of television receiver 200 are "off" and are therefore not receiving operating voltages, operating voltage for remote control receiver 202 is provided by a standby power supply (not shown).

As earlier noted, the various functions of a controlled device are controlled in sequential steps of increasing specificity. The control program for television receiver 200 is stored in ROM 214. A portion 216 of ROM 214 contains the key function information for transmitter 100 for each step or level in the control algorithm. Portion 216 of ROM 214 is shown in greater detail in FIGURE 3.

As shown schematically in FIGURE 3, the information stored in ROM portion 216 is organized in blocks corresponding to the steps or levels of the control algorithm. In each block, for each key of transmitter 100, the character representative information for displaying the function of the key and the memory location of the next step

or level of the control algorithm (if the key is activate
is stored in the respective memory locations. The relat
addresses of the memory locations within a block correspond
to the key designations. For example, the key function
5 display and next step information for key 1 is stored in the
first memory location of each block.

When a remote control message is received from
transmitter 100, control unit 208, in addition to generating
appropriate control signal, retrieves the key function
10 display and next step information from ROM portion 216,
stores the next step information in RAM 212 for later use
and composes a digitally encoded key function display
message in accordance with the key function display
information. The key function display message is coupled in
15 serial fashion to an amplifier 218 which drives a transducer
220, such as an IR LED, for transmission to transmitter unit
100.

The key function display messages transmitted by
the various controlled devices have the same format. The
20 key function display messages include a block of data for a
device code identifying the transmitting controlled device
followed by blocks of character representative data for
indicating the functions of the respective keys of user
entry device 102 of transmitter 100. The key function and
25 display message format can be schematically represented as:

DC, KEY 1, KEY 2, KEY 3, ---- KEY 15

where DC represents the device code and KEY 1 ---- KEY 15
represent the character representative key function display
information for respective keys of user input device 102.
30 Framing code words signifying the beginning and end of the
key function display message and data blocks within the
message are not indicated. It is assumed in this example,
dealing with home entertainment products, that user input
device 102 has fifteen keys. This permits ten keys for
35 numerical type of controls, such as channel selection in a
television receiver and advanced selection of programs
("auto-programming") in a VCR, with a remainder of five keys
for other functions. A three-bit device code (DC) permits

the remote control unit to control as many as nine different devices. Assuming that three alpha-numeric characters are used to designate each key function and that a five-bit ASCII code is used, 15 bits per key or 225 bits for 15 keys are required. Incorporating framing and error protection bits yields less than 1000 bits. A transmission rate of 1000 bits per second is compatible with an infra-red transmission link and provides a reasonably short time, about one second, for updating the key function display as the control operation proceeds from one step to the next.

Again with reference to FIGURE 1, the device code block of the key function display information stored in input buffer 130 is transferred to and stored in RAM 116 of control unit 112 and the character-representative key function display blocks are sequentially transferred to character generator 124 under the control of control unit 112. Character generator 124 causes the key function for each key to be displayed in the corresponding key pad area in accordance with the position of the corresponding block of coded data in the received key function display message. Thus, e.g., the key function for key 1 is displayed in the upper left-hand corner of display 106 where the first one of row conductors 108 intersects the first one of column conductors 110 and the key function for key 2 is displayed where the first one of row conductors 108 intersects the second row of column conductors 110 and so on. It is noted that for a particular step in a control sequence, some of the keys may not have corresponding functions. In that case, the ASCII code signifying "no character" or "blank" will be transmitted for each of the three alpha-numeric character positions of the data block associated with the unused key.

When a key of user input device 102 is activated by a user, the remote control message is composed by control unit 112. The remote control message, excluding framing and error protection code words, has the format:

DC, KEY No.

The device code (DC) is read from RAM 116, where it was previously stored, and the key number is derived directly from the position of the activated key.

It is noted that since the key function information is stored in the controlled devices, no ROM memory locations are required for storing unique codes designating devices and functions to be controlled. As earlier noted, the device code (DC) is derived from the key function display message previously transmitted from controlled device and the "key no." information merely designates the key that was operated and is independent of the device or function to be controlled. This characteristic of the present invention makes it readily adaptive to new controlled devices.

Again referring to FIGURE 2, when a remote control message is received by each of the receiver units 202, 302 and 402 from transmitter unit 100, the received device code is compared to the respective pre-assigned device code. Only the remote control receiver of the controlled device which has the device code corresponding to the one in the remote control message responds to the remote control message. In this example, it is assumed that the device code of the remote control message corresponds to television receiver 200. In response to the key portion of the remote control message, the function of the activated key for the current step of the control algorithm is performed in accordance with a subroutine stored in the memory locations starting at the address indicated by the next step portion of the memory location for the respective key. In some cases, the function associated with an activated key corresponds to presenting the next level of function choices by retrieving and transmitting the key function display information for the next step. In other cases, the function associated with an activated key corresponds to generating a control signal, e.g., such as for increasing the contrast of the picture, and thereafter presenting another level of function choices.

Referring once again to FIGURE 1, in addition to the multi-function keys of user input device 102, remote control transmitter 100 also includes three single-function or dedicated function keys 132, 134 and 136.

5 Dedicated function key 132, labelled "DEVICES", is used to initiate a mode of operation for selecting a particular controlled device in which each of the controlled devices is associated with a respective key of user input device 102. When a user depresses key 132, a corresponding
10 coded remote control message corresponding to "DEVICES" key 132 is composed by control unit 112 and transmitted via driver 120 and transducer 122. Each controlled device responds to the "DEVICES" remote control message by transmitting a key function display message to remote
15 control transmitter 100. Each message transmitted to transmitter 100 by a controlled device includes the respective device code and respective character-representative data (e.g., representing TV, VCR or ATP) assigned to the data block a particular key assigned
20 according to the controlled device. The device identifying messages transmitted by the controlled devices to remote control transmitter are transmitted from the controlled devices at respective predetermined different time delays after the reception of the "DEVICES" remote control message.
25 As the device identifying messages are sequentially received by transmitter 100, the corresponding device identifying characters are caused to be displayed in the touch area corresponding to the respective assigned key and the associated device codes are stored in respective memory
30 locations of RAM 116 of control unit 112.

 Thereafter, when a key of user entry device 102 corresponding to a device to be controlled is activated, control unit 112 composes and causes the transmission of a remote control message instructing the selected controlled
35 device to transmit the key function display message for the first level or step of its control algorithm. By way of example, the remote control message may be in the form of:

DC, MAIN

where DC corresponds to the device code, previously stored in RAM 116, and MAIN is a code word signifying that the key function display information for the main or first step of the control algorithm of the selected controlled device is to be transmitted from the selected controlled device to transmitter 100.

Dedicated function key 134, labelled "MAIN", is used to call up the main or first level of function control choices of the last one of the controlled devices that was controlled. When key 134 is depressed, control unit 112 retrieves the device code of the controlled device last controlled from RAM 116 and composes and causes the transmission of a remote control message in the form of:

DC, MAIN

This remote control message, as previously discussed with respect to key 132, causes the key function display information for the main or first level of the control algorithm of the selected controlled device to be transmitted to transmitter 100.

Dedicated function key 136, labelled "BACK", is used to recall the last level of function control choices of the last controlled device to be controlled. When a user depressed "BACK" key 136, control unit 112 composes and causes the transmission of a remote control message in the form of:

DC, BACK

Here also, the device code of the last controlled device that was controlled is retrieved from RAM 116. The last controlled device to be controlled responds to this remote control message by retrieving and transmitting the last key function display message. If BACK key 136 is depressed again, the resulting remote control message causes the next-to-last key function display information of the last controlled device that was controlled to be transmitted.

Operating power for transmitter 100 is supplied by a battery 138. The supply voltage (V+) provided by battery 138 is not coupled to the various units of remote control

transmitter unit 100 until one of dedicated keys 132, 134 and 136 has been depressed. When one of dedicated switches 132, 134 and 136 is depressed, an "OR" function gate 140 causes a flip-flop (FF) 142 to be set, which in turn causes an electronic switch 144 to couple the supply voltage (V+) to the various units of transmitter 100. Thereafter, switch 144 continues to provide the supply voltage until FF 142 is reset by control unit 112 at a predetermined time after the last user entry by means of either user multi-function entry device 102 or dedicated function keys 132, 134 and 136. Desirably, RAM 116 is nonvolatile since it has to maintain the device code of the selected controlled device even when the supply voltage (V+) is not provided. Alternatively, RAM 116 may be directly connected to battery 140.

The following table indicates a typical control sequence to illustrate, by way of example, the operation of the structure of the remote control system described above with reference to FIGURES 1, 2 and 3. In the table, portions of key function display messages such as KEY1/TV indicate that the data block corresponding to the identified key (e.g., KEY 1) represents the identified characters (e.g., TV).

Typical Control Sequence

<u>User Input</u>	<u>Transmitter</u>	<u>Receiver(s)</u>
Press DEVICES key.	Send DEVICES remote control message.	The controlled devices send their respective DCs and key/device information at predetermined different times. E.g., TV sends TV DC, KEY1/TV, thereafter VCR sends VCR DC, KEY2/VCR, and thereafter ATP sends ATP DC, KEY3/ATP. For all the unused keys, "BLANK" character data blocks are sent.

<u>User Input</u>	<u>Transmitter</u>	<u>Receiver(s)</u>
	Store received DCs and display key/device information.	
5 Press key 1 (to select TV).	Send TV DC, KEY1.	Retrieve and send first level function choices for TV. E.g., TV DC, KEY1/CH (channel selection), KEY2/VID (video), KEY3/AUD (audio), KEY4/BLANK, KEY5/BLANK, ... KEY14/BLANK, KEY15/OFF.
10		
15		
	Store TV DC and display key function choices for TV.	
20 Press key 1 (for channel selection).	Send TV DC, KEY1.	Retrieve and send function choices for channel selection. E.g., TV DC, KEY1/1, KEY2/2, KEY3/3, ... KEY10/0, KEY11/CHU (channel up), KEY12/CHD (channel down), KEY14/BLANK, KEY13/BLANK, KEY15/OFF.
25		
30		
35		
	Store TV DC and display key function for channel selection.	
40 Press key 2 (for first digit of channel number 25).	Send TV DC, KEY2.	Recognize that first digit of channel number has been entered (since KEY2 transmitted) and retrieve and send channel selection function choices again.
45		
50	Store TV DC and display key function information for channel selection.	

	<u>User Input</u>	<u>Transmitter</u>	<u>Receiver(s)</u>
	press key 5 (for second digit of channel number 25).	Send TV DC, KEY5.	Tune channel 25.
5	Press MAIN key.	Send TV DC, MAIN.	Retrieve and send first level function control choices for TV.
10		Store TV DC and display key function information for TV.	
	Press key 2 (for video control).	Send TV DC, KEY 2.	Retrieve and send video control function choices. E.g., TV DC, KEY1/CTU (contrast up), KEY2/CTD (contrast down), KEY3/BRU (brightness up), KEY4/BRD (brightness down), KEY5/PU (peaking up), KEY6/PD (peaking down) KEY7/COU (color up), KEY8/COD (color down), KEY9/TIU (tint up), KEY10/TID (tint down), KEY11/BLANK,... KEY14/BLANK, KEY15/OFF.
15			
20			
25			
30			
35			
		Store TV DC and display key function information for video.	
40	Press key 2 (for decreasing contrast).	Send TV DC, KEY2.	Decrease contrast as long as transmission continues. When the transmission ends, retrieve and send the video control function choices again.
45			

	<u>User Input</u>	<u>Transmitter</u>	<u>Receiver(s)</u>
		Store TV DC and display key function information for video.	
5	No entry for predetermined time.	Power down transmitter (decouple the battery).	
10	Press BACK key	Send TV DC, BACK.	Retrieve and send function choices for channel selection.
15		Store TV DC and display key function information for channel selection.	
20	Press key 11 (for increasing the channel number).	Send TV DC, KEY11.	Increase the channel number as long as the transmission continues. When transmission ends, tune the channel at which transmission stopped.
25			

It is noted that in the above control sequence that a predetermined key (i.e., key 15) of multi-function user input device 102 is assigned to the "OFF" function in various key function display messages. This allows a user to turn the television receiver off at any step of the control algorithm without having to pass through the first or main function selection step. It will be appreciated that other frequently controlled functions, such as increasing and decreasing the volume level and increasing and decreasing the channel number may be treated in the same manner. It is further noted that in some cases it may be desirable to provide dedicated keys for frequently controlled functions.

It will be appreciated that key function display arrangements are possible other than the one shown in FIGURE 1, in which touch-sensitive membrane 104 overlays display panel 106. For example, individual keys and associated individual display elements may be provided (as is disclosed in the above-noted European patent application). However,

it appears that the arrangement shown in FIGURE 1 is more compact and less cluttered, especially if a large number of function choices are anticipated for various steps of a control algorithm.

5 While in FIGURE 1, input buffer 130 is shown as a device separate from the microprocessor or microcomputer device comprising control unit 112 of transmitter 100, it will be appreciated that input buffer 130 may be incorporated in the same device.

10 As earlier noted, the present remote control arrangement in which the key function display information is stored in the controlled devices (rather than in the transmitter unit) is advantageous since it readily allows for the addition of new controlled devices without
15 modification of the transmitter unit. The present remote control arrangement is also advantageous since it significantly reduces the memory capacity required for the transmitter unit compared with the system disclosed in the above-noted European patent application. Depending on the
20 complexity of the control programs stored in the program memories of the remote control receiver units of the controlled devices, the key function display information may be stored in the same memory device as used for storing the program for controlling the controlled devices (as is
25 indicated in FIGURE 2 by ROM 214 including key function and display memory portion 216). Alternately, the key function and display information may be stored in a separate memory device.

30 The modifications described above to the embodiment shown in FIGURES 1, 2 and 3 as well as others are intended to be within the scope of the invention defined by the following claims.



CLAIMS:

1. A remote control system for at least one controlled device, comprising:

a transmitter unit including user entry means having a plurality of multi-function key elements; output means for transmitting, when a key element is operated, a remote control message identifying said controlled device and identifying the operation of said key element; and display means for displaying information identifying the functions associated with said key elements;

a receiver unit associated with said controlled device and including input means for receiving said remote control message; key function memory means for storing character-representative information for identifying the functions of said key elements of said transmitter unit and corresponding control information for various steps of a control sequence for controlling said controlled device; and output means coupled to said key function memory means for transmitting a key function display message including character-representative information for a next step of said control sequence in response to said remote control message and also information identifying said controlled device; wherein

said transmitter unit further includes input means for receiving said key function display message and for coupling the associated character-representative information to said display means to cause said key function information to be displayed;

said transmitter unit still further includes memory means for storing said device identifying information included in said key function display message; and

said remote control message transmitted by said transmitter unit includes said device identifying information stored in said memory means.



2. A remote control system as recited in Claim 1, wherein:

said display means includes a display panel ; and
said user entry means comprises a translucent or transparent touch-sensitive member that overlays said display panel.

3. A remote control system as recited in Claim 1 or 2, wherein:

said key function display message transmitted by said output means of said receiver unit is organized in data blocks each including character-representative information for identifying the function of a respective key element, the position of said data blocks within said key function display message being determined by the location of said respective key elements on said transmitter unit.

4. A remote control system as recited in any preceding Claim wherein:

said transmitter unit includes a dedicated function key element and said output means of said transmitter unit transmits a remote control message, on operation of said dedicated key element, identifying such operation; and

said output means of said receiver unit transmits a key function display message for a predetermined step of said control sequence in response to said remote control message identifying the operation of said dedicated key.

5. A remote control system as recited in any of Claims 1-3, wherein:

said transmitter unit includes a dedicated function key element and said output means of said transmitter unit transmit a remote control message, on operation of said dedicated key element, identifying such operation ; and



said output means of said receiver unit transmits
a key function display message including character-
representative information for identifying a predetermined
one of said key elements for controlling said controlled
device.

6. A remote control system substantially as
hereinbefore described with reference to the accompanying
drawings.
