

Description

This invention relates to deflection amplifier circuitry.

In accordance with the invention, a degaussing circuit is responsive to an on-off switch for providing degaussing action during a degaussing interval initiated when the on-off switch is switched to an "on" position. A vertical deflection circuit includes a vertical deflection winding and a capacitor, in which capacitor there is developed a vertical rate voltage during steady-state operation that controls the generation of vertical deflection current in the vertical deflection winding. A DC power supply generates a DC supply voltage that energizes the deflection circuit. The DC power supply is responsive to the on-off switch to generate the DC supply voltage after the on-off switch is switched to the "on" position. The DC supply voltage attains a level adequate to energize the vertical deflection circuit prior to the conclusion of the degaussing interval. A means for charging the capacitor from the DC power supply is provided, that charges the capacitor after the on-off switch is switched to the "on" position at a sufficiently slow rate to delay the generation of vertical deflection current past the conclusion of the degaussing interval.

In the Drawing:

FIGURES 1 and 2 illustrate two different vertical deflection circuits; and

FIGURE 3 illustrates a video display apparatus, embodying the invention, wherein start-up of the vertical deflection circuit is delayed until after completion of degaussing.

In vertical deflection circuit 20 of FIGURE 1, a vertical deflection amplifier 30 comprises output transistor stages Q1 and Q2 coupled together in a push-pull configuration at an amplifier output terminal 22. A vertical deflection winding L_V is coupled to terminal 22. An S-capacitor C1 is coupled to deflection winding L_V at a second terminal 21 remote from output terminal 22. A current sampling resistor R12 is coupled between the lower terminal of capacitor C1 and ground.

The collector of bottom output transistor Q2 is coupled to the base of top output transistor Q1 via a resistor R4 and a diode D4 to form a totem-pole configuration, wherein base drive for top transistor Q1 is shunted through bottom transistor Q2. A resistor R8 is coupled between output terminal 22 and the collector of transistor Q2 to reduce crossover distortion. A diode D3 parallels resistor R8 and becomes conductive during the second half of vertical trace to shunt current away from resistor R8 at large deflection current amplitudes during the second half of trace. This reduces overall power dissipation during the second half of vertical trace and enables a lower DC operating point to be selected for output terminal 22. A +24V supply source is coupled to the collector of transistor Q1 via a small current limiting resistor R6 and a diode

D5.

The control circuitry for deflection amplifier 30 includes a vertical sawtooth generator 23 that develops a vertical rate sawtooth voltage V3 that is AC coupled to the noninverting input terminal of a driver amplifier U1 via a capacitor C4 and a resistor R13. A reference voltage V_{REF} is coupled to the inverting input terminal. The output of driver U1 is coupled to the base of bottom transistor Q2 via resistor R9 of biasing resistors R9 and R14.

A base current generating circuit 40, embodying an aspect of the invention, generates a base current I_1 for top output transistor Q1. Base current generating circuit includes a bootstrap capacitor C2 having a lower terminal coupled to amplifier output terminal 22 at the emitter of transistor Q1 and an upper terminal coupled to the junction of a diode D1 and a resistor R3. Resistor R3 is coupled to the base of transistor Q1. Bootstrap capacitor C2 is charged by a current I_{C2} flowing from terminal 21 via a relatively small valued resistor R2 and diode D1. The value of current I_{C2} is established in accordance with the S-capacitor voltage V1 established at terminal 21. During normal steady-state deflection circuit operation, voltage V1 is a vertical rate parabola voltage, skewed downwardly by the superimposed sawtooth voltage V_s developed across sampling resistor R12.

At the beginning portion of the vertical trace interval T_v , output transistor Q1 is conducting a positive vertical deflection current I_v to charge S-capacitor C1 from the +24V supply via resistor R6 and diode D5. Bootstrap capacitor C2 provides the forward base current for transistor Q1 during the early portions of vertical trace. Near the beginning of vertical trace, deflection amplifier output voltage V2 developed at terminal 22 is sufficiently greater than S-capacitance voltage V1 to reverse bias diode D1 and prevent the recharging of bootstrap capacitor C2.

The decreasing, positive sawtooth portion of vertical deflection current I_v during the first half of vertical trace is produced as a result of the decreasing conduction of top output transistor Q1. In the totem-pole deflection amplifier arrangement, the upwardly ramping sawtooth input voltage V3 is amplified by driver U1 to increase the conduction of bottom output transistor Q2, thereby increasing the amount of current shunted away from the base of transistor Q1 via resistor R4 and diode D4. At some point near the center of vertical trace, transistor Q2 shunts enough base current I_1 to cut off conduction in output transistor Q1.

During the second half of vertical trace, with transistor Q2 conductive, S-capacitor voltage V1 drives vertical deflection current I_v in the negative direction via transistor Q2. Amplifier U1 increases the conduction of transistor Q2 as the second half of vertical trace progresses, to generate the negative portion of the downwardly ramping vertical deflection current.

During the vertical trace interval T_v , output voltage V2 is a downwardly ramping voltage. At some instant after the center of trace, S-capacitor voltage V1 has increased and output voltage V2 has decreased to values which enable diode D1 to become forward biased. At this time, bootstrap capacitor C2 is recharged by current i_{c2} to the S-capacitor voltage V1. With diode D1 conducting, S-capacitor terminal 21 sources currents i_{c2} and i_1 .

When diode D1 first begins conducting after the center of vertical trace, deflection current i_v flows into terminal 21 from S-capacitor C1, and is large enough to be the main source for current i_{c2} . Near the center of trace and during the second half of trace, S-capacitor C1 becomes the main source for current i_{c2} .

To maintain scan linearity, the AC sawtooth sampling voltage V_s , developed across current sampling resistor R12, is summed via a resistor R11 with the 180° out-of-phase sawtooth input voltage V3 at the noninverting input terminal of amplifier U1.

To stabilize the DC operating point of output terminal 22 at a predetermined average value, S-capacitor voltage V1, developed at terminal 21, is DC coupled to the noninverting input terminal of driver U1 via a resistor R10. A negative feedback loop is formed from output terminal 22, that includes deflection winding L_v , terminal 21, driver amplifier U1 and bottom output transistor Q2. Should, for example, S-capacitor voltage V1 tend to decrease, this decrease in voltage is applied to driver U1 to decrease conduction of transistor Q2. Conduction in transistor Q1 is increased to recharge capacitor C1 to its stabilized average value.

To initiate the vertical retrace interval T_r , sawtooth input voltage V3 abruptly decreases, producing the cutoff of bottom output transistor Q2 at the end of trace. A resonant retrace interval is initiated that charges a retrace capacitor C3 coupled across diode D5. When transistor Q2 becomes cut off, output voltage V2 begins to increase due to the inductive kick provided by deflection winding L_v . Voltage V2 forward biases a retrace diode D2 coupled between the base and emitter electrodes of transistor Q1, and forward biases the base-collector path of transistor Q1. Deflection current i_v flows via retrace diode D2 and reverse base-collector conduction into retrace capacitor C3 and the +24 volt supply. Deflection current i_v begins to rapidly ramp up during retrace.

During retrace, when deflection current i_v is negative, bootstrap capacitor C2 is discharged by deflection current i_v via reverse collector conduction of transistor Q1. When deflection current i_v ramps up during retrace through its zero current value, the inductive action of deflection winding L_v decreases output voltage V2 at the emitter of transistor Q1 by an amount that enables diode D2 to become reverse biased. Bootstrap capacitor C2 begins to discharge into the base of top output transistor Q1, maintaining the tran-

sistor in saturated conduction throughout the remainder of the retrace interval.

At the end of vertical retrace, the positive retrace deflection current i_v has increased to a value that enables sawtooth sampling voltage V_s to reestablish drive to bottom output transistor Q2, thereby initiating the subsequent vertical trace interval. With bottom device Q2 conducting, a shunt path is established for current i_1 that bypasses the base of transistor Q1, bringing the transistor out of saturation into the linear mode of operation.

At the end of vertical retrace, some voltage remains in retrace capacitor C3. Capacitor C3 becomes discharged very early within trace by conduction of transistor Q1, after which time diode D5 becomes forward biased.

One terminal of a resistor R7 is coupled to a +131V DC voltage supply of value greater than the +24V supply. The other terminal of resistor R7 is coupled to the junction of the collector of transistor Q1 and retrace capacitor C3. A resistor R5 is coupled across retrace capacitor C3. During the second half of vertical trace, when transistor Q1 is cut off, capacitor C3 is precharged to a voltage level that is established by voltage dividing resistors R7 and R5, coupled between the +131V voltage source and the +24V voltage source, in accordance with the RC time constant associated with the resistors and capacitor C3. The precharged voltage on retrace capacitor C3 at the end of trace provides a more rapid retrace of vertical deflection current i_v , thereby shortening the duration of retrace interval T_r .

S-capacitor voltage V1 is applied to base current generating circuit 40 independently of the DC stabilizing negative feedback loop, to enable the generation of current i_1 when the S-capacitor voltage V1 exceeds a predetermined magnitude.

Base current generating circuit 40 is dependent on S-capacitance voltage V1 as a DC voltage supply source. Should the magnitude of S-capacitance voltage V1 decrease below the predetermined magnitude, base current generating circuit 40 will be unable to generate adequate current i_1 to maintain top output transistor Q1 in conduction. The main charging path for S-capacitor C1 is via top output transistor Q1. When base current generating circuit 40 is unable to supply base current to maintain transistor Q1 conductive, this main charging path will be disabled.

Under certain fault operating situations, it may be desirable for the fault to trigger the disabling of base current generating circuit 40 and of the main charging path to capacitor C1. Such a situation may arise, for example, if S-capacitor C1 becomes short-circuited. When S-capacitor C1 becomes short-circuited, voltage V1 will tend to decrease to zero. The DC negative feedback loop via resistor R10 tries to maintain voltage V1 at its stabilized value by turning bottom output transistor Q2 off, in an attempt to maintain

transistor Q1 conducting heavily. If base current generating circuit 40 were not disabled in such a situation, large current would flow in the main charging path to the now short-circuited S-capacitor via deflection winding L_V , transistor Q1, diode D5 and resistor R6. Excessive dissipation and possible component failure would result. Furthermore, the large unidirectional current flowing in deflection winding L_V would deflect the electron beams of the picture tube by a large angle, permitting the electron beams to strike and possibly damage the neck of the picture tube.

When the S-capacitor voltage decreases below a predetermined magnitude, such as may occur when the S-capacitor becomes short-circuited, voltage V1 becomes too low to provide forward bias to diode D1. Bootstrap capacitor C2 becomes disconnected from its source of charging current, disabling the generation of current i_1 into the base of top output transistor Q1. Without base current, transistor Q1 becomes nonconductive, disabling the main charging path into the short-circuit of capacitor C1, thereby avoiding undesirable short-circuit fault operation of vertical deflection circuit 20.

An auxiliary or second charging path for capacitor C1 is provided directly to a DC voltage supply, bypassing the main charging path of top output transistor Q1 and the vertical deflection winding L_V . A relatively large valued resistor R1 is coupled from a +30V supply to S-capacitor terminal 21. An auxiliary charging current i_0 flows from the +30V supply via resistor R1 to S-capacitor terminal 21.

When the television receiver is first turned on, S-capacitor C1 is initially in a discharged state. When the power supply for the television receiver generates the DC supply voltages such as the +24V, +30V and +131V voltages, S-capacitor C1 begins to charge with current i_0 from the +30V supply via resistor R1. Due to the relatively large value of S-capacitor C1, voltage V1 remains below the predetermined magnitude required during start-up for enabling base current generating circuit 40. During this substantial start-up delay interval, transistor Q1 remains essentially cutoff, disabling the main charging path for capacitor C1 via deflection winding L_V .

When the television receiver is first turned on, the discharged S-capacitor C1 slowly begins to charge with current i_0 from the +30V supply. Voltage V1 begins to increase as C1 charges. As long as voltage V1 is below its normal steady-state value, the DC negative feedback loop maintains transistor Q2 cutoff. No significant current path to ground exists by which bootstrap capacitor C2 may charge.

When S-capacitor C1 has charged sufficiently to permit voltage V1 to increase to approximately or slightly greater than its normal, steady-state value, the DC negative feedback loop turns on transistor Q2, enabling bootstrap capacitor C2 to charge to a value which is capable of forward biasing transistor

Q1. Soon afterwards, normal steady-state deflection circuit operation commences.

During steady-state operation, the value of auxiliary charging current i_0 is determined by the difference in voltage between the +30V supply and the steady-state value of S-capacitor voltage V1. The DC component of current i_0 flows into terminal 21 from the +30V supply. By proper selection of component values, such as the value of resistor R3, the DC component of the current flowing in the current path (R2, D1, R3) equals the DC component of current i_0 . In this situation, no net DC current flows in deflection winding L_V from resistor R1. If the DC component of current i_1 differs from the DC component of current i_0 , the difference current will flow as a DC component in vertical deflection current i_V . This difference current is of relatively small value and may be eliminated, if so desired, by proper adjustment of a DC centering control circuit for deflection winding L_V , not illustrated in FIGURE 1.

For the values given in the circuit of FIGURE 1, the start-up delay time for the generation of vertical deflection current is approximately one to two seconds. The start-up delay advantageously permits completion of picture tube degaussing before the generation of vertical deflection current, thereby avoiding any undesirable interaction between the vertical deflection magnetic field and the degaussing process.

FIGURE 3 illustrates a portion of a video display apparatus 60, embodying an aspect of the invention, that includes a picture tube degaussing circuit 10 and vertical deflection circuit 20 of FIGURE 1, wherein start-up of the vertical deflection circuit is delayed until after completion of degaussing. Vertical deflection circuit 20 of FIGURE 1 is shown in FIGURE 3 in partial detail only.

In FIGURE 3, an AC mains supply, developing a voltage V_{AC} , energizes a DC power supply 16 when an on-off switch 15 is conductive, or switched to the on-position. DC power supply 16 develops various DC supply voltages for the circuitry of video display apparatus 60 including a +DC1, a +DC2, a +DC3 and a +DC4 voltage. Voltage +DC4, for example, energizes a horizontal deflection circuit 17 to generate horizontal deflection current in a horizontal deflection winding L_H .

Degaussing circuit 10 includes a degaussing coil DG located adjacent a picture tube 50 of video display apparatus 60. Degaussing coil DC is coupled in series with a positive temperature coefficient thermistor 13, AC mains supply 14 and the mechanical switch portion of an electro-mechanical degaussing relay 11. The mechanical switch portion of relay 11 is normally non-conductive when the relay coil is deenergized.

To initiate a degaussing interval, when degaussing action takes place, on-off switch 15 is made con-

ductive to permit DC power supply 16 to develop the DC supply voltages, including the +DC1 supply voltage. The +DC1 supply voltage is coupled via a charging capacitor 12 to the coil of relay 11. Current flows in the relay coil from the +DC1 supply, energizing the relay coil and closing the mechanical switch portion of degaussing relay 11. With the mechanical switch portion of relay 11 conductive, AC degaussing current flows from AC mains supply 14 in degaussing coil DG and thermistor 13 at the frequency of AC mains voltage V_{AC} . As thermistor 13 self-heats by the degaussing current, its resistance increases producing a decaying alternating degaussing current that reaches a very low residual amplitude, bringing the degaussing interval to a conclusion. The decaying alternating degaussing current produces a decaying alternating degaussing magnetic field that degausses the shadow mask, magnetic shield and other magnetizable material associated with picture tube 50, but not illustrated in FIGURE 3. After conclusion of the degaussing interval, series capacitor 12 charges to the +DC1 supply level, preventing current from flowing in the coil of relay 11. The mechanical switch portion of relay 11 returns to its normally non-conductive position to eliminate the flow of even a residual current in degaussing coil DG after conclusion of the degaussing interval.

The DC supply voltages developed by power supply 16 are rapidly developed from a zero voltage level after on-off switch 15 is made conductive. In particular, the DC supply voltages developed for vertical deflection circuit 20 attain levels adequate to energize the vertical deflection circuit prior to the conclusion of the degaussing interval.

Advantageously, however, capacitor C1, whose voltage V1 controls operation of vertical deflection circuit 20, disables base current generator 40 to prevent the generation of vertical deflection current in vertical deflection winding L_V immediately after on-off switch 15 is closed. Capacitor C1 is slowly charged from the +DC3 supply via resistor R1 to delay the enablement of base current generating circuit 40 and thus to delay the generation of vertical deflection current until after conclusion of the degaussing interval. This delay avoids any undesirable interaction between the vertical deflection magnetic field and the degaussing process.

FIGURE 2 illustrates a vertical deflection circuit 120, embodying the invention, similar to the vertical deflection circuit of FIGURE 1, but modified to reduce any net DC current that may flow through deflection winding L_V from auxiliary charging current i_0 . Items in FIGURES 1 and 2 similarly identified represent similar elements or quantities.

In FIGURE 2, a controllable impedance, a transistor Q3, is interposed between base current generating circuit 40 and the +30V supply, with the collector of the transistor coupled to the +30V supply and the emitter coupled to resistor R2. The base of transistor

Q3 is coupled to S-capacitor second terminal 21 at the junction of charging resistor R1 and S-capacitor C1. The S-capacitor voltage V1 controls the conductivity of transistor Q3 and the amount of current flowing in the collector circuit of transistor Q3 to base current generating circuit 40.

Should capacitor C1 become short-circuited and voltage V1 decrease to near zero, transistor Q3 becomes cut off, disconnecting the +30V supply from base current generating circuit 40, and disabling the generation of current i_1 into the base of top output transistor Q1. Similarly during start-up, because capacitor C1 is initially discharged, transistor Q3 is cut off to disable top output transistor Q1. The auxiliary charging current i_0 charges capacitor C1 after a start-up delay to the value needed to turn on transistor Q3 for enabling base current generating circuit 40. Because of the gain provided by transistor Q3, charging current i_0 may be relatively small, and the net DC current component introduced into deflection winding L_V by current i_0 is negligible.

Claims

1. Video display apparatus, comprising:
 - an on-off switch;
 - a degaussing circuit (10) responsive to said on-off switch for providing degaussing action during a degaussing interval initiated when said on-off switch is switched to an on-position;
 - a vertical deflection circuit (20) including a vertical deflection winding and a capacitor in which capacitor there is developed a vertical rate voltage during steady state operation that controls the generation of vertical deflection current in said deflection winding, start-up of the vertical deflection circuit being delayed until after completion of degaussing; characterized by
 - a DC power supply (16) for generating a DC supply voltage (+DC2) that energizes said deflection circuit (20), said DC power supply (16) being responsive to said on-off switch (15) to generate said DC supply voltage (+DC2) after said on-off switch (15) is switched to the on-position, said DC supply voltage (+DC2) attaining a level adequate to energize said vertical deflection circuit (20) prior to conclusion of said degaussing interval; and
 - means (+DC3, R1) for charging said capacitor (C1) from said DC power supply (16), after said on-off switch (15) is switched to the on-position, at a sufficiently slow rate to delay the generation of said vertical deflection current past the conclusion of said degaussing interval.



ductive to permit DC power supply 16 to develop the DC supply voltages, including the +DC1 supply voltage. The +DC1 supply voltage is coupled via a charging capacitor 12 to the coil of relay 11. Current flows in the relay coil from the +DC1 supply, energizing the relay coil and closing the mechanical switch portion of degaussing relay 11. With the mechanical switch portion of relay 11 conductive, AC degaussing current flows from AC mains supply 14 in degaussing coil DG and thermistor 13 at the frequency of AC mains voltage V_{AC} . As thermistor 13 self-heats by the degaussing current, its resistance increases producing a decaying alternating degaussing current that reaches a very low residual amplitude, bringing the degaussing interval to a conclusion. The decaying alternating degaussing current produces a decaying alternating degaussing magnetic field that degausses the shadow mask, magnetic shield and other magnetizable material associated with picture tube 50, but not illustrated in FIGURE 3. After conclusion of the degaussing interval, series capacitor 12 charges to the +DC1 supply level, preventing current from flowing in the coil of relay 11. The mechanical switch portion of relay 11 returns to its normally non-conductive position to eliminate the flow of even a residual current in degaussing coil DG after conclusion of the degaussing interval.

The DC supply voltages developed by power supply 16 are rapidly developed from a zero voltage level after on-off switch 15 is made conductive. In particular, the DC supply voltages developed for vertical deflection circuit 20 attain levels adequate to energize the vertical deflection circuit prior to the conclusion of the degaussing interval.

Advantageously, however, capacitor C1, whose voltage V1 controls operation of vertical deflection circuit 20, disables base current generator 40 to prevent the generation of vertical deflection current in vertical deflection winding L_v immediately after on-off switch 15 is closed. Capacitor C1 is slowly charged from the +DC3 supply via resistor R1 to delay the enablement of base current generating circuit 40 and thus to delay the generation of vertical deflection current until after conclusion of the degaussing interval. This delay avoids any undesirable interaction between the vertical deflection magnetic field and the degaussing process.

FIGURE 2 illustrates a vertical deflection circuit 120, embodying the invention, similar to the vertical deflection circuit of FIGURE 1, but modified to reduce any net DC current that may flow through deflection winding L_v from auxiliary charging current i_0 . Items in FIGURES 1 and 2 similarly identified represent similar elements or quantities.

In FIGURE 2, a controllable impedance, a transistor Q3, is interposed between base current generating circuit 40 and the +30V supply, with the collector of the transistor coupled to the +30V supply and the emitter coupled to resistor R2. The base of transistor

Q3 is coupled to S-capacitor second terminal 21 at the junction of charging resistor R1 and S-capacitor C1. The S-capacitor voltage V1 controls the conductivity of transistor Q3 and the amount of current flowing in the collector circuit of transistor Q3 to base current generating circuit 40.

Should capacitor C1 become short-circuited and voltage V1 decrease to near zero, transistor Q3 becomes cut off, disconnecting the +30V supply from base current generating circuit 40, and disabling the generation of current i_1 into the base of top output transistor Q1. Similarly during start-up, because capacitor C1 is initially discharged, transistor Q3 is cut off to disable top output transistor Q1. The auxiliary charging current i_0 charges capacitor C1 after a start-up delay to the value needed to turn on transistor Q3 for enabling base current generating circuit 40. Because of the gain provided by transistor Q3, charging current i_0 may be relatively small, and the net DC current component introduced into deflection winding L_v by current i_0 is negligible.

Claims

1. Video display apparatus, comprising:
 - an on-off switch;
 - a degaussing circuit (10) responsive to said on-off switch for providing degaussing action during a degaussing interval initiated when said on-off switch is switched to an on-position;
 - a vertical deflection circuit (20) including a vertical deflection winding and a capacitor in which capacitor there is developed a vertical rate voltage during steady state operation that controls the generation of vertical deflection current in said deflection winding, start-up of the vertical deflection circuit being delayed until after completion of degaussing; characterized by
 - a DC power supply (16) for generating a DC supply voltage (+DC2) that energizes said deflection circuit (20), said DC power supply (16) being responsive to said on-off switch (15) to generate said DC supply voltage (+DC2) after said on-off switch (15) is switched to the on-position, said DC supply voltage (+DC2) attaining a level adequate to energize said vertical deflection circuit (20) prior to conclusion of said degaussing interval; and
 - means (+DC3, R1) for charging said capacitor (C1) from said DC power supply (16), after said on-off switch (15) is switched to the on-position, at a sufficiently slow rate to delay the generation of said vertical deflection current past the conclusion of said degaussing interval.



Patentansprüche

1. Video-Darstellungseinrichtung, enthaltend:

- einen Ein/Aus-Schalter; 5
- eine Entmagnetisierungs-Schaltung (De- 10
gaussing-Circuit; 10), die auf den Ein/Aus-
Schalter zum Bereitstellen einer Entma-
gnetisierungs-Wirkung während eines
Entmagnetisierungs-Intervalls anspricht, das
bei Sinschalten des Ein/Aus-Schalters ein-
geleitet wird; 10
- eine Vertikal-Ablenkschaltung (20), die ei- 15
ne Vertikal-Ablenkwicklung und einen Kon-
densator enthält, an dem eine Vertikalra-
ten-Spannung während des Betriebs im
stationären Zustand gebildet wird, die das
Erzeugen von Vertikal-Ablenkstrom in der
Ablenkwicklung steuert, wobei das Anlau-
fen der Vertikal-Ablenkschaltung bis nach
Beendigung der Entmagnetisierung verzö- 20
gert wird;
gekennzeichnet durch
- eine Gleichspannungs-Versorgung (16) zur 25
Erzeugung einer Versorgungs-Gleichspan-
nung (+DC2), die die Ablenkschaltung (20)
versorgt/aktiviert und die (16) auf den
Ein/Aus-Schalter (15) anspricht, um die
Versorgungs-Gleichspannung (+DC2) nach
Einschalten des Ein/Aus-Schalters (15)
zu erzeugen, wobei die Versorgungs- 30
Gleichspannung (+DC2) einen Pegel er-
reicht, der ausreicht, die Vertikal-Ablenk-
schaltung (20) vor Beendigung des
Entmagnetisierungs-Intervalls zu aktivie-
ren/versorgen; und 35
- ein Mittel (+DC3, R1) zum Aufladen des 40
Kondensators (C1) aus der Gleichversor-
gung (16) nach dem Einschalten des
Ein/Aus-Schalters (15) mit einer genügend
geringen Steigung, um die Erzeugung des
Vertikal-Ablenkstroms bis hinter das Ende
des Entmagnetisierungs-Intervalls zu ver-
zögern. 45

Revendications

1. Dispositif d'affichage vidéo, comprenant:

- un commutateur de marche-arrêt ;
- un circuit de démagnétisation (10), sensi- 50
ble audit commutateur de marche-arrêt pour four-
nir un effet de démagnétisation pendant un inter-
valle de démagnétisation initié lorsque ledit
commutateur de marche-arrêt est commuté vers
une position marche ; 55
- un circuit de déviation verticale (20),
comprenant un enroulement de déviation vertica-
le et un condensateur dans lequel est développée

une tension de vitesse verticale pendant le fon-
ctionnement en régime permanent qui commande
la production d'un courant de déviation verticale
dans ledit enroulement de déviation, le démarra-
ge du circuit de déviation verticale étant retardé
jusqu'après l'achèvement de la démagnétisa-
tion ; caractérisé par

une alimentation électrique en continu
(16) pour produire une tension d'alimentation
continue (+DC2) qui active ledit circuit de dévia-
tion (20), ladite alimentation électrique en conti-
nu (16) étant sensible audit commutateur de mar-
che-arrêt (15) pour produire ladite tension d'ali-
mentation continue (+DC2) après que ledit
commutateur de marche-arrêt (15) est commuté
vers la position marche, ladite tension d'alimenta-
tion continue (+DC2) atteignant un niveau conve-
nable pour activer ledit circuit de déviation verti-
cale (20) avant l'achèvement dudit intervalle de
démagnétisation ; et

des moyens (+DC3, R1) pour charger ledit
condensateur (C1) à partir de ladite alimentation
électrique en continu (16), après que ledit
commutateur de marche-arrêt (15) est commuté
vers la position marche, à une vitesse suffisam-
ment lente pour retarder la formation dudit cou-
rant de déviation verticale après l'achèvement
dudit intervalle de démagnétisation.