Description

This invention relates to methods of and apparatus for focusing servo control.

It is known practice to read data recorded on an optical disc recording track by applying a laser beam through an objective lens which focuses a light spot on the recording track. In order to provide clear data recognition, the objective lens should be adjusted, with great accuracy, at a proper position with respect to the optical disc recording track. For this purpose, a measured deviation of the actual objective lens position from the optimum objective lens position is converted into a focusing error signal which is applied to a closed loop focusing servo circuit operable to reduce the focusing error signal to zero. Various methods, which include an astigmatic method, a knife edge method, a Foucault prism method, a critical angle method and the like, have been proposed to produce such a focusing error signal. In any one of these methods, a light beam reflected from the optical disc is applied through a lens which focuses a light spot on divided portions of a photoelectric converter. However, the reflected light beam includes 0-order and ± first-order diffraction beams which interfere in the photoelectric converter. Each time the light spot traverses the optical disc recording track, the intensities of the 0-order and ± first-order diffraction beams change greatly and thereby superimpose a significant disturbance on the focusing error signal. This disturbance has a serious influence on the focusing servo control in a direction which saturates the dynamic range of the focusing servo circuit thereby placing the focusing servo control into a lock-off condition, particularly during an access mode of operation for searching information recorded on the optical disc recording track.

According to one aspect of the invention there is provided a focusing control method utilising a photodetector for generating a focusing error signal, a tracking error signal and an RF signal, and a closed loop focusing servo circuit responsive to the focusing error signal applied thereto for focusing a light spot in position on an optical disc, the method being characterised by the steps of:

detecting the focusing error signal synchronously with the tracking error signal to produce a first periodic function signal;

detecting the focusing error signal synchronously with the RF signal to produce a second periodic function signal;

converting the tracking error signal into a sine-wave signal having a predetermined amplitude;

converting the RF signal into a cosine-wave signal having a predetermined amplitude;

multiplying the first periodic function signal by the cosine-wave signal to produce a first component signal;

multiplying the second periodic function signal by the sine-wave signal to produce a second component signal;

adding the first and second component signals to produce a composed disturbance signal; and

subtracting the composed disturbance signal from a signal containing the focusing error signal applied to said focusing servo circuit, thereby cancelling a disturbance superimposed on said signal containing the focusing error signal applied to the focusing servo circuit.

According to another aspect of the invention there is provided focusing control apparatus comprising:

a photodetector for generating a focusing error signal, a tracking error signal and an RF signal;

a closed loop focusing servo circuit responsive to the focusing error signal applied thereto for focusing a light spot in position on an optical disc; said apparatus being characterised by:

a cancelling signal generator connected to said photodetector for producing a cancelling signal, said cancelling signal generator including means for detecting the focusing error signal synchronously with the tracking error signal to produce a first periodic function signal, means for detecting the focusing error signal synchronously with the RF signal to produce a second periodic function signal, means for converting the tracking error signal into a sine-wave signal having a predetermined amplitude, means for converting the RF signal into a cosine-wave signal having a predetermined amplitude, means for multiplying the first periodic function signal by the cosine-wave signal to produce a first component signal, means for multiplying the second periodic function signal by the sine-wave signal to produce a second component signal, and means for adding the first and second component signals to produce the cancelling signal; and

said focusing servo circuit including means connected to said cancelling signal generator for subtracting the cancelling signal from a signal containing the focusing error signal applied to said focusing servo circuit, thereby cancelling a disturbance superimposed on said signal containing the focusing error signal applied to the focusing servo circuit.

A focusing servo control method and apparatus embodying the invention, and to be described in greater detail hereinafter, is effective to cancel a disturbance which may be superimposed on the focusing error signal provided for the focusing servo circuit, and is operable to reduce the focusing error signal to zero, particularly when an optical pickup traverses a recording track such as during an access mode of operation.

The invention will now be described by way of example with reference to the accompanying drawings, throughout which like parts are referred to by like references, and in which:

Fig. 1 is a block diagram of a closed loop focusing servo circuit for use in explaining the principles of the invention;

Fig. 2 is a graph of frequency versus gain and time delay representing the characteristics of the closed loop focusing servo circuit shown in Fig. 1;

Fig. 3 contains views for use in explaining an astigmatic method of operation of the circuit shown in Fig. 1;

Fig. 4 is a diagram showing the diffraction beams included in a light beam reflected from an optical disc;

Fig. 5 is a diagram showing a light spot projected on a photodetector;

Fig. 6 is a graph of frequency versus gain and time delay for use in explaining the offset residual on the focusing error signal;

Fig. 7 is a graph of frequency versus gain and time delay for use in explaining the offset residual on the drive signal;

Fig. 8 shows a waveform of the focusing error signal;

Fig. 9 shows a waveform of the drive signal;

Fig. 10 shows three waveforms for use in explaining the production of a periodic function signal;

Fig. 11 shows three waveforms for use in explaining the production of another periodic function signal;

Fig. 12 shows three waveforms for use in explaining the production of a first component signal;

Fig. 13 shows three waveforms for use in explaining the production of a second component signal;

Fig. 14 shows three waveforms for use in explaining a disturbance cancelling operation;

Fig. 15 is a block diagram showing a focusing control apparatus in accordance with one embodiment of the invention; and

Fig. 16 shows two waveforms of the focusing error and drive signals obtained in the presence of a significant disturbance on the focusing error signal; and

Fig. 17 shows two waveforms of the focusing error and drive signals obtained after the disturbance has been cancelled.

Prior to the description of the preferred embodiment of the invention, the principle of the invention will be briefly described in order to provide a basis for a better understanding of the invention.

Referring to Fig. 1, there is shown a closed loop focusing servo circuit 10 to which a target signal R(S) is applied. The target signal R(S) corresponds to a deflection of a surface of an optical disc, or an upward or downward change of position of the disc surface. The target signal R(S) is coupled to an input of an adder 11 having another input at which it receives a feedback signal X(S) indicative of a change of position of the objective lens. The adder 11 subtracts the feedback signal X(S) from the target signal R(S) and generates an error signal indicative of a change of position of the objective lens relative to the disc. The error signal is applied to a photoelectric converter 12 which converts the error signal into a corresponding electrical signal. The electrical signal is fed to a focusing error detector 13. The focusing error detector 13 generates a focusing error signal E(S) to a phase compensating circuit 14 which generates a drive signal D-(S). The drive signal D(S) is applied to a focusing actuator 15 which thereby moves the objective lens with respect to the disc surface in a direction tending to achieve the target position. The characters $G_{AS(S)}$, $G_{C1(S)}$, $G_{C2(S)}$, and $G_{D(S)}$ designate the gains or sensitivities of the respective components 12, 13, 14 and 15. The characteristics of the closed loop control circuit of Fig. 1 are shown in Fig. 2, where G(S) is the closed loop gain given as $G_{AS(S)} \times G_{C1(S)} \times G_{C2(S)} \times G_{D(S)}$ and θ is the phase delay.

A disturbance W(S) is shown schematically as being introduced into the signal to the focusing error detector 13, by a corresponding circuit block 17 and an adder 16. The disturbance W(S) is produced due to the interference between the 0-order and ± first-order diffraction beams in the light beam reflected from the optical disc. The disturbance introduced into the focusing error signal E(S) has a serious influence on the focusing error signal E(S) and the drive signal D(S) in a direction acting to saturate the dynamic range of the focusing servo circuit to place the focusing servo control into a lock-off condition.

The mechanism by which the disturbance W(S) is introduced will be described in greater detail under the assumption that the focusing error signal E(S) is obtained according to an astigmatic method as shown in Fig. 3(a), which utilises a photodetector placed at a position P_1 between two astigmatic points P_2 and P_3 of a light beam which is reflected from the optical disc and has passed through a cylindrical lens L. As shown in Fig. 3(b), the photodetector P has four divided portions I, II, III and IV, separated from one another. The shape and position of the relected light spot formed on the photodetector P is dependent upon the distance between the optical disc and the objective lens. In Fig. 3(b), the character S_0 indicates a circular light spot formed on the photodetector P when the objective lens is positioned in focus with respect to the optical disc, the character S_N indicates an elliptical light spot formed on the photodetector P when the

objective lens is at a shorter distance from the optical disc, and the character S_F indicates an elliptical light spot formed on the photodetector P when the objective lens is at a longer distance from the optical disc. When a light spot is formed on the photodetector P, currents I_I, I_{II}, I_{III} and I_{IV} are derived from the respective divided portions I, II, III and IV of the photodetector P. The focusing error signal E(S) is obtained in accordance with the expression $E(S) = (I_I + I_{III}) - (I_{II} + I_{IV})$.

The disturbance W(S) is introduced into the focusing error signal E(S) due to the diffraction of the light beam reflected from the optical disc, as shown in Fig. 4, where the light beam reflected from the optical disc is diffracted and includes 0-order and ± first-order diffraction beams, these diffraction beams having intensities dependent on the position of the light spot with respect to the recording track. This is true particularly for an optical disc of the data writing type formed with grooves G. The 0-order and ± first-order diffraction beams interfere on the photodetector P, as shown in Fig. 5, where the character a indicates the area where the 0-order and + first-order diffraction beams interfere, the character b indicates the area where the 0-order and - first-order diffraction beams interfere, and the character c indicates the area on which only the 0-order diffraction beam impinges. Even a small deviation of the reflected light spot S from the centre of the photodetector P causes a significant increase in the disturbance. The reflected light spot S will deviate from the centre of the photodetector P due to optical system offset, disc skew, or various astigmatic perturbations. The disturbance level changes each time the light spot traverses the recording track. Particularly during an access mode of operation for searching recorded information, a significant disturbance is introduced into the focusing error signal, causing saturation of the servo circuit dynamic range and thereby placing the focusing servo control into a lock-off condition.

The influence of the introduced disturbance on the focusing error signal E(S) and the drive signal D(S) may be expressed as:

$$E(S) = \frac{G_{C1}(S)}{1 + G(S)} .W(S) \quad \ldots\ldots (1)$$

$$D(S) = \frac{G_{C1}(S) \times G_{C2}(S)}{1 + G(S)} .W(S) \quad \ldots\ldots (2)$$

Figs. 6 and 7 show the residual offset transfer characteristics for the ratios E(S)/W(S) and D(S)/W(S), respectively, in the presence of a disturbance W(s) introduced into the closed loop control circuit of Fig. 1. It will be seen that the gain for the ratio D(S)/W(S) is about 20 dB greater than the gain for the ratio E(S)/W-(S) at frequencies greater than 10 kHz. The reason for this is that the drive signal D(S) is produced at the output of the phase compensating circuit 13 to which the focusing error signal E(S) is applied.

Fig. 8 shows an output signal waveform which may occur at the output of the focusing error detector 13 when the introduced disturbance has a frequency around 10 kHz. Such a focusing error signal E(S) is applied to the phase compensating circuit 14 where it is amplified, as can be seen from the transfer characteristic curve of Fig. 7, to exceed the dynamic range. The result is that the drive signal D(S) saturates at voltages exceeding the power source voltages as shown in Fig. 9. This saturation places the focusing servo control into a lock-off condition to bring the objective lens to a defocus position.

The disturbance W(S) introduced into the closed loop control circuit will be described in greater detail.

Assuming that the pupil function corresponds to a uniform circular opening, the following equations provide proper approximations of light intensities Ia, Ib and Ic on the respective areas a, b and c:

$$\left.\begin{aligned} Ia &= A + 2B\cos(\phi + 2\pi v/q) \\ Ib &= A + 2B\cos(\phi - 2\pi v/q) \\ Ic &= C \end{aligned}\right\} \quad \ldots\ldots (3)$$

where A is the sum of the light intensities of the 0-order diffraction beam R(0) and the ± first order diffraction beams R(±1) and expressed as $A = |R(0)|^2 + |R(+1)|^2$,B is the product of the 0-order diffraction beam R(0) and the ± first order diffraction beams R(±1) and expressed as $B = |R(0)| \times |R(\pm 1)|$,C is the light intensity of the 0-order diffraction beam R(0) and expressed as $C = |R(0)|^2$,ϕ is the phase

difference between the 0-order diffraction beam R(0) and the + or - first order diff raction beam and expressed as exp[iϕ] ={R(0) x R(±1)^{C}}/{ | R(0) | x | R(±1)^{C} |},q is the optical disc track pitch, and v is the position of the light spot relative to the centre of the optical disc.

It can be seen from these equations that, each time the light spot traverses the recording track or groove, the light intensity Ia on the area a changes in a positive or negative direction with respect to a constant value A and the light intensity Ib on the area b changes with respect to the constant value A in a direction opposite to the direction of change of the light intensity Ia, whereas the light intensity Ic on the area c is held substantially at a constant value C.

According to the astigmatic method, a focusing error signal FE is provided in such a manner as expressed by the following equation:

$$FE = (I_I + I_{III}) - (I_{II} + I_{IV}) \quad (4)$$

where I_I, I_{II}, I_{III} and I_{IV} are the currents obtained from the respective divided photodetector portions I, II, III and IV.

Using equations (3) which express the light intensities on the areas a, b and c, equation (4) is rewritten as:

$$FE = D + (E - F)\sin\phi\,\sin(2\pi v/q) + (E + F)\cos\phi\,\cos(2\pi v/q) \quad (5)$$

where E is the value corresponding to the product of 2B and the difference of the area a on the divided photodetector portions I and III from the area a on the divided photodetector portions II and IV, F is the value corresponding to the product of 2B and the difference of the area b on the divided photodetector portions I and III from the area b on the divided photodetector portions II and IV, and D is the product of A, B and the difference of the area a, b and c on the divided photodetector portions I and III from the areas a, b and c on the divided photodetector portions II and IV. The value D is approximately zero.

Therefore, equation (5) is simplified as:

$$FE = M\sin(2\pi v/q + \Psi_1) \quad (6)$$

where

$$M = \sqrt{(E - F)^2 \sin^2 \phi + (E + F)^2 \cos^2 \phi}, \text{ and}$$

$$\Psi_1 = \tan^{-1}[(E + F)/((E - F) \times \tan\phi)].$$

Since equation (6) expresses the focusing error signal FE when R(S) = 0; that is, when the light spot is in focus on the optical disc, it also expresses the disturbance W(S) introduced into the closed loop control circuit 10. Such a disturbance W(S) occurs particularly when the light spot is offset from the centre of the photodetector P and changes due to disc skew. Although the disturbance W(S) cannot be measured directly in the closed loop control circuit, it presents a residual offset on the focusing error signal E(S), as shown in Fig. 8.

The residual offset transfer characteristic E(S)/W(S) can be expressed as:

$$E(S)/W(S) = G(\omega).\exp[j\Psi_2(\omega)] \quad (7)$$

This equation is rewritten as:

$$E(S) = MG(\omega)\sin[2\pi v/q + \Psi_1 + \Psi_2(\omega)] \quad (8)$$

The gain $G(\omega)$ and the Phase $\Psi_2(\omega)$ vary with variations in frequency, as shown in Fig. 6.

Equation (8) can be expanded in the following form:

$$E(S) = MG(\omega)\cos[\Psi_1 + \Psi_2(\omega)]\sin(2\pi v/q) + MG(\omega)\sin[\Psi_1 + \Psi_2(\omega)]\cos(2\pi v/q) \quad (9)$$

and

$$E(S) = \alpha(\omega)\sin(2\pi v/q) + \beta(\omega)\cos(2\pi v/q) \quad (10)$$

where

$$a(\omega) = MG(\omega)\cos[\Psi_1 + \Psi_2(\omega)]$$
$$\beta(\omega) = MG(\omega)\sin[\Psi_1 + \Psi_2(\omega)]$$

It can be seen from equation (10) than the disturbance W(S) introduced into the closed loop control circuit 10 can be measured from the measurements of the periodic functions $\alpha(\omega)$ and $\beta(\omega)$. Description will be made of the measurement of the disturbance W(S).

As well known in the art, the tracking error signal is zero when the light spot is on the track formed on the optical disc and has a positive or negative value when the light spot is offset from the track. When the light spot traverses the recording track, for example, during an access mode of operation, the tracking error signal TE is expressed as:

$$TE = V_T \sin(2\pi v/q)$$

where q is the track pitch and v is the position of the light spot with respect to the centre of the optical disc.

The main or RF signal obtained from the photodetector during such an access mode is at maximum when the light spot is on the recording track and thus the tracking error signal TE is at minimum. The RF signal is expressed as:

$$RF = V_R \cos(2\pi v/q)$$

Referring to equation (10), the following conditions occur when $\cos(2\pi v/q) = 0$:

i) when $v = q/4$, $\sin(2\pi v/q) = 1$and thus $E(S) = \alpha(\omega)$
ii) when $v = 3q/4$, $\sin(2\pi v/q) = -1$and thus $E(S) = -\alpha(\omega)$
iii) when $v = 0$, $\cos(2\pi v/q) = 1$and thus $E(S) = \beta(\omega)$,and
iv) when $b = q/2$, $\cos(2\pi v/q) = -1$and thus $E(S) = -\beta(\omega)$

If the focusing error signal E(S) is sampled and held when $\cos(2\pi v/q) = 0$;that is, when the main or RF signal is zero, the sampled value will correspond to the periodic function $\alpha(\omega)$ or $-\alpha(\omega)$. The polarity of the focusing error signal E(S) is reversed to obtain the periodic function signal $\alpha(\omega)$ when $v = 3q/4$;that is, when the polarity of the tracking error signal TE is negative. Similarly, if the focusing error signal E(S) is sampled and held when $\sin(2\pi v/g) = 0$;that is, when the tracking error signal TE is zero, the sampled value will correspond to the periodic function $\beta(\omega)$ or $-\beta(\omega)$. The polarity of the focusing error signal E(S) is reversed to obtain the periodic function signal $\beta(\omega)$ when the polarity of the AC component of the main or RF signal is negative.

Fig. 10 shows several waveforms obtained at the outputs of the photodetector while the light spot is traversing the recording track or groove formed on the optical disc which is placed in a somewhat eccentric manner. The waveform 10a relates to the focusing error signal FE, the waveform 10b relates to the main or RF signal, and the waveform 10c relates to the tracking error signal TE. The time interval t-t indicates the time required for a full rotation of the optical disc. The illustrated focusing error signal FE has a major portion residual due to the disturbance introduced thereon when the light spot traverses the recording track or groove. It is apparent from Fig. 10 that the main or RF signal is expressed as $\cos(2\pi v/q)$and the tracking error signal is expressed as $\sin(2\pi v/q)$.It is, therefore, possible to obtain the periodic function signal $\alpha(\omega)$ by sampling the focusing error signal FE each time the main or RF signal crosses zero and reversing the polarity of the sampled value if the tracking error signal TE is negative at the sampling time. The bold curve on the waveform 10a indicates the resulting periodic function signal $\alpha(\omega)$.

Fig. 11 shows several waveforms obtained at the outputs of the photodetector while the light spot is traversing the recording track or groove formed on the optical disc. The waveform 11a relates to the focusing error signal FE, the waveform 11b relates to the tracking error signal TE, and the waveform 11c relates to the main or RF signal. The time interval t-t indicates the time required for a full rotation of the optical disc. It is possible to obtain the periodic function signal $\beta(\omega)$ by sampling the focusing error signal

FE each time the tracking error signal TE crosses zero and reversing the polarity of the sampled value if the polarity of the main or RF signal is negative. The bold curve on the waveform 11a indicates the resulting periodic function signal $\beta(\omega)$.

As can be seen from equation (10), the disturbance W(S) can be obtained by multiplying the periodic function signal $\alpha(\omega)$ by $\sin(2\pi v/q)$,multiplying the periodic function signal $\beta(\omega)$ by $\cos(2\pi v/q)$,and adding these products. It will be understood that $\sin(2\pi v/q)$corresponds to the tracking error signal TE having a constant amplitude, for example 1, and $\cos(2\pi v/q)$corresponds to the main or RF signal having a constant amplitude, for example 1.

Referring to Fig. 12, the waveform 12a relates to the periodic function signal $\alpha(\omega)$ which is multiplied by the tracking error signal TE, as shown by the waveform 12b, to produce a first disturbance component $\alpha(\omega)\cdot\sin(2\pi v/q)$,as shown by the waveform 12c.

Referring to Fig. 13, the waveform 13a relates to the periodic function signal $\beta(\omega)$ which is multiplied by the main or RF signal, as shown by the waveform 13b, to produce a second disturbance component $\beta(\omega)\cdot\cos(2\pi v/q)$,as shown by the waveform 13c.

The produced first and second disturbance components are added to obtain a composed disturbance W'(S). A signal indicative of the composed disturbance is applied to the adder 18 of the closed loop control circuit 10 so as to cancel the disturbance W(S) superimposed on the focusing error signal E(S) in order to obtain the primary focusing error signal E(S).

Referring to Fig. 14, the waveform 14a relates to the focusing error signal FE from which the composed disturbance W'(S), as shown by the waveform 14b, is subtracted to provide a primary focusing error signal E(S), as shown by the waveform 14c.

Although the composed disturbance is not equal completely to the disturbance superimposed on the focusing error signal E(S) since the composed disturbance is obtained by sampling the focusing error signal FE at time intervals, the difference is too small to saturate the closed loop focusing servo circuit, resulting in a focusing lock-off condition.

Returning to Fig. 1, a disturbance cancelling circuit, generally designated by the numeral 20, includes first and second synchronous detectors 20a and 20b. The first synchronous detector 20a detects the focusing error signal FE synchronously with the tracking error signal TE to produce a periodic function signal $\beta(\omega)$ which corresponds to the signal shown by the waveform 13a of Fig. 13. The periodic function signal $\beta(\omega)$ is applied to a first multiplier circuit 28a to which the RF signal having a constant amplitude is applied. The RF signal corresponds to the signal shown by the waveform 13b of Fig. 13. The first multiplier circuit 28a multiplies the periodic function signal $\beta(\omega)$ by the RF signal to produce a first signal which corresponds to the signal shown by the waveform 13c of Fig. 13. The second synchronous detector 20b detects the focusing error signal synchronously with the RF signal to produce a periodic function signal $\alpha(\omega)$ which corresponds to the signal shown by the waveform 12a of Fig. 12. The periodic function signal $\alpha(\omega)$ is applied to a second multiplier circuit 28b to which the tracking error signal TE having a constant amplitude is applied. The tracking error signal TE corresponds to the signal shown by the waveform 12b of Fig. 12. The second multiplier circuit 28b multiplies the periodic function signal $\alpha(\omega)$ by the tracking error signal TE to produce a second signal which corresponds to the signal shown by the waveform 12c of Fig. 12. The first and second signals are applied to an adder circuit 30 where they are added to produce a signal indicative of a composed disturbance W'(S) which corresponds to the waveform 14b of Fig. 14. The composed disturbance indicative signal W'(S) is applied through a switch 31 to the adder circuit 18 interposed between the focusing error detector 13 and the phase compensating circuit 14 of the focusing servo circuit 10 in order to cancel the disturbance W(S) introduced on the focusing error signal FE. The switch 31 is closed when the tracking control is off.

Referring to Fig. 15, there is illustrated one embodiment of a focusing servo circuit in accordance with the invention. Like reference numerals have been applied to Fig. 15 with respect to the equivalent components shown in Fig. 1. The disturbance cancelling circuit 20 receives the tracking error signal TE, the focusing error signal FE and the main or RF signal fed from the photodetector. The tracking error signal is applied to a band pass filter 21a for filtering out the disturbance and other electrical noise which may be superimposed on the tracking error signal. For this purpose, it is preferable for the band pass filter 21a to have a pass band ranging from about 2 kHz to about 100 kHz. The filtered signal is applied from the band pass filter 21a to a zero crossing detector 22a which produces a pulse to a gate circuit 24a each time the filtered signal crosses zero. The gate circuit 24a has positive and negative output terminals connected respectively to waveform shaper circuits 25a and 25b. The focusing error signal FE is applied to a band pass filter 21b having the same characteristic as the band pass filter 21a. The filtered signal is applied to sampling circuits 26a and 26c and also through an inverter 23c to sampling circuits 26b and 26d. The RF signal is applied to a band pass filter 21c having the same characteristic as the band pass filter 21a. The

filtered signal is applied to a zero crossing detector 22b. The zero crossing detector 22b produces a pulse to a gate circuit 24b each time the filtered signal crosses zero. The gate circuit 24b has positive and negative output terminals connected respectively to waveform shaper circuits 25c and 25d.

The filtered tracking error signal is also applied from the band pass filter 21a to a comparator 23a which compares the filtered signal with zero. The comparator 23a produces a logic 1 level signal to the gate circuit 24b which thereby passes the pulse from the zero crossing detector 22b to the waveform shaper circuit 25c when the filtered tracking error signal is positive. As a result, the waveform shaper circuit 25c produces a sampling pulse to cause the sampling circuit 26c to sample the filtered focusing error signal fed thereto from the band pass filter 21b. The sampled value is held in a holding circuit 27b. When the filtered tracking error signal is negative, the comparator 23a produces a logic 0 level signal to the gate circuit 24b which thereby passes the pulse from the zero crossing detector 22b to the waveform shaper circuit 25d. As a result, the waveform shaper circuit 25d produces a sampling pulse to cause the sampling circuit 26d to sample the inverted focusing error signal fed thereto from the inverter 23c. The sampled value is held in the holding circuit 27b. That is, the focusing error signal is sampled each time the tracking error signal crosses zero with its polarity being inverted before it is sampled when the tracking error signal is negative at the sampling times. It is, therefore, apparent that the output of the holding circuit 27b corresponds to the periodic function signal $\alpha(\omega)$ as indicated by the waveform 12a of Fig. 12. The periodic function signal $\alpha(\omega)$ is applied to a multiplier circuit 28b.

Similarly, the filtered RF signal is also applied from the band pass filter 21c to a comparator 23b which compares the filtered signal with zero. The comparator 23b produces a logic 1 level signal to the gate circuit 24a which thereby passes the pulse from the zero crossing detector 22a to the waveform shaper circuit 25a when the filtered RF signal is positive. As a result, the waveform shaper circuit 25a produces a sampling pulse to cause the sampling circuit 26a to sample the filtered focusing error signal fed thereto from the band pass filter 21b. The sampled value is held in a holding circuit 27a. When the filtered RF signal is negative, the comparator 23b produces a logic 0 level signal to the gate circuit 24a which thereby passes the pulse from the zero crossing detector 22a to the waveform shaper circuit 25b. As a result, the waveform shaper circuit 25b produces a sampling pulse to cause the sampling circuit 26b to sample the inverted focusing error signal fed thereto from the inverter 23c. The sampled value is held in the holding circuit 27a. That is, the focusing error signal is sampled each time the RF signal crosses zero with its polarity being inverted before it is sampled when the RF signal is negative at the sampling times. It is, therefore, apparent that the output of the holding circuit 27a corresponds to the periodic function signal $\beta(\omega)$ as indicated by the waveform 13a of Fig. 13. The periodic function signal $\beta(\omega)$ is applied to a multiplier circuit 28a.

An automatic gain control circuit 29a receives the filtered tracking error signal from the band pass filter 21a and converts it into a tracking error signal having a predetermined amplitude (in the illustrated case, 1). The automatic gain control circuit 29a may be arranged to detect the positive and negative peaks of the amplitude of the input signal and adjust its gain in accordance with the detected peaks. The signal is fed from the automatic gain control circuit 29a to the multiplier circuit 28b which multiplies it by the periodic function signal $\alpha(\omega)$ to produce an output signal, as indicated by the waveform 12c of Fig. 12. A similar automatic gain control circuit 29b receives the filtered RF signal from the band pass filter 21c and converts it into an RF signal having a predetermined amplitude (in the illustrated case, 1). The signal is fed from the automatic gain control circuit 29b to the multiplier circuit 28a which multiplies it by the periodic function signal $\beta(\omega)$ to produce an output signal, as indicated by the waveform 13c of Fig. 13. These output signals are fed to an adder circuit 30 which adds them to produce an output signal indicative of a composed disturbance W'(S). The output signal is applied through the switch 31 to the adder 18 which subtracts the composed disturbance indicative signal from the focusing error signal to cancel the disturbance W(S) superimposed on the focusing error signal E(S). The switch 31 is closed when the tracking control is off.

Fig. 16 comprises waveforms 16a and 16b illustrating the focusing error signal E(S) and the drive signal D(S), respectively, when the disturbance W(S) is not cancelled. It can be seen from the waveform 16b that the drive signal D(S) is saturated with a great offset residual thereon. Fig. 17 comprises waveforms 17a and 17b illustrating the focusing error signal E(S) and the drive signal D(S), respectively, when the disturbance W(S) is cancelled in accordance with the teachings of the invention. As can be seen from the waveform 17b, the drive signal D(S) has almost no offset residual thereon.

According to the preferred embodiment of the invention, the disturbance which may be superimposed on the focusing error signal can be cancelled or minimised. This eliminates the possibility of the focusing servo control shifting into a lock-off condition even during an operational mode where the light spot is traversing the recording track formed on an optical disc. It is, therefore, possible to increase the speed of rotation of the optical disc in order to increase the data transfer rate. It is also possible to reduce costs

through the use of an inexpensive optical pickup having a slow response if the optical disc is intended to rotate at the same speed as in conventional systems.

Although the focusing error signal is obtained according to an astigmatic method in the previously-described embodiment, it will be appreciated that the invention can be used with other focusing error detecting methods. The same technique is effective in any case where a disturbance is produced due to the interference of the 0-order and ± first-order diffraction beams included in the light beam reflected from an optical disc and superimposed on the focusing error signal when the light spot traverses the recording track formed on the optical disc.

Claims

1. A focusing control method utilising a photodetector (P) for generating a focusing error signal (FE), a tracking error signal (TE) and an RF signal (RF), and a closed loop focusing servo circuit (10) responsive to the focusing error signal (FE) applied thereto for focusing a light spot in position on an optical disc, the method being characterised by the steps of:
detecting the focusing error signal (FE) synchronously with the tracking error signal (TE) to produce a first periodic function signal;
detecting the focusing error signal (FE) synchronously with the RF signal (RF) to produce a second periodic function signal;
converting the tracking error signal (TE) into a sine-wave signal having a predetermined amplitude;
converting the RF signal (RF) into a cosine-wave signal having a predetermined amplitude;
multiplying the first periodic function signal by the cosine-wave signal to produce a first component signal;
multiplying the second periodic function signal by the sine-wave signal to produce a second component signal;
adding the first and second component signals to produce a composed disturbance signal (W'(S)); and
subtracting the composed disturbance signal (W'(S)) from a signal containing the focusing error signal (FE) applied to said focusing servo circuit(10), thereby cancelling a disturbance (W(S)) superimposed on said signal containing the focusing error signal (FE) applied to the focusing servo circuit (10).

2. A method according to claim 1, wherein the step of producing the first periodic function signal includes sampling the focusing error signal (FE) each time the tracking error signal (TE) crosses zero, the focusing error signal (FE) being inverted before it is sampled when the RF signal (RF) is negative, and wherein the step of producing the second periodic function signal includes sampling the focusing error signal (FE) each time the RF signal (RF) crosses zero, the focusing error signal (FE) being inverted before it is sampled when the tracking error signal (TE) is negative.

3. Focusing control apparatus comprising:
a photodetector (P) for generating a focusing error signal (FE), a tracking error signal (TE) and an RF signal (RF);
a closed loop focusing servo circuit (10) responsive to the focusing error signal (FE) applied thereto for focusing a light spot in position on an optical disc; said apparatus being characterised by:
a cancelling signal generator (20) connected to said photodetector (P) for producing a cancelling signal (W'(S)), said cancelling signal generator (20) including means (22a,26a,26b) for detecting the focusing error signal (FE) synchronously with the tracking error signal (TE) to produce a first periodic function signal, means (22b,26c,26d) for detecting the focusing error signal (FE) synchronously with the RF signal (RF) to produce a second periodic function signal, means (29a) for converting the tracking error signal (TE) into a sine-wave signal having a predetermined amplitude, means (29b) for converting the RF signal (RF) into a cosine-wave signal having a predetermined amplitude, means (28a) for multiplying the first periodic function signal by the cosine-wave signal to produce a first component signal, means (28b) for multiplying the second periodic function signal by the sine-wave signal to produce a second component signal, and means (30) for adding the first and second component signals to produce the cancelling signal (W'(S)); and
said focusing servo circuit (10) including means (18) connected to said cancelling signal generator (20) for subtracting the cancelling signal (W'(S)) from a signal containing the focusing error signal (FE) applied to said focusing servo circuit (10), thereby cancelling a disturbance (W(S)) superimposed on said signal containing the focusing error signal (FE) applied to the focusing servo circuit (10).

through the use of an inexpensive optical pickup having a slow response if the optical disc is intended to rotate at the same speed as in conventional systems.

Although the focusing error signal is obtained according to an astigmatic method in the previously-described embodiment, it will be appreciated that the invention can be used with other focusing error detecting methods. The same technique is effective in any case where a disturbance is produced due to the interference of the 0-order and ± first-order diffraction beams included in the light beam reflected from an optical disc and superimposed on the focusing error signal when the light spot traverses the recording track formed on the optical disc.

Claims

1. A focusing control method utilising a photodetector (P) for generating a focusing error signal (FE), a tracking error signal (TE) and an RF signal (RF), and a closed loop focusing servo circuit (10) responsive to the focusing error signal (FE) applied thereto for focusing a light spot in position on an optical disc, the method being characterised by the steps of:
detecting the focusing error signal (FE) synchronously with the tracking error signal (TE) to produce a first periodic function signal;
detecting the focusing error signal (FE) synchronously with the RF signal (RF) to produce a second periodic function signal;
converting the tracking error signal (TE) into a sine-wave signal having a predetermined amplitude;
converting the RF signal (RF) into a cosine-wave signal having a predetermined amplitude;
multiplying the first periodic function signal by the cosine-wave signal to produce a first component signal;
multiplying the second periodic function signal by the sine-wave signal to produce a second component signal;
adding the first and second component signals to produce a composed disturbance signal (W'(S)); and
subtracting the composed disturbance signal (W'(S)) from a signal containing the focusing error signal (FE) applied to said focusing servo circuit(10), thereby cancelling a disturbance (W(S)) superimposed on said signal containing the focusing error signal (FE) applied to the focusing servo circuit (10).

2. A method according to claim 1, wherein the step of producing the first periodic function signal includes sampling the focusing error signal (FE) each time the tracking error signal (TE) crosses zero, the focusing error signal (FE) being inverted before it is sampled when the RF signal (RF) is negative, and wherein the step of producing the second periodic function signal includes sampling the focusing error signal (FE) each time the RF signal (RF) crosses zero, the focusing error signal (FE) being inverted before it is sampled when the tracking error signal (TE) is negative.

3. Focusing control apparatus comprising:
a photodetector (P) for generating a focusing error signal (FE), a tracking error signal (TE) and an RF signal (RF);
a closed loop focusing servo circuit (10) responsive to the focusing error signal (FE) applied thereto for focusing a light spot in position on an optical disc; said apparatus being characterised by:
a cancelling signal generator (20) connected to said photodetector (P) for producing a cancelling signal (W'(S)), said cancelling signal generator (20) including means (22a,26a,26b) for detecting the focusing error signal (FE) synchronously with the tracking error signal (TE) to produce a first periodic function signal, means (22b,26c,26d) for detecting the focusing error signal (FE) synchronously with the RF signal (RF) to produce a second periodic function signal, means (29a) for converting the tracking error signal (TE) into a sine-wave signal having a predetermined amplitude, means (29b) for converting the RF signal (RF) into a cosine-wave signal having a predetermined amplitude, means (28a) for multiplying the first periodic function signal by the cosine-wave signal to produce a first component signal, means (28b) for multiplying the second periodic function signal by the sine-wave signal to produce a second component signal, and means (30) for adding the first and second component signals to produce the cancelling signal (W'(S)); and
said focusing servo circuit (10) including means (18) connected to said cancelling signal generator (20) for subtracting the cancelling signal (W'(S)) from a signal containing the focusing error signal (FE) applied to said focusing servo circuit (10), thereby cancelling a disturbance (W(S)) superimposed on said signal containing the focusing error signal (FE) applied to the focusing servo circuit (10).

* C L M S *

4. Apparatus according to claim 3, wherein said means for detecting the focusing error signal synchronously with the tracking error signal includes a first circuit (22a,26a,26b) for sampling the focusing error signal (FE) each time the tracking error signal (TE) crosses zero, and said means for detecting the focusing error signal synchronously with the RF signal includes a second circuit (22b,26c,26d) for sampling the focusing error signal (FE) each time the RF signal (RF) crosses zero.

5. Apparatus according to claim 4, wherein said first circuit includes means (22a) for producing a first drive pulse each time the tracking error signal (TE) crosses zero, a first sampling circuit (26a,27a) responsive to the first drive pulse for sampling the focusing error signal (FE), an inverter (23c) for inverting the focusing error signal (FE), a second sampling circuit (26b,27a) connected to said inverter (23c), said second sampling circuit (26b,27a) being responsive to the first drive pulse for sampling the inverted focusing error signal (FE), and means (23b,24a) for applying the first drive pulse to said first sampling circuit (26a,27a) when the RF signal (RF) is positive and to said second sampling circuit (26b,27a) when the RF signal (RF) is negative, and wherein said second circuit includes means (22b) for producing a second drive pulse each time the RF signal (RF) crosses zero, a third sampling circuit (26c,27b) responsive to the second drive pulse for sampling the focusing error signal (FE), a fourth sampling circuit (26d,27b) connected to said inverter (23c), said fourth sampling circuit (26d,27b) being responsive to the second drive pulse for sampling the inverted focusing error signal (FE), and means (23a,24b) for applying the second drive pulse to said third sampling circuit (26c,27b) when the tracking error signal (TE) is positive and to said fourth sampling circuit (26d,27b) when the tracking error signal (TE) is negative.

Revendications

1. Procédé de commande de focalisation utilisant un photodétecteur (P) pour générer un signal d'erreur de focalisation (FE), un signal d'erreur de suivi de piste (TE) et un signal radiofréquence (RF), et un circuit asservi de focalisation à boucle fermée (10) répondant au signal d'erreur de focalisation (FE) appliqué à lui pour focaliser une tache lumineuse en position sur un disque optique, le procédé étant caractérisé par les étapes de :
détection du signal d'erreur de focalisation (FE) de façon synchronisée avec le signal d'erreur de suivi de piste (TE) pour produire un premier signal de fonction périodique ;
détection du signal d'erreur de focalisation (FE) de façon synchronisée avec le signal radiofréquence (RF) pour produire un second signal de fonction périodique ;
conversion du signal d'erreur de suivi de piste (TE) en un signal sinus de l'onde ayant une amplitude prédéterminée ;
conversion du signal radiofréquence (RF) en un signal cosinus de l'onde ayant une amplitude prédéterminée ;
multiplication du premier signal de fonction périodique par le signal cosinus de l'onde pour produire un premier signal de composante ;
multiplication du second signal de fonction périodique par le signal sinus de l'onde pour produire un second signal de composante ;
addition des premier et second signaux de composante pour produire un signal de perturbation composé (W'(S)) ; et
soustraction du signal de perturbation composé (W'(S)) d'un signal contenant le signal d'erreur de focalisation (FE) appliqué audit circuit asservi de focalisation (10), supprimant de la sorte une perturbation (W(S)) superposée audit signal contenant le signal d'erreur de focalisation (FE) appliqué audit circuit asservi de focalisation (10).

2. Procédé selon la revendication 1, dans lequel l'étape de production du premier signal de fonction périodique comprend un échantillonnage du signal d'erreur de focalisation (FE) chaque fois que le signal d'erreur de suivi de piste (TE) passe par zéro, le signal d'erreur de focalisation (FE) étant inversé avant qu'il ne soit échantillonné quand le signal radiofréquence (RF) est négatif, et dans lequel l'étape de production du second signal de fonction périodique comprend un échantillonnage du signal d'erreur de focalisation (FE) chaque fois que le signal radiofréquence (RF) passe par zéro, le signal d'erreur de focalisation (FE) étant inversé avant qu'il ne soit échantillonné quand le signal d'erreur de suivi de piste (TE) est négatif.

3. Appareil de commande de focalisation comprenant :

* C L M S *

un photodétecteur (P) pour générer un signal d'erreur de focalisation (FE), un signal d'erreur de suivi de piste (TE) et un signal radiofréquence (RF) ;

un circuit asservi de focalisation à boucle fermée (10) répondant au signal d'erreur de focalisation (FE) appliqué à lui pour focaliser une tache lumineuse en position sur un disque optique; l'appareil étant caractérisé par :

un générateur de signal de suppression (20) relié audit photodétecteur (P) pour produire un signal de suppression (W'(S)), ledit générateur de signal de suppression (20) comprenant un moyen (22a, 26a, 26b) pour détecter le signal d'erreur de focalisation (FE) de façon synchronisée avec le signal d'erreur de suivi de piste (TE) pour produire un premier signal de fonction périodique, un moyen (22b, 26c, 26d) pour détecter le signal d'erreur de focalisation (FE) de façon synchronisée avec le signal radiofréquence (RF) pour produire un second signal de fonction périodique, un moyen (29a) pour convertir le signal d'erreur de suivi de piste (TE) en un signal sinus de l'onde ayant une amplitude prédéterminée, un moyen (29b) pour convertir le signal radiofréquence (RF) en un signal cosinus de l'onde ayant une amplitude prédéterminée, un moyen (28a) pour multiplier le premier signal de fonction périodique par le signal cosinus de l'onde pour produire un premier signal de composante, un moyen (28b) pour multiplier le second signal de fonction périodique par le signal sinus de l'onde pour produire un second signal de composante, et un moyen (30) pour additionner les premier et second signaux de composante pour produire le signal de suppression (W'(S)) ; et par

ledit circuit asservi de focalisation (10) comprenant un moyen (18) relié audit générateur de signal de suppression (20) pour soustraire le signal de suppression (W'(S)) d'un signal contenant le signal d'erreur de focalisation (FE) appliqué audit circuit asservi de focalisation (10), supprimant de la sorte une perturbation (W(S)) superposée audit signal contenant le signal d'erreur de focalisation (FE) appliqué audit circuit asservi de focalisation (10).

4. Appareil selon la revendication 3, dans lequel ledit moyen pour détecter le signal d'erreur de focalisation de façon synchronisée avec le signal d'erreur de suivi de piste comprend un premier circuit (22a, 26a, 26b) pour échantillonner le signal d'erreur de focalisation (FE) chaque fois que le signal d'erreur de suivi de piste (TE) passe par zéro, et dans lequel ledit moyen pour détecter le signal d'erreur de focalisation de façon synchronisée avec le signal radiofréquence comprend un second circuit (22b, 26c, 26d) pour échantillonner le signal d'erreur de focalisation (FE) chaque fois que le signal radiofréquence (RF) passe par zéro.

5. Appareil selon la revendication 4, dans lequel ledit premier circuit comprend un moyen (22a) pour produire une première impulsion d'actionnement chaque fois que le signal d'erreur de suivi de piste (TE) passe par zéro, un premier circuit d'échantillonnage (26a, 27a) sensible à la première impulsion d'actionnement pour échantillonner le signal d'erreur de focalisation (FE), un inverseur (23c) pour inverser le signal d'erreur de focalisation (FE), un second circuit d'échantillonnage (26b, 27a) relié audit inverseur (23c), ledit second circuit d'échantillonnage (26b, 27a) étant sensible à la première impulsion d'actionnement pour échantillonner le signal d'erreur de focalisation (FE) inversé, et un moyen (23b, 24a) pour appliquer la première impulsion d'actionnement audit premier circuit d'échantillonnage (26a, 27a) quand le signal radiofréquence (RF) est positif et audit second circuit d'échantillonnage (26b, 27a) quand le signal radiofréquence (RF) est négatif, et dans lequel ledit second circuit comprend un moyen (22b) pour produire une seconde impulsion d'actionnement chaque fois que le signal radiofréquence (RF) passe par zéro, un troisième circuit d'échantillonnage (26c, 27b) sensible à la seconde impulsion d'actionnement pour échantillonner le signal d'erreur de focalisation (FE), un quatrième circuit d'échantillonnage (26d, 27b) relié audit inverseur (23c), ledit quatrième circuit d'échantillonnage (26d, 27b) étant sensible à la seconde impulsion d'actionnement pour échantillonner le signal d'erreur de focalisation inversé (FE), et un moyen (23a, 24b) pour appliquer la seconde impulsion d'actionnement audit troisième circuit d'échantillonnage (26c, 27b) quand le signal d'erreur de suivi de piste (TE) est positif et audit quatrième circuit d'échantillonnage (26d, 27b) quand le signal d'erreur de suivi de piste (TE) est négatif.

Ansprüche

1. Fokussiersteuerverfahren, welches einen Photodetektor (P) zum Erzeugen eines Fokussierfehlersignals (FE), eines Nachlauffehlersignals (TE) und eines HF-Signals (RF), und einen auf das Fokussiersteuersignal (FE) ansprechenden ruck-gekoppelten Fokussierservoschaltkreises (10) zum an die richtige Stelle Fokussieren eines Lichtflecks auf einer optischen Platte verwendet,

* C L M S *

gekennzeichnet durch:
Erfassen des Fokussierfehlersignals (FE) synchron mit dem Nachlauffehlersignal (TE) zur Erzeugung eines Signals einer ersten periodischen Funktion,
Erfassen des Fokussierfehlersignals (FE) synchron mit dem HF-Signal (FR) zum Erzeugen eines Signals einer zweiten periodischen Funktion,
Umwandeln des Nachlauffehlersignals (TE) in ein Sinuswellensignal vorbestimmter Amplitude,
Umwandeln des HF-Signals (RF) in ein Cosinuswellensignal vorbestimmter Amplitude,
Multiplizieren des Signals der ersten periodischen Funktion mit dem Cosinuswellensignal zum Erzeugen eines ersten Komponentensignals,
Multiplizieren des Signals der zweiten periodischen Funktion mit dem Sinuswellensignal zum Erzeugen eines zweiten Komponentensignals,
Addieren des ersten und zweiten Komponentensignals zum Erzeugen eines zusammengesetzten Störgrößensignals (W'(S)) und Subtrahieren des zusammengesetzten Störgrößensignals (W'(S)) von einem das an den Fokussierservoschaltkreis (10) angelegte Fokussierfehlersignal (FE) enthaltenden Signal, wobei eine dem das an den Fokussierservorschaltkreis (10) angelegte Fokussierfehlersignal (FE) enthaltenden Signal überlagerte Störgröße (W(S)) aufgehoben wird.

2. Verfahren nach Anspruch 1, wobei der Schritt der Erzeugung des Signals der ersten periodischen Funktion ein Abtasten des Fokussierfehlersignals (FE) jedesmal beim Nulldurchgang des Nachlauffehlersignals (TE) umfaßt, wobei das Fokussierfehlersignal (FE) bei negativem HF-Signal (RF) vor dem Abtasten invertiert wird, und wobei der Schritt der Erzeugung des Signals der zweiten periodischen Funktion ein Abtasten des Fokussierfehlersignals (FE) jedesmal beim Nulldurchgang des HF-Signals (RF) umfaßt, wobei das Fokussierfehlersignal (FE) bei negativem Nachlauffehlersignal (TE) vor dem Abtasten invertiert wird.

3. Fokussiersteuervorrichtung mit
einem Photodetektor (P) zum Erzeugen eines Fokussierfehlersignals (FE), eines Nachlauffehlersignals (TE) und eines HF-Signals (RF), und
einem auf das Fokussierfehlersignal (FE) ansprechenden rückgekoppelten Fokussierservoschaltkreis (10) zum an die richtige Stelle Fokussieren eines Lichtflecks auf einer optischen Platte,
gekennzeichnet durch
einen mit dem Photodetektor (P) verbundenen Aufhebesignalgenerator (20) zum Erzeugen eines Aufhebesignals (W'(S)), der eine Einrichtung (22a, 26a, 26b) zum Erfassen des Fokussierfehlersignals (FE) synchron mit dem Nachlauffehlersignal (TE) zum Erzeugen eines Signals einer ersten periodischen Funktion, eine Einrichtung (22b, 22c, 26d) zum Erfassen des Fokussierfehlersignals (FE) synchron mit dem HF-Signal (RF) zum Erzeugen eines Signals einer zweiten periodischen Funktion, eine Einrichtung (29a) zum Umwandeln des Nachlauffehlersignals (TE) in ein Sinuswellensignal vorbestimmter Amplitude, eine Einrichtung (29b) zum Umwandeln des HF-Signals (RF) in ein Cosinuswellensignal vorbestimmter Amplitude, eine Einrichtung (28a) zum Multiplizieren des Signals der ersten periodischen Funktion mit dem Cosinuswellensignal zum Erzeugen eines ersten Komponentensignals, eine Einrichtung (28b) zum Multiplizieren des Signals der zweiten periodischen Funktion mit dem Sinuswellensignal zum Erzeugen eines zweiten Komponentensignals, und eine Einrichtung (30) zum Addieren des ersten und zweiten Komponentensignals zum Erzeugen des Aufhebesignals (W'(S)) aufweist, wobei
der Fokussierservoschaltkreis (10) eine mit dem Aufhebesignalgenerator (20) verbundene Einrichtung zum Subtrahieren des Aufhebesignals (W'(S)) von einem das an den Fokussierservoschaltkreis (10) angelegte Fokussierfehlersignal (FE) enthaltenden Signal, wobei eine dem das an den Fokussierservoschaltkreis (10) angelegte Fokussierfehlersignal (FE) überlagerte Störgröße (W(S)) aufgehoben wird, aufweist.

4. Vorrichtung nach Anspruch 3, wobei die Einrichtung zum Erfassen des Fokussierfehlersignals synchron mit dem Nachlauffehlersignals einen ersten Schaltkreis (22a, 26a, 26b) zum Abtasten des Fokussierfehlersignals (FE) jedesmal beim Nulldurchgang des Nachlauffehlersignals (TE) aufweist, und wobei die Einrichtung zum Erfassen des Fokussierfehlersignals synchron mit dem HF-Signal einen zweiten Schaltkreis (22b, 26c, 26d) zum Abtasten des Fokussierfehlersignals (FE) jedesmal beim Nulldurchgang des HF-Signals aufweist.

5. Vorrichtung nach Anspruch 4, wobei der erste Schaltkreis eine Einrichtung (22a) zum Erzeugen eines

* C L M S *

ersten Steuerimpulses jedesmal beim Nulldurchgang des Nachlauffehlersignals (TE), einen auf den ersten Steuerimpuls ansprechenden ersten Abtastschaltkreis (26a, 27a) zum Abtasten des Fokussierfehlersignals (FE), einen Inverter (23c) zum Invertieren des Fokussierfehlersignals (FE), einen mit dem Inverter (23c) verbundenen und auf den ersten Steuerimpuls ansprechenden zweiten Abtastschaltkreis (26b, 27a) zum Abtasten des invertierten Fokussierfehlersignals (FE) und eine Einrichtung (23b, 24a) zum Anlegen des ersten Steuerimpulses an den ersten Abtastschaltkreis (26a, 27a) bei positivem HF-Sginal (RF) und an den zweiten Abtastschaltkreis (26b, 27a) bei negativem HF-Signal aufweist, und wobei der zweite Schaltkreis eine Einrichtung (22b) zum Erzeugen eines zweiten Steuerimpulses jedesmal beim Nulldurchgang des HF-Signals (RF), einen auf den zweiten Steuerimpuls ansprechenden Abtastschaltkreis (26c, 27b) zum Abtasten des Fokussierfehlersignals (FE), einen mit dem Inverter (23c) verbundenen und auf den zweiten Steuerimpuls ansprechenden vierten Abtastschaltkreis (26d, 27b) zum Abtasten des invertierten Fokussierfehlersignals (FE) und eine Einrichtung (23a, 24b) zum Anlegen des zweiten Steuerimpulses an den dritten Abtastschaltkreis (26c, 27b) bei positivem Nachlauffehlersignal (TE) und an den vierten Abtastschaltkreis (26d, 27b) bei negativem Nachlauffehlersignal (TE) aufweist.

* C L M S *