

TITLE OF THE INVENTION

ELECTROMAGNETIC RADIATION MEASURING APPARATUS

BACKGROUND OF THE INVENTION

1. Field of the Invention

5 This invention relates to an electromagnetic radiation measuring apparatus for measuring an electromagnetic radiation from an operated unit such as an operated circuit board.

2. Description of the Prior Art

10 An electromagnetic radiation measuring apparatus comprising two-dimensionally arranged probe elements for receiving electromagnetic radiation and a switching unit for successively supplying a detection signal from one of probe elements to provide two-dimensional electromagnetic
15 detection result is known.

 Such a prior art electromagnetic radiation measuring apparatus is disclosed in Japanese Patent Publication No. 5-67184. This prior art electromagnetic radiation measuring apparatus comprises a wire loop antenna matrix on
20 a multi-layer print circuit board, each wire loop antenna detecting an electro-magnetic radiation and converting it into an electronic signal, and a switching circuit, including diodes, for successively outputting the electronic signal from one of the loop antenna.

25 Fig. 5 is a circuit diagram of a second prior art

electro-magnetic radiation measuring apparatus. Fig. 6 is a partial circuit diagram of a second prior art electro-magnetic radiation measuring apparatus. In Figs. 5 and 6, electromagnetic radiation measuring arrays 104
5 arranged in X direction. Each of electromagnetic radiation measuring arrays includes a plurality (generally, 20 to 40) of wire loop antennas 101 and a switching diode 103 forming an electromagnetic detection unit on a print circuit board arranged in Y direction. A transmission line 102 in each
10 electro-magnetic radiation measuring array is connected cathodes of respective diodes. An electromagnetic radiation is detected by a wire loop antenna 101 is converted into an electric detection signal which is supplied to the transmission line 102 through the switching
15 diode 103, wherein a selection in Y direction is effected by applying a Y direction selection signal to a terminal 105 to turn on the corresponding switching diode 103. Therefore, the detection signal from the selected wire loop antennas is supplied to the transmission line 102 through
20 the switching diodes 103. One end of each of the transmission lines 102 is terminated with a terminating element having a characteristic impedance (generally 50 ohms). The other ends of the respective transmission lines 102 are supplied to a signal selection portion 119 having a
25 transmission line 121 and switching diodes 120. That is,

the respective transmission lines 102 are coupled to the transmission line 21 extending in the X direction through the switching diodes 120. The transmission line 121 is so arranged as to be close to respective switching diodes 120.

5 When one of the switching diodes 120 is turned on and other switching diodes 120 is turned off to provide the selection in X direction. Therefore, the detection signal from one of loop antenna 101 is outputted.

10 In the second prior art, assuming that a switching diode 120a is turned on, because all other switching diodes 120 in the signal selection portion 119 are turned off, a portion A of the transmission line from the junction point between the switching diode 120a and the transmission line 121 to one end of the transmission line 121 acts as an open
15 end transmission line. Therefore, This portion A shows a low impedance at a frequency corresponding to a wavelength λ_g , wherein

$$\lambda_g = 4 \times A$$

20 Therefore, a transmission frequency characteristic of the signal selection portion 119 for selectively outputting one of outputs of the electromagnetic arrays is deteriorated. That is, this frequency limits the measurable high frequency (maximum frequency).

25 When it is desired to increase the maximum frequency, a positional measurable range is limited. Contrary, if it

is desired to expand the positional measurable range, the maximum frequency is limited. For example, it is assumed that a length of the transmission line is 200mm. A maximum length of the open end line of the transmission line 21 is
5 about 150 mm. Then, if the print circuit board has a general dielectric constant, the maximum measurable frequency is about 230 MHz. However, it is general to require the maximum measurable frequency of the electromagnetic radiation up to 30 MHz to 1 GHz. Therefore,
10 if the maximum measurable frequency is required to be 1 GHz, the length of the transmission line 21 should be about 70 mm. Then, this provides an insufficient positional range for a general size of a print circuit board to be measured.

SUMMARY OF THE INVENTION

15 The aim of the present invention is to provide an improved electromagnetic radiation measuring apparatus.

According to this invention a first electromagnetic radiation measuring apparatus is provided, which comprises:
a substrate (23); an antenna element matrix (20) on the
20 substrate including first to Lth arrays (4) which are successively arranged in X direction at a predetermined interval, each of the first to Lth array including a plurality of antenna elements arranged in Y direction and having an output terminal (7), each antenna element
25 receiving an electromagnetic radiation from a target and

generating a detection signal; a signal selection portion (5, 3, 2, 7) on the substrate responsive to X and Y selection signals for selectively supplying the detection signal from one of antenna elements to one of the output terminals (7), the X selection signal determining one of the arrays, the Y selection signal determining one of the antenna elements (row) in the determined array; and first to Nth signal outputting circuits, each having inputs, at least an output, and at least a signal selection circuit selectively coupling the inputs to the output terminals of which the number is less than the number of the inputs, the Nth outputting circuit has only one of the output for supplying an output detection signal, the inputs of the first signal outputting circuits being connected to the output terminals (7) respectively, L and N being natural numbers more than one, wherein each of the second to Nth outputting circuits has at least a transmission line substantially extending in the X direction to connect one of the input terminals thereof to at least the signal selection circuit thereof.

The first electromagnetic radiation measuring apparatus may further comprise a frequency compensation portion (26) for compensating a frequency characteristic of the output detection signal and outputting a frequency compensated signal.

In the first electromagnetic radiation measuring apparatus, the first signal selection portion (5, 3, 39, 36) may comprise amplifying elements such as transistors on the substrate and arranged adjacent to respective
5 antenna elements, each having one end connected to each of the antenna element and another end, some of amplifying elements is one of the first to Lth arrays are connected to the output terminal, each of amplifying elements connected to antenna elements in one of the first to Lth
10 arrays connected to the output terminal (42) of one of the first to Lth arrays, and each of amplifying elements selectively amplifies and selectively supplies the detection signal from one of antenna elements to one of the output terminals (42) with an operation of each of
15 amplifying elements controlled in response to the X and Y selection signals.

According to this invention a second electromagnetic radiation measuring apparatus is provided, which comprises:
a substrate (23); an antenna element matrix (50) on the
20 substrate including first to Lth arrays (38) which are successively arranged in X direction at a predetermined interval, each of the first to Lth arrays including a plurality of antenna elements arranged in Y direction and having an output terminal (42), each antenna element
25 receiving an electromagnetic radiation from a target and

generating a detection signal; a signal selection portion (39, 36, 47) on the substrate responsive to X and Y selection signals for selectively supplying the detection signal from one of antenna elements to one of the output terminals (42), the X selection signal determining one of the arrays, the Y selection signal determining one of the antenna elements (row) in the determined array; and a signal outputting portion, having inputs respectively connected to the output terminals (42) and an output (46) for selectively coupling one of the inputs to the output, wherein the signal selection portion comprises amplifying elements on the substrate and arranged adjacent to respective antenna elements, each having one end connected to each of the antenna elements and another end, some of amplifying elements in one of the first to Lth arrays are connected to the output terminal, some of amplifying elements are connected to some of antenna elements in one of the first to Lth arrays connected to the output terminal (42) of one of the first to Lth arrays, and each of amplifying elements selectively amplifies and selectively supplies the detection signal from one of antenna elements to one of the output terminals (42) with an operation of each of amplifying elements controlled in response to the X and Y selection signals.

25 According to this invention, a third electromagnetic

radiation measuring apparatus is provided which comprises: a substrate (23); an antenna element matrix (50) on the substrate including a plurality of arrays (38) which are successively arranged in X direction at a predetermined interval, each of the plurality of arrays including a plurality of antenna elements arranged in Y direction and having an output terminal (42), each antenna element receiving an electromagnetic radiation from a target and generating a detection signal; a signal selection portion (39, 36, 47) on the substrate responsive to X and Y selection signals for selectively supplying the detection signal from one of antenna elements to one of the output terminals (41), the X selection signal determining one of the arrays, the Y selection signal determining one of the antenna elements in the determined array; and a signal outputting portion, having inputs respectively connected to the output terminals (41) and an output (46) for selectively coupling one of the inputs to the output, wherein the signal selection portion comprises amplifying elements on the substrate and arranged adjacent to respective antenna elements, each having one end connected to each of the antenna elements and another end, and each of amplifying elements selectively amplifies and selectively supplies the detection signal from one of antenna elements to one of the output terminals (41) with

an operation of each of amplifying elements controlled in response to the X and Y selection signals.

BRIEF DESCRIPTION OF THE DRAWINGS

The object and features of the present invention
5 will become more readily apparent from the following
detailed description taken in conjunction with the
accompanying drawings in which:

Fig. 1 is a circuit diagram of an electromagnetic
radiation measuring apparatus of a first embodiment;

10 Fig. 2 is a block diagram of an electromagnetic
radiation measuring apparatus of a second embodiment;

Fig. 3 is a diagram of a frequency characteristic of
the second embodiment;

Fig. 4 is a circuit diagram of an electromagnetic
15 radiation measuring apparatus of a third embodiment;

Fig. 5 is a circuit diagram of a second prior art
electro-magnetic radiation measuring apparatus;

Fig. 6 is a partial circuit diagram of the second
prior art electro-magnetic radiation measuring apparatus;

20 Fig. 7 is a plan view of a wire loop antenna of this
invention; and

Figs. 8 and 9 are partial circuit diagrams of
modification of the first embodiment and are also referred
in the third embodiment.

25 The same or corresponding elements or parts are

designated with like references throughout the drawings.

DETAILED DESCRIPTION OF THE INVENTION

Hereinbelow will be described a first embodiment of this invention. Fig. 1 is a circuit diagram of an
5 electromagnetic radiation measuring apparatus of the first embodiment. Electromagnetic radiation measuring arrays 4 (4-1 to 4-l) are arranged in an X direction on a multi-layer print circuit board 23 (l is a natural number, generally, 50). Fig. 7 is a plan view of a wire loop
10 antenna of this invention. Each of electromagnetic radiation measuring arrays 4 includes a plurality of electromagnetic detection units 52 arranged in a Y direction and a transmission line 2 on a print circuit board 23. Each of electromagnetic detection units 52
15 includes a wire loop antennas 1 and switching diodes 3. The transmission line 2 is connected cathodes of respective switching diodes 3 and extends in the Y direction. The wire loop antennas 1 has a substantially rectangular shape having a width from 6 to 8 mm and a height of 4 mm and
20 switching diodes 3.

Twenty to forty of electromagnetic detection units 52 are arranged in each of electromagnetic radiation measuring arrays 4 and fifty of electromagnetic radiation measuring arrays 4 are arranged in the antenna element
25 matrix 20. Therefore, a thousand to two thousands of the

electromagnetic detection units 52 are arranged in a matrix X-Y in an actual electromagnetic radiation measuring apparatus.

An electromagnetic radiation is detected by each
5 wire loop antenna 1 and is converted into an electric
detection signal supplied to the transmission line 2
through the switching diode 3. The selection in the Y
direction is effected by applying a Y direction control
signal as a bias voltage to one of Y direction control
10 signal input terminals 5 corresponding to the wire loop
antenna 1 from which a detection signal to be detected.
The application of the Y direction control signal to the Y
direction control signal input terminal 5 turns on the
corresponding switching diode 3. Therefore, the detection
15 signal from the selected wire loop antennas 1 is supplied
to the transmission line 2 through the switching diode 3.
One end of each of the transmission lines 2 is terminated
with a terminating element 6 having a characteristic
impedance which is generally 50 ohms. Junction points
20 between the transmission lines 2 and the terminating
elements are connected X direction control signal input
terminals 19 respectively through a dc resistive element
58 such as a resistor or a reactor. An X direction control
signal is applied to one of X direction control signal
25 input terminals 19 corresponding to the wire loop antenna 1

from which a detection signal is to be detected. The application of the X direction control signal having a low voltage or the ground level to the X direction control signal input terminal 19 to select one of the

5 electromagnetic measuring arrays 4 including this wire loop antenna 1. Contrary, applying a supply voltage to the X direction control signal input terminal 19 turns of the switching diode 3. The other ends of the respective transmission lines 2 have output terminals 7-1 to 7-1

10 connected to a first signal selection portion 8. The first signal selection portion 8 includes m (a natural number) switching circuits 9, i.e., 9-1 to 9-m. The switching circuit 9-1 having switching diodes 9a to 9c of which cathodes respectively connected to output terminals 7-1 to

15 7-3 for supplying the detection signals from the selected electromagnetic radiation detection array 4 when one of the electromagnetic radiation detection arrays 4-1 to 4-3 is selected. Anodes of the switching diodes 9a to 9c are connected to an output terminal 10-1. Other switching

20 circuits 9-2 to 9-m have the similar structure and operation for supplying the detection signals from the selected electromagnetic radiation detection array 4 when one of the electromagnetic radiation detection arrays 4 coupled to the switching circuit 9 is selected. Therefore,

25 the first signal selection portion 8 supplies one of the

detection signal from l output terminals 7-1 to 7- l to m output terminals 10-1 to 10- m ($l > m$).

The switching circuits 9-1 to 9- m have output terminals 10-1 to 10- m respectively. The output terminals
5 10-1 to 10- m are connected to a second signal selection (outputting) portion 11 including switching circuit 13-1 to 13- n (n is a natural number and $l > m > n$). The output terminals 10-1 to 10-3 are respectively coupled to cathodes of diodes 13a to 13c, wherein the cathodes of diodes 13a
10 and 13c are coupled to the output terminals 10-1 and 10-3 through transmission lines 12a and 12b respectively but the cathode of the diode 13b is directly connected to the output terminal 10-2. Anodes of the switching diodes 13a to 13c are connected to an output terminal 14-1. The other
15 switching circuits 13-2 to 13- n have similarly connected. Therefore, the second signal selection portion 11 supplies one of the detection signal from m output terminals 10-1 to 10- m to one of n output terminals 14-1 to 14- n ($m > n$).

The switching circuits 13-1 to 13- n have output
20 terminals 14-1 to 14- n respectively. The output terminals 14-1 to 14- n are connected to a third signal selection portion 15, i.e., a final stage of signal selection portion in this embodiment, including switching circuit 17. That is, the output terminals 14-1 to 14- n ($n = 3$, in this
25 embodiment) are coupled to cathodes of diodes 17a to 17c,

wherein the cathodes of diodes 17a and 17c are coupled to the output terminals 14-1 and 14-3 (14-n) through transmission line 16a and 16b but the cathode of the diode 17b is directly connected to the output terminal 14-2. The
5 final stage of signal selection portion 15 has one output terminal 18, connected to anodes of the switching diodes 17a to 17c, for supplying the detection signal from one of wire loop antenna 1 as an output detection signal of this electromagnetic radiation measuring apparatus. In this
10 embodiment, there are three stages of the signal selection portions. However, this structure can be hierarchically expanded in accordance with the number of the electromagnetic detection units 52.

The transmission lines 12a, 12b, 16a and 16, etc.
15 couple the output terminals to the diodes with the shortest distances. That is, these extend in the X direction. Leads of diodes 9a and 9c from the cathodes can be considered as transmission lines also.

An operation of this embodiment will be described.
20 A target print circuit board (not shown in Fig. 1) is arranged to confront the print circuit board 23 of this electromagnetic radiation measuring apparatus with a predetermined space and the target print circuit board is operated. The output terminal 18 is coupled to a measuring
25 instrument such as a spectrum analyzer or the like. Then,

the Y direction control signal and the X direction control signal (L level) are selectively supplied to one of the Y direction control signal input terminals 5 and to one of the X direction control signal input terminals 19-1 to 19l.

5 The Y direction control signal has a bias voltage to turn on the switching diodes 3 on the same row (ROW) connected to the same Y direction control signal input terminal 5. When the X direction control signal is Low voltage (the ground level) supplied to one of X direction control signal
10 input terminals 19 and a bias current from one of the wire loop antennas 1 on the row to which the Y direction control signal is supplied flows. That is, a bias current flows through the wire loop antenna supplied with both the Y direction control signal and the X direction control signal.

15 The electromagnetic radiation received by one loop antenna 1 is converted into an ac detection signal on the bias current, and the ac detection signal is supplied to the output terminal 7. Then, a detection signal from one wire loop antenna 1 corresponding to the X direction

20 control signal input terminal 19 and the corresponding Y direction control signal input terminal 5 is outputted at the output terminal 18 via one of the output terminal 7-1 to 7-l, one of switching diodes in the first signal selection portion 8, one of output terminals 10-1 to 10-m,
25 one of switching diodes in th second signals selection

portion 11, one of output terminals 14-1 to 14-m, one of switching diodes in the third signal selection portion 15 with a unique signal passage formed. Application of the X direction control signal and the Y direction control signal is successively changed such that all wire loop antennas 1 arranged in a matrix are scanned. The measuring instrument observes the detection signal from the output terminal 18 in phase with this scanning operation and can output a map of a frequency spectrum analysis indicative of electromagnetic radiation from respective points of the target printed circuit board, i.e. an electromagnetic radiation intensity distribution of the target printed circuit board 25.

In the first to third signal selection portions 8, 11, and 15, there is no open-end transmission line during the detection signal passes therethrough, so that the transmission characteristic in the signal selection portions are improved. That is, the electromagnetic measurement up to a higher frequency can be obtained with the same circuit board size and the same resolution.

In the above-mentioned embodiment, there are three stages of the signal selection portions. However, this structure can be hierarchically expanded to increase the number 1 of the electromagnetic radiation detection arrays. Moreover, there are three switching diodes in each of

switching circuits in the first to third signal selection portion 8, 11, and 15. It is also possible to increase the number of the switching diodes with a consideration of the frequency characteristic. In this embodiment, the
5 switching diodes are used in the first to third signal selection portions 8, 11, and 15. However, FETs (field effect transistors) or the like can be used in place of the switching diodes.

A modification of the first embodiment will be
10 described.

Figs. 8 and 9 are partial circuit diagrams of modification of the first embodiment and will be also referred in the third embodiment. In Fig. 8, the an FET 53 having a gate connected to the wire loop antenna, a source
15 connected to the transmission line, and a drain grounded replaces the switching diode 3. The FET 53 and the wire loop antenna 1 forms an electromagnetic detection unit 52' for selectively outputting a detection signal in accordance with the Y direction control signal and the X
20 direction control signal similarly.

In Fig. 9, a signal selection circuit 57 including FETs as switching elements replaces the signal selection portions 8 and 9. The FETs 54-1 to 54-3 require a bias resistor 55 and between the output terminals 7-1 to 7-3 and
25 FETs 54-1 to 54-3 ac coupling capacitors 56-1 to 56-3 are

provided. Each of the FETs 54 is controlled by a control signal externally supplied.

A second embodiment will be described.

Fig. 2 is a block diagram of an electromagnetic
5 radiation measuring apparatus of the second embodiment.
The electromagnetic radiation measuring apparatus of the second embodiment comprises the multi-layer printed circuit 23 having the circuit structure shown in Fig. 1 for detecting electromagnetic radiation from a target printed
10 circuit board 25, a frequency characteristic compensation circuit 26 coupled to the output terminal 18 on the printed circuit board 23 via an input terminal 27 thereof for compensating a frequency characteristic of the detection
15 signal and for outputting a frequency compensated detection signal at an output terminal 32. The frequency characteristic compensation circuit 25 comprises a low noise amplifier 28 for amplifying the detection signal from the output terminal 18, a filter circuit 29, including a low pass filter 29c, at least a band pass filter 29b, and a
20 high pass filter 29a, and an amplifier 29d for combining these filters, for compensating a frequency characteristic of the detection signal, and a power amplifier 30 for outputting the frequency compensated detection signal at an output terminal 32.

25 An operation of the second embodiment will be

described.

A target print circuit board 25 is arranged to confront the print circuit board 23 of this electromagnetic radiation measuring apparatus with a predetermined space and the target print circuit board 25 is operated. The print circuit board 23 and the frequency characteristic circuit 26 are mounted in a case 24. The output terminal 32 is coupled to the measuring instrument mentioned in the first embodiment such as the spectrum analyzer or the like. Then, the Y direction control signal and the X direction control signal are selectively supplied to one of the Y direction control signal input terminals 5 and to the X direction control signal input terminals 19-1 to 19l. A detection signal from one wire loop antenna 1 corresponding to the X direction control signal input terminal 19 and the corresponding Y direction control signal input terminal 5 is outputted at the output terminal 18. The application of the X direction control signal and the Y direction control signal is successively changed such that all wire loop antennas 1 arranged in a matrix are scanned.

The frequency characteristic compensation circuit 26 compensates the frequency characteristic of the detection signal from the output terminal 18 and supplies the frequency characteristic compensated detection signal to the external measuring instrument.

The measuring instrument can provide a map of a frequency spectrum analysis indicative of electromagnetic radiation from respective points of the target printed circuit board with a frequency compensation.

5 The low noise amplifier 28 amplifies the detection signal from the output terminal 18 with a flat frequency characteristic gain over a wide frequency range. The filter circuit 29 compensates the frequency characteristic of the detection signal from the low noise amplifier 28
10 through a combination of the low pass filter 29c, a band pass filter(s) 29b, and the high pass filter 29a to obtain a flat frequency characteristic in the detection signal over a required frequency range. The power amplifier 31 amplifies the frequency compensated signal to output the
15 frequency compensated signal with a sufficient power with a sufficient low impedance.

Fig. 3 is a diagram of a frequency characteristic of the second embodiment. A curve 33 represents a frequency characteristic of the detection signal at the output
20 terminal 18. A curve 34 represents a frequency characteristic of the frequency-characteristic-compensated detection signal at the output terminal 32 in the condition that the frequency characteristic compensation circuit has a total gain from about 18 to 40dB. As the result, the
25 frequency characteristic of the detection signal is

compensated to have a flat frequency characteristic around the level of -70 dBm with a variation within about 10 dbm and this electromagnetic radiation measuring apparatus provides the detection signal up to 1500 MHz.

5 Hereinbelow will be described a third embodiment of this invention. Fig. 4 is a circuit diagram of an electromagnetic radiation measuring apparatus of the third embodiment. Electromagnetic radiation measuring arrays 38 are arranged in the X direction on a multi-layer print
10 circuit board 23. Each of electromagnetic radiation measuring arrays 38 includes wire loop antennas 1, transistors 36, and a transmission line 37. Each of the wire loop antennas 1 and each of transistors 36 form an electromagnetic detection unit. The wire loop antenna 1
15 has the shape as shown in Fig. 7 similar to the first embodiment.

A base of each transistors 36 is connected to one end of each wire loop antenna 35, the emitter of the transistor 36 is grounded, and the collectors of the
20 transistors 36 in the same electromagnetic radiation measuring arrays 38 are commonly connected to one transmission line 37. The output terminal 42 is coupled to a cathode of the switching diode 44 through a bias resistor 51 and a bypass capacitor 41 connected to the bias resistor
25 51 in parallel.

In the actual circuit, generally, twenty to forty electromagnetic radiation detection arrays are arranged in X direction and fifty electromagnetic units are arranged in each of the electromagnetic radiation detection arrays.

5 Therefore, a thousand to two thousands of the electromagnetic detection units are arranged in a matrix X-Y in the actual electromagnetic radiation measuring apparatus.

An electromagnetic radiation is detected by each
10 wire loop antenna 1 and is converted into an electric detection signal supplied to the transmission line 37 through the transistor 36 when the transistor 36 is activated by the X and Y direction control signals. That is, the selection in the Y direction is effected by
15 applying a Y direction control signal 39 as a bias current to a Y direction control signal input terminal 39 corresponding to the wire loop antenna from which detection signal to be detected. The application of the Y direction control signal to the Y direction control signal activates
20 the corresponding transistor 36 together with the X direction control signal. Therefore, the detection signals from the selected wire loop antenna 35 is supplied to the transmission line 37 through the transistor 36. One end of each of the transmission lines 37 is terminated with a
25 terminating element 40 having a characteristic impedance

which is generally 50 ohms. Junction points between the transmission lines 37 and the terminating elements 40 are connected X direction control signal input terminals 47 through resistors 59 respectively. An X direction control
5 signal having a low level is applied to one of the X direction control signal input terminals 47 corresponding to the wire loop antenna 1 from which detection signal is to be detected. The application of the X direction control signal to the X direction control signal input terminal 47
10 to select one of the electromagnetic measuring arrays 38 including this wire loop antenna 35. The other ends of the respective transmission lines 37 are coupled to output terminals 42 through the bypass capacitors 41. The output terminals 42 are connected to a signal selection portion 43.
15 The signal selection portion 43 includes switching circuits having switching diodes 44 operating as similar to the first embodiment to output the detection signal at the output terminal 46.

An operation of this embodiment will be described.

20 A target print circuit board (not shown in Fig. 4) is arranged to confront the print circuit board of this electromagnetic radiation measuring apparatus with a predetermined space and the target print circuit board is operated. The output terminal 46 is coupled to a measuring
25 instrument such as a spectrum analyzer or the like. Then,

the Y direction control signal and the X direction control signal are selectively supplied to one of the Y direction control signal input terminals 39 and to the X direction control signal input terminals 47. The Y direction control
5 signal has a bias voltage supplied through a suitable bias resistance to a base of transistors 36 on the same row of the electromagnetic radiation detection units connected to the same Y direction control signal input terminal 39.

When the X direction control signal is a LOW voltage or the
10 ground level supplied to one of X direction control signal input through the resistor 59, the switching diode 44 turns on through a bias resistor 51 and a current including a bias current and an electromagnetic radiation detection current from one of the wire loop antennas 1 on the row to
15 which the Y direction control signal is supplied to base of the transistors 36. Then, only the transistor supplied with the X and Y direction control signals amplifies the base current. An ac component, that is, a magnetic radiation detection signal, in the amplified current is
20 coupled to the bypass capacitor 41 as the detection signal to the output terminal 46. Then, the application of the X direction control signal and the Y direction control signal is successively changed such that all wire loop antennas 35 arranged in a matrix are scanned. The measuring instrument
25 observes the detection signal from the output terminal 46

in phase with this scanning operation and can output a map of a frequency spectrum analysis indicative of electromagnetic radiation from respective points of the target printed circuit board, i.e. an electromagnetic
5 radiation intensity distribution of the target printed circuit board 25.

As mentioned, the detection signal is amplified by the transistor 36 provided adjacent to the wire loop antenna, i.e., directly connected to the wire loop antenna,
10 with a gain from 5 dB to 10 dB, so that a dynamic range of the detection signal is increased. Moreover, the sensitivity of the wire loop antenna 36 is increased by the transistor 36, so that it is possible to make the size of the wire loop antenna 35 smaller. Then, the smaller size
15 of the wire loop antenna 35 provides a sensitivity to higher frequency, for example, 2 GHz, so that the frequency characteristic of the electromagnetic radiation measuring apparatus can be improved. Moreover, the smaller size of the wire loop antenna 35 provides a higher resolution of
20 the electromagnetic radiation measuring.

In this embodiment, the transistor 36 is used as the switching and amplifying element. However, other amplifying element such as FETs can be used also. That is the FET shown in Fig. 8 can be used in place of the
25 transistor 36. Moreover, the signal selection portion 43

uses the switching diodes 44. However, the FETs 54 shown in Fig. 9 can be also used in place of the switching diodes 44.

In the third embodiments, the signal selection
5 portion 43 has the hierarchically structured switching
circuits. However, the feature that the detection signal
is amplified by adjacent transistor 36 can be also effected
in the case that the switching circuit used in the prior
art shown in Fig. 5.

10

15

20

25



WHAT IS CLAIMED IS:

1. An electromagnetic radiation measuring apparatus comprising:

5 a substrate (23);

an antenna element matrix (20) on said substrate including first to Lth arrays (4) which are successively arranged in X direction at a predetermined interval, each of said first to Lth array including a plurality of antenna
10 elements arranged in Y direction and having an output terminal (7), each antenna element receiving an electromagnetic radiation from a target and generating a detection signal;

signal selection means (5, 3, 2, 7) on said
15 substrate responsive to X and Y selection signals for selectively supplying said detection signal from one of antenna elements to one of said output terminals (7), said X selection signal determining one of said arrays, said Y selection signal determining one of said antenna elements
20 in said determined array; and

first to Nth signal outputting circuits, each having inputs, at least an output, and at least a signal selection circuit selectively coupling said inputs to said output terminals of which the number is less than the number of
25 said inputs, said Nth outputting circuit has only one of



said output for supplying an output detection signal, said inputs of said first signal outputting circuits being connected to said output terminals respectively, L and N being natural numbers more than one, wherein each of said second to Nth outputting circuits has at least a transmission line substantially extending in said X direction to connect one of said input terminals thereof to at least said signal selection circuit thereof.

10 2. An electromagnetic radiation measuring apparatus as claimed in claim 1, wherein each of at least said signal selection circuit of said first outputting circuit comprises a first signal selection element (9a) having one end connected to said output terminal of said first array and the other end connected one of outputs of said first outputting circuit, a second signal selection element (9b) having one end connected to said output terminal of said second array neighbouring with said first array and the other end connected said one of outputs of said first outputting circuit and said second outputting circuit comprises a first and second transmission lines (12a, 12b) as said at least transmission line, a third signal selection element (13a) having one end coupled to said output terminal of said first array through said first transmission line (12a) and the other end connected one of

15

20

25



outputs of said second outputting circuit, a fourth signal selection element (13c) having one end connected to one of said outputs of said second outputting circuits and the other end connected said another one of outputs of said
5 first outputting circuit through said second transmission line (12b).

3. An electromagnetic radiation measuring apparatus as claimed in claim 1, wherein each of at least said signal
10 selection circuit of said first signal selection circuit further comprises at least a fifth signal selection element (9c) having one end connected to said output terminal of said third array neighbouring with said second array and the other end connected said one of outputs of said first
15 outputting circuit and said second outputting circuit further comprises at least a sixth signal selection element (13b) having one end coupled to another one of outputs of said output terminals of said first signal outputting circuit.

20

4. An electromagnetic radiation measuring apparatus as claimed in claim 1, wherein said first signal outputting means (5, 3, 2, 7) comprises switching elements on said substrate and arranged adjacent to respective antenna
25 elements, each having one end connected to each of said



antenna elements and some of said switching elements connected to antenna elements in one of said first to Lth arrays are connected to said output terminal of said one of said first to Lth arrays.

5

5. An electromagnetic radiation measuring apparatus as claimed in claim 4, wherein each of said switching elements comprises a diode.

10 6. An electromagnetic radiation measuring apparatus as claimed in claim 4, wherein each of said switching elements comprises a transistor.

7. An electromagnetic radiation measuring apparatus as
15 claimed in claim 2, wherein each of said first and second signal selection elements comprises a diode.

8. An electromagnetic radiation measuring apparatus as
20 claimed in claim 2, wherein each of said first and second signal selection elements comprises a transistor.

9. An electromagnetic radiation measuring apparatus as
claimed in claim 1, further comprising a frequency
compensation means for compensating a frequency
25 characteristic of said output signal and outputting a



frequency compensated signal.

10. An electromagnetic radiation measuring apparatus as claimed in claim 9, wherein said frequency compensation.
5 means includes a broad band amplifier (28) for amplifying said output signal, a high pass filter (29a) for high-pass filtering an output of said broad band amplifier, a band pass filter (29b) for band-pass filtering said output of said broad band amplifier, a low pass filter for low-pass
10 filtering said output of said broad band amplifier (29c), and an output circuit (29c) for providing said frequency compensated signal from said outputs of said high pass filter, band pass filter, and said low pass filter.
- 15 11. An electromagnetic radiation measuring apparatus as claimed in claim 1, wherein said first signal selection means (5, 3, 39, 36) comprises amplifying elements on said substrate and arranged adjacent to respective antenna
20 elements, each having one end connected to each of said antenna element and another end, some of amplifying elements is one of said first to Lth arrays are connected to said output terminal, each of amplifying elements connected to antenna elements in one of said first to Lth arrays connected to said output terminal (42) of said one
25 of said first to Lth arrays, and each of amplifying



elements selectively amplifies and selectively supplies said detection signal from one of antenna elements to one of said output terminals (42) with an operation of each of amplifying elements controlled in response to said X and Y selection signals.

12. An electromagnetic radiation measuring apparatus comprising:

a substrate (23);

10 an antenna element matrix (50) on said substrate including first to Lth arrays (38) which are successively arranged in X direction at a predetermined interval, each of said first to Lth arrays including a plurality of antenna elements arranged in Y direction and having an output terminal (42), each antenna element receiving an electromagnetic radiation from a target and generating a detection signal;

signal selection means (39, 36, 47) on said substrate responsive to X and Y selection signals for 20 selectively supplying said detection signal from one of antenna elements to one of said output terminals (42), said X selection signal determining one of said arrays, said Y selection signal determining one of said antenna elements in said determined array; and

25 signal outputting means, having inputs



-33-

respectively connected to said output terminals (42) and an output (46) for selectively coupling one of said inputs to said output, wherein said signal selection means comprises amplifying elements on said substrate and arranged adjacent
5 to respective antenna elements, each having one end connected to each of said antenna elements and another end, some of amplifying elements is one of said first to Lth arrays are connected to said output terminal, some of amplifying elements are connected to some of antenna
10 elements in one of said first to Lth arrays connected to said output terminal (42) of said one of said first to Lth arrays, and each of amplifying elements selectively amplifies and selectively supplies said detection signal from one of antenna elements to one of said output
15 terminals (42) with an operation of each of amplifying elements controlled in response to said X and Y selection signals.

13. An electromagnetic radiation measuring apparatus as
20 claimed in claim 12, wherein each of said amplifying elements comprises a transistor and said Y selection signal controls a bias of said transistor connected to antenna elements on a row of said matrix in said Y direction.

25 14. An electromagnetic radiation measuring apparatus as



claimed in claim 13, wherein said transistor comprises a base connected to each of antenna elements, a collector connected to said output terminal (42) of said one of said first to Lth arrays, and emitter connected to the ground,
5 said Y selection signal controls a bias of transistor connected to antenna elements on a row of said matrix in said Y direction, and said X selection signal is selectively supplied to said collectors in one of said arrays, wherein one of said transistor supplied with said Y
10 and said X signals supplying said detection signal.

15. An electromagnetic radiation measuring apparatus as claimed in claim 12, wherein each of said amplifying elements comprises a field effect transistor and said Y
15 selection signal controls a gate bias of said field effect transistor connected to antenna elements on a row of said matrix in said Y direction.

16. An electromagnetic radiation measuring apparatus as
20 claimed in claim 15, wherein said field effect transistor comprises a gate connected to each of antenna elements, a drain connected to said output terminal (42) of said one of said first to Lth arrays, and a source connected to the ground, said Y selection signal controls a gate bias of
25 said field effect transistor connected to antenna elements



-35-

on a row of said matrix in said Y direction, and said X selection signal is selectively supplied to said collectors in one of said arrays, wherein one of said field effect transistor supplied with both said Y and said X signal
5 supplying said detection signal.

17. An electromagnetic radiation measuring apparatus comprising:

a substrate (23);

10 an antenna element matrix (50) on said substrate including a plurality of arrays (38) which are successively arranged in X direction at a predetermined interval, each of said plurality of arrays including a plurality of antenna elements arranged in Y direction and having an
15 output terminal (42), each antenna element receiving an electromagnetic radiation from a target and generating a detection signal;

signal selection means (39, 36, 47) on said substrate responsive to X and Y selection signals for
20 selectively supplying said detection signal from one of antenna elements to one of said output terminals (41), said X selection signal determining one of said arrays, said Y selection signal determining one of said antenna elements in said determined array; and

25 signal outputting means, having inputs



-36-

respectively connected to said output terminals (41) and an
output (46) for selectively coupling one of said inputs to
said output, wherein said signal selection means comprises
amplifying elements on said substrate and arranged adjacent
5 to respective antenna elements, each having one end
connected to each of said antenna elements and another end,
and each of amplifying elements selectively amplifies and
selectively supplies said detection signal from one of
antenna elements to one of said output terminals (41) with
10 an operation of each of amplifying elements controlled in
response to said X and Y selection signals.

15

20

25