

Description

This invention relates to video apparatus and, in particular, to video apparatus that incorporates deflection circuitry in which the field rate synchronization signal is derived from the line deflection rate.

A video apparatus, such as a television receiver or a computer monitor, incorporates some form of image display, which may be a cathode ray tube (CRT), for example. The CRT produces one or more electron beams, via an electron gun assembly, which are caused to impinge or land on a phosphor display screen by electron beam forming and accelerating voltages. The display screen emits light in proportion to the energy of the electron beam or beams.

A deflection yoke produces electromagnetic deflection fields in response to cyclically varying deflection currents that act to deflect or scan the electron beams across the display screen in a predetermined pattern to form a raster. The electron beam energy, i.e., current, is controlled in response to the information contained in a video signal in order to reproduce a video image on the display screen.

The video signal includes synchronizing information to properly synchronize the line or horizontal rate and field or vertical rate deflection of the electron beams with the video information in order to provide a stable video display. The video apparatus may incorporate circuitry that internally derives horizontal and vertical rate synchronizing (sync) pulses by frequency dividing and counting a high frequency clock signal. The derived horizontal rate pulses of such a countdown circuit are locked to the horizontal rate sync information contained in the video signal by phase locked loop circuitry. For broadcast video signals that produce a line interlaced scan or deflection, the vertical rate sync information will occur at a predetermined ratio with respect to the horizontal rate sync information. If the vertical rate sync information of the video signal is found to occur at a "standard" ratio with respect to the horizontal rate sync information, synchronization of the vertical deflection circuitry will be accomplished via the internally generated sync pulses. If the video signal vertical rate sync information does not occur at the standard ratio, direct synchronization of the vertical deflection circuit by the video signal vertical rate sync information may be provided. This direct synchronization of the vertical deflection circuitry is appropriate for truly non-standard signal sources, such as a VCR operating in a fast search or slow motion mode, for example.

Personal computers and video game circuitry may provide video signals that produce a noninterlaced scan in which the horizontal-to-vertical sync information ratio is fixed but does not occur at the ratio attributed to a designated standard signal source such as a broadcast signal. In such a situation, direct synchronization of the vertical deflection circuitry by

the vertical rate sync information of the video signal will occur. The circuitry incorporated in personal computers and, in particular, video game apparatus, may lack the sophistication of those circuits found in conventional television receivers, for example. As a result, the sync signal may comprise poorly formed pulses which can cause erratic triggering and synchronization of the deflection circuits to occur. Vertical jitter of the displayed video image may result. It would be desirable in such a situation to cause the deflection circuitry to operate in the standard or countdown mode, rather than the nonstandard or direct synchronization mode.

A synchronization system for standard and non-standard signals is described in US-A-4228 461.

According to the present invention, there is provided a deflection circuit for a video apparatus, comprising: deflection means responsive to an input signal for producing deflection current; a first source of field rate and line rate synchronizing signals; a second source of a signal having a line rate related frequency; means coupled to said second source for frequency dividing said line rate related frequency signal to provide successive line representative counts within a field rate interval; first window generator means coupled to said first source and responsive to first and second ones of said line representative counts and becoming enabled during a first interval that begins with said first count and ends with said second count for generating a first pulse synchronized to said field rate synchronizing signal when said field rate synchronizing signal occurs during said first interval; characterized by second window generator means responsive to third and fourth ones of said line representative counts that respectively represent first and second predetermined ratios of field period to line period for generating a second pulse within a second interval that begins with said third count and ends with said fourth count, said fourth count being different from said second count; and means coupled to said deflection means and the two window generating means for applying said second pulse as said deflection means input signal when the field rate and line rate synchronizing signals of the first source have one of the first and second predetermined ratios of field period to line period, and for otherwise applying said first pulse as said deflection means input signal.

In the accompanying drawing:

The sole FIGURE is a block and schematic diagram of a portion of a video apparatus incorporating deflection circuitry embodying with the present invention.

Referring to the FIGURE, a video apparatus illustratively receives a video signal either in modulated form via an antenna 10, or as a direct video signal from a video cassette recorder, for example, via an input terminal 11. The signal received by antenna 10 is applied to tuner and intermediate frequency (IF) cir-

cuitry 12, which generates an output signal that is applied to chrominance and luminance processing circuitry 13. The direct video signal received via input terminal 11 is also applied to chrominance and luminance processing circuitry 13. Chrominance and luminance processing circuitry 13 produces drive signals for the electron gun assembly 14 of a cathode ray tube (CRT) 15 via a conductor 16. Electron gun assembly 14 produces one or more electron beams 17 which are made to impinge upon a phosphor display screen 20 located on the front panel of CRT 15.

Chrominance and luminance processing circuitry 13 also produces a composite synchronizing signal, derived from the video signal, that is applied to a synchronizing (sync) pulse separator 21. Sync pulse separator 21 provides line rate, or horizontal, sync pulses on a conductor HS and field rate, or vertical, sync pulses on a conductor VS. The horizontal sync pulses on conductor HS are applied via a terminal 22 to deflection processing circuitry 23, which is illustratively shown by a dashed line as being incorporated as part of an integrated circuit. Deflection processing circuitry 23 incorporates an oscillator 24, having a free running frequency illustratively of the order of sixteen times the horizontal deflection rate. The high frequency signal from oscillator 24 is frequency divided by a counter 25 to provide horizontal rate pulses which are applied to horizontal driver circuit 26 via an interface terminal 27. The horizontal rate pulses from counter 25 are also applied to horizontal automatic frequency control (AFC) circuit 30. AFC circuit 30 controls oscillator 24 in response to the comparison of the horizontal rate pulses from counter 25 and horizontal sync pulses received from sync separator 21 via terminal 22.

The output of horizontal driver circuit 26 is applied to horizontal output and high voltage generating circuit 31, which may illustratively be of conventional design, such as a resonant retrace circuit, for example. Circuit 31 produces a horizontal rate deflection current via terminals H and H' in a horizontal deflection winding 32 located on the neck of CRT 15. The deflection current flow in winding 32 generates an electromagnetic deflection field that deflects or scans electron beam 17 at a line rate across phosphor display screen 20 of CRT 15. Circuit 31 also produces a high voltage or ultor potential that is applied to CRT 15 via a terminal 33 in order to provide an accelerating potential for electron beam 17.

As previously described, a broadcast encoded video signal comprises a predetermined number of horizontal deflection or scan lines in each vertical deflection field. For a "standard" signal of this type, deflection processing circuitry 23 can provide synchronization of the field or vertical deflection circuitry via a frequency division or countdown mode in which an internally generated reset or sync signal is applied to the vertical deflection circuitry. The video signal must

meet certain criteria in order for the deflection processing circuitry 23 to operate in the previously described standard or countdown mode. For a "nonstandard" signal, such as that provided by a VCR operating in a special effects situation, in which the number of horizontal lines per field is modified, the deflection processing circuitry 23 will operate in a nonstandard or direct sync mode, in which the vertical sync pulses from sync separator 21 are utilized to provide direct synchronization of the vertical deflection circuitry.

A more detailed description of the operation of this aspect of deflection processing circuitry 23 is as follows: The vertical sync pulses on conductor VS are applied to a pulse generator 34 of deflection processing circuitry 23 via an interface terminal 35. Pulse generator 34, which may comprise a flip-flop, produces a narrow pulse indicative of the presence of the vertical sync pulse. The output of pulse generator 34 is applied to window generator 36. The window interval of window generator 36 is determined by pulse counts provided from counter 25. Counter 25 illustratively produces pulse counts at twice the horizontal deflection rate. Therefore, a standard NTSC vertical field having 262.5 horizontal scan lines will comprise 525 pulse counts. The vertical sync pulse for a standard NTSC field will therefore be coincident with the 525th pulse count from counter 25. Window generator 36 is illustratively enabled or opened to respond to the presence of the vertical sync representative pulses from pulse generator 34 by pulse count 465 from counter 25, illustratively provided on conductor 41, and to become disabled or closed by pulse count 593 from counter 25 on conductor 42. The window interval of window generator 36 is chosen to be of sufficient duration to encompass vertical sync pulses from VCRs operating in special effects modes. Pulse generator 34 is configured to produce pulses having durations of approximately one pulse count. The actual pulse count values provided by counter 25 are given for illustrative purposes only. Window generator 36 produces an output pulse, which is applied to logic gates 37 and 40, that is coincident with the presence of a vertical sync pulse if the vertical sync pulse occurs within the window interval. If the vertical sync pulse does not occur within the window interval, window generator 36 will produce a default pulse occurring coincident to the window disabling or closure pulse count, in this example, pulse count 593.

In order to provide stable synchronization of the vertical or field rate deflection circuitry, and eliminate the need for a vertical hold control, for example, it is desirable to operate deflection processing circuitry 23 in a countdown or standard mode by utilizing the known line per field relationship of the standard broadcast signal. Operation in the countdown mode requires continuing detection of the vertical sync pulse occurrence at the desired horizontal line relationship, which may be accomplished by detection of

the vertical sync pulse occurrence at a particular pulse count from counter 25.

Some signal sources, such as personal computers or video games, for example, provide a noninterlaced video signal that has a fixed relationship of horizontal lines per vertical field, but the relationship may not precisely correspond to the standard broadcast ratio, with the result that deflection processing circuitry 23 would ordinarily operate in the direct synchronization mode. If the synchronizing signal is noisy or not precisely formed, as may occur with video games, for example, direct synchronization of the vertical deflection circuitry may result in unpredictable synchronization, causing jitter in the displayed image.

Embodying an aspect of the present invention, deflection processing circuitry 23 incorporates a coincidence or sync ratio acceptance window generator 43. Coincidence window generator 43 is enabled or generates a signal for a plurality of pulse counts from counter 25. The enabling interval of coincidence window generator 43 is sufficient to detect the presence of vertical sync pulses corresponding to a range of line-per-field ratios in order to permit deflection processing circuitry 23 to operate in a standard or countdown mode even with certain nonstandard video signal sources that provide noninterlaced video signals.

Illustratively, coincidence window generator 43 is enabled by a 524 pulse count from counter 25 on conductor 44, and disabled by pulse count 526 on conductor 45. Coincidence window generator produces an output signal that is applied to gates 37 and 40 during the coincidence window enabling interval. Gates 37 and 40, which may comprise conventional logic elements and be implemented in accordance with the integration topology of deflection processing circuitry 23, also receive an input from a mode switch 46 indicative of the present operating mode (countdown or direct synchronization) of deflection processing circuitry 23.

Gate 37 produces an output signal that resets both counter 25 and the vertical current ramp generator of vertical deflection circuit 47, which acts to synchronize the operation of vertical deflection circuit 47. Circuit 47 produces vertical deflection current via terminals V and V' in a vertical deflection winding 50 located on the neck of CRT 15. Winding 50 generates an electromagnetic deflection field that provides field rate deflection of electron beam 17 across display screen 20.

The output pulse of gate 37 is produced, and hence synchronization of vertical deflection circuit 47 is achieved as follows: The logic of gate 37 is configured such that when deflection processing circuit 23 is operating in the countdown or standard mode, the output pulse of gate 37 is produced coincident with the predictable stable enabling of coincidence window generator 43. When circuit 23 is operating in the nonstandard or direct synchronization mode, the gate

37 output pulse is produced coincident with the occurrence of vertical sync within the enabling window of window generator 36, or if sync fails to occur, coincident with the window disabling or closing pulse count.

Gate 40 forms a portion of a circuit, incorporating mode switch 46, that monitors the operation of deflection processing circuit 23 in order to select the proper operating mode. The output of gate 40 is determined as follows: when circuit 23 is operating in the standard or countdown mode and the occurrence of vertical sync, as received from window generator 36, coincides with the enabling interval of coincidence window generator 43, gate 40 produces an output pulse which is applied to and resets a vertical field counter 51. Vertical field counter 51 is incremented by vertical blanking pulses provided by vertical deflection circuit 47. Resetting of vertical field counter 51 acts to maintain the current operating mode of deflection processing circuit 23. Embodying a novel aspect of the present invention, the enabling interval of coincidence window generator 43 is chosen to encompass the occurrence of vertical sync pulses from certain nonstandard signal sources that produce noninterlaced signals and/or signals that do not precisely conform to broadcast line-per-field ratio, thereby permitting the advantageous operation of deflection processing circuit 23 in the standard or countdown mode even when nonstandard signal sources are used.

When circuit 23 is operating in the countdown mode and vertical sync from window generator 36 does not coincide with the enabling window of coincidence window generator 43, the output of gate 40 is inhibited and vertical field counter 51 is not reset. If this condition continues, vertical field counter 51 will continue to be incremented without being reset. After a predetermined number of vertical fields, vertical field counter 51 will produce an output pulse on conductor 52, for example, that is applied to mode switch 46, causing mode switch 46 to produce a signal indicative of a nonstandard or direct synchronization operating mode. In a similar manner, if circuit 23 is operating in a nonstandard mode and vertical sync is not coincident with the coincidence window generator 43 window interval, gate 40 produces an output pulse to reset vertical field counter 51, thereby maintaining nonstandard operation. If sync coincidence within the generator 43 window interval is detected, however, during the nonstandard mode of operation, gate 40 is inhibited from producing an output pulse. After a predetermined number of incremented vertical fields, which may be different than the number of fields required to switch out of the countdown mode, counter 51 will produce an output signal on a conductor 53. Mode switch 46 will then produce a signal indicative of a standard or countdown operating mode, which will cause gates 37 and 40 to switch to standard mode.

The deflection processing circuit 23 has been de-

scribed with reference to NTSC broadcast standard line per field ratios. It is of course apparent that this circuitry may be operated at other line per field ratios or with other video signal standards.

Claims

1. A deflection circuit for a video apparatus, comprising:

deflection means (47) responsive to an input signal for producing deflection current;

a first source (21) of field rate (VS) and line rate (HS) synchronizing signals;

a second source (24) of a signal having a line rate related frequency;

means (25) coupled to said second source (24) for frequency dividing said line rate related frequency signal to provide successive line representative counts within a field rate interval;

first window generator means (36) coupled to said first source (21) and responsive to first (on 41) and second (on 42) ones of said line representative counts and becoming enabled during a first interval that begins with said first count and ends with said second count for generating a first pulse (from 36) synchronized to said field rate synchronizing signal when said field rate synchronizing signal occurs during said first interval; characterized by

second window generator means (43) responsive to third (on 44) and fourth (on 45) ones of said line representative counts that respectively represent first and second predetermined ratios of field period to line period for generating a second pulse (from 43) within a second interval that begins with said third count and ends with said fourth count, said fourth count being different from said second count; and,

means (37) coupled to said deflection means (47) and the two window generating means (36,43) for applying said second pulse (from 43) as said deflection means input signal when the field rate and line rate synchronizing signals of the first source have one of the first and second predetermined ratios of field period to line period, and for otherwise applying said first pulse (from 36) as said deflection means input signal.

2. Apparatus according to claim 1, further comprising means (40,51,46) for

a) causing the applying means (37) to respond to the second pulse generated by the second window generating means (43) if the applying means is responding to the first pulse generated by the first generating means (36) and the first and second pulses are substantially coincident in time for a first pre-

terminated number of field interval, and

b) causing the applying means (37) to respond to the first pulse generated by the first window generating means (36) if the applying means is responding to the second pulse generated by the second generating means (43) and the first and second pulses are not coincident in time for a second predetermined number of field intervals.

3. Apparatus according to claim 2, wherein the causing means (40,51,46) comprises

means (51) for counting the first and second predetermined numbers of field intervals,

mode selection means (46) responsive to the counting means for causing the applying means to respond to the second pulses when the second number is counted and for causing the applying means to respond to the first pulses when the first number is counted, and means (40), responsive to the mode selector means (46), for resetting the counting means if the first and second pulses are not coincident in time when the applying means (37) responds to the first pulses and for resetting the counting means (51) if the first and second pulses are coincident in time when the applying means (37) responds to the second pulses, and for otherwise not resetting the counting means (51).

Patentansprüche

1. Ablenkschaltung für ein Videogerät, umfassend:

Ablenkmittel (47), die auf ein Eingangssignal ansprechen, um einen Ablenkstrom zu erzeugen;

eine erste Quelle (21) für bildfrequente (VS) und zeilenfrequente (HS)-Synchronsignale;

eine zweite Quelle (24) für ein Signal mit einer auf die Zeilenfrequenz bezogenen Frequenz;

mit der zweiten Quelle (24) verbundene Mittel (25) zur Frequenzteilung des auf die Zeilenfrequenz bezogenen Frequenzsignals, um aufeinanderfolgende zeilendarstellende Zählungen innerhalb eines Bildfrequenz-Intervalls zu erzeugen;

erste Fenstergeneratormittel (36), die mit der ersten Quelle (21) verbunden sind und auf erste (bei 41) und zweite (bei 42) der zeilendarstellenden Zählungen ansprechen und während eines ersten Intervalls freigegeben werden, das bei der ersten Zählung beginnt und bei der zweiten Zählung endet, um einen ersten Impuls (von 36) zu erzeugen, der mit dem bildfrequenten Synchronsignal synchronisiert wird, wenn das



scribed with reference to NTSC broadcast standard line per field ratios. It is of course apparent that this circuitry may be operated at other line per field ratios or with other video signal standards.

Claims

1. A deflection circuit for a video apparatus, comprising:

deflection means (47) responsive to an input signal for producing deflection current;

a first source (21) of field rate (VS) and line rate (HS) synchronizing signals;

a second source (24) of a signal having a line rate related frequency;

means (25) coupled to said second source (24) for frequency dividing said line rate related frequency signal to provide successive line representative counts within a field rate interval;

first window generator means (36) coupled to said first source (21) and responsive to first (on 41) and second (on 42) ones of said line representative counts and becoming enabled during a first interval that begins with said first count and ends with said second count for generating a first pulse (from 36) synchronized to said field rate synchronizing signal when said field rate synchronizing signal occurs during said first interval; characterized by

second window generator means (43) responsive to third (on 44) and fourth (on 45) ones of said line representative counts that respectively represent first and second predetermined ratios of field period to line period for generating a second pulse (from 43) within a second interval that begins with said third count and ends with said fourth count, said fourth count being different from said second count; and,

means (37) coupled to said deflection means (47) and the two window generating means (36,43) for applying said second pulse (from 43) as said deflection means input signal when the field rate and line rate synchronizing signals of the first source have one of the first and second predetermined ratios of field period to line period, and for otherwise applying said first pulse (from 36) as said deflection means input signal.

2. Apparatus according to claim 1, further comprising means (40,51,46) for

a) causing the applying means (37) to respond to the second pulse generated by the second window generating means (43) if the applying means is responding to the first pulse generated by the first generating means (36) and the first and second pulses are substantially coincident in time for a first pre-

terminated number of field interval, and
b) causing the applying means (37) to respond to the first pulse generated by the first window generating means (36) if the applying means is responding to the second pulse generated by the second generating means (43) and the first and second pulses are not coincident in time for a second predetermined number of field intervals.

3. Apparatus according to claim 2, wherein the causing means (40,51,46) comprises

means (51) for counting the first and second predetermined numbers of field intervals,

mode selection means (46) responsive to the counting means for causing the applying means to respond to the second pulses when the second number is counted and for causing the applying means to respond to the first pulses when the first number is counted, and means (40), responsive to the mode selector means (46), for resetting the counting means if the first and second pulses are not coincident in time when the applying means (37) responds to the first pulses and for resetting the counting means (51) if the first and second pulses are coincident in time when the applying means (37) responds to the second pulses, and for otherwise not resetting the counting means (51).

Patentansprüche

1. Ablenkschaltung für ein Videogerät, umfassend:

Ablenkmittel (47), die auf ein Eingangssignal ansprechen, um einen Ablenkstrom zu erzeugen;

eine erste Quelle (21) für bildfrequente (VS) und zeilenfrequente (HS)-Synchronsignale;

eine zweite Quelle (24) für ein Signal mit einer auf die Zeilenfrequenz bezogenen Frequenz;

mit der zweiten Quelle (24) verbundene Mittel (25) zur Frequenzteilung des auf die Zeilenfrequenz bezogenen Frequenzsignals, um aufeinanderfolgende zeilendarstellende Zählungen innerhalb eines Bildfrequenz-Intervalls zu erzeugen;

erste Fenstergeneratormittel (36), die mit der ersten Quelle (21) verbunden sind und auf erste (bei 41) und zweite (bei 42) der zeilendarstellenden Zählungen ansprechen und während eines ersten Intervalls freigegeben werden, das bei der ersten Zählung beginnt und bei der zweiten Zählung endet, um einen ersten Impuls (von 36) zu erzeugen, der mit dem bildfrequenten Synchronsignal synchronisiert wird, wenn das



bildfrequente Synchronsignal während des ersten Intervalls auftritt, gekennzeichnet durch:

zweite Fenstergeneratormittel (43), die auf dritte (bei 44) und vierte (bei 45) der zeilen-darstellenden Zählungen ansprechen, die jeweils erste und zweite vorgegebene Verhältnisse von Bildperiode zu Zeilenperiode darstellen, um einen zweiten Impuls (von 43) innerhalb eines zweiten Intervalls zu erzeugen, das bei der dritten Zählung beginnt und bei der vierten Zählung endet, wobei die vierte Zählung sich von der zweiten Zählung unterscheidet; und

Mittel (37), die mit den Ablenkmitteln (47) und mit den beiden Fenstergeneratormitteln (36, 43) verbunden sind, um den zweiten Impuls (von 43) als das Ablenkmittel-Eingangssignal zuzuführen, wenn die bildfrequenten und die zeilenfrequenten Synchronsignale der ersten Quelle eines der ersten und zweiten vorgegebenen Verhältnisse von Bildperiode zu Zeilenperiode aufweisen, und um andernfalls den ersten Impuls (von 36) als das Ablenkmittel-Eingangssignal zuzuführen.

2. Schaltung nach Anspruch 1, die ferner Mittel (40, 51, 46) enthält, um:

a) die Zuführungsmittel (37) zu veranlassen, auf den zweiten, von den zweiten Fenstererzeugungsmitteln (43) erzeugten Impuls anzusprechen, wenn die Zuführungsmittel auf den von den ersten Generatormitteln (36) erzeugten ersten Impuls ansprechen und der erste und zweite Impuls im wesentlichen zeitlich während einer ersten vorgegebenen Zahl von Bildintervallen zusammenfallen, und:

b) die Zuführungsmittel (37) zu veranlassen, auf den ersten, von den ersten Fenstererzeugungsmitteln (36) erzeugten ersten Impuls anzusprechen, wenn die Zuführungsmittel auf den zweiten, von den zweiten Erzeugermitteln (43) erzeugten zweiten Impuls ansprechen, und der erste und zweite Impuls zeitlich nicht für eine zweite vorgegebene Zahl von Bildintervallen zusammenfallen.

3. Schaltung nach Anspruch 2, bei der die Veranlassungsmittel (40, 51, 46) umfassen:

Mittel (51) zur Zählung der vorgegebenen ersten und zweiten Zahl von Bildintervallen,

Betriebsart-Auswahlmittel (46), die auf die Zählmittel ansprechen, um die Zuführungsmittel zu veranlassen, auf die zweiten Impulse anzusprechen, wenn die zweite Zahl gezählt wird und um die Zuführungsmittel zu veranlassen, auf die ersten Impulse anzusprechen, wenn die erste Zahl gezählt wird, und Mittel (40), die auf die Betriebsart-Auswahlmittel (46) ansprechen, um die Zählmittel zurückzustellen, falls die ersten Impul-

se nicht mit den zweiten Impulsen zeitlich zusammenfallen, wenn die Zuführungsmittel (37) auf die ersten Impulse ansprechen, und um die Zählmittel (51) zurückzustellen, wenn die ersten Impulse zeitlich mit den zweiten Impulsen zusammenfallen, wenn die Zuführungsmittel (37) auf die zweiten Impulse ansprechen, und um andernfalls die Zählmittel (51) nicht zurückzustellen.

Revendications

1. Circuit de déviation pour un appareil vidéo, comprenant :

un moyen de déviation (47) sensible à un signal d'entrée pour produire un courant de déviation ;

une première source (21) de signaux de synchronisation de fréquence de champ (VS) et de fréquence de ligne (HS) ;

une seconde source (24) d'un signal possédant une fréquence reliée à la fréquence de ligne ;

un moyen (25) couplé à ladite seconde source (24) pour diviser en fréquence ledit signal de fréquence relié à la fréquence de ligne pour fournir des comptages représentatifs des lignes successives à l'intérieur d'un intervalle de fréquence de champ ;

un premier moyen générateur de fenêtres (36) couplé à ladite première source (21) et sensible au premier comptage (sur 41) et au second comptage (sur 42) des comptages représentatifs des lignes et devenant validé pendant un premier intervalle qui commence avec ledit premier comptage et se termine avec ledit second comptage pour générer une première impulsion (à partir de 36) synchronisée audit signal de synchronisation de fréquence de champ lorsque ledit signal de synchronisation de fréquence de champ se produit pendant ledit premier intervalle ;

caractérisé par

un second moyen générateur de fenêtres (43) sensible au troisième comptage (sur 44) et au quatrième comptage (sur 45) desdits comptages représentatifs des lignes qui représentent respectivement les premier et second rapports prédéterminés de période de champ à période de ligne pour générer une seconde impulsion (venant de 43) à l'intérieur d'un second intervalle qui commence avec ledit troisième comptage et se termine avec ledit quatrième comptage, ledit quatrième comptage étant différent dudit second comptage ; et,

un moyen (37) couplé audit moyen de déviation (47) et aux deux moyens générateurs de fenêtres (36,43) pour appliquer ladite seconde



impulsion (venant de 43) comme dit signal d'entrée du moyen de déviation lorsque les signaux de synchronisation de fréquences de champ et de fréquences de ligne de la première source possèdent l'un des premier et second rapports prédéterminés de période de champ à période de ligne et pour appliquer, par ailleurs, ladite première impulsion (venant de 36) comme dit signal d'entrée du moyen de déviation .

5

10

2. Appareil selon la revendication 1, comprenant de plus des moyens (40, 51, 46) pour

a) entraîner le moyen d'application (37) à répondre à la seconde impulsion générée par le second moyen générateur de fenêtres (43) si le moyen d'application répond à la première impulsion générée par le premier moyen générateur 36 et si les première et seconde impulsions sont sensiblement en coïncidence dans le temps pour un premier nombre prédéterminé d'intervalles de champ, et

15

20

(b) entraîner le moyen d'application (37) à répondre à la première impulsion générée par le premier moyen générateur de fenêtres (36) si le moyen d'application répond à la seconde impulsion générée par le second moyen générateur (43) et si les première et seconde impulsions ne sont pas en coïncidence dans le temps pour un second nombre prédéterminé d'intervalles de champ.

25

30

3. Appareil selon la revendication 2, dans lequel les moyens d'entraînement (40, 51, 46) comprennent:

un moyen (51) pour compter les premier et second nombres prédéterminés d'intervalles de champ,

35

un moyen de sélection de mode (46) sensible au moyen de comptage pour entraîner le moyen d'application à répondre aux secondes impulsions lorsque le second nombre est compté et pour entraîner le moyen d'application à répondre aux premières impulsions lorsque le premier nombre est compté et un moyen (40) sensible au moyen sélecteur de mode (46) , pour réinitialiser le moyen de comptage si les premières et secondes impulsions ne sont pas en coïncidence dans le temps lorsque le moyen d'application 37 répond aux premières impulsions et pour réinitialiser le moyen de comptage (51) si les premières et secondes impulsions sont en coïncidence dans le temps lorsque le moyen d'application 537) répond aux secondes impulsions et pour, autrement, ne pas réinitialiser le moyen de comptage (51).

40

45

50

55