

DIE PRESS PROCESS FOR MANUFACTURING A Z-DIRECTED COMPONENT FOR A
PRINTED CIRCUIT BOARD

BACKGROUND

[0001] 1. Field of the Disclosure

5 **[0002]** The present invention relates generally to processes for manufacturing printed circuit board components and more particularly to a die press process for manufacturing a Z-directed component for a printed circuit board.

[0003] 2. Description of the Related Art

[0004] The following co-pending United States patent applications, which are assigned to the
10 assignee of the present application, describe various “Z-directed” components that are intended to be embedded or inserted into a printed circuit board (“PCB”): Serial No. 12/508,131 entitled “Z-Directed Components for Printed Circuit Boards,” Serial No. 12/508,145 entitled “Z-Directed Pass-Through Components for Printed Circuit Boards,” Serial No. 12/508,158 entitled “Z-Directed Capacitor Components for Printed Circuit Boards,” Serial No. 12/508,188 entitled “Z-Directed Delay
15 Line Components for Printed Circuit Boards,” Serial No. 12/508,199 entitled “Z-Directed Filter Components for Printed Circuit Boards,” Serial No. 12/508,204 entitled “Z-Directed Ferrite Bead Components for Printed Circuit Boards,” Serial No. 12/508,215 entitled “Z-Directed Switch Components for Printed Circuit Boards,” Serial No. 12/508,236 entitled “Z-Directed Connector Components for Printed Circuit Boards,” and Serial No. 12/508,248 entitled “Z-Directed Variable
20 Value Components for Printed Circuit Boards.”

[0005] As densities of components for printed circuit boards have increased and higher frequencies of operation are used, some circuits’ designs have become very difficult to achieve. The Z-directed components described in the foregoing patent applications are designed to improve the component densities and frequencies of operation. The Z-directed components occupy less space on
25 the surface of a PCB and for high frequency circuits, e.g. clock rates greater than 1 GHz, allow for higher frequency of operation. The foregoing patent applications describe various types of Z-directed components including, but not limited to, capacitors, delay lines, transistors, switches, and connectors. A process that permits mass production of these components on a commercial scale is desired.

SUMMARY

30 **[0006]** A method for manufacturing a Z-directed component for insertion into a mounting hole in a printed circuit board according to one example embodiment includes punching a plurality of

segments out of at least one sheet of substrate material to form a plurality of layers of the Z-directed component. A channel is formed through the substrate material either before or after the segments are punched. At least one of the formed layers includes at least a portion of the channel. A conductive material is applied to at least one surface of at least one of the formed layers. A stack of the formed layers is combined to form the Z-directed component.

[0007] A method for manufacturing a Z-directed component for insertion into a mounting hole in a printed circuit board according to another example embodiment includes punching a segment out of a sheet of substrate material to form a layer of the Z-directed component. A channel is formed through the substrate material either before or after the segment is punched. The formed layer includes at least a portion of the channel. A conductive material is applied to at least one surface of the formed layer. Additional segments are punched out of the same sheet or different sheets of substrate material to form additional layers of the Z-directed component. The formed layers are stacked and combined to form the Z-directed component.

[0008] A method for manufacturing a Z-directed component for insertion into a mounting hole in a printed circuit board according to another example embodiment includes forming a channel through a first sheet of substrate material. A conductive material is applied to a predetermined portion of the first sheet. The first sheet is stacked with additional sheets of substrate material. Segments are punched out of the stacked sheets to form a plurality of stacked layers of the Z-directed component. The punched segment from the first sheet includes at least a portion of the channel and the conductive material on a surface thereof. The stacked layers are combined to form the Z-directed component.

BRIEF DESCRIPTION OF THE DRAWINGS

[0009] The above-mentioned and other features and advantages of the various embodiments, and the manner of attaining them, will become more apparent and will be better understood by reference to the accompanying drawings.

[0010] Figure 1 is a perspective view of a Z-directed component according to one example embodiment.

[0011] Figure 2 is a transparent perspective view of the Z-directed component shown in Figure 1 illustrating the internal arrangement of elements of the Z-directed component.

[0012] Figures 3A-3F are perspective views showing various example shapes for the body of a Z-directed component.

[0013] Figures 4A-4C are perspective views showing various example side channel configurations for a Z-directed component.

[0014] Figures 5A-5H are perspective views showing various example channel configurations for the body of a Z-directed component.

5 **[0015]** Figure 6A is a perspective view of a Z-directed component having O-rings for connecting to internal layers of a PCB and having a body having regions comprised of similar and/or dissimilar materials according to one example embodiment.

[0016] Figure 6B is a top plan view of the Z-directed component shown in Figure 6A.

[0017] Figure 6C is a schematic side elevation view of the Z-directed component shown in
10 Figure 6A.

[0018] Figure 7 is a schematic illustration of various example elements or electronic components that may be provided within the body of a Z-directed component in series with a conductive channel.

[0019] Figure 8 is a schematic cross-sectional view of a Z-directed component flush mounted
15 in a PCB showing conductive traces and connections to the Z-directed component according to one example embodiment.

[0020] Figure 9 is a top plan view of the Z-directed component and PCB shown in Figure 8.

[0021] Figure 10 is a schematic cross-sectional view of a Z-directed component flush
20 mounted in a PCB showing ground loops for the Z-directed component with the Z-directed component further having a decoupling capacitor within its body according to one example embodiment.

[0022] Figure 11 is a schematic cross-sectional view of a Z-directed component flush mounted in a PCB showing a Z-directed component for transferring a signal trace from one internal layer of a PCB to another internal layer of that PCB according to one example embodiment.

25 **[0023]** Figure 12 is a perspective view of a Z-directed capacitor having semi-cylindrical sheets according to one example embodiment.

[0024] Figure 13 is an exploded view of another embodiment of a Z-directed capacitor having stacked discs according to one example embodiment.

[0025] Figure 14 is a perspective view of a sheet of substrate material having channels formed therein according to one example embodiment.

[0026] Figure 15 is an exploded view of a punch and a die block for forming a layer of a Z-directed component according to one example embodiment.

5 [0027] Figure 16 is a perspective cutaway view of a die block having a punched layer of a Z-directed component supported by a raisable elevator in a cavity of the die block according to one example embodiment.

[0028] Figure 17 is a perspective view of a layer of a Z-directed component in a constraining plate with a gap formed between a side wall surface of the constraining plate and a side channel of the layer according to one example embodiment.

[0029] Figure 18 is a schematic view of a mask for applying conductive material to a layer of a Z-directed component according to one example embodiment.

[0030] Figure 19 is a perspective view of a layer of a Z-directed component having conductive material applied through the mask shown in Figure 18 to a top surface of the layer.

15 [0031] Figure 20 is a perspective view of a Z-directed component having offset side channels according to one example embodiment.

[0032] Figure 21 is a perspective view of a punch and a die block having a stack of sheets of substrate material according to one example embodiment.

[0033] Figure 22A is a perspective view of a Z-directed component having a dome formed on an end thereof according to one example embodiment.

[0034] Figure 22B is a perspective view of a Z-directed component having a chamfered end according to one example embodiment.

[0035] Figure 23 is a perspective view of a plug for forming a taper in an end of a Z-directed component according to one example embodiment.

25 [0036] Figure 24 is a perspective view of a bottom surface of a PCB having an adhesive applied thereto in contact with a side surface of a Z-directed component inserted into a mounting hole in the PCB according to one example embodiment.

[0037] Figure 25A is a perspective view of a Z-directed component inserted into a mounting hole in a PCB, the Z-directed component having a conductive strip applied to a side surface thereof according to one example embodiment.

[0038] Figure 25B is a side cutaway view of the Z-directed component and PCB shown in
5 Figure 25A.

DETAILED DESCRIPTION

[0039] The following description and drawings illustrate embodiments sufficiently to enable those skilled in the art to practice the present invention. It is to be understood that the disclosure is not limited to the details of construction and the arrangement of components set forth in the following
10 description or illustrated in the drawings. The invention is capable of other embodiments and of being practiced or of being carried out in various ways. For example, other embodiments may incorporate structural, chronological, electrical, process, and other changes. Examples merely typify possible variations. Individual components and functions are optional unless explicitly required, and the sequence of operations may vary. Portions and features of some embodiments may be included in or
15 substituted for those of others. The scope of the application encompasses the appended claims and all available equivalents. The following description is, therefore, not to be taken in a limited sense and the scope of the present invention is defined by the appended claims.

[0040] Also, it is to be understood that the phraseology and terminology used herein is for the purpose of description and should not be regarded as limiting. The use of “including,”
20 “comprising,” or “having” and variations thereof herein is meant to encompass the items listed thereafter and equivalents thereof as well as additional items. Unless limited otherwise, the terms “connected,” “coupled,” and “mounted,” and variations thereof herein are used broadly and encompass direct and indirect connections, couplings, and mountings. In addition, the terms “connected” and “coupled” and variations thereof are not restricted to physical or mechanical
25 connections or couplings.

[0041] Overview of Z-Directed Components

[0042] An X-Y-Z frame of reference is used herein. The X and Y axes describe the plane defined by the face of a printed circuit board. The Z-axis describes a direction perpendicular to the plane of the circuit board. The top surface of the PCB has a zero Z- value. A component with a
30 negative Z-direction value indicates that the component is inserted into the top surface of the PCB. Such a component may be above (extend past), flush with, or recessed below either the top surface and/or the bottom surface of the PCB. A component having both a positive and negative Z-direction value indicates that the component is partially inserted into the surface of the PCB. The Z-directed

components are intended to be inserted into a hole or recess in a printed circuit board. Depending on the shape and length of the component(s), more than one Z-directed component may be inserted into a single mounting hole in the PCB, such as being stacked together or positioned side by side. The hole may be a through hole (a hole from the top surface through to the bottom surface), a blind hole (an opening or recess through either the top or bottom surface into an interior portion or internal layer of the PCB) or an internal cavity such that the Z-directed component is embedded within the PCB.

[0043] For a PCB having conductive traces on both external layers, one external layer is termed the top surface and the other the bottom surface. Where only one external layer has conductive traces, that external surface is referred to as the top surface. The Z-directed component is referred to as having a top surface, a bottom surface and a side surface. The references to top and bottom surfaces of the Z-directed component conform to the convention used to refer to the top and bottom surfaces of the PCB. The side surface of a Z-directed component extends between the top and bottom surfaces of the PCB and would be adjacent to the wall of the mounting hole in the PCB where the mounting hole is perpendicular to the face of the PCB. This use of top, bottom and side should not be taken as limiting how a Z-directed component may be mounted into a PCB. Although the components are described herein as being mounted in a Z-direction, this does not mean that such components are limited to being inserted into a PCB only along the Z-axis. Z-directed components may be mounted normal to the plane of the PCB from the top or bottom surfaces or both surfaces, mounted at an angle thereto or, depending on the thickness of the PCB and the dimensions of the Z-directed component, inserted into the edge of the PCB between the top and bottom surfaces of the PCB. Further, the Z-directed components may be inserted into the edge of the PCB even if the Z-directed component is wider than the PCB is tall as long as the Z-directed component is held in place.

[0044] The Z-directed components may be made from various combinations of materials commonly used in electronic components. The signal connection paths are made from conductors, which are materials that have high conductivity. Unless otherwise stated, reference to conductivity herein refers to electrical conductivity. Conducting materials include, but are not limited to, copper, gold, aluminum, silver, tin, lead and many others. The Z-directed components may have areas that need to be insulated from other areas by using insulator materials that have low conductivity like plastic, glass, FR4 (epoxy & fiberglass), air, mica, ceramic and others. Capacitors are typically made of two conducting plates separated by an insulator material that has a high permittivity (dielectric constant). Permittivity is a parameter that shows the ability to store electric fields in the materials like ceramic, mica, tantalum and others. A Z-directed component that is constructed as a resistor requires materials that have properties that are between a conductor and insulator having a finite amount of resistivity, which is the reciprocal of conductivity. Materials like carbon, doped semiconductor, nichrome, tin-oxide and others are used for their resistive properties. Inductors are typically made of

coils of wires or conductors wrapped around a material with high permeability. Permeability is a parameter that shows the ability to store magnetic fields in the material which may include iron and alloys like nickel-zinc, manganese-zinc, nickel-iron and others. Transistors such as field effect transistors ("FETs") are electronic devices that are made from semiconductors that behave in a nonlinear fashion and are made from silicon, germanium, gallium arsenide and others.

[0045] Throughout the application there are references that discuss different materials, properties of materials or terminology interchangeably as currently used in the art of material science and electrical component design. Because of the flexibility in how a Z-directed component may be employed and the number of materials that may be used, it is also contemplated that Z-directed components may be constructed of materials that have not been discovered or created to date. The body of a Z-directed component will in general be comprised of an insulator material unless otherwise called out in the description for a particular design of a Z-directed component. This material may possess a desired permittivity, e.g., the body of a capacitor will typically be comprised of an insulator material having a relatively high dielectric constant.

[0046] PCBs using a Z-directed component may be constructed to have a single conductive layer or multiple conductive layers as is known. The PCB may have conductive traces on the top surface only, on the bottom surface only, or on both the top and bottom surfaces. In addition, one or more intermediate internal conductive trace layers may also be present in the PCB.

[0047] Connections between a Z-directed component and the traces in or on a PCB may be accomplished by soldering techniques, screening techniques, extruding techniques or plating techniques known in the art. Depending on the application, solder pastes and conductive adhesives may be used. In some configurations, compressive conductive members may be used to interconnect a Z-directed component to conductive traces found on the PCB.

[0048] The most general form of a Z-directed component comprises a body having a top surface, a bottom surface and a side surface, a cross-sectional shape that is insertable into a mounting hole of a given depth D within a PCB with a portion of the body comprising an insulator material. All of the embodiments described herein for Z-directed components are based on this general form.

[0049] Figures 1 and 2 show an embodiment of a Z-directed component. In this embodiment, Z-directed component 10 includes a generally cylindrical body 12 having a top surface 12t, a bottom surface 12b, a side surface 12s, and a length L generally corresponding to the depth D of the mounting hole. The length L can be less than, equal to or greater than the depth D. In the former two cases, Z-directed component 10 would in one case be below at least one of the top and bottom surfaces of the PCB and in the other it may be flush with the two surfaces of the PCB. Where length

L is greater than depth D, Z-directed component 10 would not be flush mounted with at least one of the top and bottom surfaces of the PCB. However, with this non-flush mount, Z-directed component 10 would be capable of being used to interconnect to another component or another PCB that is positioned nearby. The mounting hole is typically a through-hole extending between the top and bottom surfaces of the PCB but it may also be a blind hole. When recessed below the surface of the PCB, additional resist areas may be required in the hole of the PCB to keep from plating the entire circumferential area around the hole.

[0050] Z-directed component 10 in one form may have at least one conductive channel 14 extending through the length of body 12. At the top and bottom ends 14t and 14b of conductive channel 14, top and bottom conductive traces 16t, 16b are provided on the top and bottom end surfaces 12t, 12b of body 12 and extend from respective ends of the conductive channel 14 to the edge of Z-directed component 10. In this embodiment, body 12 comprises an insulator material. Depending on its function, body 12 of Z-directed component 10 may be made of variety of materials having different properties. These properties include being conductive, resistive, magnetic, dielectric, or semi-conductive or various combinations of properties as described herein. Examples of materials that have the properties are copper, carbon, iron, ceramic or silicon, respectively. Body 12 of Z-directed component 10 may also comprise a number of different networks needed to operate a circuit that will be discussed later.

[0051] One or more longitudinally extending channels or wells may be provided on the side surface of body 12 of Z-directed component 10. The channel may extend from one of the top surface and the bottom surface of body 12 toward the opposite surface. As illustrated, two concave side wells or channels 18 and 20 are provided in the outer surface of Z-directed component 10 extending the length of body 12. When plated or soldered, these channels allow electrical connections to be made to Z-directed component 10, through the PCB, as well as to internal conductive layers within the PCB. The length of side channels 18 or 20 may extend less than the entire length of body 12.

[0052] Figure 2 shows the same component as in Figure 1 but with all the surfaces transparent. Conductive channel 14 is shown as a cylinder extending through the center of Z-directed component 10. Other shapes may also be used for conductive channel 14. Traces 16t and 16b can be seen extending from ends 14t and 14b of conductive channel 14, respectively, to the edge of body 12. While traces 16t and 16b are shown as being in alignment with one another (zero degrees apart), this is not a requirement and they may be positioned as needed for a particular design. For example, traces 16t and 16b may be 180 degrees apart or 90 degrees apart or any other increment.

[0053] The shape of the body of the Z-directed component may be any shape that can fit into a mounting hole in a PCB. Figures 3A – 3F illustrate possible body shapes for a Z-directed

component. Figure 3A shows a triangular cross-sectional body 40; Figure 3B shows a rectangular cross-sectional body 42; Figure 3C shows a frusto-conical body 44; Figure 3D shows an ovate cross-sectional cylindrical body 46; and Figure 3E shows a cylindrical body 48. Figure 3F shows a stepped cylindrical body 50 where one portion 52 has a larger diameter than another portion 54. With this arrangement, the Z-directed component may be mounted on the surface of the PCB while having a section inserted into a mounting hole provided in the PCB. The edges of the Z-directed component may be beveled to help with aligning the Z-directed component for insertion into a mounting hole in a PCB. Other shapes and combinations of those illustrated may also be used for a Z-directed component as desired.

[0054] For a Z-directed component, the channels for plating can be of various cross-sectional shapes and lengths. The only requirement is that plating or solder material make the proper connections to the Z-directed component and corresponding conductive traces in or on the PCB. Side channels 18 or 20 may have, for example, V-, C- or U-shaped cross-sections, semi-circular or elliptical cross-sections. Where more than one channel is provided, each channel may have the same or a different cross-sectional shape. Figures 4A – 4C illustrate three side channel shapes. In Figure 4A, V-shaped side channels 60 are shown. In Figure 4B, U- or C-shaped side channels 62 are shown. In Figure 4C, wavy or irregular cross-sectional side channel shapes 65 are shown.

[0055] The numbers of layers in a PCB varies from being single sided to being over 22 layers and may have different overall thicknesses that range from less than 0.051 inch to over 0.093 inch or more. Where a flush mount is desired, the length of the Z-directed component will depend on the thickness of the PCB into which it is intended to be inserted. The Z-directed component's length may also vary depending on the intended function and tolerance of a process. The preferred lengths will be where the Z-directed component is either flush with the surfaces or extends slightly beyond the surface of the PCB. This would keep the plating solution from plating completely around the interior of the PCB hole that may cause a short in some cases. It is possible to add a resist material around the interior of a PCB hole to only allow plating in the desired areas. However, there are some cases where it is desired to completely plate around the interior of a PCB hole above and below the Z-directed component. For example, if the top layer of the PCB is a V_{CC} plane and the bottom layer is a GND plane then a decoupling capacitor would have lower impedance if the connection used a greater volume of copper to make the connection.

[0056] There are a number of features that can be added to a Z-directed component to create different mechanical and electrical characteristics. The number of channels or conductors can be varied from zero to any number that can maintain enough strength to take the stresses of insertion, plating, manufacturing processes and operation of the PCB in its intended environment. The outer surface of a Z-directed component may have a coating that glues it in place. Flanges or radial

projections may also be used to prevent over or under insertion of a Z-directed component into the mounting hole, particularly where the mounting hole is a through-hole. A surface coating material may also be used to promote or impede migration of the plating or solder material. Various locating or orienting features may be provided such as a recess or projection, or a visual or magnetic indicator on an end surface of the Z-directed component. Further, a connecting feature such as a conductive pad, a spring loaded style pogo-pin or even a simple spring may be included to add an additional electrical connection (such as frame ground) point to a PCB.

[0057] A Z-directed component may take on several roles depending on the number of ports or terminals needed to make connections to the PCB. Some possibilities are shown in Figures 5A – H. Figure 5A is a Z-directed component configured as 0-port device 70A used as a plug so that if a filter or a component is optional then the plug stops the hole from being plated. After the PCB has been manufactured, the 0-port device 70A may be removed and another Z-directed component may be inserted, plated and connected to the circuit. Figures 5B – 5H illustrate various configurations useful for multi-terminal devices such as resistors, diodes, transistors, and/or clock circuits. Figure 5B shows a 1-port or single signal Z-directed component 70B having a conductive channel 71 through a center portion of the component connected to top and bottom conductive traces 72t, 72b. Figure 5C shows a 1-port 1-channel Z-directed component 70C where one plated side well or channel 73 is provided in addition to conductive channel 71 through the component, which is connected to top and bottom conductive traces 72t and 72b. Figure 5D shows a Z-directed component 70D having two side wells 73 and 75 in addition to conductive channel 71 through the component which is connected to top and bottom traces 72t, 72b. The Z-directed component 70E of Figure 5E has three side wells 73, 75 and 76 in addition to conductive channel 71 through the component, which is connected to top and bottom traces 72t, 72b. Figure 5F shows Z-directed component 70F having two conductive channels 71 and 77 through the component each with their respective top and bottom traces 72t, 72b and 78t, 78b and no side channels or wells. Z-directed component 70F is a two signal device to be primarily used for differential signaling. Figure 5G shows a Z-directed component 70G having one side well 73 and two conductive channels 71 and 77 each with their respective top and bottom traces 72t, 72b and 78t, 78b. Figure 5H shows Z-directed component 70H having one conductive channel 71 with top and bottom traces 72t, 72b and a blind well or partial well 78 extending from the top surface along a portion of the side surface that will allow the plating material or solder to stop at a given depth. For one skilled in the art, the number of wells and signals is only limited by the space, required well or channel sizes.

[0058] Figures 6A-C illustrate another configuration for a Z-directed component utilizing O-rings for use in a PCB having a top and bottom conductive layer and at least one internal conductive layer. Z-directed component 150 is shown having on its top surface 150t, a locating feature 152 and a

conductive top trace 154t extending between a conductive channel 156 and the edge of body 150d on its top surface 150t. A conductive bottom trace (not shown) is provided on the bottom surface.

Conductive channel 156 extends through a portion of the body 150d as previously described. Located on the side surface 150s of body 150d is a least one semi-circular channel or groove. As shown, a pair of axially spaced apart circumferential channels 158a, 158b is provided having O-rings 160a, 160b, respectively disposed within channels 158a, 158b. A portion of the O-rings 160a, 160b extend out beyond the side surface 150s of the body 150d. O-rings 160a, 160b would be positioned adjacent one or more of the internal layers of the PCB to make electrical contact to one or more traces provided at that point in the mounting hole for the Z-directed component. Depending on the design employed, an O-ring would not have to be provided adjacent every internal layer.

[0059] O-rings 160a, 160b may be conductive or non-conductive depending on the design of the circuit in which they are used. O-rings 160a, 160b preferably would be compressive helping to secure Z-directed component 150 within the mounting hole. The region 162 of body 150d intermediate O-rings 160a, 160b may be comprised of different material than the regions 164 and 166 of the body 150d outside of the O-rings. For example, if the material of region 162 is of a resistive material and O-rings 160a, 160b are conductive then internal circuit board traces in contact with the O-rings 160a, 160b see a resistive load.

[0060] Regions 164 and 166 may also be comprised of a material having different properties from each other and region 162. For example, region 164 may be resistive, region 162 capacitive and region 166 inductive. Each of these regions can be electrically connected to the adjoining layers of the PCB. Further, conductive channel 156 and traces 154t, 154b do not need to be provided. So for the illustrated construction, between the top layer of the PCB and the first internal layer from the top, a resistive element may be present in region 164, a capacitive element between the first internal layer and the second internal layer in region 162 and an inductive element between the second internal layer and the bottom layer of the PCB in region 166. Accordingly, for a signal transmitted from an internal trace contacting conductive O-ring 160a to a second internal trace contacting conductive O-ring 160b, the signal would see an inductive load. The material for regions 162, 164, 166 may have properties selected from a group comprising conductive, resistive, magnetic, dielectric, capacitive or semi-conductive and combinations thereof. The design may be extended to circuit boards having fewer or more internal layers than that described without departing from the spirit of the invention.

[0061] In addition, regions 162, 164, 166 may have electronic components 167, 169, 171 embedded therein and connected as described herein. Also, as illustrated for component 171, a component may be found within one or more regions within the body of a Z-directed component. Internal connections may be provided from embedded components to O-rings 160a, 160b.

Alternatively, internal connections may be provided from the embedded components to plateable pads provided on the side surface 150s.

[0062] The various embodiments and features discussed for a Z-directed component are meant to be illustrative and not limiting. A Z-directed component may be made of a bulk material that performs a network function or may have other parts embedded into its body. A Z-directed component may be a multi-terminal device and, therefore, may be used to perform a variety of functions including, but not limited to: transmission lines, delay lines, T filters, decoupling capacitors, inductors, common mode chokes, resistors, differential pair pass throughs, differential ferrite beads, diodes, or ESD protection devices (varistors). Combinations of these functions may be provided within one component.

[0063] Figure 7 illustrates various example configurations for a conductive channel in a Z-directed component. As shown, channel 90 has a region 92 intermediate the ends comprising a material having properties selected from a group comprising conductive, resistive, magnetic, dielectric, capacitive or semi-conductive properties and combinations thereof. These materials form a variety of components. Additionally, a component may be inserted or embedded into region 92 with portions of the conductive channel extending from the terminals of the component. A capacitor 92a may be provided in region 92. Similarly, a diode 92b, a transistor 92c such as a MOSFET 92d, a zener diode 92e, an inductor 92f, a surge suppressor 92g, a resistor 92h, a diac 92i, a varactor 92j and combinations of these items are further examples of materials that may be provided in region 92 of conductive channel 90. While region 92 is shown as being centered within the conductive channel 90, it is not limited to that location.

[0064] For a multi-terminal device such as transistor 92c, MOSFET 92d, an integrated circuit 92k, or a transformer 92l, one portion of the conductive channel may be between the top surface trace and a first terminal of the device and the other portion of the conductive channel between the bottom surface trace and a second terminal of the device. For additional device terminals, additional conductors may be provided in the body of the Z-directed component to allow electrical connection to the remaining terminals or additional conductive traces may be provided within the body of the Z-directed component between the additional terminals and channels on the side surface of the body of a Z-directed component allowing electrical connection to an external conductive trace. Various connection configurations to a multiple terminal device may be used in a Z-directed component.

[0065] Accordingly, those skilled in the art will appreciate that various types of Z-directed components may be utilized including, but not limited to, capacitors, delay lines, transistors, switches, and connectors. For example, Figures 8 and 9 illustrate a Z-directed component termed a signal pass-through that is used for passing a signal trace from the top surface of a PCB to the bottom surface.

[0066] Z-Directed Signal Pass-Through Component

[0067] Figure 8 shows a sectional view taken along line 8–8 in Figure 9 of a PCB 200 having 4 conductive planes or layers comprising, from top to bottom, a ground (GND) plane or trace 202, a voltage supply plane V_{CC} 204, a second ground GND plane 206 and a third ground GND plane or trace 208 separated by nonconductive material such as a phenolic plastic such as FR4 which is widely used as is known in the art. PCB 200 may be used for high frequency signals. The top and bottom ground planes or traces 202 and 208, respectively, on the top and bottom surfaces 212 and 214, respectively, of PCB 200 are connected to conductive traces leading up to Z-directed component 220. A mounting hole 216 having a depth D in a negative Z direction is provided in PCB 200 for the flush mounting of Z-directed component 220. Here depth D corresponds to the thickness of PCB 200; however, depth D may be less than the thickness of PCB 200 creating a blind hole therein. Mounting hole 216, as illustrated, is a through-hole that is round in cross-section to accommodate Z-directed component 220 but may have cross sections to accommodate the insertion of Z-directed components having other body configurations. In other words, mounting holes are sized so that Z-directed components are insertable therein. For example, a Z-directed component having a cylindrical shape may be inserted into a square mounting hole and vice versa. In the cases where Z-directed component does not make a tight fit, resist materials will have to be added to the areas of the component and PCB where copper plating is not desired.

[0068] Z-directed component 220 is illustrated as a three lead component that is flush mounted with respect to both the top surface 212 and bottom surface 214 of PCB 200. Z-directed component 220 is illustrated as having a generally cylindrical body 222 of a length L. A center conductive channel or lead 224, illustrated as being cylindrical, is shown extending the length of body 222. Two concave side wells or channels 226 and 228, which define the other two leads, are provided on the side surface of Z-directed component 220 extending the length of body 222. Side channels 226 and 228 are plated for making electrical connections to Z-directed component 220 from various layers of PCB 200. As shown, the ground plane traces on layers 202, 206, and 208 of PCB 100 are electrically connected to side channels 226 and 228. V_{CC} plane 204 does not connect to Z-directed component 220 as shown by the gap 219 between V_{CC} plane 204 and wall 217 of mounting hole 216.

[0069] Figure 9 illustrates a top view of Z-directed component 220 in PCB 200. Three conductive traces 250, 252 and 254 lead up to the edge of wall 217 of mounting hole 216. As illustrated, trace 252 serves as a high-frequency signal trace to be passed from the top surface 212 to the bottom surface 214 of PCB 200 via Z-directed component 220. Conductive traces 250 and 254 serve as ground nets. Center lead or conductive channel 224 is electrically connected to trace 252 on the top surface 212 of PCB 200 by a top trace 245 and plating bridge 230. Top trace 245 on the top surface of Z-directed component 220 extends from the top end 224t of conductive channel 224 to the

edge of Z-directed component 220. Although not shown, the bottom side of Z-directed component 220 and bottom surface 214 of PCB 200 is configured in a similar arrangement of traces as shown on top surface 212 of PCB 200 illustrated in Figure 12. A bottom trace on the bottom surface of Z-directed component 220 extends from bottom of conductive channel 224 to the edge of Z-directed component 220. A plating bridge is used to make the electrical connection between the bottom trace and another high frequency signal trace provided on the bottom surface of PCB 200. The transmission line impedance of the Z-directed component can be adjusted to match the PCB trace impedance by controlling the conductor sizes and distances between each conductor which improves the high speed performance of the PCB.

[0070] During the plating process, wells 256 and 258 formed between wall 217 of mounting hole 216 and side channels 226 and 228 allow plating material or solder pass from the top surface 212 to the bottom surface 214 electrically interconnecting traces 250 and 254, respectively to side channels 226 and 228, respectively, of Z-directed component 220 and also to similarly situated traces provided on the bottom surface 214 of PCB 200 interconnecting ground planes or traces 202, 206 and 208. The plating is not shown for purposes of illustrating the structure. In this embodiment, V_{CC} plane 204 does not connect to Z-directed component 220.

[0071] One of the challenges for high frequency signal speeds is the reflections and discontinuities due to signal trace transmission line impedance changes. Many PCB layouts try to keep high frequency signals on one layer because of these discontinuities caused by the routing of signal traces through the PCB. Standard vias through a PCB have to be spaced some distance apart which creates high impedance between the signal via and the return signal via or ground via. As illustrated in Figures 8 and 9, the Z-directed component and the return ground or signals have a very close and controlled proximity that allow essentially constant impedance from the top surface 212 to the bottom surface 214 of PCB 200.

[0072] A Z-directed signal pass through component may also comprise a decoupling capacitor that will allow the reference plane of a signal to switch from a ground plane, designated GND, to a voltage supply plane, designated V_{CC} , without having a high frequency discontinuity. Figure 10 shows a cross-sectional view of a typical 4-layer PCB 300 with a signal trace 302 transferring between the top layer 304 and the bottom layer 306. Z-directed component 310, similar to that shown in Figure 5D, having body 312 connects signal trace 302 through center conductive channel 314. Z-directed component 310 also comprises plated side channels 316 and 318 extending along the side surface 312s of the body 312. The top 314t and bottom 314b of conductive channel 314 are connected to conductive traces 318t and 318b on the top 312t and bottom 312b of body 312. These, in turn, are connected to signal trace 302 via top and bottom plating bridges 330t and 330b. Side channels 316 and 318 are plated to GND plane 332 and V_{CC} plane 334, respectively. Connection

points 336 and 338, respectively, illustrate this electrical connection. Schematically illustrated decoupling capacitor 350 is internal to body 312 and is connected between side channels 316 and 318. Decoupling capacitor 350 may be a separate capacitor integrated into the body 312 of Z-directed component 310 or it can be formed by fabricating a portion of the body 312 of Z-directed component 310 from the required materials with dielectric properties between conductive surfaces.

[0073] The path for signal trace 302 is illustrated with diagonal hatching and can be seen to run from top layer 304 to bottom layer 306. GND plane 332 and side channel 316 are electrically connected at 336 with the signal path return indicated by the dark stippling 362. V_{CC} plane 334 and side channel 318 are electrically connected at 338 with the signal path return indicated by the light stippling 364. As is known in the art, where a signal plane or trace is not to be connected to the inserted part, those portions are spaced apart from the component as shown at 370. Where a signal plane or trace is to be connected to an inserted component, the signal plane or trace is provided at the wall or edge of the opening to allow the plating material or solder to bridge therebetween as illustrated at points 330t, 330b, 336, and 338.

[0074] The vertically hatched portion 380 shows the high speed loop area between the signal trace and return current path described by the signal trace 302 and the GND plane 332 or V_{CC} plane 334. The signal trace 302 on the bottom surface 306 is referenced to power plane V_{CC} 334 that is coupled to the GND plane 332 through decoupling capacitor 350. This coupling between the two planes will keep the high frequency impedance close to constant for the transition from one return plane to another plane of a different DC voltage.

[0075] Internally mounting Z-directed components in a PCB greatly facilitates the PCB technique of using outer ground planes for EMI reduction. With this technique, signals are routed on the inner layers as much as possible. Figure 11 illustrates one embodiment of this technique. PCB 400 is comprised of, from top to bottom, top ground layer 402, internal signal layer 404, internal signal layer 406 and bottom ground layer 408. Ground layers 402 and 408 are on the top and bottom surfaces 400t and 400b of PCB 400. A mounting hole 410, shown as a through-hole, extends between the top and bottom surfaces 400t and 400b. Z-directed component 420 is shown flush mounted in PCB 400. Z-directed component 420 comprises body 422 having a center region 424 intermediate the top 422t and bottom 422b of body 422 and two side channels 425 and 427 on side surface 422s.

[0076] Side channels 425 and 427 and wall 411 of hole 410 form plating wells 413 and 415 respectively. Center region 424 is positioned within body 422 and extends a distance approximately equal to the distance separating the two internal signal layers 404 and 406. Side channel 425 extends from the bottom surface 422b of body 422 to internal signal level 406 while side channel 427 extends from top surface 422t of body 422 to internal signal level 404. Here, side channels 425 and 427

extend only along a portion of side surface 422s of body 422. Conductive channel 426 extends through center region 424 but does not extend to the top and bottom surfaces 422t, 422b of body 422. Figure 5H illustrates a partial channel similar to side channel 427. Conductive channel 426 has conductive traces 428t and 428b extending from the top 426t and bottom 426b of conductive channel 426 to side channels 427 and 425, respectively. While illustrated as separate elements, conductive channel 426 and traces 428t, 428b may be one integrated conductor electrically interconnecting side channels 425, 427. As shown, conductive trace 428b is connected to internal signal layer 406 via plated side channel 425 and well 413 while trace 428t connects to internal signal level 404 via side channel 427 and well 415. Ground layers 402 and 408 are not connected to Z-directed component 420 and are spaced away from mounting hole 410 as previously described for Figures 8 and 10. As shown by double headed dashed arrow 430, a signal on signal layer 406 can be via'd to signal layer 404 (or vice versa) via Z-directed component 420 through a path extending from well 413, side channel 425, trace 428b, conductive channel 426, trace 428t, side channel 427, and well 415 to allow the signal to remain on the inner layers of PCB 400 with ground layers 402 and 408 providing shielding.

[0077] Z-directed Decoupling Capacitors

[0078] Figures 12 and 13 illustrate two additional example Z-directed components in the form of decoupling capacitors. In Figure 12, a Z-directed capacitor 500 is shown with a body 502 having a conductive channel 504 and two side channels 506 and 508 extending along its length similar to those previously described. Conductive channel 504 is shown connected to a signal 526. Vertically oriented interleaved partial cylindrical sheets 510, 512 forming the plates of Z-directed capacitor 500 are connected to reference voltages such as voltage V_{CC} and ground (or any other signals requiring capacitance) and are used with intervening layers of dielectric material (not shown). Partial cylindrical sheet 510 is connected to plated channel 506 which is connected to ground 520. Partial cylindrical sheet 512 is connected to plated channel 508 which is connected to supply voltage V_{CC} 522. Sheets 510, 512 may be formed of copper, aluminum or other material with high conductivity. The material between the partial cylindrical sheets is a material with dielectric properties. Only one partial cylindrical sheet is shown connected to each of V_{CC} 522 and ground 520; however, additional partial cylindrical sheets may be provided to achieve the desired capacitance/voltage rating.

[0079] Another embodiment of a Z-directed capacitor is shown in Figure 13 using stacked support members connected to voltage V_{CC} or ground. Z-directed capacitor 600 is comprised of center conductive channel 601 and a body 605 comprised of a top member 605t, a bottom member 605b, and a plurality of support members 610 (illustrated as disks) between the top and bottom members 605t, 605b.

[0080] Center conductive channel 601 extends through openings 615 in the assembled Z-directed capacitor 600 and openings 602t and 602b, all of which are sized to closely receive the center conductor. Center conductive channel 601 is electrically connectable to conductive traces 603t and 603b on the top and bottom portions 605t, 605b forming a signal path for signal 626. This connection
5 is made by plating or soldering. Center conductive channel 601 is connected to signal 626 via conductive trace 603t. The bottom end of conductive channel 601 is connected in a similar fashion to a signal trace (not shown) via conductive trace 603b.

[0081] Opposed openings 607t and 608t are provided at the edge of top portion 605t. Bottom portion 605b is of similar construction as top portion 605t having opposed openings 607b and
10 608b provided at the edge. Between top and bottom portions 605t, 605b are a plurality of support members 610, which provide the capacitive feature. Support members 610 each have at least one opening 613 at their outer edge and an inner hole 615 allowing for passage of conductive channel 601 therethrough. As shown, two opposed openings 613 are provided in each support member 610. When assembled, the opposed openings 607t, 607b, 608t, 608b, and 613 align to form opposed side
15 channels 604 and 608 extending along the side surface of Z-directed capacitor 600. Side channel 604 is shown connected to reference voltage such as ground 620 and side channel 606 to another reference voltage such as V_{CC} 622. Support members 610 may be fabricated from a dielectric material and may be all of the same or varying thickness allowing for choice in designing the desired properties for Z-directed capacitor 600.

[0082] Annular plating 617 is provided on one of top and bottom surfaces of support member 610 or, if desired, on both surfaces. Annular plating is shown on the top surface of each support member but location of the annular plating can vary from support member to support member. Annular plating 617 generally conforms to the shape of the support member and extends from one of the edge openings 613 toward the other if an additional opening is provided. The annular plate 617 is
25 of a diameter or dimension or overall size that is less than the diameter, dimension or overall size of support member 610 on which it is affixed. While the plate 617 is described as annular, other shapes may also be used provided that the plating does not contact the center conductive channel or extend to the edge of the support member on which it is plated or otherwise affixed. The annular plate does contact one of the edge openings 613 but is spaced apart from the other openings if more than one
30 channel is present in the side surface of the body of Z-directed capacitor 600. Also, there is an opening 619 in annular plate 617 having a larger diameter than opening 615 in annular plate 617 through which conductive channel 601 passes. Opening 619 has a larger diameter than that of conductive channel 601 leaving annular plate 617 spaced apart from conductive channel 601.

[0083] As illustrated, the support members 610 are substantially identical except that when
35 stacked, alternate members are rotated 180 degrees with respect to the member above or below it.

This may be referred to as a 1-1 configuration. In this way, alternate members will be connected to one or the other of the two side channels. As shown in Figure 13, the annular plating on the upper one of the two support members 610 is connected to side channel 608 and voltage V_{CC} 622 while the annular plating on the lower one of the two support members 610 is connected to side channel 604 and ground 620. Other support member arrangements may also be used such as having two adjacent members connected to the same channel with the next support member being connected to the opposite channel which may be referred to as a 2-1 configuration. Other configurations may include 2-2, 3-1 and are a matter of design choice. The desired capacitance or voltage rating determines the number of support members that are inserted between top and bottom portions 605t, 605b. Although not shown, dielectric members comprised of dielectric material and similarly shaped to support members 610 may be interleaved with support members 610. Based on design choice, only a single channel may be used or more channels may be provided and/or the annular plating may be brought into contact with the center conductive channel and not in contact with the side channels. Again, the embodiments for Z-directed capacitors are for purposes of illustration and are not meant to be limiting.

[0084] With either design for a Z-directed capacitor, a second conductive channel may be provided in parallel with the first conductive channel that is disposed within the conductive plates to create a differential decoupling capacitor. Another embodiment of a Z-directed capacitor can be constructed from Figure 12 or Figure 13 by connecting the center conductive channel to one of the reference voltages at each support member that also has its annular plating connected to the same reference voltage. This may be accomplished simply by connecting the conductive channel to the annular plating as schematically illustrated by the jumper 621. In practice, the annular opening 619 in the annular plate 617 would be sized so that the annular plate and conductive channel 601 would be electrically connected. This component may be placed directly below a power pin or ball of an integrated circuit or other surface mounted component for optimum decoupling placement.

[0085] Again, the Z-directed signal pass-through components illustrated in Figures 8-11 and the Z-directed decoupling capacitors illustrated in Figures 12 and 13 provide merely a few example applications of a Z-directed component. Those skilled in the art will appreciate that various other types of Z-directed components may be utilized including, but not limited to, transmission lines, delay lines, T filters, decoupling capacitors, inductors, common mode chokes, resistors, differential pair pass throughs, differential ferrite beads, diodes, or ESD protection devices (varistors).

[0086] Die Press Process for Manufacturing a Z-Directed Component

[0087] A die press process for manufacturing the Z-directed components on a commercial scale is provided. In the die press process, the bodies of the Z-directed components are formed from

sheets of a material that forms the component substrate. As needed, the sheets may also include a binder material as is known in the art. As discussed above, a variety of different Z-directed components are contemplated herein including, but not limited to, transmission lines, delay lines, T filters, decoupling capacitors, inductors, common mode chokes, resistors, differential pair pass
5 throughs, differential ferrite beads, diodes, and ESD protection devices (varistors). Accordingly, it will be appreciated that the substrate material used will depend on the Z-directed component desired. The substrate material may include a single dielectric material that has a relative permittivity from about 3, e.g., polymers, to over 10,000, e.g., barium titanate (BaTiO_3). For example, a material with a relatively high dielectric value may be used in a Z-directed decoupling capacitor and a material with a
10 relatively low dielectric value may be used in a Z-directed signal pass-through component. If a Z-directed component is desired to have an inductive function or a delay line then a ferrite material may be selected that has a low or high relative permeability with a range of about 1 to about 50,000. If a Z-directed component is desired to have some degree of conductivity then a conductive material may be mixed with a dielectric material to create a desired resistance. Depending on the function of the Z-
15 directed component desired, these or other compatible materials may be mixed together to form a component layer.

[0088] With reference to Figure 14, a sheet 700 of substrate material is illustrated. In one embodiment, sheet 700 is a green (unfired) ceramic tape; however, various substrate materials may be used as discussed above. In some embodiments, the thickness of sheet 700 is between about 0.5 mil
20 and about 62 mil (about 0.0127 mm and about 1.57mm), including all increments and values therebetween, depending on the application in which the Z-directed component will be used. Dashed line 702 outlines one layer of the Z-directed component. A substantially cylindrical layer is shown in the example embodiment illustrated; however, as discussed above, many different shapes may be used. The thicknesses of the layers making up a Z-directed component may be uniform or may vary
25 within a single Z-directed component.

[0089] At least one channel 704 is formed through sheet 700 that will later be plated with conductive material to form at least one conductive channel through the layer as discussed in greater detail below. Channel(s) 704 may pass through an interior portion of the layer, along the side surface of the layer or a combination of the two may be used. For example, in the embodiment illustrated,
30 one center channel 704a and two side channels 704b, 704c have been formed in the layer outlined by dashed line 702 in sheet 700. Each channel 704 may pass through the entire length of the Z-directed component or only a portion thereof as desired. In one embodiment, each channel 704 is punched using a solid core punch tool. Channel 704 may also be formed using a thin wall core punch that removes material like a cookie cutter or by mechanically or laser cutting the channel(s) 704.

[0090] With reference to Figure 15, each layer of the Z-directed component is punched out of sheet 700 to form a plurality of layers of the Z-directed component. The layers making up a single Z-directed component may be punched from the same sheet or different sheets. Each layer may be formed from the same substrate material or some layers may be formed from different substrate materials. Sheet 700 is positioned on a die block 706 having a cavity 708 formed therein. A punch 710 is then used to punch a segment of sheet 700 through die block 706 into cavity 708 to form a layer of the Z-directed component. Punch 710 may include a solid core punch tool or a thin wall core punch. In one embodiment, one or more channels 704 are formed in sheet 700 before the component layer is punched; however, this sequence may be reversed as desired such that a component layer is punched and then channel(s) 704 are formed therein.

[0091] Cavity 708 may be shaped to matably receive the punched layer or to further shape the punched layer. For example, in the example embodiment illustrated in Figure 15, cavity 708 includes a pair of side wall protrusions 709a, 709b therein. Protrusions 709a, 709b are each sized and shaped to receive side channels 704b, 704c, respectively, formed in the punched layer. In an alternative embodiment, side channels 704b, 704c are not formed prior to punching the segment into die block 706. Rather, when the layer is punched, protrusions 709a, 709b form side channels 704b, 704c in the punched layer. The punched layers are then stacked to form the Z-directed component as discussed in greater detail below.

[0092] For the sake of simplicity, Figure 15 illustrates a single punch 710; however, the punch tool used for commercial production purposes may include an array of punches 710 and corresponding cavities 708 formed in one or more die blocks 706 in order to process many parts at a time. A planar batch process may be used where a series of punches 710 are lowered simultaneously or a roller process may be used that can punch layers continuously. In some embodiments, sheet 700 includes a backing layer for stability due to its low beam strength. This backing layer is removed before stacking the punched layers to form the Z-directed component. Removal can be performed before component layers are punched from sheet 700 or after; however, removing the backing layer after the component layers have been punched may require additional processing steps.

[0093] With reference to Figure 16, if a conductive trace or plating on a top surface 712t or both top and bottom surfaces of a component layer 712 is desired or if a conductive channel through the layer 712 is desired, conductive material is applied to the punched layer 712. In the example embodiment illustrated, a conductive trace or plating is applied to top surface 712t of the layer 712 as it is retained in cavity 708 of die block 706. In one embodiment, cavity 708 has a height that is substantially equal to the height of layer 712, i.e., the thickness of sheet 700, so that top surface 712t of the punched layer 712 is positioned flush with a top surface 706t of die block 706 to facilitate the application of conductive material to top surface 712t of the punched layer 712. Alternatively, cavity

708 may have a height that is greater than the height of layer 712 such that top surface 712t is recessed below top surface 706t of die block 706. However, it will be appreciated that positioning top surface 712t of the punched layer 712 flush with top surface 706t of die block 706 minimizes the distance from the conductive material source to the layer 712 and thereby permits optimal placement of conductive material on top surface 712t.

[0094] If it is desired to plate one or more side channels in the component layer 712, such as side channels 704b, 704c, the layer 712 is placed in a cavity 715 in a constraining plate 714 that has a side wall surface 716 that is spaced from the side channels 704b, 704c in the component layer 712 such that a gap 718 is formed therebetween (Figure 17). This spacing allows conductive material to flow into gap 718 to plate the desired side channel(s) 704b, 704c. Another alternative to plate side channels 704b, 704c is to apply conductive material after the Z-directed component has been assembled by painting, jetting, sputter, or other known methods.

[0095] A number of different methods may be used to apply conductive material to top surface 712t of the punched layer 712. For example, in one embodiment, a mask is applied to top surface 712t that restricts the application of conductive material to selected portions of top surface 712t. Conductive material is then screened through the mask onto the component layer 712. Figure 18 shows an example mask in the form of a physical mask 720 that is placed on top surface 712t of the punched layer 712. The diagonal hatching included in Figure 18 illustrates the openings in mask 720. Mask 720 includes a center opening 722 that permits conductive material to flow into and plate center conductive channel 704a. Mask 720 also includes a pair of peripheral openings 724a, 724b that permit conductive material to plate top surface 712t. Peripheral openings 724a, 724b are separated by a thin mask portion 726 that also separates center opening 722 from peripheral openings 724a, 724b. Portion 726 is required when one or more conductive channels through the interior of the layer 712 are desired in order to provide one or more interior openings in the mask such as center opening 722 in mask 720. Mask 720 includes a pair of scalloped portions 728a, 728b that are positioned above side channels 704b, 704c in the example embodiment illustrated. Scalloped portion 728b projects slightly further inward than scalloped portion 728a. As a result, in this example embodiment, conductive material is permitted to flow onto the portion of top surface 712t that connects with side channel 704b but conductive material is not permitted to connect with side channel 704c.

[0096] The resulting plated layer 712 utilizing example mask 720 is shown in Figure 19 having conductive material 730 thereon. As shown, center channel 704a has been plated with conductive material 730. Top surface 712t of layer 712 has been plated to make a connection with side channel 704b but not side channel 704c. The mask 720 shown in Figure 18 is intended to illustrate one example of a suitable mask. Alternative masks may be employed depending on such

factors as the shape of the layer, the number of center channels and/or side channels that require plating, and the plating pattern desired for top surface 712t.

[0097] As an alternative to a physical mask, such as mask 720, a photoresist mask may be applied using photochemical methods known in the art. In this embodiment, a radiation-sensitive photoresist is applied to top surface 712t and then selectively exposed to a radiation source, such as X-ray or UV light. The photoresist is then developed to wash away the areas where the photoresist layer is not desired. It will be appreciated that positive or negative photoresists may be used as desired. Conductive material can then be screened through the photoresist mask onto top surface 712t of the component layer 712 such as by spin coating liquid conductive material on top of the photoresist mask. After the conductive material is applied, the remaining photoresist can then be removed.

[0098] In another embodiment, instead of using a mask, a selective jetting process is used to apply conductive material to top surface 712t and/or channel(s) 704. In this embodiment, liquid conductive material is applied to the component layer 712 using a fluid ejection mechanism as is known in the art. Where an etchable conductive material is used, another alternative is to spin coat or otherwise apply a layer of liquid conductive material across the entire top surface 712t and then selectively etch the conductive material from top surface 712t to form the desired conductive pattern thereon.

[0099] Another alternative is to first selectively apply a seed layer of conductive material to the component layer 712 and then apply additional conductive material by electrolysis techniques. One suitable method for applying the seed layer includes the use of photochemical methods. A photoresist layer is applied across the entire top surface 712t of the Z-directed component layer 712 and then selectively exposed to a radiation source. The photoresist is then developed to wash away the areas where the photoresist layer is not desired. Again, positive or negative photoresists may be used as desired. Conductive material is then applied across the entire top surface 712t of the Z-directed component layer 712. The remainder of the photoresist is then etched away thereby also removing the conductive material from those areas where the seed layer is not desired. Electrolysis techniques are then applied to thicken the layer of conductive material on the component layer 712.

[00100] The various methods for applying conductive material to the Z-directed component layer described herein are equally applicable where it is desired to apply a material other than conductive material such as, for example resistive, magnetic, dielectric, or semi-conductive material to component layer 712. It will be appreciated that the Z-directed component layers do not need to be punched prior to applying conductive material. In an alternative embodiment, conductive material is first applied to predetermined portions of sheet 700 and one or more segments of sheet 700 are then

punched to form one or more punched layers. Further, channel(s) 704 do not need to be plated after each layer is formed. Rather, channel(s) 704 may be filled with conductive material after the component layers are stacked together.

[00101] Once a desired number of component layers are formed and conductive and/or other materials are applied as desired, the component layers are stacked and combined to form the Z-directed component. With reference back to Figure 15, in the example embodiment illustrated, a raisable elevator 740 is positioned in cavity 708. Elevator 740 allows successive layers of the Z-directed component to be conveniently punched and stacked on top of each other. Elevator 740 is first positioned in cavity 708 such that a height of the open space in cavity 708 is at least the height of the first layer to be punched. In one embodiment, elevator 740 is first positioned in cavity 708 such that a height of the open space in cavity 708 is substantially equal to the height of the first layer to be punched in order to position a top surface of the first layer flush with top surface 706t of die block 706 as discussed above. A first segment is then punched from sheet 700 to form the first layer. Conductive material is applied to the first layer as desired. Elevator 740 is then lowered to create additional space in cavity 708 on top of the first punched segment that is at least the height of the second layer to be punched. As discussed above, the height of the additional space in cavity 708 may be substantially equal to the height of the next layer to be punched. The second segment is then punched from sheet 700 or a different sheet to form a second layer stacked on top of the first layer. Conductive material is then applied to the second layer as desired. This process is repeated until all of the layers for a given Z-directed component are punched and stacked.

[00102] Alternatively, multiple stackable die blocks 706 may be used to form the Z-directed component. Elevator 740 is not required in this embodiment. Each of the stackable die blocks 706 has a cavity 708 through the die block 706 for a punched segment therein. The height of each die block 706 may be substantially equal to the height of a corresponding layer of the Z-directed component to minimize the distance from the conductive material source to the component layer as discussed above. The lowermost die block 706 includes an enclosed cavity 708 or is positioned on a flat plate in order to retain the punched segment(s) in its cavity 708. After a first segment is punched from sheet 700 into cavity 708 of a first die block and conductive material is applied, a second die block is stacked on top of the first die block. A second segment is punched from sheet 700 into cavity 708 of the second die block and conductive material is applied as desired. Again, this process can be repeated until all of the layers for a given Z-directed component are punched and stacked.

[00103] In some embodiments, a Z-directed component 742 may be desired that includes partial side channels 704 that are twisted or offset from each other between the top and bottom halves of the component as shown in Figure 20. This type of component may be desired in order to permit an interior signal to enter on one side of the Z-directed component 742 and exit at a 90 degree angle

thereto without running into a side channel 704. This offset can be accomplished using a die block 706 that has a cylindrical cavity 708 in combination with different punch 710 shapes or by stacking die blocks 706 having different shaped cavities 708.

[00104] As an alternative to stacking each layer of the Z-directed component after it has been punched, multiple sheets 700 of substrate material can be stacked one on top of the other as shown in Figure 21 prior to punching the component layers. Prior to stacking the sheets 700, conductive material can be applied as desired to a predetermined portion of each sheet 700 as discussed above. Channel(s) 704 can be formed either before the sheets 700 are stacked or after depending on whether the channel 704 is to extend all the way through the part. Where a blind channel 704 is desired, a portion of the sheets 700 may be stacked together and the blind channel formed therethrough. The sheets 700 having the blind channel 704 formed therein can then be combined with the rest of the sheets 700 forming the Z-directed component. After the sheets 700 are stacked, they may be pressed and temperature treated to solidify the stack if desired. A punch 710 and die block 706 is then used to press out the entire stack of component layers 712 simultaneously. Figure 21 illustrates a plurality of layers 712 within cavity 708 of die block 706 that have been punched by punch 710 from corresponding sheets 700.

[00105] In one embodiment, once the component layers are stacked, they are compressed with moderate heat to create an aggregate that is solid enough to be removed from the die block(s) 706 or constraining plate(s) 714 in which they are positioned to be fired later. Where elevator 740 is used, it is first lowered so that the entire stack is contained within cavity 708 or 715. This pressing step is similar to the punch step described above in that a movable component similar to a punch, e.g., a rod or a plug, applies a desired force to one end of the stacked layers to create the desired pressure profile for the materials chosen. Heating elements can be embedded into the walls of cavity 708 or 715 in order to supply a desired temperature profile to the stacked layers. Where multiple stackable die blocks 706 are used, different spatial temperatures may be applied through each die block 706. In this configuration, each die block 706 defines the contact points between the heating elements and the stacked layers thereby allowing substantially uniform heating contact between the internal cavity walls of die blocks 706 and the stacked layers. The spatial temperature profile may also be varied in those embodiments where elevator 740 is used with a single cavity 708 or 715 by varying the arrangement of the heating elements in cavity 708 or 715.

[00106] In some embodiments, a chamfer, dome or other form of taper or lead-in of at least one of the top and bottom edge of the Z-directed component is desired in order to ease insertion of the Z-directed component into the mounting hole in the PCB. For example, Figure 22A shows a Z-directed component 744 having a dome 745 formed on an end thereof. Figure 22B shows a Z-directed component 746 having a chamfered end 747. The dome 745 or chamfer 747 may be part of

the component or attached thereto. In one embodiment, the dome 745 or chamfer 747 is a separate part that is partially inserted into the mounting hole in the PCB. In this embodiment, the Z-directed component is then inserted behind the dome 745 or chamfer 747 to push it through the mounting hole causing the dome 745 or chamfer 747 to expand the mounting hole and prevent the component from cutting or tearing the PCB. Where the dome 745 or chamfer 747 is attached to the Z-directed component, it may be configured to remain attached to the Z-directed component following insertion into the mounting hole in the PCB or it may be used to facilitate insertion and then removed.

[00107] One method for forming the desired taper as part of the Z-directed component utilizes a plug 750 having a recess 752 formed in an end 754 thereof having a tapered rim 756 around a periphery of recess 752 as shown in Figure 23. Tapered rim 756 is chamfered in the example embodiment illustrated; however, a domed, elliptical or rounded rim may also be used depending on the shape of the taper desired. Plug 750 is used to compress the stacked component layers as described above. When plug 750 applies a force to an end of the stacked layers, the end of the part is reflowed to have the desired geometry and the conductive path(s) on the end of the part are allowed to continue across or through the corresponding taper formed on the end of the part. As a result, the tapered end portion of the part can then be used to facilitate board to board electrical connections in multi-PCB applications. It will be appreciated that where the desired taper extends across multiple component layers, successive layers of the Z-directed component forming the taper will have decreasing diameters (or widths in the case of a component layer with a non-circular cross-section). Alternatively, the desired taper may be formed in a single component layer.

[00108] After the aggregate Z-directed component has been formed, a firing process is applied to solidify the part. The firing process also shrinks the part to its final dimensions. At this point, the Z-directed component can be tested for yield and performance and any additional processes may be performed as desired. For example, in some instances, the pressing and heating steps may cause burrs to form. Accordingly, in some embodiments, the Z-directed components are tumbled with various abrasive agents to smooth the corners and edges of the part. Further, resist areas may be added to the Z-directed component to keep the conductive materials from sticking to areas that are not intended to be conductive. Glue areas may be applied to the component to assist with retaining it in the PCB. Visible markings and/or locating features may be added to the Z-directed component to assist with assembly into the PCB.

[00109] Once production of the Z-directed component is complete, it is ready to be inserted into the mounting hole of the PCB. As discussed above, the component may be mounted normal to the plane of the PCB from the top or bottom surfaces or both surfaces, mounted at an angle thereto or inserted into the edge of the PCB between the top and bottom surfaces of the PCB. In some embodiments, the Z-directed component is press fit into the mounting hole. This press fit may be in

the form of an interference fit between the component and the mounting hole. After the Z-directed component is positioned in the mounting hole, a conductive plating bridge may be applied to connect one or more traces on the top and/or bottom surface of the component to a corresponding trace on the PCB. Further, where the Z-directed component includes side channels therein, such as side channels 704b, 704c, additional conductive plating may be applied to these side channels to form the desired signal connections between the Z-directed component and the PCB.

[00110] With reference to Figure 24, in one embodiment, after a Z-directed component 760 is inserted into a mounting hole 762 in a PCB 764, an adhesive 766 is applied to a surface 768 of PCB 764 external to mounting hole 762. Adhesive 766 is positioned to contact a surface of Z-directed component 760 when it is inserted into mounting hole 762 in order to fix the location of Z-directed component 760 and prevent it from rotating or translating out of position.

[00111] With reference to Figures 25A and 25B, manufacturing variations in the thickness of the PCB and the length of the Z-directed component may prevent the Z-directed component from being perfectly flush with both the top and bottom surfaces of the PCB. As a result, in one embodiment, a conductive strip 772 is formed along a side surface 770s of a Z-directed component 770. Conductive strip 772 runs along side surface 770s to either the top or bottom surface of Z-directed component 770. It will be appreciated that conductive strip 772 may be applied after the Z-directed component 770 is formed. Alternatively, conductive strip 772 may be formed during fabrication of Z-directed component 770 such as by applying conductive material to a predetermined portion of the component layer(s) 712 as discussed above. In the example embodiment illustrated, conductive strip 772 runs along side surface 770s to a top surface 770t of Z-directed component 770. In this manner, conductive strip 772 forms a bridge between a trace 774 on the respective top or bottom surface of Z-directed component 770 and a trace 776 on a PCB 778 when the top or bottom surface of the Z-directed component extends past the corresponding top or bottom surface of the PCB. As a result, trace 774 on Z-directed component 770 is able to connect to trace 776 on PCB 778 even if the top or bottom surface of Z-directed component 770 is not flush with the corresponding top or bottom surface of PCB 778. In the example configuration illustrated in Figure 25B, conductive strip 772 runs from top surface 770t of Z-directed component 770 to a point along side surface 770s that is below the top surface of the PCB 778. In one embodiment, conductive strip 772 extends into the side of Z-directed component 770 both to decrease its resistance and to ensure that it is not removed if another feature such as a taper is later applied to Z-directed component 770.

[00112] The foregoing description of several embodiments has been presented for purposes of illustration. It is not intended to be exhaustive or to limit the application to the precise forms disclosed, and obviously many modifications and variations are possible in light of the above teaching. It is understood that the invention may be practiced in ways other than as specifically set

forth herein without departing from the scope of the invention. It is intended that the scope of the application be defined by the claims appended hereto.

[00113] What is claimed is:

CLAIMS

- 1 1. A method for manufacturing a Z-directed component for insertion into a mounting hole in a
2 printed circuit board, comprising:
3 punching a plurality of segments out of at least one sheet of substrate material to form a
4 plurality of layers of the Z-directed component;
5 forming a channel through the substrate material, at least one of the formed layers including at
6 least a portion of the channel;
7 applying a conductive material to at least one surface of at least one of the formed layers; and
8 combining a stack of the formed layers to form the Z-directed component.
- 1 2. The method of claim 1, wherein punching the plurality of segments includes punching each
2 segment into a respective cavity in a respective die block and further comprising stacking the die
3 blocks on top of each other to stack the punched segments.
- 1 3. The method of claim 1, wherein punching the plurality of segments includes:
2 punching a first segment of substrate material into a cavity in a die block having a raisable
3 elevator therein;
4 lowering the elevator to create additional space in the cavity on top of the first punched
5 segment; and
6 punching the second segment into the additional space in the cavity to stack the second
7 punched segment on the first punched segment.
- 1 4. The method of claim 1, wherein at least a portion of the segments are punched into a
2 respective cavity that is shaped to matably receive the punched layer.
- 1 5. The method of claim 1, wherein applying the conductive material to the at least one surface of
2 the at least one formed layer includes:
3 applying a mask to a top surface of the at least one formed layer that restricts the application
4 of conductive material to selected portions of the at least one formed layer; and
5 screening conductive material through the mask onto the at least one formed layer.
- 1 6. The method of claim 5, wherein the mask includes a physical mask placed on the top surface
2 of the at least one formed layer.
- 1 7. The method of claim 5, wherein the mask includes a photoresist layer applied to and
2 developed on the top surface of the at least one formed layer.

1 8. The method of claim 1, wherein applying the conductive material to the at least one surface of
2 the at least one formed layer includes spin coating a top surface of the at least one formed layer with
3 liquid conductive material and then selectively etching conductive material from the top surface of the
4 at least one formed layer.

1 9. The method of claim 1, wherein applying the conductive material to the at least one surface of
2 the at least one formed layer includes applying a seed layer of conductive material onto a
3 predetermined portion of the at least one formed layer and then applying additional conductive
4 material by an electrolysis technique.

1 10. The method of claim 1, wherein applying the conductive material to the at least one surface of
2 the at least one formed layer includes:

3 positioning the at least one formed layer in a constraining plate having a side wall surface that
4 is spaced from a side wall channel in the at least one formed layer forming a gap
5 therebetween; and
6 applying conductive material in the gap formed between the side wall surface of the
7 constraining plate and the side wall channel in the at least one formed layer to plate the side
8 wall channel in the at least one formed layer with the conductive material.

1 11. The method of claim 1, wherein combining the formed layers to form the Z-directed
2 component includes heating and compressing the stacked layers to form an aggregate part.

1 12. The method of claim 11, wherein the layers are compressed with a plug that includes a recess
2 formed in an end thereof having a tapered rim around a periphery of the recess that forms a
3 corresponding taper in at least one of a top surface and a bottom surface of the Z-directed component
4 when the stack of formed layers is combined.

1 13. A method for manufacturing a Z-directed component for insertion into a mounting hole in a
2 printed circuit board, comprising:

3 punching a segment out of a sheet of substrate material to form a layer of the Z-directed
4 component;
5 forming a channel through the substrate material, the formed layer including at least a portion
6 of the channel;
7 applying a conductive material to at least one surface of the formed layer;
8 punching additional segments out of at least one of the same sheet and a different sheet of
9 substrate material to form additional layers of the Z-directed component; and

10 stacking and combining the formed layers to form the Z-directed component.

1 14. The method of claim 13, wherein stacking the formed layers includes punching each segment
2 into a respective cavity in a respective die block and successively stacking the die blocks on top of
3 each other to stack the punched segments.

1 15. The method of claim 13, wherein stacking the formed layers includes punching each segment
2 into a cavity in a die block having a raisable elevator therein and lowering the elevator after each
3 segment is punched to create space in the cavity for the next punched segment.