

Description

The present invention relates to data processing apparatus with selective instruction prefetching.

Background information respecting the 80386, its characteristics and its use in microcomputer systems including cache memory subsystems are described in "Introduction to the 80386", April 1986 and the 80386 Hardware Reference Manual (1986). The characteristics and operating performance of the 82385 are described in the publication "82385 High Performance 32-Bit Cache Controller" (1987). All of these publications are produced by Intel Corporation.

In microcomputer systems, as in other computer systems, speed of operations is an important criterion which in most cases has to be balanced against system cost. Many features which were first introduced to speed up operations in mainframe computers and minicomputers are now finding their way into microcomputer systems. These include cache memory subsystems and pipelined operations, these latter requiring instruction prefetching. In older systems, the term pipelining had a further seriality and timing connotations but, in smaller systems, such as those indicated above and as the term is used by the makers thereof, is now satisfied by instruction prefetching.

In some microcomputer systems (for example those employing the microprocessor 80386), pipelined operations are an attractive operating option. For 80386/82385 microcomputer systems the 82385 cache controller provides next address (NA) signal which it is suggested should be connected to a corresponding input on the 80386. This allows the 82385 to assert the NA signal to the 80386 prior to completion of a given bus cycle to enable the 80386 to output information (data, address and/or control) for the next operating cycle. The timing is arranged, along with connected components, so that if a cache operation is the given operation, information for the given operation has already been accepted by the cache memory and therefore changing the 80386 output information to correspond to the next cycle will not interfere with the operation which is in the process of being completed. This also holds true for situations in which a cache miss condition has occurred requiring reference not to the cache memory but to main memory since access to main memory is via latched buffers which therefore store information respecting the given operation.

The 80386 also has the capability of operating with what is referred to as dynamic bus sizing. The 80386 is nominally a 32-bit machine, i.e. the width of the data bus is 32 bits. However, the 80386 can operate with 16-bit devices (devices which will transfer only 16 bits of data) by responding to a BS16 signal which is provided to the 80386 to indicate the presence of a 16-bit device. The BS16 signal is important to the 80386 in the event that it has performed a 32-bit operation. Of course the 16-bit device cannot, in one operation, transfer the 32 bits of data which the 80386 is capable of generating and/or accepting. Thus, a second operation (cycle) is necessary and the 80386 responds to the BS16 signal to automatically generate the next, necessary, cycle.

In order for this type of operation to be successful when the 82385 is present it is also necessary for the 82385 to have information respecting the character of the device taking part in the operation so that the NA signal to the 80386 is not improvidently generated. As described in the referenced Intel publications the 82385 requires device information at the beginning of a cycle in contrast to the 80386 which can accept and act on device information substantially later in the cycle.

In some microcomputer systems, this constraint is accepted by correlating the address of a device with its size so that for example all 32-bit devices are in a first predetermined address range and all 16-bit devices are in a second, different address range. By this technique then, the size of a device can be determined by its address.

However, in systems which require the flexibility of locating a wide variety of devices within widely varying address ranges, this constraint cannot be complied with. One class of such systems are those employing the IBM Micro-Channel (TM) bus.

In many systems, including systems of the foregoing type, a device when addressed will return an indication of its size. However, since the 82385 requires device size information to be available at the beginning of a bus cycle, in systems where this information is only available later in the cycle, there is the possibility of an improvident NA signal.

Therefore it is an object of the present invention to provide an arrangement in a microcomputer system which selectively controls the NA signal so that it is coupled to the microprocessor only under appropriate circumstances. In other circumstances the NA signal is prevented from reaching the microprocessor. Preventing the NA signal from reaching the microprocessor prevents pipelined operation, i.e. it prevents the generation of information for a next cycle before the given cycle has been completed. With this flexible control of the NA signal, the microcomputer system can now operate with dynamic bus sizing, i.e. it can now operate with devices of various sizes without information at the beginning of the cycle as to the size of the device being operated with.

Cacheable devices, i.e. devices generating data which can be cached, are necessarily 32-bit devices. All

such devices have addresses (specifically, tags) indicating cacheability. All other devices (whether or not 32-bit devices) have addresses indicating information they generate will not be found in cache. Control of the NA signal depends in part on cacheability. Specifically, since any cacheable device is a 32-bit device, there is no question of improvident NA signals when operating with cacheable devices. Furthermore, in the event of a cache hit, there is no question but that the NA signal is appropriate since only cacheable devices (32-bit devices) will produce a cache hit. Thus an important feature of allowing dynamic bus sizing and pipelined operations is preventing or inhibiting the NA signal from reaching the 80386 in the event of assertion of an address to a non-cacheable device.

If, during the course of a given cycle (where the NA signal has been inhibited), it turns out the device is a 32-bit device, then the cycle completes in normal fashion (without pipelining). On the other hand, if it turns out during the course of the cycle that the device being operated with is a 16-bit device (and the cycle is a 32-bit cycle), then the microprocessor generates the additional, necessary cycle. This operation is entirely transparent to the cache controller, i.e. it takes no part in controlling the second of the two cycles. Finally, if the device being operated with turns out to be an 8-bit device, then the microprocessor "sees" a 16-bit device so that it operates exactly as has been described for the case when the device is a 16-bit device. In other words, it "sees" a 16-bit device so that after the first cycle is completed (during which cycle it is informed that it is operating with a 16-bit device), a second cycle is generated. However, not only transparent to the cache controller, but also transparent to the microprocessor, other logic converts each of the 16-bit cycles of the microprocessor into two 8-bit cycles. Thus in the case where a 32-bit cycle is directed at an 8-bit device, the cache controller takes no part in the operation, the microprocessor generates two 16-bit cycles, and other logic operates on each of the microprocessor 16-bit cycles to generate two 8-bit cycles.

Thus, in accordance with the invention, there is provided data processing apparatus according to claim 1 and a method of operating a data processing system according to claim 7.

An embodiment of the invention will now be described, by way of example, and contrasted with examples of the prior art, with reference to the accompanying drawings, in which:

Fig. 1 is an overall three-dimensional view of a typical microcomputer system which may embody the present invention;

Fig. 2 is a detailed block diagram of a majority of the components of a microcomputer system embodying the present invention;

Fig. 3 is a block diagram, in more detail than Fig. 2, showing those connections between the microprocessor and the cache controller recommended by the manufacturer and which is useful to an understanding of why such an arrangement is inconsistent with dynamic bus sizing;

Fig. 4 is a more detailed block diagram similar to Fig. 3 but illustrating application of the present invention which allows both pipelined instruction sequencing and dynamic bus sizing;

Fig. 5 is further detailed block diagram of apparatus which handles 16-to-8-bit cycle conversion; and

Figs. 6 and 7 are a timing diagram and a block diagram of the latch DL and its control signal LEDMA (Latch Enable from DMA) to illustrate how the synchronous DMA subsystem is interfaced to the CPU local bus (operating under a different clock) to avoid possible contention on the system bus 250.

Fig. 1 shows a typical microcomputer system in which the present invention can be employed. As shown, the microcomputer system 10 comprises a number of components which are interconnected together. More particularly, a system unit 30 is coupled to and drives a monitor 20 (such as a conventional video display). The system unit 30 is also coupled to input devices such as a keyboard 40 and a mouse 50. An output device such as a printer 60 can also be connected to the system unit 30. Finally, the system unit 30 may include one or more disk drives, such as the disk drive 70. As will be described below, the system unit 30 responds to input devices such as the keyboard 40 and the mouse 50, and input/output devices such as the disk drive 70 for providing signals to drive output devices such as the monitor 20 and the printer 60. Of course, those skilled in the art are aware that other and conventional components can also be connected to the system unit 30 for interaction therewith. In this arrangement, the microcomputer system 10 includes (as will be more particularly described below) a cache memory subsystem such that there is a CPU local bus interconnecting a processor, a cache control and a cache memory which itself is coupled via a buffer to a system bus. The system bus is interconnected to and interacts with the I/O devices such as the keyboard 40, mouse 50, disk drive 70, monitor 20 and printer 60. Furthermore, the system unit 30 may also include a third bus comprising a Micro Channel (TM) architecture for interconnection between the system bus and other input/output devices.

Fig. 2 is a high level block diagram illustrating the various components of a typical microcomputer system in accordance with the present invention. A CPU local bus 230 (comprising data, address and control components) provides for the connection of a microprocessor 225 (such as an 80386), a cache control 260 (which may include an 82385 cache controller) and a random access cache memory 255. Also coupled on the CPU local bus 230 is a buffer 240. The buffer 240 is itself connected to the system bus 250, also comprising address,

data and control components. The system bus 250 extends between the buffer 240 and a further buffer 253. The system bus 250 is also connected to a bus control and timing element 265 and a DMA controller 325. An arbitration control bus 340 couples the bus control and timing element 265 and a central arbitration element 335. The main memory 350 is also connected to the system bus 250. The main memory includes a memory control element 351, an address multiplexer 352 and a data buffer 353. These elements are interconnected with memory elements 360 through 364, as shown in Fig. 2.

A further buffer 254 is coupled between the system bus 250 and a planar bus 270. The planar bus 270 includes address, data and control components, respectively. Coupled along the planar bus 270 are a variety of I/O adaptors and other components such as the display adaptor 275 (which is used to drive the monitor 20), a clock 280, additional random access memory 285, an RS 232 adaptor 290 (used for serial I/O operations), a printer adaptor 295 (which can be used to drive the printer 60), a timer 300, a diskette adaptor 305 (which cooperates with the disk drive 70), an interrupt controller 310 and read only memory 315.

The buffer 253 (coupled on one side to the system bus 250) is coupled on the other side to the Micro-Channel (TM) sockets 401 of the Micro-Channel (TM) bus 320. Bus 320 can support devices of various size including 32-bit devices, 16-bit devices and 8-bit devices. A typical memory device 331 is shown coupled on the bus 320. One of the advantages of this bus is the flexibility the user is provided with to freely insert various devices in the different sockets, at will. The mixing of these devices and their appearance at different sockets prevents rigid addressing allocation and is a prime reason for the necessity of the present invention. Absent the present invention, the 80386/82385 microcomputer system as described herein would be either wholly prevented from using pipelining operations or alternatively subjected to faulty operation caused by improvident or inappropriate pipelining operations.

Fig. 3 shows selected interconnections between the 80386 and 82385, relative to generation and use of the Next Address (NA) signal, as recommended by the manufacturer. More particularly, the interface between the CPU local bus 230 and the system bus 250 is the buffer 240 whose components include a control buffer DL (for data) and AL (for address). As shown in Fig. 3, the data component of the CPU local bus (CPULBD) is one input/output connection for the DL, on the CPU local bus side. Likewise, the data component SBD of the system bus 250 is the input/output connection to the DL, on the side of the system bus 250. The buffer DL is controlled by its input signals LDSTB, BT/R and DOE. LDSTB latches data into DL and DOE enables the output of DL. The direction from which input is accepted (CPU local bus 230 or system bus 250) and to which output is directed (system bus 250 or CPU local bus 230) is determined by BT/R. Likewise, the address component of the buffer AL has an input from the address component of the CPU local bus (CPULBA) and an output to the address component of the system local bus 250 (SBA). In a similar fashion, the AL component of the buffer is controlled by its two control signals BACP and BAOE, the former latches address information from CPULBA into AL and the latter enables the output, i.e. to the system bus 250. The control signals LDSTB, DOE, BACP and BAOE are provided for by the 82385.

The address component CPULBA of the CPU local bus 230 originates at the 80386 and the data component CPULBD of the CPU local bus 230 originates/terminates at the 80386.

The 82385 uses two additional signals X16 and NCA in the generation of the NA signal. The X16 signal indicates whether the device which is being operated with is a 16-bit or 32-bit device. One source of the signal X16 is the Local Bus Address Decoder (LBAD). In addition, the manufacturer recommends that the signal BS16 be tied to the signal X16. The signal BS16 is input to the 80386 to indicate to the 80386 whether the device being operated with is 16 or 32 bits in size. A source of the signal BS16 is a device address decoder, such as MAD. MAD represents the address decoder of any device coupled to the system bus 250 or any other bus coupled thereto such as the bus 270 or 320. When a device such as MAD recognizes its address on a bus address component such as MA, it returns the signal BS16, which is high or low depending on whether the device is a 16- or 32-bit device.

The Non-Cacheable Address (NCA) is another input to the 82385 which indicates whether an address asserted is a cacheable address. A cacheable address is defined as an address for a device which is compatible with the cache subsystem and hence is a 32-bit device. This signal is generated by the Cache Address Decoder (CAD) by virtue of an input from the address component of the CPU local bus 230. The manufacturer suggests that a portion of memory can be set aside as non-cacheable by use of this input to the 82385.

The recommended architecture illustrated in Fig. 3 provides for effective pipelined operations (by use of the NA signal) under any one of the following circumstances:

- 1) where all devices connected to the system bus 250 or any bus coupled thereto are 32-bit devices, or
- 2) where the devices connected to the system bus 250 or any bus coupled thereto may be 32-bit or 16-bit devices, so long as the signal X16 is available at the beginning of any bus cycle.

When the X16 signal is available at the beginning of a given bus cycle, the 82385 based on that information determines whether the NA signal is appropriate, and if it is not appropriate, it is not generated. Thus in the

event the 80386 is operating with a 32-bit device, then the NA signal is normally generated prior to completion of a given cycle for effecting pipelined operation. On the other hand, if the device is a 16-bit device, then the NA signal is not generated, allowing the 80386 to generate the second necessary cycle for proper operation with a 16-bit device.

However, the architecture of some bus subsystems (for example the Micro-Channel (TM) bus) provides for the mixing of 8-bit and 16-bit and 32-bit devices. Because the signal BS16 is not returned until sometime after the typical device MAD has recognized its address on the bus subsystem, it is not generated early enough for the 82385 to take into account in determining whether to generate NA. Accordingly, the peculiarities of the 82385 make it incompatible, particularly in the generation of the NA signal, with bus subsystems having the flexibility such as is exhibited by the Micro-Channel (TM) bus.

Fig. 4 is a block diagram similar to Fig. 3 but altered for use in accordance with the present invention. Before describing the operation of the apparatus shown in Fig. 4, a number of the differences between Figs. 3 and 4 will be described.

One major difference is that the outputs X16 and NA from the 82385 are no longer utilized. In addition, a new logic element CL is interposed between the 82385 and the 80386. The logic element CL generates the CPUNA signal (replacing the unused NA signal from the 82385). The logic unit CL is responsive to the NCA signal from the CADR and BADS signal from the 82385. The BADS (Bus Address Status) signal is a signal generated by the 82385 when a valid address for the local address bus is available. This 82385 output is tri-stated when the 82385 is not in control of the local bus and it also, in its absence, provides an indication of a cache miss. The logic element CL also has an input BW/R indicating whether any system bus cycle is a read or a write. As will be described, while BW/R is used in an embodiment of the invention, it is a signal which is not essential.

The decoder CADR receives, in addition to its inputs from bits A17-A26 and A31 of the CPULBA, Programmable Cacheability Bits (PCB). In an embodiment actually constructed, the first of these three bits represents a decision to allow caching ROM space. A second bit either enables the decoder CADR to output NCA based on the decoded information, or alternatively, to declare all accesses non-cacheable, i.e. assert NCA regardless of the asserted address on the CPULBA. Finally, a third bit indicates, in one state, that address space between 0 and 8 megabytes is cacheable and that address space between 8 to 16 megabytes is non-cacheable. In the other state, the bit indicates that address space in the range 0 to 16 megabytes is all cacheable. If desired, the effect of this bit can be multiplied by simply reflecting the status of the first 16 megabytes through the succeeding 16 megabyte ranges. Of course, the use of these particular cacheability indicators (or others) is not essential to the invention. It is, however, important to arrange the CADR so that it can quickly decode its inputs and produce NCA. In an embodiment actually constructed, the timing window for production of NCA, from valid addresses on the CPULBA, was very short, on the order of ten nanoseconds.

A further major difference between Figs. 3 and 4 is that the typical MAD now generates not a single BS16 signal (as is the case in Fig. 3), but two signals, CS32 and CS16. This enables the MAD to identify itself as a 32-bit device, a 16-bit device or an 8-bit device. The signal CS32 is input to a flip-flop FF which is now used to generate the BS16 signal which is in one condition in the event the MAD is a 32-device and in a different condition if the MAD is an 8-bit or a 16-bit device. If neither CS32 nor CS16 is generated by the device, then by default the device is an 8-bit device.

The logic equations which have been referenced above are reproduced immediately below. In this material the symbols have the following meanings associated with them:

Symbol	Definition
/	Negation
:=	A registered term, equal to
=	A combinatorial term, equal to
&	Logical AND
+	Logical OR

Logic Equations

$$\begin{aligned} /BT2 &= BUSCYC385 \& PIPECYC385 \& /BADS \& CLK \& BT2 \\ &+ BUSCYC385 \& /PIPECYC385 \& BADS \& CLK \& NACACHE \& BT2 \\ &+ MISS1 \& /BUSCYC385 \& /BADS \& /(BW/R) \& CLK \& NCA \& /BREADY \end{aligned}$$

+ /MISS1 & /BREADY & /BUSCYC385 & CLK + /BT2 & BREADY & NACACHE
+ /CLK & /BT2 (1)

/BUSCYC385: = BUSCYC385 & /BADS & CLK

+ BUSCYC385 & /PIPECYC385 & CLK

+ BUSCYC385 & /BT2 & CLK

+ /BUSCYC385 & BREADY

+ /BUSCYC385 & /CLK (2)

/CPUNA: = /MISS1 & CLK & CPUNA & /NACACHE

+ /MISS1 & CLK & CPUNA & /BREADY & /BUSCYC385

+ /CPUNA & /CLK

+ /CPUNA & /MISS1 & CLK

+ /CPUNA & CLK & BREADY

+ /CPUNA & BUSCYC385 & NACACHE & CLK (3)

/MISS1: = MISS1 & BUSCYC385 & CPUNA & /BADS & /(BW/R) & CLK & NCA

+ MISS1 & /BUSCYC385 & /BADS & /(BW/R) & CLK & NCA & /BREADY

+ /MISS1 & /CLK

+ /MISS1 & BREADY (4)

/PIPECYC385: = PIPECYC385 & /BADS & /BUSCYC385 & CLK & /BREADY + PIPECYC385 & /MISS1 & BT2 & /BUSCYC385 & CLK & /BREADY + /PIPECYC385 & /CLK (5)

In the foregoing logic equations the following signals are described or referred to in the cited Intel publications:

BADS

BREADY

(BW/R) actually referred to as BW/R, the parenthesis are used to indicate that the entire term is one signal

CLK

(W/R) actually referred to as W/R, the parenthesis are used to indicate the entire term is one signal

BADS, when active indicates a valid address on the local bus 230. BREADY is a ready signal from the system bus 250 to the CPU local bus 230. BW/R defines a system bus 250 Write or Read. CLK is a processor clocking signal which is in phase with the processor 225. (W/R) is the conventional Write or Read signal for the CPU local bus 230.

Equations (1)-(5) define:

BT2

BUSCYC385

CPUNA

MISS1

PIPECYC385

In terms of the defined signals, the signals described or referred to in the cited Intel publications and NCA and NACACHE. BT2 reflects the state of the system bus 250. The state BT2 is a state defined in the cited Intel publications.

BUSCYC385 also reflects the state of the system bus 250. It is high for bus states BT1, BT1P and low for bus states BT2, BT2P and BT2I (again these are bus states referenced in the cited Intel publications).

CPUNA is a signal to the 80386 allowing pipelined operation. This is the signal which replaces the NA signal from the 82385.

MISS1 is active defining the first cycle in a double cycle for handling 64 bit read to cacheable devices.

PIPECYC385 is active during BT1P (which is a bus state referred to in the cited Intel publications).

NCA is a signal created by decoding the address component on the CPU local bus 230 to reflect, when active, a non-cacheable access. Cacheability is determined by a tag component (A31 to A17) and program-mable information defining what tags (if any) refer to cacheable as opposed to non-cacheable addresses.

NACACHE is a signal similar to the BNA signal. BNA is a system generated signal requesting a next address from the CPU local bus 230, and is referenced in the cited Intel publications. NACACHE differs from BNA only in respect of the fact that BNA is created for 32K cache while NACACHE is created for a 64K cache. So long as the cache memory is 32K, as cited in the Intel publications the NACACHE signal referred to here could be replaced by the BNA signal.

Reviewing Equation 3, the set terms are found in lines 1 and 2. The term on line 1 indicates a pipelined operation. /MISS1 indicates a 32-bit operation (as will be described) and so CPUNA is appropriate. The term on line 2 is a cycle that ends early without pipelining, e.g. /BREADY. Referring to Equation 4, the terms on lines 1 and 2 are the set terms. Both depend on NCA.

Fig. 5 is a detailed block diagram of apparatus associated with the buffer and decoder 267 (associated

with bus 270) and buffer 253 associated with a Micro-Channel (TM) bus 320). As has already been described, the apparatus of Fig. 4 provides for two 16-bit cycles when 32-bit cycles are directed to 8- or 16-bit devices, and does so in a manner transparent to the 82385. The apparatus of Fig. 5 is employed so as to generate, for each 16-bit cycle directed to an 8-bit device, two 8-bit cycles, in a manner which is transparent to the 80386.

More particularly, the apparatus includes control logic CLA, a sequencer S and a controlled coupler ALS which couples selective ones of the data lines to others of the data lines. More particularly, as shown in Fig. 5, the low order eight bits (D0-D7) can be coupled to the second 8-bit segment (D8-D15) under the control of the signal DIR and /G. Further, the direction of transfer (left to right or vice versa) is also controlled by DIR.

More particularly, in any 16-bit cycle generated by the 80386, data is placed on the low order sixteen bits of the data bus. In order to convert a 16-bit cycle generated by the 80386 into two 8-bit cycles for the appropriate MAD, the hardware shown in Fig. 5 forces the 16-bit operation to look like two 8-bit operations to the 8-bit device MAD while to the 80386 the two 8-bit cycles look like a single 16-bit cycle.

The control logic CLA performs a decode function for the conversion cycle control. It detects when a conversion cycle must occur and controls the GATE 245 and DIR 245 signals of the ALS which connect the low order eight bits of the data bus to a second 8-bit segment of the data bus. The logic equations for CLA are listed below. Once the conversion cycle conditions have been detected, the signal DATA CONV activates the sequence. The signal CS16, when inactive, signals presence of an 8-bit device and hence the necessity for the conversion. The signal CS16, when active, indicates a 16- or 32-bit device. Q1 is used in the sequence to indicate the end of the first half of the conversion cycle. The signals DATA CONV and Q1 are input to the sequencer S. The sequencer S performs two functions. One is to hold the 80386 not ready until the second half of the cycle has been initiated. ARDYEN is driven to a logic 1 to signal the 80386 not to end the cycle. The sequencer also stimulates the end of one 8-bit cycle and the beginning of a second. ALTALE clocks a logic 1 onto the A0 address line and causes the wait state generator to restart. CMTLOFF causes the active command signal to go inactive and active again to stimulate the end of one cycle and the beginning of another. CONVA0 is used as an input to the A0 address latch to force A0 to a logic 1 for the second half of the conversion cycle.

The completed 16- to 8-bit conversion cycle is equivalent in time and function to two consecutive 8-bit cycles.

The signals referred to above and shown in Fig. 5 are defined as follows:

MEMCS16	16 bit memory device select
(/OCS16)	16 bit I/O device select. Parenthesis are used to indicate the expression relates to a single signal
AEN1, AEN2	Address enables from DMA controllers
MEMR, MEMW, IOR, IOW	CPU command signals
XBHE	Bus high enable, indicates when data should appear on a higher order eight bit segment of the data bus
XA0	Least significant address order line
Q1	Wait state generator output (2d state output)
D0-D7	Lowest order eight bit segment of the data bus
D8-D15	Second eight bit segment of the data bus
ARDYEN	Asynchronous ready enable to 82284. ADDS wait states in conversion cycle to provide for the generation of two 8 bit cycles.
ALT ALE(active high)	Alternate address latch. User to clock A0 to a logic one and to restart the wait state generator for second 8 bit transfer
CONV.A0 (active high)	Conversion cycle A0. Provides a logic one to the A0 address latch so that A0 will increment for the second 8 bit cycle
CNTLOFF	Control off. Turns off the active command signal for 3 clocks to simulate the end of one 8 bit cycle and the start of the second 8 bit cycle. CNTLOFF is also used to latch the low order data bus to the CPU (during a read cycle) on the first 8 bit transfer.

Logic Equations

$$\begin{aligned}
 \text{/GATE 245} = & \text{MEMCS16} \& \text{AEN1} \& \text{AEN2} \& \text{/MEMR} \& \text{/XBHE} \& \text{XA0} \\
 & + \text{MEMCS16} \& \text{AEN1} \& \text{AEN2} \& \text{/MEMW} \& \text{/XBHE} \& \text{XA0} \\
 & + \text{(}/\text{OCS16)} \& \text{AEN1} \& \text{AEN2} \& \text{/IOR} \& \text{/XBHE} \& \text{XA0} \\
 & + \text{(}/\text{OCS16)} \& \text{AEN1} \& \text{AEN2} \& \text{/IOW} \& \text{/XBHE} \& \text{XA0} \\
 & + \text{/AEN1} \& \text{/MEMCS16} \& \text{/XBHE} \& \text{/IOR} \\
 & + \text{/AEN1} \& \text{/MEMCS16} \& \text{/XBHE} \& \text{/MEMR} \quad (6)
 \end{aligned}$$

$\text{/DIR245} = \text{/AEN1} \ \& \ \text{/MEMR}$
 $+ \text{AEN1} \ \& \ \text{AEN2} \ \& \ \text{/XBHE} \ \& \ \text{/MEMW}$
 $+ \text{AEN1} \ \& \ \text{AEN2} \ \& \ \text{/XBHE} \ \& \ \text{/IOW} \quad (7)$
 $\text{/DATA CONV} = \text{MEMCS16} \ \& \ \text{AEN1} \ \& \ \text{AEN2} \ \& \ \text{/MEMR} \ \& \ \text{Q1} \ \& \ \text{/XBHE} \ \& \ \text{/XA0}$
 $+ \text{MEMCS16} \ \& \ \text{AEN1} \ \& \ \text{AEN2} \ \& \ \text{/MEMW} \ \& \ \text{Q1} \ \& \ \text{/XBHE} \ \& \ \text{/XA0}$
 $+ (\text{/OCS16}) \ \& \ \text{AEN1} \ \& \ \text{AEN2} \ \& \ \text{/IOR} \ \& \ \text{Q1} \ \& \ \text{/XBHE} \ \& \ \text{/XA0}$
 $+ (\text{/OCS16}) \ \& \ \text{AEN1} \ \& \ \text{AEN2} \ \& \ \text{/IOW} \ \& \ \text{Q1} \ \& \ \text{/XBHE} \ \& \ \text{/XA0} \quad (8)$

Fig. 7 shows a detail of the latch DL, the data input/output connections between the system bus 250 and the CPU local bus 230 as well as the control signal LEDMA. Fig. 6 relates the signal LEDMA to other signals on the CPU local bus 230 (indicated in the top third of Fig. 6 with the legend "82385 Local Bus Signals & 25 MHz"), signals on the optional feature bus 320 (indicated by the reference "Micro-Channel (TM)" bus 320 signals and signals on the system bus 250 (indicated in the bottom third by the legend "DMA Signals"). As indicated in the upper third of Fig. 6, the CPU local bus 230 is a synchronously clocked bus (clocks CPUCLK2 and CPUCLK are related as indicated). The central portion (comprising the major portion of Fig. 6) shows a single cycle on the CPU local bus 230. The beginning of the cycle is indicated by the left-most vertical line, and the end of the cycle is indicated by the right-most vertical line. As shown in Fig. 6 in the middle third, once a cycle has begun on the CPU local bus 230, for a cycle which extends through the system bus 250 to the bus 320, the command signals SS0* and SS1* become active (low). Shortly thereafter, an address is latched into the buffer 253 (referenced ADL*). Subsequently, the signal CMD* also becomes active (low). It is this point which defines the beginning of the DMA cycle on the system bus 250 and the optional feature bus 320. This is indicated by a continuation of the third vertical line (from the left) extending into the lower third of Fig. 6. Shortly after the beginning of the DMA cycle, the signals DMAS0 and DMAS1 become active (low). As seen in Fig. 6, the signal DMARDY* subsequently changes state. On the next transition in DMARDY* (the low going transition), the required data is located on the system bus 250. Accordingly, the signal LEDMA changes state (rising transition). This has the effect of latching the data on the system bus 250 into the latch DL. The same transition which produced the change of state in LEDMA also has an effect on BREADY* (as shown by the arrow in Fig. 6). In other words, once DMARDY* is sampled low, the required data has already latched into the latch DL and the DMA channel has released the bus 250. Thus as shown in Fig. 6, the transition in DMARDY* leads to a transition in BREADY*. On the next subsequent high going transition of BT2, the CPU cycle can safely end and this is the right-most vertical line in Fig. 6). As seen in Fig. 6, ending the CPU cycle produces a change of state in CMD* (on the Micro-Channel (TM) bus 320) and also has the effect of releasing LEDMA, since at the termination of the cycle the CPU 225 accepted the data from the latch DL.

The foregoing illustrates that antecedent to terminating the CPU cycle, and a requirement for terminating the CPU cycle, is the prior termination of the DMA cycle. This guarantees that when the CPU initiates a following cycle (to the right of the right-most vertical line in Fig. 6), the DMA cycle had earlier completed and so the bus is free of any data that may have been driven during the course of the DMA cycle. Thus the invention provides an accommodation between dynamic bus sizing (which provides the flexibility essential to the Micro-Channel (TM) bus 320) and pipelining operation through selected generation of CPUNA, at the appropriate time. As has been indicated, CPUNA depends either on detection of a cacheable access, where CPUNA is produced prior to completion of the pending cycle. On the other hand, where a non-cacheable access is detected, then pipelining is withheld, i.e. CPUNA is not asserted until the system bus 250 indicates that the cycle has completed (BREADY is asserted).

At the same time, an accommodation is created between the synchronous DMA mechanism and the synchronous (but driven by a different clock) CPU local bus through the buffer DL. While the DMA cycle is initiated by the CPU local bus 230, the cycle on the CPU local bus 230 will not terminate until after the termination of the DMA cycle.

Claims

1. Data processing apparatus comprising
 an instruction execution unit (225, 80386) of a given bit width,
 an asynchronous next address generating means (225, 80386) capable of generating, when enabled, the address of the next instruction required by the instruction execution unit during execution of the instruction currently executing, whereby instructions can be prefetched,
 means (240, DL, AL) for interfacing the execution unit with addressable system components of the same and/or smaller bit widths, the system component addresses within a certain specified range of system component addresses relating exclusively to components of the same bit width as that of the execution



/DIR245: = /AEN1 & /MEMR
 + AEN1 & AEN2 & /XBHE & /MEMW
 + AEN1 & AEN2 & /XBHE & /IOW (7)
 /DATA CONV: = MEMCS16 & AEN1 & AEN2 & /MEMR & Q1 & /XBHE & /XA0
 + MEMCS16 & AEN1 & AEN2 & /MEMW & Q1 & /XBHE & /XA0
 + (/OCS16) & AEN1 & AEN2 & /IOR & Q1 & /XBHE & /XA0
 + (/OCS16) & AEN1 & AEN2 & /IOW & Q1 & /XBHE & /XA0 (8)

Fig. 7 shows a detail of the latch DL, the data input/output connections between the system bus 250 and the CPU local bus 230 as well as the control signal LEDMA. Fig. 6 relates the signal LEDMA to other signals on the CPU local bus 230 (indicated in the top third of Fig. 6 with the legend "82385 Local Bus Signals & 25 MHz"), signals on the optional feature bus 320 (indicated by the reference "Micro-Channel (TM)" bus 320 signals and signals on the system bus 250 (indicated in the bottom third by the legend "DMA Signals"). As indicated in the upper third of Fig. 6, the CPU local bus 230 is a synchronously clocked bus (clocks CPUCLK2 and CPUCLK are related as indicated). The central portion (comprising the major portion of Fig. 6) shows a single cycle on the CPU local bus 230. The beginning of the cycle is indicated by the left-most vertical line, and the end of the cycle is indicated by the right-most vertical line. As shown in Fig. 6 in the middle third, once a cycle has begun on the CPU local bus 230, for a cycle which extends through the system bus 250 to the bus 320, the command signals SS0* and SS1* become active (low). Shortly thereafter, an address is latched into the buffer 253 (referenced ADL*). Subsequently, the signal CMD* also becomes active (low). It is this point which defines the beginning of the DMA cycle on the system bus 250 and the optional feature bus 320. This is indicated by a continuation of the third vertical line (from the left) extending into the lower third of Fig. 6. Shortly after the beginning of the DMA cycle, the signals DMAS0 and DMAS1 become active (low). As seen in Fig. 6, the signal DMARDY* subsequently changes state. On the next transition in DMARDY* (the low going transition), the required data is located on the system bus 250. Accordingly, the signal LEDMA changes state (rising transition). This has the effect of latching the data on the system bus 250 into the latch DL. The same transition which produced the change of state in LEDMA also has an effect on BREADY* (as shown by the arrow in Fig. 6). In other words, once DMARDY* is sampled low, the required data has already latched into the latch DL and the DMA channel has released the bus 250. Thus as shown in Fig. 6, the transition in DMARDY* leads to a transition in BREADY*. On the next subsequent high going transition of BT2, the CPU cycle can safely end and this is the right-most vertical line in Fig. 6). As seen in Fig. 6, ending the CPU cycle produces a change of state in CMD* (on the Micro-Channel (TM) bus 320) and also has the effect of releasing LEDMA, since at the termination of the cycle the CPU 225 accepted the data from the latch DL.

The foregoing illustrates that antecedent to terminating the CPU cycle, and a requirement for terminating the CPU cycle, is the prior termination of the DMA cycle. This guarantees that when the CPU initiates a following cycle (to the right of the right-most vertical line in Fig. 6), the DMA cycle had earlier completed and so the bus is free of any data that may have been driven during the course of the DMA cycle. Thus the invention provides an accommodation between dynamic bus sizing (which provides the flexibility essential to the Micro-Channel (TM) bus 320) and pipelining operation through selected generation of CPUNA, at the appropriate time. As has been indicated, CPUNA depends either on detection of a cacheable access, where CPUNA is produced prior to completion of the pending cycle. On the other hand, where a non-cacheable access is detected, then pipelining is withheld, i.e. CPUNA is not asserted until the system bus 250 indicates that the cycle has completed (BREADY is asserted).

At the same time, an accommodation is created between the synchronous DMA mechanism and the synchronous (but driven by a different clock) CPU local bus through the buffer DL. While the DMA cycle is initiated by the CPU local bus 230, the cycle on the CPU local bus 230 will not terminate until after the termination of the DMA cycle.

Claims

1. Data processing apparatus comprising
 an instruction execution unit (225, 80386) of a given bit width,
 an asynchronous next address generating means (225, 80386) capable of generating, when enabled, the address of the next instruction required by the instruction execution unit during execution of the instruction currently executing, whereby instructions can be prefetched,
 means (240, DL, AL) for interfacing the execution unit with addressable system components of the same and/or smaller bit widths, the system component addresses within a certain specified range of system component addresses relating exclusively to components of the same bit width as that of the execution



- unit,
means (CL) for generating a next address signal (CPUNA) as a function of the execution of the instruction currently executing to enable the next address generating means and means (CADR) for generating a control signal (NCA) if execution of an instruction relating to an address outside the specified range is detected,
5 the apparatus being characterized in that,
in response to such a control signal, the means for generating a next address signal is inhibited.
2. Apparatus as claimed in claim 1, wherein the instruction execution unit and the address generating means are two units within a microprocessor (225, 80386), the microprocessor being connected to a cache memory subsystem, including a cache controller (260, 82385) and a cache memory (255) of the given bit width, by a local bus (230) of the given bit width which also interfaces with a system bus (250) connecting to the addressable system components, the cache memory subsystem caching data with respect to only those system components within the specified range of addresses, the next address signal generating means being connected between the cache controller and the address generating means.
 3. Apparatus as claimed in claim 2, wherein the next address signal generating means (CL), absent any action by the means for generating a control signal, is enabled by a signal (/BADS) from the cache controller indicating that there is no valid address on the local bus and by a signal (BNA) from the system indicating that a next address is required from the local bus.
 4. Apparatus as claimed in claim 3, wherein the means for generating a control signal includes an address decoder connected to the address lines (CPULBA) of the local bus for determining whether or not an address thereon lies within the specified range and, in response to an out-of-range determination, to generate a signal (NCA) to disable the next address signal generating means (CL).
 5. Apparatus as claimed in claim 4, wherein the means for generating a control signal is also responsive to a system generated signal (NACACHE) indicating that the address indicated on the local bus is not cacheable - even though it lies within the specified range - to generate a signal to disable the next address signal generating means.
 6. Apparatus as claimed in claim 5, wherein the microprocessor is responsive to a signal (CS32, BS16) indicating that an addressed system component is of half the bit width of the microprocessor for programming a double execution cycle, logic (CLA, S, ALS) being provided, responsive to signal combinations (CS 16) indicating that an addressed system component is a quarter of the bit width of the microprocessor, to re-double the execution cycle, transparently to the microprocessor.
 7. A method of operating a data processing system which comprises an instruction execution unit (225, 80386) of a given bit width, an asynchronous next address generating means (225, 80386) capable of generating, when enabled, the address of the next instruction required by the instruction execution unit during execution of the instruction currently executing, whereby instructions can be prefetched, and means (240, DL, AL) for interfacing the execution unit with addressable system components of the same and/or smaller bit widths, the method comprising
 - assigning system component addresses within a certain specified range thereof exclusively to components of the same bit width as that of the execution unit,
 - generating a next address signal (CPUNA) as a function of the execution of the instruction currently executing to enable early generation of the next address and hence instruction prefetching, and
 - generating a control signal (NCA) if execution of an instruction relating to an address outside the specified address range is detected,
 - the method being characterized in that,
 - in response to such a control signal generation of the next address signal is inhibited.

Patentansprüche

1. Ein Datenverarbeitungsgerät, umfassend
 - eine Befehlsausführungseinheit (225, 80386) mit einer gegebenen Bitbreite,
 - ein asynchrones Mittel (225, 80386) zur Generierung der nächsten Adresse, das in der Lage ist, wenn es aktiviert ist, die Adresse des nächsten Befehls zu generieren, der von der Befehlsausführungseinheit wäh-



- rend der Ausführung des derzeit ausgeführten Befehls benötigt wird, wodurch Befehle vorgeholt werden können,
 ein Mittel (240, DL, AL) zum Anschluß der Ausführungseinheit an adressierbare Systemkomponenten von gleicher und/oder geringerer Bitbreite, wobei sich die Systemkomponentenadressen innerhalb eines bestimmten festgelegten Bereichs von Systemkomponentenadressen ausschließlich auf Komponenten mit derselben Bitbreite wie die der Ausführungseinheit beziehen,
 ein Mittel (CL) zur Generierung eines Signals Nächste Adresse (CPUNA) als Funktion der Ausführung des derzeit ausgeführten Befehls zur Freigabe des Mittels zur Generierung der nächsten Adresse und
 ein Mittel (CADR) zur Generierung eines Steuerungssignals (NCA), wenn die Ausführung eines Befehls, der sich auf eine Adresse außerhalb des festgelegten Bereichs bezieht, erkannt wird, wobei das Gerät dadurch gekennzeichnet ist, daß
 als Reaktion auf ein derartiges Steuerungssignal das Mittel zur Generierung eines Signals Nächste Adresse inhibiert wird.
2. Ein Gerät nach Anspruch 1, bei dem die Befehlsausführungseinheit und das Adressengenerierungsmittel zwei Einheiten innerhalb eines Mikroprozessors (225, 80386) sind, wobei der Mikroprozessor an ein Cachespeichersubsystem angeschlossen ist, das eine Cachesteuerungseinheit (260, 82385) und einen Cachespeicher (255) mit der gegebenen Bitbreite umfaßt, und zwar durch einen lokalen Bus (230) mit der gegebenen Bitbreite, der auch an einen Systembus (250) angeschlossen ist, der mit den adressierbaren Systemkomponenten verbunden ist, wobei das Cachespeichersubsystem Daten nur bei diesen Systemkomponenten innerhalb des festgelegten Adreßbereichs cacht, wobei das Mittel, das das Signal Nächste Adresse generiert, zwischen der Cachesteuerungseinheit und dem Adressengenerierungsmittel angeschlossen ist.
 3. Ein Gerät nach Anspruch 2, bei dem das Mittel (CL), das das Signal Nächste Adresse generiert, in Abwesenheit jeglicher Aktion des Mittels zur Generierung eines Steuerungssignals freigegeben wird durch ein Signal (BADS) von der Cachesteuerungseinheit, das anzeigt, daß es auf dem lokalen Bus keine gültige Adresse gibt, und durch ein Signal (BNA) vom System, das anzeigt, daß eine nächste Adresse von dem lokalen Bus benötigt wird.
 4. Ein Gerät nach Anspruch 3, bei dem das Mittel zur Generierung eines Steuerungssignals einen Adressendecodierer umfaßt, der an die Adreßleitungen (CPULBA) des lokalen Busses angeschlossen ist, um festzustellen, ob eine Adresse auf diesem Bus innerhalb des festgelegten Bereichs liegt, und als Reaktion auf die Feststellung, daß sie nicht in diesem Bereich liegt, ein Signal (NCA) erzeugt, um das Mittel (CL) zu deaktivieren, das das Signal Nächste Adresse generiert.
 5. Ein Gerät nach Anspruch 4, bei dem das Mittel zur Generierung eines Steuerungssignals auch auf ein vom System generiertes Signal (NACACHE) reagiert, das anzeigt, daß die auf dem lokalen Bus angegebene Adresse - selbst wenn sie innerhalb des festgelegten Bereichs liegt - nicht cachefähig ist, um ein Signal zur Deaktivierung des Mittels zu generieren, das das Signal Nächste Adresse generiert.
 6. Ein Gerät nach Anspruch 5, bei dem der Mikroprozessor auf ein Signal (CS32, BS16) reagiert, das anzeigt, daß eine adressierte Systemkomponente die halbe Bitbreite des Mikroprozessors aufweist, um einen doppelten Ausführungszyklus zu programmieren, wobei eine Logik (CLA, S, ALS) bereitgestellt wird, die auf Signalkombinationen (CS16) reagiert, die anzeigen, daß eine adressierte Systemkomponente ein Viertel der Bitbreite des Mikroprozessors aufweist, um den Ausführungszyklus wieder zu verdoppeln, und zwar transparent für den Mikroprozessor.
 7. Ein Verfahren zum Betrieb eines Datenverarbeitungssystems, umfassend eine Befehlsausführungseinheit (225, 80386) mit einer gegebenen Bitbreite, ein asynchrones Mittel (225, 80386) zur Generierung der nächsten Adresse, das in der Lage ist, wenn es aktiviert ist, die Adresse des nächsten Befehls zu generieren, der von der Befehlsausführungseinheit während der Ausführung des derzeit ausgeführten Befehls benötigt wird, wodurch Befehle vorgeholt werden können, und ein Mittel (240, DL, AL) zum Anschluß der Ausführungseinheit an adressierbare Systemkomponenten von gleicher und/oder geringerer Bitbreite, wobei das Verfahren umfaßt:
 Zuweisen von Systemkomponentenadressen innerhalb eines festgelegten Bereichs ausschließlich an Komponenten mit derselben Bitbreite wie die der Ausführungseinheit,
 Generieren eines Signals Nächste Adresse (CPUNA) als Funktion der Ausführung des derzeit ausgeführten Befehls zur Freigabe der frühzeitigen Generierung der nächsten Adresse und daher des Befehlsvor-



holens, und
 Generieren eines Steuerungssignals (NCA), wenn die Ausführung eines Befehls hinsichtlich einer Adresse außerhalb des festgelegten Adreßbereichs entdeckt wird,
 wobei das Verfahren dadurch gekennzeichnet ist, daß
 5 als Reaktion auf die Generierung eines solchen Steuerungssignals die Generierung des Signals Nächste Adresse inhibiert wird.

Revendications

10

1. Dispositif de traitement de données comprenant
 une unité d'exécution d'instructions (225, 80 386) d'une largeur de bit donnée,
 un moyen de génération d'adresses suivantes asynchrone (225, 80 386) pouvant produire lorsque validée
 l'adresse de l'instruction suivante requise par l'unité d'exécution d'instructions pendant l'exécution de
 15 l'instruction actuellement exécutée, d'où il résulte que les instructions peuvent être pré-extraites,
 un moyen (240, DL, AL) pour interfacer l'unité d'exécution avec des composants de systèmes adressables
 de même largeur de bit ou de largeur de bit plus faible, les adresses des composants du système à l'intérieur d'une certaine plage spécifiée des adresses de composants du système se rapportant exclusivement
 20 aux composants de la même largeur de bit que ceux de l'unité d'exécution,
 un moyen (CL) pour produire un signal d'adresses suivant (CPUNA) en tant que fonction de l'exécution de l'instruction actuellement exécutée afin de valider le moyen de génération d'adresses suivantes et
 un moyen (CADR) pour produire un signal de commande (NCA) si l'exécution d'une instruction se rapportant à une adresse à l'extérieur de la plage spécifiée est détectée, le dispositif étant caractérisé en
 25 ce que, en réponse à un tel signal de commande, le moyen pour produire un signal d'adresses suivant est interdit.
2. Dispositif selon la revendication 1, dans lequel l'unité d'exécution d'instructions et le moyen de génération d'adresses sont deux unités à l'intérieur d'un micro-processeur (225, 80 386), le microprocesseur étant
 30 relié à un sous-système d'antémémoire, comportant un contrôleur d'antémémoire (260, 82 385) et une antémémoire (255) de la largeur de bit donnée par un bus local (230) de la largeur de bit donnée qui également s'interface avec un bus système (250) se connectant aux composants du système adressable, le sous-système d'antémémoire mettant en antémémoire des données par rapport à seulement les composants du système à l'intérieur de la plage spécifiée d'adresses, le moyen de génération de signal d'adresses suivant étant connecté entre le contrôleur d'antémémoire et le moyen de génération d'adresses.
3. Dispositif selon la revendication 2, dans lequel le moyen de génération de signal d'adresses suivant (CL) en l'absence de toute action quelconque par le moyen pour produire un signal de commande est validé
 35 par un signal (/BADS) provenant du contrôleur d'antémémoire indiquant qu'il n'y a pas d'adresse valide sur le bus local et par un signal (BNA) provenant du système indiquant qu'une adresse suivante est requise à partir du bus local.
4. Dispositif selon la revendication 3, dans lequel le moyen pour produire un signal de commande comporte un décodeur d'adresses connecté aux lignes d'adresses (CPULBA) du bus local pour déterminer si oui
 40 ou non une adresse sur celui-ci se trouve à l'intérieur de la plage spécifiée et, en réponse à une détermination en dehors de la plage, à produire un signal (NCA) pour désactiver le moyen de génération de signal d'adresses suivant (CL).
5. Dispositif selon la revendication 4, dans lequel le moyen pour produire un signal de commande est également sensible à un signal produit par le système (NACACHE) indiquant que l'adresse indiquée sur le
 50 bus local n'est pas utilisable en antémémoire, bien qu'elle se trouve à l'intérieur de la plage spécifiée, afin de produire un signal pour désactiver le moyen de génération de signal d'adresses suivant.
6. Dispositif selon la revendication 5, dans lequel le microprocesseur est sensible à un signal (CS32, BS16) indiquant qu'une composante du système adressée est de la moitié de la largeur de bit du microprocesseur
 55 pour programmer un double cycle d'exécution, une logique (CLA, S, ALS) étant prévue, répondant aux combinaisons de signaux (CS16) indiquant qu'une composante du système adressée est d'un quart de la largeur de bit du microprocesseur pour redoubler le cycle d'exécution de manière transparente pour le microprocesseur.



7. Procédé pour mettre en oeuvre un système de traitement de données qui comprend une unité d'exécution d'instructions (225, 80 386) d'une largeur de bit donnée, un moyen de génération d'adresses suivantes asynchrone (225, 80 386) pouvant produire lorsque validé, l'adresse de l'instruction suivante requise par l'unité d'exécution d'instructions pendant l'exécution de l'instruction qui est actuellement exécutée, d'où il résulte que les instructions peuvent être pré-extraites et un moyen (240, DL, AL) pour interfacer l'unité d'exécution avec des composants du système adressables de la même largeur et/ou de largeur de bit plus faible, procédé comprenant les étapes consistant à
- 5 affecter des adresses des composants du système à l'intérieur d'une certaine plage spécifiée de celui-ci exclusivement pour les composants de la même largeur de bit que celle de l'unité d'exécution,
- 10 produire un signal d'adresses suivant (CPUNA) en tant que fonction de l'exécution de l'instruction actuellement exécutée pour valider la production en avance de l'adresse suivante et ainsi la pré-extraction d'instructions, et
- 15 produire un signal de commande (NCA) si l'exécution d'une instruction se rapportant à une adresse à l'extérieur de la plage d'adresses spécifiée est détectée, le procédé étant caractérisé en ce que, en réponse à un tel signal de commande, la production du signal d'adresses suivant est interdite.

20

25

30

35

40

45

50

55